



US007852302B2

(12) **United States Patent**
Chiang et al.

(10) **Patent No.:** **US 7,852,302 B2**
(45) **Date of Patent:** **Dec. 14, 2010**

(54) **LIQUID CRYSTAL DISPLAY HAVING PIXEL UNITS EACH HAVING TWO SUB-PIXELS AND OPERATION METHOD THEREOF**

7,283,109 B2* 10/2007 Koyama 345/76
7,535,448 B2* 5/2009 Hiroki 345/89
2003/0095223 A1 5/2003 Song et al.
2005/0122441 A1 6/2005 Shimoshikiryoh

(75) Inventors: **Min-Feng Chiang**, Hsin-Chu (TW);
Hsueh-Ying Huang, Hsin-Chu (TW);
Ming-Sheng Lai, Hsin-Chu (TW)

FOREIGN PATENT DOCUMENTS

CN 1550854 12/2004
CN 1821842 8/2006
TW 240103 B 9/2005
TW I322401 3/2010
TW I330746 9/2010

(73) Assignee: **AU Optronics Corporation**, Hsin-Chu (TW)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 756 days.

OTHER PUBLICATIONS

English language translation of abstract of TW 240103B.
S.S. Kim; "66.1: Invited Paper: The World's Largest (82-in) TFT-LCD;" SID 05 Digest; 2005; pp. 1842-1847.
English language translation of abstract of CN 1550854.
English language translation of abstract of CN 1821842.
English language translation of abstract of TW I322401 (published Mar. 21, 2010).
English language translation of abstract of TW I330746 (published Sep. 21, 2010).

(21) Appl. No.: **11/745,663**

(22) Filed: **May 8, 2007**

(65) **Prior Publication Data**

US 2008/0048999 A1 Feb. 28, 2008

(30) **Foreign Application Priority Data**

Aug. 25, 2006 (TW) 95131463 A

(51) **Int. Cl.**
G09G 3/36 (2006.01)

(52) **U.S. Cl.** **345/93; 345/95**

(58) **Field of Classification Search** **345/50, 345/51, 55, 84, 87, 90, 92, 98, 100, 204**
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,648,793 A * 7/1997 Chen 345/96
5,903,249 A * 5/1999 Koyama et al. 345/92
6,850,302 B2 2/2005 Song et al.
7,071,911 B2* 7/2006 Inukai 345/92

* cited by examiner


Primary Examiner—Chanh Nguyen
Assistant Examiner—Pegeman Karimi

(74) *Attorney, Agent, or Firm*—Thomas, Kayden, Horstemeyer & Risley, LLP

(57) **ABSTRACT**

A pixel unit in the present invention is divided into two sub-pixels. Each sub-pixel includes a thin film transistor, a liquid crystal capacitor and a storage capacitor. The two transistors respectively located in different sub-pixels are connected to different scan lines. One of the two transistors is connected to the data line through another transistor. Therefore, two different pixel voltages are formed in a pixel.

15 Claims, 5 Drawing Sheets






Fig. 1
(PRIOR ART)




Fig. 2
(PRIOR ART)




Fig. 3A




Fig. 3B




Fig. 4A




Fig. 4B

LIQUID CRYSTAL DISPLAY HAVING PIXEL UNITS EACH HAVING TWO SUB-PIXELS AND OPERATION METHOD THEREOF

RELATED APPLICATIONS

This application claims priority to Taiwan Application Serial Number 95131463, filed Aug. 25, 2006, which is herein incorporated by reference.

FIELD OF THE INVENTION

The present invention relates to a liquid crystal display, and more particularly to a liquid crystal display with improved view angles.

BACKGROUND OF THE INVENTION

Liquid crystal displays have been used in various electronic devices. A Multi-Domain Vertically Aligned Mode (MVA mode) liquid crystal display is developed by Fujitsu in 1997 to provide a wider viewing range. In the MVA mode, a 160 degree view angle and a high response speed may be realized. However, when a user looks at this LCD from the oblique direction, the skin color of Asian people (light orange or pink) appears bluish or whitish from an oblique viewing direction. Such a phenomenon is called color shift.

The transmittance-voltage (T-V) characteristic of the MVA mode liquid crystal display is shown in FIG. 1. The vertical axis is the transmittance rate. The horizontal axis is the applied voltage. When the applied voltage is increased, the transmittance rate curve **101** in the normal direction is also increased. The transmittance changes monotonically as the applied voltage increases. In the oblique direction, the transmittance rate curve **102** winds and the various gray scales become the same. However, in the region **100**, when the applied voltage is increased, the transmittance rate curve **102** is not increased. That is the reason to cause the color shift.

A method is provided to improve the foregoing problem. According to the method, a pixel unit is divided into two sub pixels. The two sub pixels may generate two different T-V characteristics. By combining the two different T-V characteristics, a monotonic T-V characteristic can be realized. The line **201** in FIG. 2 shows the T-V characteristic of a sub-pixel. The line **202** in FIG. 2 shows the T-V characteristic of another sub-pixel. By combining the two different T-V characteristics of line **201** and line **202**, a monotonic T-V characteristic can be realized, as shown by the line **203** in FIG. 2.

Therefore, a pixel unit with two sub pixels and drive method thereof are required.

SUMMARY OF THE INVENTION

One object of the present invention is to provide a liquid crystal display with a wide view angle.

Another object of the present invention is to provide a pixel with two sub pixels.

One aspect of the present invention is directed to a liquid crystal display with a plurality of pixel units that may be driven by a drive wave to form two different pixel electrode voltages in a pixel unit.

Another aspect of the present invention is directed to a method for driving a liquid crystal display with a plurality of pixel units, wherein each pixel unit has two sub pixels.

Accordingly, the present invention provides a liquid crystal display, comprising: a plurality of data lines; a plurality of scan lines crossing said data lines, wherein said scan lines are

grouped into a first group and a second group and are alternatively arranged, adjacent data lines and adjacent scan lines define a pixel; a plurality of common electrodes respectively located in corresponding pixels to divide pixels to first sub-pixels and second sub-pixels; a plurality of switching devices formed in the locations of the scan lines crossing the data lines, wherein part of the switching devices connected with the second group's scan line are connected to the first group's scan line and the other switching devices connected with the second group's scan line are located in corresponding first sub-pixels, and wherein the switching devices connected with the first group's scan line are located in corresponding second sub-pixels and are coupled to corresponding data line through the switching devices connected with the second group's scan line; and a plurality pixel electrodes connected to the switching devices respectively.

According to an embodiment, the liquid crystal display further comprises a data line drive integrated circuit for driving said data lines.

According to an embodiment, the liquid crystal display further comprises a scan line drive integrated circuit for driving said scan lines.

Accordingly, the present invention provides a liquid crystal display, comprising: a plurality of data lines; a plurality of scan lines crossing the data lines, wherein adjacent first and second data lines and adjacent first and second scan lines define a pixel, wherein each pixel comprises: a first pixel electrode; a second pixel electrode; a common electrode, wherein the common electrode and the first pixel electrode define a first sub-pixel and the common electrode and the second pixel electrode define a second sub-pixel; a first transistor located in the first sub-pixel, a gate electrode of the first transistor is connected to the first scan line, a first source/drain electrode of the first transistor is connected to the first data line and a second source/drain electrode of the first transistor is connected to the first pixel electrode; a second transistor located in the second sub-pixel, a gate electrode and a first source/drain electrode of the first transistor is connected to the second scan line and a second source/drain electrode of the first transistor is connected to the second pixel electrode; and a third transistor located between two adjacent pixel, a gate electrode of the third transistor is connected to the first scan line, a second source/drain electrode of the third transistor is connected to the second scan line and a first source/drain electrode of the third transistor is connected to the first data line, wherein the second transistor is coupled to the first data line through the third transistor.

According to an embodiment, the common electrode and corresponding pixel electrode form storage capacitor.

According to an embodiment, the embodiment provides a drive method for driving a liquid crystal display disclosed in the above, the method comprises: providing a first signal to the first scan line; providing a second signal to the second scan line, wherein a time difference exists between the first signal and the second signal; and providing two-step signals to the data lines sequentially, the two-step signal includes a first voltage signal and a second voltage signal, wherein the first voltage signal is written to the first sub-pixel through the first transistor when the first scan line is driven by the first signal, and the second voltage signal is written to the second sub-pixel through the second transistor and the third transistor when the first scan line is not driven and the second scan line is driven by the second signal and adjacent pixel's first scan line is driven by the first signal.

According to an embodiment, the time difference is equal to half width of the first signal.

According to an embodiment, the first signal and the second signal are pulse signals.

According to an embodiment, the first signal is a pulse signal and the second signal is a clock signal.

According to an embodiment, further comprises the second scan line is driven by pulse signal when the first scan line is driven by pulse signal.

According to an embodiment, further comprises the second scan line is driven by clock signal when the first scan line is driven by pulse signal.

Accordingly, a pixel unit in the present invention is divided into two sub-pixels. Each sub-pixel includes a thin film transistor, a liquid crystal capacitor and a storage capacitor. The two transistors respectively located in different sub-pixels are connected to different scan lines. One of the two transistors is connected to the data line through another transistor. Therefore, two different pixel voltages are formed in a pixel.

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing aspects and many of the attendant advantages of this invention are more readily appreciated and better understood by referencing the following detailed description, when taken in conjunction with the accompanying drawings, wherein:

FIG. 1 and FIG. 2 illustrate the transmittance-voltage (T-V) characteristic of MVA mode liquid crystal display;

FIG. 3A illustrates a top view of a liquid crystal display according to the first embodiment of the present invention.

FIG. 3B illustrates an enlarged schematic diagram of a pixel unit according to an embodiment of the present invention.

FIG. 4A illustrates a drive waveform and the corresponding electric voltage of four adjacent sub pixels according to an embodiment of the present invention.

FIG. 4B illustrates a drive waveform and the corresponding electric voltage of four adjacent sub pixels according to another embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

FIG. 3A illustrates a top view of a liquid crystal display according to the first embodiment of the present invention. The liquid crystal display is composed of data lines $D_1, D_2, D_3, \dots, D_n$, the scan lines $G_1(A), G_2(A), G_3(A), \dots, G_n(A)$ of group A and the scan lines $G_2(B), G_3(B), \dots, G_{n-1}(B)$ of group B. These scan lines are arranged in parallel to each other. Moreover, the scan lines of group A and the scan lines of group B are alternatively formed over a substrate (not shown in this figure).

The data lines and the scan lines are perpendicular to each other. Adjacent two data lines and adjacent two scan lines respectively belong to the group A and group B define a pixel unit. Each pixel includes a common electrode V_{com} parallel to the scan line. According to the present invention, two transistors are connected to the scan line of group B located between adjacent two pixels to control the data of the data line to transfer to the corresponding pixel.

According to the present invention, a pixel includes two sub-pixels. Each sub-pixel includes a storage capacitor, a liquid crystal capacitor and a thin film transistor. The storage capacitor is composed of the pixel electrode and the common electrode. The liquid crystal capacitor is composed of the pixel electrode and the conductive electrode in the upper substrate (not shown in figure). The thin film transistor is formed in the location that the data line crosses the scan line.

According to the present invention, the transistors located in adjacent two sub-pixels are connected to adjacent two scan lines that belong to the group A and group B respectively. These two scan lines are connected together through a transistor that is controlled by this scan line of group B. A data line drive integrated circuit **301** is used to control the data lines $D_1, D_2, D_3, \dots, D_n$. A scan line drive integrated circuit **302** is used to control the scan lines $G_1(A), G_2(A), G_3(A), \dots, G_n(A)$ of group A and the scan lines $G_2(B), G_3(B), \dots, G_{n-1}(B)$ of group B.

The storage capacitors and the liquid crystal capacitors in the sub pixels described in the following are indicated by different symbols. These symbols are not related to their capacitance.

FIG. 3B illustrates an enlarged diagram of a pixel. The pixel **303** is defined by the data lines D_{n-2}, D_{n-1} and the scan lines $G_{n-2}(B), G_{n-1}(A)$. A common electrode V_{com} parallel to the scan line is arranged between the scan line $G_{n-2}(B)$ and the scan line $G_{n-1}(A)$. The pixel **303** is divided into two sub-pixels. The sub-pixel **3031** is located between the scan line $G_{n-2}(B)$ and the common electrode V_{com} . The sub pixel **3032** is located between the scan line $G_{n-1}(A)$ and the common electrode V_{com} .

The sub-pixel **3031** includes a transistor Q_1 . According to the transistor Q_1 , the gate electrode is connected to the scan line $G_{n-2}(B)$, the first source/drain electrode is connected to the data line D_{n-1} and the second source/drain electrode is connected to the pixel electrode P_1 . The storage capacitor C_{st1} is composed of the pixel electrode P_1 and the common electrode V_{com} . The liquid crystal capacitor C_{LC1} is composed of the pixel electrode P_1 and the conductive electrode in the upper substrate (not shown in figure).

The sub-pixel **3032** also includes a transistor Q_2 . According to the transistor Q_2 , the gate electrode is connected to the scan line $G_{n-1}(A)$, the first source/drain electrode is connected to the data line D_{n-1} through another transistor Q_5 and the second source/drain electrode is connected to the pixel electrode P_2 . The storage capacitor C_{st2} is composed of the pixel electrode P_2 and the common electrode V_{com} . The liquid crystal capacitor C_{LC2} is composed of the pixel electrode P_2 and the conductive electrode in the upper substrate (not shown in figure). In addition, according to the transistor Q_5 , the gate electrode is connected to the scan line $G_{n-1}(B)$, the first source/drain electrode is connected to the data line D_{n-1} .

The transistors Q_1, Q_2 and Q_5 act as switches. When a scan voltage is applied to the gate electrode of a transistor, the data voltage in the data line is transferred to the second source/drain electrode and is written into the corresponding storage capacitor and the liquid crystal capacitor. In this invention, the transistor Q_2 is not directly connected to the data line D_{n-1} . This transistor Q_2 is connected to the data line D_{n-1} through the transistor Q_5 . In other words, the transistor Q_2 and the transistor Q_5 together control the sub-pixel **3032** whether or not to display the data in the data line. Therefore, when a data is written into the storage capacitor C_{st2} and the liquid crystal capacitor C_{LC2} , the transistor Q_2 and the transistor Q_5 have to be conducted together. Accordingly, in the present invention, a voltage waveform in the scan line is used to control the transistors Q_1, Q_2 and Q_5 to co-operates with the voltage waveform in the data line to make the two sub-pixels **3031** and **3032** have different pixel voltages.

FIG. 4A illustrates a drive waveform and the corresponding electric voltage of four adjacent sub pixels according to an embodiment of the present invention. The drive signal of each scan line is pulse. When scanning, drive signal is sequentially transferred to these scan lines. The time difference between the two drive signals transferred to adjacent scan lines respec-

tively is half period of the pulse. In other words, the two drive signals transferred to adjacent scan lines respectively partially overlap. Therefore, in the time period of the two drive signals overlapping, the transistors connected with the two scan lines are turned on together.

In this embodiment, the drive waveform of the data line is a two steps drive waveform. The positive part of this drive waveform includes two drive voltage Va and Vb. The negative part of this drive waveform also includes two drive voltage -Va and -Vb. The absolute value of the drive voltage Va is larger than the absolute value of the drive voltage Vb.

Please refer to the FIG. 3A and FIG. 4A. During the time segment t_1 , the voltage state of both the scan line $G_{n-2}(A)$ and $G_{n-2}(B)$ are in a high level state. The voltage state of both the scan line $G_{n-1}(A)$ and $G_{n-1}(B)$ are in a low level state. Therefore, the transistors Q_1 , Q_3 and Q_4 are turned on and the transistors Q_2 , Q_5 and Q_6 are turned off. In this case, the voltage -Vb in the data line D_{n-1} may charge the liquid crystal capacitors C_{LC0} and the storage capacitors C_{S0} through the transistors Q_3 and Q_4 . At this time, the sub-pixel **3030** may present the pixel voltage, -Vb. Moreover, the voltage -Vb in the data line D_{n-1} may charge the liquid crystal capacitors C_{LC1} and the storage capacitors C_{S1} through the transistor Q_1 . At this time, the sub-pixel **3031** may also present the pixel voltage, -Vb. The transistors Q_2 , Q_5 and Q_6 are turned off. Therefore, the pixel voltage of the sub-pixels **3032** and **3033** is not changed. In this embodiment, the sub-pixel **3032** presents the pixel voltage, -Vb. The sub-pixel **3033** presents the pixel voltage, -Vb.

During the time segment t_2 , the voltage state of both the scan line $G_{n-2}(B)$ and $G_{n-1}(A)$ are in a high level state. The voltage state of both the scan line $G_{n-2}(A)$ and $G_{n-1}(B)$ are in a low level state. Therefore, the transistors Q_1 , Q_2 and Q_3 are turned on and the transistors Q_4 , Q_5 and Q_6 are turned off. In this case, the voltage +Va in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC1} and the storage capacitor C_{S1} through the transistor Q_1 . At this time, the sub-pixel **3031** may present the pixel voltage, +Va. The transistors Q_4 , Q_5 and Q_6 are turned off. Therefore, the liquid crystal capacitors C_{LC0} , C_{LC2} and C_{LC3} and the storage capacitors C_{S0} , C_{S2} and C_{S3} coupling with the transistors Q_4 , Q_5 and Q_6 respectively are not charged by the voltage +Va. At this time, the sub-pixel **3030**, the sub-pixel **3032** and the sub-pixel **3033** still present the pixel voltage of the previous state. In other words, the sub-pixel **3030** presents the pixel voltage, -Vb. The sub-pixel **3032** presents the pixel voltage, -Vb. The sub-pixel **3033** presents the pixel voltage, +Va.

During the time segment t_3 , the voltage state of both the scan line $G_{n-1}(A)$ and $G_{n-1}(B)$ are in a high level state. The voltage state of both the scan line $G_{n-2}(A)$ and $G_{n-2}(B)$ are in a low level state. Therefore, the transistors Q_2 , Q_5 and Q_6 are turned on and the transistors Q_1 , Q_3 and Q_4 are turned off. In this case, the voltage +Vb in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC2} and the storage capacitor C_{S2} through the transistors Q_2 and Q_5 . At this time, the sub-pixel **3032** may present the pixel voltage, +Vb. On the other hand, the voltage +Vb in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC3} and the storage capacitor C_{S3} through the transistor Q_6 . At this time, the sub-pixel **3033** may present the pixel voltage, +Vb. Because the transistors Q_3 and Q_4 are turned off, the liquid crystal capacitor C_{LC0} and the storage capacitor C_{S0} are not charged by the voltage +Vb. At this time, the sub-pixel **3030** still presents the pixel voltage, -Vb. On the other hand, because the transistor Q_1 is turned off, the liquid crystal capacitors C_{LC1} and the storage capacitors C_{S1} are not charged by the voltage +Vb. At this time, the sub-pixel **3031** still present the pixel voltage, +Va.

During the time segment t_4 , the voltage state of the scan line $G_{n-1}(B)$ is in a high level state. The voltage state of both the scan line $G_{n-1}(A)$, $G_{n-2}(A)$ and $G_{n-2}(B)$ are in a low level state. Therefore, the transistors Q_5 and Q_6 are turned on and the transistors Q_1 , Q_2 , Q_3 and Q_4 are turned off. In this case, the voltage -Vb in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC3} and the storage capacitor C_{S3} through the transistor Q_6 . At this time, the sub-pixel **3033** may present the pixel voltage, -Vb. Because the transistors Q_3 and Q_4 are turned off, the liquid crystal capacitor C_{LC0} and the storage capacitor C_{S0} are not charged by the voltage -Vb. At this time, the sub-pixel **3030** still presents a pixel voltage, -Vb. Because the transistor Q_1 is turned off, the liquid crystal capacitors C_{LC1} and the storage capacitors C_{S1} are not charged by the voltage -Vb. At this time, the sub-pixel **3031** still presents the pixel voltage, +Va. Because the transistor Q_2 is turned off, the liquid crystal capacitors C_{LC2} and the storage capacitors C_{S2} are not charged by the voltage -Vb. At this time, the sub-pixel **3032** still presents the pixel voltage, +Vb.

Accordingly, from the time segment t_1 to t_4 , at least two pixel voltages, Vb and +Va, are presented in the pixel **303** together. Different pixel voltage may present different optical characteristics. Therefore, the color shift phenomenon may be eased by combining the two pixel voltages in a pixel.

FIG. 4B illustrates a drive waveform and the corresponding electric voltage of four adjacent sub pixels according to another embodiment of the present invention. The drive signal transferred in the scan line of the group A is a clock signal. The drive signal transferred in the scan line of the group B is pulse signal. When scanning, pulse signal is sequentially transferred to these scan lines of the group B. The pulse width is equal to the period the clock signal. In other words, the two drive signals, the clock signal and the pulse signal, transferred to adjacent scan lines respectively partially overlap. Therefore, in the time period of the two drive signals overlapping, the transistors connected with the two scan lines are turned on together.

In this embodiment, the drive waveform of the data line is a two steps drive waveform. The positive part of this drive waveform includes two drive voltage Va and Vb. The negative part of this drive waveform also includes two drive voltage -Va and -Vb. The absolute value of the drive voltage Va is larger than the absolute value of the drive voltage Vb.

Please refer to the FIG. 3A and FIG. 4B. During the time segment t_1 , the voltage state of the scan line $G_{n-1}(A)$, $G_{n-2}(A)$ and $G_{n-2}(B)$ are in a high level state. The voltage state of the scan line $G_{n-1}(B)$ is in a low level state. Therefore, the transistors Q_1 , Q_2 , Q_3 and Q_4 are turned on and the transistors Q_5 and Q_6 are turned off. In this case, the voltage -Vb in the data line D_{n-1} may charge the liquid crystal capacitors C_{LC0} and the storage capacitors C_{S0} through the transistors Q_3 and Q_4 . At this time, the sub-pixel **3030** may present the pixel voltage, -Vb. Moreover, the voltage -Vb in the data line D_{n-1} may charge the liquid crystal capacitors C_{LC1} and the storage capacitors C_{S1} through the transistor Q_1 . At this time, the sub-pixel **3031** may also present the pixel voltage, -Vb. The transistors Q_5 and Q_6 are turned off. The transistor Q_2 is connected to the data line D_{n-1} through the transistors Q_5 . Therefore, the liquid crystal capacitor C_{LC2} and the storage capacitor C_{S2} are not charged by the voltage -Vb. On the other hand, because the transistor Q_6 is turned off, the liquid crystal capacitors C_{LC3} and the storage capacitors C_{S3} are not charged by the voltage -Vb. Therefore, the sub-pixel **3032** and the sub-pixel **3033** still present the pixel voltage of the previous state. In this embodiment, the sub-pixel **3032** presents the pixel voltage, -Vb. The sub-pixel **3033** presents the pixel voltage, Va.

During the time segment t_2 , the voltage state of both the scan line $G_{n-2}(B)$ is in a high level state. The voltage state of the scan lines $G_{n-1}(A)$, $G_{n-2}(A)$ and $G_{n-1}(B)$ are in a low level state. Therefore, the transistors Q_1 and Q_3 are turned on and the transistors Q_2 , Q_4 , Q_5 and Q_6 are turned off. In this case, the voltage $+Va$ in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC1} and the storage capacitor C_{st1} through the transistor Q_1 . At this time, the sub-pixel **3031** may present the pixel voltage, $+Va$. On the other hand, because the transistor Q_4 is turned off, the liquid crystal capacitor C_{LC0} and the storage capacitor C_{st0} are not charged by the voltage $+Va$. At this time, the sub-pixel **3030** still presents the previous pixel voltage state, $-Vb$. Because the transistor Q_1 and Q_5 are turned off, the liquid crystal capacitors C_{LC2} and the storage capacitors C_{st2} are not charged by the voltage $+Va$. At this time, the sub-pixel **3032** still present the previous pixel voltage state, $-Vb$. Because the transistor Q_6 is turned off, the liquid crystal capacitors C_{LC3} and the storage capacitors C_{st3} are not charged by the voltage $+Va$. At this time, the sub-pixel **3033** still present the previous pixel voltage state, $+Va$.

During the time segment t_3 , the voltage state of the scan line $G_{n1}(A)$, $G_{n-2}(A)$ and $G_{n-1}(B)$ are in a high level state. The voltage state of the scan line $G_{n-2}(B)$ is in a low level state. Therefore, the transistors Q_2 , Q_4 , Q_5 and Q_6 are turned on and the transistors Q_1 , Q_3 and are turned off. In this case, the voltage $+Vb$ in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC2} and the storage capacitor C_{st2} through the transistors Q_2 and Q_5 . At this time, the sub-pixel **3032** may present the pixel voltage, $+Vb$. On the other hand, the voltage $+Vb$ in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC3} and the storage capacitor C_{st3} through the transistor Q_6 . At this time, the sub-pixel **3033** may present the pixel voltage, $+Vb$. Because the transistors Q_3 and Q_4 are turned off, the liquid crystal capacitor C_{LC0} and the storage capacitor C_{st0} are not charged by the voltage $+Vb$. At this time, the sub-pixel **3030** still presents the pixel voltage, $-Vb$. On the other hand, because the transistor Q_1 is turned off, the liquid crystal capacitors C_{LC1} and the storage capacitors C_{st1} are not charged by the voltage $+Vb$. At this time, the sub-pixel **3031** still present the pixel voltage, $+Va$.

During the time segment t_4 , the voltage state of the scan line $G_{n-1}(B)$ is in a high level state. The voltage state of both the scan line $G_{n-1}(A)$, $G_{n-2}(A)$ and $G_{n-2}(B)$ are in a low level state. Therefore, the transistors Q_5 and Q_6 are turned on and the transistors Q_1 , Q_2 , Q_3 and Q_4 are turned off. In this case, the voltage $-Vb$ in the data line D_{n-1} may charge the liquid crystal capacitor C_{LC3} and the storage capacitor C_{st3} through the transistor Q_6 . At this time, the sub-pixel **3033** may present the pixel voltage, $-Vb$. Because the transistors Q_3 and Q_4 are turned off, the liquid crystal capacitor C_{LC0} and the storage capacitor C_{st0} are not charged by the voltage $-Vb$. At this time, the sub-pixel **3030** still presents the previous pixel voltage state, $-Vb$. Because the transistor Q_1 is turned off, the liquid crystal capacitors C_{LC1} and the storage capacitors C_{st1} are not charged by the voltage $-Vb$. At this time, the sub-pixel **3031** still presents the previous pixel voltage state, $+Va$. Because the transistor Q_2 is turned off, the liquid crystal capacitors C_{LC2} and the storage capacitors C_{st2} are not charged by the voltage $-Vb$. At this time, the sub-pixel **3032** still presents the previous pixel voltage state, $+Vb$.

Accordingly, from the time segment t_1 to t_4 , at least two pixel voltages, Vb and $+Va$, are presented in the pixel **303** together. Different pixel voltage may present different optical characteristics. Therefore, the color shift phenomenon may be eased by combining the two pixel voltages in a pixel.

Accordingly, a pixel unit in the present invention is divided into two sub-pixels. Each sub-pixel includes a thin film tran-

sistor, a liquid crystal capacitor and a storage capacitor. The two transistors in a pixel are connected to different scan lines. One of the two transistors is connected to the data line through another transistor. Therefore, two different pixel voltages are formed in a pixel. The color shift phenomenon may be eased by combining the two pixel voltages in a pixel.

As is understood by a person skilled in the art, the foregoing descriptions of the preferred embodiment of the present invention are an illustration of the present invention rather than a limitation thereof. Various modifications and similar arrangements are included within the spirit and scope of the appended claims. The scope of the claims should be accorded to the broadest interpretation so as to encompass all such modifications and similar structures. While a preferred embodiment of the invention has been illustrated and described, it will be appreciated that various changes can be made therein without departing from the spirit and scope of the invention.

What is claimed is:

1. A drive method for driving a liquid crystal display, wherein said liquid crystal display comprises: a plurality of data lines; a plurality of scan lines crossing said data lines; a plurality of pixels defined by two neighboring data lines and two neighboring scan lines crossing the two neighboring data lines, wherein each pixel comprises: a first pixel electrode; a second pixel electrode; a common electrode, wherein said common electrode and said first pixel electrode define a first sub-pixel and said common electrode and said second pixel electrode define a second sub-pixel; a first transistor located in said first sub-pixel, a gate electrode of said first transistor is connected to said first scan line, a first source/drain electrode of said first transistor is connected to said first data line and a second source/drain electrode of said first transistor is connected to said first pixel electrode, wherein the first pixel electrode receives a data signal from the first data line through the first transistor; a second transistor located in said second sub-pixel, a gate electrode of said second transistor is connected to said second scan line and a second source/drain electrode of said second transistor is connected to said second pixel electrode; and a third transistor located between two adjacent pixel, a gate electrode of said third transistor is connected to said first scan line, a second source/drain electrode of said third transistor is connected to a first source/drain electrode of said second transistor and a first source/drain electrode of said third transistor is connected to said first data line, wherein said second transistor is coupled to said first data line through said third transistor, wherein the second pixel electrode receives a data signal from the first data line through the second transistor and the third transistor, said method comprises:

providing pulse signals to said scan lines sequentially, wherein a time difference exists between two pulse signals providing to adjacent scan lines; and

providing two-step signals to said data lines sequentially, said two-step signal includes a first voltage signal and a second voltage signal, wherein said first voltage signal is written to said first sub-pixel through said first transistor when said first and second scan line are driven together, and said second voltage signal is written to said second sub-pixel through said second transistor and said third transistor when said first scan line is not driven and said second scan line and adjacent pixel's first scan line are driven.

2. The drive method of claim 1, wherein the time difference is equal to half of a width of the pulse signal.

3. The drive method of claim 1, wherein the value of said first voltage signal is larger than the value of said second voltage signal.

4. A drive method for driving a liquid crystal display, wherein said liquid crystal display comprises: a plurality of data lines; a plurality of scan lines crossing said data lines; a plurality of pixels defined by two neighboring data lines and two neighboring scan lines crossing the two neighboring data lines, wherein each pixel comprises: a first pixel electrode; a second pixel electrode; a common electrode, wherein said common electrode and said first pixel electrode define a first sub-pixel and said common electrode and said second pixel electrode define a second sub-pixel; a first transistor located in said first sub-pixel, a gate electrode of said first transistor is connected to said first scan line, a first source/drain electrode of said first transistor is connected to said first data line and a second source/drain electrode of said first transistor is connected to said first pixel electrode, wherein the first pixel electrode receives a data signal from the first data line through the first transistor; a second transistor located in said second sub-pixel, a gate electrode of said second transistor is connected to said second scan line and a second source/drain electrode of said second transistor is connected to said second pixel electrode; and a third transistor located between two adjacent pixel, a gate electrode of said third transistor is connected to said first scan line, a second source/drain electrode of said third transistor is connected to a first source/drain electrode of said second transistor and a first source/drain electrode of said third transistor is connected to said first data line, wherein said second transistor is coupled to said first data line through said third transistor, wherein the second pixel electrode receives a data signal from the first data line through the second transistor and the third transistor, said method comprises:

providing pulse signals to said scan lines sequentially, wherein a time difference exists between two pulse signals providing to adjacent scan lines; and

providing two-step signals to said data lines sequentially, said two-step signal includes a first voltage signal and a second voltage signal, wherein said first voltage signal is written to said first sub-pixel through said first transistor when said first scan line is driven, and said second voltage signal is written to said second sub-pixel through said second transistor and said third transistor when said first scan line is not driven and said second scan line and adjacent pixel's first scan line are driven.

5. The drive method of claim 4, wherein the time difference is equal to half of a width of the pulse signal.

6. The drive method of claim 4, wherein the value of said first voltage signal is larger than the value of said second voltage signal.

7. The drive method of claim 4, wherein said second scan line is driven when said first scan line is driven.

8. The drive method of claim 4, wherein said second scan line is not driven when said first scan line is driven.

9. A drive method for driving a liquid crystal display, wherein said liquid crystal display comprises: a plurality of data lines; a plurality of scan lines crossing said data lines; a plurality of pixels defined by two neighboring data lines and

two neighboring scan lines crossing the two neighboring data lines, wherein each pixel comprises: a first pixel electrode; a second pixel electrode; a common electrode, wherein said common electrode and said first pixel electrode define a first sub-pixel and said common electrode and said second pixel electrode define a second sub-pixel; a first transistor located in said first sub-pixel, a gate electrode of said first transistor is connected to said first scan line, a first source/drain electrode of said first transistor is connected to said first data line and a second source/drain electrode of said first transistor is connected to said first pixel electrode, wherein the first pixel electrode receives a data signal from the first data line through the first transistor; a second transistor located in said second sub-pixel, a gate electrode of said second transistor is connected to said second scan line and a second source/drain electrode of said second transistor is connected to said second pixel electrode; and a third transistor located between two adjacent pixel, a gate electrode of said third transistor is connected to said first scan line, a second source/drain electrode of said third transistor is connected to a first source/drain electrode of said second transistor and a first source/drain electrode of said third transistor is connected to said first data line, wherein said second transistor is coupled to said first data line through said third transistor, wherein the second pixel electrode receives a data signal from the first data line through the second transistor and the third transistor, said method comprises:

providing a first signal to said first scan line; providing a second signal to said second scan line, wherein a time difference exists between said first signal and said second signal; and

providing two-step signals to said data lines sequentially, said two-step signal includes a first voltage signal and a second voltage signal, wherein said first voltage signal is written to said first sub-pixel through said first transistor when said first scan line is driven by said first signal, and said second voltage signal is written to said second sub-pixel through said second transistor and said third transistor when said first scan line is not driven and said second scan line is driven by said second signal and adjacent pixel's first scan line is driven by said first signal.

10. The drive method of claim 9, wherein the time difference is equal to half of a width of the first signal.

11. The drive method of claim 9, wherein the first signal and the second signal are pulse signals.

12. The drive method of claim 11, wherein said second scan line is driven by pulse signal when said first scan line is driven by pulse signal.

13. The drive method of claim 9, wherein the first signal is a pulse signal and the second signal is a clock signal.

14. The drive method of claim 13, wherein said second scan line is driven by clock signal when said first scan line is driven by pulse signal.

15. The drive method of claim 9, wherein the value of said first voltage signal is larger than the value of said second voltage signal.

专利名称(译)	具有每个具有两个子像素的像素单元的液晶显示器及其操作方法		
公开(公告)号	US7852302	公开(公告)日	2010-12-14
申请号	US11/745663	申请日	2007-05-08
[标]申请(专利权)人(译)	友达光电股份有限公司		
申请(专利权)人(译)	友达光电股份有限公司		
当前申请(专利权)人(译)	友达光电股份有限公司		
[标]发明人	CHIANG MIN FENG HUANG HSUEH YING LAI MING SHENG		
发明人	CHIANG, MIN-FENG HUANG, HSUEH-YING LAI, MING-SHENG		
IPC分类号	G09G3/36		
CPC分类号	G09G3/3659 G02F1/13624 G02F2001/134345 G09G2300/0443 G09G2300/0447 G09G2310/0205 G09G2320/028		
审查员(译)	阮箐		
优先权	095131463 2006-08-25 TW		
其他公开文献	US20080048999A1		
外部链接	Espacenet USPTO		

摘要(译)

本发明中的像素单元分为两个子像素。每个子像素包括薄膜晶体管，液晶电容器和存储电容器。分别位于不同子像素中的两个晶体管连接到不同的扫描线。两个晶体管中的一个通过另一个晶体管连接到数据线。因此，在像素中形成两个不同的像素电压。

