




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8

Fig. 9A




Fig. 9B





Fig. 9C



DISPLAY DEVICE

CROSS-REFERENCE TO RELATED APPLICATION

[0001] The entire disclosure of Japanese Patent Application Nos. 2004-152485, 2004-152489, 2004-152493, and 2004-152497 including specification, claims, drawings and abstract is incorporated herein by reference.

BACKGROUND OF THE INVENTION

[0002] 1. Field of the Invention

[0003] The present invention relates to a display device having display circuits arranged in a matrix configuration.

[0004] 2. Description of the Related Art

[0005] Conventionally, liquid crystal display devices are known as low power consumption display devices that can assume a thinner and more lightweight form and are employed in various types of equipment as display devices. Liquid crystal display devices (hereinafter referred to as LCD) have two substrates with electrodes formed on opposing sides thereof, laminated with liquid crystals injected between them. A display operation is performed by applying a voltage signal across the electrodes to control the alignment of the liquid crystals, the optical characteristics of which change according to the alignment so as to control the transmissivity of light from a light source.

[0006] It is well known that when a DC voltage is continuously applied across electrodes formed on opposing surfaces of the substrates, the alignment of the liquid crystal molecules becomes fixed, namely, the problem of screen burn-in occurs. Thus, an AC voltage signal having a polarity that periodically inverts with respect to a reference voltage is conventionally used as the voltage signal for driving the liquid crystals.

[0007] Well known methods for inverting the polarity of the liquid crystal driving voltage signal in a liquid crystal display device having a plurality of pixels arranged in a matrix configuration are inversion at every frame, inversion at every vertical scan (1V) or field, inversion at every horizontal scan (1H), and inversion at every pixel (dot). A frame unit corresponds to a frame in an NTSC signal, for example, and a field unit corresponds to various units (for example, odd fields and even fields) of a plurality of fields forming one frame.

[0008] In Japanese Patent Laid-Open Publication No. 2003-150127, the dot inversion method for inverting the polarity in one-pixel (dot) units is preferable among the above-mentioned methods as the adverse effect of inversion on display quality is least likely to appear. However, a problem was that its driving method is likely to become complex.

[0009] It should be noted that modifying the voltage of an SC line, which is a line that becomes a base for a storage capacitance, has been proposed in the dot inversion method in Japanese Patent Laid-Open Publication No. 2003-150127.

SUMMARY OF THE INVENTION

[0010] When changing the level of a storage capacitor line in the present invention, the potential of at least one level is

used in common with the potential of at least one of either an H level or L level used in a selection line. Therefore, the circuits and wiring for creating power source voltages can be optimized.

[0011] Furthermore, the values of storage capacitance and parasitic capacitance with respect to the storage capacitor line can be set within a specific range. This makes it possible to suppress the parasitic capacitance that develops from the storage capacitor line which is not connected to the circuit for a white pixel from adversely affecting the operation and to ensure circuit operation.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] FIG. 1 shows a configuration of an embodiment.

[0013] FIG. 2 shows the signal waveforms of capacitance lines SC-A and SC-B.

[0014] FIG. 3 shows the voltage shift states in the case of normally black.

[0015] FIG. 4 shows the voltage shift states in the case of normally white.

[0016] FIG. 5 shows a planar structure of pixel circuits.

[0017] FIG. 6 shows a cross-sectional structure of pixel circuits.

[0018] FIG. 7 shows the change in transmissivity for TN liquid crystals and VA liquid crystals.

[0019] FIG. 8 shows a configuration of an SC driver.

[0020] FIG. 9 shows a structure and operation of a VA mode pixel.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0021] The present invention will be described hereinafter with reference to the attached drawings.

[0022] FIG. 1 is a block diagram of the embodiment. Pixel circuit 1 is arranged in a matrix on the entire display region. The matrix arrangement may have a zigzag form and need not be a perfect lattice. Furthermore, the display may be monochrome or full color. In the case of full color, although the pixels normally have the three RGB colors, it is also preferable to add specific color pixels including white as necessary.

[0023] As shown in the figure, one pixel circuit 1 comprises a pixel TFT 10 for each of n channels with each drain connected to a data line DL, and a liquid crystal element 12 and a storage capacitor 14 connected to the source of the pixel TFT 10. To the gate of the pixel TFT 10 is connected a gate line GL disposed at each horizontal scan line. A gate capacitor 18 inevitably develops between the gate and source of the pixel TFT 10.

[0024] The liquid crystal element 12 is configured so that a pixel electrode provided individually at each pixel is connected to the source of the pixel TFT 10, and opposed to this pixel electrode so as to sandwich a liquid crystal material is disposed a common electrode for all pixels. The common electrode is connected to a common electrode power source Vcom.

[0025] Furthermore, the storage capacitor **14** has one electrode which is an extension of the semiconductor layer forming the source of the pixel TFT **10** and a counter electrode which is part of a capacitance line SC formed in opposition via an oxide film. The parts that form the electrodes of the storage capacitor **14** may be separated into a different semiconductor layer from that of the pixel TFT **10** with both connected by metal wires.

[0026] Two capacitance lines SC, SC-A and SC-B, are provided for one line (horizontal scan line), and in the direction of the horizontal scan, the storage capacitor of each pixel circuit alternately connects to SC-A and SC-B. The storage capacitor **14** of the pixel circuit shown on the left side in the figure is connected to the capacitance line SC-A and the storage capacitor **14** of the adjacent pixel is connected to the capacitance line SC-B.

[0027] Furthermore, in this pixel, the capacitance line SC-B is not connected but passes through the pixel region. Therefore, a parasitic capacitance **16** develops between the pixel electrode of the liquid crystal element **12** and the capacitance line SC-B.

[0028] To the gate line GL is connected a vertical driver **20**. The vertical driver **20** sequentially selects and sets to an H level one gate line GL at a time at each horizontal period. The vertical driver **20** has a shift register so that when a signal STV indicating the start of one vertical scan period is received and the first stage of the shift register is set to the H level, the H level is shifted one at a time thereafter by a clock signal, for example, so that the gate line GL for each horizontal scan line is selected and set to an H level one line at a time. As an example herein, the H level for the gate line GL is the VDD potential and the L level is the VSS potential. These power source voltages VDD and VSS are supplied to the vertical driver **20** so that the H level and L level are set for the gate line GL, which is the output of the vertical driver.

[0029] An SC driver **22** outputs two voltage levels to two storage capacitor lines SC-A and SC-B.

[0030] Namely, in this embodiment, the SC driver **22** receives the supply of two voltage levels, $V_{SC}(H)$ and $V_{SC}(L)$, from a voltage generator circuit **24** for use in controlling the voltages of the two storage capacitor lines SC-A and SC-B. Furthermore, the voltage generator circuit **24** generates $V_{SC}(H)$ and $V_{SC}(L)$ on the basis of preset data stored in a data memory **26**.

[0031] The preset data within the data memory **26** can be rewritten by a setting signal that is supplied from an external source, and the preset data corresponding to the setting signal is stored into the data memory **26**. The voltage generator circuit **24** generates $V_{SC}(H)$ and $V_{SC}(L)$ on the basis of preset data stored in the data memory **26**. Therefore, $V_{SC}(H)$ and $V_{SC}(L)$ can be set by the setting signal. The voltage generator circuit utilizes $V_{SC}(H)$ and $V_{SC}(L)$ from VDD and VSS and uses a constant voltage generator circuit to generate $V_{SC}(H)$ and $V_{SC}(L)$. For a simple configuration, a resistive potential divider or the like can be utilized.

[0032] It should be noted that the setting signal may be stored into the data memory **26**, such as by serial transfer from an external microcomputer.

[0033] The display device usually is provided with adjustment buttons for contrast and brightness, and the setting

signal is determined according to their preset values and stored into the data memory **26**.

[0034] Although not shown in the figure, the display device is also provided with a horizontal driver, for example, to control the line-sequential supply to the data line DL of a video signal that is input. Namely, in this example, the horizontal driver outputs a sampling clock for each pixel in accordance with a video signal clock for each pixel. This sampling clock turns a switch on and off and latches the video signal (data signal) for one horizontal scan line. The data signal for each pixel in the latched horizontal scan line is output during one horizontal scan period to the data line DL.

[0035] In actuality, there are three types of video signals for RGB and each pixel in the vertical direction has the same color as one of R, G, or B. Consequently, the data line DL is set with the data signal for one of the RGB colors.

[0036] The device of this embodiment employs an AC application method for the dot inversion method. Namely, at each pixel (dot) in the horizontal scan direction, the voltage applied to the pixel electrode of the liquid crystal element **12** is applied as a data signal having an opposite polarity with respect to the voltage Vcom of the common electrode.

[0037] The left side of FIG. 3 shows the data signal based on a first polarity and the hypotenuse of the triangle denoted by Vvideo represents the data signal (write voltage) corresponding to the brightness. The data signal has a potential difference (dynamic range) of Vb from the black level to the white level, and the voltage applied to the pixel electrode subsequent to shifting is white for the voltage closer to Vcom with the center at Vcom and black for the voltage farther from Vcom. Therefore, in this example, the white level is $Vcom - Vb/2$ and the black level is $Vcom + Vb/2$. Furthermore, at an adjacent pixel as shown on the right side in FIG. 3, the voltage has a second polarity that is opposite to that of the first polarity so that the white level is $Vcom + Vb/2$ and the black level is $Vcom - Vb/2$.

[0038] As shown in FIG. 2, after the pixel TFT **10** is turned on and the data write operation ends, the capacitance lines SC-A and SC-B shift only by a predetermined voltage ΔV_{sc} . In this example, a normally white TN liquid crystal is used. Regarding the pixel on the left side of FIG. 3, the capacitance line SC-A is connected and Vsc shifts only by ΔV_{sc} toward an increase in voltage. Furthermore, regarding the pixel on the right side of FIG. 3, the capacitance line SC-B is connected and Vsc shifts only by ΔV_{sc} toward a decrease in voltage.

[0039] As a result, as shown in FIG. 3, the data signal applied to the pixel electrode shifts only by a voltage corresponding to ΔV_{sc} and is applied across Vcom. Here, ΔV_{sc} is set as a voltage corresponding to threshold voltage Vath where a change in transmissivity starts in accordance with the voltage applied to the liquid crystal, and the voltage subsequent to shifting makes it possible to perform display operations on the liquid crystal element **12**. Furthermore, the dynamic range of the data signal is set so that the dynamic range subsequent to shifting becomes the potential difference of the white level from the black level in the display.

[0040] In FIG. 3, $V_a(W)$ is the amount of shift of the data signal for the white level and $V_a(B)$ is the amount of shift of the data signal for the black level. Therefore, these

amounts of shift are determined by ΔV_{sc} . Furthermore, V_b is the potential difference (dynamic range) of the black level and the white level of the data signal and V_b' is the dynamic range subsequent to shifting.

[0041] The use of a normally-black vertically aligned (VA) type is shown in FIG. 4. In this manner, the data signal has the potential difference (dynamic range) of V_b , and the voltage applied to the pixel electrode subsequent to shifting is black for the voltage closer to V_{com} with the center at V_{com} and white for the voltage farther from V_{com} . Therefore, in this example, the black level is $V_{com}-V_b/2$ and the white level is $V_{com}+V_b/2$. Furthermore, at an adjacent pixel as shown on the right side of FIG. 4, the voltage has a second polarity that is opposite to that of the first polarity so that the black level is $V_{com}+V_b/2$ and the white level is $V_{com}-V_b/2$.

[0042] The voltage value V_{pixel} of the pixel electrode of the liquid crystal element 12 subsequent to shifting can be expressed as follows:

$$V_{pixel}=V_{video}\pm\{(C_{sc}-C_{pa})/(C_{gs}+C_{lc}+C_{sc}+C_{pa})\}\cdot\Delta V_{sc} \quad (1)$$

[0043] In this embodiment, a TN type normally-white liquid crystal is utilized. A black display operation is performed by the application of a voltage. With the black level voltage with respect to V_{com} subsequent to shifting denoted by V_B and the dynamic range during a write operation denoted by V_b , it is necessary to satisfy the following expression to perform the black display operation.

$$\{(C_{sc}-C_{pa})/(C_{gs}+C_{lc}+C_{sc}+C_{pa})\}\cdot\Delta V_{sc}=V_B-V_b/2 \quad (2)$$

[0044] Namely, $V_b/2$ corresponds to the black level voltage with respect to V_{com} during a write operation and V_B is the black level voltage subsequent to shifting so that $V_B-V_b/2$ becomes the shift voltage.

[0045] Furthermore, the pixel circuit operates on the basis of the power source voltage V_{DD} . Therefore, a shift voltage ΔV_{sc} lower than V_{DD} becomes an operating condition.

$$\Delta V_{sc}<V_{DD} \quad (3)$$

[0046] Therefore, to satisfy expressions (2) and (3), it is necessary to form the pixel circuit.

[0047] On the other hand, the capacitance C_{lc} of the liquid crystal element 12 is determined when panel size, number of pixels, and liquid crystal to be used are determined. Furthermore, the gate-source capacitance C_{gs} of the pixel TFT 10 is determined when the size of the pixel TFT 10 is determined. Therefore, major changes cannot be made in the design stage for the display panel.

[0048] Accordingly, the capacitance C_{sc} of the storage capacitor 14 and the capacitance C_{ps} of the parasitic capacitance 16 are varied in this embodiment. Namely, if the capacitance C_{sc} of the storage capacitor 14 is increased to a certain proportion or greater compared with the capacitance C_{ps} of the parasitic capacitance 16, expression (2) can be satisfied even when setting ΔV_{sc} to a small value so that expression (3) can also be satisfied. By then setting ΔV_{sc} to a small value, it is possible to design for lower power consumption.

[0049] Furthermore, setting C_{pa} so that ΔV_{sc} does not exceed V_{DD} obviates the need for providing a special power supply for the V_{sc} voltage generator circuit. Furthermore,

advantages can be realized, such as lower power consumption, improved pixel aperture ratio, and so forth.

[0050] The parasitic capacitance 16 is provided at the same level as the gate electrode and an interlayer insulating film and a planarization film are found between it and the pixel electrode. Thickening this planarization film makes it possible to reduce the parasitic capacitance 16. On the other hand, to increase the storage capacitor 14, the gate oxide film may be made thinner. The capacitance of the storage capacitor 14 can be easily changed by changing its area. These techniques permit the capacitances of the storage capacitor 14 and the parasitic capacitance 16 to be adjusted.

SPECIFIC EXAMPLE

[0051] When configured so that $C_{sc}=320$ fF, $C_{pa}=10$ fF, $C_{lc}=430$ fF, $C_{gs}=3$ fF, $\Delta V_{sc}=5.58$, $V_B=3.5$ V, $V_b=2.5$ V, and $V_{DD}=8.5$ V:

$$\{(320-C_{pa})/(3+430+320+C_{pa})\}\cdot\Delta V_{sc}=3.5-2.5/2$$

[0052] Furthermore:

$$\Delta V_{sc}<8.5$$

[0053] Therefore, in this case, $C_{pa}<95$ fF can be derived for the capacitance of the parasitic capacitance 16.

[0054] For example, when C_{pa} is greater than or equal to 95 fF and this condition is not satisfied, the shift voltage becomes insufficient and the black level display is not performed properly.

[0055] Furthermore, the voltage value V_{pixel} of the pixel electrode of the liquid crystal element 12 subsequent to shifting can be expressed as follows (identical to expression (1) given above):

$$V_{pixel}=V_{video}\pm\{(C_{sc}-C_{pa})/(C_{gs}+C_{lc}+C_{sc}+C_{pa})\}\cdot\Delta V_{sc}$$

[0056] When C_{gs} and C_{pa} are substantially smaller than C_{sc} and C_{lc} , V_{pixel} can be expressed as follows:

$$V_{pixel}\approx V_{video}\pm C_{sc}/(C_{lc}+C_{sc})\cdot\Delta V_{sc}$$

[0057] Furthermore, the molecules in the TN liquid crystal are aligned in parallel with respect to the electrodes in the state where voltage is not applied, at which time the dielectric constant $\epsilon_{//}$ is smaller compared to the dielectric constant $\epsilon_{\perp}$ when the molecules are vertically aligned with respect to the electrodes in the state where voltage is applied. Namely, $\epsilon_{\perp}>\epsilon_{//}$. Furthermore, C_{lc} , which is the capacitance of the liquid crystal element, is determined by the dielectric constant of the liquid crystal material. Thus, $C_{lc\perp}>C_{lc//}$.

[0058] For this embodiment, a TN-type normally white liquid crystal is utilized. Accordingly, a black display operation is performed by the application of a voltage. With the black level voltage with respect to V_{com} subsequent to shifting denoted by V_B , the dynamic range during a write operation denoted by V_b , the black level voltage shift denoted by $V_a(B)$, and the white level voltage shift denoted by $V_a(W)$, $V_a(B)$ and $V_a(W)$ can be expressed as follows:

$$V_a(B)=C_{sc}/(C_{lc\perp}+C_{sc})\cdot\Delta V_{sc}$$

$$V_a(W)=C_{sc}/(C_{lc//}+C_{sc})\cdot\Delta V_{sc}$$

[0059] Thus, $V_a(W)>V_a(B)$.

[0060] Furthermore, the dynamic range Vb' subsequent to shifting is expressed as follows:

$$Vb' = Vb - \{Va(W) - Va(B)\}$$

[0061] Thus, $Vb' < Vb$.

[0062] From these relationships, changing the magnitude of ΔVsc enables $Va(B)$, $Va(W)$, and Vb' to be changed.

[0063] In this embodiment, as described hereinbefore, $Vsc(H)$ and $Vsc(L)$ are changed by the setting signal so that the difference of both signals, ΔVsc , is changed. Due to the change in ΔVsc , the brightness and contrast are then adjusted. Namely, the brightness changes as $Va(B)$ and $Va(W)$ change, the contrast changes as Vb' changes, and the brightness and contrast are adjusted by the adjustment of ΔVsc .

[0064] The pixel circuit operates on the basis of the power source voltage VDD . Therefore, it is preferable for the shift voltage ΔVsc to be lower than VDD so as to satisfy $\Delta Vsc < VDD$.

[0065] FIG. 5 shows a schematic planar structure of a display panel. In this manner, the DL data line is disposed for each column in the column (vertical scan) direction and two capacitance lines, SC-A and SC-B, are disposed at each row in the row (horizontal scan) direction.

[0066] Although the DL data lines have a linear form and the same width, this is not necessary. Due to light shading between pixels, it is preferable to widen the line width at those points when DL data lines are used. Furthermore, in the case of a delta arrangement, the DL data lines inevitably become curved.

[0067] Furthermore, the capacitance lines SC-A and SC-B widen at the places where the storage capacitor 14 is formed to yield the capacitance. Moreover, in this example, part of the adjacent pixel is also utilized for the storage capacitor 14. Namely, by extending the semiconductor layer (electrode on the opposite side of the storage capacitor line SC-A) that forms the storage capacitor 14 in the pixel on the left side of the figure, parts between pixels and of adjacent pixels are also utilized for the storage capacitor 14. Furthermore, as will be described hereinafter, the lower part of the data line is also utilized as part of the storage capacitor 14.

[0068] It is preferable to narrow the line widths only at the intersections between the DL data lines and the storage capacitor lines SC-A and SC-B so as to reduce the areas at these intersections.

[0069] The areas at the intersections of the storage capacitor lines SC-A and SC-B and the DL data lines are made uniform. As a result, the values of the parasitic capacitances formed from the storage capacitor lines SC-A and SC-B with the DL data lines become uniform and the fluctuations in potential of the DL data lines during inversion of the storage capacitor lines SC-A and SC-B can be reduced so as to minimize any adverse effect on the display.

[0070] FIG. 6 shows a cross section of a part where one storage capacitor line SC is disposed. In this manner, on a glass substrate 100 is provided a buffer layer 102 on which is provided a semiconductor layer SCL. Although the semiconductor layer SCL forms the pixel TFT 10, the part shown forms the storage capacitor 14. On the semiconductor layer SCL is formed an oxide film 104. The oxide film 104 is

formed by a process identical to that for the gate oxide film of the pixel TFT 10. On the gate oxide film 104 is formed the storage capacitor line SC. The storage capacitor line SC is formed by a process identical to that for the gate electrode of the pixel TFT 10.

[0071] On the storage capacitor line SC is formed an interlayer insulating film 106 on which the data line DL is formed.

[0072] Furthermore, a planarization layer 108 is formed to cover the data line DL and on it is formed a pixel electrode 30. Although not shown, a liquid crystal layer is provided via an alignment film the pixel electrode 30 and on it is disposed an opposing substrate formed with a common electrode to sandwich the liquid crystal layer.

[0073] In this manner, the storage capacitor line SC and the data line DL oppose each other via the interlayer insulating film 106 at the intersection. Therefore, a capacitance develops at this part. In this example, the semiconductor layer SCL extends below the intersection and is utilized as part of the storage capacitor 14.

[0074] Furthermore, FIG. 7 shows the transmissivity with respect to an applied voltage to the TN liquid crystal and to the VA liquid crystal. In the case of the TN liquid crystal, as the voltage applied to the liquid crystal is raised, the initial transmissivity is at a certain high level (white level), and when the voltage applied to the liquid crystal exceeds a threshold voltage, the transmissivity begins to decrease. Thereafter, the transmissivity decreases at a certain rate until a certain low level (black level). On the other hand, in the case of the VA liquid crystal, when the voltage applied to the liquid crystal is raised, the initial transmissivity is at a certain low level (black level), and when the voltage applied to the liquid crystal exceeds a threshold voltage, the transmissivity begins to increase. Thereafter, the transmissivity increases at a certain rate until a certain high level (white level).

[0075] Furthermore, although the voltage range (dynamic range) necessary for the display in the TN liquid crystal and in the VA liquid crystal differs as shown in FIG. 7, the voltage range can be adjusted by changing ΔVsc in this embodiment.

[0076] In the SC driver 22 in this embodiment, the power source voltages VDD and VSS used in the vertical driver 20 or the voltages input by the panel are utilized for the H level voltage ($V_{sc}(H)$) and/or L level voltage ($V_{sc}(L)$) in the capacitance lines SC (SC-A or SC-B). Besides VDD and VSS , a GND potential is also supplied to the vertical driver 20. Namely, the vertical driver 20 includes the shift register for driving the gate line GL and utilizes the GND potential in the shift register. Accordingly, the GND potential can also be used for one of either the H level voltage ($V_{sc}(H)$) or the L level voltage ($V_{sc}(L)$). Moreover, another potential is usable provided that potential is input by the panel. Therefore, it is preferable to utilize the potentials utilized in the vertical driver 20 for both the H level voltage ($V_{sc}(H)$) and the L level voltage ($V_{sc}(L)$) in the SC driver 22. In the description hereinafter, an example is given where VDD or VSS is basically utilized for either the H level voltage ($V_{sc}(H)$) or the L level voltage ($V_{sc}(L)$).

[0077] Namely, as shown in FIG. 8, a display control signal, which becomes an H level, is supplied to the control

terminals of switches SW1 and SW2 for the period where the H level is supplied to the capacitance line SC. Switches SW1 and SW2 are respectively an n-channel TFT and a p-channel TFT connected in parallel. The gate of the p-channel TFT of switch SW1 and the gate of the n-channel TFT of switch SW2 are connected and to this connection is supplied a display control signal that has been inverted by an inverter. The display control signal is supplied to the gate of the n-channel TFT of switch SW1 and the gate of the p-channel TFT of switch SW2. Furthermore, VDD or V_{SC} (H) is input by the input of switch SW1 and V_{SC} (L) or VSS is input by the input of switch SW2, for example. The outputs of switches SW1 and SW2 are connected to the capacitance line SC-A or SC-B.

[0078] Namely, although the SC driver 22 requires two voltages to drive the capacitance lines SC-A and SC-B, either one or both voltages in this embodiment is set as VDD or VSS to be utilized in the vertical driver 20. For example, when V_{SC} (L) is utilized for the L level, the H level is VDD, and when V_{SC} (H) is utilized for the H level, the L level is VSS or the voltage that is input by the panel. Therefore, since only one of either V_{SC} (H) or V_{SC} (L) and not both need be generated, the power source circuit can be simplified. Furthermore, since the SC driver 22 is provided in proximity to the vertical driver 20, the wiring for VDD or VSS to be input by the vertical driver 20 for input by the SC driver 22 may be short.

[0079] For the circuit shown in FIG. 8, one circuit is provided per capacitance line SC (SC-A or SC-B). V_{SC} (L) is determined with respect to VDD or VSC (H) is determined with respect to VSS so that, for example, the difference between the H level and the L level becomes ΔV_{SC} .

[0080] Due to the circuit of FIG. 8, when the display control signal is at the H level switch SW1 turns on so that V_{SC} (H), for example, is output, and when the display control signal is at the L level, switch SW2 turns on so that V_{SS} , for example, is output.

[0081] The configuration and operation of a pixel in a VA mode display device using VA liquid crystals are described herein with reference to FIG. 9 (a) to FIG. 9 (c).

[0082] FIG. 9 (a) and FIG. 9 (b) are schematic cross sections of the VA mode liquid crystal display device (LCD) using VA liquid crystals along line A-A of the LCD having the schematic cross section shown in FIG. 9 (c). This LCD normally employs a rubbing-less type alignment film where a rubbing process is not performed. For this reason, the initial alignment of the liquid crystal has no pre-tilt angle, and when voltage is not applied, the direction of the major axis of the liquid crystal molecule is aligned facing the normal line of the substrate. As shown in FIG. 9 (a) and FIG. 9 (b) where a liquid crystal molecule 60 is initially aligned in the vertical direction, as a voltage is applied between the pixel electrode 30 and a common electrode 40 of the LCD, a weak electric field (refer to electric lines of force indicated by dotted lines in the figure) generated in a state of low initial voltage is tilted at an angle, such as at the end of the pixel electrode 30. The direction along which the liquid crystal molecule slants following the rise in voltage is defined according to this tilted electric field.

[0083] As shown in the figure, an alignment dividing part 50 is provided within the region for each one pixel so that

a plurality of regions within the one pixel region can be divided into various directions. In the example of FIG. 9 (a)-(c), the alignment dividing part 50 is formed by providing projections on electrodes and electrode-free regions (windows) so that a pattern extends in the form of polygonal lines respectively in the vertical direction on the screen for both the common electrode 40 and the pixel electrode 30. It should be noted that the alignment dividing part 50 is not limited to this pattern and may be formed, for example, by providing electrode-free regions (windows) and projections in a pattern where the lengthwise top end and bottom end within one pixel are divided in a forked manner. Due to the alignment dividing part 50 as shown in FIG. 9 (a) and FIG. 9 (b), the boundary of the liquid crystal alignment direction within one pixel can be fixed at the dividing part 50, and the boundary position within the pixel of the direction in which the liquid crystal molecule tilts differs depending on the pixel and the particular drive timing so as to prevent an adverse effect on the display quality, such as display flickering.

[0084] In the embodiment, the display operation is performed only by the light from a light source, such as one disposed in the back of the panel, so that it is applicable to any type of transmissive LCDs employing transparent conducting electrodes, such as ITO, for both the pixel electrodes and common electrode, reflective LCDs that perform display operations by reflecting ambient light using reflective metal electrodes for the pixel electrodes, and also semi-transmissive LCDs that function in a transmissive mode when a light source is used and in a reflective mode when the light source is turned off. Although improvements, such as greater contrast, are demanded in reflective LCDs and semi-transmissive LCDs, performing polarity inversion as in the embodiment makes it possible to perform display operations at a sufficiently high contrast even with reflective or semi-transmissive LCDs in the ECB mode, for example.

What is claimed is:

1. A display device having pixel circuits disposed in a matrix, each pixel circuit comprising:

- a pixel TFT that is turned on and off by connecting one end to a data line for supplying a data signal, connecting a gate to a selection line, and setting a selection signal on the selection line to an H level or an L level;
- a storage capacitor for storing a voltage of the data signal supplied from the data line, one end of which is connected to another end of the pixel TFT and the other end of which is connected to a storage capacitor line; and
- a liquid crystal element for applying a voltage to a liquid crystal between electrodes, one electrode of which is connected to said another end of the pixel TFT and the other electrode of which is held at a common electrode potential;

wherein said storage capacitor line, after said pixel TFT is turned on and the data signal on the data line is written to the storage capacitor, changes from a first level to a second level; and

either said first level or said second level is used in common with one of a plurality of voltage levels which are used in vertical driver which drives the said selection line.

2. A display device according to claim 1, wherein:

two types of data signals having opposite polarities with respect to said common electrode potential are supplied to said data line;

said storage capacitor line is provided with two lines to correspond to each pixel circuit row, a plurality of pixel circuits disposed in a row direction are connected to at least one of the two storage capacitor lines and said two storage capacitor lines are controlled by two types of potentials; and

the potential of said two storage capacitor lines is set in accordance with said data signal that is supplied in each pixel circuit.

3. A display device according to claim 2, wherein:

when one potential of said two types of potentials shifts in a positive to negative direction or a negative to positive direction, the other potential shifts in an opposite direction.

4. A display device according to claim 2, wherein:

said two storage capacitor lines are connected alternately to each pixel circuit in the row direction.

5. A display device according to claim 2, wherein:

the expressions (i), (ii) below are satisfied

$$\{(C_{sc}-C_{pa})/(C_{gs}+C_{lc}+C_{sc}+C_{pa})\}*\Delta V_{sc}=VB-V_{cont}/2 \quad (i)$$

$$\Delta V_{sc}<VDD \quad (ii)$$

where

capacitance of said storage capacitor is C_{sc} ;

parasitic capacitance developed at a node of said pixel electrode and said storage capacitor line connected to an adjacent pixel circuit is C_{pa} ;

gate-source capacitance developed at a node of said pixel electrode and the gate of said pixel TFT is C_{gs} ;

capacitance of said liquid crystal element is C_{lc} ;

voltage value to be shifted in said storage capacitor line is ΔV_{sc} ;

potential difference of a black level voltage and a white level voltage of said data signal is V_{cont} ;

a black level voltage subsequent to voltage shifting is VB ; and

voltage of a power source supplying power to operate pixel circuits is VDD .

6. A display device having pixel circuits disposed in a matrix, each pixel circuit comprising:

a pixel TFT that is turned on and off by connecting one end to a data line for supplying a data signal, connecting a gate to a selection line, and setting a selection signal on the selection line to an H level or an L level;

a storage capacitor for storing a voltage of the data signal supplied from the data line, one end of which is connected to another end of the pixel TFT and the other end of which is connected to a storage capacitor line; and

a liquid crystal element for applying a voltage to a liquid crystal between electrodes, one electrode of which is connected to said another end of the pixel TFT and the other electrode of which is held at a common electrode potential;

wherein said storage capacitor line, after said pixel TFT is turned on and the data signal on the data line is written to the storage capacitor, changes from a first level to a second level causing a voltage to be applied to the liquid crystal element to shift;

said storage capacitor line is provided with two lines to correspond to each pixel circuit row, a plurality of pixel circuits disposed in a row direction are connected to at least one of the two storage capacitor lines and the two storage capacitor lines are controlled by two types of potentials; and

the expressions (i), (ii) below are satisfied

$$\{(C_{sc}-C_{pa})/(C_{gs}+C_{lc}+C_{sc}+C_{pa})\}*\Delta V_{sc}=VB-V_{cont}/2 \quad (i)$$

$$\Delta V_{sc}<VDD \quad (ii)$$

where

capacitance of said storage capacitor is C_{sc} ;

parasitic capacitance developed at a node of said pixel electrode and said storage capacitor line connected to an adjacent pixel circuit is C_{pa} ;

gate-source capacitance developed at a node of said pixel electrode and the gate of said pixel TFT is C_{gs} ;

capacitance of said liquid crystal element is C_{lc} ;

voltage value to be shifted in said storage capacitor line is ΔV_{sc} ;

potential difference of a black level voltage and a white level voltage of said data signal is V_{cont} ;

a black level voltage subsequent to voltage shifting is VB ; and

voltage of a power source supplying power to operate pixel circuits is VDD .

7. A display device according to claim 6, wherein:

when one potential of said two types of potentials shifts in a positive to negative direction or a negative to positive direction, the other potential shifts in an opposite direction.

* * * * *

专利名称(译)	显示设备		
公开(公告)号	US20050264509A1	公开(公告)日	2005-12-01
申请号	US11/133950	申请日	2005-05-20
[标]申请(专利权)人(译)	森达三 广泽KOJI 横山良一		
申请(专利权)人(译)	森达三 广泽KOJI 横山良一		
当前申请(专利权)人(译)	SANYO ELECTRIC CO. , LTD.		
[标]发明人	SENDA MICHIRU HIROSAWA KOJI YOKOYAMA RYOICHI		
发明人	SENDA, MICHIRU HIROSAWA, KOJI YOKOYAMA, RYOICHI		
IPC分类号	G02F1/1362 G09G3/36		
CPC分类号	G02F1/1362		
优先权	2004152489 2004-05-21 JP 2004152497 2004-05-21 JP 2004152485 2004-05-21 JP 2004152493 2004-05-21 JP		
其他公开文献	US7696960		
外部链接	Espacenet USPTO		

摘要(译)

存储电容器线的电平在两种类型之间变化，H电平和L电平。作为该变化的结果，施加到液晶的电压被移位，使得足够的电压施加到液晶以执行显示操作。然后，存储电容器线的两个电压电平中的至少一个与用于驱动所述选择线的垂直驱动器中的至少一个电压电平的电位共用。此外，存储电容器线的存储电容和寄生电容的值被设置在特定范围内。

