



US 20090135323A1

(19) United States

(12) Patent Application Publication

Yang et al.

(10) Pub. No.: US 2009/0135323 A1

(43) Pub. Date: May 28, 2009

(54) LIQUID CRYSTAL DISPLAY

(75) Inventors: **Young-Chol Yang**, Seongnam-si (KR); **JianGang Lu**, Suwon-si (KR); **Seung-Hoon Lee**, Yongin-si (KR)

Correspondence Address:
F. CHAU & ASSOCIATES, LLC
130 WOODBURY ROAD
WOODBURY, NY 11797 (US)

(73) Assignee: **Samsung Electronics, Co., Ltd.**, Suwon-si, (KR)

(21) Appl. No.: **12/275,673**

(22) Filed: **Nov. 21, 2008**

(30) Foreign Application Priority Data

Nov. 26, 2007 (KR) 10-2007-0121092

Publication Classification

(51) Int. Cl.
G02F 1/1343 (2006.01)
G02F 1/133 (2006.01)

(52) U.S. Cl. **349/37; 349/48; 349/39**

(57) ABSTRACT

A liquid crystal display includes first and second gate lines arranged in parallel to each other and sequentially transmitting a gate voltage, a data line crossing the first and second gate lines and transmitting a data voltage, a pixel electrode constituted by first and second sub-pixel electrodes and electrically disconnected from each other, a first switching element connected to the first gate line, the data line, and the first sub-pixel electrode, a second switching element connected to the first gate line, the data line, and the second sub-pixel electrode, a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor, and a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.





FIG. 1


FIG. 2

FIG. 3




FIG. 4





FIG. 5

FIG. 6




FIG. 7





FIG. 8

LIQUID CRYSTAL DISPLAY

CROSS-REFERENCE TO RELATED APPLICATION

[0001] This application is based on and claims priority from Korean Patent Application No. 10-2007-0121092 filed on Nov. 26, 2007, the disclosure of which is incorporated by reference herein.

BACKGROUND OF THE INVENTION

[0002] 1. Technical Field

[0003] The present invention relates to a display apparatus, and, more particularly, to a liquid crystal display.

[0004] 2. Discussion of the Related Art

[0005] A liquid crystal display is one of the most widely used flat panel displays. Liquid crystal displays include two panels provided with field-generating electrodes such as pixel electrodes and a common electrode and a liquid crystal layer interposed therebetween. The liquid crystal display displays images by applying voltages to the field-generating electrodes to generate an electric field in the liquid crystal layer, which determines orientations of liquid crystal molecules in the liquid crystal layer to adjust polarization of incident light.

[0006] A vertical alignment mode liquid crystal display, in which liquid crystal molecules are aligned such that the long axes of the liquid crystal molecules are perpendicular to the two panels (i.e., upper and lower panels) in the absence of an electric field, has become the focus of attention because of its high contrast ratio and wide reference viewing angle, which is defined as a viewing angle making the contrast ratio equal to 1:10 or as a limit angle for the inversion in luminance (brightness) between the grays.

[0007] In the vertical alignment mode liquid crystal display, the wide viewing angle can be achieved by forming cutouts in field-generating electrodes and forming protrusions on the field-generating electrodes. Since the cutouts and the protrusions can determine the tilt directions of the liquid crystal LC molecules, the tilt directions can be distributed into several directions by using the cutouts and the protrusions such that the reference viewing angle is widened.

[0008] The conventional vertical alignment mode liquid crystal display has relatively poor lateral visibility compared with front visibility. For example, a patterned VA (PVA) mode LCD having the cutouts shows an image that becomes bright as it goes far from the front, and, in the worst case, the luminance difference between high grays vanishes such that the images cannot be perceived.

SUMMARY OF THE INVENTION

[0009] Accordingly, embodiments of the present invention provide a liquid crystal display which can prevent a reduction in the brightness of the display while improving lateral visibility.

[0010] According to an exemplary embodiment of the present invention, there is provided a liquid crystal display including first and second gate lines arranged in parallel to each other and sequentially transmitting a gate voltage, a data line crossing the first and second gate lines and transmitting a data voltage, a pixel electrode constituted by first and second sub-pixel electrodes electrically disconnected from each other, a first switching element connected to the first gate line, the data line, and the first sub-pixel electrode, a second switching element connected to the first gate line, the data line, and the second sub-pixel electrode, a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor, and a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.

line, and the second sub-pixel electrode, a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor, and a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.

[0011] According to another exemplary embodiment of the present invention, there is provided a liquid crystal display including a gate driver driving first and second gate lines arranged in parallel to each other and sequentially transmitting a gate voltage, a data driver driving a data line crossing the first and second gate lines and transmitting a data voltage, a signal controller controlling the gate driver and the data driver, a pixel electrode constituted by first and second sub-pixel electrodes electrically disconnected from each other, a first switching element connected to the first gate line, the data line, and the first sub-pixel electrode, a second switching element connected to the first gate line, the data line, and the second sub-pixel electrode, a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor; and a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] Exemplary embodiments of the present invention will become apparent by reference to the following detailed description taken in conjunction with the accompanying drawings, wherein:

[0013] FIG. 1 is a block diagram of a liquid crystal display according to an exemplary embodiment of the present invention;

[0014] FIG. 2 is an equivalent circuit diagram of one pixel of the liquid crystal display shown in FIG. 1;

[0015] FIG. 3 is a graph showing the relationship between a data voltage and a pixel voltage in the liquid crystal display shown in FIG. 1;

[0016] FIG. 4 is an equivalent circuit diagram of one pixel of a liquid crystal display according to an exemplary embodiment of the present invention;

[0017] FIG. 5 is a graph showing the relationship between a data voltage and a pixel voltage in the liquid crystal display shown in FIG. 3;

[0018] FIG. 6 is a block diagram of a liquid crystal display according to an exemplary embodiment of the present invention;

[0019] FIG. 7 is an equivalent circuit diagram of one pixel of the liquid crystal display shown in FIG. 6; and

[0020] FIG. 8 is a graph showing the relationship between a data voltage and a pixel voltage in the liquid crystal display shown in FIG. 6.

DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

[0021] Hereinafter, exemplary embodiments of the present invention will be described in detail with reference to the accompanying drawings. Like reference numerals refer to like elements throughout the specification and drawings.

[0022] Referring to FIG. 1, the liquid crystal display includes a liquid crystal panel assembly 300, a gate driver 400 and a data driver 500 operatively connected to the liquid crystal panel assembly 300, a gray-voltage generator 800

operatively connected to the data driver **500**, and a signal controller **600** for controlling the gate driver **400** and the data driver **500**.

[0023] The liquid crystal panel assembly **300** includes a plurality of display signal lines (gate lines G_1-G_n and data lines D_1-D_m) and a plurality of pixels **PX** connected to the signal lines and arranged in a matrix. The liquid crystal panel assembly **300** includes lower and upper panels which face each other and a liquid crystal layer interposed between the panels (not shown).

[0024] The display signal lines include a plurality of gate lines G_1-G_n for transmitting gate signals (also referred to as scan signals) and a plurality of data lines D_1-D_m for transmitting data signals to individual pixels. The gate lines G_1-G_n substantially extend in a row (e.g., horizontal) direction and are parallel to each other, and the data lines D_1-D_m substantially extend in a column (e.g., vertical) direction and are perpendicular to the gate lines G_1-G_n .

[0025] Each pixel **PX** includes a switching element connected to one of the gate lines G_1-G_n and to one of the data lines D_1-D_m , a liquid crystal (LC) capacitor operatively connected to the switching element, and a storage capacitor. The storage capacitor may be cascade-connected to the switching element and the LC capacitor if necessary.

[0026] The switching element of each pixel **PX** is composed of a thin film transistor (TFT) and is a three-terminal element having a control terminal connected to each of the gate lines G_1-G_n , an input terminal connected to each of the data lines D_1-D_m , and an output terminal connected to the LC capacitor.

[0027] The gate driver **400** is connected to the gate lines G_1-G_n of the liquid crystal panel assembly **300**, applies the gate signals (composed of a combination of a gate-on voltage V_{on} and a gate-off voltage V_{off}) to the gate lines G_1-G_n . Although FIG. 1 shows that the gate driver **400** is provided at one side of the liquid crystal panel assembly **300** to be connected to the gate lines G_1-G_n , the invention is not limited thereto, a pair of gate drivers may be provided at opposite sides of the liquid crystal panel assembly **300** to be connected to the respective gate lines G_1-G_n at the same time. In a large liquid crystal display, for example, it is difficult to transmit the gate-on voltage V_{on} or the gate-off voltage V_{off} to the gate lines G_1-G_n using only one gate driver. Thus, a couple of gate drivers are provided at opposite sides of each of the gate lines G_1-G_n . The gate driver **400** can be incorporated into the lower panel of the liquid crystal assembly **300** as an IC chip having one or more TFTs.

[0028] The gray voltage generator **800** generates a gray voltage associated with the transmission of each pixel. The gray voltage is provided to each pixel and has a positive polarity and a negative polarity with respect to a common voltage V_{com} .

[0029] The data driver **500** is connected to the data lines D_1-D_m of the liquid crystal panel assembly **300**, and applies the gray voltage output from the gray voltage generator **800** to each pixel as a data voltage. When the gray voltage generator **800** only provides a predetermined number of reference gray voltages instead of supplying gray voltages for all grays, the data driver **500** generates a gray voltage for all grays by dividing the reference gray voltage, and selects one among them.

[0030] The gate driver **400** or the data driver **500** may be integrated in the liquid crystal panel assembly **300** together with the display signal lines G_1-G_n and D_1-D_m and TFTs may

be mounted on a flexible printed circuit film (not shown) to be attached to the liquid crystal panel assembly **300** in a tape carrier package form.

[0031] The data driver **500** can be mounted directly on a liquid crystal panel assembly **300** as an IC chip. Alternatively, the data driver **500** can be attached on the liquid crystal panel assembly **300** as a TCP by being mounted on a flexible printed circuit film (not shown).

[0032] The signal controller **600** controls the gate driver **400** and the data driver **500**.

[0033] The signal controller **600** receives an input control signal including a vertical synchronization signal V_{sync} , a horizontal synchronizing signal H_{sync} , a main clock signal $MCLK$, a data enable signal DE , and others, from an external graphics controller (not shown) for controlling display of input image signals R , G and B . The signal controller **600** processes image signals R , G and B based on the input image signals R , G , and B and the input control signals received by the signal controller **600** to be suitable to an operating condition of the liquid crystal panel assembly **300**. Then, the signal controller **600** generates a gate control signal **CONT1** and a data control signal **CONT2**, and outputs them to the gate driver **400** and data driver **500**, respectively.

[0034] The gate control signal **CONT1** includes a scan start signal STV indicating the start of an operation, e.g., scanning, of the gate driver **400**, and at least one clock signal for controlling output time of the gate-on voltage V_{on} . The gate control signal **CONT1** may further include an output enable signal OE for defining the duration of the gate-on voltage V_{on} .

[0035] The data control signal **CONT2** includes a horizontal synchronization start signal STH that indicates that valid data is transmitted to a row of pixels, a load signal $LOAD$ for applying the respective data voltages to the data lines D_1-D_m , and a data clock signal $HCLK$. The data control signal **CONT2** may further include a reverse signal RVS for reversing the polarity of the data voltage with respect to the common voltage V_{com} , which is referred to as the "polarity of the data voltage" hereinafter.

[0036] The data driver **500** receives image data DAT for each pixel **PX**, selects gray voltages corresponding to the image data DAT supplied from the gray voltage generator **800** in response to the data control signals **CONT2** from the signal controller **600**, converts the image data DAT into corresponding data voltages, and applies the converted data voltages to the respective data lines D_1-D_m .

[0037] The gate driver **400** sequentially applies the gate-on voltage V_{on} to the gate lines G_1-G_n and turns ON the switching elements connected to the gate lines G_1-G_n in accordance with the gate control signal **CONT1** output from the signal controller **600**. The data voltages applied to the data lines D_1-D_m are applied to each pixel **PX** through the turned-ON switching elements.

[0038] The difference between the common voltage V_{com} and the data voltage applied to the data line of each pixel **PX** is applied across the pixel and appears as a charge voltage of the LC capacitor, that is, a pixel voltage. The arrangement (orientations) of liquid crystal molecules varies depending on the size of the pixel voltage and thus the polarization of the light passing through the liquid crystal layer varies. The liquid crystal molecules have orientations depending on the magnitude of the pixel voltage and the orientations determine the polarization of light passing through the LC capacitor.

[0039] In the liquid crystal display according to an exemplary embodiment of the present invention, after applying the

same data voltage to a pair of sub pixels constituting each pixel PX, the gate-on voltage Von is applied to a gate line adjacent to the gate line corresponding to the pair of sub pixels. In this case, the data voltage charged in either one of the sub pixels is decreased by charge sharing. Since the sub pixels of the same pixel electrode are charged with different voltages, a gamma curve of a pixel PX becomes a merged gamma curve of the two sub pixels. When the data voltages charged in the respective sub pixels are determined by charge sharing, the frontal merged gamma curve is made to be close to the frontal reference gamma curve, and the lateral merged gamma curve is made to be closest to the frontal reference gamma curve and the frontal merged gamma curve of the two sub pixels is close to the frontal reference gamma curve, thereby improving lateral visibility.

[0040] Referring to FIG. 2, the liquid crystal display according to an exemplary embodiment of the present invention includes include a plurality of gate lines GL_1 - GL_{i+1} transmitting a gate signal and a plurality of data lines DL_i crossing the gate lines GL_1 - GL_{i+1} and transmitting a data signal.

[0041] Each pixel PX includes a first sub pixel SP_1 and a second sub pixel SP_2 . The first sub pixel SP_1 includes a first switching element T_1 , a first LC capacitor C_{lc1} and a first storage capacitor C_{st1} , and the second sub pixel SP_2 includes a second switching element T_2 , a second LC capacitor C_{lc2} and a second storage capacitor C_{st2} , respectively.

[0042] A first switching element T_1 and a second switching element T_2 are formed at an intersection point of an ith gate line GL_i and an nth data line DL_i , a third switching element T_3 connected to the ith gate line GL_i , and a fourth switching element T_4 is connected to the (i+1)th gate line GL_{i+1} . The first through fourth switching elements may be thin film transistors (TFTs).

[0043] The first switching element T_1 has a control terminal connected to the ith gate line GL_i , an input terminal connected to a jth data line DL_j , and an output terminal connected to the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} . The second switching element T_2 has a control terminal connected to the ith gate line GL_i , an input terminal connected to a jth data line DL_j , and an output terminal connected to the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} . The third switching element T_3 has a control terminal connected to the ith gate line GL_i , an output terminal connected to the output terminal of the first switching element T_1 with a charge-sharing capacitor C_{CS} interdisposed therebetween, and an input terminal connected to a storage line SL. In more detail, the input terminal of the third switching element T_3 is directly connected to the storage line SL. The fourth switching element T_4 has a control terminal connected to the (i+1)th gate line GL_{i+1} , an input terminal connected to the output terminal of the second switching element T_2 , and an output terminal connected to the output terminal of the third switching element T_3 . Accordingly, the output terminal of the fourth switching element T_4 is connected to the output terminal of the first switching element T_1 with the charge-sharing capacitor C_{CS} interposed therebetween.

[0044] Each pixel PX includes a pixel electrode consisting of a first sub-pixel electrode connected to the output terminal of the first switching element T_1 , and a second sub-pixel electrode connected to the output terminal of the second switching element T_2 . A common electrode is provided on the upper panel facing the lower panel.

[0045] The first LC capacitor C_{lc1} includes a first sub-pixel electrode connected to the first switching element T_1 , a common electrode, and liquid crystals interposed therebetween. The first storage capacitor C_{st1} includes a first sub-pixel electrode, a storage electrode line SL that is provided on the lower panel with an insulator disposed therebetween.

[0046] The second LC capacitor C_{lc2} includes a second sub-pixel electrode connected to the second switching element T_2 , a common electrode, and liquid crystals interposed therebetween. The second storage capacitor C_{st2} includes a second sub-pixel electrode, a storage electrode line SL that is provided on the lower panel, and an insulator disposed between the second sub-pixel electrode and the storage electrode line SL.

[0047] The charge-sharing capacitor C_{CS} includes an output terminal of the first switching element T_1 , an output terminal of the third switching element T_3 , and an insulator disposed therebetween. The charge-sharing capacitor C_{CS} and the third switching element T_3 function to decrease the pixel voltages charged in the second LC capacitor C_{lc2} while increasing the pixel voltages charged in the first LC capacitor C_{lc1} .

[0048] The first storage capacitor C_{st1} and the second storage capacitor C_{st2} sustain pixel voltages charged in the first LC capacitor C_{lc1} and the second LC capacitor C_{lc2} , respectively. A fixed voltage, e.g., a common voltage $Vcom$, is applied to the storage line SL.

[0049] If a gate-on signal Von is applied to the ith gate line GL_i , a data voltage of the same level is transmitted to the first and second sub-pixel electrodes in the ith row of pixels through the first switching element T_1 and the second switching element T_2 . That is, the same data voltage is charged in the first LC capacitor C_{lc1} and the second LC capacitor C_{lc2} connected to the ith gate line GL_i . The data voltage charged in the first LC capacitor C_{lc1} and the second LC capacitor C_{lc2} is referred to as a pixel voltage.

[0050] If a gate-on voltage Von is applied to the ith gate line GL_i , the third switching element T_3 is turned on and the common voltage $Vcom$ is transmitted to the output terminal of the third switching element T_3 . Thus, a voltage corresponding to a difference between the data voltage and the common voltage $Vcom$ is charged in the charge-sharing capacitor C_{CS} .

[0051] If a gate-off voltage $Voff$ is then applied to the ith gate line GL_i , the first sub pixel SP_1 and the second sub pixel SP_2 are electrically disconnected from each other. That is, after a data voltage of the same level is applied to the first sub-pixel electrode and the second sub-pixel electrode, the first sub-pixel electrode and the second sub-pixel electrode are maintained at a floating state.

[0052] If the gate-on signal Von is applied to the (i+1)th gate line GL_{i+1} , a data voltage of the same level is transmitted a pair of second sub-pixel electrodes in the (i+1)th row of pixels through a first switching element (not shown) and a second switching element (not shown) connected to the (i+1)th gate line GL_{i+1} .

[0053] In addition, if the gate-on signal Von is applied to the (i+1)th gate line GL_{i+1} , the fourth switching element T_4 is turned on. Accordingly, the data voltage stored in the second sub-pixel electrode connected to the second switching element T_2 is distributed to the charge-sharing capacitor C_{CS} through the fourth switching element T_4 . This is because the input terminal of the fourth switching element T_4 is connected to the output terminal of the second switching element T_2 and the output terminal of the fourth switching element T_4 is

connected to the charge-sharing capacitor C_{CS} . Accordingly, data voltages stored in the first sub-pixel electrode and the second sub-pixel electrode in the i th row of pixels and connected to the first switching element T_1 and the second switching element T_2 will have different levels.

[0054] Next, pixel voltages of the first sub-pixel electrode and the second sub-pixel electrode will be described in detail using the principle of conservation of charge. Here, a first node N_1 is a node between the output terminal of the first switching element T_1 and the charge-sharing capacitor C_{CS} , a second node N_2 is a node between the output terminal of the second switching element T_2 and the input terminal of the fourth switching element T_4 , a third node N_3 is a node between the charge-sharing capacitor C_{CS} and the output terminal of the third switching element T_3 . The third node N_3 may also be a node between the charge-sharing capacitor C_{CS} and the output terminal of the fourth switching element T_4 .

[0055] If the gate-on signal V_{on} is applied to the i th gate line GL_i , the first switching element T_1 and the second switching element T_2 are turned on so that a data voltage Vd is applied to the first node N_1 and the second node N_2 . As the third switching element T_3 is turned on, the common voltage V_{com} is applied to the third node N_3 . For explanatory convenience, it is assumed that a common voltage V_{com} is 0 V, a data voltage Vd is defined as a relative voltage with respect to the common voltage V_{com} . Therefore, voltages applied to a first node N_1 , a second node N_2 and a third node N_3 are Vd , Vd , and 0, respectively. It is also assumed that the capacitance sum of the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} , is denoted by Ch , the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} is denoted by Cl , and the capacitance of the charge-sharing capacitor C_{CS} is denoted by Cb .

[0056] The quantity of charge Qh corresponding to the capacitance sum of the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} , the quantity of charge Ql corresponding to the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} , and the quantity of charge Qb of the charge-sharing capacitor C_{CS} are given by the following equation (1):

$$Qh = Ch \times Vd$$

$$Ql = Cl \times Vd$$

$$Qb = Cb \times Vd$$

[0057] Next, if the gate-off voltage V_{off} is applied to the i th gate line GL_i and the gate-on signal V_{on} is applied to the $(i+1)$ th gate line GL_{i+1} , the first switching element T_1 , the second switching element T_2 and the third switching element T_3 are turned off and the fourth switching element T_4 is turned on.

[0058] Assuming that voltages applied to the first node N_1 , the second node N_2 and the third node N_3 are $V1$, $V2$ and $V3$ ($=V2$), respectively, the quantity of charge Qh' corresponding to the capacitance sum of the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} , the quantity of charge Ql' corresponding to the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} and the quantity of charge Qb' of the charge-sharing capacitor C_{CS} are given by the following equation (2):

$$Qh' = Ch \times V1$$

$$Ql' = Cl \times V2$$

$$Qb' = Cb \times (V1 - V2)$$

[0059] Since total quantity of charge in capacitors connected to the first node N_3 is conserved, the following equation (3) is satisfied:

$$Qh + Qb = Qh' + Qb'$$

[0060] Since total quantity of charge in capacitors connected to the third node N_3 is conserved, the following equation (4) is satisfied:

$$Ql - Qb = Ql' - Qb'$$

[0061] Based on the relationships (1) through (4), the voltages $V1$ and $V2$ applied to the first node N_1 and the second node N_2 can be obtained using the following equation (5):

$$V1 = Vd \left(1 + \frac{C1 \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot Cl} \right)$$

$$V2 = Vd \left(1 - \frac{Ch \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot Cl} \right)$$

[0062] If a data voltage Vd is a positive-polarity voltage greater than the common voltage V_{com} (e.g., 0 V), the pixel voltage $V1$ of the first sub pixel SP_1 rises compared to the data voltage Vd , while the pixel voltage $V2$ of the second sub pixel SP_2 drops compared to the data voltage Vd . In contrast, if a data voltage Vd is a negative-polarity voltage smaller than the common voltage V_{com} (e.g., 0 V), the pixel voltage $V1$ of the first sub pixel SP_1 drops compared to the data voltage Vd , while the pixel voltage $V2$ of the second sub pixel SP_2 rises compared to the data voltage Vd . Accordingly, the absolute value of the pixel voltage $V1$ of the first sub pixel SP_1 is larger than that of the pixel voltage $V2$ of the second sub pixel SP_2 all the time.

[0063] As described above, if the pixel voltages $V1$ and $V2$ applied to the first sub pixel SP_1 and the second sub pixel SP_2 constituting one and the same pixel are different from each other, the lateral visibility can be improved. Sets of gray voltages having different gamma curves obtained from image information are stored in the first sub pixel SP_1 , and a gamma curve of a pixel constituted by the first sub pixel SP_1 and the second sub pixel SP_2 is close to the merged gamma curve of the first and second sub pixels SP_1 and SP_2 . Accordingly, when determining the sets of gray voltages, the frontal merged gamma curve is preferably made to be close to the frontal reference gamma curve and the lateral merged gamma curve is preferably made to be closest to the frontal reference gamma curve, thereby improving the lateral visibility.

[0064] FIG. 3 is a graph showing a change in the pixel voltage of a first sub-pixel electrode and a second sub-pixel electrode with respect to the data voltage applied across data lines shown in FIG. 1, in which the pixel voltage is calculated based on the charge ratio $Cl:Ch:Cb=2:1:2$, for example.

[0065] As shown in FIG. 3, when a data voltage applied to data lines is 6 V, the pixel voltage of the first sub-pixel electrode is 9 V, as represented by the plotted line (-●-), increased by 3 V, while the pixel voltage of the second sub-pixel electrode is 4.5 V, as represented by the plotted line (-○-), decreased by 1.5 V. Therefore, a sufficiently large difference can be obtained between the pixel voltages charged in the first and second sub-pixel electrodes. In particular, since a difference between the pixel voltage of the second sub-pixel electrode and the data voltage, as represented by the dotted line, is not sufficiently large, a sharp reduction in the brightness can be suppressed.

[0066] Hereinafter, a liquid crystal display according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 4 and 5. FIG. 4 is an equivalent circuit diagram of one pixel of a liquid crystal display according to an exemplary embodiment of the present invention, and FIG. 5 is a graph showing the relationship between a data voltage and a pixel voltage in the liquid crystal display shown in FIG. 3. For explanatory convenience, components each having the same function for describing the exemplary embodiment shown in FIGS. 1 through 3 are respectively identified by the same reference numerals, and their detailed descriptions will not be repeated.

[0067] Referring to FIG. 4, a third switching element T_3 has a control terminal connected to an i th gate line GL_i , an output terminal connected to the output terminal of a first switching element T_1 with a charge-sharing capacitor C_{CS} disposed therebetween, and an input terminal connected to a storage line SL . In more detail, the input terminal of the third switching element T_3 is directly connected to the storage line SL with an auxiliary capacitor C_3 disposed therebetween. The input terminal of the third switching element T_3 and the storage line SL , which are formed at different layers in the LCD manufacturing process, are quite difficult to be directly coupled to each other. In such a case, the auxiliary capacitor C_3 may be used for coupling the input terminal of the third switching element T_3 to the storage line SL .

[0068] Next, pixel voltages of the first sub-pixel electrode and the second sub-pixel electrode will be described in detail using the principle of conservation of charge. Here, a fourth node N_4 is a node between the input terminal of the third switching element T_3 and the auxiliary capacitor C_3 . For explanatory convenience, it is assumed that a common voltage V_{com} is 0 V, a data voltage Vd is defined as a relative voltage with respect to the common voltage V_{com} , and the capacitance of an auxiliary capacitor C_3 is denoted by Cc .

[0069] In addition, assuming that voltages applied to a first node N_1 , a second node N_2 , a third node N_3 and a fourth node N_4 are $V1$, $V2$, $V3$, and $V4$, respectively, for an $(n-1)$ th frame, $V2=V3$. The quantity of charge Qh corresponding to the capacitance sum of the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} , the quantity of charge Ql corresponding to the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} , the quantity of charge Qb of the charge-sharing capacitor C_{CS} , and the quantity of charge Qc of the auxiliary capacitor C_3 are given by the following equation (6):

$$Qh = Ch \times V1$$

$$Ql = Cl \times V2$$

$$Qb = Cb \times (V1 - V3) = Cb \times (V1 - V2)$$

$$Qc = Cc \times V4$$

[0070] If the gate-on signal Von is applied to the i th gate line GL_i for an n th frame, the first switching element T_1 and the second switching element T_2 are turned on so that the data voltage Vd is applied to the first node N_1 and the second node N_2 . As the third switching element T_3 is turned on, the third node N_3 and the fourth node N_4 are connected to each other. Here, assuming that voltages of the first node N_1 , the second node N_2 , the third node N_3 , and the fourth node N_4 are $V1'$, $V2'$, $V3'$, and $V4'$, respectively, $V1'=V2'=Vd$, and $V3'=V4'$.

[0071] In this case, the quantity of charge Qh' corresponding to the capacitance sum of the first LC capacitor C_{lc1} and

the first storage capacitor C_{st1} , the quantity of charge Ql' corresponding to the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} , the quantity of charge Qb' of the charge-sharing capacitor C_{CS} , and the quantity of charge Qc' of the auxiliary capacitor C_3 are given by the following equation (7):

$$Qh' = Ch \times V1' = Ch \times Vd$$

$$Ql' = Cl \times V2' = Cl \times Vd$$

$$Qb' = Cb \times (V1' - V3') = Cb \times (Vd - V3')$$

$$Qc' = Cc \times V4' = Cc \times V3'$$

[0072] Since the total quantity of charge in capacitors connected to the third node N_3 and the fourth node N_4 is conserved, the following relationship given by the equation (8) is satisfied:

$$Qc - Qb = Qc' - Qb'$$

[0073] Next, if a gate-off voltage $Voff$ is applied to the i th gate line GL_i and the gate-on signal Von is applied to the $(i+1)$ th gate line GL_{i+1} , the first switching element T_1 , the second switching element T_2 and the third switching element T_3 are turned off and the fourth switching element T_4 is turned on.

[0074] Assuming that voltages of the first node N_1 , the second node N_2 , the third node N_3 , and the fourth node N_4 are $V1''$, $V2''$, $V3''$ and $V4''$, respectively, $V2''=V3''$. In this case, the quantity of charge Qh'' corresponding to the capacitance sum of the first LC capacitor C_{lc1} and the first storage capacitor C_{st1} , the quantity of charge Ql'' corresponding to the capacitance sum of the second LC capacitor C_{lc2} and the second storage capacitor C_{st2} , the quantity of charge Qb'' of the charge-sharing capacitor C_{CS} , and the quantity of charge Qc'' of the auxiliary capacitor C_3 are given by the following equation (9):

$$Qh'' = Ch \times V1''$$

$$Ql'' = Cl \times V2''$$

$$Qb'' = Cb \times (V1'' - V3'') = Cb \times (V1'' - V2'')$$

$$Qc'' = Cc \times V4''$$

[0075] Since the total quantity of charge in capacitors connected to the first node N_1 is conserved, the following equation (10) is satisfied:

$$Qh + Qb' = Qh'' + Qb''$$

[0076] Since the total quantity of charge in capacitors connected to the third node N_3 is conserved, the following equation (11) is satisfied:

$$Ql' + Qc' - Qb' = Ql'' + Qc'' - Qb''$$

[0077] Based on the equations (6) through (11), the voltages $V1''$ and $V2''$ applied to the first node N_1 and the second node N_2 can be obtained using the following equation (12):

$$V1'' = Vd + (Vd - V0) \frac{C1 \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1}$$

$$V2'' = Vd - (Vd - V0) \frac{Ch \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1}$$

-continued

Here,

$$V_0 = \frac{(Cb \cdot Vd + Cc \cdot V4) - Cb(V1 - V2)}{Cb + Cc}.$$

[0078] Therefore, if the data voltage Vd is a positive-polarity voltage greater than the common voltage V_{com} (e.g., 0 V), the pixel voltage $V1''$ of the first sub pixel SP_1 rises compared to the data voltage Vd , while the pixel voltage $V2''$ of the second sub pixel SP_2 drops compared to the data voltage Vd . In contrast, if the data voltage Vd is a negative-polarity voltage smaller than the common voltage V_{com} (e.g., 0 V), the pixel voltage $V1''$ of the first sub pixel SP_1 drops compared to the data voltage Vd , while the pixel voltage $V2''$ of the second sub pixel SP_2 rises compared to the data voltage Vd . Accordingly, the absolute value of the pixel voltage $V1''$ of the first sub pixel SP_1 is larger than that of the pixel voltage $V2''$ of the second sub pixel SP_2 all the time.

[0079] As described above, if the pixel voltages $V1''$ and $V2''$ applied to the first sub pixel SP_1 and the second sub pixel SP_2 constituting one and the same pixel are different, the lateral visibility can be improved.

[0080] FIG. 5 is a graph showing a change in the pixel voltage of a first sub-pixel electrode and a second sub-pixel electrode with respect to the data voltage applied across data lines for each frame, in which the pixel voltage is calculated based on the charge ratio $C1:Ch:Cb:Cc=2:1:0.8:2$ and the data voltage changes from 6V to 2V to 6V, for example.

[0081] As shown in FIG. 5, the pixel voltage of the first sub pixel SP_1 rises compared to the data voltage Vd , while the pixel voltage of the second sub pixel SP_2 drops compared to the data voltage Vd . Accordingly, a sufficient difference between the pixel voltages of the first sub-pixel electrode and the second sub-pixel electrode can be obtained. In particular, since a difference between the pixel voltage of the second sub-pixel electrode and the data voltage is not sufficiently large, a sharp reduction in the brightness can be suppressed.

[0082] Hereinafter, a liquid crystal display according to an exemplary embodiment of the present invention will be described with reference to FIGS. 6 through 8. FIG. 6 is a block diagram of a liquid crystal display according to a third exemplary embodiment of the present invention, FIG. 7 is an equivalent circuit diagram of one pixel of the liquid crystal display shown in FIG. 6, and FIG. 8 is a graph showing the relationship between a data voltage and a pixel voltage in the liquid crystal display shown in FIG. 6. For explanatory convenience, components each having the same function for describing the exemplary embodiment shown in FIGS. 1 through 3 are respectively identified by the same reference numerals, and their detailed descriptions will not be repeated.

[0083] Referring to FIG. 6, in the equivalent circuit, the liquid crystal panel assembly 300 includes a plurality of display signal lines (gate lines G_1-G_n and data lines D_1-D_m) and a plurality of pixels PX connected to the signal lines and arranged in a matrix. The liquid crystal panel assembly 300 includes lower and upper panels which face each other and a liquid crystal layer interposed between the panels.

[0084] The plurality of display signal lines are provided on the lower panel and include a plurality of gate lines G_1-G_n for transmitting gate signals, a plurality of data lines DA_1-DA_m for transmitting data signals, and a plurality of charge-sharing wires DB_1-DB_m for transmitting charge sharing signals to

switching elements. The gate lines G_1-G_n substantially extend in a row direction and are substantially parallel to one another. The data lines DA_1-DA_m extend in a column direction and are substantially parallel to one another. The charge-sharing wires DB_1-DB_m extend in a direction substantially perpendicular to the data lines DA_1-DA_m .

[0085] Referring to FIG. 7, the liquid crystal display according to an exemplary embodiment, unlike the liquid crystal display previously described, a charge-sharing wire DB_j is formed to be substantially parallel to a data line DA_j in each pixel. The third switching element T_3 has a control terminal connected to the i th gate line GL_i , an output terminal connected to the output terminal of the first switching element T_1 with a charge-sharing capacitor C_{CS} interposed therebetween, and an input terminal connected to the charge-sharing wire DB_j .

[0086] A data voltage (e.g., $+|Vp|$), which is a positive-polarity data and is greater than the common voltage V_{com} , is applied to the data line DA_j , and a charge-sharing voltage (e.g., $-|Vm|$), which is negative-polarity data and is smaller than the common voltage V_{com} , is applied to the charge-sharing wire DB_j . Here, the positive-polarity voltage means a voltage greater than the common voltage V_{com} , and the negative-polarity voltage means a voltage smaller than the common voltage V_{com} .

[0087] Although in the previously described exemplary embodiment, the common voltage V_{com} is applied to the input terminal of the third switching element T_3 (that is, $V_{com}=0V$), here, a charge-sharing voltage smaller than the common voltage V_{com} , e.g., $-|Vm|$, is applied to the input terminal of the third switching element T_3 . Therefore, if the gate-on voltage Von is applied to the i th gate line GL_i and the third switching element T_3 is turned on, a voltage $|Vp|+|Vm|$ is charged in the charge-sharing capacitor C_{CS} . Therefore, charge sharing for the first sub pixel SP_1 and the second sub pixel SP_2 is more effectively performed. As the pixel voltage calculation results, as described above in the exemplary embodiment described in connection with FIGS. 1-3, pixel voltages charged in the first sub-pixel electrode and the second sub-pixel electrode, that is, voltages $V1$ and $V2$ of first and nodes N_1 and N_2 , can be given by the following equation (13):

$$V1 = |Vp| + (|Vp| + |Vm|) \frac{C1 \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1} + 2|Vm| \frac{Cb \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1}$$

$$V2 = |Vp| - (|Vp| - |Vm|) \frac{Ch \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1} + 2|Vm| \frac{Cb \cdot Cb}{C1 \cdot Ch + Ch \cdot Cb + Cb \cdot C1}$$

[0088] It can be deduced from the relationship (13) that the pixel voltage $V1$ of the first sub pixel SP_1 rises relative to the data voltage $|Vp|$ and the pixel voltage $V2$ of the second sub pixel SP_2 drops relative to the pixel voltage $V1$ of the first sub pixel SP_1 .

[0089] Further, not only the pixel voltage $V1$ of the first sub pixel SP_1 but also the pixel voltage $V2$ of the second sub pixel SP_2 may rise relative to the data voltage $|Vp|$, if the following equation (14) is satisfied:

$$\frac{|V_m|}{|V_p|} \geq \frac{Ch}{2Cb + Ch}$$

[0090] As shown in equation (14), unless $|V_m|$ is much less than $|V_p|$, the pixel voltages V_1 and V_2 can be boosted in most cases. In such cases, even if a low data voltage is supplied from a data driver, two different pixel voltages having a large level can be produced at the first sub pixel SP_1 and the second sub pixel SP_2 . In a general VA (vertical alignment) mode liquid crystal display requiring a high-level data voltage, if an appropriate charge-sharing voltage is applied to the third switching element T_3 through the charge-sharing wire DB_j , a high-level pixel voltage can be obtained even by a small data voltage. Here, the polarity of the charge-sharing voltage is preferably opposite to the polarity of the data voltage. For example, if a data voltage is a positive-polarity voltage, the charge-sharing voltage is preferably a negative-polarity voltage, if the data voltage is a negative-polarity voltage, the charge-sharing voltage is preferably a positive-polarity voltage.

[0091] The operation described above may be also true for a case where the data voltage is a negative-polarity voltage smaller than the common voltage V_{com} .

[0092] FIG. 8 is a graph showing a change in the pixel voltage of a first sub-pixel electrode and a second sub-pixel electrode with respect to the data voltage applied across data lines, in which the pixel voltage is calculated based on the charge ratio $Cl:Ch:Cb=2:1:2$, for example.

[0093] As shown in FIG. 8, when a data voltage applied to data lines is 6 V, the pixel voltage of the first sub-pixel electrode increases to 14.4 V, as represented by the plotted line (-●-), and the pixel voltage of the second sub-pixel electrode also increases to 10.8 V, as represented by the plotted line (-○-). Therefore, a sufficiently large difference can be obtained between the pixel voltages charged in the first and second sub-pixel electrodes while boosting the pixel voltages of the first and second sub-pixel electrodes. Therefore, a reduction in the brightness can be prevented.

[0094] As described above, a pixel electrode is divided into a pair of sub-pixel electrodes to produce a difference in the pixel voltage between the pair of sub-pixel electrodes by charge sharing, thereby improving the lateral visibility. In addition, a switching element is connected to one end of a charge-sharing capacitor, which makes a difference in the pixel voltage between the pair of sub-pixel electrodes, thereby further improving the lateral visibility. Further, the switching element functions to prevent the pixel voltage from sharply decreasing compared to the data voltage, thereby suppressing a reduction in the brightness by charge sharing.

[0095] While exemplary embodiments of the present invention have been described for illustrative purposes, it will be understood by those of ordinary skill in the art that various changes in form and details are possible without departing from the spirit and scope of the disclosure.

What is claimed is:

1. A liquid crystal display comprising:
first and second gate lines arranged in parallel to each other and sequentially transmitting a gate voltage;
a data line crossing the first and second gate lines and transmitting a data voltage;
a pixel electrode constituted by first and second sub-pixel electrodes electrically disconnected from each other;

a first switching element connected to the first gate line, the data line, and the first sub-pixel electrode;

a second switching element connected to the first gate line, the data line, and the second sub-pixel electrode;

a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor; and

a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.

2. The liquid crystal display of claim 1, further comprising a storage line parallel to the gate lines and transmitting a common voltage, wherein the third switching element has a control terminal connected to the first gate line, an output terminal connected to the charge-sharing capacitor, and an input terminal connected to the storage line.

3. The liquid crystal display of claim 2, wherein the input terminal of the third switching element is directly connected to the storage line.

4. The liquid crystal display of claim 3, wherein when a gate-on voltage is applied to the first gate line, a voltage corresponding to a difference between the data voltage and the common voltage is charged in the charge-sharing capacitor.

5. The liquid crystal display of claim 2, wherein the input terminal of the third switching element is connected to the storage line via an auxiliary capacitor.

6. The liquid crystal display of claim 1, further comprising a charge-sharing wire parallel to the data line and transmitting a charge-sharing voltage, wherein the third switching element has a control terminal connected to the first gate line, an output terminal connected to the charge-sharing capacitor, and an input terminal connected to the charge-sharing wire.

7. The liquid crystal display of claim 6, wherein the polarity of the charge-sharing voltage is opposite to the polarity of the data voltage.

8. The liquid crystal display of claim 6, wherein after charge sharing is performed between the pixel voltages of the first and second sub-pixel electrodes, the pixel voltages of the first and second sub-pixel electrodes are boosted relative to the data voltage.

9. The liquid crystal display of claim 8, further comprising:
a first liquid crystal (LC) capacitor and a first storage capacitor which are cascade-connected to the first switching element; and
a second LC capacitor and a second storage capacitor cascade-connected to the second switching element, wherein the data voltage and the charge-sharing voltage satisfy the following relationship:

$$\frac{|V_m|}{|V_p|} \geq \frac{Ch}{2Cb + Ch}$$

wherein V_p is a data voltage, V_m is a charge-sharing voltage, Ch denotes a capacitance sum of the first LC capacitor and the first storage capacitor, and Cb denotes a capacitance of the charge-sharing capacitor.

10. The liquid crystal display of claim 1, further comprising lower and upper panels facing each other, and a liquid crystal layer interposed between the panels.

11. A liquid crystal display comprising:
 a gate driver driving first and second gate lines arranged in parallel to each other and sequentially transmitting a gate voltage;
 a data driver driving a data line crossing the first and second gate lines and transmitting a data voltage;
 a signal controller controlling the gate driver and the data driver;
 a pixel electrode constituted by first and second sub-pixel electrodes electrically disconnected from each other;
 a first switching element connected to the first gate line, the data line, and the first sub-pixel electrode;
 a second switching element connected to the first gate line, the data line, and the second sub-pixel electrode;
 a third switching element connected to the first sub-pixel electrode across a charge-sharing capacitor; and
 a fourth switching element connected to the second gate line and the second sub-pixel electrode and connected to the first sub-pixel electrode across the charge-sharing capacitor.

12. The liquid crystal display of claim **11**, further comprising a storage line parallel to the gate lines and transmitting a common voltage, wherein the third switching element has a control terminal connected to the first gate line, an output terminal connected to the charge-sharing capacitor, and an input terminal connected to the storage line.

13. The liquid crystal display of claim **12**, wherein the input terminal of the third switching element is directly connected to the storage line.

14. The liquid crystal display of claim **13**, wherein when a gate-on voltage is applied to the first gate line, a voltage corresponding to a difference between the data voltage and the common voltage is charged in the charge-sharing capacitor.

15. The liquid crystal display of claim **12**, wherein the input terminal of the third switching element is connected to the storage line via an auxiliary capacitor.

16. The liquid crystal display of claim **11**, further comprising a charge-sharing wire parallel to the data line and transmitting a charge-sharing voltage, wherein the third switching element has a control terminal connected to the first gate line, an output terminal connected to the charge-sharing capacitor, and an input terminal connected to the charge-sharing wire.

17. The liquid crystal display of claim **16**, wherein the polarity of the charge-sharing voltage is opposite to the polarity of the data voltage.

18. The liquid crystal display of claim **16**, wherein after charge sharing is performed between the pixel voltages of the first and second sub-pixel electrodes, the pixel voltages of the first and second sub-pixel electrodes are boosted relative to the data voltage.

19. The liquid crystal display of claim **18**, further comprising:
 a first liquid crystal (LC) capacitor and a first storage capacitor which are cascade-connected to the first switching element; and
 a second LC capacitor and a second storage capacitor cascade-connected to the second switching element, wherein the data voltage and the charge-sharing voltage satisfy the following relationship:

$$\frac{|V_m|}{|V_p|} \geq \frac{C_h}{2C_b + C_h}$$

wherein V_p is a data voltage, V_m is a charge-sharing voltage, C_h denotes a capacitance sum of the first LC capacitor and the first storage capacitor, and C_b denotes a capacitance of the charge-sharing capacitor.

20. The liquid crystal display of claim **11**, further comprising lower and upper panels facing each other and a liquid crystal layer interposed between the panels.

* * * * *

专利名称(译)	液晶显示器		
公开(公告)号	US20090135323A1	公开(公告)日	2009-05-28
申请号	US12/275673	申请日	2008-11-21
[标]申请(专利权)人(译)	三星电子株式会社		
申请(专利权)人(译)	三星电子 , CO. , LTD.		
当前申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
[标]发明人	YANG YOUNG CHOL LU JIANGANG LEE SEUNG HOON		
发明人	YANG, YOUNG-CHOL LU, JIANGANG LEE, SEUNG-HOON		
IPC分类号	G02F1/1343 G02F1/133		
CPC分类号	G02F1/13624 G02F1/1393 G02F2001/134345 G09G3/3659 G09G2320/068 G09G2300/0447 G09G2300/0814 G09G2300/0842 G09G2300/0443		
优先权	1020070121092 2007-11-26 KR		
其他公开文献	US7995155		
外部链接	Espacenet USPTO		

摘要(译)

液晶显示器包括彼此平行排列并顺序传输栅极电压的第一和第二栅极线，与第一和第二栅极线交叉并传输数据电压的数据线，由第一和第二子像素构成的像素电极电极并彼此电断开，第一开关元件连接到第一栅极线，数据线和第一子像素电极，第二开关元件连接到第一栅极线，数据线和第二子电极像素电极，第三开关元件，跨越电荷共享电容器连接到第一子像素电极;第四开关元件，连接到第二栅极线和第二子像素电极并连接到第一子像素电极跨过电荷共享电容器。

