



US 20010043205A1

(19) United States

(12) Patent Application Publication

Huang et al.

(10) Pub. No.: US 2001/0043205 A1

(43) Pub. Date: Nov. 22, 2001

(54) GRAPHIC CONTROLLER FOR ACTIVE MATRIX ADDRESSED BISTABLE REFLECTIVE CHOLESTERIC DISPLAYS

(76) Inventors: Xiao-Yang Huang, Stow, OH (US); Nick Martin Miller IV, Rootstown, OH (US)

Correspondence Address:
WESTERLUND POWELL, P.C.
122 N. Alfred Street
Alexandria, VA 22314-3011 (US)

(21) Appl. No.: 09/836,640

(22) Filed: Apr. 18, 2001

Related U.S. Application Data

(63) Non-provisional of provisional application No. 60/200,001, filed on Apr. 27, 2000.


Publication Classification

(51) Int. Cl. 7 G09G 5/00

(52) U.S. Cl. 345/204

ABSTRACT

A graphics controller for a color display system having a bistable liquid crystal display (LCD) for displaying a plurality of pixels arranged in a matrix includes a memory device for storing color data and status bits corresponding to each of the pixels, and a generating device for generating voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels. In an exemplary case, the bistable LCD is a Cholesteric LCD. Preferably, the generating device has a first mode of operation in which the data corresponding to the pixels is generated for each corresponding pixel and a second mode of operation in which no data is generated; the generating device switches from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros.






Fig.1a




Fig. 1b




Fig. 2




Fig. 3




Fig. 4






Fig. 5a
Fig. 5b






Fig. 7a




Fig. 7b




Fig. 8a




Fig. 8b

GRAPHIC CONTROLLER FOR ACTIVE MATRIX ADDRESSED BISTABLE REFLECTIVE CHOLESTERIC DISPLAYS

BACKGROUND OF THE INVENTION

[0001] The present invention relates generally to bistable, reflective Cholesteric displays. More specifically, the present invention relates to a graphic controller for active matrix addressed bistable, reflective Cholesteric displays. Advantageously, a corresponding system and method of operation for driving the bistable, reflective Cholesteric displays are also disclosed.

[0002] The present application claims priority from previously filed Provisional patent application Ser. No. 60/200,001, which was filed on Apr. 27, 2000. The Provisional Patent Application is incorporated herein, in its entirety, by reference.

[0003] Liquid crystal displays (LCD's) have been widely adapted for use in a number of products such as digital watches and clocks, laptop computers, and information and advertising display signs. LCD's are generally classified according to their drive scheme, e.g., passive matrix LCD's and active matrix LCD's.

[0004] With respect to passive matrix LCD's, the display includes a thin layer of liquid crystal material sandwiched between two transparent panels. An electrode array comprising a first set or plurality of parallel oriented electrode segments (row electrode segments) disposed on an inwardly facing side of one panel and a second set or plurality of parallel oriented electrode segments (column electrode segments) which are perpendicular to the row electrode segments disposed on an inwardly facing side of the other panel is provided. The row and column electrode segments are spaced apart by spacer material and the liquid crystal material is filled in the spaced apart region between the panels.

[0005] Display picture elements or pixels are defined by regions of liquid crystal material adjacent the intersections of aligned electrodes of the horizontal and vertical electrode segments of the electrode array. Upon application of a suitable electric field, a pixel in a reflective display will assume either a reflective or a non-reflective state. A pixel, p_{ij} , formed at the overlapping or intersection of the i th row electrode and the j th column electrode is subject to an electric field resulting from the potential difference between a voltage applied to the i th row electrode segment and a voltage applied to the j th column electrode segment.

[0006] Recent advances in liquid crystal material research have resulted in the discovery of bistable chiral nematic (also called cholesteric) liquid crystal materials. Cholesteric liquid crystal materials are able to maintain a given state (reflective or non-reflective) without the need for the constant application of an electric field. When data or an image displayed on a display is to be changed, the display driver circuitry will update the display corresponding to the changes.

[0007] If the panel furthest from the viewer is painted with a black substrate, a pixel with a low reflectance will appear as a black area to the viewer. If the liquid crystal material has a light color appearance (such as yellow) in its highly

reflective state, a pixel in a high reflectance state will appear to the viewer as an iridescent colored area on a black background.

[0008] Bistable Cholesteric liquid crystal displays (hereinafter Ch-LCD) have received considerable attention of display designers and manufacturers in recent years for portable applications because of their advantageous optical properties and low power consumption. It will be appreciated that this interest has resulted in the introduction of a significant number of products employed in a wide variety of applications. Moreover, this interest has produced various improvements in bistable, reflective Cholesteric displays in terms of optical properties such as brightness, contrast, and full color.

[0009] The most prevalent technique for driving the Ch-LCD is by passive matrix addressing. In that case, display driver circuitry is coupled to the vertical and horizontal electrodes of the electrode array. Operating under the control of a logic and control unit, the display driver circuitry energizes the row and column electrodes with appropriate voltage waveforms such that an appropriate voltage across each pixel is generated. The voltage across a pixel will either cause it to remain in its present state of reflectance or change its state of reflectance. The image generated by the display pixels may be modified by changing the state of selected pixels. In this way, text or image data can be presented for viewing.

[0010] In the invention disclosed in U.S. Pat. No. 5,748,277 (the '277 patent), which is entitled "Dynamic Drive Method and Apparatus for a Bistable Liquid Crystal Display," a method and display driver circuitry for speeding the rate of updating a 1,000 row cholesteric liquid crystal display was disclosed. The '277 patent is incorporated herein in its entirety by reference. An updating time of approximately one-second for a 1000 row display was achieved. By simultaneously addressing multiple rows of the display with a pipelining scheme, the overall updating time for the display was kept at one second.

[0011] With suitable thresholds, zero voltage bistability enables low cost passive matrix addressing for Ch-LCD. However, the slow material response time and the unique switching scheme required by the bistable display makes it difficult for a Ch-LCD to achieve video rate updates on a large format display. While a significant amount of effort has also been devoted to improving the update speed (in milliseconds (ms)) of the bistable, reflective Cholesteric displays, results to date have been less than optimal, as discussed in greater detail immediately below.

[0012] The dynamic and electro-optical responses of a typical, bistable reflective Ch-LCD are illustrated in FIGS. 1A and 1B. As shown in FIG. 1a, an AC voltage in the form of pulses varying from 0V to 50V is applied to the display and the reflectance is plotted; in FIG. 1b, reflectance is plotted as a function of time.

[0013] Referring to FIG. 1a, the reflectance is initially high, i.e., before any voltage is applied. Upon the application of the voltage pulse, the display is switched into the Homeotropic State and the reflectance becomes very low. Once the voltage pulse is switched off, the reflectance gradually increases to the maximum. The rise time of the display is about 250 ms, as illustrated in FIG. 1b. It will be appreciated that in video applications, this long rise time will cause unpleasant image ghosting.

[0014] It will be noted that the final display reflectance versus the voltage amplitude is shown in FIG. 1a. More specifically, there are two initial (stable) states: the planar (higher reflectance) state and the focal conic (lower reflectance) state. It will also be noted that there are several threshold voltages. When the applied voltage is below V₁, the display will stay in either of its initial states after the pulse. When the voltage increases from V₁ to V₂, the reflectance of the initially ON display will decrease to a minimal value. The reflectance of the initially OFF display begins to increase when the voltage is above V₃' and the reflectance reaches the maximum when the voltage is above V₄. The reflectance of the initially ON display begins to increase its reflectance when the voltage is above V₃ and the reflectance reaches the maximum when the voltage is above V₄'. Therefore, for voltage between V₂ and V₃, the display is switched to the low Reflectance State regardless of its initial state; for voltage above V₄, the display is switched to the high reflective state regardless of its initial state. Note that there are regions in the voltage response diagram, such as between V₁ and V₂, where there exists stable partially reflecting states providing the opportunity for gray scale addressing.

[0015] Basic concepts and schemes for passive matrix addressing of a bistable reflective cholesteric display are disclosed in U.S. Pat. No. 5,251,048 and U.S. Pat. No. 5,644,330, which patents are incorporated herein by reference. A basic requirement for passive matrix addressing is that:

$$[(V_4 - V_3)/2] > V_1.$$

[0016] This requirement can be met by adjusting the display process and associated material parameters. However, this requirement also limits the adaptation of certain display configurations, which configurations may have other benefits.

[0017] Several drive methods have been developed in an effort to improve the speed at which the cells of a bistable, reflective Cholesteric display can be changed between the ON and OFF states. For example, specialized drive schemes and erase sequences can be employed to improve the speed of a conventional drive system to approximately 3 ms/row, as described in U.S. Pat. No. 5,644,330. In contrast, dynamic driving of the bistable, reflective Cholesteric display makes use of the fast homeotropic-transient planar transition, which results in a drive speed of approximately 0.5 ms/row. The dynamic driving technique is described in greater detail U.S. Pat. No. 5,748,277 and in the paper by X. Y. Huang et al. in the SID>95 Technical Digest, p. 347 (1995).

[0018] It should be noted that, due to the use of a passive matrix addressing scheme, the user always sees a black scan line sweeping across the entire screen. The development of a cumulative drive scheme removes the black scan line; however, it is limited by how many rows that can be addressed in one frame period. Additional details regarding the cumulative drive are disclosed in U.S. Pat. No. 6,133,895, which patent is incorporated herein by reference in its entirety for all purposes. All of these limitations are inherent in the passive matrix addressing methods used in addressing and driving bistable, reflective Cholesteric displays.

[0019] An active matrix addressing method for bistable, reflective Cholesteric displays has been proposed which

makes use of the planar and the homeotropic states. Further details regarding this proposed method are available in the article by J. Y. Nahm et al. presented in the proceedings of Asia Display '98 (18th International Display Research Conference, Seoul, Korea), p. 979 (1998), and by Y. Kawata et. al. in Proceedings Of The International Research Conference 97 (Toronto, Canada), p. 246 (1997). However, in that addressing scheme, the bistability of the Cholesteric display was sacrificed, which, in turn, resulted in an increase in the power required to drive the active matrix Cholesteric displays. Furthermore, it will be noted that it is not possible to provide a gray scale using the previously proposed active matrix addressing method.

[0020] Before discussing the present invention in greater detail, it should be mentioned that all of the patents and articles cited within the instant specification are incorporated herein by reference.

[0021] What is needed is a drive method and corresponding circuitry for an active matrix addressed bistable, reflective Cholesteric display which avoids the relatively low update speed limitation associated with such displays. Moreover, what is needed is a drive method and corresponding circuitry for an active matrix addressed bistable, reflective Cholesteric display which maintains the low power benefit of Cholesteric display technology. What is also needed is a combination including an active matrix addressed bistable, reflective Cholesteric display and associated drive circuitry. It would be beneficial if the combination could be included into a plurality of different products.

SUMMARY OF THE INVENTION

[0022] Based on the above and foregoing, it can be appreciated that there presently exists a need in the art for a graphic controller for an active matrix addressed bistable, reflective Cholesteric display which overcomes the above-described deficiencies. The present invention was motivated by a desire to overcome the drawbacks and shortcomings of the presently available technology, and thereby fulfill this need in the art.

[0023] According to one aspect of the present invention, an active matrix addressed Cholesteric display is achieved by careful design of the drive scheme, implemented via the driver and controller, to thereby allow the Cholesteric display to maintain its superior optical performance, e.g., high brightness, high contrast, flicker-free viewing, and the low power bistability, i.e., only the pixels that need to be changed are updated. The improved active matrix addressed bistable, reflective Cholesteric display according to the present invention advantageously provides a video rate compatible, scan-line free update capability.

[0024] According to one aspect, the present invention provides graphics controller for a color display system having a bistable liquid crystal display (LCD) for displaying a plurality of pixels arranged in a matrix, the graphics controller including a memory device for storing color data and status bits corresponding to each of the pixels, and a generating device for generating voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels. In an exemplary case, the bistable LCD is a Cholesteric LCD. Preferably, the generating device has a first mode of operation in which the data corresponding to the pixels is generated for each corresponding pixel and a

second mode of operation in which no data is generated; the generating device switches from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros.

[0025] According to another aspect, the present invention provides a graphics controller for a low power color display having a bistable liquid crystal display (LCD) including a plurality of cells arranged in a matrix, each cell corresponding to a pixel, including a memory which stores color data and status bits corresponding to all of the pixels, and circuitry which generates voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels. Preferably, the circuitry generates the voltage data for a corresponding pixel when the status bits correspond to a non-zero binary number. Most preferably, the circuitry has a first mode of operation in which the voltage data corresponding to the pixels is generated for each corresponding pixel and a second mode of operation in which no voltage data is generated, the circuitry switching from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros. Advantageously, the circuitry generates the data for a corresponding pixel N times to thereby permit application of the generated pixel data to the LCD N time, where N is an integer established by the status bits.

[0026] According to yet another aspect, the present invention provides a graphics controller for a low power color display including a bistable liquid crystal display (LCD) having multiple cells arranged in a matrix, each cell corresponding to a pixel. Preferably, the graphics controller includes a memory which stores color data and status bits corresponding to a plurality of pixels, status logic which generates the status bits responsive to receipt of color data for a respective one of the pixels, a data generator which generates voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels, and driver circuitry which generates voltage signals responsive to receipt of the voltage data for each of the pixels, wherein the LCD is responsive to the voltage signals produced by the driver circuitry. In an exemplary case, the bistable LCD comprises a Cholesteric LCD. Advantageously, the graphics controller includes a power supply which provides power to the driver circuitry, and a power manager which turns the power supply ON when the data generator is in a first operating mode and which turns the power supply OFF when the data generator is in a second operating mode. In an exemplary embodiment, the data generator cycles between the first and second operating modes based on the integer value of the status bits. In another exemplary embodiment, the graphics controller includes status logic which decrements the status bits of a corresponding one of the pixels each time the voltage data for that corresponding pixel is generated by the data generator, and replaces the status bits with decremented status bits after the voltage data is output by the data generator, permitting the data generator to generate the voltage data for a corresponding pixel N times and thereby permit application of the voltage signal corresponding to the pixel data to the LCD N time, where N is an integer established by the status bits.

BRIEF DESCRIPTION OF THE DRAWINGS

[0027] These and various other features and aspects of the present invention will be readily understood with reference

to the following detailed description taken in conjunction with the accompanying drawings, in which like or similar numbers are used throughout and in which:

[0028] FIGS. 1a and 1b illustrate the dynamic and electro-optical response of a surface stabilized Cholesteric display with respect to variations in applied voltage and relaxation time, respectively;

[0029] FIG. 2 illustrates the pixel waveforms of the pulses employed in driving the active matrix addressed Cholesteric display between its various states;

[0030] FIG. 3 is a representational diagram illustrating the storage of both status and image data in a single frame buffer;

[0031] FIG. 4 illustrates the row, column, and back plane (BP) voltage combination employed by the method according to the present invention;

[0032] FIG. 5a illustrates the row, column and backplane waveforms corresponding to the pixels illustrated in FIG. 5b;

[0033] FIG. 6 illustrates circuitry employed in driving the active matrix addressed Cholesteric display according to the present invention;

[0034] FIGS. 7a and 7b illustrate the dynamic and electro-optical response of a polymer stabilized finger-print cholesteric texture (PSFPCI) display with respect to variations in applied voltage and relaxation time, respectively; and

[0035] FIGS. 8a and 8b illustrate the dynamic and electro-optical response of a surface stabilized bistable cholesteric display with respect to variations in applied voltage and relaxation time, respectively.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0036] As mentioned above, the present invention provides an active matrix addressed Cholesteric display, e.g., the Ch-LCD. Careful design of the drive scheme, implemented via the driver and controller, permits the Cholesteric display to maintain its superior optical performance, e.g., high brightness, high contrast, flicker-free viewing, and the low power bistability, i.e., only the pixels that need to be changed are updated. Moreover, the improved active matrix addressed bistable, reflective Ch-LCD according to the present invention advantageously provides a video rate compatible, scan-line free update capability.

[0037] Before describing the preferred embodiments of the present invention in detail, it should be mentioned that there are two stable states of a bistable reflective Ch-LCD, the planar state and the focal conic state. The planar state exhibits high reflectivity and is commonly referred to as the ON state. The focal conic state has low reflectivity and is, in contrast, referred to as the OFF state. With a black paint on the back of the substrate of the Ch-LCD, the planar state appears in some pre-selected color, e.g., yellow, while the focal conic state appears to be black. The amount of light reflected from the planar state can be adjusted to achieve different shades of a particular reflected color or gray levels. This feature makes possible a full-color display as described in publication "Full color (4096) reflective cholesteric liquid crystal display" by Huang et.al. Asia Display '98 Technical

Digest, p 883. A full-color display is made by stacking three display cells, each of a different primary color, red, green and blue with the black background painted on the back substrate of the bottom cell.

[0038] It should be noted that the display could be switched from the planar state to the focal conic state directly by application of a suitable pulse having a proper magnitude as characterized by voltage level and time duration or pulse width. However, the display cannot be switched from the focal conic state to the planar state directly. Instead, a large magnitude pulse is first applied to the cells of the display in the focal conic state to thereby align the liquid crystal in the selected cells to the homeotropic state, which is then switched OFF quickly. It will be appreciated that the liquid crystal material first relaxes into the transient planar state in about 1 ms, and then more slowly to the planar state. At room temperature, a typical voltage pulse would be about 10 ms in duration, which would permit the Cholesteric liquid crystal to relax into the planar state approximately 100-300 ms after the pulse has been terminated. During this transient time, each effected pixel in the Ch-LCD changes from black to a state with predetermined reflectivity.

[0039] In contrast, i.e., in the case of passive matrix addressing, the data voltage difference between the ON and OFF states is limited. Therefore, all the pixels in a row are selected, independent of their previous image state, and the voltage pulse with suitable magnitude is applied according to the desired final state of the pixel, i.e., a relatively low magnitude for the focal conic state and a relatively high magnitude for the planar state. The relatively low magnitude immediately drives each pixel in the row to the focal conic state and the pixel appears black. The relatively high magnitude drives the pixel to the homeotropic state in which each pixel also appears to be black. Therefore, the whole selected row appears black. It will be appreciated that the maximum drive speed for this one-line-at-a-time drive scheme, i.e., passive matrix addressing, is approximately 5 ms/row. For a large display panel with many rows, e.g., 100 rows, the users can actually see a black line scan down the screen. In the dynamic drive scheme, the average row selection time can be reduced to about 1 ms/row. However, there are many driven rows, e.g., 40 rows, in the active driving pipeline. Thus, the user will still see a black band, the black line is just sweeping down the screen at a faster rate.

[0040] It should also be mentioned that the cumulative drive scheme is able to remove the black scan line by scanning the screen, or at least a selected portion of the screen, repetitively at a high refresh rate, i.e., greater than 40 scans/second. Due to image retention characteristic of the human eye, the black scanning line disappears. However, the maximum driver voltage, maximum data voltage and the material response time limits the row selection time to about 2 ms/row, which is equivalent to eight rows at a 60 Hz scanning rate. The limited number of rows that advantageously can be driven while avoiding the characteristic black scan line of Ch-LCD's implies that this passive matrix drive scheme can only be of benefit in a limited number of specific applications. In any event, the cumulative drive scheme's ability to minimize black scan lines down the face of the Ch-LCD also demonstrates that the Cholesteric material advantageously can be operated at speeds approaching

that of a conventional video update rate, provide that the proper drive scheme can be applied.

[0041] Fundamentally, an active matrix display can be conceptualized as a matrix display in which each pixel of the display advantageously can be switched ON and OFF independently. Examples of active matrix displays are disclosed in U.S. Pat. Nos. 4,042,854, 4,062,626, 4,404,555, and 4,717,244, to name but a few. In a conventional active matrix display without bistability, a voltage is always applied to maintain the pixels at the selected ON or OFF state. To make the best use of the bistability of Ch-LCD, the Ch-LCD according to the present invention implements a three-state drive method for an active matrix display. The three states are:

[0042] (1) OFF to ON;

[0043] (2) ON to OFF; and

[0044] (3) NC (no change).

[0045] When any pixel in the active matrix display is to be switched from the OFF state to the ON state, a high voltage is applied to the selected pixel to thereby effect the change of state. When a pixel or group of pixels in the active matrix display is to be switched from the ON state to the OFF state, a low voltage is applied to thereby cause the desired change of state. Furthermore, when any pixel in the active matrix display needs to maintain its current state, zero volts are applied to the pixel. The waveform on each pixel is shown in FIG. 2. The characteristics and features associated with these waveforms are discussed immediately below.

[0046] 1. The high or low pulse is applied repetitively with a time interval depending on the frame rate. If the frame rate is 60 Hz, the interval is 16.7 ms. If the frame rate is 30 Hz, the interval is 33.3 ms.

[0047] 2. The width and the number of the pulses depend on the material response time. The goal is for the pixels that need to be switched from OFF to ON, during the last pulse the whole pixel should be switched to the homeotropic state; for the pixels that need to be switched from ON to OFF, during the last pulse, the whole pixel should be switched to the focal conic state.

[0048] 3. The pixel voltages are turned OFF at the end of each frame to reduce the operation voltage of driver cost in the frame inversion scheme.

[0049] 4. The voltage difference between the ON and OFF waveform is not as limited as that of the passive matrix drive.

[0050] 5. The cumulative effect of the display is also used so that the pixel can be completely switched in several frames. However, once the destination state is achieved, the voltage applied to the pixel is zero. This can significantly reduce the power consumption.

[0051] It will be appreciated that the use of the active matrix enables the whole display to be updated almost at the same time. However, it will also be appreciated that the pixel voltage level is changed inside a frame time. Therefore, modifications in the drive control circuitry are needed.

[0052] It will be noted that there are two states in the row driver, i.e., select and non-select, for an active matrix display. Thus, the row data only needs to be 1 bit. In contrast, in order to implement the three state drive scheme according to the present invention, the column drive needs to have three states: ON, OFF, and NC (no change). For that reason, the column driver requires two data bits in order to select between the three states. Thus, the column driver advantageously receives both pixel image data and pixel status data. An exemplary image array block representing storage of these data bits is shown in **FIG. 3**.

[0053] Referring specifically to the exemplary data organization illustrated in **FIG. 3**, it will be appreciated that the frame buffer data includes both 24 bits of image data, permitting display in excess of one million colors in the resultant image, and 3 bits of status data. It will be appreciated that colors are represented by three groups each having 8 bits representing 256 gray levels for each color, which requirement dictates that the column driver are amplitude modulated. In addition, the 3 bits of status data allow as many as 8 frames to update an image. In other words, for every frame advance the status bits are decremented by 1 bit; once the status bits are cleared, NC state is assumed, and no further updates occur to the pixel. Moreover, once the pixel has been changed, all status bits are set to 1's.

[0054] It should be mentioned that the number of status bits and color bits described above relate to only one exemplary embodiment according to the present invention; other combinations of status and color bits are considered to within the scope of the present invention. For example, four status bits and sixteen bits, advantageously could be used. Moreover, the four status bit, twelve color bit configuration illustrated in **FIG. 6** beneficially can be employed in particular applications.

[0055] It will be appreciated that with the help of the three status bits, more complicated drive sequences can be implemented. For example, the status bits advantageously can be employed in connection with erase cycles to enhance the contrast and the gray scale accuracy.

[0056] **FIG. 4** shows the row, column and back plane (BP) voltage combination, assuming 40V for ON and 30V for OFF, provided by the drive circuitry according to the present invention, which drive circuitry will be discussed in greater detail below. It will be appreciated that in all cases, the row voltage for selection is preferably about 5 V and, most preferably, at least 5V higher than column voltage.

[0057] In order to change the voltage level inside one frame, the row, column and backplane voltages need to be arranged as shown in **FIG. 5a** to drive the pixel pattern illustrated in **FIG. 5b**. Referring to **FIG. 5b**, pixel 11 is switched from OFF to ON and Pixel 22 is switched from ON to OFF. Pixel 12 and Pixel 21 are maintained in their previous state, i.e., no change.

[0058] It should be mentioned that, during one frame, each row is selected twice. More specifically, the first selection, i.e., pulse, advantageously can be employed to charge the pixel according to the image data and pixel status while the second selection is used to discharge the pixel to zero voltage with respect to the back plane voltage. Therefore, the column voltage during the first selection should reflect the pixel image data and pixel status, and the column voltage during the second selection should be set as NC (no change) so as to discharge the pixel.

[0059] It will be appreciated that the time difference between the two selection pulses defines the pulse width. Typically, the pulse width should be kept as short as possible so that the Cholesteric material can have time to relax to the desired state.

[0060] One preferred embodiment of the drive circuitry according to the present invention will now be described in detail with reference to **FIG. 6**. However, before the discussion of the embodiment is presented, it would be helpful to provide some additional general discussion. In particular, it should be mentioned that combining an active matrix-addressing scheme with a bistable reflective Cholesteric liquid crystal display (Ch-LCD) could significantly improve the response speed of the display. Moreover, active matrix addressing of the Ch-LCD advantageously maintains the lower power advantage offered by its bistability and reflective viewing characteristic of the Ch-LCD. It should also be mentioned that the controller design is predicated on the concept that, unlike existing active matrix displays, the drive circuitry for the active matrix Ch-LCD can be completely shut down when the image does not need to be changed. It will be appreciated that the power consumption of the active matrix Ch-LCD is extremely low with respect to other LCD's currently available in the market.

[0061] **FIG. 6** is a high-level block diagram of an active matrix Ch-LCD system 1 according to the present invention. The display system 1 includes an active matrix Ch-LCD 100, row (gate) and column (data) drivers 200, a back plane driver 300, a power supply 400 for the above-mentioned drivers, and the controller 500. The controller 500 receives both commands and image data from a processor 600, which processor will be discussed in greater detail below. It should be mentioned that the power supply 400 powering the drivers 200, 300 is controlled by the controller 500 for the efficient power management. As previously discussed, during a wake up operation, the power supplied to the drivers 200, 300 by the power supply 400 is active; during the sleep mode, the power provided to the drivers 200, 300 is removed completely.

[0062] An exemplary embodiment of the controller 500 according to the present invention includes a memory 502, which advantageously can be partitioned into image memory 502a and status memory 502b. Preferably, the memory 502 is a static random access memory; alternatively, other types of non-volatile memory, e.g., ferromagnetic random access memory (FRAM), advantageously can be employed. It will be appreciated that a non-volatile memory is preferred, since this type of memory complements the low power characteristic of the Ch-LCD 100. The controller 500 includes a status manager 504, which receives commands via the control/status input/output (I/O) port 506 and which receives data via the data I/O port 508 and a buffer 510. Preferably, buffer 510 facilitates the writing of data into memory 502a under control of a memory arbiter 512 driving address counter 514. The commands received via I/O port 506 are also applied to command decoder 516. In addition, the controller includes a power manager 518, which commands the startup and/or shutdown of the power supply 400. In the controller 500, the image data is read out of memory 502 by column data generator 520 and row data generator 522 in accordance with timing signals produced by the display timing circuit 524. Moreover, the display

timing is influenced by the temperature of the display **100**, as discussed in greater detail below.

[0063] The preferred embodiment of the controller **500** advantageously can be constructed from several ICs, such as an SRAM, an Altera programmable logic, and a National Semiconductor COP8, a power supply chip set, and some other discrete components. However, it will be appreciated that **FIG. 6** is a functional block diagram, i.e., **FIG. 6** illustrates functions, not discrete components, which functions are discussed in greater detail below. A detailed description of each of these functions is provided below.

[0064] In the exemplary embodiment, the Power Manager (function block) **518** advantageously oversees the power supply to the active matrix Ch-LCD system **1**. A “wake up” generated by the host **600** will toggle at least the controller **500** of the active matrix Ch-LCD system **1** into the high power awake mode. As noted above, the signal from the Status Manager **504** (discussed below) can determine whether to continue operation in the power consuming awake mode or to power down to the power conserving sleep mode. It will be appreciated that there will be a predetermined amount of delay between the time that the status manager **504** signals the power manager to enter the sleep mode of operation and the time that the system **1** actually powers down, thereby preventing cycling between the sleep and awake modes of operation when the host **600** issues a sequence of widely spaced commands or data, e.g., a hunt and peck typist enters a data string with relatively long pauses between characters.

[0065] The I/O port **506** permits receipt of commands from the host **600** to the controller **500**. In addition, the status if the controller, i.e., Sleep mode, Busy mode, and Awake mode, advantageously can be sensed by the host **600** via this port. This is the I/O control logic and the controller status port. The controller status can be detected by the host from this port. In contrast, the I/O port **508** and buffer **510** receives and buffers the data or commands provided on lines D0-D7 from the host **600**.

[0066] In controller **500**, the command decoder **516**, which advantageously could be a section of logic in a larger logic device, decodes commands received from the host **600**, which commands control the overall operation of the active matrix Ch-LCD system **1**, e.g., brightness control, frame rate adjustment, image SRAM allocation, etc. In contrast, the display timing circuit **524**, which again may be a section of a larger device, provides all necessary timing signals for controller **500** and display **100** operation, e.g., column shift clock, row shift clock, frame, data latch, SRAM clock, etc. The address counter **514** accesses the SRAM memory **502a** in response to timing signal from the display timing circuit **524**. As will be discussed below, some of the clock frequencies are temperature dependent.

[0067] It will be appreciate that access to/from the SRAM memory **502a** necessitates the presence of a memory arbitrator **512**. This section of logic accommodates memory access priority and resolves any possible conflicts between the host **600** and display driver **200**, **300** demand for memory **502** access. It will be appreciated that, in any active matrix addressing scheme, display scanning can not be stopped while the host **600** accesses (read from or writes to) memory **502**; the host **600** can only access the memory **502** while the drivers **200**, **300** are not demanding data.

[0068] It will be appreciated from **FIG. 6** that the memory **502** advantageously includes both an image SRAM **502a** and a status SRAM **502b**. The image SRAM **502a** provides the memory required for storing the display image, pixel by pixel. In the exemplary embodiment of system **1**, the display **100** displays 16 level of gray scale for each layer in a three-layer full color display. Therefore, each pixel corresponds to 12 data bits. The memory **502a** advantageously provides a low power standby mode so that the display image can be stored in the low power sleep mode. Moreover, the status SRAM **502b** advantageously can be employed to the pixel status information needed for the active matrix-addressing scheme according to the present invention. In the exemplary embodiment, a complete update of a pixel will take 16 frames, which can be represented by 4 data bits. When the host **600** updates a pixel, all of its corresponding status bits preferably are set to “1”. For every frame in which image data is provided to the active matrix Ch-LCD **100**, the status bits are decremented by 1. When all of the status bits reach zero, the controller **500** will determine that the “NC” criteria has been satisfied, and the pixel on the display **100** will not be updated, i.e., the row/column driver **200** will apply zero voltage with respect to the back plane.

[0069] The status manager **504** provides logic functions with respect to: setting status bits to 1’s in the status SRAM **502b** when a pixel is changed by the host **600**; decrementing the status bits by 1 and storing the decremented status bits back into the status SRAM **502b** after every frame update; monitoring the status SRAM **502b** to determined whether there is any pixel in the memory needing to be updated further; and issuing the power down signal to the power manager **518**.

[0070] As mentioned above, the controller **500** advantageously includes both a column data generator **520** and a row data generator **522**. The logic incorporated into the column data generator **520** takes image data, frame, and the status bits and forms the column voltage data which is to be applied to the row/column driver **200**. If the status bits are zero, the column voltage should be the same as the back plane voltage. If the status bits are not zero, this logic device, i.e., the column data generator **520**, will form the voltage data needed to update each pixel. It will be appreciated that the data generator **520** advantageously can include a lookup table (LUT) or comparable device for using the values stored in memories **520a**, **520b** as addresses to predetermined values which are to be output by data generator **520**. Thus, the data generator **520** provides the capability to implement more complicated multistage drive schemes by, for example, varying the values stored in the LUT. Likewise, the row data generator **522** permits row voltage data to be generated according to the frame and drive progress of each frame.

[0071] It will be appreciated from the brief discussion above, the frequencies of respective ones of the timing signals generated by the display timing circuit **524** are temperature dependent. This is because Ch-LCD’s are very sensitive to the temperature, especially in gray scale implementation. In the exemplary embodiment of the present invention illustrated in **FIG. 6**, it will be appreciated that temperature data derived from the substrate of the controller **500** advantageously can be employed to determine the drive voltage, pulse width, and even updating frequency of the

controller **500**, providing the display and the controller are in thermal contact and their temperatures are very close to one another.

[0072] A better understanding of the operation of the controller **500** can be obtained by considering the input/output (I/O) signals applied to or generated by the controller, as listed in TABLE 1 immediately below.

TABLE 1

nRes	Hardware reset. nRes = 0 to reset the complete controller to its default state.
nError	Indicates controller error when nError = 0
D/nC	Indicates the D0~D7 is data or command from host. D/nC = 1: data D/nC = 0: command
Sleep	Indicates the controller power status Sleep = 1: low power sleep mode Sleep = 0: high power awake mode
Busy	Indicates the controller process status Busy = 1: controller is processing last command Busy = 0: controller is ready for next command
nWk	Host wake up signal. Falling edge wakes up the controller. nWk = 0: controller needs to stay awake nWk = 1: controller can go to sleep once finished its current task
nWr	Write pulse. Falling edge to latch D0~D7
D0~D7	Image data or command
Vcc	5 V power supply
Gnd	Power ground

[0073] The essential functionality provided by the controller **500** illustrated in FIG. 6 is summarized immediately below.

[0074] 1. When the image on the display does not need to be updated, the controller **500** advantageously can be in the Sleep Mode.

[0075] 2. Minimal power is drained in maintaining the image data in the SRAM **502a** and in monitoring the interface activity, i.e., I/O ports **506** and **508**.

[0076] 3. Once the host (e.g., central processing unit (CPU)) **600** transmits data which needs to be reflected in the display **100**, the power manager circuitry **518** advantageously will wake up the controller **500** by driving the nWk line low.

[0077] 4. After powering up from the Sleep Mode, the controller **500** advantageously can start to respond to commands and accept the new image data from host **600**.

[0078] 5. Immediately after new image data is received, the controller **500** starts to update the display **100**.

[0079] 6. After the update of the display **100** has been completed, i.e., if no more new image data exists, the controller **500** powers down and returns to the Sleep Mode.

[0080] 7. The controller **600** will stay in the Sleep Mode until the host **600**, e.g., a computer, again wakes up the controller, i.e., until the host computer applies a predetermined "wake up" signal to the controller.

[0081] It should be mentioned here that during the display update period, the drive voltage is only applied to those pixels that need to be changed. No voltage is needed to

maintain the respective pixel in its previous state. It should also be mentioned that this drive-when-change method advantageously can be employed to dramatically reduce display power consumption.

[0082] As discussed above in connection with FIG. 3, the drive-when-changed operating method of the controller requires status bits associated with every displayed pixel in addition to the data corresponding to that pixel. In addition, the controller must employ "Status Manger" logic to direct the controller with respect to the employment of the status bits. Preferably, the number of status bits is determined in accordance with the number of frames that are needed to update each displayed pixel. For example, 3 bits indicates that $8=2^3$ frames are employed in updating a pixel while 4 bits indicates that $16=2^4$ frames are employed. In an exemplary case, when a pixel is changed in image memory, i.e., image SRAM, **502a**, that pixel's related status bits are all set to a predetermined value, e.g., all 1's, by the status manager **504**. For each frame in which the pixel is driven, the status bits is decremented by 1 and written back to the status SRAM **502b**. Once the status bits corresponding to a particular pixel in the image data are counted down to zero, the related pixel will not be driven any more, i.e., zero voltage will be applied to that pixel with respect to the back plane. It will be appreciated that the status manager **504** advantageously can monitor whether or not any particular pixel needs to be updated, i.e., the status manager **504** simply checks to determine if there are any non-zero status bits after each frame has been updated. If there is no pixel requiring an update, the status manager **504** informs the power manager **518** of the controller **500**, which power manager cycles controller **500** into the Sleep mode of operation.

[0083] As mentioned above, the three state active matrix drive scheme or method can significantly improve the update speed of CH-LCD while maintaining the bistability for low power operation. This drive method can be also extended to full color gray scale application. With the removal of cross talk voltage afforded by the active matrix-driving scheme, the power consumption advantageously can be even lower than the passive matrix display in the page update mode.

[0084] Moreover, from the discussion provided above, it will be appreciated that the operating characteristic of the Ch-LCD **100** advantageously can be tailored to permit operation of the Ch-LCD **100** with a reduced V1 threshold. Advantageously, in order to achieve a rapid response speed, the display **100** can be a Polymer stabilized finger-print cholesteric texture (PSFPCT) display or a Ch-LCD having a strong homeotropic alignment layer with a lower V1 threshold of the display.

[0085] It should be mentioned that a polymer stabilized finger-print cholesteric texture (PSFPCT) display was disclosed in U.S. Pat. No. 5,570,216 and described in a paper entitled "Bistable Reflective Cholesteric Liquid Crystal Display" (J. Appl. Phys. 81(3), (Feb. 1, 1997)), by Min-Hua Lu. This display can be fabricated mixing a predetermined percentage of monomer with the cholesteric liquid crystal mixture. After vacuum filling the display, the display is heated to the isotropic state, and is then slowly cooled down to the room temperature. In this manner, a large domain focal conic fan texture is formed during the cooling with the assistance of a side chain polyimide alignment layer. UV curing is facilitated without any external electric field.

[0086] The polymer networks are locked into the large domain fan texture. With proper polymer selection and concentration, the display exhibits fast homeotropic to planar transition, e.g., on the order of 10 ms. Several test displays fabricated according to the procedure set forth above have been characterized as having a repeatable rise time of approximately 10 ms. FIGS. 7a and 7b illustrate the dynamic response and the switching response, respectively, of a typical PSFPCT cell. It will be noticed that this display also has very good black state. It will also be noted that the V1 threshold for this cell is so low that the driving of such a display using a passive matrix drive scheme is not possible.

[0087] A typical surface stabilized bistable cholesteric display can be made according to method described in U.S. Pat. No. 5,453,863 by Yang and West. However, if the alignment layer has too strong of a homeotropic alignment effect, the display will exhibit a low V1 threshold value, meaning that the device can not be driven by the passive matrix method. Advantageously, this kind of device also exhibits a very fast homeotropic-to-planar (H-P) transition. The dynamic response and the electro-optical response, respectively, are shown in FIGS. 8a and 8b. It will be appreciated from their figures that the rise time in the H-P transition is about 10 ms and the hysteresis between V3 and V3', V4 and V4' is very small. It should be mentioned that the advantage of this device is that it does not require a polymer network. This can significantly simplify the manufacturing process and improve the display reliability.

[0088] Application of the active matrix driving method according to the present invention can fundamentally resolve any limitation on the V1 value relative to the ON and OFF voltage values. For example, in a thin film transistor based active matrix display, the drive voltage on the selected rows are not seen by any of the non-selected rows. The state of the non-selected rows is not effected by the driving the pixels in the selected row. This enables the selection of materials, display process parameters, surface treatment, etc., without regard to cell crosstalk. It will be appreciated that the very attractive features of a Ch-LCD with low V1 threshold, while not particularly suitable for existing passive matrix driving methods, provides a display with a fast H-P transition, which satisfies a key requirement for displays employed in video rate applications.

[0089] It should be mentioned at this point that the active matrix Ch-LCD system 1 according to the present invention advantageously can be employed as the display of such a devices as personal digital assistants (PDAs), electronic books (e-books), advertising displays, etc. It will also be mentioned that the active matrix Ch-LCD system can be adapted to accept inputs from devices such as desktop and laptop computers, particularly the latter. It will be appreciated that the graphics subsystem of the typical computer generates data sufficient to update the display at 30 or more frames per second. Since much of this data does not vary from frame to frame, providing such repetitive pixel data to the active matrix Ch-LCD system according to the present invention would be counter productive. However, it will be appreciated that the logic provided by the status manager 504 can be augmented with comparison logic. In that case, data provided to the status manager can be compared with the data already stored in image SRAM 502a; only new

color data would be written to memory 502a and, consequently, only the status bits corresponding to the new color data would be changed.

[0090] It should also be mentioned that the active matrix Ch-LCD system 1 is not limited to the specific embodiments discussed above. For example, when large Ch-LCD's are to be driven according to the present invention, multiple ones of row/column drivers 200 advantageously can be included so that rows 1-50 are driven by row/column driver 200a, rows 51-100 are driven by row/column driver 200b, etc.

[0091] Although presently preferred embodiments of the present invention have been described in detail above, it should be clearly understood that many variations and/or modifications of the basic inventive concepts taught herein, which may appear to those skilled in the pertinent art, will still fall within the spirit and scope of the present invention. For example, while an exemplary SRAM stores 24 bits of image data and 3 bits of status data per pixel, other memory arrangements advantageously could be employed. Thus, the SRAM could store 12 bits of image data and 4 bits of status data per pixel without departing from the teachings of the present invention.

What is claimed is:

1. A graphics controller for a color display system having a bistable liquid crystal display (LCD) having a plurality of pixels arranged in a matrix, comprising:

memory means for storing color data and status bits corresponding to each of the pixels; and

means for generating voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels.

2. The graphics controller as recited in claim 1, wherein the bistable LCD comprises a Cholesteric LCD.

3. The graphics controller as recited in claim 1, wherein the data generating means generates the voltage data for a corresponding pixel when the status bits correspond to a non-zero binary number.

4. The graphics controller as recited in claim 3, wherein: the generating means has a first mode of operation in which the voltage data corresponding to the pixels is generated for each corresponding pixel and a second mode of operation in which no voltage data is generated; and

wherein the generating means switches from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros.

5. The graphics controller as recited in claim 1, further comprising:

decrementing means for decrementing the status bits of a corresponding one of the pixels each time the data for that corresponding pixel is generated,

wherein the data generating means generates the voltage data for that corresponding pixel when the status bits correspond to a non-zero binary number.

6. The graphics controller as recited in claim 1, wherein the data generating means generates the voltage data for a corresponding pixel N times and applies the generated pixel data to the LCD N time, where N is an integer established by the status bits.

7. A graphics controller for a low power color display having a bistable liquid crystal display (LCD) comprising a plurality of cells arranged in a matrix, each cell corresponding to a pixel, comprising:

a memory which stores color data and status bits corresponding to all of the pixels; and

circuitry which generates data corresponding to the pixels based on the color data and the status bits for each of the pixels.

8. The graphics controller as recited in claim 7, wherein the bistable LCD comprises a Cholesteric LCD.

9. The graphics controller as recited in claim 7, wherein the circuitry generates the data for a corresponding pixel when the status bits correspond to a non-zero binary number.

10. The graphics controller as recited in claim 9, wherein:

the circuitry has a first mode of operation in which the data corresponding to the pixels is generated for each corresponding pixel and a second mode of operation in which no data is generated; and

wherein the circuitry switches from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros.

11. The graphics controller as recited in claim 7, further comprising:

status logic which decrements the status bits of a corresponding one of the pixels each time the data for that corresponding pixel is generated by the circuitry,

wherein the circuitry generates the data for that corresponding pixel when the status bits for that pixel represent a non-zero binary number.

12. The graphics controller as recited in claim 7, wherein the circuitry generates the data for a corresponding pixel N times to thereby permit application of the generated pixel data to the LCD N time, where N is an integer established by the status bits.

13. A graphics controller for a low power color display including a bistable liquid crystal display (LCD) having multiple cells arranged in a matrix, each cell corresponding to a pixel, comprising:

a memory which stores color data and status bits corresponding to a plurality of pixels;

status logic which generates the status bits responsive to receipt of color data for a respective one of the pixels;

a data generator which generates voltage data corresponding to the pixels based on the color data and the status bits for each of the pixels; and

driver circuitry which generates voltage signals responsive to receipt of the voltage data for each of the pixels,

wherein the LCD is responsive to the voltage signals produced by the driver circuitry.

14. The graphics controller as recited in claim 13, wherein the bistable LCD comprises a Cholesteric LCD.

15. The graphics controller as recited in claim 13, wherein the data generator generates the voltage data for a corresponding pixel when the status bits for that pixel correspond to a non-zero binary number.

16. The graphics controller as recited in claim 13, wherein:

the data generator generates the voltage data for a corresponding pixel when the status bits for that pixel correspond to a non-zero binary number;

the data generator has a first mode of operation in which the voltage data corresponding to the pixels is generated for each corresponding pixel and a second mode of operation in which no voltage data is generated; and

wherein the data generator switches from the first operating mode to the second operating mode when all of the status bits for all of the pixels are zeros.

17. The graphics controller as recited in claim 16, further comprising:

a power supply which provides power to the driver circuitry; and

a power manager which turns the power supply ON when the data generator is in the first operating mode and which turns the power supply OFF when the data generator is in the second operating mode.

18. The graphics controller as recited in claim 13, further comprising:

status logic which decrements the status bits of a corresponding one of the pixels each time the data for that corresponding pixel is generated by the circuitry,

wherein the data generator generates the voltage data for that corresponding pixel when the status bits for that pixel represent a non-zero binary number.

19. The graphics controller as recited in claim 13, wherein the data generator generates the voltage data for a corresponding pixel to thereby permit application of the generated pixel data to the display means N time, where N is an integer established by the status bits.

20. The graphics controller as recited in claim 13, further comprising:

status logic which:

decrements the status bits of a corresponding one of the pixels each time the voltage data for that corresponding pixel is generated by the data generator, and

replaces the status bits with decremented status bits after the voltage data is output by the data generator;

wherein the data generator generates the voltage data for a corresponding pixel N times to thereby permit application of the voltage signal corresponding to the pixel data to the LCD N time, where N is an integer established by the status bits.

专利名称(译)	用于有源矩阵的图形控制器用于双稳态反射胆固体显示器		
公开(公告)号	US20010043205A1	公开(公告)日	2001-11-22
申请号	US09/836640	申请日	2001-04-18
[标]申请(专利权)人(译)	黄萧养 MILLER Nick Martin先生		
申请(专利权)人(译)	黄小阳 MILLER Nick Martin先生		
当前申请(专利权)人(译)	黄小阳 MILLER Nick Martin先生		
[标]发明人	HUANG XIAO YANG MILLER NICK MARTIN IV		
发明人	HUANG, XIAO-YANG MILLER, NICK MARTIN IV		
IPC分类号	G02F1/1368 G09G3/36 G09G5/36 G09G5/39 G09G5/00		
CPC分类号	G02F1/1368 G09G3/3651 G09G5/363 G09G5/39 G09G2300/0486 G09G2310/04 G09G2320/041 G09G2320/103 G09G2330/022		
优先权	60/200001 2000-04-27 US		
其他公开文献	US6816138		
外部链接	Espacenet USPTO		

摘要(译)

用于彩色显示系统的图形控制器，具有用于显示以矩阵排列的多个像素的双稳态液晶显示器(LCD)，包括用于存储与每个像素对应的颜色数据和状态位的存储器装置，以及用于基于每个像素的颜色数据和状态位产生对应于像素的电压数据。在示例性情况下，双稳态LCD是胆甾型LCD。优选地，生成装置具有第一操作模式和第二操作模式，在第一操作模式中，对应于每个像素生成对应于像素的数据，第二操作模式不生成数据。当所有像素的所有状态位都为零时，生成设备从第一操作模式切换到第二操作模式。

