




US 20120113080A1

(19) **United States**(12) **Patent Application Publication**
den Boer(10) **Pub. No.: US 2012/0113080 A1**(43) **Pub. Date: May 10, 2012**(54) **THIN-FILM TRANSISTOR LIQUID-CRYSTAL
DISPLAY WITH VARIABLE FRAME
FREQUENCY****Publication Classification**(51) **Int. Cl.****G09G 3/36** (2006.01)**G06F 3/038** (2006.01)(52) **U.S. Cl. 345/211; 345/87**(75) **Inventor:** **Willem den Boer**, Brighton, MI
(US)(73) **Assignee:** **ScanVue Technologies, LLC**,
Brighton, MI (US)(21) **Appl. No.:** **13/270,140**(22) **Filed:** **Oct. 10, 2011****Related U.S. Application Data**(60) **Provisional application No. 61/410,305, filed on Nov.
4, 2010.**(57) **ABSTRACT**

An active matrix includes an array of pixels individually addressable over a first frame-frequency range and over a second, higher frame-frequency range. The active matrix also includes, for each pixel of the array, a charging circuit through which that pixel is addressed. Each charging circuit includes an adjustable storage capacitance and is configured such that the storage capacitance is maintained at a first level over the first frame-frequency range, and at a second, lower level over the second frame-frequency range.






FIG. 1




FIG. 2




FIG. 3




FIG. 4

FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11

THIN-FILM TRANSISTOR LIQUID-CRYSTAL DISPLAY WITH VARIABLE FRAME FREQUENCY

CROSS REFERENCE TO RELATED APPLICATIONS

[0001] This application claims priority to U.S. Provisional Application 61/410,305, filed 4 Nov. 2010 and entitled PIXEL DESIGN FOR THIN FILM TRANSISTOR LIQUID CRYSTAL DISPLAYS WITH VARIABLE REFRESH RATE, the entirety of which is hereby incorporated by reference herein for all purposes.

TECHNICAL FIELD

[0002] This application relates to the field of digital display electronics, and more particularly, to reducing power consumption in a liquid-crystal display (LCD).

BACKGROUND

[0003] Low power consumption is desirable for any LCD—especially one installed in a mobile device such as a notebook computer or smart phone. In these devices, power consumption in the LCD significantly affects battery life.

[0004] In a conventional LCD array, each column of pixels is accessed through a data line. The capacitance of the data line is repeatedly charged and discharged at a frequency of N_{select} times the frame frequency, where N_{select} is the number of rows of the array. A frame frequency of 60 Hertz (Hz) is conventionally used to display video. For static images, however, a much lower frame frequency would suffice, the lower frame frequency demanding less frequent capacitive charging and therefore consuming less power.

[0005] To operate a conventional pixel array at a reduced frame frequency, however, the leakage current through each pixel and associated thin-film transistor (TFT) must be suppressed so that the image is retained over a longer period between successive refresh events. It has been demonstrated that obliquely evaporated SiO_x liquid-crystal alignment layers, having increased ionic impurity adsorption, may improve voltage holding in an LCD array. This feature may enable the pixels of the display to operate at refresh frequencies as low as 1 Hz. TFT I_{off} may be reduced to less than 10 femtoamperes (fA) in a recently developed, optimized oxide TFT. In addition, a TFT engineered with an especially narrow channel (low in width-to-length ratio) may exhibit attractively low I_{off} .

[0006] To display video, however, I_{on} must remain high enough to charge the pixels at the conventional frame frequency (e.g., 60 Hz). All told, this would require an I_{on}/I_{off} ratio of at least eight orders of magnitude. In a manufacturing environment, such a ratio may be difficult to achieve, especially when photo-leakage current in the TFT is taken into account.

SUMMARY

[0007] Accordingly, one embodiment of this disclosure provides an active matrix including an array of pixels individually addressable over a first frame-frequency range and over a second, higher frame-frequency range. The active matrix also includes, for each pixel of the array, a charging circuit through which that pixel is addressed. Each charging circuit includes an adjustable storage capacitance and is configured such that the storage capacitance is maintained at a

first level over the first frame-frequency range, and at a second, lower level over the second frame-frequency range.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] FIGS. 1 and 2 show a mobile device in accordance with an embodiment of this disclosure.

[0009] FIG. 3 shows an LCD array and controller in accordance with an embodiment of this disclosure.

[0010] FIG. 4 summarizes power consumption for an example LCD array.

[0011] FIG. 5 shows an LCD array in greater detail in accordance with an embodiment of this disclosure.

[0012] FIG. 6 shows a cross section of a pixel and a charging circuit in accordance with an embodiment of this disclosure.

[0013] FIG. 7 shows in plan a pixel and charging circuit in accordance with an embodiment of this disclosure.

[0014] FIG. 8 schematically shows a charging circuit in accordance with an embodiment of this disclosure.

[0015] FIG. 9 shows a simulated voltage waveform at node P of FIG. 8 at a 60-Hz frame frequency, in accordance with an embodiment of this disclosure.

[0016] FIG. 10 shows a simulated voltage waveform at node P of FIG. 8 at a 6-Hz frame frequency, in accordance with an embodiment of this disclosure.

[0017] FIG. 11 illustrates an example method for driving an active-matrix display in accordance with an embodiment of this disclosure.

DETAILED DESCRIPTION

[0018] Aspects of this disclosure will now be described by example and with reference to the illustrated embodiments listed above. Components, process steps, and other elements that may be substantially the same in one or more embodiments are identified coordinately and are described with minimal repetition. It will be noted, however, that elements identified coordinately may also differ to some degree. It will be further noted that the drawing figures included in this disclosure are simplified for clearer understanding and generally not drawn to scale. Rather, the various drawing scales, aspect ratios, and numbers of components shown in the figures may be purposely distorted to make certain features or relationships easier to see.

[0019] FIGS. 1 and 2 show, respectively, front and side views of an example mobile device 10. The mobile device may be a tablet computer, a personal media player, an e-book, or a smart phone, for example. The mobile device may be configured to display video, still graphics, text, and/or other image data. To this end, the device includes LCD array 12 disposed in front of backlight 14. The LCD array and backlight are operatively coupled to controller 16, which provides appropriate electronic control signals to enable the desired image data to be displayed. In some embodiments, the controller may be a microcomputer having memory, one or more processors, networking componentry, and the like.

[0020] FIG. 3 schematically shows LCD array 12 and controller 16 in greater detail. In the illustrated embodiment, the LCD array is an active matrix comprising individually addressable color pixels 18. The controller includes suitable drive componentry configured to individually address each pixel of the array. In various embodiments, the drive componentry may be configured to address the pixels at a switchable, or otherwise variable, frame frequency. In the embodi-

ment of FIG. 3, the drive componentry includes data driver 20 and select driver 22. As shown in FIG. 3 and described in further detail hereinafter, the data driver drives a plurality of data lines 24 coupled each to a corresponding column of the LCD array. The select driver drives a plurality of select lines 26 coupled each to a corresponding row of the LCD array.

[0021] Table 1 lists example operating parameters for a seven-inch, normally white, twisted-nematic, backlit LCD panel in which each pixel is addressed through a TFT.

TABLE 1

Display parameters for an example backlit LCD	
Diagonal size	7 inches
Resolution	svga, 800 (rgb) × 600
Pixel aperture ratio	48.2%
Display luminance	296 nits
Cell transmittance	5.68%
Total power consumption	1515 milliwatts (mW) for black screen
Pixel capacitance	0.095 picofarads (pF)
Data voltage swing	0-10 volts
Drive method	dot inversion
Frame frequency (frame frequency)	60 Hz
Data line capacitance	45 pF

[0022] FIG. 4 summarizes power consumption for the system of Table 1; it shows that the data driver consumes 343 mW—i.e., 23% of the total power under black-screen conditions. In an LCD having no backlight—e.g., a reflective or transparent LCD—the data driver may be the largest power consumer.

[0023] Most of the power supplied to the data driver is dissipated in charging the data lines—viz.,

$$P_{\text{datalines}} = \frac{f C_{\text{datalines}} V^2}{2}, \quad (1)$$

where $C_{\text{datalines}}$ is the combined capacitance of the data lines (108 nanofarads (nF) for 2400 data lines in this example), f is the data-line frequency (the frame frequency times number of select lines, 36 kHz in this example), and V is the voltage swing on the data lines. As shown above, $P_{\text{datalines}}$ is proportional to the frame frequency. The power dissipated within the data driver itself is also approximately proportional to the frame frequency. Accordingly, power consumption in the LCD can be reduced significantly by lowering the frame frequency. In particular, a lower frame frequency of 1 to 6 Hz, for example, may be used to maintain a static image, reducing power consumption in the data driver by a factor of ten or more. For video, text entry, updates after touch events, scrolling, etc., the frame frequency may be restored automatically to a higher rate. In this manner, the frame-rate reduction may go unnoticed by the user.

[0024] To obtain an accurate, uniform gray scale and prevent flicker, an alternating-current (AC) square wave with data-voltage amplitude and with little or no direct-current (DC) offset should be applied to each pixel. To this end, a TFT charges each pixel to the appropriate data voltage and is subsequently switched off, so that the pixel electrode and TFT drain are left floating. To maintain an AC square wave on each pixel, the voltage holding ratio (VHR in equation 2) should be close to 100%.

$$VHR = 100\% \times \left(1 - \frac{0.5 \times I_{\text{leak}} \times t_{\text{frame}}}{C_{st} + C_{LC}} \right). \quad (2)$$

[0025] In equation 2, t_{frame} is the frame time (the inverse of the frame frequency), I_{leak} is the leakage current associated with the pixel, C_{LC} is the capacitance of the pixel itself (i.e., the sandwich structure formed by two transparent electrodes and a liquid crystal between them), and C_{st} is the storage capacitance arranged parallel to the pixel. The leakage current is the sum of several components—viz.,

$$I_{\text{leak}} = I_{\text{offTFT}} + I_{\text{leakLC}} + I_{\text{leakCst}}, \quad (3)$$

where I_{offTFT} is the off current of the associated TFT, I_{leakLC} is the leakage current through the pixel itself, and I_{leakCst} is the leakage current through the C_{st} capacitance. For high-quality dielectrics, I_{leakCst} is assumed to be negligible compared to the leakage currents I_{offTFT} and I_{leakLC} .

[0026] Based on equation 2, a large C_{st} is desirable at low frame frequencies (long t_{frame}) to optimize the voltage holding ratio. A large C_{st} would make it difficult, however, for a TFT to charge a pixel to the required data voltage at a conventional (e.g., 60 Hz) frame frequency. Accordingly, C_{st} is made variable in the embodiments disclosed herein—a larger capacitance being provided at low frame frequencies and a smaller capacitance at higher frame frequencies.

[0027] FIG. 5 schematically shows an embodiment of LCD array 12 in greater detail. Associated with each pixel 18 of the array is a corresponding charging circuit 28, through which that pixel is addressed. To address the pixels, a data line 24 is connected to each charging circuit of every column of pixels; a select line 26 is connected to each charging circuit of every row of pixels. In addition to the data and select lines, capacitance-control line 30 (C_{st2_ENABLE}) and common-voltage line 32 (V_{com}) are connected to each charging circuit.

[0028] Example pixel 18 and charging circuit 28 are shown in cross section in FIG. 6, in plan in FIG. 7, and illustrated schematically in FIG. 8. It will be noted, however, that the particular circuits and structures shown here in no way limit the scope of this disclosure, as other circuits and structures may be used to the same or similar ends. For instance, while the description herein makes reference to the twisted-nematic (TN) mode of liquid-crystal display, the present disclosure is equally compatible with vertical alignment (VA) and in-plane switching (IPS) modes.

[0029] In FIG. 6, each pixel 18 includes liquid-crystal 34 sandwiched between transparent pixel electrode 36 and transparent shared electrode 38. The liquid crystal may be of any variant suitable for display applications; it may comprise a TN liquid crystal material in one embodiment. The shared electrode and the pixel electrode may each comprise any suitable, optically transparent conductor, such as indium tin oxide (ITO). The pixel electrodes of LCD array 12 are isolated from each other, while the shared electrode extends over a plurality of pixels.

[0030] Continuing in FIG. 6, pixel electrode 36 and various components of charging circuit 28 are arranged on a first glass sheet 40, which faces backlight 14 and receives light therefrom. Shared electrode 38 is formed on a second glass sheet 42 aligned parallel to the first. In the illustrated embodiment, the first glass sheet supports a first polarizing filter 40P, and the second glass sheet supports a second polarizing filter 42P. The polarization planes of the two filters may be aligned

orthogonally to effect a 'normally white' display, in which pixel **18** is maximally transmissive (in TN mode) with the pixel and shared electrodes unbiased. In this embodiment, transmittance in the unbiased state is due to a ninety-degree rotation of the light as it traverses liquid crystal **34**. Voltage applied between the shared electrode and the pixel electrode disrupts the alignment of the liquid crystal, effecting less rotation of the light, thereby reducing transmittance through the pixel.

[0031] As shown in the drawings, each charging circuit **28** includes a pixel-selecting transistor **44** having a source **44S**, a drain **44D**, and a gate **44G**. The source of the pixel-selecting transistor is connected to data line **24**, the drain is connected to pixel electrode **36**, and the gate is connected to select line **26**. Each charging circuit also includes a capacitance-control transistor **46** having a source **46S**, a drain **46D**, and a gate **46G**, as further described hereinafter. In one embodiment, both the pixel-selecting transistor and the capacitance-control transistor are amorphous-silicon (a-Si), TFTs. The illustrated TFT configuration can be manufactured using five to seven mask steps.

[0032] In the illustrated embodiment, dielectric **48** is sandwiched between pixel electrode **36** and a transparent auxiliary electrode **50** to form an auxiliary capacitor **52**. Like pixel electrode **36** and shared electrode **38**, auxiliary electrode **50** may also comprise ITO. In one embodiment, the dielectric may comprise the same material as the gate-insulation and/or passivation layer of the pixel-selecting and/or capacitance-control transistors. In other embodiments, the dielectric may comprise a different material—e.g., tantalum oxide—and it may be situated differently. For example, instead of being directly coupled to the pixel electrode, the dielectric may in some cases be coupled to an opaque conductor linked to the pixel electrode. Accordingly, the auxiliary electrode need not be transparent in every embodiment.

[0033] In the illustrated embodiment, source **46S** of the capacitance-control transistor is connected to auxiliary electrode **38**; drain **46D** is connected to common-voltage line **32**, which is also connected to shared electrode **38**; and gate **46G** is connected to capacitance-control line **30**. Turning again to FIG. 6, charging circuit **28** also includes a permanent capacitor **56** connected in parallel to pixel **18**. In the illustrated embodiment, the permanent capacitor is formed by drain **46D** and the portion of pixel electrode **36** directly opposite the drain, with dielectric **48** sandwiched in between. In such embodiments, the size of auxiliary electrode **38** relative to drain **46D** may be chosen such that the capacitance of auxiliary capacitor **52** is much greater than the combined capacitance of permanent capacitor **56** and pixel **18**—i.e., $C_{st2} \gg C_{st1} + C_{LC}$. In other embodiments, a deliberately engineered permanent capacitance may be omitted, such that C_{st1} can be negligible, or substantially zero.

[0034] With its permanent capacitor **56** and decoupleable auxiliary capacitor **52**, charging circuit **28** provides, effectively, an adjustable storage capacitance, as shown schematically in FIG. 8. At the higher, conventional frame frequencies (e.g., 60 Hz), C_{st2} may be disconnected from V_{com} by keeping capacitance-control transistor **46** off, so that node A is allowed to float, and ultimately follows node P. Under these conditions, C_{st2} is not charged when the pixel is updated. At the lower frame frequencies (e.g., 1 to 6 Hz), the capacitance-control TFT is switched on, connecting node A to V_{com} . The large capacitance of C_{st2} ensures that during the long frame time at low frame frequencies, the root-mean-square (RMS)

voltage drop at pixel node P is less than a gray level (5 to 10 mV), even for a liquid crystal and TFT with non-optimized leakage, provided that the C_{st2} leakage is much lower. For static images, the higher capacitance may be used along with a low frame frequency, for decreased power consumption in the data driver. For dynamic images, including video, the lower capacitance may be used along with a higher frame frequency. To this end, controller **16** may include suitable capacitance-control componentry configured to maintain the storage capacitance of each charging circuit at a first level over a first frame-frequency range, and at a second, lower level over a second, higher frame-frequency range. Capacitance-control line **30** may be connected to such componentry.

[0035] The desired value of C_{st2} depends on the lower frame frequency. For example, if the frame frequency for static images is 6 Hz, both the frame time and line-select time are increased tenfold relative to high frame-frequency conditions. The total pixel capacitance may be increased tenfold as well to maintain an RMS voltage drop less than the gray level during the hold time. Accordingly,

$$C_{st2} = 9 \times (C_{st1} + C_{LC}) \quad (4)$$

[0036] The small RMS voltage drop at low frame frequencies also eliminates flicker at 3 or 6 Hz. Here capacitance-control transistor **46** is ON, which may cause a threshold voltage shift in some types of TFTs (including a-Si TFTs). The threshold voltage shift can be minimized by balancing the on and off state of the capacitance-control transistor. In some embodiments, a negative bias may be left on the $C_{st2_}$ ENABLE line when the display is not in use. In this and other embodiments, dot inversion driving may help to eliminate flicker at both high and low frame frequencies.

[0037] In the case of transreflective LCDs, the extra TFT for switching C_{st2} , as well as the extra control line, can be hidden under the reflective part of the pixel electrode. In LCDs with patterned photo spacers, the extra circuitry can also be routed under the photo spacer. C_{st1} and C_{st2} may also be connected to the next gate line, rather than to V_{com} . This eliminates the V_{com} line in charging circuit **28** and improves the aperture ratio of the display. Another option is to replace the ITO-ITO storage capacitance described hereinabove with a small-area storage capacitance having a high dielectric constant, low leakage dielectric, such as tantalum oxide.

[0038] The circuit shown in FIG. 8 was investigated using a Simulation Program with Integrated Circuit Emphasis (SPICE). Pixel-selecting transistor **44** and capacitance-control transistor **46** were each modeled as an a-Si TFT with a mobility of 0.5 square centimeters per volt-second and a threshold voltage of 2.5 volts. Table 2 shows additional modeling parameters.

TABLE 2

Parameters for SPICE simulation of the circuit of FIG. 8		
W/L	channel width/length both TFTs	10/4 micrometers
C_{LC}	LC capacitance	0.2 pF
R_{offTFT}	off (leakage) resistance of TFT	1E+13 ohm
R_{LC}	LC leakage resistance	1E+13 ohm
C_{st1}	permanent storage capacitance	0.2 pF
C_{st2}	auxiliary storage capacitance at 6 Hz	3.6 pF
$V_{S\ high}$	select on voltage	20 V
$V_{S\ low}$	select off voltage	-5 V

TABLE 2-continued

Parameters for SPICE simulation of the circuit of FIG. 8		
$V_{D\ high}$	high data voltage	8 V
$V_{D\ low}$	low data voltage	0 V
V_{COM}	common-voltage line and color filter plate	~4 V
t_{frame}	frame time for 60 Hz/6 Hz frame frequency	16.7/167 millisecond
C_{st2_ENABLE}	voltage on C_{st} control TFT for 60 Hz/6 Hz	-5 V/20 V
N_{select}	number of select lines (pixel rows)	600

[0039] FIGS. 9 and 10 show results of the simulation for high and low frame frequencies, respectively. In both figures, the pixel voltage is plotted versus time for conditions in which C_{st2} is enabled (dashed plot) and for conditions in which C_{st2} is disabled (dot-dashed plot). The requirement of a square wave with data-voltage amplitude across the pixel is achieved at 60 Hz only when C_{st2} is disabled and at 6 Hz only when C_{st2} is enabled. With C_{st2} enabled at 60 Hz, the access TFT cannot fully charge the pixel within the short line select time; with C_{st2} disabled at 6 Hz, the RMS voltage on the pixel drops significantly during the long frame time due to the leakage in the transistor and the pixel. In addition, the pixel voltage shift after switching off the gate is ten times smaller when C_{st2} is enabled than when C_{st2} is disabled. Accordingly, V_{com} may be adjusted when switching between modes to maintain a pure AC voltage with no DC component across the LC.

[0040] At high frame frequencies, the data-line capacitance is given by

$$C_{loadhr} = C_{dataline} + C_{LC} + C_{st1}, \quad (5)$$

and at low frame frequencies, the data-line capacitance is given by

$$C_{loadhr} = C_{dataline} + C_{LC} + C_{st1} + C_{st2}. \quad (6)$$

Since the data line capacitance, which is the sum of row-column crossover capacitances, gate-source capacitances, and pixel-to-data line capacitances of all pixels on one column (data line), is much larger than C_{LC} , C_{st1} and C_{st2} combined, there is less than 3% difference between C_{loadhr} and C_{loadlr} (see also Table 1). Therefore, power consumption in the data driver is substantially proportional to frame frequency.

[0041] The configurations described above enable various methods for driving an active-matrix display. Accordingly, some such methods are now described, by way of example, with continued reference to the above configurations. It will be understood, however, that the methods here described, and others fully within the scope of this disclosure, may be enabled by other configurations as well.

[0042] FIG. 11 illustrates an example method 58 for driving an active-matrix display, the display including an array of pixels individually addressable by drive componentry over a first frame-frequency range and over a second, higher frame-frequency range. As described hereinabove, a charging circuit with an adjustable storage capacitance is provided for each pixel of the display.

[0043] At 60 of method 58, a new image frame is received into one or more memory segments of a controller that provide a signal to the drive componentry of the LCD. At 62 the new image frame is compared to one or more previous image frames. At 64 it is determined whether the rate of change of

the image exceeds a predetermined threshold. As further described below, the first and second frame-frequency ranges may be selected based on the rate of change of the image.

[0044] In one embodiment, the action at 64 may comprise determining how long the image remains unchanged. Here, the rate of change will vary inversely as the lifetime of the unchanged image. In another embodiment, the rate of change may be a binary value reflecting, simply, whether the current image frame exactly matches the previous image frame. The rate of change is zero if it does and one otherwise. In any case, if the rate of change does not exceed the predetermined threshold, then the method advances to 66; otherwise, the method advances to 68.

[0045] At 66 of method 58, the C_{st2_ENABLE} line is set to a high (e.g., positive) level, and at 70, a low frame frequency is selected. The low frame frequency may be selected from a first frame-frequency range, which includes frequencies of 1 to 7 Hz. The high level on the C_{st2_ENABLE} line causes the data line to charge the C_{st2} capacitance every time the pixel is charged. Accordingly, the storage capacitance of each charging circuit is maintained at a first level over the first frame-frequency range. At 72, V_{COM} is adjusted to a higher value to reduce the DC offset across each pixel at low frame frequencies.

[0046] Step 68 of method 58 is reached when the rate of change of the image exceeds the predetermined threshold. At 68 the C_{st2_ENABLE} line is set to a low (e.g., negative) value, and at 74, a high frame frequency is selected. The high frame frequency may be selected from a second frame-frequency range, which includes frequencies of 50 to 70 Hz. In other embodiments, the second frame-frequency range may differ; it may include frequencies of 120 and/or 240 Hz, for example. The low level on the C_{st2_ENABLE} line prevents the data line from charging the C_{st2} capacitance when the pixel is charged. Accordingly, the storage capacitance of each charging circuit is maintained at a second, lower level over the second frame-frequency range. At 76 V_{COM} is adjusted to a lower value to reduce the DC offset across each pixel at high frame frequencies. From 76 or 72, method 58 returns.

[0047] In sum, the approach described herein enables an LCD with conventional-leakage TFT and LC components to operate at a variable frame frequency. By switching to the lower frame frequency during static-image display, the data driver consumes much less power. This technology is applicable in mobile devices ranging from smart phones to tablet PCs, as well as larger-format displays for internet television. In transreflective LCDs, which have room to route the extra circuitry under the reflective part of the pixel electrode, and which also may include a lower-power backlight, the variable load-capacitance design may offer an even greater reduction in power consumption. For transparent LCDs having no backlight at all, the energy savings may be greater still. In addition to numerous other applications, TFT LCDs for digital signage and e-books, which in typical operation exhibit would allow extended periods of low-refresh operation, are good candidates for implementing the strategies disclosed herein.

[0048] Finally, it will be understood that the articles, systems, and methods described hereinabove are embodiments of this disclosure—non-limiting examples for which numerous variations and extensions are contemplated as well. Accordingly, this disclosure includes all novel and non-obvious combinations and sub-combinations of the articles, systems, and methods disclosed herein, as well as any and all equivalents thereof.

1. An active-matrix display comprising:
an array of pixels;
drive componentry to individually address each pixel of the array at a variable frame frequency;
for each pixel of the array, a charging circuit through which that pixel is addressed, the charging circuit including an adjustable storage capacitance; and
capacitance-control componentry configured to maintain the storage capacitance of each charging circuit at a first level over a first frame-frequency range, and at a second, lower level over a second, higher frame-frequency range.
2. The display of claim 1 wherein each pixel includes a liquid-crystal sandwiched between a transparent pixel electrode and a transparent shared electrode, wherein the shared electrode extends over a plurality of pixels of the array.
3. The display of claim 2 wherein the liquid-crystal is a twisted-nematic liquid crystal.
4. The display of claim 2 wherein each charging circuit includes:
a pixel-selecting transistor having a drain connected to the pixel electrode;
a capacitance-control transistor; and
an auxiliary capacitor including a dielectric and an auxiliary electrode, a source of the capacitance-control transistor connected to the auxiliary electrode.
5. The display of claim 4 wherein the pixel-selecting transistor, the capacitance-control transistor, and the pixel electrode are arranged on a first glass sheet, wherein the shared electrode is formed on a second glass sheet parallel to the first, and wherein the first and second glass sheets each support a polarizing filter.
6. The display of claim 4 wherein the pixel-selecting transistor and the capacitance-control transistor are amorphous-silicon, thin-film transistors.
7. The display of claim 6 wherein the transistors include a gate-insulation and/or passivation layer, and wherein the dielectric comprises the same material as the gate-insulation and/or passivation layer.
8. The display of claim 4 wherein the dielectric comprises tantalum oxide.
9. The display of claim 4 wherein the dielectric is sandwiched between the pixel electrode and the auxiliary electrode, and wherein the auxiliary electrode is transparent.
10. The display of claim 4 wherein the shared electrode, the pixel electrode, and the auxiliary electrode comprise indium tin oxide.
11. The display of claim 4 further comprising:
for each column of pixels, a data line connected to the charging circuit of each pixel of the column at a source of the pixel-selecting transistor;
for each row of pixels, a select line connected to the charging circuit of each pixel of the row at a gate of the pixel-selecting transistor;
a common-voltage line connected to the shared electrode and to the charging circuit of each pixel of the array at a drain of the capacitance-control transistor; and
a capacitance-control line connected to the charging circuit of each pixel of the array at a gate of the capacitance-control transistor;

wherein the common-voltage line, each data line, and each select line are connected to the drive componentry, and wherein the capacitance-control line is connected to the capacitance-control componentry.

12. The display of claim 4 wherein each charging circuit further includes a permanent capacitor connected in parallel to the corresponding pixel.

13. The display of claim 12 wherein a size of the auxiliary electrode is such that the capacitance of the auxiliary capacitor is greater than the combined capacitance of the permanent capacitor and the pixel.

14. A method of driving an active-matrix display, the display including an array of pixels individually addressable by drive componentry over a first frame-frequency range and over a second, higher frame-frequency range, and, for each pixel of the array, a charging circuit through which that pixel is addressed, the charging circuit including an adjustable storage capacitance, the method comprising:

maintaining the storage capacitance of each charging circuit at a first level over the first frame-frequency range; and

maintaining the storage capacitance of each charging circuit at a second, lower level over the second frame-frequency range.

15. The method of claim 14 wherein the first frame-frequency range includes frequencies of 1 to 7 Hz.

16. The method of claim 14 wherein the second frame-frequency range includes frequencies of 50 to 70 Hz and/or frequencies of 120 and 240 Hz.

17. The method of claim 14 wherein maintaining the storage capacitance at the first level includes applying a positive voltage to a capacitance-control line of the display, the capacitance control line connected to a charging circuit of each pixel of the array at a gate of a capacitance-control transistor;

and wherein maintaining the storage capacitance at the second level includes applying a negative voltage to the capacitance-control line.

18. The method of claim 17 further comprising adjusting a voltage applied to a shared electrode of the pixel array based on whether a positive or negative voltage is applied to the capacitance-control line, in order to reduce a dc offset across each pixel in both the first and second frame-frequency ranges.

19. The method of claim 14 further comprising selecting between the first and second frame-frequency ranges based on a rate of change of a signal provided to the drive componentry.

20. An active matrix comprising:

an array of pixels individually addressable over a first frame-frequency range and over a second, higher frame-frequency range; and

for each pixel of the array, a charging circuit through which that pixel is addressed, the charging circuit including an adjustable storage capacitance and configured such that the storage capacitance of each charging circuit is maintained at a first level over the first frame-frequency range, and at a second, lower level over the second frame-frequency range.

* * * * *

专利名称(译)	可变帧频薄膜晶体管液晶显示器		
公开(公告)号	US20120113080A1	公开(公告)日	2012-05-10
申请号	US13/270140	申请日	2011-10-10
[标]申请(专利权)人(译)	SCANVUE TECH		
申请(专利权)人(译)	SCANVUE技术有限责任公司		
当前申请(专利权)人(译)	苹果公司.		
[标]发明人	DEN BOER WILLEM		
发明人	DEN BOER, WILLEM		
IPC分类号	G09G3/36 G06F3/038		
CPC分类号	G09G2300/0876 G09G2320/103 G09G2330/021 G09G2300/0456 G02F1/136213 G02F1/13624 G09G3/3648 G09G2340/0435		
优先权	61/410305 2010-11-04 US		
其他公开文献	US8730226		
外部链接	Espacenet USPTO		

摘要(译)

有源矩阵包括可在第一帧频范围和第二较高帧频范围内单独寻址的像素阵列。对于阵列的每个像素，有源矩阵还包括充电电路，通过该充电电路寻址该像素。每个充电电路包括可调节的存储电容，并且被配置为使得存储电容在第一帧频范围内保持在第一水平，并且在第二帧频范围内保持在第二低水平。

