



US009318218B2

(12) **United States Patent**
Wang et al.

(10) **Patent No.:** **US 9,318,218 B2**
(45) **Date of Patent:** **Apr. 19, 2016**

(54) **SHIFT REGISTER AND DRIVING CIRCUIT FOR LIQUID CRYSTAL DISPLAY**

(71) Applicant: **Century Technology (Shenzhen) Corporation Limited**, Shenzhen (CN)

(72) Inventors: **Ming-Tsung Wang**, New Taipei (TW); **Wen-Lin Mei**, Shenzhen (CN); **Hui Wang**, Shenzhen (CN); **Chia-Hua Huang**, New Taipei (TW)

(73) Assignee: **Century Technology (Shenzhen) Corporation Limited**, Shenzhen (CN)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 15 days.

(21) Appl. No.: **14/301,495**

(22) Filed: **Jun. 11, 2014**

(65) **Prior Publication Data**

US 2014/0362067 A1 Dec. 11, 2014

(30) **Foreign Application Priority Data**

Jun. 11, 2013 (CN) 2013 1 02302745

(51) **Int. Cl.**

G09G 3/36 (2006.01)

G11C 19/28 (2006.01)

(52) **U.S. Cl.**

CPC **G11C 19/28** (2013.01); **G09G 3/3677** (2013.01); **G09G 2310/0286** (2013.01); **G09G 2320/0219** (2013.01)

(58) **Field of Classification Search**

CPC G09G 3/30; G09G 5/00; G06F 3/038
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

2007/0274433 A1* 11/2007 Tobita G11C 19/28
377/64
2011/0044423 A1* 2/2011 Lin G09G 3/32
377/64
2011/0058642 A1* 3/2011 Tsai G09G 3/3677
377/79
2011/0216877 A1* 9/2011 Hsu G11C 19/00
377/79
2011/0234577 A1* 9/2011 Yang G09G 3/3677
345/212
2012/0008731 A1* 1/2012 Hsu G11C 19/28
377/79

* cited by examiner

Primary Examiner — Pegeman Karimi


(74) *Attorney, Agent, or Firm* — Novak Druce Connolly Bove + Quigg LLP

(57) **ABSTRACT**

A shift register for an LCD display includes N shift register units. Each shift register unit outputs a shift signal. An N^{th} shift register unit includes a waveform-shaping unit electrically coupled to an shift signal output terminal of the N^{th} register to perform a waveform-shaping operation on the N^{th} shift signal according to the $(N+1)^{th}$ shift signal output by an $(N+1)^{th}$ shift register, to reduce the feed-through effect which causes display flicker.

16 Claims, 5 Drawing Sheets

10




10

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5

SHIFT REGISTER AND DRIVING CIRCUIT FOR LIQUID CRYSTAL DISPLAY

CROSS-REFERENCE TO RELATED APPLICATIONS

This application claims priority to Chinese Patent Application No. 201310230274.5 filed on Jun. 11, 2013 in the China Intellectual Property Office, the contents of which are incorporated by reference herein.

FIELD

The disclosure generally relates to shift registers, and more particularly to a shift register in a driving circuit for a liquid crystal display (LCD).

BACKGROUND

An LCD panel usually employs a scanning driving circuit and a data driving circuit to provide scanning signals and display data signals, respectively. A shift register is an important component of both the data driving circuit and the scanning driving circuit. Generally, the shift register includes a plurality of shift register units coupled one by one. In the operation of the shift register circuit, the shift register provides the gate signals having periodical pulses to pixel units of the LCD panel for writing the data signals which become pixel voltages of the pixel units. However, each pulse of the gate signals is substantially a square waveform signal, and a falling edge of each pulse may cause an occurrence of pulling down the written pixel voltages due to the coupling effect of the parasitic capacitors corresponding to the pixel units. This phenomenon is referred to as the feed-through effect. The feed-through effect is likely to cause image flicker, and the display quality of liquid crystal displays using the shift register circuit is therefore degraded.

BRIEF DESCRIPTION OF THE DRAWINGS

Implementations of the present technology will now be described, by way of example only, with reference to the attached figures:

FIG. 1 is a block diagram of a shift register including a plurality of shift register units according to an exemplary embodiment of the present disclosure.

FIG. 2 is a waveform diagram of exemplary clock signals of the shift register of FIG. 1.

FIG. 3 is a circuit diagram of an N^{th} shift register of FIG. 1.

FIG. 4 is a diagram of sequential waveforms of exemplary pulse signals of the N^{th} shift register of FIG. 3.

FIG. 5 is a block diagram of a liquid crystal display including the shift register of FIG. 1.

DETAILED DESCRIPTION

It will be appreciated that for simplicity and clarity of illustration, where appropriate, reference numerals have been repeated among the different figures to indicate corresponding or analogous elements. In addition, numerous specific details are set forth in order to provide a thorough understanding of the embodiments described herein. However, it will be understood by those of ordinary skill in the art that the embodiments described herein can be practiced without these specific details. In other instances, methods, procedures, and components have not been described in detail so as not to obscure the related relevant feature being described. The

drawings are not necessarily to scale and the proportions of certain parts may be exaggerated to better illustrate details and features. The description is not to be considered as limiting the scope of the embodiments described herein.

Referring to FIG. 1, a shift register 10 can include a plurality of shift register units 100. The shift register units 100 sequentially output a plurality of first shift signals, namely Vout1, Vout2, Vout3 . . . Vout(N-1), VoutN, Vout(N+1), Vout(N+2) . . . , wherein N is a natural number.

Each shift register unit 100 can include a clock signal input terminal CIN, a starting signal input terminal STV, a shift signal output terminal OUT, a first cascade signal output terminal V1, a first cascade signal input terminal L1, a second cascade signal output terminal V2, a second cascade signal input terminal L2, a first feedback terminal FB1, and a second feedback terminal FB2. The clock signal input terminal CIN receives a clock signal. Each of the four shift register units 100 receive different clock signals. For example, in this exemplary embodiment, the $(N-1)^{th}$, N^{th} , $(N+1)^{th}$, and $(N+2)^{th}$ shift register units 100 receive different clock signals, as shown in FIG. 2.

In at least one embodiment, the clock signal input terminal CIN of the N^{th} shift register unit 100 receives a first clock signal CLK1. The first cascade signal output terminal V1 of the N^{th} shift register unit 100 is electrically coupled to the first cascade signal input terminal L1 of the $(N-1)^{th}$ shift register unit 100. The second cascade signal input terminal L2 of the N^{th} shift register unit 100 is electrically coupled to the second cascade signal output terminal V2 of the $(N-1)^{th}$ shift register unit 100. The first cascade signal input terminal L1 of the N^{th} shift register unit 100 is electrically coupled to the first cascade signal output terminal V1 of the $(N+1)^{th}$ shift register unit 100. The second cascade signal output terminal V2 of the N^{th} shift register unit 100 is electrically coupled to the second cascade signal input terminal L2 of the $(N+1)^{th}$ shift register unit 100. The starting signal input terminal STV of the N^{th} shift register unit 100 is electrically coupled to the shift signal output terminal OUT of the $(N-1)^{th}$ shift register unit 100. The $(N-1)^{th}$ shift signal Vout(N-1) is a starting signal of the N^{th} shift register unit 100 which is configured to start the N^{th} shift register unit 100. The shift signal output terminal OUT of the N^{th} shift register unit 100 is electrically coupled to the starting signal input terminal STV of the $(N+1)^{th}$ shift register unit 100. The first feedback terminal FB1 of the N^{th} shift register unit 100 is electrically coupled to the shift signal output terminal OUT of the $(N+1)^{th}$ shift register unit 100, and the $(N+1)^{th}$ shift signal Vout(N+1) output by the $(N+1)^{th}$ shift register unit 100 is defined as a first feedback signal. The second feedback terminal FB2 of the N^{th} shift register unit 100 is electrically coupled to the shift signal output terminal OUT of the $(N+2)^{th}$ shift register unit 100, and the $(N+2)^{th}$ shift signal Vout(N+2) output by the $(N+2)^{th}$ shift register unit 100 is defined as a second feedback signal.

Referring to FIG. 3, the N^{th} shift register unit 100 can include a starting unit 101, a pull-up unit 103, a pull-down unit 105, a control unit 107, and a waveform-shaping unit 109. The starting unit 101 outputs a first driving signal to the pull-up unit 103 according to the starting signal. The pull-up unit 103 is electrically coupled between the starting unit 101 and the shift signal output terminal OUT. The pull-up unit 103 pulls up the value of the shift signal VoutN according to the first driving signal and the first clock signal CLK1. The pull-down unit 105 is electrically coupled between the starting unit 101 and the shift signal output terminal OUT to pull down the value of the first driving signal. The control unit 107 is electrically coupled between the starting unit and the pull-down unit 105 to control a working time of the pull-down unit 105

according to the $(N+2)^{th}$ shift signal, a first control signal VG1, and a second control signal VG2. In the embodiment, the first control signal VG1 and the second control signal VG2 are both output by an external controller. The waveform-shaping unit 109 is electrically coupled to the shift signal output terminal OUT to perform a waveform-shaping operation on the Nth shift signal VoutN under the control of the $(N+1)^{th}$ shift signal.

The starting unit 101 can include a first transistor T1. A gate electrode of the first transistor T1 is electrically coupled to the starting signal input terminal STV and a source electrode of the first transistor T1.

The pull-up unit 103 can include a second transistor T2 and a first capacitor C1. A gate electrode of the second transistor T2 is electrically coupled to a drain electrode of the first transistor T1. The first capacitor C1 is electrically coupled between the gate electrode of the second transistor T2 and a drain electrode of the second transistor T2. A source electrode of the second transistor T2 is electrically coupled to the clock signal input terminal CIN to receive the first clock signal CLK1. The gate electrode of the second transistor T2 is electrically coupled to the first cascade signal output terminal V1 of the Nth shift register unit 100.

The pull-down unit 105 can include a first pull-down transistor M1, a second pull-down transistor M2, a third pull-down transistor M3, and a fourth pull-down transistor M4. A gate electrode of the first pull-down transistor M1 is electrically coupled to a gate electrode of the second pull-down transistor M2. Source electrodes of the first and third pull-down transistors M1 and M3 are electrically coupled to the gate electrode of the second transistor T2. Source electrodes of the second and fourth pull-down transistors M2 and M4 are electrically coupled to the shift signal output terminal OUT. Drain electrodes of the first, second, third, and fourth pull-down transistors, M1, M2, M3, and M4, receive a logic-low signal provided by an external power source. A node between the gate electrode of the third pull-down transistor M3 and the gate electrode of the fourth pull-down transistor M4 is electrically coupled to the second cascade signal input terminal L2 of the Nth shift register unit 100.

The control unit 107 can include a third transistor T3, a fourth transistor T4, a fifth transistor T5, a sixth transistor T6, a seventh transistor T7, and an eighth transistor T8. A gate electrode of the third transistor T3 is the second feedback terminal FB2 of the Nth shift register unit 100. A source electrode of the third transistor T3 is electrically coupled to the drain electrode of the first transistor T1. A drain electrode of the third transistor T3 receives the logic-low signal VEE. In the embodiment, the drain electrode of the third transistor T3 is grounded. A gate electrode of the fourth transistor T4 is electrically coupled to the drain electrode of the first transistor T1, and a drain electrode of the fourth transistor T4 receives the logic-low signal VEE. A source electrode of the fourth transistor T4 is electrically coupled to the source electrodes of the fifth, sixth, seventh, and eighth transistors, T5-T8. The source electrodes of the fourth, fifth, sixth, seventh, and eighth transistors, T4-T8, receive the logic-low signal VEE. A gate electrode of the sixth transistor T6 is electrically coupled to the source electrode of the sixth transistor T6. The gate electrode of the sixth transistor T6 receives the first control signal VG1 from the external controller, and a gate electrode of the eighth transistor T8 receives the second control signal VG2 from the external controller. A gate electrode of the fifth transistor T5 is electrically coupled to the first cascade signal input terminal L1. The gate electrode of the fifth transistor T5 is electrically coupled to the first cascade signal output terminal V1 of the $(N+1)^{th}$ shift register

unit 100. A gate of the seventh transistor T7 is electrically coupled to the second feedback terminal FB2 to receive the $(N+2)^{th}$ shift signal output by the $(N+2)^{th}$ shift register unit 100. A node between the drain electrode of the sixth transistor T6 and the drain electrode of the eighth transistor T8 is electrically coupled to the second cascade signal output terminal V2 of the Nth shift register unit 100. In the embodiment, a ratio of width and length of a channel layer of the sixth transistor T6 is 100 times greater than a ratio of width and length of a channel layer of the eighth transistor T8. A ratio of width and length of a channel layer of fifth transistor T5 is 100 times greater than a ratio of width and length of a channel layer of the eighth transistor T8.

The waveform-shaping unit 109 can include a ninth transistor T9. A gate electrode of the ninth transistor T9 can be electrically coupled to the first feedback terminal FB1 of the Nth shift register unit 100 to receive the $(N+1)^{th}$ shift signal output by the $(N+1)^{th}$ shift register unit 100. A source electrode of the ninth transistor T9 can be electrically coupled to the shift signal output terminal OUT, and a drain electrode of the ninth transistor T9 to receive the logic-low signal VEE.

Referring to FIG. 4, VIN represents a first cascade output signal output by the first cascade signal output terminal V1 of the Nth shift register unit 100. L1N represents a first cascade input signal to be transmitted to the first cascade signal input terminal L1 of the Nth shift register unit 100. V2N represents a second cascade output signal output by the second cascade signal output terminal V2 of the Nth shift register unit 100. L2N represents a second cascade input signal to be transmitted to the second cascade signal input terminal L2 of the Nth shift register unit 100.

During a first period P1, the starting signal STV is at logic-high, the first clock signal CLK1 is logic-low, the first control signal VG1 is at logic-high, and the second control signal VG2 is at logic-low. The first transistor T1 and the second transistor T2 are both turned on under control of the starting signal STV and the first control signal VG1. The first clock signal CLK1 is output by the shift signal output terminal OUT, thus the Nth shift signal VoutN is at logic-low. The first capacitor C1 is charged by the starting signal STV, and the first cascade output signal V1N is at logic-high. In the control unit 107, the fourth transistor T4 and the sixth transistor T6 are turned on, the second cascade output signal V2N is at logic-low, thus the first and second pull-down transistors M1 and M2 are turned off.

During a second period P2, the starting signal STV changes to a logic-low to turn off the first transistor T1 from the logic-high and the first clock signal CLK1 changes from a logic-low to a logic-high. The first cascade signal output terminal V1 is at logic-high because of the existence of the first capacitor C1. In the control unit 107, the fourth transistor T4 and the sixth transistor T6 are turned on, the second cascade output signal V2N is at logic-low to turn off the first and second pull-down transistors M1 and M2.

During a third period P3, the starting signal STV is at logic-low and the first transistor T1 is turned off. The first cascade signal output terminal V1 is at logic-high because of the existence of the first capacitor C1. The $(N+1)^{th}$ shift signal Vout(N+1) is at logic-high to turn on the ninth transistor T9, and the logic-low signal VEE performs a waveform-shaping operation on the Nth shift signal VoutN to pull it down.

During a fourth period P4, the $(N+2)^{th}$ shift signal Vout(N+2) is at logic-high, and the third transistor T3 is turned on, the first cascade output signal V1N changes from a logic-high to a logic-low to turn off the second transistor T2 and the fourth transistor T4. The first transistor T1 is turned on. The second cascade output signal V2N is at logic-low.

During a fifth period P5, the first cascade input signal L1N changes from a logic-high to a logic-low, and the second cascade output signal V2N is at logic-high, thus the first and second pull-down transistors M1 and M2 are turned on and the first cascade output signal V1N changes from a logic-high to a logic-low.

Referring to FIG. 5, a liquid crystal display 1 can include a liquid crystal panel 12, a data driver 14, and a gate driver 16. The gate driver 16 outputs a plurality of gate signals to control a working state of a plurality of thin film transistors of the liquid crystal panel 12. The data driver 14 outputs a plurality of data signals to the liquid crystal panel 12. The gate driver 16 controls a timing sequence of the gate signals through the shift register 100.

It is to be understood that even though numerous characteristics and advantages of the present embodiments have been set forth in the foregoing description, with details of the structures and functions of the embodiments, the disclosure is illustrative only; and changes may be in detail, including in the matter of arrangement of parts within the principles of the embodiments to the full extent indicated by the broad general meaning of the terms in which the appended claims are expressed.

What is claimed is:

1. A shift register comprising:
 - a plurality of shift register units, each shift register unit outputting a shift signal, an N^{th} shift register unit comprising:
 - a starting unit electrically coupled to an $(N-1)^{th}$ shift register and outputting a first driving signal according to an $(N-1)^{th}$ shift signal output by an $(N-1)^{th}$ shift register;
 - a pull-up unit electrically coupled between the starting unit and a shift signal output terminal of the N^{th} shift register unit and pulling up an N^{th} shift signal output by an N^{th} shift register according to the first driving signal and a first clock signal;
 - a pull-down unit electrically coupled between the starting unit and the shift signal output terminal of the N^{th} shift register unit and pulling down the first driving signal;
 - a control unit electrically coupled between the starting unit and the pull-down unit to control a working time of the pull-down unit according to an $(N+2)^{th}$ shift signal, a first control signal, and a second control signal; and
 - a waveform-shaping unit electrically coupled to the shift signal output terminal of the N^{th} register to perform a waveform-shaping operation on the N^{th} shift signal according to the $(N+1)^{th}$ shift signal;
 - wherein each of the shift register units comprises a first cascade signal output terminal, a first cascade signal input terminal, a second cascade signal input terminal, a second cascade signal output terminal, a first feedback terminal, and a second feedback terminal; the first cascade signal output terminal of the N^{th} shift register unit is electrically coupled to the first cascade signal output terminal of an $(N+1)^{th}$ shift register unit, the first cascade signal output terminal of the N^{th} shift register unit is electrically coupled to the first cascade signal input terminal of the $(N-1)^{th}$ shift register unit, the second cascade signal output terminal of the N^{th} shift register unit is electrically coupled to the second cascade signal input terminal of the $(N-1)^{th}$ shift register unit, the first feedback terminal of the N^{th} shift register unit receives the $(N+1)^{th}$ shift signal, and the second feedback terminal of the N^{th} shift register unit receives the $(N+2)^{th}$ shift signal.
2. The shift register of claim 1, wherein the starting unit comprises a first transistor, and a gate electrode of the first

transistor is electrically coupled to the starting signal input terminal STV and a source electrode of the first transistor.

3. The shift register of claim 2, wherein the pull-up unit comprises a second transistor and a first capacitor, a gate electrode of the second transistor is electrically coupled to a drain electrode of the first transistor; the first capacitor is electrically coupled between the gate electrode of the second transistor and a drain electrode of the second transistor, a source electrode of the second transistor is electrically coupled to the clock signal input terminal to receive the first clock signal.

4. The shift register of claim 3, wherein the gate electrode of the second transistor is electrically coupled to the first cascade signal output terminal of the N^{th} shift register.

5. The shift register of claim 3, wherein the pull-down unit comprises a first pull-down transistor, a second pull-down transistor, a third pull-down transistor, and a fourth pull-down transistor, a gate electrode of the first pull-down transistor is electrically coupled to a gate electrode of the second pull-down transistor, source electrodes of the first and third pull-down transistors and are electrically coupled to the gate of the second transistor, and source electrodes of the second and fourth pull-down transistors are electrically coupled to the shift signal output terminal, and drain electrodes of the first, second, third, and fourth pull-down transistor receive a logic-low signal provided by an external power source.

6. The shift register of claim 5, wherein a node between the gate electrode of the third pull-down transistor and the gate electrode of the fourth pull-down transistor is electrically coupled to the second cascade signal input terminal of the N^{th} shift register unit.

7. The shift register of claim 5, wherein the control unit comprises third, fourth, fifth, sixth, seventh, and eighth transistors, and a gate of the third transistor is electrically coupled to the second feedback terminal of the N^{th} shift register unit, and a source electrode of the third transistor is electrically coupled to the drain electrode of the first transistor, a drain electrode of the third transistor receives the logic-low signal; a gate electrode of the fourth transistor is electrically coupled to the drain electrode of the first transistor; a drain electrode of the fourth transistor receives the logic-low signal, and a source electrode of the fourth transistor is electrically coupled to source electrodes of the fifth, sixth, seventh, and eighth transistors, the source electrodes of the fourth, fifth, seventh, and eighth transistors receive the logic-low signal, a gate electrode of the sixth transistor is electrically coupled to the source electrode of the sixth transistor, the gate electrode of the sixth transistor receives the first control signal; and a gate electrode of the eighth transistor receives the second control signal, a gate electrode of the fifth transistor is electrically coupled to the first cascade signal input terminal and the first cascade signal output terminal of the $(N+1)^{th}$ shift register unit, a gate electrode of the seventh transistor is electrically coupled to the second feedback terminal to receive the $(N+2)^{th}$ shift signal output by the $(N+2)^{th}$ shift register unit; and a node between the drain electrode of the sixth transistor and the drain electrode of the eighth transistor is electrically coupled to the second cascade signal output terminal of the N^{th} shift register unit.

8. The shift register of claim 7, wherein the waveform-shaping unit comprises a ninth transistor, a gate electrode of the ninth transistor is electrically coupled to the first feedback terminal of the N^{th} shift register unit to receive the $(N+1)^{th}$ shift signal output by the $(N+1)^{th}$ shift register unit, a source electrode of the ninth transistor is electrically coupled to the shift signal output terminal, and a drain electrode of the ninth transistor receives the logic-low signal.

9. A liquid crystal display comprising:
 a display panel, a date driver, and a gate driver;
 the gate driver comprising a shift register comprising:
 a plurality of shift register units, each shift register unit
 outputting a shift signal, an Nth shift register unit
 comprising:
 a starting unit electrically coupled to an (N-1)th
 shift register and outputting a first driving signal accord-
 ing to an (N-1)th shift signal output by an (N-1)th shift
 register;
 a pull-up unit electrically coupled between the starting unit
 and a shift signal output terminal of the Nth shift register
 unit and pulling up an Nth shift signal output by an Nth
 shift register according to the first driving signal and a
 first clock signal;
 a pull-down unit electrically coupled between the starting
 unit and a shift signal output terminal of the Nth shift
 register unit and pulling down the first driving signal;
 a control unit electrically coupled between the starting unit
 and the pull-down unit to control a working time of the
 pull-down unit according to an (N+2)th shift signal, a
 first control signal, and a second control signal; and
 a waveform-shaping unit electrically coupled to the shift
 signal output terminal of the Nth register to perform a
 waveform-shaping operation on the Nth shift signal
 according to the (N+1)th shift signal;
 wherein each of the shift register units comprises a first
 cascade signal output terminal, a first cascade signal
 input terminal, a second cascade signal input terminal, a
 second cascade signal output terminal, a first feedback
 terminal, and a second feedback terminal; the first cas-
 cade signal output terminal of the Nth shift register unit is
 electrically coupled to the first cascade signal output
 terminal of an (N+1)th shift register unit, the first cas-
 cade signal output terminal of the Nth shift register unit is
 electrically coupled to the first cascade signal input ter-
 minal of the (N-1)th shift register unit, the second cas-
 cade signal output terminal of the Nth shift register unit is
 electrically coupled to the second cascade signal input
 terminal of the (N-1)th shift register unit, the first feed-
 back terminal of the Nth shift register unit receives the
 (N+1)th shift signal, and the second feedback terminal of
 the Nth shift register unit receives the (N+2)th shift sig-
 nal.

10. The liquid crystal display of claim 9, wherein the start-
 ing unit comprises a first transistor, and a gate electrode of the
 first transistor is electrically coupled to the starting signal
 input terminal STV and a source electrode of the first transis-
 tor.

11. The liquid crystal display of claim 10, wherein the
 pull-up unit comprises a second transistor and a first capaci-
 tor, a gate electrode of the second transistor is electrically
 coupled to a drain electrode of the first transistor; the first
 capacitor is electrically coupled between the gate electrode of
 the second transistor and a drain electrode of the second
 transistor, a source electrode of the second transistor is elec-
 trically coupled to the clock signal input terminal to receive
 the first clock signal.

12. The liquid crystal display of claim 11, wherein the gate
 electrode of the second transistor is electrically coupled to the
 first cascade signal output terminal of the Nth shift register.

13. The liquid crystal display of claim 11, wherein the
 pull-down unit comprises a first pull-down transistor, a sec-
 ond pull-down transistor, a third pull-down transistor, and a
 fourth pull-down transistor, a gate electrode of the first pull-
 down transistor is electrically coupled to a gate electrode of
 the second pull-down transistor, source electrodes of the first
 and third pull-down transistors and are electrically coupled to
 the gate of the second transistor, and source electrodes of the
 second and fourth pull-down transistors are electrically
 coupled to the shift signal output terminal, and drain elec-
 trodes of the first, second, third, and fourth pull-down tran-
 sistor receive a logic-low signal provided by an external
 power source.

14. The liquid crystal display of claim 13, wherein a node
 between the gate electrode of the third pull-down transistor
 and the gate electrode of the fourth pull-down transistor is
 electrically coupled to the second cascade signal input termi-
 nal of the Nth shift register unit.

15. The liquid crystal display of claim 13, wherein the
 control unit comprises third, fourth, fifth, sixth, seventh, and
 eighth transistors, and a gate of the third transistor is electri-
 cally coupled to the second feedback terminal of the Nth shift
 register unit, and a source electrode of the third transistor is
 electrically coupled to the drain electrode of the first transis-
 tor, a drain electrode of the third transistor receives the logic-
 low signal; a gate electrode of the fourth transistor is electri-
 cally coupled to the drain electrode of the first transistor; a
 drain electrode of the fourth transistor receives the logic-low
 signal, and a source electrode of the fourth transistor is elec-
 trically coupled to source electrodes of the fifth, sixth, sev-
 enth, and eighth transistors, the source electrodes of the
 fourth, fifth, seventh, and eighth transistors receive the logic-
 low signal, a gate electrode of the sixth transistor is electri-
 cally coupled to the source electrode of the sixth transistor,
 the gate electrode of the sixth transistor receives the first
 control signal; and a gate electrode of the eighth transistor
 receives the second control signal, a gate electrode of the fifth
 transistor is electrically coupled to the first cascade signal
 input terminal and the first cascade signal output terminal of
 the (N+1)th shift register unit, a gate electrode of the seventh
 transistor is electrically coupled to the second feedback ter-
 minal to receive the (N+2)th shift signal output by the (N+2)th
 shift register unit; and a node between the drain electrode of
 the sixth transistor and the drain electrode of the eighth tran-
 sistor is electrically coupled to the second cascade signal
 output terminal of the Nth shift register unit.

16. The liquid crystal display of claim 15, wherein the
 waveform-shaping unit comprises a ninth transistor, a gate
 electrode of the ninth transistor is electrically coupled to the
 first feedback terminal of the Nth shift register unit to receive
 the (N+1)th shift signal output by the (N+1)th shift register
 unit, a source electrode of the ninth transistor is electrically
 coupled to the shift signal output terminal, and a drain elec-
 trode of the ninth transistor receives the logic-low signal.

* * * * *

专利名称(译)	用于液晶显示器的移位寄存器和驱动电路		
公开(公告)号	US9318218	公开(公告)日	2016-04-19
申请号	US14/301495	申请日	2014-06-11
[标]申请(专利权)人(译)	深超光电(深圳)有限公司		
申请(专利权)人(译)	世纪科技 (深圳) 股份有限公司		
当前申请(专利权)人(译)	世纪科技 (深圳) 股份有限公司		
[标]发明人	WANG MING TSUNG MEI WEN LIN WANG HUI HUANG CHIA HUA		
发明人	WANG, MING-TSUNG MEI, WEN-LIN WANG, HUI HUANG, CHIA-HUA		
IPC分类号	G09G3/36 G11C19/28		
CPC分类号	G11C19/28 G09G3/3677 G09G2310/0286 G09G2320/0219		
优先权	201310230274.5 2013-06-11 CN		
其他公开文献	US20140362067A1		
外部链接	Espacenet USPTO		

摘要(译)

用于LCD显示器的移位寄存器包括N个移位寄存器单元。每个移位寄存器单元输出移位信号。Nth 移位寄存器单元包括波形整形单元，其电耦合到Nth 寄存器的移位信号输出端子，以在第N移位执行波形整形操作根据 (N + 1)th 移位寄存器输出的 (N + 1)th 移位信号，以减少导致显示闪烁的馈通效应。

register to perform a waveform-shaping operation on the Nth shift signal according to the (N+1)th shift signal output by an (N+1)th shift register, to reduce the feed-through effect which