

(19)



(11)

EP 2 345 023 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:

16.01.2013 Bulletin 2013/03

(51) Int Cl.:

G09G 3/32 (2006.01)

(21) Application number: **09789397.8**

(86) International application number:

PCT/US2009/005466

(22) Date of filing: **05.10.2009**

(87) International publication number:

WO 2010/044827 (22.04.2010 Gazette 2010/16)

(54) **DISPLAY DEVICE WITH COMPENSATION FOR VARIATIONS IN PIXEL TRANSISTORS MOBILITY**

ANZEIGEANORDNUNG MIT KOMPENSATION VON SCHWANKUNGEN DER
PIXELTRANSISTORMOBILITÄT

DISPOSITIF D'AFFICHAGE AVEC COMPENSATION DES VARIATIONS DE LA MOBILITÉ DES
TRANSISTORS DE PIXEL

(84) Designated Contracting States:

**AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL
PT RO SE SI SK SM TR**

(72) Inventor: **KAWABE, Kazuyoshi**

Kanagawa, 222-0033 (JP)

(30) Priority: **16.10.2008 JP 2008267708**

(74) Representative: **Wibbelmann, Jobst**

Wuesthoff & Wuesthoff

Patent- und Rechtsanwälte

Schweigerstrasse 2

81541 München (DE)

(43) Date of publication of application:

20.07.2011 Bulletin 2011/29

(73) Proprietor: **Global OLED Technology LLC**

Herndon, VA 20171 (US)

(56) References cited:

US-A1- 2006 066 254

US-A1- 2008 048 955

US-A1- 2008 055 299

EP 2 345 023 B1

Note: Within nine months of the publication of the mention of the grant of the European patent in the European Patent Bulletin, any person may give notice to the European Patent Office of opposition to that patent, in accordance with the Implementing Regulations. Notice of opposition shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

Description

FIELD OF THE INVENTION

[0001] The present invention relates to a display panel with pixels, including current driven type light emitting elements, arranged in a matrix shape.

BACKGROUND OF THE INVENTION

[0002] Because an organic EL display that uses organic EL elements, being current driven light emitting elements, is of the self-emissive type, it has high contrast and fast response, making it suitable for moving picture applications such as a television for displaying natural images. Generally, an organic EL element is driven with a fixed current using a control element such as a transistor, but the transistor in that case is used in the saturation region. Therefore, even if the same gradation voltage is supplied, a different current is generated in each pixel due to variations in characteristics such as V_{th} (threshold voltage) and mobility of the transistors, making it difficult to maintain uniformity of emission brightness. In order to solve this problem, a structure having a circuit for compensating for V_{th} provided inside a pixel is disclosed in WO 98/48403.

[0003] If the V_{th} correction circuit shown in FIG. 3 of WO 98/48403 is used, a gradation signal voltage is normally applied to the gate terminal of a drive transistor for supplying current to an organic EL element to offset that V_{th} . V_{th} of the drive transistor is therefore automatically corrected. However, it is also difficult to correct mobility of carriers such as electrons in the transistor with the V_{th} correction circuit of the related art disclosed in WO 98/48403, and it is difficult to ensure high brightness uniformity over a wide gradation range when there are variations in mobility between pixels.

[0004] Document US 2008/0048955 A1 concerns a pixel circuit in which a scan line is arranged in a row direction to supply a control signal and a data line is arranged in a column direction to supply a video signal. The pixel circuit includes a sampling transistor, a drive transistor, a capacitor connected between the current path end of the sampling transistor and the gate of the drive transistor, and a light-emitting device connected to the current path end of the drive transistor. The pixel circuit connects the mobility with negative feedback during a mobility connection.

SUMMARY OF THE INVENTION

[0005] Some or all of the above problems are overcome by a display device having a power supply, including pixels arranged in a matrix form, wherein each pixel comprises the features of claim 1.

[0006] It is also possible for the current driven light-emitting element to be an organic EL element.

[0007] It is also possible for the driver to be capable of

varying the time that the reset transistor is turned on with the selection transistor and the emission control transistors in an off state.

[0008] It is also possible for the driver to turn the emission control transistor on in a state where the selection transistor and the reset transistor are turned off, and after that turn the reset transistor on with the selection transistor and the emission control transistor turned off.

[0009] It is also possible for the driver to write a compensation voltage to the coupling capacitor in a state where the same gradation signal is supplied to all pixels, then turn off the selection transistor, turn on the emission control transistor and the reset transistor, and write a voltage corresponding to voltage lowering of the driving transistor to the coupling capacitor, and after that perform equalization processing for the current characteristics of the driving transistor by causing current to flow in the drive transistor based on a voltage at the coupling capacitor.

[0010] Since it is possible to carry out correction based on mobility of the driving transistor, high brightness uniformity can be ensured even in the event that there are variations in mobility between driving transistors of each pixel.

BRIEF DESCRIPTION OF THE DRAWINGS

[0011]

FIG 1 is a drawing showing the structure of one example of a pixel circuit of the present invention;

FIG 2 is a timing chart showing an example of states of each line;

FIG 3 is a drawing showing variation in I-V curve accompanying differences in mobility of a driving transistor,

FIGS 4 is a timing chart showing another example of states of each line;

FIG. 5 is a timing chart showing a further example of states of each line;

FIG. 6 is a drawing showing another example structure for a pixel circuit;

FIG 7 is a drawing showing yet another example structure for a pixel circuit; and

FIG. 8 is a drawing showing the overall structure of a display device.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0012] Embodiments of the present invention will be described in the following based on the drawings.

[0013] The circuit structure for a pixel of this embodiment is shown in FIG. 1. In a pixel 14, an organic EL element 1 has a cathode connected to a cathode electrode 13 common to all pixels (for supplying a specified low voltage VSS), and an anode connected to a drain terminal of a light emission control transistor 5 having a gate terminal connected to a light emission control line

12. A source terminal of the light emission control transistor 5 is connected to a drain terminal of a driving transistor 2 having a source connected to a power supply line 9 common to all pixels (for supplying a specified high voltage VDD). A source terminal of a reset transistor 4 having a gate terminal connected to a reset line 11 is connected to a point of connection between the light emission control transistor 5 and the driving transistor 2. Also, a drain terminal of the reset transistor 4 is connected to one end of a coupling capacitor 6 having its other end connected to a data line 8, and to a drain terminal of a selection transistor 3 having its gate terminal connected to a selection line 10. The source terminal of the selection transistor 3 is connected to a gate terminal of the driving transistor 2 and to one end of a storage capacitor 7 that has its other end connected to the power supply line 9.

[0014] Here, a coupling capacitor 6 has a capacitance value C_c , and the storage capacitor 7 has a capacitance value C_s . It is preferable, in preventing reduction in dynamic range of a gradation signal voltage V_{sig} supplied to the data line 8, to make the capacitance value C_c of the coupling capacitor large compared to the capacitance value C_s of the storage capacitor. With this embodiment, by forming the coupling capacitor 6 crossing the data line 8 its capacitance C_c is sufficiently ensured.

[0015] A control method for compensating V_{th} and mobility of the driving transistor 2 using the pixel 14 of FIG. 1 is shown in FIG. 2. As shown in FIG. 2, one horizontal period is divided into a reset period (1), a first data write period (2), a current supply period (3), a mobility compensation period (4), and a second data write period (5).

[0016] In a horizontal period for selecting a line of pixels 14, the selection line 10 is made Low to select the line of pixels. Here, in the reset period (1) in the first half of this horizontal period, the reset line 11 is made Low, the selection transistor 3 and the reset transistor 4 are turned on, and the drive transistor 2 is diode connected to enable current to temporarily flow in the organic EL element 1. After that, because the light emission control line 12 is made High and the light emission control transistor 5 is turned off, the current that was flowing in the organic EL element 1 is made to flow via the reset transistor 4 to the coupling capacitor 6 and storage capacitor 7. While this is happening the same power supply potential VDD as on the power supply line 9 is supplied to the data line 8, and so by the time a certain length of time has elapsed and current no longer flows, V_{th} is held at the coupling capacitor 6 and the storage capacitor 7. The reset transistor 4 is turned off by setting the reset line 11 High at this time, and the potential held at the coupling capacitor 6 and the storage capacitor 7 is settled, and the reset period (1) is completed.

[0017] After that, a transition is made to the first write period (2), and if the gradation signal potential V_{sig} is supplied to the data line 8, the gate source potential V_{gs} of the driving transistor 2 is controlled to $V_{gs} = \{C_c / (C_c + C_s)\} * V_{sig} + V_{th}$ with coupling by the coupling capacitor, and the gradation signal potential V_{sig} with V_{th} of

the driving transistor 2 corrected is written. Next, by making the selection line 10 High, that potential is written to the storage capacitor 7 (above described V_{gs} is retained), and the first data write period (2) is completed. However, the previously described reset period does not have to continue until there is substantially no current flow in the driving transistor 2, and can be a length of time such as a few μs to a few tens of μs .

[0018] The capacitance C_c of the coupling capacitor 6 is sufficiently larger than the capacitance C_s of the storage capacitor 7, which shows that $C_c / (C_c + C_s)$ is substantially equal to 1, and the dynamic range of the gradation signal potential V_{sig} is maintained.

[0019] If the reset period (1) and the first data write period (2) are complete, specifically, if V_{th} is compensated and the gradation signal potential V_{sig} has been written, there is a transition to the current supply period (3), where the light emission control line 12 is made Low and the light emission control transistor 5 is turned on. Therefore, drive current corresponding to the written gradation signal potential V_{sig} flows via the light emission control transistor 5 into the organic EL element 1. With the lapse of a comparatively short current supply period (3) the light emission control line 12 is made High, current flow is interrupted, and the current supply period (3) is completed.

[0020] Next, there is a transition to the mobility compensation period (4), where the reset line is made Low, and current that was flowing in the organic EL element 1 (mobility compensation current) flows via the reset transistor 4 to the coupling capacitor 6. At this time, a gradation signal potential being supplied to the data line 8 stays at V_{sig} .

[0021] At this time, if mobility of the driving transistor 2 is high, mobility compensation current is large, that is, the drain potential of the driving transistor 2 is increased, which shows that a higher potential is written to the coupling transistor 6, while in the case of low mobility the mobility compensation current is small and the drain potential of the driving transistor 2 is lowered, which shows that a lower potential is written.

[0022] If the reset line 11 is made High, the mobility compensation period (4) is completed, and a potential that has been compensated according to mobility difference is settled at the coupling capacitor 6.

[0023] After that, there is a transition to the second data write period (5), and if the selection line 10 is made Low and the second write period commences, the correction signal potential written to the coupling capacitor 6 is reflected at the gate terminal of the driving transistor 2, and by making the selection line 10 High a mobility corrected potential is written to the storage capacitor 7. The selection line 10 is then made High and the light emission control line 12 made Low, to complete the second data write period (5).

[0024] In this manner, in a single horizontal period where a line of pixels 14 are selected, data write to each pixel of that line is completed. Light emission is then car-

ried out according to the compensated potential written to the storage capacitor 7 at this time, until writing is carried out in the next frame. Accordingly display is carried out using a signal with V_{th} and mobility compensated.

[0025] If control is carried out in this way, the mobility compensation potential V_u is represented as $V_u = I_{ds} \cdot \Delta t / C_c$, using a rather short mobility compensation period Δt , and is proportional to drive current I_{ds} and compensation period Δt . Also, using mobility μ , gate capacitance per unit area C_{ox} , and transistor size W, L , drive current I_{ds} is expressed as $I_{ds} = 0.5 \cdot \mu \cdot C_{ox} \cdot (W/L) \cdot V_{sig}^2$ (provided V_{th} is compensated and C_c is sufficiently larger than C_s), and since it is proportional to mobility μ , the mobility compensation potential V_u is dependent on mobility μ , compensation period Δt and V_{sig} . Accordingly, after completion of the second write period the signal potential becomes $V_{gs} = \{C_c / (C_c + C_s)\} \cdot V_{sig} + V_{th} - I_{ds} \cdot \Delta t / C_c$, and an offset potential V_u corresponding to mobility and the gradation signal potential is subtracted from a potential with V_{th} compensated.

[0026] The effect of this type of mobility compensation will be described using FIG. 3. FIG. 3 shows I-V curves for a driving transistor a and a driving transistor b with V_{th} compensated. If mobility differs, a difference in the inclination of the I-V curve arises between the transistors, and current flowing in the organic EL element 1 is different even if the same signal potential V_{sig} is applied. For example, even if V_{sig1} is written to a pixel after V_{th} compensation, the transistor a and the transistor b with different mobility output respectively different drive currents of $I_a(V_{sig1})$ and $I_b(V_{sig1})$ to the organic EL element 1.

[0027] If the mobility compensation of this embodiment is adopted, a mobility compensated potential V_u corresponding to drive current I_{ds} is subtracted from a potential across a gate and source with V_{th} compensated, which indicates that it is possible to make the drive current uniform. For example, if V_{sig1} is written after compensation of V_{th} , with the transistor a current $I_a(V_{sig1})$ flows in the mobility compensation period, and with the transistor b current $I_b(V_{sig1})$ flows in the mobility compensation period, and these currents flow into the respective coupling capacitors 6 via the reset transistor 4. As shown in FIG. 3, driving transistor b with a more upright I-V curve has greater current mobility compensation current than transistor a, and mobility compensation potential V_u is larger. Specifically, since $V_u(I_b(V_{sig1})) > V_u(I_a(V_{sig1}))$, driving transistor b has a smaller gate source potential, and output current is constrained. As a result, after completion of mobility compensation, if a signal is again written to the storage capacitor 7 in the second write period the drive current output to the organic EL elements is substantially $I(V_{sig1})$, and differences in output current due to mobility of the driving transistors a and b are made uniform.

[0028] Even in the case of writing V_{sig2} that generates a smaller driving current, mobility compensation is carried out on the same principle and made uniform. In the case of writing V_{sig1} since the current $I(V_{sig1})$ that has

been made uniform flows in the driving transistors a and b, a potential difference of $\Delta V_{u1} = V_u(I_b(V_{sig1})) - V_u(I_a(V_{sig1}))$ is necessary, but in the case of V_{sig2} , this potential difference $\Delta V_{u2} = V_u(I_b(V_{sig2})) - V_u(I_a(V_{sig2}))$ is required to be smaller than ΔV_{u1} . It is therefore necessary to adjust the potential difference ΔV_u after compensation depending on the gradation signal potential V_{sig} , but with mobility compensation of the present invention, since mobility compensation potential V_u is automatically adjusted according to drive current I_{ds} , namely V_{sig} , appropriate mobility compensation is carried out at all gradations.

[0029] Also, with the mobility compensation of this embodiment it is possible to vary the mobility compensation period Δt by either changing a pulse width input to the reset line 11 or inputting pulses a plurality of times etc., and it is possible to easily adjust the mobility compensation potential V_u . For example, by setting the mobility compensation period Δt long in the case of a panel with large variation in mobility, and setting the mobility compensation period Δt short with a panel having only slight variation in mobility, it is possible to avoid the drawbacks of insufficient or excessive compensation. Specifically, it is possible to realize an effective compensation amount for each panel by adjusting the mobility compensation period Δt . For example, it is possible to provide a register for setting Δt in a data driver and select driver, that will be described later, to write an externally supplied setting value for Δt in this register, and to carry out control in accordance with a value for Δt written to the register by the select driver at the time of mobility compensation.

[0030] Another mobility compensation method using the pixels 14 of FIG. 1 is shown in FIG. 4. The power supply period (3) is omitted from FIG. 4. Specifically, once the gradation signal potential V_{sig} is written after V_{th} compensation, by making the reset line 11 Low with the light emission control line 12 still High, the mobility compensation current I_{ds} is charged from the driving transistor 2 to the coupling capacitor 6.

[0031] The reason this type of control becomes possible is that immediately after making the reset line 11 Low, one terminal of the coupling capacitor 6 and the drain terminal of the driving transistor 2 are connected via the reset transistor 4, but the drain terminal of the driving transistor 2 is at substantially the same potential as the gate terminal, which indicates that the driving transistor is operated in the saturation region, and a mobility compensation current according to a difference in mobility flows. Accordingly, the mobility compensation potential V_u is represented as $V_u = I_{ds} \cdot \Delta t / C_c$, and mobility compensation according to gradation is realized. As the current supply period (3) can be omitted in this way, control is simplified and it is possible to efficiently utilize the horizontal period. For example, the second write period can be sufficiently ensured, and the horizontal period can be shortened, and image signal writing can be simplified even if there are a lot of lines.

[0032] Further, by using control such as that in FIG. 5

using the pixels 14, it becomes possible to make variations in brightness accompanying degradation of the organic EL elements uniform. In FIG. 5, a drive voltage readout period (6) and a third write period (7) have been added to the horizontal period of FIG. 4.

[0033] First, V_{th} is compensated in the reset period, and after writing the gradation signal V_{sig} in the first write period mobility is compensated, and the description up to this point is the same as previously. At the time of this processing to make deterioration of the organic EL elements uniform, the same gradation pixel is supplied to all pixels.

[0034] In FIG 5, after the second write period (5) there is a transition to the drive voltage readout period (6). The light emission control line 12 is made Low, and the organic EL element 1 temporarily emits light. At this time, current flowing in the organic EL element 1 is constant for each pixel, due to compensation of V_{th} and mobility of the driving transistor 2.

[0035] If the reset line 11 is set Low after waiting for the lapse of a specified time, the anode potential of the organic EL element 1 is written to one end of the coupling capacitor 6. While this is taking place, the other end of the coupling capacitor 6 is fixed at V_{sig} or another arbitrary potential. In this way, it is possible to read out an anode potential of the organic EL element at the time a fixed current flows, to the coupling capacitor 6.

[0036] The drive potential rises with elapse of time if the flow of current continues in the organic EL element. Specifically, if the same current flows in a deteriorated organic EL element, the drive voltage increases. The potential read out to the coupling capacitor 6 in the drive voltage readout period reflects the extent of deterioration of the organic EL element, and a higher voltage is read out for organic EL elements that suffer greater deterioration.

[0037] After that, if the reset line 11 is set High and the drive voltage readout period is completed, the selection line 10 is set low to commence the third write period (7), and the read out drive potential is reflected on the gate terminal of the drive transistor 2. At this time, V_{test} is applied to the data line 8 in order to adjust the equalizing processing current, and an equalizing potential written to the storage capacitor 7 is adjusted using this adjustment potential V_{test} to control current for the equalization processing.

[0038] If the selection line 10 is set High and the equalizing potential is written to the storage capacitor 7, a current corresponding to the equalizing potential flows in the organic EL element 1.

[0039] In pixels that have significant deterioration of the organic EL element, since a high drive potential is read out the potential V_{gs} across the gate and source of the driving transistor 2 becomes smaller, and equalizing current becomes smaller, but in pixels with only slight deterioration a low drive voltage is read out, and so the potential V_{gs} across the gate and source becomes larger and the equalizing current is increased. During equaliza-

tion processing, a smaller current flows in those pixels with greater deterioration, while a larger current flows in those pixels with slight deterioration. Specifically, since pixels with only slight deterioration deteriorate rapidly, if the equalization process continues deterioration will become uniform across pixels. This equalization process can be carried out during non-use periods of the display. It is also possible for this equalization process to be carried out with a refresh rate of 60 Hz, the same as normal display, or to be carried out at a refresh rate that is different from that of normal display, such as a lower frequency of 30 Hz, for example. In this way a single horizontal period becomes longer, and it is made possible to sufficiently ensure the V_{th} compensation time and the deterioration potential readout time.

[0040] The pixel 14 of this embodiment uses P-type transistors for all transistors, but it is also possible to use N-type transistors in some sections, or to use all N-type transistors.

[0041] FIG 6 is one example of the pixel 14 constructed with N-type transistors, and is controlled on the basis of FIG. 2 and FIG 4. First, in the reset period an arbitrary potential, for example, a cathode potential V_{SS} , is supplied to the data line 8, the selection line 10 is made high and the reset line 11 is made high, and the selection transistor 3 and the reset transistor 4 are turned on, and by diode connecting the driving transistor 2 current temporarily flows in the organic EL element 1. Then, the light emission control line 12 that was High is made Low, and the light emission control transistor 5 is turned off to write V_{th} of the driving transistor 2 to the coupling capacitor 6 and the storage capacitor 7. In the case of the pixel 14 of FIG 6, the potential written to the coupling capacitor 6 and the storage capacitor 7 is not strictly speaking V_{th} of the driving transistor 2, but can be considered to reflect substantially V_{th} . Next, if the reset line 11 is set Low to turn the reset transistor 4 off and there is a transition to the first write period, a signal potential V_{sig} is supplied to the data line 8, and a signal potential V_{sig} with V_{th} compensated is written to the storage capacitor 7. After that, the selection line 10 is set Low, and if the reset line 11 is set High and the reset transistor 4 is turned on in order to carry out mobility compensation a current corresponding to the gradation signal V_{sig} flows from the driving transistor 2 operated in the saturation region through the reset transistor 4 to discharge the coupling capacitor 6. The discharge amount is dependent on the mobility of the driving transistor 2, and so a potential having the mobility compensated is generated at the coupling capacitor. If the reset line 11 is set Low, the reset transistor turned off and the selection line 10 again set High, the select transistor 3 is turned on and the gradation potential with mobility compensated is written to the storage capacitor 7 and that potential is held by setting the select line to Low. Following that, by setting the light emission control line 5 High, a current with V_{th} and mobility compensated flows in the organic EL element 1, and the organic EL element emits light. That is, the mobility com-

pensation of the present invention also acts efficiently if N-type transistors are used.

[0042] However, since it is difficult to read out the drive potential of the organic EL element 1 with the pixel 14 of FIG. 6, in the case of using N-type transistors it is desirable to have the pixel structure of FIG 7.

[0043] FIG. 7 shows the pixel 14 with the anode of the organic EL element 1 made common. Therefore, VDD is supplied to the anode 13 while VSS is supplied to the power supply line 9. Control of the pixel 14 can use the same method as in FIG. 2 and FIG. 4, but the polarities of pulses input to the selection line 10, reset line 11 and emission control line 12 are reversed. In the reset period, while VSS is being supplied to the data line 8, the selection line 10 and reset line 11 are made High, and the selection transistor 3 and the reset transistor 4 are turned on to diode connect the driving transistor 2. At this time current temporarily flows in the organic EL element 1, but by making the light emission control line 12 Low and turning the light emission control transistor 5 off, V_{th} of the driving transistor 2 is written to the coupling capacitor 6 and the storage capacitor 7. Continuing on, in the first write period the select line is made High to keep the select transistor 3 turned on, the reset line 11 is made Low to turn the reset transistor 4 off, and the gradation signal V_{sig} supplied to the data line 8 is written to the storage capacitor 7, before a transition to the mobility compensation period. In the mobility compensation period the reset line 11 is made High to turn the reset transistor 4 on, and mobility compensation current I_{ds} flows from the driving transistor 2, that is operated in the saturation region, to the coupling capacitor 6, and a potential corresponding to mobility and the gradation signal potential V_{sig} is generated. By turning the reset transistor 4 off, this compensation potential is held at the coupling capacitor 6, and in the second write period if the selection line 10 is again set High to turn the selection transistor 3 on then the compensation potential held at the coupling capacitor 6 is written to the storage capacitor 7. If the select transistor 3 is turned off and the light emission control transistor 5 is turned on, current flows in the organic EL element 1.

[0044] In the case of making deterioration in the organic EL elements uniform, with the control method shown in FIG 5 the previously described V_{th} and mobility compensation are carried out, and it is possible to write a drive voltage of the organic EL element 1 with flow of equalized current in the organic EL element 1, into the coupling capacitor 6. Specifically, by making the reset line 11 High and turning the reset transistor 4 on, the drive potential is written to the coupling capacitor 6. Since the drive voltage is large for a severely deteriorate organic EL element, the cathode potential is low, while for a slightly deteriorated organic EL element the drive voltage is low and so the cathode potential is high. If the reset line 11 is set Low and the reset transistor 4 is turned off, this drive potential is temporarily held at the coupling capacitor 6, and if the selection line 10 is again made

High to turn the selection transistor 3 on, this read out drive potential is then reflected at the gate terminal of the driving transistor 2. That is, in the case of a lot of deterioration, the potential V_{gs} across the gate and source of the driving transistor 2 is small, and equalizing current becomes small, while in the case of only slight deterioration the potential V_{gs} across the gate and source of the driving transistor is large and equalizing current becomes large. If the selection line 10 is made Low and the selection transistor 3 is turned off, equalizing current flows in the organic EL element 1 until the next selection of the selection line 10.

[0045] During equalization processing, a smaller current is supplied to those pixels with greater deterioration, while a larger current is supplied to those pixels with slight deterioration, thus facilitating equalization. Similarly to FIG 5, the equalization current can be adjusted using V_{test} supplied to the data line 8. When it is desired to perform equalization more rapidly, it is preferable to increase equalization current by adjusting V_{test} , and in the case where it is desirable for display of equalization processing to not be noticeable it is preferable to perform equalization processing with a low current.

[0046] In this manner, even in the case where the pixels 14 are constructed using N-type transistors, it is possible for the V_{th} and mobility compensation of FIG 2 and FIG. 4, and the equalization processing for deterioration of the organic EL element, to be carried out in the same way as for the case where the pixels 14 are constructed of P-type transistors. Also, with the above described example, for P-type or N-type, fixed potentials of VDD and VSS are supplied to the data line 8 in the reset period, and then V_{th} is compensated with V_{sig} supplied in the first write period, but it is also possible to reverse this. That is, it is possible to supply V_{sig} onto the data line 8 in the reset period, and supply a fixed potential constituting V_{ref} in the first write period. If this is done, control is carried out so as to write a difference between V_{sig} and V_{th} to the coupling capacitor 6 in the reset period, and commence flow of current to the driving transistor 2 when the potential of the data line 8 becomes V_{sig} . Accordingly, if V_{ref} is written in the first write period, a difference between V_{ref} and V_{sig} is reflected at the gate of the driving transistor 2, and added to V_{th} , and so V_{th} is compensated. Next, in the mobility compensation period, the selection transistor 3 and the light emission control transistor 5 are kept off, and the reset transistor 4 is turned on, to write a difference in mobility to the coupling capacitor 6 as a potential difference. In the second write period, this potential is written to the storage capacitor 7 to carry out mobility compensation. In this way, mobility compensation of this embodiment is utilized efficiently, even if the V_{th} compensation method is different.

[0047] FIG. 8 shows the overall structure of an organic EL display 100 formed from an array of the pixels 14 of the present invention. The organic EL display 100 includes a pixel array 15 having pixels 14 arranged in an array on a glass substrate or plastic substrate etc., a data

driver 16 for driving data lines 8, and a selection driver 17 for driving select lines 10, reset line 11, and emission control lines 12. However, power supply lines 8 and cathode electrodes 13 that are common to all pixels are omitted from the drawing. In a pixel array 15, an example of full-color pixels is shown formed from R (red) G (green) and B (blue) sub-pixels, but it is also possible to have a structure where W (white) is added to give full-color pixels of RGBW.

[0048] The data driver 16 converts image data that has been transferred in dot units from an external section to line unit data using a shift register or the like, and outputs an analog signal potential in line units to the data line 8 by way of digital to analog conversion. In a reset period, in order to write V_{th} , VDD and VSS signal potentials are output, but in the write period a gradation signal potential V_{sig} is supplied. As a result of this V_{th} and mobility compensation are carried out in units of one line. The selection driver 17 has three outputs per one line, specifically output to drive the select lines 10, output to drive the reset lines 11, and output to drive the light emission control lines 12, but the respective lines are selectively driven to be made High or Low at the timing of FIG 4 and FIG. 5. The data driver 16 and the selection driver 17 can be formed from elements such as low temperature polysilicon on the same substrate as the pixels 14, or can be provided as driver ICs with the outputs of these ICs connected to each of the lines. From the structure of FIG 8, V_{th} compensation and mobility compensation, and also equalization of deterioration of the organic EL elements, is carried out efficiently in the pixels 14.

[0049] The structure of this embodiment can be used not only with organic EL elements, but with any other display device that uses current driven type light emitting elements.

PARTS LIST

[0050]

- | | | |
|---|-----------------------------------|----|
| 1 | organic EL element | 40 |
| 2 | driving transistor | |
| 3 | selection transistor | 45 |
| 4 | reset transistor | |
| 5 | light emission control transistor | 50 |
| 6 | coupling capacitor | |
| 7 | storage capacitor | |
| 8 | data line | 55 |
| 9 | power supply line | |

- | | |
|-------|--------------------|
| 10 | selection line |
| 11 | reset line |
| 5 12 | control line |
| 13 | cathode electrode |
| 14 | pixel |
| 10 15 | pixel array |
| 16 | data driver |
| 15 17 | selection driver |
| 100 | organic EL display |

20 Claims

1. A display device having a power supply, including pixels arranged in a matrix form, each pixel comprising:

a coupling capacitor (6) having one end connected to a data line (8);

a selection transistor (3) with two ends and a control terminal, having one end connected to the other end of the coupling capacitor (6), and configured to be switchable between ON and OFF states by a selection line (10) connected to its control terminal;

a driving transistor with two ends and a control terminal, having its control terminal connected to the other end of the selection transistor (3), and one end connected to the power supply;

a light emission control transistor (5) with two ends and a control terminal, having one end connected to the other end of the driving transistor (2), and configured to be turned ON and OFF by a light emission control line;

a current driven type light emitting element (1) connected to the other end of the light emission control transistor (5);

a storage capacitor (7) which connects the control terminal of the driving transistor (2) and the one end of the driving transistor (2) that is connected to the power supply side;

a reset transistor (4), with two ends and a control terminal, the two ends of said reset transistor being connected respectively to the other end of the driving transistor (2), on the side of the light emission control transistor, and to the other end the coupling capacitor (6) on the side of the selection transistor, which reset transistor configured to be turned ON and OFF by a reset line 11; and

a driver arranged to control the potential of each of said lines, by writing a data voltage, corresponding to a gradation signal supplied to the data line (8), to the storage capacitor (7) via the coupling capacitor (6), and to write a compensation voltage according to mobility of the driving transistor (2) to the coupling capacitor (6), said writing of the compensation voltage taking place while the selection transistor (3) and the light emission control transistor (5) are in an off state and the reset transistor (4) is turned on.

2. The display device of claim 1, wherein the current driven type light emitting elements (1) are organic EL elements.
3. The display device of claim 1, wherein the driver is capable of varying the time that the reset transistor (4) is turned on while the selection transistor (3) and the light emission control transistors (5) are in an off state.
4. The display device of claim 1, wherein the driver is configured to turn the light emission control transistor (5) on in a state where the selection transistor (3) and the reset transistor (4) are turned off, and after that turn the reset transistor (4) on with the selection transistor (3) and the light emission control transistor (5) turned off.
5. The display device of claim 1, wherein the driver is configured to write a correction voltage to the coupling capacitor (6) in a state where the same gradation signal is supplied to all pixels, then turn off the selection transistor (3), turn on the light emission control transistor (5) and the reset transistor (4), and write a voltage corresponding to voltage lowering of the driving transistor (2) to the coupling capacitor (6), and after that perform equalization processing of the current characteristics of the driving transistor (2) by causing current to flow in the driving transistor (2) based on a voltage at the coupling capacitor (6).

Patentansprüche

1. Anzeigevorrichtung mit einer Stromversorgung, die in einer Matrixform angeordnete Pixel aufweist, wobei jedes Pixel aufweist:

einen Koppelkondensator (6), wobei ein Ende mit einer Datenleitung (8) verbunden ist;
einen Auswahltransistor (3) mit zwei Enden und einem Steueranschluss, wobei ein Ende mit dem anderen Ende des Koppelkondensators (6) verbunden ist, und der dazu ausgebildet ist, durch eine mit dem Steueranschluss davon verbundene Auswahlleitung zwischen den Zustän-

den AN (ON) und AUS (OFF) schaltbar zu sein;
einen Treibertransistor (2) mit zwei Enden und einem Steueranschluss, wobei der Steueranschluss davon mit dem anderen Ende des Auswahltransistors (3) verbunden ist, und ein Ende mit der Stromversorgung verbunden ist;
einen Steuertransistor (5) der Lichtausstrahlung mit zwei Enden und einem Steueranschluss, wobei ein Ende mit dem anderen Ende des Treibertransistors (2) verbunden ist, und der dazu ausgebildet ist, über eine Steuerleitung der Lichtausstrahlung an- und ausgeschaltet zu werden;
ein Lichtausstrahlungselement (1) eines strombetriebenen Typs, das mit dem anderen Ende des Steuertransistors (5) der Lichtausstrahlung verbunden ist;
einen Speicherkondensator (7), der den Steueranschluss des Treibertransistors (2) und das eine Ende des Treibertransistors (2) verbindet, das mit der Stromversorgungsseite verbunden ist;
einen Reset-Transistor (4) mit zwei Enden und einem Steueranschluss, wobei die beiden Enden des Reset-Transistors jeweils mit dem anderen Ende des Treibertransistors (2), an der Seite des Steuertransistors der Lichtausstrahlung, und mit dem anderen Ende des Koppelkondensators (6), auf der Seite des Auswahltransistors, verbunden sind, wobei der Reset-Transistor dazu ausgebildet ist, durch eine Reset-Leitung (11) an- und ausgeschaltet zu werden; und
einen Treiber, der dazu ausgebildet ist, die Spannung einer jeden der Leitungen zu steuern, indem eine Datenspannung, die einem der Datenleitung (8) zugeführten Gradationssignal entspricht, in den Speicherkondensator (7) über den Koppelkondensator (6) geschrieben wird, und eine Kompensationsspannung gemäß der Mobilität des Treibertransistors (2) in den Koppelkondensator (6) zu schreiben, wobei das Schreiben der Kompensationsspannung stattfindet, während der Auswahltransistor (3) und der Steuertransistor (5) der Lichtabstrahlung sich in einem ausgeschalteten Zustand befinden und der Reset-Transistor (4) eingeschaltet ist.

2. Anzeigevorrichtung nach Anspruch 1, wobei die Lichtausstrahlungselemente (1) des stromgesteuerten Typs organische EL-Bauteile sind.
3. Anzeigevorrichtung nach Anspruch 1, wobei der Treiber in der Lage ist, die Zeit zu variieren, die der Reset-Transistor (4) angeschaltet ist, während der Auswahltransistor (3) und die Steuertransistoren (5) der Lichtausstrahlung sich in einem ausgeschalteten

Zustand befinden.

4. Anzeigevorrichtung nach Anspruch 1, wobei der Treiber dazu ausgebildet ist, den Steuertransistor (5) der Lichtausstrahlung in einem Zustand einzuschalten, in dem der Auswahltransistor (3) und der Reset-Transistor (4) ausgeschaltet sind, und danach den Reset-Transistor (4) anzuschalten, wobei der Auswahltransistor (3) und der Steuertransistor (5) der Lichtausstrahlung ausgeschaltet sind. 5 10
5. Anzeigevorrichtung nach Anspruch 1, wobei der Treiber dazu ausgebildet ist, eine Korrekturspannung in den Koppelkondensator (6) in einem Zustand zu schreiben, in dem allen Pixeln das gleiche Gradationssignal bereitgestellt wird, dann den Auswahltransistor (3) auszuschalten, den Steuertransistor (5) der Lichtausstrahlung und den Reset-Transistor (4) einzuschalten, und eine Spannung, die einer Spannungssenkung des Treibertransistors (2) entspricht, in den Koppelkondensator (6) zu schreiben, und danach eine Abgleichsverarbeitung der Stromeigenschaften des Treibertransistors (2) durchzuführen, indem das Fließen eines Stroms im Treibertransistor (2) basierend auf einer Spannung am Koppelkondensators (6) veranlasst wird. 15 20 25

Revendications

1. Dispositif d'affichage comportant une alimentation, comprenant des pixels disposés sous forme de matrice, chaque pixel comprenant :

un condensateur de couplage (6) comportant une extrémité connectée à une ligne de données (8) ;

un transistor de sélection (3) avec deux extrémités et un terminal de commande comportant une extrémité connectée à l'autre extrémité du condensateur de couplage (6), et configuré pour être commuté entre des états actif et inactif par une ligne de sélection (10) connectée à son terminal de commande ;

un transistor d'attaque (2) avec deux extrémités et un terminal de commande comportant son terminal de commande connecté à l'autre extrémité du transistor de sélection (3), et une extrémité connectée à l'alimentation ;

un transistor de commande d'émission de lumière (5) avec deux extrémités et un terminal de commande comportant une extrémité connectée à l'autre extrémité du transistor d'attaque (2), et configuré pour être activé et désactivé par une ligne de commande d'émission de lumière ; un élément d'émission de lumière du type attaqué par le courant (1) connecté à l'autre extrémité du transistor de commande d'émission de

lumière (5) ;

un condensateur de stockage (7) qui connecte le terminal de commande du transistor d'attaque (2) et l'une extrémité du transistor d'attaque (2) qui est connecté au côté alimentation ;

un transistor de réinitialisation (4) avec deux extrémités et un terminal de commande, les deux extrémités dudit transistor de réinitialisation étant connectées respectivement à l'autre extrémité du transistor d'attaque (2) sur l'autre côté du transistor de commande d'émission de lumière, et l'autre extrémité du condensateur de couplage (6) sur le côté du transistor de sélection, lequel transistor de réinitialisation est configuré pour être activé et désactivé par une ligne de réinitialisation (11) ; et

un circuit d'attaque prévu pour commander le potentiel de chacune desdites lignes, en écrivant une tension de données, correspondant à un signal gradation délivré vers la ligne de données (8), sur le condensateur de stockage (7) via le condensateur de couplage (6), et pour écrire une tension de compensation conformément à une mobilité du transistor d'attaque (2) sur le condensateur de couplage (6), ladite écriture de tension de compensation se produisant alors que le transistor de sélection (3) et le transistor de commande d'émission de lumière (5) se trouvent dans un état inactif et que le transistor de réinitialisation (4) est activé. 30

2. Dispositif d'affichage selon la revendication 1, dans lequel les éléments d'émission de lumière du type attaqués par le courant (1) sont des éléments électroluminescents organiques. 35

3. Dispositif d'affichage selon la revendication 1, dans lequel le circuit d'attaque est capable de varier le temps pendant lequel le transistor de réinitialisation (4) est activé alors que le transistor de sélection (3) et les transistors de commande d'émission de lumière (5) se trouvent dans un état inactif. 40

4. Dispositif d'affichage selon la revendication 1, dans lequel le circuit d'attaque est configuré pour activer le transistor de commande d'émission de lumière (5) dans un état dans lequel le transistor de sélection (3) et le transistor réinitialisation (4) sont désactivés, et après cela active le transistor de réinitialisation (4) avec le transistor de sélection (3) et le transistor de commande d'émission de lumière (5) désactivés. 45 50

5. Dispositif d'affichage selon la revendication 1, dans lequel le circuit d'attaque est configuré pour écrire une tension de correction sur le condensateur de couplage (6) dans un état dans lequel le même signal gradation est délivré vers tous les pixels, ensuite désactive le transistor de sélection (3), active le tran- 55

sistor de commande d'émission de lumière (5) et le transistor de réinitialisation (4), et écrit une tension correspondant à la baisse de tension du transistor d'attaque (2) sur le condensateur de couplage (6), et après cela réalise un traitement d'égalisation des caractéristiques de courant du transistor d'attaque (2) en amenant le courant à circuler dans le transistor d'attaque (2) sur la base d'une tension au niveau du condensateur de couplage (6).

10

15

20

25

30


35

40

45

50

55







FIG. 2

**FIG. 3**




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- WO 9848403 A [0002] [0003]
- US 20080048955 A1 [0004]

专利名称(译)	具有补偿像素晶体管移动性变化的显示装置		
公开(公告)号	EP2345023B1	公开(公告)日	2013-01-16
申请号	EP2009789397	申请日	2009-10-05
[标]申请(专利权)人(译)	全球OLED TECH		
申请(专利权)人(译)	全球OLED科技有限责任公司		
当前申请(专利权)人(译)	全球OLED科技有限责任公司		
[标]发明人	KAWABE KAZUYOSHI		
发明人	KAWABE, KAZUYOSHI		
IPC分类号	G09G3/32		
CPC分类号	G09G3/3233 G09G2300/0417 G09G2300/0819 G09G2300/0852 G09G2300/0861 G09G2320/0233		
优先权	2008267708 2008-10-16 JP		
其他公开文献	EP2345023A1		
外部链接	Espacenet		

摘要(译)

为了有效地执行驱动晶体管的阈值补偿，耦合电容器的一端连接到数据线。耦合电容器的另一端连接到选择晶体管和复位晶体管的一端。驱动晶体管的控制端子连接到选择晶体管的另一端，并且有机EL元件经由发光控制晶体管连接到该驱动晶体管。对应于提供给数据线的灰度信号的数据电压经由耦合电容器写入存储电容器，并且选择晶体管和发光控制晶体管处于截止状态并且复位晶体管导通，补偿对应于驱动晶体管的迁移率的电压被写入耦合电容器。

