



US 20070279342A1

(19) **United States**(12) **Patent Application Publication**
Park(10) **Pub. No.: US 2007/0279342 A1**(43) **Pub. Date: Dec. 6, 2007**(54) **DRIVING CIRCUIT AND ORGANIC
ELECTROLUMINESCENCE DISPLAY
THEREOF****Publication Classification**(51) **Int. Cl.**
G09G 3/30 (2006.01)(52) **U.S. Cl.** **345/77**(57) **ABSTRACT**(75) **Inventor:** **Yong Sung Park, Seoul (KR)**

Correspondence Address:

STEIN, MCEWEN & BUI, LLP
1400 EYE STREET, NW, SUITE 300
WASHINGTON, DC 20005(73) **Assignee:** **Samsung SDI Co., Ltd., Suwon-si (KR)**(21) **Appl. No.:** **11/647,336**(22) **Filed:** **Dec. 29, 2006**(30) **Foreign Application Priority Data**

Jun. 5, 2006 (KR) KR10-2006-0050483

An organic electroluminescence display capable of reducing a size of a data driving unit by decreasing an area of a D/A converter, and a driving circuit thereof. The data driving unit includes a first decoder to generate a first selection signal to correspond to a data signal; a first switch unit to receive first voltages and second voltages and to select one of the first voltages or the second voltages to correspond to the data signal; a second switch unit to select first and second reference voltages from the selected first or second voltages in response to the first selection signal; a second decoder to generate a second selection signal to correspond to the data signal; and a grey level voltage generating unit to receive and distribute the first and second reference voltages, selected by the switch units, to generate grey level voltages and to select and output one grey level voltage to correspond to the second selection signal.




FIG. 1
(PRIOR ART)




FIG. 2
(PRIOR ART)




FIG. 3




FIG. 4





FIG. 5



DRIVING CIRCUIT AND ORGANIC ELECTROLUMINESCENCE DISPLAY THEREOF

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application claims the benefit of Korean Patent Application No. 2006-50483, filed on Jun. 5, 2006, in the Korean Intellectual Property Office, the disclosure of which is incorporated herein by reference.

BACKGROUND OF THE INVENTION

[0002] 1. Field of the Invention

[0003] Aspects of the present invention relate to a driving circuit and an organic electroluminescence display using the same, more specifically to a driving circuit capable of decreasing a grey level error to improve linearity by preventing a voltage sag generated in an analog switch, and an organic electroluminescence display using the same.

[0004] 2. Description of the Related Art

[0005] A flat panel display has a plurality of pixels arranged in a matrix type pattern on a substrate as a display area, and a scan line and a data line connected to each pixel to display an image by selectively applying a data signal to the pixels. The flat panel displays are classified into passive matrix-type light-emitting displays and active matrix-type light-emitting displays according to a driving mode of respective pixels. The active matrix-type light-emitting displays which turn on light by individual pixels has been mainly used in terms of a high resolution, good contrast and fast operating speed.

[0006] Active matrix flat panel displays have been used as displays in such applications as personal computers, portable phones, PDAs, etc., or as monitors of various information appliances. Active matrix flat panel displays have been fabricated of liquid crystal displays (LCDs) using a liquid crystal panel, organic electroluminescence displays using organic electroluminescence devices, plasma display panels (PDPs) using plasma panels, etc. as have been known in the art. Recently, various light-emitting displays having a smaller weight and volume than a cathode ray tube have been developed, and attention has been particularly paid to the organic electroluminescence display which exhibits excellent luminous efficiency, luminance and viewing angle and has a rapid response time.

[0007] FIG. 1 is a circuit view showing a configuration of a conventional organic electroluminescence display 10. Referring to FIG. 1, the organic electroluminescence display 10 includes a pixel unit 100, a data driving unit 200 and a scan driving unit 300. The pixel unit 100 includes a plurality of data lines (D1, D2 . . . Dm-1, Dm) and a plurality of scan lines (S1, S2 . . . Sn-1, Sn), and a plurality of pixels formed in a region defined in a plurality of the data lines (D1, D2 . . . Dm-1, Dm) and a plurality of the scan lines (S1, S2 . . . Sn-1, Sn). The pixel 101 includes a pixel circuit and an organic electroluminescence device, and the pixel 101 generates a pixel current in the pixel circuit to flow to the organic electroluminescence device, the pixel current flows in the pixels according to data signals transmitted through a plurality of the data lines (D1, D2 . . . Dm-1, Dm) and scan signals transmitted through a plurality of the scan lines (S1, S2 . . . Sn-1, Sn).

[0008] The data driving unit 200 is connected with a plurality of the data lines (D1, D2 . . . Dm-1, Dm), and generates data signals to sequentially transmit a row of data signals to a plurality of the data lines (D1, D2 . . . Dm-1, Dm). The data driving unit 200 also has a digital-to-analog (D/A) converter, and generates a grey level voltage which is converted from a digital signal into an analog signal by the D/A converter, thereby to transmit the grey level voltage to the data lines (D1, D2 . . . Dm-1, Dm).

[0009] The scan driving unit 300 is connected to a plurality of scan lines (S1, S2 . . . Sn-1, Sn), and generates a scan signal to transmit the scan signal to a plurality of the scan lines (S1, S2 . . . Sn-1, Sn). A certain row is selected by the scan signals, and a data signal is transmitted to a pixel 101 arranged in the selected row, such that a current corresponding to the data signal is generated in the pixel.

[0010] FIG. 2 is a circuit view showing a resistance unit which generates a grey level voltage in the D/A converter used in the data driving unit 200 of the organic electroluminescence display 10 as shown in FIG. 1. Referring to FIG. 2, assume that the resistance unit generates 8 grey level voltages for illustration. In order to generate 8 grey level voltages, 8 resistances (R1, R2, . . . R8) are connected in series, and a first reference voltage having a high voltage (VrefH) and a second reference voltage having a low voltage (VrefL) are respectively transmitted to both ends of the resistances connected in series, and then the first reference voltage (VrefH) and the second reference voltage (VrefL) become a grey level voltage distributed by the 8 resistances.

[0011] The organic electroluminescence display 10 as configured above is preferably realized by preparing a small size of a driving circuit to manufacture a small size of the organic electroluminescence display 10.

SUMMARY OF THE INVENTION

[0012] Accordingly, aspects of the present invention are designed to solve such drawbacks of the prior art and/or realize additional advantages, and therefore an aspect of the present invention is to provide a driving circuit capable of reducing a size of a data driving unit by decreasing an area of a D/A converter, and an organic electroluminescence display using the same.

[0013] Aspects of the present invention provide an organic electroluminescence display including a pixel unit, a data driving unit and a scan driving unit, wherein the data driving unit includes a first decoder to generate a first selection signal to correspond to a data signal; a first switch unit to receive a plurality of first voltages from a first bus and a plurality of second voltages from a second bus and to select the first voltages or the second voltages to correspond to the data signal; a second switch unit to select a first reference voltage and a second reference voltage from the selected first voltages or the selected second voltages in response to the first selection signal and to transmit the selected first reference voltage and selected second reference voltage; a second decoder to generate a second selection signal to correspond to a data signal; and a grey level voltage generating unit to receive and distribute the first selected reference voltage and the second selected reference voltage, selected by the second switch unit, to generate a plurality of grey level voltages and to select and output one grey level voltage out of the plurality of the grey level voltages to correspond to the second selection signal.

[0014] Aspects of the present invention provide a driving circuit including a first decoder to generate a first selection signal to correspond to a data signal; a first switch unit to receive a plurality of first voltages from a first bus and a plurality of second voltages from a second bus and to select the first voltages or the second voltages to correspond to the data signal; a second switch unit to select a first reference voltage and a second reference voltage from the selected first voltages or the selected second voltages in response to the first selection signal; a second decoder to generate a second selection signal to correspond to a data signal; and a grey level voltage generating unit to receive and distribute the first reference voltage and the second reference voltage, selected by the second switch unit, to generate a plurality of grey level voltages and to select and output one grey level voltage out of the plurality of the grey level voltages to correspond to the second selection signal.

[0015] Further aspects of the present invention provide a method for driving an organic electroluminescence display, including selecting a plurality of first voltages or a plurality of second voltages to correspond to a data signal and selecting one plurality of voltages out of the plurality of the first voltages and the plurality of the second voltages; selecting a first reference voltage and a second reference voltage out of the selected first voltages or the selected second voltages to correspond to the data signal; distributing the first reference voltage and the second reference voltage using the lower bit of the data signal; generating a grey level voltage from the distributed first and second reference voltages; and transmitting the generated grey level voltage to a data line.

[0016] Additional aspects and/or advantages of the invention will be set forth in part in the description which follows and, in part, will be obvious from the description, or may be learned by practice of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0017] These and/or other aspects and advantages of the invention will become apparent and more readily appreciated from the following description of the preferred embodiments, taken in conjunction with the accompanying drawings of which:

[0018] FIG. 1 is a circuit view showing a configuration of a conventional organic electroluminescence display;

[0019] FIG. 2 is a circuit view showing a resistance unit which generates a grey level voltage in a conventional D/A converter;

[0020] FIG. 3 is a schematic view showing a data driving unit used in an organic electroluminescence display according to an embodiment of the present invention;

[0021] FIG. 4 is a schematic view showing a configuration of the D/A converter according to an embodiment of the present invention; and

[0022] FIG. 5 is a circuit view showing one example of a pixel used in an organic electroluminescence display according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE EMBODIMENTS

[0023] Reference will now be made in detail to the present embodiments of the present invention, examples of which are illustrated in the accompanying drawings, wherein like reference numerals refer to the like elements throughout.

The embodiments are described below in order to explain the present invention by referring to the figures.

[0024] Hereinafter, embodiments according to the present invention will be described with reference to the accompanying drawings. Here, when one element is connected to another element, one element may be not only directly connected to another element but also indirectly connected to another element via another element. Further, irrelative elements are omitted for clarity.

[0025] FIG. 3 is a circuit view showing a data driving unit used in an organic electroluminescence display according to an embodiment of the present invention. Referring to FIG. 3, the data driving unit 205 includes a shift register 210, a sampling latch 220, a holding latch 230, a level shifter 240, a D/A converter 250 and a buffer unit 260.

[0026] The shift register 210 comprises a plurality of flip flops, and the shift register 210 controls the sampling latch 220 to correspond to a clock signal (CLK) and a synchronizing signal (Hsync). The sampling latch 220 sequentially receives a row of data signals according to a control signal of the shift register 210, and then outputs the data signals in parallel. A mode for sequentially receiving a signal and outputting the signal in parallel is referred to as Serial-In-Parallel-Out (SIPO). The holding latch 230 receives the signal in parallel, and then outputs the signal in parallel. A mode for receiving a signal in parallel and outputting the signal in parallel is referred to as Parallel-In-Parallel Out (PIPO). The level shifter 240 changes a level of the signal, outputted from the holding latch 230, into an operating voltage of the system and transmits the operating voltage to the D/A converter 250. The D/A converter 250 transmits the signal, received as the digital signal, as an analog signal to select a corresponding grey level voltage and transmits the grey level voltage to the buffer unit 260, and the buffer unit 260 amplifies the grey level voltage, and then transmits the amplified grey level voltage to data lines.

[0027] FIG. 4 is a schematic view showing a configuration of the D/A converter according to an embodiment of the present invention. Referring to FIG. 4, the D/A converter 250 includes a first decoder 251, a first switch unit 252, a second switch unit 253, a second decoder 254 and a grey level voltage generating unit 255. Assume that the D/A converter 250 displays 256 grey levels, and the data signal transmitted to the D/A converter 250 comprises 8-bit signals.

[0028] In order to generate 256 grey levels from 8-bit signals, the first decoder 251 uses 3 bits, that is, all bits except an uppermost bit out of the upper 4 bits of the data signal to generate a first selection signal. The first switch unit 252 comprises 32 transistors, and odd-numbered transistors from a left to a right direction have respective sources connected to first bus lines (v11, v21 . . . v91), respective gates to receive the uppermost bit signal, and respective drains connected to the second switch unit 253. Even-numbered transistors have respective sources connected to second bus lines (v12, v22 . . . v92), respective gates to receive an accessory signal of the uppermost bit signal, and respective drains connected to the second switch unit 253. At this time, the first bus lines (v11, v21 . . . v91) and the second bus lines (v12, v22, . . . v92) transmit nine first voltages and nine second voltages, respectively, and one group of voltages out of the voltages transmitted through the first bus lines (v11, v21 . . . v91) and the voltages transmitted through the second bus lines (v12, v22 . . . v92) is transmitted to the

second switch unit **253** through the first switch unit **252** using the uppermost bit of the data signal. That is to say, the nine voltages, transmitted through the first bus lines (v11, v21 . . . v91) to correspond to the uppermost bit of the data signal, are sequentially transmitted to the second switch unit **253** through the odd-numbered transistors, and the nine voltages transmitted through the second bus lines (v12, v22 . . . v92) to correspond to the uppermost bit of the data signal, are sequentially transmitted through the even-numbered transistors, to the second switching unit **253**. The second bus lines (v12, v22 . . . v92) and the first switch unit **252** are connected in the same manner as in the first bus lines (v11, v21 . . . v91) and the first switch unit **252**. At this time, the first voltages are higher than the second voltages. The transistors connected to the first bus lines (v11, v21 . . . v91) and the transistors connected to the second bus lines (v12, v22 . . . v92) are operated by receiving the uppermost bit signal of the data signal, and the transistors connected to the first bus lines (v11, v21 . . . v91) and the transistors connected to the second bus lines (v12, v22 . . . v92) are operated in a reverse manner as follows. When the uppermost bit is set to 1, a grey level of the data signal is estimated to range from 128 to 256 grey levels, and therefore the odd-numbered transistors are in an ON state to select the first bus lines (v11, v21 . . . v91), and when the uppermost bit is set to 0, the grey level of the data signal is estimated to range from 0 to 127 grey levels, and therefore the even-numbered transistors are in an ON state to select the second bus lines (v12, v22 . . . v92). That is to say, one group of bus lines out of the first bus lines (v11, v21 . . . v91) and the second bus lines (v12, v22 . . . v92) is selected by the transistors. The odd-numbered transistors sequentially transmit the voltage to the second switch unit **253** in order from a highest voltage to a lower voltage, and the even-numbered transistors sequentially transmit the voltage to the second switch unit **253** in order from below the lower voltage to a lowest voltage.

[0029] The second switch unit **253** carries out a switching operation in response to the first selection signal generated in the first decoder **251**, and the 16 transistors selectively output the signals, transmitted from the first switch unit **252**, according to the first selection signal, and then transmit the signals to the grey level voltage generating unit **255**. At this time, two transistors of the second switch unit **253** are connected to one output terminal of the second decoder **254**, and the second switch unit **253** outputs two voltages from one group of bus lines, selected by the first switch unit **252**, out of the first bus lines (v11, v21 . . . v91) and the second bus lines (v12, v22 . . . v92) to select a first reference voltage and a second reference voltage. The first reference voltage is changed by the first selection signal, and the second reference voltage is reduced to the lowest voltage which is transmitted through the selected bus lines.

[0030] The second decoder **254** receives a lower 4 bits of the data signal to generate a 16-bit second selection signal. Sixteen resistances are connected in series in the grey level voltage generating unit **255**, and the first reference voltage and the second reference voltage, selected by the second switch unit **253**, are transmitted to respective ends of the grey level voltage generating unit **255**, and then 16 grey level voltages are generated by the 16 resistances. The grey level voltage generating unit **255** receives the second selection signal to select and output one grey level voltage out of the 16 grey level voltages. Accordingly, the total 256 grey

level voltages are generated by the uppermost bit of the data signal, the first selection signal and the second selection signal.

[0031] FIG. 5 is a circuit view showing one example of a pixel used in the organic electroluminescence display according to an embodiment of the present invention. Referring to FIG. 5, the pixel is connected to the data line (Dm), the scan line (Sn) and the pixel power line (ELVdd) and includes a first transistor (M1), a second transistor (M2), a capacitor (Cst) and an organic electroluminescence device (OLED).

[0032] The first transistor (M1) has a source connected to the pixel power line (ELVdd); a drain connected to an anode electrode of the organic electroluminescence device (OLED); and a gate connected to a first node (N1). The second transistor (M2) has a source connected to the data line (Dm); a drain connected to the first node (N1); and a gate connected to the scan line (Sn). The capacitor (Cst) is connected between the first node (N1) and the pixel power line (ELVdd) to maintain a voltage between the first node (N1) and the pixel power line (ELVdd) during a predetermined period. The organic electroluminescence device (OLED) includes the anode electrode, a cathode electrode and an emitting layer, wherein if the anode electrode is connected to a drain of the first transistor (M1) and the cathode electrode is connected to the low-potential power resource (ELVSS) so as to allow a current to flow from an anode electrode to a cathode electrode of the organic electroluminescence device (OLED) to correspond to the voltage which is applied to the gate of the first transistor (M1), then the light is emitted in the emitting layer and a brightness is adjusted to correspond to a capacity of the current.

[0033] According to the driving circuit according to aspects of the present invention and the organic electroluminescence display using the same, a size of the D/A converter may be decreased by selecting a reference voltage using an analog switch since the uppermost bit is connected to the analog switch.

[0034] Although a few embodiments of the present invention have been shown and described, it would be appreciated by those skilled in the art that changes may be made in this embodiment without departing from the principles and spirit of the invention, the scope of which is defined in the claims and their equivalents.

What is claimed is:

1. An organic electroluminescence display comprising:
 - a pixel unit comprising pixels to display an image;
 - a data driving unit to generate display signals in the pixels of the pixel unit; and
 - a scan driving unit to generate a current corresponding to the display signals in the pixels of the pixel unit,
 wherein the data driving unit comprises:
 - a first decoder to generate a first selection signal to correspond to a data signal;
 - a first switch unit to receive a plurality of first voltages from a first bus and a plurality of second voltages from a second bus and to select the first voltages or the second voltages to correspond to the data signal;
 - a second switch unit to select a first reference voltage and a second reference voltage from the selected first voltages or the selected second voltages in response to the first selection signal;
 - a second decoder to generate a second selection signal to correspond to the data signal; and

- a grey level voltage generating unit to receive and distribute the first reference voltage and the second reference voltage, selected by the second switch unit, to generate a plurality of grey level voltages and to select and output one grey level voltage out of the plurality of the grey level voltages to correspond to the second selection signal.
2. The organic electroluminescence display according to claim 1, wherein the data signal is classified into upper bits and lower bits, and the first bus or second bus is selected by the uppermost bit out of the upper bits and the remaining upper bits except the uppermost bit are transmitted to the first decoder to generate the first selection signal, and the lower bits are transmitted to the second decoder to generate the second selection signal.
 3. The organic electroluminescence display according to claim 2, wherein the first switch unit includes a first transistor to switch the plurality of first reference voltages to correspond to the uppermost bit of the data signal; and a second transistor to switch the plurality of second reference voltages to correspond to the uppermost bit of the data signal.
 4. The organic electroluminescence display according to claim 3, wherein the second switch unit includes a third transistor to transmit the first reference voltage or the second reference voltage, transmitted through the first or second transistor by the first selection signal, to the grey level voltage generating unit.
 5. The organic electroluminescence display according to claim 1, wherein the grey level voltage generating unit includes a resistor having a plurality of resistances connected in series; and switches respectively connected between the resistances to carry out a switching operation in response to the second selection signal.
 6. A driving circuit comprising:
 - a first decoder to generate a first selection signal to correspond to a data signal;
 - a first switch unit to receive a plurality of first voltages from a first bus and a plurality of second voltages from a second bus to select the first voltages or the second voltages to correspond to the data signal;
 - a second switch unit to select a plurality of first reference voltages and second reference voltages from the selected first voltages or the selected second voltages in response to the first selection signal;
 - a second decoder to generate a second selection signal to correspond to the data signal; and
 - a grey level voltage generating unit to receive and distribute the first reference voltages or the second reference voltages, selected by the second switch unit, to generate a plurality of grey level voltages and to select and output one grey level voltage out of the plurality of the grey level voltages to correspond to the second selection signal.
 7. The driving circuit according to claim 6, wherein the data signal is classified into upper bits and lower bits, and the first bus or second bus is selected by the uppermost bit out of the upper bits and the remaining upper bits except the uppermost bit are transmitted to the first decoder to generate the first selection signal, and the lower bits are transmitted to the second decoder to generate the second selection signal.
 8. The driving circuit according to claim 7, wherein the first switch unit includes a first transistor to switch the plurality of first reference voltages to correspond to the uppermost bit of the data signal; and a second transistor to switch the plurality of second reference voltages to correspond to the uppermost bit of the data signal.
 9. The driving circuit according to claim 8, wherein the second switch unit includes a third transistor to transmit the first reference voltage or the second reference voltage, transmitted through the first or second transistor by the first selection signal, to the grey level voltage generating unit.
 10. The driving circuit according to claim 6, wherein the grey level voltage generating unit includes a resistor having a plurality of resistances connected in series; and switches respectively connected between the resistances to carry out a switching operation in response to the second selection signal.
 11. A method for driving an organic electroluminescence display, comprising:
 - selecting a plurality of first voltages and a plurality of second voltages to correspond to a data signal and selecting one voltage out of the plurality of first voltages and the plurality of second voltages;
 - selecting a first reference voltage and a second reference voltage out of the selected first voltages or the selected second voltages;
 - distributing the first reference voltage and the second reference voltage using a lower bit of the data signal and generating a grey level voltage; and
 - transmitting the generated grey level voltage to a data line.
 12. The method for driving an organic electroluminescence display according to claim 11, further comprising: changing a voltage of the first reference voltage while not changing a voltage of the second reference voltage.
 13. A driving circuit comprising:
 - a first decoder to generate a first selection signal to correspond to a data signal;
 - a first switch unit to select first voltages or second voltages to correspond to the data signal;
 - a second switch unit to select a first reference voltage and a second reference voltage from the selected first voltages or the selected second voltages in response to the first selection signal;
 - a second decoder to generate a second selection signal to correspond to the data signal; and
 - a grey level voltage generating unit to receive and distribute the first reference voltage and the second reference voltage, to generate grey level voltages and to select and output one of the grey level voltages to correspond to the second selection signal.
 14. An organic electroluminescence display comprising:
 - a pixel unit comprising pixels to display an image;
 - a data driving unit to generate display signals in pixels of the pixel unit, wherein the data driving unit comprises the driving circuit of claim 13; and
 - a scanning unit to generate a current corresponding to the display signals in the pixels of the pixel unit.
 15. The organic electroluminescence display according to claim 14, further comprising:

a data line to transmit the grey level voltages to the pixels;
a scan line to transmit a scanning current to the pixels; and
a pixel power line to supply power to the pixels.

16. The organic electroluminescence display according to claim **15**, wherein each pixel further comprises:

an organic electroluminescence device comprising an anode electrode, a cathode electrode connected to a low potential power resource, and an emitting layer;

a first transistor comprising a source connected to the pixel power line, a drain connected to the anode electrode of the organic electroluminescence device, and a gate to receive the grey level voltage corresponding to the display signal, the first transistor to switch power to the anode electrode of the organic electroluminescence device;

a second transistor comprising a source connected to the data line, a drain connected to the gate of the first transistor, and a gate connected to the scan line, the second transistor to supply the grey level voltage to the gate of the first transistor corresponding to the display signal; and

a capacitor connected between the pixel power line and the gate of the first transistor to maintain a voltage during a predetermined period;

wherein, the organic electroluminescence device emits light according to a capacity of the current flowing through the first transistor.

17. A D/A converter comprising:

a first switch unit to select first voltages or second voltages to correspond to the uppermost bit of a data signal classified into upper bits and lower bits;

a first decoder to generate a first selection signal to correspond to upper bits of the data signal except the uppermost data bit;

a second switch unit to select a first reference voltage and a second reference voltage from the selected first voltages or the selected second voltages in response to the first selection signal;

a second decoder to generate a second selection signal to correspond to the lower bits of the data signal; and

a grey level voltage generating unit to receive and distribute the first reference voltage and the second reference voltage, to generate grey level voltages and to select and output one of the grey level voltages to correspond to the second selection signal.

18. An organic electroluminescence display comprising:

a pixel unit comprising pixels to display an image;

a data driving unit to generate display signals in pixels of the pixel unit, wherein the data driving unit comprises the D/A converter of claim **17**; and

a scanning unit to generate a current corresponding to the display signals in the pixels of the pixel unit.

* * * * *

专利名称(译)	驱动电路及其有机电致发光显示器		
公开(公告)号	US20070279342A1	公开(公告)日	2007-12-06
申请号	US11/647336	申请日	2006-12-29
申请(专利权)人(译)	三星SDI CO. , LTD.		
当前申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
[标]发明人	PARK YONG SUNG		
发明人	PARK, YONG SUNG		
IPC分类号	G09G3/30		
CPC分类号	H03M1/765 H03M1/682		
优先权	1020060050483 2006-06-05 KR		
其他公开文献	US8537090		
外部链接	Espacenet USPTO		

摘要(译)

一种能够通过减小D/A转换器的面积来减小数据驱动单元的尺寸的有机电致发光显示器及其驱动电路。数据驱动单元包括第一解码器，用于产生对应于数据信号的第一选择信号；第一开关单元，用于接收第一电压和第二电压，并选择第一电压或第二电压中的一个以对应于数据信号；第二开关单元，用于响应于第一选择信号从所选择的第一或第二电压中选择第一和第二参考电压；第二解码器，用于产生与数据信号对应的第二选择信号；灰度级电压产生单元，用于接收和分配由开关单元选择的第一和第二参考电压，以产生灰度级电压，并选择和输出一个灰度级电压，以对应于第二选择信号。

