

(10) **Patent No.:** US 9,390,648 B2
(45) **Date of Patent:** Jul. 12, 2016

U.S. PATENT DOCUMENTS

- | | | | | |
|--------------|------|--------|--------------|-------------------------|
| 8,692,821 | B2 * | 4/2014 | Park | G09G 3/3233
345/211 |
| 2005/0017934 | A1 | 1/2005 | Chung et al. | |
| 2008/0036371 | A1 * | 2/2008 | Kim | G09G 3/3233
313/504 |
| 2008/0211397 | A1 * | 9/2008 | Choi | G09G 3/3233
313/504 |
| 2012/0019504 | A1 | 1/2012 | Han et al. | |
| 2012/0038605 | A1 * | 2/2012 | Han | 345/211 |
| 2012/0038683 | A1 * | 2/2012 | Park | G09G 3/3233
345/690 |
| 2014/0168180 | A1 * | 6/2014 | Kim | H05B 33/0896
345/205 |

KR	10-2005-0005646	A	1/2005
KR	10-2012-0009669	A	2/2012
KR	10-2012-0015076	A	2/2012

Primary Examiner — Ilana Spar
Assistant Examiner — Mihir Rayan

(57) **ABSTRACT**

A pixel capable of realizing desired brightness and of displaying a uniform image is disclosed. In one aspect, the pixel includes an organic light emitting diode (OLED), a first transistor having a second electrode thereof coupled to an anode electrode of the OLED to control an amount of current supplied to the OLED in response to a voltage applied to a gate electrode thereof. The pixel also includes at least one second transistor coupled between the second electrode and the gate electrode of the first transistor, and a third transistor coupled between the second transistor and the gate electrode of the first transistor. The third transistor is turned off in a partial period of a period in which the second transistor is turned on.

(58) **Field of Classification Search**
CPC . G09G 3/3659; G09G 3/3233; G09G 3/3208;
G09G 2300/0819; G09G 2300/0861; G09G
2320/043; G09G 230/0842
See application file for complete search history.





FIG. 1







FIG. 4



PIXEL AND ORGANIC LIGHT EMITTING DISPLAY USING THE SAME

CROSS-REFERENCE TO RELATED APPLICATION

This application claims priority to and the benefit of Korean Patent Application No. 10-2012-0096306, filed on Aug. 31, 2012, in the Korean Intellectual Property Office, the entire content of which is incorporated herein by reference.

BACKGROUND

1. Field

The described technology generally relates to a pixel and an organic light emitting display using the same.

2. Description of the Related Technology

Recently, various flat panel displays (FPD) have been developed. The FPDs include liquid crystal displays (LCD), field emission displays (FED), plasma display panels (PDP), and organic light emitting diode (OLED) displays.

OLED displays display images using an OLED that generate light by re-combination of electrons and holes. OLED displays generally have high response speed and reduced power consumption.

SUMMARY

One inventive aspect is a pixel capable of realizing desired brightness and of displaying a uniform image and an organic light emitting display using the same.

Another aspect is a pixel, including an organic light emitting diode (OLED), a first transistor having a second electrode thereof coupled to an anode electrode of the OLED to control an amount of current supplied to the OLED to correspond to a voltage applied to a gate electrode thereof, at least one second transistor coupled between the second electrode and the gate electrode of the first transistor, and a third transistor coupled between the second transistor and the gate electrode of the first transistor. The third transistor is turned off in a partial period of a period in which the second transistor is turned on.

The third transistor may be turned on at timing when the second transistor may be turned on. The third transistor may be turned off before the second transistor is turned off. The third transistor may be turned on after the second transistor is turned off. The pixel further includes a fourth transistor coupled between a data line and the first electrode of the first transistor and simultaneously turned on and off with the second transistor, a fifth transistor coupled between the first electrode of the first transistor and a first power supply and turned off in a period where the second transistor is turned on, a sixth transistor coupled between the second electrode of the first transistor and the OLED and simultaneously turned on and off with the fifth transistor, a seventh transistor coupled between an initializing power supply and the gate electrode of the first transistor and turned on prior to the second transistor, and a storage capacitor coupled between the gate electrode of the first transistor and the first power supply.

Another aspect is an organic light emitting display, including a scan driver for driving scan lines and emission control lines, a data driver for driving data lines, and pixels positioned at intersections of the scan lines and the data lines. Each of the pixels positioned in an *i*th (*i* is a natural number) horizontal line includes an OLED, a first transistor having a second electrode thereof coupled to the OLED to control an amount of current supplied to the OLED to correspond to a voltage

applied to a gate electrode thereof, a second transistor coupled between the second electrode and the gate electrode of the first transistor and turned on when a scan signal is supplied to an *i*th scan line, and a third transistor coupled between the second transistor and the gate electrode of the first transistor, turned off when an emission control signal is supplied to an (*i*+2)th emission control line, and turned on in the other cases.

The scan driver supplies an emission control signal to an *i*th emission control line to overlap scan signals supplied to (*i*-1)th and *i*th scan lines. The scan driver supplies the emission control signal to the (*i*+2)th emission control line to overlap the scan signal supplied to the *i*th scan line in a partial period. The turn on period of the third transistor partially overlaps the turn on period of the second transistor to correspond to the emission control signal supplied to the (*i*+2)th emission control line. The third transistor is turned off before the second transistor is turned off. The third transistor is turned on after the second transistor is turned off.

Each of the pixels positioned in the *i*th horizontal line includes a fourth transistor that is coupled between the data line and the first electrode of the first transistor and whose gate electrode is coupled to the *i*th scan line, a fifth transistor that is coupled between the first electrode of the first transistor and a first power supply and whose gate electrode is coupled to the *i*th emission control line, a seventh transistor that is coupled between an initializing power supply and the gate electrode of the first transistor and whose gate electrode is coupled to the (*i*-1)th scan line, and a storage capacitor coupled between the gate electrode of the first transistor and the first power supply. The initializing power supply is set to have a lower voltage than the data signal supplied to the data line.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a view illustrating an organic light emitting display according to an embodiment.

FIG. 2 is a circuit diagram of the pixel of FIG. 1 according to one embodiment.

FIG. 3 illustrates driving waveforms supplied to the pixel of FIG. 2 according to one embodiment.

FIG. 4 is a circuit diagram of the pixel of FIG. 1 according to another embodiment.

DETAILED DESCRIPTION

An OLED display generally includes a plurality of pixels arranged at intersections of a plurality of data lines, scan lines, and power supply lines in a matrix. Each of the pixels commonly includes an OLED, at least two transistors including a driving transistor, and at least one capacitor.

The OLED display has an advantage of reduced power consumption, however, has a disadvantage in that an amount of current that flows to the OLEDs changes in accordance with deviation in the threshold voltages of the driving transistors included in the pixels, causing non-uniform display. That is, the characteristics of the driving transistors change in accordance with the manufacturing process variables of the driving transistors. Actually, it is not possible to manufacture an OLED display which has all of its transistors with the same current characteristics, which results in the deviation in the threshold voltages of the driving transistors.

There is a method of adding compensating circuits each formed of a plurality of transistors and a capacitor to the pixels, respectively. The compensating circuits couple the driving transistors in the form of diodes in a period where

scan signals are supplied to compensate for the deviation in the threshold voltages of the driving transistors. Here, in order to secure driving stability, a plurality of transistors are added between the gate electrode and the drain electrode of a driving transistor in order to couple the driving transistor in the form of a diode.

The transistors are generally turned off after a predetermined voltage is charged in the storage capacitor. Here, the voltage charged in the storage capacitor changes due to a kickback voltage generated when the transistors are turned off. In this case, the pixels do not display an image with desired brightness. In addition, when the characteristics of the transistors included in each of the pixels are different from each other, a non-uniform image is displayed on a panel.

Hereinafter, embodiments will be described with reference to the accompanying drawings. Here, when a first element is described as being coupled to a second element, the first element may be not only directly coupled to the second element but may also be indirectly coupled to the second element via a third element. Further, some of the elements that are not essential to the complete understanding of the present disclosure are omitted for clarity. Also, like reference numerals refer to like elements throughout.

Hereinafter, a pixel and an organic light emitting display using the same will be described in detail as follows with reference to FIGS. 1 to 4.

FIG. 1 is a view illustrating an organic light emitting display according to an embodiment.

Referring to FIG. 1, the organic light emitting display includes a pixel unit **130** including pixels **140** positioned at the intersections of scan lines **S1** to **Sn** and data lines **D1** to **Dm**, a scan driver **110** for driving the scan lines **S1** to **Sn** and emission control lines **E1** to **En**, a data driver **120** for driving the data lines **D1** to **Dm**, and a timing controller **150** for controlling the scan driver **110** and the data driver **120**.

The timing controller **150** generates a data driving control signal **DCS** and a scan driving control signal **SCS** in response to synchronizing signals supplied from the outside of the organic light emitting display. The data driving control signal **DCS** and the scan driving control signal **SCS** generated by the timing controller **150** are supplied to the data driver **120** and the scan driver **110**, respectively. The timing controller **150** supplies data (Data) provided from the outside of the organic light emitting display to the data driver **120**.

The scan driver **110** receives the scan driving control signal **SCS** from the timing controller **150**. The scan driver **110** that receives the scan driving control signal **SCS** generates scan signals and sequentially supplies the generated scan signals to the scan lines **S1** to **Sn**. In addition, the scan driver **110** generates emission control signals in response to the scan driving control signal **SCS** and sequentially supplies the generated emission control signals to the emission control lines **E1** to **En**. Here, the emission control signals are set to have a larger width than the scan signals. For example, the emission control signal supplied to the *i*th (*i* is a natural number) emission control line **E_i** overlaps the scan signals supplied to the (*i*-1)th and *i*th scan lines **S_{i-1}** and **S_i**. In one embodiment, the emission control signal supplied to the (*i*+2)th emission control line **E_{i+2}** overlaps with the scan signal supplied to the *i*th scan line **S_i** in a partial period.

On the other hand, the scan signals are set to have voltages at which the transistors included in the pixels **140** may be turned on, for example, low voltage. The emission control signals are set to have voltages at which the transistors included in the pixels **140** may be turned off, for example, high voltages.

The data driver **120** receives the data driving control signal **DCS** from the timing controller **150**. The data driver **120** that receives the data driving control signal **DCS** generates data signals and supplies the generated data signals to the data lines **D1** to **Dm** in synchronization with the scan signals.

The pixel unit **130** receives a first power supply **ELVDD** and a second power supply **ELVSS** from the outside of the organic light emitting display and supplies the **ELVDD** and **ELVSS** to the pixels **140**. The pixels **140** that receive the first power supply **ELVDD** and the second power supply **ELVSS** generate light components corresponding to the data signals, respectively. On the other hand, the pixel **140** positioned in an *i*th horizontal line is coupled to the (*i*-1)th and *i*th scan lines **S_{i-1}** and **S_i** and the (*n*+2)th and *n*th emission control lines **E_{n+2}** and **E_n**. For this purpose, the (*n*+1)th and *n*th emission control lines **E_{n+1}** and **E_n** (not shown) and an 0th scan line **S₀** are further formed in the pixel unit **130**. Here, the structure of the emission control lines coupled to the pixels **140** may change to correspond to the pixels **140**.

FIG. 2 is a circuit diagram of the pixel of FIG. 1 according to one embodiment. In FIG. 2, for convenience sake, the pixel **140** coupled to the *m*th data line **D_m**, the *n*th scan line **S_n**, the (*n*-1)th scan line **S_{n-1}**, the *n*th emission control line **E_n**, and the (*n*+2)th emission control line **E_{n+2}** will be illustrated.

Referring to FIG. 2, the pixel **140** includes an organic light emitting diode (OLED) and a pixel circuit **142** coupled to the data line **D_m**, the scan lines **S_{n-1}** and **S_n**, and the emission control lines **E_n** and **E_{n+2}** to control the amount of current supplied to the OLED.

The anode electrode of the OLED is coupled to the pixel circuit **142** and the cathode electrode of the OLED is coupled to the second power supply **ELVSS**. Here, the voltage value of the second power supply **ELVSS** is set to be lower than the voltage value of the first power supply **ELVDD**. The OLED generates light with predetermined brightness to correspond to the amount of current supplied from the pixel circuit **142**.

The pixel circuit **142** controls the amount of current supplied to the OLED to correspond to the data signal supplied to the data line **D_m** when the scan signal is supplied to the scan line **S_n**. For this purpose, the pixel circuit **142** includes first to seventh transistors **M1** to **M7** and a storage capacitor **C_{st}**.

The first electrode of the fourth transistor **M4** is coupled to the data line **D_m** and the second electrode of the fourth transistor **M4** is coupled to a first node **N1**. The gate electrode of the fourth transistor **M4** is coupled to the *n*th scan line **S_n**. The fourth transistor **M4** is turned on when the scan signal is supplied to the *n*th scan line **S_n** to supply the data signals supplied to the data line **D_m** to the first node **N1**.

The first electrode of the first transistor **M1** is coupled to the first node **n1** and the second electrode of the first transistor **M1** is coupled to the first electrode of the sixth transistor **M6**. The gate electrode of the first transistor **M1** is coupled to a second node **N2**. The first transistor **M1** supplies current corresponding to the voltage charged in the storage capacitor **C_{st}** to the OLED.

The first electrode of the second transistor **M2** is coupled to the second electrode of the first transistor **M1** and the second electrode of the second transistor **M2** is coupled to the first electrode of the third transistor **M3**. The gate electrode of the second transistor **M2** is coupled to the *n*th scan line **S_n**. The second transistor **M2** is turned on when the scan signal is supplied to the *n*th scan line **S_n** to couple the second electrode of the first transistor **M1** to the first electrode of the third transistor **M3**.

The first electrode of the third transistor **M3** is coupled to the second electrode of the second transistor **M2** and the second electrode of the third transistor **M3** is coupled to the

second node N2. The gate electrode of the third transistor M3 is coupled to the (n+2)th emission control line En+2. The third transistor M3 is turned off when the emission control signal is supplied to the (n+2)th emission control line En+2 and is turned on in the other cases. On the other hand, in the period where the second transistor M2 and the third transistor M3 are turned on, the first transistor M1 is coupled in the form of a diode.

The seventh transistor M7 is coupled between the second node N2 and an initializing power supply Vint. The gate electrode of the seventh transistor M7 is coupled to the (n-1)th scan line Sn-1. The seventh transistor M7 is turned on when the scan signal is supplied to the (n-1)th scan line to supply the voltage of the initializing power supply Vint to the second node N2. Here, the initializing power supply Vint is set to have a voltage lower than the data signal.

The first electrode of the fifth transistor M5 is coupled to the first power supply ELVDD and the second electrode of the fifth transistor M5 is coupled to the first node N1. The gate electrode of the fifth transistor M5 is coupled to the nth emission control line En. The fifth transistor M5 is turned off when the emission control signal is supplied to the nth emission control line En and is turned on when the emission control signal is not supplied.

The first electrode of the sixth transistor M6 is coupled to the second electrode of the first transistor M1 and the second electrode of the sixth transistor M6 is coupled to the anode electrode of the OLED. The gate electrode of the sixth transistor M6 is coupled to the nth emission control line En. The sixth transistor M6 is turned off when the emission control signal is supplied to the nth emission control line En and is turned on when the emission control signal is not supplied.

The storage capacitor Cst is coupled between the first power supply ELVDD and the second node N2. The storage capacitor Cst stores the data signal and a voltage corresponding to the threshold voltage of the first transistor M1.

FIG. 3 illustrates driving waveforms supplied to the pixel of FIG. 2 according to one embodiment.

Referring to FIG. 3, the emission control signal is supplied to the nth emission control line En so that the fifth transistor M5 and the sixth transistor M6 are turned off. When the fifth transistor M5 is turned off, electrical coupling between the first power supply ELVDD and the first node N1 is blocked. When the sixth transistor M6 is turned off, electrical coupling between the second electrode of the first transistor M1 and the anode electrode of the OLED is blocked. Therefore, in the period where the emission control signal is supplied to the nth emission control line En, the pixel 140 is set in a non-emission state.

Then, the scan signal is supplied to the (n-1)th scan line Sn-1 so that the seventh transistor M7 is turned on. When the seventh transistor M7 is turned on, the voltage of the initializing power supply Vint is supplied to the second node N2.

After the initializing power supply Vint is supplied to the second node N2, the scan signal is supplied to the nth scan line Sn. When the scan signal is supplied to the nth scan line Sn, the second transistor M2 and the fourth transistor M4 are turned on. When the second transistor M2 is turned on, the second electrode of the first transistor M1 is coupled to the first electrode of the third transistor M3. At this time, since the third transistor M3 is turned on, the first transistor M1 is coupled in the form of a diode. When the fourth transistor M4 is turned on, the data signal is supplied from the data line Dm to the first node N1. At this time, since the second node N2 is initialized to the voltage of the initializing power supply Vint, the first transistor M1 coupled in the form of the diode is turned on.

Then, the data signal supplied to the first node N1 is supplied to the second node N2 via the first transistor M1 coupled in the form of the diode. At this time, the storage capacitor Cst stores the data signal and the voltage corresponding to the threshold voltage of the first transistor M1.

After a predetermined voltage is charged in the storage capacitor Cst, the emission control signal is supplied to the (n+2)th emission control line En+2. When the emission control signal is supplied to the (n+2)th emission control line, the third transistor M3 is turned off when the third transistor M3 is turned off, the voltage of the second node N2 is partially changed to correspond to the turning off of the third transistor M3.

After the third transistor M3 is turned off, supply of the scan signal to the nth scan line Sn is stopped so that the fourth transistor M4 and the second transistor M2 are turned off. At this time, since the third transistor M3 is turned off, although the second transistor M2 is turned off, the voltage of the second node N2 is not changed.

Then, supply of the emission control signal to the nth emission control line En is stopped so that the fifth transistor M5 and the sixth transistor M6 are turned on. When the fifth transistor M5 and the sixth transistor M6 are turned on, a current path is formed from the first power supply ELVDD to the OLED via the first transistor M1.

After the supply of the emission control signal to the nth emission control line En is stopped, supply of the emission control signal to the (n+2)th emission control line En+2 is stopped. When the supply of the emission control signal to the (n+2)th emission control line En+2 is stopped, the third transistor M3 is turned on. At this time, the voltage of the second node N2 is partially changed to correspond to the turning on of the third transistor M3.

Here, after the predetermined voltage is charged in the storage capacitor Cst, the voltage of the second node N2 is changed in response to the turning off and on of the third transistor M3. In this case, theoretically, a first voltage corresponding to the turning off of the third transistor M3 is offset by a second voltage corresponding to the turning on of the third transistor M3 (that is, the first voltage=the second voltage) so that the second node N2 maintains a predetermined voltage. In one embodiment, after the voltage is charged in the storage capacitor Cst, the third transistor M3 is turned off and on so that it is possible to prevent the voltage of the second node N2 from being changed.

Then, the first transistor M1 controls the amount of current supplied from the first power supply ELVDD to the OLED in response to the voltage applied to the second node N2. In this case, the pixels 140 may realize an image with desired brightness and the pixel unit 130 may display an image with uniform brightness.

A plurality of transistors including the third transistor M3 may be formed between the gate electrode and the second electrode of the first transistor M1. For example, as illustrated in FIG. 4, a plurality of second transistors M2_1 and M2_2 may be formed between the third transistor M3 and the second electrode of the first transistor M1. At this time, since the third transistor M3 is turned off before the second transistors M2_1 and M2_2 are turned off and is turned on after the second transistors M2_1 and M2_2 are turned off, it is possible to prevent the voltage of the second node N2 from changing regardless of the second transistors M2_1 and M2_2.

In one embodiment, the third transistor M3 is coupled to the (n+2)th emission control line En+2. The third transistor M3 may be coupled to an additional signal line so that the

third transistor M3 is turned off before the second transistor M2 is turned off and is turned on after the second transistor M2 is turned off.

According to at least one of the disclosed embodiments, after a predetermined voltage is charged in the storage capacitor, transistors for coupling a driving transistor in the form of a diode are sequentially turned off and on. In this case, a voltage change generated by turning off the transistors is offset by a voltage change generated by turning on the transistors so that the voltage stored in the storage capacitor can be stably maintained.

Furthermore, the voltage charged in the storage capacitor may be stably maintained regardless of the transistors for coupling the driving transistor in the form of the diode so that an image with uniform brightness may be displayed.

While the above embodiments have been described in connection with the accompanying drawings, it is to be understood that the present disclosure is not limited to the disclosed embodiments, but, on the contrary, is intended to cover various modifications and equivalent arrangements included within the spirit and scope of the appended claims, and equivalents thereof.

What is claimed is:

1. A pixel, comprising:

an organic light emitting diode (OLED) comprising an anode electrode;

a first transistor comprising i) first and second electrodes and ii) a gate electrode, wherein the second electrode is operatively coupled to the anode electrode of the OLED, and wherein the first transistor is configured to control an amount of current supplied to the OLED in response to a voltage applied to the gate electrode;

at least one second transistor operatively coupled between the second electrode and the gate electrode of the first transistor; and

a third transistor directly coupled to the second transistor and the gate electrode of the first transistor, wherein the third transistor comprises i) a gate electrode and ii) first and second electrodes respectively directly connected to the gate electrode of the first transistor and the second transistor; and

wherein the third transistor is configured to be partially turned off during part of a period in which the second transistor is turned on.

2. The pixel as claimed in claim 1, wherein the third transistor is configured to be turned on when the second transistor is turned on.

3. The pixel as claimed in claim 2, wherein the third transistor is configured to be turned off before the second transistor is turned off.

4. The pixel as claimed in claim 3, wherein the third transistor is configured to be turned on after the second transistor is turned off.

5. The pixel as claimed in claim 1, wherein the first transistor is connected in parallel with the second and third transistors.

6. A pixel, comprising:

an organic light emitting diode (OLED) comprising an anode electrode;

a first transistor comprising i) first and second electrodes and ii) a gate electrode, wherein the second electrode is operatively coupled to the anode electrode of the OLED, and wherein the first transistor is configured to control an amount of current supplied to the OLED in response to a voltage applied to the gate electrode;

at least one second transistor operatively coupled between the second electrode and the gate electrode of the first transistor; and

a third transistor operatively coupled between the second transistor and the gate electrode of the first transistor, wherein the third transistor is configured to be partially turned off during part of a period in which the second transistor is turned on,

wherein the pixel further comprises:

a fourth transistor operatively coupled between a data line and the first electrode of the first transistor and configured to be substantially simultaneously turned on and off with the second transistor;

a fifth transistor operatively coupled between the first electrode of the first transistor and a first power supply and configured to be turned off in a period where the second transistor is turned on;

a sixth transistor operatively coupled between the second electrode of the first transistor and the OLED and configured to be substantially simultaneously turned on and off with the fifth transistor;

a seventh transistor operatively coupled between an initializing power supply and the gate electrode of the first transistor and configured to be turned on before the second transistor is turned on; and

a storage capacitor operatively coupled between the gate electrode of the first transistor and the first power supply.

7. An organic light emitting display, comprising:

a scan driver configured to drive a plurality of scan lines and a plurality of emission control lines;

a data driver configured to drive a plurality of data lines; and

a plurality of pixels positioned at intersections of the scan lines and the data lines,

wherein each of the pixels positioned in an i th (i is a natural number) horizontal line comprises:

an organic light emitting diode (OLED);

a first transistor comprising i) first and second electrodes and ii) a gate electrode, wherein the second electrode is operatively coupled to the OLED, and wherein the first transistor is configured to control an amount of current supplied to the OLED in response to a voltage applied to the gate electrode;

a second transistor operatively coupled between the second electrode and the gate electrode of the first transistor and configured to be turned on when a scan signal is supplied to an i th scan line; and

a third transistor operatively coupled between the second transistor and the gate electrode of the first transistor and configured to be turned on except when an emission control signal is supplied to an $(i+2)$ th emission control line,

wherein the scan driver is configured to supply an emission control signal to an i th emission control line to at least partially overlap with scan signals supplied to $(i-1)$ th and i th scan lines.

8. The organic light emitting display as claimed in claim 7, wherein the scan driver is configured to supply the emission control signal to the $(i+2)$ th emission control line to overlap with the scan signal supplied to the i th scan line in a partial period.

9. The organic light emitting display as claimed in claim 7, wherein a turn on period of the third transistor at least partially overlaps with a turn on period of the second transistor in response to the emission control signal supplied to the $(i+2)$ th emission control line, and

wherein the third transistor is configured to be turned off before the second transistor is turned off.

10. The organic light emitting display as claimed in claim 9, wherein the third transistor is configured to be turned on after the second transistor is turned off. 5

11. The organic light emitting display as claimed in claim 7, wherein each of the pixels positioned in the *i*th horizontal line comprises:

a fourth transistor operatively coupled between the corresponding data line and the first electrode of the first transistor and comprising a gate electrode coupled to the *i*th scan line; 10

a fifth transistor operatively coupled between the first electrode of the first transistor and a first power supply and comprising a gate electrode coupled to the *i*th emission control line; 15

a seventh transistor operatively coupled between an initializing power supply and the gate electrode of the first transistor and comprising a gate electrode coupled to the (*i*-1)th scan line; and 20

a storage capacitor operatively coupled between the gate electrode of the first transistor and the first power supply.

12. The organic light emitting display as claimed in claim 11, wherein the initializing power supply has a lower voltage than the data signal supplied to the data line. 25

* * * * *

专利名称(译)	使用其的像素和有机发光显示器		
公开(公告)号	US9390648	公开(公告)日	2016-07-12
申请号	US13/707372	申请日	2012-12-06
[标]申请(专利权)人(译)	三星显示有限公司		
申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
当前申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
[标]发明人	LEE CHANG HO KIM YANG WAN		
发明人	LEE, CHANG-HO KIM, YANG-WAN		
IPC分类号	G09G3/32		
CPC分类号	G09G3/3208 G09G3/3233 G09G2300/0819 G09G2300/0842 G09G2300/0861 G09G2310/0262 G09G2320/043		
优先权	1020120096306 2012-08-31 KR		
其他公开文献	US20140062982A1		
外部链接	Espacenet USPTO		

摘要(译)

公开了一种能够实现所需亮度和显示均匀图像的像素。在一个方面，像素包括有机发光二极管（OLED），第一晶体管，其第二电极连接到OLED的阳极，以响应施加到OLED的电压控制提供给OLED的电流。其栅电极。像素还包括耦合在第一电晶体和第一晶体管的栅电极之间的至少一个第二晶体管，以及耦合在第二晶体管和第一晶体管的栅电极之间的第三晶体管。第三晶体管在第二晶体管导通的时段的部分时段中截止。

