



US010679533B2

(12) **United States Patent**
Chaji et al.

(10) **Patent No.:** **US 10,679,533 B2**
(45) **Date of Patent:** **Jun. 9, 2020**

(54) **SYSTEM AND METHODS FOR AGING COMPENSATION IN AMOLED DISPLAYS**

(58) **Field of Classification Search**
CPC G09G 3/006
(Continued)

(71) Applicant: **Ignis Innovation Inc.**, Waterloo (CA)

(56) **References Cited**

(72) Inventors: **Gholamreza Chaji**, Waterloo (CA);
Joseph Marcel Dionne, Waterloo (CA);
Yaser Azizi, Waterloo (CA); **Javid Jaffari**, Kitchener (CA); **Abbas Hormati**, Kitchener (CA); **Tong Liu**, Waterloo (CA); **Stefan Alexander**, Waterloo (CA)

U.S. PATENT DOCUMENTS

3,506,851 A 4/1970 Polkinghorn et al.
3,774,055 A 11/1973 Bapat et al.
(Continued)

FOREIGN PATENT DOCUMENTS

CA 1 294 034 1/1992
CA 2 109 951 11/1992
(Continued)

(73) Assignee: **Ignis Innovation Inc.**, Waterloo (CA)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS

(21) Appl. No.: **15/703,260**

Ahnood et al.: "Effect of threshold voltage instability on field effect mobility in thin film transistors deduced from constant current measurements"; dated Aug. 2009.

(22) Filed: **Sep. 13, 2017**

(Continued)

(65) **Prior Publication Data**

US 2018/0005557 A1 Jan. 4, 2018

Primary Examiner — Ricky Ngou

(74) *Attorney, Agent, or Firm* — Stratford Managers Corporation

Related U.S. Application Data

(60) Continuation of application No. 14/477,971, filed on Sep. 5, 2014, now Pat. No. 9,786,209, which is a (Continued)

(57) **ABSTRACT**


Methods and systems to provide baseline measurements for aging compensation for a display device are disclosed. An example display system has a plurality of active pixels and a reference pixel. Common input signals are provided to the reference pixel and the plurality of active pixels. The outputs of the reference pixel is measured and compared to the output of the active pixels to determine aging effects. The display system may also be tested applying a first known reference current to a current comparator with a second variable reference current and the output of a device under test such as one of the pixels. The variable reference current is adjusted until the second current and the output of the device under test is equivalent of the first current. The resulting current of the device under test is stored in a look (Continued)

(30) **Foreign Application Priority Data**

Nov. 30, 2009 (CA) 2688870

(51) **Int. Cl.**
G09G 3/00 (2006.01)
G09G 3/3233 (2016.01)
(Continued)

(52) **U.S. Cl.**
CPC **G09G 3/006** (2013.01); **G01R 31/44** (2013.01); **G09G 3/3233** (2013.01);
(Continued)



up table for a baseline for aging measurements during the display system operation. The display system may also be tested to determine production flaws by determining anomalies such as short circuits in pixel components such as OLEDs and drive transistors.

3 Claims, 8 Drawing Sheets

Related U.S. Application Data

division of application No. 12/956,842, filed on Nov. 30, 2010, now Pat. No. 8,914,246.

- (51) **Int. Cl.**
G01R 31/44 (2020.01)
G09G 3/3283 (2016.01)
- (52) **U.S. Cl.**
 CPC ... *G09G 3/3283* (2013.01); *G09G 2300/0842* (2013.01); *G09G 2320/029* (2013.01); *G09G 2320/0233* (2013.01); *G09G 2320/0285* (2013.01); *G09G 2320/0295* (2013.01); *G09G 2320/043* (2013.01); *G09G 2320/045* (2013.01)
- (58) **Field of Classification Search**
 USPC 702/58
 See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,090,096 A 5/1978 Nagami
 4,160,934 A 7/1979 Kirsch
 4,354,162 A 10/1982 Wright
 4,943,956 A 7/1990 Noro
 4,996,523 A 2/1991 Bell et al.
 5,153,420 A 10/1992 Hack et al.
 5,198,803 A 3/1993 Shie et al.
 5,204,661 A 4/1993 Hack et al.
 5,266,515 A 11/1993 Robb et al.
 5,489,918 A 2/1996 Mosier
 5,498,880 A 3/1996 Lee et al.
 5,557,342 A 9/1996 Eto et al.
 5,572,444 A 11/1996 Lentz et al.
 5,589,847 A 12/1996 Lewis
 5,619,033 A 4/1997 Weisfield
 5,648,276 A 7/1997 Hara et al.
 5,670,973 A 9/1997 Bassetti et al.
 5,684,365 A 11/1997 Tang et al.
 5,691,783 A 11/1997 Numao et al.
 5,714,968 A 2/1998 Ikeda
 5,723,950 A 3/1998 Wei et al.
 5,744,824 A 4/1998 Kousai et al.
 5,745,660 A 4/1998 Kolpatzik et al.
 5,748,160 A 5/1998 Shieh et al.
 5,815,303 A 9/1998 Berlin
 5,870,071 A 2/1999 Kawahata
 5,874,803 A 2/1999 Garbuzov et al.
 5,880,582 A 3/1999 Sawada
 5,903,248 A 5/1999 Irwin
 5,917,280 A 6/1999 Burrows et al.
 5,923,794 A 7/1999 McGrath et al.
 5,945,972 A 8/1999 Okumura et al.
 5,949,398 A 9/1999 Kim
 5,952,789 A 9/1999 Stewart et al.
 5,952,991 A 9/1999 Akiyama et al.
 5,982,104 A 11/1999 Sasaki et al.
 5,990,629 A 11/1999 Yamada et al.
 6,023,259 A 2/2000 Howard et al.
 6,069,365 A 5/2000 Chow et al.
 6,091,203 A 7/2000 Kawashima et al.

6,097,360 A 8/2000 Holloman
 6,144,222 A 11/2000 Ho
 6,177,915 B1 1/2001 Beeteson et al.
 6,229,506 B1 5/2001 Dawson et al.
 6,229,508 B1 5/2001 Kane
 6,246,180 B1 6/2001 Nishigaki
 6,252,248 B1 6/2001 Sano et al.
 6,259,424 B1 7/2001 Kurogane
 6,262,589 B1 7/2001 Tamukai
 6,271,825 B1 8/2001 Greene et al.
 6,288,696 B1 9/2001 Holloman
 6,304,039 B1 10/2001 Appelberg et al.
 6,307,322 B1 10/2001 Dawson et al.
 6,310,962 B1 10/2001 Chung et al.
 6,320,325 B1 11/2001 Cok et al.
 6,323,631 B1 11/2001 Juang
 6,356,029 B1 3/2002 Hunter
 6,373,454 B1 4/2002 Knapp et al.
 6,392,617 B1 5/2002 Gleason
 6,414,661 B1 7/2002 Shen et al.
 6,417,825 B1 7/2002 Stewart et al.
 6,433,488 B1 8/2002 Bu
 6,437,106 B1 8/2002 Stoner et al.
 6,445,369 B1 9/2002 Yang et al.
 6,475,845 B2 11/2002 Kimura
 6,501,098 B2 12/2002 Yamazaki
 6,501,466 B1 12/2002 Yamagishi et al.
 6,518,962 B2 2/2003 Kimura et al.
 6,522,315 B2 2/2003 Ozawa et al.
 6,525,683 B1 2/2003 Gu
 6,531,827 B2 3/2003 Kawashima
 6,542,138 B1 4/2003 Shannon et al.
 6,555,420 B1 4/2003 Yamazaki
 6,580,408 B1 6/2003 Bae et al.
 6,580,657 B2 6/2003 Sanford et al.
 6,583,398 B2 6/2003 Harkin
 6,583,775 B1 6/2003 Sekiya et al.
 6,594,606 B2 7/2003 Everitt
 6,618,030 B2 9/2003 Kane et al.
 6,639,244 B1 10/2003 Yamazaki et al.
 6,668,645 B1 12/2003 Gilmour et al.
 6,677,713 B1 1/2004 Sung
 6,680,580 B1 1/2004 Sung
 6,687,266 B1 2/2004 Ma et al.
 6,690,000 B1 2/2004 Muramatsu et al.
 6,690,344 B1 2/2004 Takeuchi et al.
 6,693,388 B2 2/2004 Oomura
 6,693,610 B2 2/2004 Shannon et al.
 6,697,057 B2 2/2004 Koyama et al.
 6,720,942 B2 4/2004 Lee et al.
 6,724,151 B2 4/2004 Yoo
 6,734,636 B2 5/2004 Sanford et al.
 6,738,034 B2 5/2004 Kaneko et al.
 6,738,035 B1 5/2004 Fan
 6,753,655 B2 6/2004 Shih et al.
 6,753,834 B2 6/2004 Mikami et al.
 6,756,741 B2 6/2004 Li
 6,756,952 B1 6/2004 Decaux et al.
 6,756,958 B2 6/2004 Furuhashi et al.
 6,771,028 B1 8/2004 Winters
 6,777,712 B2 8/2004 Sanford et al.
 6,777,888 B2 8/2004 Kondo
 6,781,567 B2 8/2004 Kimura
 6,806,497 B2 10/2004 Jo
 6,806,638 B2 10/2004 Lih et al.
 6,806,857 B2 10/2004 Sempel et al.
 6,809,706 B2 10/2004 Shimoda
 6,815,975 B2 11/2004 Nara et al.
 6,828,950 B2 12/2004 Koyama
 6,853,371 B2 2/2005 Miyajima et al.
 6,859,193 B1 2/2005 Yumoto
 6,873,117 B2 3/2005 Ishizuka
 6,876,346 B2 4/2005 Anzai et al.
 6,885,356 B2 4/2005 Hashimoto
 6,900,485 B2 5/2005 Lee
 6,903,734 B2 6/2005 Eu
 6,909,243 B2 6/2005 Inukai
 6,909,419 B2 6/2005 Zavracky et al.
 6,911,960 B1 6/2005 Yokoyama

(56)

References Cited

U.S. PATENT DOCUMENTS

6,911,964 B2	6/2005	Lee et al.	7,978,187 B2	7/2011	Nathan et al.
6,914,448 B2	7/2005	Jinno	7,994,712 B2	8/2011	Sung et al.
6,919,871 B2	7/2005	Kwon	8,026,876 B2	9/2011	Nathan et al.
6,924,602 B2	8/2005	Komiya	8,049,420 B2	11/2011	Tamura et al.
6,937,215 B2	8/2005	Lo	8,077,123 B2	12/2011	Naugler, Jr.
6,937,220 B2	8/2005	Kitaura et al.	8,115,707 B2	2/2012	Nathan et al.
6,940,214 B1	9/2005	Komiya et al.	8,208,084 B2	6/2012	Lin
6,943,500 B2	9/2005	LeChevalier	8,223,177 B2	7/2012	Nathan et al.
6,947,022 B2	9/2005	McCartney	8,232,939 B2	7/2012	Nathan et al.
6,954,194 B2	10/2005	Matsumoto et al.	8,259,044 B2	9/2012	Nathan et al.
6,956,547 B2	10/2005	Bae et al.	8,264,431 B2	9/2012	Bulovic et al.
6,975,142 B2	12/2005	Azami et al.	8,279,143 B2	10/2012	Nathan et al.
6,975,332 B2	12/2005	Arnold et al.	8,339,386 B2	12/2012	Leon et al.
6,995,510 B2	2/2006	Murakami et al.	8,410,788 B2*	4/2013	Hartrampf G09G 3/006
6,995,519 B2	2/2006	Arnold et al.			324/537
7,023,408 B2	4/2006	Chen et al.	8,493,296 B2	7/2013	Ogawa
7,027,015 B2	4/2006	Booth, Jr. et al.	2001/0002703 A1	6/2001	Koyama
7,027,078 B2	4/2006	Reihl	2001/0009283 A1	7/2001	Arao et al.
7,034,793 B2	4/2006	Sekiya et al.	2001/0024181 A1	9/2001	Kubota
7,038,392 B2	5/2006	Libsch et al.	2001/0024186 A1	9/2001	Kane et al.
7,057,359 B2	6/2006	Hung et al.	2001/0026257 A1	10/2001	Kimura
7,061,451 B2	6/2006	Kimura	2001/0030323 A1	10/2001	Ikeda
7,064,733 B2	6/2006	Cok et al.	2001/0035863 A1	11/2001	Kimura
7,071,932 B2	7/2006	Libsch et al.	2001/0040541 A1	11/2001	Yoneda et al.
7,088,051 B1	8/2006	Cok	2001/0043173 A1	11/2001	Troutman
7,088,052 B2	8/2006	Kimura	2001/0045929 A1	11/2001	Prache
7,102,378 B2	9/2006	Kuo et al.	2001/0052606 A1	12/2001	Sempel et al.
7,106,285 B2	9/2006	Naugler	2001/0052940 A1	12/2001	Hagihara et al.
7,112,820 B2	9/2006	Chang et al.	2002/0000576 A1	1/2002	Inukai
7,116,058 B2	10/2006	Lo et al.	2002/0011796 A1	1/2002	Koyama
7,119,493 B2	10/2006	Fryer et al.	2002/0011799 A1	1/2002	Kimura
7,122,835 B1	10/2006	Ikeda et al.	2002/0012057 A1	1/2002	Kimura
7,127,380 B1	10/2006	Iverson et al.	2002/0014851 A1	2/2002	Tai et al.
7,129,914 B2	10/2006	Knapp et al.	2002/0018034 A1	2/2002	Ohki et al.
7,164,417 B2	1/2007	Cok	2002/0030190 A1	3/2002	Ohtani et al.
7,193,589 B2	3/2007	Yoshida et al.	2002/0047565 A1	4/2002	Nara et al.
7,224,332 B2	5/2007	Cok	2002/0052086 A1	5/2002	Maeda
7,227,519 B1	6/2007	Kawase et al.	2002/0067134 A1	6/2002	Kawashima
7,245,277 B2	7/2007	Ishizuka	2002/0084463 A1	7/2002	Sanford et al.
7,248,236 B2	7/2007	Nathan et al.	2002/0101172 A1	8/2002	Bu
7,262,753 B2	8/2007	Tanghe et al.	2002/0105279 A1	8/2002	Kimura
7,274,363 B2	9/2007	Ishizuka et al.	2002/0117722 A1	8/2002	Osada et al.
7,310,092 B2	12/2007	Imamura	2002/0122308 A1	9/2002	Ikeda
7,315,295 B2	1/2008	Kimura	2002/0158587 A1	10/2002	Komiya
7,321,348 B2	1/2008	Cok et al.	2002/0158666 A1	10/2002	Azami et al.
7,339,560 B2	3/2008	Sun	2002/0158823 A1	10/2002	Zavracky et al.
7,355,574 B1	4/2008	Leon et al.	2002/0167474 A1	11/2002	Everitt
7,358,941 B2	4/2008	Ono et al.	2002/0180369 A1	12/2002	Koyama
7,368,868 B2	5/2008	Sakamoto	2002/0180721 A1	12/2002	Kimura et al.
7,411,571 B2	8/2008	Huh	2002/0181276 A1	12/2002	Yamazaki
7,414,600 B2	8/2008	Nathan et al.	2002/0186214 A1	12/2002	Siwinski
7,423,617 B2	9/2008	Giraldo et al.	2002/0190924 A1	12/2002	Asano et al.
7,453,054 B2	11/2008	Lee et al.	2002/0190971 A1	12/2002	Nakamura et al.
7,474,285 B2	1/2009	Kimura	2002/0195967 A1	12/2002	Kim et al.
7,502,000 B2	3/2009	Yuki et al.	2002/0195968 A1	12/2002	Sanford et al.
7,528,812 B2	5/2009	Tsuge et al.	2003/0020413 A1	1/2003	Oomura
7,535,449 B2	5/2009	Miyazawa	2003/0030603 A1	2/2003	Shimoda
7,554,512 B2	6/2009	Steer	2003/0043088 A1	3/2003	Booth et al.
7,569,849 B2	8/2009	Nathan et al.	2003/0057895 A1	3/2003	Kimura
7,576,718 B2	8/2009	Miyazawa	2003/0058226 A1	3/2003	Bertram et al.
7,580,012 B2	8/2009	Kim et al.	2003/0062524 A1	4/2003	Kimura
7,589,707 B2	9/2009	Chou	2003/0063081 A1	4/2003	Kimura et al.
7,609,239 B2	10/2009	Chang	2003/0071821 A1	4/2003	Sundahl et al.
7,619,594 B2	11/2009	Hu	2003/0076048 A1	4/2003	Rutherford
7,619,597 B2	11/2009	Nathan et al.	2003/0090447 A1	5/2003	Kimura
7,633,470 B2	12/2009	Kane	2003/0090481 A1	5/2003	Kimura
7,656,370 B2	2/2010	Schneider et al.	2003/0107560 A1	6/2003	Yumoto et al.
7,800,558 B2	9/2010	Routley et al.	2003/0111966 A1	6/2003	Mikami et al.
7,847,764 B2	12/2010	Cok et al.	2003/0122745 A1	7/2003	Miyazawa
7,859,492 B2	12/2010	Kohno	2003/0122813 A1	7/2003	Ishizuki et al.
7,868,859 B2	1/2011	Tomida et al.	2003/0142088 A1	7/2003	LeChevalier
7,876,294 B2	1/2011	Sasaki et al.	2003/0151569 A1	8/2003	Lee et al.
7,924,249 B2	4/2011	Nathan et al.	2003/0156101 A1	8/2003	Le Chevalier
7,932,883 B2	4/2011	Klompouhouwer et al.	2003/0174152 A1	9/2003	Noguchi
7,969,390 B2	6/2011	Yoshida	2003/0179626 A1	9/2003	Sanford et al.
			2003/0185438 A1	10/2003	Osawa et al.
			2003/0197663 A1	10/2003	Lee et al.
			2003/0210256 A1	11/2003	Mori et al.
			2003/0230141 A1	12/2003	Gilmour et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2003/0230980	A1	12/2003	Forrest et al.	2005/0285822	A1	12/2005	Reddy et al.
2003/0231148	A1	12/2003	Lin et al.	2005/0285825	A1	12/2005	Eom et al.
2004/0032382	A1	2/2004	Cok et al.	2006/0001613	A1	1/2006	Routley et al.
2004/0041750	A1	3/2004	Abe	2006/0007072	A1	1/2006	Choi et al.
2004/0066357	A1	4/2004	Kawasaki	2006/0007249	A1	1/2006	Reddy et al.
2004/0070557	A1	4/2004	Asano et al.	2006/0012310	A1	1/2006	Chen et al.
2004/0070565	A1	4/2004	Nayar et al.	2006/0012311	A1	1/2006	Ogawa
2004/0090186	A1	5/2004	Kanauchi et al.	2006/0022305	A1	2/2006	Yamashita
2004/0090400	A1	5/2004	Yoo	2006/0027807	A1	2/2006	Nathan et al.
2004/0095297	A1	5/2004	Libsch et al.	2006/0030084	A1	2/2006	Young
2004/0100427	A1	5/2004	Miyazawa	2006/0038758	A1	2/2006	Routley et al.
2004/0108518	A1	6/2004	Jo	2006/0038762	A1	2/2006	Chou
2004/0135749	A1	7/2004	Kondakov et al.	2006/0066533	A1	3/2006	Sato et al.
2004/0140982	A1	7/2004	Pate	2006/0077135	A1	4/2006	Cok et al.
2004/0145547	A1	7/2004	Oh	2006/0077142	A1	4/2006	Kwon
2004/0150592	A1	8/2004	Mizukoshi et al.	2006/0082523	A1	4/2006	Guo et al.
2004/0150594	A1	8/2004	Koyama et al.	2006/0092185	A1	5/2006	Jo et al.
2004/0150595	A1	8/2004	Kasai	2006/0097628	A1	5/2006	Suh et al.
2004/0155841	A1	8/2004	Kasai	2006/0097631	A1	5/2006	Lee
2004/0174347	A1	9/2004	Sun et al.	2006/0103611	A1	5/2006	Choi
2004/0174349	A1	9/2004	Libsch et al.	2006/0149493	A1	7/2006	Sambandan et al.
2004/0174354	A1	9/2004	Ono et al.	2006/0170623	A1	8/2006	Naugler, Jr. et al.
2004/0178743	A1	9/2004	Miller et al.	2006/0176250	A1	8/2006	Nathan et al.
2004/0183759	A1	9/2004	Stevenson et al.	2006/0208961	A1	9/2006	Nathan et al.
2004/0196275	A1	10/2004	Hattori	2006/0208971	A1	9/2006	Deane
2004/0207615	A1	10/2004	Yumoto	2006/0214888	A1	9/2006	Schneider et al.
2004/0227697	A1	11/2004	Mori	2006/0232522	A1	10/2006	Roy et al.
2004/0239596	A1	12/2004	Ono et al.	2006/0244697	A1	11/2006	Lee et al.
2004/0252089	A1	12/2004	Ono et al.	2006/0261841	A1	11/2006	Fish
2004/0257313	A1	12/2004	Kawashima et al.	2006/0273997	A1	12/2006	Nathan et al.
2004/0257353	A1	12/2004	Imamura et al.	2006/0279481	A1	12/2006	Haruna et al.
2004/0257355	A1	12/2004	Naugler	2006/0284801	A1	12/2006	Yoon et al.
2004/0263437	A1	12/2004	Hattori	2006/0284895	A1	12/2006	Marcu et al.
2004/0263444	A1	12/2004	Kimura	2006/0290618	A1	12/2006	Goto
2004/0263445	A1	12/2004	Inukai et al.	2007/0001937	A1	1/2007	Park et al.
2004/0263541	A1	12/2004	Takeuchi et al.	2007/0001939	A1	1/2007	Hashimoto et al.
2005/0007355	A1	1/2005	Miura	2007/0008251	A1	1/2007	Kohno et al.
2005/0007357	A1	1/2005	Yamashita et al.	2007/0008268	A1	1/2007	Park et al.
2005/0007392	A1	1/2005	Kasai et al.	2007/0008297	A1	1/2007	Bassetti
2005/0017650	A1	1/2005	Fryer et al.	2007/0057873	A1	3/2007	Uchino et al.
2005/0024081	A1	2/2005	Kuo et al.	2007/0057874	A1	3/2007	Le Roy et al.
2005/0024393	A1	2/2005	Kondo et al.	2007/0069998	A1	3/2007	Naugler et al.
2005/0030267	A1	2/2005	Tanghe et al.	2007/0075727	A1	4/2007	Nakano et al.
2005/0057193	A1*	3/2005	Ono G09G 3/006 315/291	2007/0076226	A1	4/2007	Klompenuhouwer et al.
2005/0057484	A1	3/2005	Diefenbaugh et al.	2007/0080905	A1	4/2007	Takahara
2005/0057580	A1	3/2005	Yamano et al.	2007/0080906	A1	4/2007	Tanabe
2005/0067970	A1	3/2005	Libsch et al.	2007/0080908	A1	4/2007	Nathan et al.
2005/0067971	A1	3/2005	Kane	2007/0097038	A1	5/2007	Yamazaki et al.
2005/0068270	A1	3/2005	Awakura	2007/0097041	A1	5/2007	Park et al.
2005/0068275	A1	3/2005	Kane	2007/0103419	A1	5/2007	Uchino et al.
2005/0073264	A1	4/2005	Matsumoto	2007/0115221	A1	5/2007	Buchhauser et al.
2005/0083323	A1	4/2005	Suzuki et al.	2007/0164664	A1	7/2007	Ludwicki et al.
2005/0088103	A1	4/2005	Kageyama et al.	2007/0182671	A1	8/2007	Nathan et al.
2005/0110420	A1	5/2005	Arnold et al.	2007/0236134	A1	10/2007	Ho et al.
2005/0110807	A1	5/2005	Chang	2007/0236440	A1	10/2007	Wacyk et al.
2005/0140598	A1	6/2005	Kim et al.	2007/0236517	A1	10/2007	Kimpe
2005/0140610	A1	6/2005	Smith et al.	2007/0241999	A1	10/2007	Lin
2005/0145891	A1	7/2005	Abe	2007/0273294	A1	11/2007	Nagayama
2005/0156831	A1	7/2005	Yamazaki et al.	2007/0285359	A1	12/2007	Ono
2005/0162079	A1	7/2005	Sakamoto	2007/0290958	A1	12/2007	Cok
2005/0168416	A1	8/2005	Hashimoto et al.	2007/0296672	A1	12/2007	Kim et al.
2005/0179626	A1	8/2005	Yuki et al.	2008/0001525	A1	1/2008	Chao et al.
2005/0179628	A1	8/2005	Kimura	2008/0001544	A1	1/2008	Murakami et al.
2005/0185200	A1	8/2005	Tobol	2008/0030518	A1	2/2008	Higgins et al.
2005/0200575	A1	9/2005	Kim et al.	2008/0036708	A1	2/2008	Shirasaki
2005/0206590	A1	9/2005	Sasaki et al.	2008/0042942	A1	2/2008	Takahashi
2005/0212787	A1	9/2005	Noguchi et al.	2008/0042948	A1	2/2008	Yamashita et al.
2005/0219184	A1	10/2005	Zehner et al.	2008/0048951	A1	2/2008	Naugler, Jr. et al.
2005/0225683	A1	10/2005	Nozawa	2008/0055209	A1	3/2008	Cok
2005/0248515	A1	11/2005	Naugler et al.	2008/0055210	A1*	3/2008	Cok G09G 3/006 345/77
2005/0269959	A1	12/2005	Uchino et al.	2008/0055211	A1*	3/2008	Ogawa G09G 3/006 345/77
2005/0269960	A1	12/2005	Ono et al.	2008/0074413	A1	3/2008	Ogura
2005/0280615	A1	12/2005	Cok et al.	2008/0088549	A1	4/2008	Nathan et al.
2005/0280766	A1	12/2005	Johnson et al.	2008/0088648	A1	4/2008	Nathan et al.
				2008/0111766	A1	5/2008	Uchino et al.
				2008/0116787	A1	5/2008	Hsu et al.
				2008/0117144	A1	5/2008	Nakano et al.

(56)	References Cited			CA	2 522 396	11/2004
	U.S. PATENT DOCUMENTS			CA	2 443 206	3/2005
				CA	2 472 671	12/2005
				CA	2 567 076	1/2006
2008/0150845	A1	6/2008	Ishii et al.	CA	2 526 782	4/2006
2008/0150847	A1	6/2008	Kim et al.	CA	2 541 531	7/2006
2008/0158115	A1	7/2008	Cordes et al.	CA	2 550 102	4/2008
2008/0158648	A1	7/2008	Cummings	CA	2 773 699	10/2013
2008/0198103	A1	8/2008	Toyomura et al.	CN	1381032	11/2002
2008/0211749	A1	9/2008	Weitbruch et al.	CN	1448908	10/2003
2008/0231558	A1*	9/2008	Naugler G09G 3/3233	CN	1682267 A	10/2005
			345/76	CN	1760945	4/2006
				CN	1886774	12/2006
2008/0231562	A1	9/2008	Kwon	CN	101261803	9/2008
2008/0231625	A1	9/2008	Minami et al.	CN	102656621	9/2012
2008/0252223	A1	10/2008	Toyoda et al.	EP	0 158 366	10/1985
2008/0252571	A1	10/2008	Hente et al.	EP	1 028 471	8/2000
2008/0259020	A1	10/2008	Fisekovic et al.	EP	1 111 577	6/2001
2008/0290805	A1	11/2008	Yamada et al.	EP	1 130 565 A1	9/2001
2008/0297055	A1	12/2008	Miyake et al.	EP	1 194 013	4/2002
2009/0058772	A1	3/2009	Lee	EP	1 335 430 A1	8/2003
2009/0109142	A1	4/2009	Takahara	EP	1 372 136	12/2003
2009/0121994	A1	5/2009	Miyata	EP	1 381 019	1/2004
2009/0146926	A1	6/2009	Sung et al.	EP	1 418 566	5/2004
2009/0160743	A1	6/2009	Tomida et al.	EP	1 429 312 A	6/2004
2009/0174628	A1	7/2009	Wang et al.	EP	145 0341 A	8/2004
2009/0184901	A1	7/2009	Kwon	EP	1 465 143 A	10/2004
2009/0195483	A1	8/2009	Naugler, Jr. et al.	EP	1 469 448 A	10/2004
2009/0201281	A1	8/2009	Routley et al.	EP	1 521 203 A2	4/2005
2009/0206764	A1	8/2009	Schemmann et al.	EP	1 594 347	11/2005
2009/0213046	A1	8/2009	Nam	EP	1 784 055 A2	5/2007
2009/0244046	A1	10/2009	Seto	EP	1854338 A1	11/2007
2009/0262047	A1	10/2009	Yamashita	EP	1 879 169 A1	1/2008
2010/0004891	A1	1/2010	Ahlers et al.	EP	1 879 172	1/2008
2010/0026725	A1	2/2010	Smith	GB	2 389 951	12/2003
2010/0039422	A1	2/2010	Seto	JP	1272298	10/1989
2010/0039458	A1	2/2010	Nathan et al.	JP	4-042619	2/1992
2010/0060911	A1	3/2010	Marcu et al.	JP	6-314977	11/1994
2010/0079419	A1	4/2010	Shibusawa	JP	8-340243	12/1996
2010/0165002	A1	7/2010	Ahn	JP	09-090405	4/1997
2010/0194670	A1	8/2010	Cok	JP	10-254410	9/1998
2010/0207960	A1	8/2010	Kimpe et al.	JP	11-202295	7/1999
2010/0225630	A1	9/2010	Levey et al.	JP	11-219146	8/1999
2010/0251295	A1	9/2010	Amento et al.	JP	11 231805	8/1999
2010/0277400	A1*	11/2010	Jeong G09G 3/3275	JP	11-282419	10/1999
			345/76	JP	2000-056847	2/2000
				JP	2000-81607	3/2000
2010/0315319	A1	12/2010	Cok et al.	JP	2001-134217	5/2001
2011/0063197	A1	3/2011	Chung et al.	JP	2001-195014	7/2001
2011/0069051	A1	3/2011	Nakamura et al.	JP	2002-055654	2/2002
2011/0069089	A1	3/2011	Kopf et al.	JP	2002-91376	3/2002
2011/0074750	A1	3/2011	Leon et al.	JP	2002-514320	5/2002
2011/0149166	A1	6/2011	Botzas et al.	JP	2002-278513	9/2002
2011/0181630	A1	7/2011	Smith et al.	JP	2002-333862	11/2002
2011/0199395	A1	8/2011	Nathan et al.	JP	2003-076331	3/2003
2011/0227964	A1	9/2011	Chaji et al.	JP	2003-124519	4/2003
2011/0273399	A1	11/2011	Lee	JP	2003-177709	6/2003
2011/0293480	A1	12/2011	Mueller	JP	2003-271095	9/2003
2012/0056558	A1	3/2012	Toshiya et al.	JP	2003-308046	10/2003
2012/0062565	A1	3/2012	Fuchs et al.	JP	2003-317944	11/2003
2012/0262184	A1	10/2012	Shen	JP	2004-004675	1/2004
2012/0299978	A1	11/2012	Chaji	JP	2004-145197	5/2004
2013/0027381	A1	1/2013	Nathan et al.	JP	2004-287345	10/2004
2013/0057595	A1	3/2013	Nathan et al.	JP	2005-057217	3/2005
2013/0112960	A1	5/2013	Chaji et al.	JP	2007-065015	3/2007
2013/0135272	A1	5/2013	Park	JP	2008-102335	5/2008
2013/0309821	A1	11/2013	Yoo et al.	JP	4-158570	10/2008
2013/0321671	A1	12/2013	Cote et al.	KR	2004-0100887	12/2004
				TW	342486	10/1998
				TW	473622	1/2002
				TW	485337	5/2002
CA	2 249 592	7/1998		TW	502233	9/2002
CA	2 368 386	9/1999		TW	538650	6/2003
CA	2 242 720	1/2000		TW	1221268	9/2004
CA	2 354 018	6/2000		TW	1223092	11/2004
CA	2 432 530	7/2002		TW	200727247	7/2007
CA	2 436 451	8/2002		WO	WO 1998/48403	10/1998
CA	2 438 577	8/2002		WO	WO 1999/48079	9/1999
CA	2 463 653	1/2004		WO	WO 2001/06484	1/2001
CA	2 498 136	3/2004				

(56)

References Cited

FOREIGN PATENT DOCUMENTS

WO	WO 2001/27910 A1	4/2001
WO	WO 2001/63587 A2	8/2001
WO	WO 2002/067327 A	8/2002
WO	WO 2003/001496 A1	1/2003
WO	WO 2003/034389 A	4/2003
WO	WO 2003/058594 A1	7/2003
WO	WO 2003/063124	7/2003
WO	WO 2003/077231	9/2003
WO	WO 2004/003877	1/2004
WO	WO 2004/025615 A	3/2004
WO	WO 2004/034364	4/2004
WO	WO 2004/047058	6/2004
WO	WO 2004/104975 A1	12/2004
WO	WO 2005/022498	3/2005
WO	WO 2005/022500 A	3/2005
WO	WO 2005/029455	3/2005
WO	WO 2005/029456	3/2005
WO	WO 2005/055185	6/2005
WO	WO 2006/000101 A1	1/2006
WO	WO 2006/053424	5/2006
WO	WO 2006/063448 A	6/2006
WO	WO 2006/084360	8/2006
WO	WO 2007/003877 A	1/2007
WO	WO 2007/079572	7/2007
WO	WO 2007/120849 A2	10/2007
WO	WO 2009/048618	4/2009
WO	WO 2009/055920	5/2009
WO	WO 2010/023270	3/2010
WO	WO 2011/041224 A1	4/2011
WO	WO 2011/064761 A1	6/2011
WO	WO 2011/067729	6/2011
WO	WO 2012/160424 A1	11/2012
WO	WO 2012/160471	11/2012
WO	WO 2012/164474 A2	12/2012
WO	WO 2012/164475 A2	12/2012

OTHER PUBLICATIONS

Alexander et al.: "Pixel circuits and drive schemes for glass and elastic AMOLED displays"; dated Jul. 2005 (9 pages).

Alexander et al.: "Unique Electrical Measurement Technology for Compensation, Inspection, and Process Diagnostics of AMOLED HDTV"; dated May 2010 (4 pages).

Ashtiani et al.: "AMOLED Pixel Circuit With Electronic Compensation of Luminance Degradation"; dated Mar. 2007 (4 pages).

Chaji et al.: "A Current-Mode Comparator for Digital Calibration of Amorphous Silicon AMOLED Displays"; dated Jul. 2008 (5 pages).

Chaji et al.: "A fast settling current driver based on the CCII for AMOLED displays"; dated Dec. 2009 (6 pages).

Chaji et al.: "A Low-Cost Stable Amorphous Silicon AMOLED Display with Full V~I- and V~O~L~E~D Shift Compensation"; dated May 2007 (4 pages).

Chaji et al.: "A low-power driving scheme for a-Si:H active-matrix organic light-emitting diode displays"; dated Jun. 2005 (4 pages).

Chaji et al.: "A low-power high-performance digital circuit for deep submicron technologies"; dated Jun. 2005 (4 pages).

Chaji et al.: "A novel a-Si:H AMOLED pixel circuit based on short-term stress stability of a-Si:H TFTs"; dated Oct. 2005 (3 pages).

Chaji et al.: "A Novel Driving Scheme and Pixel Circuit for AMOLED Displays"; dated Jun. 2006 (4 pages).

Chaji et al.: "A Novel Driving Scheme for High Resolution Large-area a-Si:H AMOLED displays"; dated Aug. 2005 (3 pages).

Chaji et al.: "A Stable Voltage-Programmed Pixel Circuit for a-Si:H AMOLED Displays"; dated Dec. 2006 (12 pages).

Chaji et al.: "A Sub- μ A fast-settling current-programmed pixel circuit for AMOLED displays"; dated Sep. 2007.

Chaji et al.: "An Enhanced and Simplified Optical Feedback Pixel Circuit for AMOLED Displays"; dated Oct. 2006.

Chaji et al.: "Compensation technique for DC and transient instability of thin film transistor circuits for large-area devices"; dated Aug. 2008.

Chaji et al.: "Driving scheme for stable operation of 2-TFT a-Si AMOLED pixel"; dated Apr. 2005 (2 pages).

Chaji et al.: "Dynamic-effect compensating technique for stable a-Si:H AMOLED displays"; dated Aug. 2005 (4 pages).

Chaji et al.: "Electrical Compensation of OLED Luminance Degradation"; dated Dec. 2007 (3 pages).

Chaji et al.: "eUTDSP: a design study of a new VLIW-based DSP architecture"; dated My 2003 (4 pages).

Chaji et al.: "Fast and Offset-Leakage Insensitive Current-Mode Line Driver for Active Matrix Displays and Sensors"; dated Feb. 2009 (8 pages).

Chaji et al.: "High Speed Low Power Adder Design With a New Logic Style: Pseudo Dynamic Logic (SDL)"; dated Oct. 2001 (4 pages).

Chaji et al.: "High-precision, fast current source for large-area current-programmed a-Si flat panels"; dated Sep. 2006 (4 pages).

Chaji et al.: "Low-Cost AMOLED Television with IGNIS Compensating Technology"; dated May 2008 (4 pages).

Chaji et al.: "Low-Cost Stable a-Si:H AMOLED Display for Portable Applications"; dated Jun. 2006 (4 pages).

Chaji et al.: "Low-Power Low-Cost Voltage-Programmed a-Si:H AMOLED Display"; dated Jun. 2008 (5 pages).

Chaji et al.: "Merged phototransistor pixel with enhanced near infrared response and flicker noise reduction for biomolecular imaging"; dated Nov. 2008 (3 pages).

Chaji et al.: "Parallel Addressing Scheme for Voltage-Programmed Active-Matrix OLED Displays"; dated May 2007 (6 pages).

Chaji et al.: "Pseudo dynamic logic (SDL): a high-speed and low-power dynamic logic family"; dated 2002 (4 pages).

Chaji et al.: "Stable a-Si:H circuits based on short-term stress stability of amorphous silicon thin film transistors"; dated May 2006 (4 pages).

Chaji et al.: "Stable Pixel Circuit for Small-Area High-Resolution a-Si:H AMOLED Displays"; dated Oct. 2008 (6 pages).

Chaji et al.: "Stable RGBW AMOLED display with OLED degradation compensation using electrical feedback"; dated Feb. 2010 (2 pages).

Chaji et al.: "Thin-Film Transistor Integration for Biomedical Imaging and AMOLED Displays"; dated 2008 (177 pages).

European Search Report for Application No. EP 01 11 22313 dated Sep. 14, 2005 (4 pages).

European Search Report for Application No. EP 04 78 6661 dated Mar. 9, 2009.

European Search Report for Application No. EP 05 75 9141 dated Oct. 30, 2009 (2 pages).

European Search Report for Application No. EP 05 81 9617 dated Jan. 30, 2009.

European Search Report for Application No. EP 06 70 5133 dated Jul. 18, 2008.

European Search Report for Application No. EP 06 72 1798 dated Nov. 12, 2009 (2 pages).

European Search Report for Application No. EP 07 71 0608.6 dated Mar. 19, 2010 (7 pages).

European Search Report for Application No. EP 07 71 9579 dated May 20, 2009.

European Search Report for Application No. EP 07 81 5784 dated Jul. 20, 2010 (2 pages).

European Search Report for Application No. EP 10 16 6143, dated Sep. 3, 2010 (2 pages).

European Search Report for Application No. EP 10 83 4294.0-1903, dated Apr. 8, 2013, (9 pages).

European Search Report for Application No. PCT/CA2006/000177 dated Jun. 2, 2006.

European Supplementary Search Report for Application No. EP 04 78 6662 dated Jan. 19, 2007 (2 pages).

Extended European Search Report for Application No. 11 73 9485.8 dated Aug. 6, 2013(14 pages).

Extended European Search Report for Application No. EP 09 73 3076.5, dated Apr. 27, (13 pages).

Extended European Search Report for Application No. EP 11 16 8677.0, dated Nov. 29, 2012, (13 page).

Extended European Search Report for Application No. EP 11 19 1641.7 dated Jul. 11, 2012 (14 pages).

(56)

References Cited

OTHER PUBLICATIONS

- Extended European Search Report for Application No. EP 10834297 dated Oct. 27, 2014 (6 pages).
- Fossum, Eric R.. "Active Pixel Sensors: Are CCD's Dinosaurs?" SPIE: Symposium on Electronic Imaging. Feb. 1, 1993 (13 pages).
- Goh et al., "A New a-Si:H Thin-Film Transistor Pixel Circuit for Active-Matrix Organic Light-Emitting Diodes", IEEE Electron Device Letters, vol. 24, No. 9, Sep. 2003, pp. 583-585.
- International Preliminary Report on Patentability for Application No. PCT/CA2005/001007 dated Oct. 16, 2006, 4 pages.
- International Search Report for Application No. PCT/CA2004/001741 dated Feb. 21, 2005.
- International Search Report for Application No. PCT/CA2004/001742, Canadian Patent Office, dated Feb. 21, 2005 (2 pages).
- International Search Report for Application No. PCT/CA2005/001007 dated Oct. 18, 2005.
- International Search Report for Application No. PCT/CA2005/001897, dated Mar. 21, 2006 (2 pages).
- International Search Report for Application No. PCT/CA2007/000652 dated Jul. 25, 2007.
- International Search Report for Application No. PCT/CA2009/000501, dated Jul. 30, 2009 (4 pages).
- International Search Report for Application No. PCT/CA2009/001769, dated Apr. 8, 2010 (3 pages).
- International Search Report for Application No. PCT/IB2010/055481, dated Apr. 7, 2011, 3 pages.
- International Search Report for Application No. PCT/IB2010/055486, dated Apr. 19, 2011, 5 pages.
- International Search Report for Application No. PCT/IB2014/060959, dated Aug. 28, 2014, 5 pages.
- International Search Report for Application No. PCT/IB2010/055541 filed Dec. 1, 2010, dated May 26, 2011; 5 pages.
- International Search Report for Application No. PCT/IB2011/050502, dated Jun. 27, 2011 (6 pages).
- International Search Report for Application No. PCT/IB2011/051103, dated Jul. 8, 2011, 3 pages.
- International Search Report for Application No. PCT/IB2011/055135, Canadian Patent Office, dated Apr. 16, 2012 (5 pages).
- International Search Report for Application No. PCT/IB2012/052372, dated Sep. 12, 2012 (3 pages).
- International Search Report for Application No. PCT/IB2013/054251, Canadian Intellectual Property Office, dated Sep. 11, 2013; (4 pages).
- International Search Report for Application No. PCT/JP02/09668, dated Dec. 3, 2002, (4 pages).
- International Written Opinion for Application No. PCT/CA2004/001742, Canadian Patent Office, dated Feb. 21, 2005 (5 pages).
- International Written Opinion for Application No. PCT/CA2005/001897, dated Mar. 21, 2006 (4 pages).
- International Written Opinion for Application No. PCT/CA2009/000501 dated Jul. 30, 2009 (6 pages).
- International Written Opinion for Application No. PCT/IB2010/055481, dated Apr. 7, 2011, 6 pages.
- International Written Opinion for Application No. PCT/IB2010/055486, dated Apr. 19, 2011, 8 pages.
- International Written Opinion for Application No. PCT/IB2010/055541, dated May 26, 2011; 6 pages.
- International Written Opinion for Application No. PCT/IB2011/050502, dated Jun. 27, 2011 (7 pages).
- International Written Opinion for Application No. PCT/IB2011/051103, dated Jul. 8, 2011, 6 pages.
- International Written Opinion for Application No. PCT/IB2011/055135, Canadian Patent Office, dated Apr. 16, 2012 (5 pages).
- International Written Opinion for Application No. PCT/IB2012/052372, dated Sep. 12, 2012 (6 pages).
- International Written Opinion for Application No. PCT/IB2013/054251, Canadian Intellectual Property Office, dated Sep. 11, 2013; (5 pages).
- International Written Opinion for Application No. PCT/IB2014/060879, Canadian Intellectual Property Office, dated Jul. 17, 2014; (4 pages).
- Jafarabadiashtiani et al.: "A New Driving Method for a-Si AMOLED Displays Based on Voltage Feedback"; dated 2005 (4 pages).
- Kanicki, J., et al. "Amorphous Silicon Thin-Film Transistors Based Active-Matrix Organic Light-Emitting Displays." Asia Display: International Display Workshops, Sep. 2001 (pp. 315-318).
- Karim, K. S., et al. "Amorphous Silicon Active Pixel Sensor Readout Circuit for Digital Imaging." IEEE: Transactions on Electron Devices. vol. 50, No. 1, Jan. 2003 (pp. 200-208).
- Lee et al.: "Ambipolar Thin-Film Transistors Fabricated by PECVD Nanocrystalline Silicon"; dated 2006.
- Lee, Wonbok: "Thermal Management in Microprocessor Chips and Dynamic Backlight Control in Liquid Crystal Displays", Ph.D. Dissertation, University of Southern California (124 pages).
- Ma E Y et al.: "organic light emitting diode/thin film transistor integration for foldable displays" dated Sep. 15, 1997(4 pages).
- Matsueda y et al.: "35.1: 2.5-in. AMOLED with Integrated 6-bit Gamma Compensated Digital Data Driver"; dated May 2004.
- Mendes E., et al. "A High Resolution Switch-Current Memory Base Cell." IEEE: Circuits and Systems. vol. 2, Aug. 1999 (pp. 718-721).
- Nathan A. et al., "Thin Film imaging technology on glass and plastic" ICM 2000, proceedings of the 12 international conference on microelectronics, dated Oct. 31, 2001 (4 pages).
- Nathan et al., "Amorphous Silicon Thin Film Transistor Circuit Integration for Organic LED Displays on Glass and Plastic", IEEE Journal of Solid-State Circuits, vol. 39, No. 9, Sep. 2004, pp. 1477-1486.
- Nathan et al.: "Backplane Requirements for active Matrix Organic Light Emitting Diode Displays,"; dated 2006 (16 pages).
- Nathan et al.: "Call for papers second international workshop on compact thin-film transistor (TFT) modeling for circuit simulation"; dated Sep. 2009 (1 page).
- Nathan et al.: "Driving schemes for a-Si and LTPS AMOLED displays"; dated Dec. 2005 (11 pages).
- Nathan et al.: "Invited Paper: a-Si for AMOLED—Meeting the Performance and Cost Demands of Display Applications (Cell Phone to HDTV)"; dated 2006 (4 pages).
- Office Action in Japanese patent application No. JP2006-527247 dated Mar. 15, 2010. (8 pages).
- Office Action in Japanese patent application No. JP2007-545796 dated Sep. 5, 2011. (8 pages).
- Office Action in Japanese patent application No. JP2012-541612 dated Jul. 15, 2014. (3 pages).
- Partial European Search Report for Application No. EP 11 168 677.0, dated Sep. 22, 2011 (5 pages).
- Partial European Search Report for Application No. EP 11 19 1641.7, dated Mar. 20, 2012 (8 pages).
- Philipp: "Charge transfer sensing" Sensor Review, vol. 19, No. 2, Dec. 31, 1999 (Dec. 31, 1999), 10 pages.
- Rafati et al.: "Comparison of a 17 b multiplier in Dual-rail domino and in Dual-rail D L (D L) logic styles"; dated 2002 (4 pages).
- Safavian et al.: "3-TFT active pixel sensor with correlated double sampling readout circuit for real-time medical x-ray imaging"; dated Jun. 2006 (4 pages).
- Safavian et al.: "A novel current scaling active pixel sensor with correlated double sampling readout circuit for real time medical x-ray imaging"; dated May 2007 (7 pages).
- Safavian et al.: "A novel hybrid active-passive pixel with correlated double sampling CMOS readout circuit for medical x-ray imaging"; dated May 2008 (4 pages).
- Safavian et al.: "Self-compensated a-Si:H detector with current-mode readout circuit for digital X-ray fluoroscopy"; dated Aug. 2005 (4 pages).
- Safavian et al.: "TFT active image sensor with current-mode readout circuit for digital x-ray fluoroscopy [5969D-82]"; dated Sep. 2005 (9 pages).
- Safavian et al.: "Three-TFT image sensor for real-time digital X-ray imaging"; dated Feb. 2, 2006 (2 pages).
- Search Report for Taiwan Invention Patent Application No. 093128894 dated May 1, 2012. (1 page).

(56)

References Cited

OTHER PUBLICATIONS

Search Report for Taiwan Invention Patent Application No. 94144535 dated Nov. 1, 2012. (1 page).

Singh, et al., "Current Conveyor: Novel Universal Active Block", Samriddhi, S-JPSET vol. I, Issue 1, 2010, pp. 41-48 (12EPPT).

Smith, Lindsay I., "A tutorial on Principal Components Analysis," dated Feb. 26, 2001 (27 pages).

Spindler et al., System Considerations for RGBW OLED Displays, Journal of the SID 14/1, 2006, pp. 37-48.

Stewart M. et al., "polysilicon TFT technology for active matrix oled displays" IEEE transactions on electron devices, vol. 48, No. 5, dated May 2001 (7 pages).

Vygranenko et al.: "Stability of indium-oxide thin-film transistors by reactive ion beam assisted deposition"; dated 2009.

Wang et al.: "Indium oxides by reactive ion beam assisted evaporation: From material study to device application"; dated Mar. 2009 (6 pages).

Yi He et al., "Current-Source a-Si:H Thin Film Transistor Circuit for Active-Matrix Organic Light-Emitting Displays", IEEE Electron Device Letters, vol. 21, No. 12, Dec. 2000, pp. 590-592.

Yu, Jennifer: "Improve OLED Technology for Display", Ph.D. Dissertation, Massachusetts Institute of Technology, Sep. 2008 (151 pages).

International Search Report for Application No. PCT/IB2014/058244, Canadian Intellectual Property Office, dated Apr. 11, 2014; (6 pages).

International Search Report for Application No. PCT/IB2014/059753, Canadian Intellectual Property Office, dated Jun. 23, 2014; (6 pages).

Written Opinion for Application No. PCT/IB2014/059753, Canadian Intellectual Property Office, dated Jun. 12, 2014 (6 pages).

International Search Report for Application No. PCT/IB2014/060879, Canadian Intellectual Property Office, dated Jul. 17, 2014 (3 pages).

Extended European Search Report for Application No. EP 14158051.4, dated Jul. 29, 2014, (4 pages).

Office Action in Chinese Patent Invention No. 201180008188.9, dated Jun. 4, 2014 (17 pages) (w/English translation).

A current mode comparator for digital calibration of amorphous silicon amolded displays. IEEE Transactions on circuits and systems: Express briefs cols. 55 No. 7, Chaji G. Reza et al., Jul. 2008, 6 pages.

* cited by examiner




FIG. 1




FIG. 2A




FIG. 2B




FIG. 3




FIG. 4A




FIG. 4B




FIG. 4C




FIG. 5A




FIG. 5B




FIG. 6




FIG. 7




FIG. 8




FIG. 9

SYSTEM AND METHODS FOR AGING COMPENSATION IN AMOLED DISPLAYS

PRIORITY CLAIM

This application is a continuation of U.S. patent application Ser. No. 14/477,971, filed Sep. 5, 2014, now allowed, which is a divisional of and claims priority to U.S. patent application Ser. No. 12/956,842, filed Nov. 30, 2010, now U.S. Pat. No. 8,914,246, which claims priority to Canadian Application No. 2,688,870, filed Nov. 30, 2009, each of which is hereby incorporated by reference herein in its entirety.

COPYRIGHT

A portion of the disclosure of this patent document contains material which is subject to copyright protection. The copyright owner has no objection to the facsimile reproduction by anyone of the patent disclosure, as it appears in the Patent and Trademark Office patent files or records, but otherwise reserves all copyright rights whatsoever.

FIELD OF THE INVENTION

The present invention generally relates to active matrix organic light emitting device (AMOLED) displays, and particularly determining aging conditions requiring compensation for the pixels of such displays.

BACKGROUND

Currently, active matrix organic light emitting device ("AMOLED") displays are being introduced. The advantages of such displays include lower power consumption, manufacturing flexibility and faster refresh rate over conventional liquid crystal displays. In contrast to conventional liquid crystal displays, there is no backlighting in an AMOLED display as each pixel consists of different colored OLEDs emitting light independently. The OLEDs emit light based on current supplied through a drive transistor. The drive transistor is typically a thin film transistor (TFT). The power consumed in each pixel has a direct relation with the magnitude of the generated light in that pixel.

The drive-in current of the drive transistor determines the pixel's OLED luminance. Since the pixel circuits are voltage programmable, the spatial-temporal thermal profile of the display surface changing the voltage-current characteristic of the drive transistor impacts the quality of the display. The rate of the short-time aging of the thin film transistor devices is also temperature dependent. Further the output of the pixel is affected by long term aging of the drive transistor. Proper corrections can be applied to the video stream in order to compensate for the unwanted thermal-driven visual effects. Long term aging of the drive transistor may be properly determined via calibrating the pixel against stored data of the pixel to determine the aging effects. Accurate aging data is therefore necessary throughout the lifetime of the display device.

Currently, displays having pixels are tested prior to shipping by powering all the pixels at full brightness. The array of pixels is then optically inspected to determine whether all of the pixels are functioning. However, optical inspection fails to detect electrical faults that may not manifest themselves in the output of the pixel. The baseline data for pixels is based on design parameters and characteristics of the

pixels determined prior to leaving the factory but this does not account for the actual physical characteristics of the pixels in themselves.

Various compensation systems use a normal driving scheme where a video frame is always shown on the panel and the OLED and TFT circuitries are constantly under electrical stress. Moreover, pixel calibration (data replacement and measurement) of each sub-pixel occurs during each video frame by changing the grayscale value of the active sub-pixel to a desired value. This causes a visual artifact of seeing the measured sub-pixel during the calibration. It may also worsen the aging of the measured sub-pixel, since the modified grayscale level is kept on the sub-pixel for the duration of the entire frame.

Therefore, there is a need for techniques to provide accurate measurement of the display temporal and spatial information and ways of applying this information to improve display uniformity in an AMOLED display. There is also a need to determine baseline measurements of pixel characteristics accurately for aging compensation purposes.

SUMMARY

Aspects of the present disclosure include a voltage-programmed display panel allowing measurement of effects on pixels in the panel. The panel includes a plurality of active pixels forming the display panel to display an image under an operating condition. The active pixels are each coupled to a supply line and a programming line. A reference pixel is coupled to the supply line and the programming line. The reference pixel has a controlled condition independent of the operating condition of the active pixels. A controller is coupled to each of the plurality of active pixels and reference pixel. The controller causes a test voltage to be applied to the plurality of active pixels and the reference pixel. The controller compares an output of the reference pixel in comparison with the output of one of the plurality of active pixels.

Another example is a method of determining a baseline value for aging effects of a transistor based display including a plurality of light emitting device pixels. Each of the pixels has a programming voltage input to determine brightness. A set programming voltage is input to a device under test of the display. An output current is generated based on the set programming voltage input. A first reference current and a variable second reference current is compared with the output current via a current comparator until the first reference current and the combination of the second reference current and the output current is the same. The output current value based on the value of the second reference current is determined when the combination of the second reference current and the output current is the same as the first reference current.

Another example is a method for determining data for production of a display device having a plurality of pixels. A test signal is applied to each of the plurality of pixels. Voltage and current characteristics are measured for each of the pixels. It is determined whether anomalies exist for each of the pixels. Anomaly data is read from the pixels with anomalies. The anomaly data from the pixels demonstrating anomalies is stored.

Another example is a display system including an array of pixels to display images. A memory includes characteristic data. A profile generator is coupled to the memory to generate a plurality of luminance profiles based on the characteristic data. A controller is coupled to the profile

generator and the array of pixels to change the luminance of the array of pixels according to a selected one of the plurality of luminance profiles.

The foregoing and additional aspects and embodiments of the present invention will be apparent to those of ordinary skill in the art in view of the detailed description of various embodiments and/or aspects, which is made with reference to the drawings, a brief description of which is provided next.

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing and other advantages of the invention will become apparent upon reading the following detailed description and upon reference to the drawings.

FIG. 1 is a block diagram of a AMOLED display with reference pixels to correct data for parameter compensation control;

FIG. 2A is a block diagram of a driver circuit of one of the pixels of the AMOLED that may be tested for aging parameters;

FIG. 2B is a circuit diagram of a driver circuit of one of the pixels of the AMOLED;

FIG. 3 is a block diagram for a system to determine one of the baseline aging parameters for a device under test;

FIG. 4A is a block diagram of the current comparator in FIG. 3 for comparison of a reference current level to the device under test for use in aging compensation;

FIG. 4B is a detailed circuit diagram of the current comparator in FIG. 4A;

FIG. 4C is a detailed block diagram of the device under test in FIG. 3 coupled to the current comparator in FIG. 4A;

FIG. 5A is a signal timing diagram of the signals for the current comparator in FIGS. 3-4 in the process of determining the current output of a device under test;

FIG. 5B is a signal timing diagram of the signals for calibrating the bias current for the current comparator in FIGS. 3-4;

FIG. 6 is a block diagram of a reference current system to compensate for the aging of the AMOLED display in FIG. 1;

FIG. 7 is a block diagram of a system for the use of multiple luminance profiles for adjustment of a display in different circumstances;

FIG. 8 are frame diagrams of video frames for calibration of pixels in a display; and

FIG. 9 is a graph showing the use of a small current applied to a reference pixel for more accurate aging compensation.

While the invention is susceptible to various modifications and alternative forms, specific embodiments have been shown by way of example in the drawings and will be described in detail herein. It should be understood, however, that the invention is not intended to be limited to the particular forms disclosed. Rather, the invention is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the invention as defined by the appended claims.

DETAILED DESCRIPTION

FIG. 1 is an electronic display system 100 having an active matrix area or pixel array 102 in which an array of active pixels 104a-d are arranged in a row and column configuration. For ease of illustration, only two rows and columns are shown. External to the active matrix area which is the pixel array 102 is a peripheral area 106 where

peripheral circuitry for driving and controlling the area of the pixel array 102 are disposed. The peripheral circuitry includes a gate or address driver circuit 108, a source or data driver circuit 110, a controller 112, and an optional supply voltage (e.g., Vdd) driver 114. The controller 112 controls the gate, source, and supply voltage drivers 108, 110, 114. The gate driver 108, under control of the controller 112, operates on address or select lines SEL[i], SEL[i+1], and so forth, one for each row of pixels 104 in the pixel array 102.

In pixel sharing configurations described below, the gate or address driver circuit 108 can also optionally operate on global select lines GSEL[j] and optionally /GSEL[j], which operate on multiple rows of pixels 104a-d in the pixel array 102, such as every two rows of pixels 104a-d. The source driver circuit 110, under control of the controller 112, operates on voltage data lines Vdata[k], Vdata[k+1], and so forth, one for each column of pixels 104a-d in the pixel array 102. The voltage data lines carry voltage programming information to each pixel 104 indicative of brightness of each light emitting device in the pixel 104. A storage element, such as a capacitor, in each pixel 104 stores the voltage programming information until an emission or driving cycle turns on the light emitting device. The optional supply voltage driver 114, under control of the controller 112, controls a supply voltage (EL_Vdd) line, one for each row of pixels 104a-d in the pixel array 102.

The display system 100 may also include a current source circuit, which supplies a fixed current on current bias lines. In some configurations, a reference current can be supplied to the current source circuit. In such configurations, a current source control controls the timing of the application of a bias current on the current bias lines. In configurations in which the reference current is not supplied to the current source circuit, a current source address driver controls the timing of the application of a bias current on the current bias lines.

As is known, each pixel 104a-d in the display system 100 needs to be programmed with information indicating the brightness of the light emitting device in the pixel 104a-d. A frame defines the time period that includes a programming cycle or phase during which each and every pixel in the display system 100 is programmed with a programming voltage indicative of a brightness and a driving or emission cycle or phase during which each light emitting device in each pixel is turned on to emit light at a brightness commensurate with the programming voltage stored in a storage element. A frame is thus one of many still images that compose a complete moving picture displayed on the display system 100. There are at least two schemes for programming and driving the pixels: row-by-row, or frame-by-frame. In row-by-row programming, a row of pixels is programmed and then driven before the next row of pixels is programmed and driven. In frame-by-frame programming, all rows of pixels in the display system 100 are programmed first, and all of the frames are driven row-by-row. Either scheme can employ a brief vertical blanking time at the beginning or end of each frame during which the pixels are neither programmed nor driven.

The components located outside of the pixel array 102 may be disposed in a peripheral area 106 around the pixel array 102 on the same physical substrate on which the pixel array 102 is disposed. These components include the gate driver 108, the source driver 110 and the optional supply voltage control 114. Alternately, some of the components in the peripheral area can be disposed on the same substrate as the pixel array 102 while other components are disposed on a different substrate, or all of the components in the peripheral area can be disposed on a substrate different from the

substrate on which the pixel array **102** is disposed. Together, the gate driver **108**, the source driver **110**, and the supply voltage control **114** make up a display driver circuit. The display driver circuit in some configurations may include the gate driver **108** and the source driver **110** but not the supply voltage control **114**.

The display system **100** further includes a current supply and readout circuit **120**, which reads output data from data output lines, VD [k], VD [k+1], and so forth, one for each column of pixels **104a**, **104c** in the pixel array **102**. A set of column reference pixels **130** is fabricated on the edge of the pixel array **102** at the end of each column such as the column of pixels **104a** and **104c**. The column reference pixels **130** also may receive input signals from the controller **112** and output data signals to the current supply and readout circuit **120**. The column reference pixels **130** include the drive transistor and an OLED but are not part of the pixel array **102** that displays images. As will be explained below, the column reference pixels **130** are not driven for most of the programming cycle because they are not part of the pixel array **102** to display images and therefore do not age from the constant application of programming voltages as compared to the pixels **104a** and **104c**. Although only one column reference pixel **130** is shown in FIG. 1, it is to be understood that there may be any number of column reference pixels although two to five such reference pixels may be used for each column of pixels in this example. Each row of pixels in the array **102** also includes row reference pixels **132** at the ends of each row of pixels **104a-d** such as the pixels **104a** and **104b**. The row reference pixels **132** include the drive transistor and an OLED but are not part of the pixel array **102** that displays images. As will be explained the row reference pixels **132** have the function of providing a reference check for luminance curves for the pixels which were determined at the time of production.

FIG. 2A shows a block diagram of a driver circuit **200** for the pixel **104** in FIG. 1. The driver circuit **200** includes a drive device **202**, an organic light emitting device (“OLED”) **204**, a storage element **206**, and a switching device **208**. A voltage source **212** is coupled to the drive transistor **206**. A select line **214** is coupled to the switching device to activate the driver circuit **200**. A data line **216** allows a programming voltage to be applied to the drive device **202**. A monitoring line **218** allows outputs of the OLED **204** and or the drive device **202** to be monitored. Alternatively, the monitor line **218** and the data line **216** may be merged into one line (i.e. Data/Mon) to carry out both the programming and monitoring functions through that single line.

FIG. 2B shows one example of a circuit to implement the driver circuit **200** in FIG. 2A. As shown in FIG. 2B, the drive device **202** is a drive transistor which is a thin film transistor in this example that is fabricated from amorphous silicon. The storage element **206** is a capacitor in this example. The switching device **208** includes a select transistor **226** and a monitoring transistor **230** that switch the different signals to the drive circuit **200**. The select line **214** is coupled to the select transistor **226** and the monitoring transistor **230**. During the readout time, the select line **214** is pulled high. A programming voltage may be applied via the programming voltage input line **216**. A monitoring voltage may be read from the monitoring line **218** that is coupled to the monitoring transistor **230**. The signal to the select line **214** may be sent in parallel with the pixel programming cycle. As will be explained below, the driver circuit **200** may be periodically tested by applying reference voltage to the gate of the drive transistor.

There are several techniques for extracting electrical characteristics data from a device under test (DUT) such as the display system **100**. The device under test (DUT) can be any material (or device) including (but not limited to) a light emitting diode (LED), or OLED. This measurement may be effective in determining the aging (and/or uniformity) of an OLED in a panel composed of an array of pixels such as the array **102** in FIG. 1. This extracted data can be stored in lookup tables as raw or processed data in memory in the controller **112** in FIG. 1. The lookup tables may be used to compensate for any shift in the electrical parameters of the backplane (e.g., threshold voltage shift) or OLED (e.g., shift in the OLED operating voltage). Despite using an OLED display in FIG. 1 in these examples, the techniques described herein may be applied to any display technology including but not limited to OLED, liquid crystal displays (LCD), light emitting diode displays, or plasma displays. In the case of OLED, the electrical information measured may provide an indication of any aging that may have occurred.

Current may be applied to the device under test and the output voltage may be measured. In this example, the voltage is measured with an analog to digital converter (ADC). A higher programming voltage is necessary for a device such as an OLED that ages as compared to the programming voltage for a new OLED for the same output. This method gives a direct measurement of that voltage change for the device under test. Current flow can be in any direction but the current is generally fed into the device under test (DUT) for illustration purposes.

FIG. 3 is a block diagram of a comparison system **300** that may be used to determine a baseline value for a device under test **302** to determine the effects of aging on the device under test **302**. The comparison system uses two reference currents to determine the baseline current output of the device under test **302**. The device under test **302** may be either the drive transistor such as the drive transistor **202** in FIG. 2B or an OLED such as the OLED **204** in FIG. 2B. Of course other types of display devices may also be tested using the system shown in FIG. 3. The device under test **302** has a programming voltage input **304** that is held at a constant level to output a current. A current comparator **306** has a first reference current input **308** and a second reference current input **310**. The reference current input **308** is coupled to a first reference current source **312** via a switch **314**. The second current input **310** of the comparator **306** is coupled to a second reference current source **316** via a switch **318**. An output **320** of the device under test **302** is also coupled to the second current input **310**. The current comparator **306** includes a comparison output **322**.

By keeping the voltage to the input **304** constant, the output current of the device under test **302** is also constant. This current depends on the characteristics of the device under test **302**. A constant current is established for the first reference current from the first reference current source **312** and via the switch **314** the first reference current is applied to the first input **308** of the current comparator **306**. The second reference current is adjusted to different levels with each level being connected via the switch **318** to the second input **310** of the comparator **306**. The second reference current is combined with the output current of the device under test **302**. Since the first and second reference current levels are known, the difference between the two reference current levels from the output **322** of the current comparator **306** is the current level of the device under test **302**. The resulting output current is stored for the device under test **302** and compared with the current measured based on the

same programming voltage level periodically during the lifetime operation of the device under test 302 to determine the effects of aging.

The resulting determined device current may be stored in look up tables for each device in the display. As the device under test 302 ages, the current will change from the expected level and therefore the programming voltage may be changed to compensate for the effects of aging based on the base line current determined through the calibration process in FIG. 3.

FIG. 4A is a block diagram of a current comparator circuit 400 that may be used to compare reference currents with a device under test 302 such as in FIG. 3. The current comparator circuit 400 has a control junction 402 that allows various current inputs such as two reference currents and the current of the device under test such as the pixel driver circuit 200 in FIG. 1. The current may be a positive current when the current of the drive transistor 202 is compared or negative when the current of the OLED 204 is compared. The current comparator circuit 400 also includes an operational trans-resistance amplifier circuit 404, a preamplifier 406 and a voltage comparator circuit 408 that produces a voltage output 410. The combined currents are input to the operational trans-resistance amplifier circuit 404 and converted to a voltage. The voltage is fed to the preamplifier and the voltage comparator circuit 408 determines whether the difference in currents is positive or negative and outputs a respective one or a zero value.

FIG. 4B is a circuit diagram of the components of the example current comparator system 400 in FIG. 4A that may be used to compare the currents as described in the process in FIG. 3 for a device under test such as the device 302. The operational trans-resistance amplifier circuit 404 includes an operational amplifier 412, a first voltage input 414 (CMP_VB), a second voltage input 416 (CMP_VB), a current input 418, and a bias current source 420. The operational trans-resistance amplifier circuit 404 also includes two calibration switches 424 and 426. As will be explained below, various currents such as the current of the device under test 302, a variable first reference current and a fixed second reference current as shown in FIG. 3 are coupled to the current input 418 in this example. Of course, the fixed second reference current may be set to zero if desired.

The first reference current input is coupled to the negative input of the operational amplifier 412. The negative input of the operational amplifier 412 is therefore coupled to the output current of the device under test 302 in FIG. 3 as well as one or two reference currents. The positive input of the operational amplifier 412 is coupled to the first voltage input 414. The output of the operational amplifier 412 is coupled to the gate of a transistor 432. A resistor 434 is coupled between the negative input of the operational amplifier 412 and the source of the transistor 432. A resistor 436 is coupled between the source of the transistor 432 and the second voltage input 416.

The drain of the transistor 432 is coupled directly to the drain of a transistor 446 and via the calibration switch 426 to the gate. A sampling capacitor 444 is coupled between the gate of the transistor 446 and a voltage supply rail 411 through a switch 424. The source of the 446 is also coupled to the supply rail 411. The drain and gate of the transistor 446 are coupled to the gate terminals of transistors 440 and 442, respectively. The sources of the transistors 440 and 442 are tied together and coupled to a bias current source 438. The drains of the transistors 442 and 440 are coupled to respective transistors 448 and 450 which are wired in

diode-connected configuration to the supply voltage rail 411. As shown in FIG. 4B, the transistors 440, 442, 448 and 450 and the bias current source 438 are parts of the preamplifier 406.

The drains of the transistors 442 and 440 are coupled to the gates of the respective transistors 452 and 454. The drains of the transistors 452 and 454 are coupled to the transistors 456 and 458. The drains of the transistors 456 and 458 are coupled to the respective sources of the transistors 460 and 462. The drain and gate terminals of the transistors 460 and 462 are coupled to the respective drain and gate terminals of the transistors 464 and 466. The source terminals of the transistors 464 and 466 are coupled to the supply voltage rail 411. The sources and drains of the transistors 464 and 466 are tied to the respective sources and drains of transistors 468 and 470. The gates of the transistors 456 and 458 are tied to an enable input 472. The enable input 472 is also tied to the gates of dual transistors 468 and 470.

A buffer circuit 474 is coupled to the drain of the transistor 462 and the gate of the transistor 460. The output voltage 410 is coupled to a buffer circuit 476 which is coupled to the drain of the transistor 460 and the gate of the transistor 462. The buffer circuit 474 is used to balance the buffer 476. The transistors 452, 454, 456, 458, 460, 462, 464, 466, 468 and 470 and the buffer circuits 474 and 476 make up the voltage comparator circuit 408.

The current comparator system 400 may be based on any integrated circuit technology including but not limited to CMOS semiconductor fabrication. The components of the current comparator system 400 are CMOS devices in this example. The values for the input voltages 414 and 416 are determined for a given reference current level from the first current input 418 (I_{ref}). In this example, the voltage levels for both the input voltages 414 and 416 are the same. The voltage inputs 414 and 416 to the operational amplifier 412 may be controlled using a digital to analog converter (DAC) device which is not shown in FIG. 4. Level shifters can also be added if the voltage ranges of the DACs are insufficient. The bias current may originate from a voltage controlled current source such as a transimpedance amplifier circuit or a transistor such as a thin film transistor.

FIG. 4C shows a detailed block diagram of one example of a test system such as the system 300 shown in FIG. 3. The test system in FIG. 4C is coupled to a device under test 302 which may be a pixel driver circuit such as the pixel driver circuit 200 shown in FIG. 2. In this example, all of the driver circuits for a panel display are tested. A gate driver circuit 480 is coupled to the select lines of all of the driver circuits. The gate driver circuit 480 includes an enable input, which in this example enables the device under test 302 when the signal on the input is low.

The device under test 302 receives a data signal from a source driver circuit 484. The source circuit 484 may be a source driver such as the source driver 120 in FIG. 1. The data signal is a programming voltage of a predetermined value. The device under test 302 outputs a current on a monitoring line when the gate driver circuit 480 enables the device. The output of the monitoring line from the device under test 302 is coupled to an analog multiplexer circuit 482 that allows multiple devices to be tested. In this example, the analog multiplexer circuit 482 allows multiplexing of 210 inputs, but of course any number of inputs may be multiplexed.

The signal output from the device under test 302 is coupled to the reference current input 418 of the operational trans-resistance amplifier circuit 404. In this example a variable reference current source is coupled to the current

input **418** as described in FIG. 3. In this example, there is no fixed reference current such as the first reference current source in FIG. 3. The value of first reference current source in FIG. 3 in this example is therefore considered to be zero.

FIG. 5A is a timing diagram of the signals for the current comparator shown in FIGS. 4A-4C. The timing diagram in FIG. 5A shows a gate enable signal **502** to the gate driver **480** in FIG. 4C, a CSE enable signal **504** that is coupled to the analog multiplexer **482**, a current reference signal **506** that is produced by a variable reference current source that is set at a predetermined level for each iteration of the test process and coupled to the current input **418**, a calibration signal **508** that controls the calibration switch **426**, a calibration signal **510** that controls the calibration switch **424**, a comparator enable signal **512** that is coupled to the enable input **472**, and the output voltage **514** over the output **410**. The CSE enable signal **504** is kept high to ensure that any leakage on the monitoring line of the device under test **302** is eliminated in the final current comparison.

In a first phase **520**, the gate enable signal **502** is pulled high and therefore the output of the device under test **302** in FIG. 4C is zero. The only currents that are input to the current comparator **400** are therefore leakage currents from the monitoring line of the device under test **302**. The output of the reference current **506** is also set to zero such that the optimum quiescent condition of the transistors **432** and **436** in FIGS. 4B and 4C is minimally affected only by line leakage or the offset of the readout circuitry. The calibration signal **508** is set high causing the calibration switch **426** to close. The calibration signal **510** is set high to cause the calibration switch **424** to close. The comparator enable signal **512** is set low and therefore the output from the voltage comparator circuit **408** is reset to a logical one. The leakage current is therefore input to the current input **418** and a voltage representing the leakage current of the monitoring line on the panel is stored on the capacitor **444**.

In a second phase **522**, the gate enable signal **502** is pulled low and therefore the output of the device under test **302** produces an unknown current at a set programming voltage input from the source circuit **484**. The current from the device under test **302** is input through the current input **418** along with the reference current **506** which is set at a first predetermined value and opposite the direction of the current of the device under test. The current input **418** therefore is the difference between the reference current **506** and the current from the device under test **302**. The calibration signal **510** is momentarily set low to open the switch **424**. The calibration signal **508** is then set low and therefore the switch **426** is opened. The calibration signal **510** to the switch **424** is then set high to close the switch **424** to stabilize the voltage on the gate terminal of the transistor **446**. The comparator enable signal **512** remains low and therefore there is no output from the voltage comparator circuit **408**.

In a third phase **524**, the comparator enable signal **512** is pulled high and the voltage comparator **408** produces an output on the voltage output **410**. In this example, a positive voltage output logical one for the output voltage signal **514** indicates a positive current therefore showing that the current of the device under test **302** is greater than the predetermined reference current. A zero voltage on the voltage output **410** indicates a negative current showing that the current of the device under test **302** is less than the predetermined level of the reference current. In this manner, any difference between the current of the device under test and the reference current is amplified and detected by the current comparator circuit **400**. The value of the reference current is

then shifted based on the result to a second predetermined level and the phases **520**, **522** and **524** are repeated. Adjusting the reference current allows the comparator circuit **400** to be used by the test system to determine the current output by the device under test **302**.

FIG. 5B is a timing diagram of the signals applied to the test system shown in FIG. 4C in order to determine an optimal bias current value for the bias current source **420** in FIG. 4B for the operational trans-resistance amplifier circuit **404**. In order to achieve the maximum signal-to-noise ratio (SNR) for the current comparator circuit **400** it is essential to calibrate the current comparator. The calibration is achieved by means of fine tuning of the bias current source **420**. The optimum bias current level for the bias current source **420** minimizes the noise power during the measurement of a pixel which is also a function of the line leakage. Accordingly, it is required to capture the line leakage during the calibration of the current comparator.

The timing diagram in FIG. 5B shows a gate enable signal **552** to the gate driver **480** in FIG. 4C, a CSE enable signal **554** that is coupled to the analog multiplexer **482**, a current reference signal **556** that is produced by a variable reference current source that is set at a predetermined level for each iteration of the calibration process and coupled to the current input **418**, a calibration signal **558** that controls the calibration switch **426**, a comparator enable signal **560** that is coupled to the enable input **472**, and the output voltage **562** over the output **410**.

The CSE enable signal **554** is kept high to ensure that any leakage on the line is included in the calibration process. The gate enable signal **552** is also kept high in order to prevent the device under test **302** from outputting current from any data inputs. In a first phase **570**, the calibration signal **556** is pulled high thereby closing the calibration switch **426**. Another calibration signal is pulled high to close the calibration switch **424**. The comparator enable signal **558** is pulled low in order to reset the voltage output from the voltage comparator circuit **408**. Any leakage current from the monitoring line of the device under test **302** is converted to a voltage which is stored on the capacitor **444**.

A second phase **572** occurs when the calibration signal to the switch **424** is pulled low and then the calibration signal **556** is pulled low thereby opening the switch **426**. The signal to the switch **424** is then pulled high closing the switch **424**. A small current is output from the reference current source to the current input **418**. The small current value is a minimum value corresponding to the minimum detectable signal (MDS) range of the current comparator **400**.

A third phase **574** occurs when the comparator enable signal **560** is pulled high thereby allowing the voltage comparator circuit **408** to read the inputs. The output of the voltage comparator circuit **408** on the output **410** should be positive indicating a positive current comparison with the leakage current.

A fourth phase **576** occurs when the calibration signal **556** is pulled high again thereby closing the calibration switch **426**. The comparator enable signal **558** is pulled low in order to reset the voltage output from the voltage comparator circuit **408**. Any leakage current from the monitoring line of the device under test **302** is converted to a voltage which is stored on the capacitor **444**.

A fifth phase **578** occurs when the calibration signal to the switch **424** is pulled low and then the calibration signal **556** is pulled low thereby opening the switch **426**. The signal to the switch **424** is then pulled high closing the switch **424**. A small current is output from the reference current source to the current input **418**. The small current value is a minimum

value corresponding to the minimum detectable signal (MDS) range of the current comparator 400 but is a negative current as opposed to the positive current in the second phase 572.

A sixth phase 580 occurs when the comparator enable signal 560 is pulled high thereby allowing the voltage comparator circuit 408 to read the inputs. The output of the voltage comparator circuit 408 on the output 410 should be zero indicating a negative current comparison with the leakage current.

The phases 570, 572, 574, 576, 578 and 580 are repeated. By adjusting the value of the bias current, eventually the rate of the valid output voltage toggles between a one and a zero will maximize indicating an optimal bias current value.

FIG. 6 is a block diagram of the compensation components of the controller 112 of the display system 100 in FIG. 1. The compensation components include an aging extraction unit 600, a backplane aging/matching module 602, a color/share gamma correction module 604, an OLED aging memory 606, and a compensation module 608. The backplane with the electronic components for driving the display system 100 may be any technology including (but not limited to) amorphous silicon, poly silicon, crystalline silicon, organic semiconductors, oxide semiconductors. Also, the display system 100 may be any display material (or device) including (but not limited to) LEDs, or OLEDs.

The aging extraction unit 600 is coupled to receive output data from the array 102 based on inputs to the pixels of the array and corresponding outputs for testing the effects of aging on the array 102. The aging extraction unit 600 uses the output of the column reference pixels 130 as a baseline for comparison with the output of the active pixels 104a-d in order to determine the aging effects on each of the pixels 104a-d on each of the columns that include the respective column reference pixels 130. Alternatively, the average value of the pixels in the column may be calculated and compared to the value of the reference pixel. The color/share gamma correction module 604 also takes data from the column reference pixels 130 to determine appropriate color corrections to compensate from aging effects on the pixels. The baseline to compare the measurements for the comparison may be stored in lookup tables on the memory 606. The backplane aging/matching module 602 calculates adjustments for the components of the backplane and electronics of the display. The compensation module 608 is provided inputs from the extraction unit 600 the backplane/matching module 602 and the color/share gamma correction module 604 in order to modify programming voltages to the pixels 104a-d in FIG. 1 to compensate for aging effects. The compensation module 608 accesses the look up table for the base data for each of the pixels 104a-d on the array 102 to be used in conjunction with calibration data. The compensation module 608 modifies the programming voltages to the pixels 104a-d accordingly based on the values in the look up table and the data obtained from the pixels in the display array 102.

The controller 112 in FIG. 2 measures the data from the pixels 104a-d in the display array 102 in FIG. 1 to correctly normalize the data collected during measurement. The column reference pixels 130 assist in these functions for the pixels on each of the columns. The column reference pixels 130 may be located outside the active viewing area represented by the pixels 104a-d in FIG. 1, but such reference pixels may also be embedded within the active viewing areas. The column reference pixels 130 are preserved with a controlled condition such as being un-aged, or aged in a predetermined fashion, to provide offset and cancellation

information for measurement data of the pixels 104a-d in the display array 102. This information helps the controller 112 cancel out common mode noise from external sources such as room temperature, or within the system itself such as leakage currents from other pixels 104a-d. Using a weighted average from several pixels on the array 102 may also provide information on panel-wide characteristics to address problems such as voltage drops due to the resistance across the panel, i.e. current/resistance (IR) drop. Information from the column reference pixels 130 being stressed by a known and controlled source may be used in a compensation algorithm run by the compensation module 608 to reduce compensation errors occurring from any divergence. Various column reference pixels 130 may be selected using the data collected from the initial baseline measurement of the panel. Bad reference pixels are identified, and alternate reference pixels 130 may be chosen to insure further reliability. Of course it is to be understood that the row reference pixels 132 may be used instead of the column reference pixels 130 and the row may be used instead of columns for the calibration and measurement.

There are various compensation methods that may make use of the column reference pixels 130 in FIG. 1. For example in thin film transistor measurement, the data value required for the column reference pixel 130 to output a current is subtracted from the data value of a pixel 104a-d in the same column of pixels in the active area (the pixel array 102) to output the same current. The measurement of both the column reference pixels 130 and pixels 104a-d may occur very close in time, e.g. during the same video frame. Any difference in current indicates the effects of aging on the pixels 104a-d. The resulting value may be used by the controller 112 to calculate the appropriate adjustment to programming voltage to the pixels 104a-d to maintain the same luminance during the lifetime of the display. Another use of a column reference pixel 130 is to provide a reference current for the other pixels 104 to serve as a baseline and determine the aging effects on the current output of those pixels. The reference pixels 130 may simplify the data manipulation since some of the common mode noise cancellation is inherent in the measurement because the reference pixels 130 have common data and supply lines as the active pixels 104. The row reference pixels 132 may be measured periodically for the purpose of verifying that luminance curves for the pixels that are stored for use of the controller for compensation during display production are correct.

A measurement of the drive transistors and OLEDs of all of the driver circuits such as the driver circuit 200 in FIG. 2 on a display before shipping the display take 60-120 seconds for a 1080p display, and will detect any shorted and open drive transistors and OLEDs (which result in stuck or unlit pixels). It will also detect non-uniformities in drive transistor or OLED performance (which result in luminance non-uniformities). This technique may replace optical inspection by a digital camera, removing the need for this expensive component in the production facility. AMOLEDs that use color filters cannot be fully inspected electrically, since color filters are a purely optical component. In this case, technology that compensates for aging such as Max-Life™ from Ignis may be useful in combination with an optical inspection step, by providing extra diagnostic information and potentially reducing the complexity of optical inspection.

These measurements provide more data than an optical inspection may provide. Knowing whether a point defect is due to a short or open driver transistor or a short or open

OLED may help to identify the root cause or flaw in the production process. For example, the most common cause for a short circuit OLED is particulate contamination that lands on the glass during processing, shorting the anode and cathode of the OLED. An increase in OLED short circuits could indicate that the production line should be shut down for chamber cleaning, or searches could be initiated for new sources of particles (changes in processes, or equipment, or personnel, or materials).

A relaxation system for compensating for aging effects such as the MaxLife™ system may correct for process non-uniformities, which increases yield of the display. However the measured current and voltage relationships or characteristics in the TFT or OLED are useful for diagnostics as well. For example, the shape of an OLED current-voltage characteristic may reveal increased resistance. A likely cause might be variations in the contact resistance between the transistor source/drain metal and the ITO (in a bottom emission AMOLED). If OLEDs in a corner of a display showed a different current-voltage characteristic, a likely cause could be mask misalignment in the fabrication process.

A streak or circular area on the display with different OLED current-voltage characteristics could be due to defects in the manifolds used to disperse the organic vapor in the fabrication process. In one possible scenario, a small particle of OLED material may flake from an overhead shield and land on the manifold, partially obstructing the orifice. The measurement data would show the differing OLED current-voltage characteristics in a specific pattern which would help to quickly diagnose the issue. Due to the accuracy of the measurements (for example, the 4.8 inch display measures current with a resolution of 100 nA), and the measurement of the OLED current-voltage characteristic itself (instead of the luminance), variations can be detected that are not visible with optical inspection.

This high-accuracy data may be used for statistical process control, identifying when a process has started to drift outside of its control limits. This may allow corrective action to be taken early (in either the OLED or drive transistor (TFT) fabrication process), before defects are detected in the finished product. The measurement sample is maximized since every TFT and OLED on every display is sampled.

If the drive transistor and the OLED are both functioning properly, a reading in the expected range will be returned for the components. The pixel driver circuit requires that the OLED be off when the drive transistor is measured (and vice-versa), so if the drive transistor or OLED is in a short circuit, it will obscure the measurement of the other. If the OLED is a short circuit (so the current reading is MAX), the data will show the drive transistor is an open circuit (current reading MIN) but in reality, the drive transistor could be operational or an open circuit. If extra data about the drive transistor is needed, temporarily disconnecting the supply voltage (EL_VSS) and allowing it to float will yield a correct drive transistor measurement indicating whether the TFT is actually operational or in an open circuit.

In the same way, if the drive transistor is a short circuit, the data will show the OLED is an open circuit (but the OLED could be operational or an open circuit). If extra data about the OLED is needed, disconnecting the supply voltage (EL_VDD) and allowing it to float will yield a correct OLED measurement indicating whether the OLED is actually operational or in an open circuit.

If both the OLED and TFT in a pixel behave as a short circuit, one of the elements in the pixel (likely the contact between TFT and OLED) will quickly burn out during the

measurement, causing an open circuit, and moving to a different state. These results are summarized in Table 1 below.

TABLE 1

		OLED		
		Short	OK	Open
Drive transistor (TFT)	Short	n/a	TFT max OLED min	TFT max OLED min
	OK	TFT min OLED max	TFT OK OLED OK	TFT OK OLED min
	Open	TFT min	TFT min	TFT min
		OLED max	OLED OK	OLED min

FIG. 7 shows a system diagram of a control system 700 for controlling the brightness of a display 702 over time based on different aspects. The display 702 may be composed of an array of OLEDs or other pixel based display devices. The system 700 includes a profile generator 704 and a decision making machine 706. The profile generator 704 receives characteristics data from an OLED characteristics table 710, a backplane characteristics table 712 and a display specifications file 714. The profile generator 704 generates different luminance profiles 720a, 720b . . . 720n for different conditions. Here, to improve the power consumption, display lifetime, and image quality, the different brightness profiles 720a, 720b . . . 720n may be defined based on OLED and backplane information. Also, based on different applications, one can select different profiles from the luminance profiles 720a, 720b . . . 720n. For example, a flat brightness vs. time profile can be used for displaying video outputs such as movies whereas for brighter applications, the brightness can be drop at a defined rate. The decision making machine 706 may be software or hardware based and includes applications inputs 730, environmental parameter inputs 732, backplane aging data inputs 734 and OLED aging data inputs 736 that are factors in making adjustments in programming voltage to insure the proper brightness of the display 702.

To compensate for display aging perfectly, the short term and long term changes are separated in the display characteristics. One way is to measure a few points across the display with faster times between the measurements. As a result, the fast scan can reveal the short term effects while the normal aging extraction can reveal the long term effects.

The previous implementation of compensation systems uses a normal driving scheme, in which there was always a video frame shown on the panel and the OLED and TFT circuitries were constantly under electrical stress. Calibration of each pixel occurred during a video frame by changing the grayscale value of the active pixel to a desired value which caused a visual artifact of seeing the measured sub-pixel during the calibration. If the frame rate of the video is X, then in normal video driving, each video frame is shown on the pixel array 102 in FIG. 1 for 1/X of second and the panel is always running a video frame. In contrast, the relaxation video driving in the present example divides the frame time into four sub-frames as shown in FIG. 8. FIG. 8 is a timing diagram of a frame 800 that includes a video sub-frame 802, a dummy sub-frame 804, a relaxation sub-frame 806 and a replacement sub-frame 808.

The video sub-frame 802 is the first sub-frame which is the actual video frame. The video frame is generated the same way as normal video driving to program the entire pixel array 102 in FIG. 1 with the video data received from

the programming inputs. The dummy sub-frame **804** is an empty sub-frame without any actual data being sent to the pixel array **102**. The dummy sub-frame **804** functions to keep the same video frame displayed on the panel **102** for some time before applying the relaxation sub-frame **806**. This increases the luminance of the panel.

The relaxation sub-frame **806** is the third sub-frame which is a black frame with zero gray scale value for all of the red green blue white (RGBW) sub-pixels in the pixel array **102**. This makes the panel black and sets all of the pixels **104** to a predefined state ready for calibration and next video sub-frame insertion. The replacement sub-frame **808** is a short sub-frame generated solely for the purpose of calibration. When the relaxation sub-frame **806** is complete and the panel is black the data replacement phase starts for the next video frame. No video or blank data is sent to the pixel array **102** during this phase except for the rows with replacement data. For the non-replacement rows only the gate driver's clock is toggled to shift the token throughout the gate driver. This is done to speed up the scanning of the entire panel and also to be able to do more measurement per each frame.

Another technique is used to further alleviate the visual artifact of the measured sub-pixel during the replacement sub-frame **808**. This has been done by re-programming the measured row with black as soon as the calibration is done. This returns the sub-pixel to the same state as it was during the relaxation sub-frame **806**. However, there is still a small current going through the OLEDs in the pixels, which makes the pixel light up and become noticeable to the outside world. Therefore to re-direct the current going through OLED, the controller **112** is programmed with a non-zero value to sink the current from the drive transistor of the pixel and keep the OLED off.

Having a replacement sub-frame **808** has a drawback of limiting the time of the measurement to a small portion of the entire frame. This limits the number of sub-pixel measurements per each frame. This limitation is acceptable during the working time of the pixel array **102**. However, for a quick baseline measurement of the panel it would be a time-consuming task to measure the entire display because each pixel must be measured. To overcome this issue a baseline mode is added to the relaxation driving scheme. FIG. **8** also shows a baseline frame **820** for the driving scheme during the baseline measurement mode for the display. The baseline measurement frame **820** includes a video sub-frame **822** and a replacement sub-frame **824**. If the system is switched to the baseline mode, the driving scheme changes such that there would only be two sub-frames in a baseline frame such as the frame **820**. The video sub-frame **822** includes the normal programming data for the image. In this example, the replacement (measurement sub-frame) **824** has a longer duration than the normal replacement frame as shown in FIG. **8**. The longer sub-frame drastically increases the total number of measurements per each frame and allows more accurate measurements of the panel because more pixels may be measured during the frame time.

The steep slope of the ΔV shift (electrical aging) at the early OLED stress time results in a curve of efficiency drop versus ΔV shift that behaves differently for the low value of ΔV compared to the high ΔV ranges. This may produce a highly non-linear $\Delta\eta$ - ΔV curve that is very sensitive to initial electrical aging of the OLED or to the OLED pre-aging process. Moreover, the shape (the duration and slope) of the early ΔV shift drop can vary significantly from panel to panel due to process variations.

The use of a reference pixel and corresponding OLED is explained above. The use of such a reference pixel cancels the thermal effects on the ΔV measurements since the thermal effects affect both the active and reference pixels equally. However, instead of using an OLED that is not aging (zero stress) as a reference pixel such as the column reference pixels **130** in FIG. **1**, a reference pixel with an OLED having a low level of stress may be used. The thermal impact on the voltage is similar to the non-aging OLED, therefore the low stress OLED may still be used to remove the measurement noise due to thermal effects. Meanwhile, due to the similar manufacturing condition with the rest of OLED based devices on the same panel the slightly stressed OLED may be as a good reference to cancel the effects of process variations on the $\Delta\eta$ - ΔV curve for the active pixels in a column. The steep early ΔV shift will also be mitigated if such an OLED is used as a reference.

To use a stressed-OLED as a reference, the reference OLED is stressed with a constant low current ($1/5$ to $1/2$ of full current) and its voltage (for a certain applied current) must be used to cancel the thermal and process issues of the pixel OLEDs as follows:

$$W = \frac{V_{\text{pixelOLED}} - V_{\text{refOLED}}}{V_{\text{refOLED}}}$$

In this equation, W is the relative electrical aging based on the difference between the voltage of the active pixel OLED and the reference pixel OLED is divided by the voltage of the reference pixel OLED. FIG. **9** is a graph **900** that shows a plot **902** of points for a stress current of 268 μA based on the W value. As shown by the graph **900**, the W value is a close-to-linear relation with the luminance drop for the pixel OLEDs as shown for a high stress OLED.

The above described methods of extracting baseline measurements of the pixels in the array may be performed by a processing device such as the **112** in FIG. **1** or another such device which may be conveniently implemented using one or more general purpose computer systems, microprocessors, digital signal processors, micro-controllers, application specific integrated circuits (ASIC), programmable logic devices (PLD), field programmable logic devices (FPLD), field programmable gate arrays (FPGA) and the like, programmed according to the teachings as described and illustrated herein, as will be appreciated by those skilled in the computer, software and networking arts.

In addition, two or more computing systems or devices may be substituted for any one of the controllers described herein. Accordingly, principles and advantages of distributed processing, such as redundancy, replication, and the like, also can be implemented, as desired, to increase the robustness and performance of controllers described herein.

The operation of the example baseline data determination methods may be performed by machine readable instructions. In these examples, the machine readable instructions comprise an algorithm for execution by: (a) a processor, (b) a controller, and/or (c) one or more other suitable processing device(s). The algorithm may be embodied in software stored on tangible media such as, for example, a flash memory, a CD-ROM, a floppy disk, a hard drive, a digital video (versatile) disk (DVD), or other memory devices, but persons of ordinary skill in the art will readily appreciate that the entire algorithm and/or parts thereof could alternatively be executed by a device other than a processor and/or embodied in firmware or dedicated hardware in a well

17

known manner (e.g., it may be implemented by an application specific integrated circuit (ASIC), a programmable logic device (PLD), a field programmable logic device (FPLD), a field programmable gate array (FPGA), discrete logic, etc.). For example, any or all of the components of the baseline data determination methods could be implemented by software, hardware, and/or firmware. Also, some or all of the machine readable instructions represented may be implemented manually.

While particular embodiments and applications of the present invention have been illustrated and described, it is to be understood that the invention is not limited to the precise construction and compositions disclosed herein and that various modifications, changes, and variations can be apparent from the foregoing descriptions without departing from the spirit and scope of the invention as defined in the appended claims.

What is claimed is:

1. A method of display device production for display devices each having a plurality of pixels, each pixel of the plurality of pixels comprising a drive transistor and a light emitting device, the method comprising:

18

applying test signals to each of the plurality of pixels, the test signals applied to each pixel including a first control signal which turns off one of the drive transistor and the light emitting device of the pixel;

electrically measuring, for each of the pixels, voltage and current characteristics of the other one of the drive transistor and the light emitting device which is not turned off by said first control signal, while said one of the drive transistor and the light emitting device is off; and

varying at least one process of the display device production based on the measurements of said voltage and current characteristics.

2. The method of claim 1, wherein the measurements of said voltage and current characteristics are indicative of at least one of a shorted organic light emitting device and a shorted drive transistor.

3. The method of claim 1, wherein said test signals further include a second control signal for controlling a decoupling of a supply voltage from the one of the drive transistor and the light emitting device which is turned off by said first control signal.

* * * * *

专利名称(译)	AMOLED显示器中用于老化补偿的系统和方法		
公开(公告)号	US10679533	公开(公告)日	2020-06-09
申请号	US15/703260	申请日	2017-09-13
[标]申请(专利权)人(译)	伊格尼斯创新公司		
申请(专利权)人(译)	IGNIS创新INC.		
当前申请(专利权)人(译)	IGNIS创新INC.		
[标]发明人	CHAJI GHOLAMREZA DIONNE JOSEPH MARCEL AZIZI YASER JAFFARI JAVID HORMATI ABBAS LIU TONG ALEXANDER STEFAN		
发明人	CHAJI, GHOLAMREZA DIONNE, JOSEPH MARCEL AZIZI, YASER JAFFARI, JAVID HORMATI, ABBAS LIU, TONG ALEXANDER, STEFAN		
IPC分类号	G09G3/00 G01R31/44 G09G3/3283 G09G3/3233 G09G3/32 G09G3/3208		
CPC分类号	G09G3/3233 G09G3/3283 G09G3/006 G01R31/44 G09G2320/029 G09G2320/0295 G09G2300/0842 G09G2320/0233 G09G2320/043 G09G2320/0285 G09G2320/045		
优先权	2688870 2009-11-30 CA		
其他公开文献	US20180005557A1		
外部链接	Espacenet		

摘要(译)

公开了提供基线测量以用于显示设备的老化补偿的方法和系统。示例显示系统具有多个有源像素和参考像素。公共输入信号被提供给参考像素和多个有源像素。测量参考像素的输出，并将其与有效像素的输出进行比较以确定老化效果。还可以通过将第一已知参考电流施加到具有第二可变参考电流的电流比较器和诸如像素之一的被测设备的输出，来对显示系统进行测试。调整可变参考电流，直到第二电流和被测设备的输出等于第一电流为止。被测设备的合成电流存储在查找表中，作为显示系统运行期间老化测量的基准。还可以通过确定诸如OLED和驱动晶体管之类的像素组件中的短路之类的异常来测试显示系统以确定生产缺陷。

