



US009916784B2

(12) **United States Patent**
Pietro et al.

(10) **Patent No.:** **US 9,916,784 B2**
(45) **Date of Patent:** **Mar. 13, 2018**

(54) **INTEGRATED DRIVE CIRCUIT FOR
MULTI-SEGMENT ELECTROLUMINESCENT
DISPLAYS**

(71) Applicant: **Scobil Industries Corp.**, Brampton
(CA)

(72) Inventors: **Patrick D. Pietro**, Grand Island, NY
(US); **William J. Pietro**, Toronto (CA);
Paul Savel, Pickering (CA)

(73) Assignee: **SCOBIL INDUSTRIES CORP.**,
Brampton (CA)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 0 days.

(21) Appl. No.: **15/194,615**

(22) Filed: **Jun. 28, 2016**

(65) **Prior Publication Data**

US 2016/0379536 A1 Dec. 29, 2016

Related U.S. Application Data

(63) Continuation of application No. 13/859,211, filed on
Apr. 9, 2013, now Pat. No. 9,406,256, which is a
(Continued)

(51) **Int. Cl.**
G09G 3/30 (2006.01)
G09G 3/12 (2006.01)
H05B 33/08 (2006.01)

(52) **U.S. Cl.**
CPC **G09G 3/12** (2013.01); **G09G 3/30**
(2013.01); **H05B 33/08** (2013.01);
(Continued)

(58) **Field of Classification Search**
CPC . H05B 33/08; G09G 3/12; G09G 3/30; G09G
2330/028

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,854,539 A 12/1998 Pace et al.
5,886,475 A 3/1999 Horiuchi et al.
(Continued)

FOREIGN PATENT DOCUMENTS

WO 2005015529 A2 2/2005

OTHER PUBLICATIONS

Document relating to PCT Application No. PCT/CA2011/001137,
dated Jan. 18, 2012 (International Search Report).

(Continued)


Primary Examiner — Xuemei Zheng

(74) *Attorney, Agent, or Firm* — Bereskin & Parr
LLP/S.E.N.C.R.L., s.r.l.

(57) **ABSTRACT**

An integrated drive circuit for multi-segment electroluminescent displays is provided. During a charging phase, the electroluminescent segments are charged by a common charge circuit, and partially discharged using separate discharge circuits associated with individual electroluminescent segments. A controller provides essentially independent control over the respective discharge circuits so, by the end of the charging phase, the EL segments can be charged to correspondingly different final voltages. Then during a discharging phase following the charging phase, the electroluminescent segments are completely discharged, thereby emitting an intensity of light that varies roughly in proportion to the final accumulated voltage. The controller can be pre-programmed with a spatial-temporal light pattern so that, using the disclosed integrated drive circuit, the electroluminescent display can be operated to generate rudimentary animations.

20 Claims, 7 Drawing Sheets



Related U.S. Application Data

continuation of application No. PCT/CA2011/001137, filed on Oct. 7, 2011.

(60) Provisional application No. 61/391,927, filed on Oct. 11, 2010.

(52) **U.S. Cl.**

CPC . *G09G 2310/061* (2013.01); *G09G 2330/028* (2013.01); *Y02B 20/325* (2013.01)

(56) **References Cited**

U.S. PATENT DOCUMENTS

6,369,516	B1	4/2002	Iketsu et al.	
6,580,409	B1	6/2003	Ito et al.	
8,026,670	B2	9/2011	Fryer	
2004/0178747	A1	9/2004	Jones et al.	
2005/0057458	A1 *	3/2005	Forsythe	G09G 3/14 345/76
2009/0153064	A1	6/2009	Fryer	
2010/0188049	A1 *	7/2010	Haddani	G01R 31/3613 320/134

OTHER PUBLICATIONS

Document relating to PCT Application No. PCT/CA2011/001137, dated Jan. 18, 2012 (Written Opinion of the Searching Authority).
Document relating to PCT Application No. PCT/CA2011/001137, dated Apr. 16, 2013 (International Preliminary Report Patentability).

* cited by examiner




Figure 1




Figure 2




Figure 3





Figure 4



5010




Figure 6




Figure 7

INTEGRATED DRIVE CIRCUIT FOR MULTI-SEGMENT ELECTROLUMINESCENT DISPLAYS

CROSS-REFERENCE TO RELATED PATENT APPLICATIONS

The application is a continuation of U.S. patent application Ser. No. 13/859,211 filed on Apr. 9, 2013, which is a continuation of International Application No. PCT/CA2011/001137 filed on Oct. 7, 2011, which claims the benefit of U.S. Provisional Application No. 61/391,927, filed on Oct. 11, 2010.

FIELD

The described embodiments relate generally to an integrated drive circuit for multi-segment electroluminescent displays and, more particularly, to an integrated drive circuit for producing animated illumination of multi-segment electroluminescent displays.

BACKGROUND

Electroluminescent ("EL") cells or segments generally comprise a layer of phosphor material, such as a zinc sulphide powder, housed between two electrodes. Typically although not in every case, one of the cell electrodes can be composed of a transparent material, such as indium tin oxide, deposited onto a transparent substrate, which provides the front surface for the electroluminescent segment. The phosphor layer housed between the two conductors behaves generally like a capacitor, in which the phosphor layer acts as a dielectric insulator. Depending on its size, the effective capacitance of the electroluminescent segment can range anywhere from picofarads to microfarads. Light is radiated from the electroluminescent cell by subjecting the phosphor layer to a strong electric field, causing photoemission as electron-hole pairs separated in the phosphor layer recombine.

To produce light from the electroluminescent cell, a large voltage is applied across its electrodes. In the resulting current flow, charge is accumulated on the cell electrodes due to the capacitive nature of the electroluminescent segment. To prevent the long-term buildup of charge on the cell electrodes, the applied voltage is typically alternated between positive and negative polarities. Any charge that is accumulated across the electroluminescent segment electrodes during a charging phase is subsequently dissipated during a discharging phase and, through alternation of the two discrete phases, effectively continuous photoemission can be maintained within the phosphor layer. Depending on the size of the electroluminescent segment and the desired illumination intensity, an alternating voltage in the range of 100-150 V, and having a frequency in the range of 100-400 Hz, may be appropriate.

Because of their compact size and relatively low current consumption, electroluminescent cells are widely used in small battery operated electronic devices. For example, liquid crystal displays can be backlight using electroluminescent cells in portable communication devices, such as mobile phones, personal data assistants, portable music players, and the like. The output of the batteries used in these electronic devices, however, is commonly a low-level DC voltage in the range of about 1-5 V. Accordingly, some form of voltage converter is often used to convert the low-voltage

DC output of the battery into the high-voltage AC current used to driving the electroluminescent cell.

SUMMARY

In a first broad aspect, at least some of the described embodiments provide an integrated drive circuit for an electroluminescent display that has at least one electroluminescent segment. The integrated drive circuit includes a charge circuit coupled to the electroluminescent segment and configured to transmit energy received from a power supply to the electroluminescent segment as a discrete sequence of charge pulses to accumulate a voltage across the electroluminescent segment, and a discharge circuit coupled to the electroluminescent segment and configured to dissipate the accumulated voltage by selectively forming a shunt path across the electroluminescent segment to drain energy stored in the electroluminescent segment.

In some embodiments, the integrated drive circuit includes a controller configured to control the voltage across the electroluminescent segment by generating a charge control signal for the charge circuit and a discharge control signal for the discharge circuit. The charge circuit can be configured to generate and transmit the discrete sequence of charge pulses to the electroluminescent segment in response to the charge control signal. The discharge circuit can be configured to selectively form the shunt path across the electroluminescent segment in response to the discharge control signal.

The controller can be configured to control a final voltage accumulated across the electroluminescent segment at the end of a charging phase by controlling the charge circuit to transmit the discrete sequence of charge pulses during the charging phase, and determining a number of charge pulses to be transmitted in the discrete sequence of charge pulses.

The controller can be configured to reset the voltage across the electroluminescent segment by controlling the discharge circuit to completely discharge the electroluminescent segment during a discharging phase succeeding the charging phase.

In some embodiments, the charge circuit includes a charge pump coupled across the electroluminescent segment, which is used to generate the discrete sequence of charge pulses. The charge pump can be implemented using a storage element for coupling to the power supply, an output element coupled to the storage element, and a gating switch that is controllable by the charge control signal to selectively accumulate energy received from the power supply in the storage element, and release energy from the storage element to the output element for transmission to the electroluminescent segment.

In some embodiments, the discharge circuit includes a shunt switch connected across the electroluminescent segment, which is controllable by the discharge control signal to provide a short circuit across the electroluminescent segment.

In some embodiments, the integrated drive circuit includes an isolation switch for coupling the charge circuit to the power supply, and which is controllable to selectively connect and disconnect the power supply to and from the charge circuit.

In some embodiments, the electroluminescent display has a plurality of parallel-connected electroluminescent segments, in which case the charge circuit can be coupled to each electroluminescent segment, and can be configured to transmit the discrete sequence of charge pulses to the plurality of electroluminescent segments to accumulate a

corresponding voltage across each electroluminescent segment. A corresponding discharge circuit can also be coupled to each electroluminescent segment, with each corresponding discharge circuit configured to selectively form a corresponding shunt path across that electroluminescent segment to dissipate the corresponding accumulated voltage. The controller can be also configured to control the corresponding voltage accumulated across each electroluminescent segment by generating a corresponding discharge control signal for each corresponding discharge circuit.

The controller can be configured to control a corresponding final voltage accumulated by each electroluminescent segment at the end of a charging phase by controlling at least one corresponding discharge circuit to partially discharge the corresponding voltage accumulated across that electroluminescent segment during the charging phase.

The controller can be configured to control the at least one corresponding discharge circuit to partially discharge the corresponding accumulated voltage by controlling the charge circuit to transmit the discrete sequence of charge pulses having a number of charge pulses during the charging phase, controlling the at least one corresponding discharge circuit to drain a discrete sequence of partial discharge pulses from that electroluminescent segment during the charging phase and, for the at least one corresponding discharge circuit, determining a number of partial discharge pulses to be drained in the discrete sequence of partial discharge pulses based upon the number of charge pulses in the discrete sequence of charge pulses.

The controller can be configured to control a timing of the discrete sequence of partial discharge pulses to coincide with intervals between successive charge pulses in the discrete sequence of charge pulses.

The controller can be configured to control the corresponding final voltage accumulated by each electroluminescent segment at the end of the charging phase independently of other electroluminescent segments, so that the corresponding final voltage of at least two electroluminescent segments differs.

The controller can be configured to reset the voltage across each electroluminescent segment by controlling each corresponding discharge circuit to completely discharge that electroluminescent segment during a discharging phase succeeding the charging phase.

In a second broad aspect, at least some of the described embodiments provide a method of supplying power to an electroluminescent display that has at least one electroluminescent segment. The method involves accumulating a voltage across the electroluminescent segment during a charging phase by transmitting energy from a power supply to the electroluminescent segment as a discrete sequence of charge pulses, and dissipating the voltage accumulated across the electroluminescent segment during a discharging phase succeeding the charging phase by forming a shunt path across the electroluminescent segment.

In some embodiments, the method can involve controlling a final voltage accumulated across the electroluminescent segment at the end of the charging phase. The final voltage accumulated across the electroluminescent segment can be controlled by determining a number of charge pulses in the discrete sequence of charge pulses to be transmitted to the electroluminescent segment.

In some embodiments, the electroluminescent display has a plurality of parallel-connected electroluminescent segments, in which case the method can involve accumulating a corresponding voltage across each electroluminescent segment during the charging phase by transmitting the discrete

sequence of charge discrete pulses to each electroluminescent segment, and dissipating the corresponding voltage accumulated across each electroluminescent segment during the discharging phase by connecting a corresponding shunt path across that electroluminescent segment.

The method can involve controlling a corresponding final voltage accumulated across each electroluminescent segment at the end of the charging phase by partially discharging the corresponding voltage accumulated across at least one electroluminescent segment during the charging phase. The corresponding final voltage accumulated across each electroluminescent segment can be controlled by transmitting the discrete sequence of charge pulses having a number of charge pulses during the charging phase, draining a discrete sequence of partial discharge pulses from that electroluminescent segment during the charging phase and, for the at least one corresponding discharge circuit, determining a number of partial discharge pulses to be drained in the discrete sequence of partial discharge pulses based upon the number of charge pulses in the discrete sequence of charge pulses.

In some embodiments, the method can involve timing the discrete sequence of partial discharge pulses to coincide with intervals between successive charge pulses in the discrete sequence of charge pulses.

In some embodiments, the method can involve controlling the corresponding final voltage accumulated by each electroluminescent segment at the end of the charging phase independently of other electroluminescent segments, so that the corresponding final voltage of at least two electroluminescent segments differs.

In some embodiments, the method can involve completely discharging each electroluminescent segment during the discharging phase.

These and other aspects of the described embodiments are set forth herein.

BRIEF DESCRIPTION OF THE DRAWINGS

A detailed description of various embodiments of the invention, including at least one preferred embodiment, is provided herein below with reference to the following drawings, by way of example only, and in which:

FIG. 1 is a simplified schematic diagram of an integrated drive circuit for an electroluminescent display having at least one electroluminescent segment;

FIG. 2 is a simplified schematic diagram of a charge circuit included in the integrated drive circuit shown in FIG. 1;

FIG. 3 is a simplified schematic diagram of a discharge circuit included in the integrated drive circuit shown in FIG. 1;

FIG. 4 is a timing diagram illustrating operation of the integrated drive circuit shown in FIG. 1;

FIG. 5 is a simplified schematic diagram of an integrated drive circuit for an electroluminescent display having multiple parallel-connected electroluminescent segments;

FIG. 6 is a timing diagram illustrating operation of the integrated drive circuit shown in FIG. 5; and

FIG. 7 is a flow chart illustrating a method of supplying power to an electroluminescent display having multiple parallel-connected electroluminescent segments.

It will be understood that reference to the drawings is made for illustrative purposes only, and is not intended to limit the scope of the described embodiments in any way. For clarity and convenience, reference numerals may be

repeated throughout the drawings (with or without an offset) to indicate analogous components or features.

DESCRIPTION OF EXEMPLARY EMBODIMENTS

Electroluminescent displays are often divided into a grid of electroluminescent segments that can be individually illuminated. The illumination emitted by each individual EL segment can be maintained at a constant intensity to provide an overall static, or time-invariant, display output. Alternatively, to provide the appearance of animation, the illuminations emitted by different EL segments within the grid can be varied according to a pre-programmed sequence to form a mixed temporal-spatial pattern of light, (i.e., light intensity that is modulated both spatially and temporally). For example, the EL display can be operated so as to produce flashing or scrolling text, rudimentary graphics, and other forms of animations. The described embodiments provide an integrated drive circuit for a multi-segment EL display that provides independent control over individual segments within the EL display.

Reference is made initially to FIG. 1, which illustrates a schematic diagram of an integrated drive circuit 100 for an electroluminescent display. The integrated drive circuit 100 includes a power supply 110, charge circuit 120, discharge charge circuit 130, controller 140, electroluminescent (“EL”) segment 150, and isolation switch 160. A single EL segment 150 is shown in FIG. 1, although as will be described in more detail below, in an alternative configuration, the integrated drive circuit 100 can be adapted to drive a plurality of paralleled-connected EL segments contained within the EL display.

The positive terminal of the power supply 110 is coupled to the charge circuit 120 via the isolation switch 160 and provides a supply voltage signal 115, which can be low-voltage DC, to the charge circuit 120. The negative terminal of the power supply 110 can be connected to ground. In some cases, the power supply 110 is implemented using a DC source, such as a battery or solar panel, to generate low-voltage DC for supplying the charge circuit 120. However, the power supply 110 is not limited to low-voltage DC sources and alternatively can be implemented using an AC power supply, such as a 50-Hz or 60-Hz utility connection, together with a rectifier or voltage converter to generate the supply voltage signal 115 for the charge circuit 120. If desired, a voltage regulator can also be implemented in the power supply 110 to provide a temperature-stabilization of the supply voltage signal 115.

Charge circuit 120 is configured to absorb energy from the supply voltage signal 115 received from the power supply 110 and, in response to a charge control signal 160 provided by the controller 140, charge the EL segment 150 by generating a discrete sequence of charge pulses 170. As the sequence of charge pulses 170 is pumped to the EL segment 150, some energy is dissipated as waste heat, but most of the transferred charge is stored in the EL segment 150, resulting in the incremental accumulation of a voltage 155 across the positive and negative electrodes of the EL segment 150. When subsequent activation of the discharge circuit 130 causes the accumulated voltage 155 to dissipate, the resulting re-polarization of the electric field formed within the phosphor layer (i.e., due to the accumulated voltage) causes photoemissive recombination of electron-hole pairs.

The controller 140 controls the charge circuit 120, as will be explained in more detail below, so that each individual pulse in the sequence of charge pulses 170 delivers approxi-

mately the same incremental charge ΔQ to the EL segment 150. Since each incremental charge ΔQ accumulates a corresponding incremental voltage ΔV across the EL segment 150, related proportionally to the incremental charge ΔQ by the effective capacitance of the EL segment 150, the total accumulated voltage 155 is roughly proportionate to the number of charge pulses 170 delivered by the charge circuit 120. The intensity of the illumination emitted by the EL segment 150 is then in turn related proportionately to the accumulated voltage 155.

The capacitive characteristics of the EL segment 150 can vary depending on different properties of the EL segment 150, such as the material characteristics and thickness of the phosphor layer, and the effective area of the EL segment 150. By testing the electroluminescent performance of the EL segment 150 during design of the EL display, the electroluminescent performance of the EL segment 150 can be characterized for a range of different accumulated voltages 155. Using this information, a relationship between light intensity and the total accumulated voltage 155 can be formulated and subsequently used to program different charge pulse sequences in the controller 140 corresponding to different light intensities. In this way, the intensity of light generated by the EL segment 150 is controllable based upon the characterization of the EL segment 150, the number and duration of charge pulses delivered by the charge circuit 120 and other parameters of the integrated drive circuit 100 as will be apparent.

Referring now to FIG. 2, the charge circuit 120 can be implemented using a modified form of a charge pump 122, in which the EL segment 150 replaces the capacitive element normally associated with the charge pump 122. In the exemplary configuration shown, the charge pump 122 includes the inductor 124, diode 126 and gating switch 128 coupled together in boost configuration. One terminal of the inductor 124 is coupled to the positive terminal of the power supply 110 and, depending on the state of the gating switch 128, either stored energy absorbed from the voltage supply signal 115, releases some of that stored energy to the diode 126 for transmission to the EL segment 150.

The gating switch 128 is implemented, for example, using a semiconductor switch, such as a metal oxide semiconductor field effect transistor (MOSFET), bipolar junction transistor (BJT), or junction field effect transistor (JFET). As shown in FIG. 2, gating switch 128 is implemented using a PMOS transistor driven by the charge control signal 170, although other types or configurations of gating switches may be apparent.

When the gating switch 128 is closed and conducting, the voltage drop across the gating switching 128 is minimal, pulling the common node 129 of the charge pump 122 down near to ground potential. Current flow in the inductor 124 ramps up in proportion to the internal field generated as energy from the power supply 110 is absorbed. Reversing biasing of the diode 126 also prevents the accumulated voltage 155 across the EL segment 150 from dissipating (unless through the discharge circuit 130, as will be explained more below). When the gating switch 128 is opened and no longer conducting, current flowing through the inductor 124 is forced out through the diode 126 to the EL segment 150 until either the gating switch 128 is closed again or all the energy stored in the inductor 124 is released.

By modulating the charge control signal 160 between high and low voltage states, the gating switch 128 is alternately opened and closed, causing the charge circuit 120 to pump charge intermittently to the EL segment 150. In order to generate the sequence of charge pulses 170 having

approximately equally weighted charge pulses, the controller **140** can apply a pulse width modulation (PWM) or pulse density modulation (PDM) scheme, for example, but other suitable schemes may be apparent as well. Moreover, as will be appreciated, with this particular arrangement of the inductor **124**, diode **126** and gating switching **128**, the effective voltage applied across the EL segment **150** can be made to be substantially larger than the magnitude of the supply voltage signal **115**, if the duty cycle of the charge control signal **160** is sufficiently large.

Referring now to FIG. 3, the discharge circuit **130** is parallel-coupled to the EL segment **150** and, in response to a discharge control signal **180** provided by the controller **140**, selectively forms a shunt path **135** connecting the positive and negative electrodes of the EL segment **150**. The discharge circuit **130** is controllable using the discharge control signal **180**, so that the shunt path **135** can be formed only when the charge circuit **120** is not delivering charge pulses to the EL segment **150**. Accordingly, when the charge circuit **120** is active, the shunt path **135** can be broken so that the only path to ground from the output of the charge circuit **120** includes the EL segment **150**. However, when formed, the shunt path **135** provides an alternate path to ground for draining any charge stored in the EL segment **150** and thereby dissipating any voltage that had accumulated across the EL segment **150**. As mentioned above, the field repolarization caused by draining the EL segment **150** results in photoemission within the phosphor layer.

The discharge circuit **130** is implemented using a switching transistor **134**, which is an NMOS transistor in the exemplary configuration shown in FIG. 3, and an optional shunt resistor **136**. The source of the switching transistor **134** is coupled to the negative terminal of the EL segment **150**, while the gate of switching transistor **134** is driven by the discharge control signal **180**. When implemented using an NMOS transistor, as will be appreciated, the switching transistor **134** is closed and conducting when driven with a gate voltage that exceeds the threshold voltage of the switching transistor **134**, but is open and not conducting when the gate voltage is less than the transistor threshold voltage.

In some cases, the drain of the switching transistor **134** is coupled directly to the positive terminal of the EL segment **150**, but alternatively (as shown) can be coupled using the shunt resistor **136**. The shunt resistor **136** is optional and can be included in the discharge circuit **130** to adjust the rate at which the EL segment **150** drains through the shunt path **132** when formed (i.e., by changing the effective time constant of the shunt path **135**).

Referring back to FIG. 1, isolation switch **160** couples the charge circuit **120** to the power supply **110**, and is controllable using the isolation switch control signal **190** generated by the controller **140**. When the isolation switch **160** is closed and conducting, the charge circuit **120** is connected to the power supply **110** and absorbing the voltage supply signal **115** received from the power supply **110**. However, when the isolation switch **160** is opened, the power supply **110** is disconnected from the charge circuit **120** and effectively isolated from the rest of the integrated drive circuit **100**. Depending on the current handling requirements of the isolation switch **190**, different semiconductor devices can be used to implement the isolation switch **190**, as will be appreciated, which MOSFETs, BJTs and JFETs, for example.

The isolation switch **160** can be used by the controller **140** as a form of ON/OFF switch for the EL segment **150** within the integrated drive circuit **100**. By disconnecting its source

of power, opening the isolation switch **160** effectively turns off the EL segment **150**. In the reverse situation, closing the isolation switch **160** effectively turns on the EL segment **150** by connecting the power supply **110** and thereby re-establishing a source of power for the EL segment **150**.

The controller **140** generates the isolation switch control signal **190** for the isolation switch **160** based on sensor data generated by one or more sensors associated with the EL display. For example, an associated light sensor can detect a level of ambient light in the vicinity of the EL display and, if the detected ambient light falls below a threshold level, the controller **140** can decide to connect the power supply **110** by closing the isolation switch **160**. As other examples, the controller **140** can generate the isolation switch control signal **190** based upon sensor data provided by one or both of a motion sensor (which detects relative motion of the EL display) and a noise sensor (which detects an ambient level of noise in the vicinity of the EL display). Alternatively, the isolation switch **160** can be implemented using a tumbler switch (i.e., a Mercury switch) that closes when the EL display is in certain relative orientations.

In some configurations, a real-time clock can also be associated with the EL display, so that the controller **140** can execute programmed device turn on or turn off. For example, the controller **140** can be programmed to turn the device off, by opening the isolation switch **160**, if a maximum idle time has been exceeded or after a pre-programmed duration following the EL display being turned on. Scheduled turn on and turn off is also possible in some configurations of the integrated drive circuit **100**.

The controller **140** is coupled to the charge circuit **120** and the discharge circuit **130** for providing corresponding signals used to control to each component. Thus, as mentioned above, controller **140** is programmed to generate the charge control signal **160** for the charge circuit **120** and the discharge control signal **180** for the discharge circuit **130**.

Referring now to FIGS. 1 and 4, the integrated drive circuit **100** operates under the direction of the controller **140** as follows. A charging phase **165** commences shortly after the isolation switch control signal **190**, which had previously been driven to the low-voltage state, is re-asserted to a high-voltage state, thereby closing the isolation switch **160** and connecting the charge circuit **120** to the power supply **110**. As mentioned before, with the isolation switch **160** closed and connecting, the integrated drive circuit **100** is in an active mode. Throughout the charging phase **165**, the discharge control signal **180** is also driven to the low-voltage state to open the shunt path **135** and force current flowing out of the charge circuit **120** to accumulate in the EL segment **150**. Shortly after the charging phase **165** commences, the controller **140** provides a sequence of gating signals **162** to the charge circuit **120** to begin charging the EL segment **150**.

The controller **140** determines the sequence of gating signals **162** so that the charge circuit **120** outputs the sequence of charge pulses **170**. For example, the controller **140** determines (or alternatively has been pre-programmed with) the total number of charge pulses **167** in the sequence of charge pulses **162** based on the characterization of the EL segment **150** and the desired final voltage **155** to be accumulated across the EL segment at the end of the charging phase **165**. The controller **140** also determines (or is pre-programmed with) the duration of each individual charge pulse in the sequence of charge pulses **162**, in terms of the pulse duty cycle, so that approximately the same incremental charge ΔQ is contained within each pulse. Although the sequence of gating signals **162** is illustrated for convenience

having a constant duty cycle, it should be appreciated that the controller 140 may implement a more complex modulation scheme, such as PWM or PDM, in which the duty cycle of the sequence of gating signals 162 varies with time.

The charging phase 165 ends once the voltage 155 accumulated across the EL segment 150 reaches its desired final voltage. At that point the charging phase 165 ends and is succeeded by a discharging phase 185. Shortly after the start of the discharging phase 185, the isolation switch control signal 190 is lowered to the low-voltage state in order to isolate the power supply 110 from the rest of the integrated drive circuit 100. Temporarily disconnecting the power supply 110 during the discharging phase 185 increases the overall efficiency of the integrated drive circuit 100 by reducing losses in the power supply 110 and charge circuit 120 when these components are not actively operating.

At or near the same time as the isolation switch 160 is opened, the controller 140 also generates a discharge signal 182, in response to which the discharge circuit 130 forms the shunt path 135 across the EL segment 150. Due to the reverse isolation of the charge circuit 120 (i.e. provided by the diode 126 in FIG. 2), any charge stored in the EL segment 150 during the charging phase 165 is completely drained through the shunt path 135. The length of the discharge signal 182 is variable and can depend on the magnitude of the final accumulated voltage 155, as well as the discharge rate of the shunt path 132, but should be sufficiently long that the EL segment 150 completely discharges. Thus, by the end of the discharging phase 185, the final voltage 155 accumulated across the EL segment 150 during the charging phase 165 will have been completely dissipated and the EL segment 150 reset for a new charging phase 165.

An optional idle phase 195 can be added between the end of the discharging phase 185 and the start of a new charging phase 165. During the optional idle phase 195, the EL segment 150 is being neither charged nor discharged, while the power supply 110 remains isolated from the rest of the integrated drive circuit 100 by opening of the isolation switch 160. The optional idle phase 195 ends shortly after the controller 140 asserts the isolation switch control signal 190 in order to re-connect the power supply 110 and begin a new charging phase 165. The optional idle phase 195 has a variable duration and, in some configurations, can be eliminated altogether. In that case, the isolation switch control signal 190 can be asserted at or near the end of the discharge signal 182 to mark the start of the new charging phase 165 immediately following the end of the discharging phase 185.

By charging the EL segment 150 to the same final voltage 155 at the end of each charging phase 165, followed alternately with the discharging phase 185 and optional idle phase 195, the EL segment 150 will produce an essentially constant intensity of light. As mentioned above, the intensity of illumination produced can be controlled based on the magnitude of the final accumulated voltage 155. The intensity is also adjustable by the controller 140 determining the number of charge pulses in the sequence of charge pulses 170 to pump into the EL segment 150. But in general, the intensity of light produced by the EL segment 150 can be made to vary as a function of time by controlling the number of charge pulses delivered to the EL segment 150 in successive charging phases 165.

Referring now to FIG. 5, there is illustrated an integrated drive circuit 200 for an electroluminescent display. The integrated drive circuit 200 is similar to the integrated drive circuit 100 shown in FIG. 1, but is adapted for an electrolu-

minescent display having multiple parallel-connected EL segments 250_{1-N}. Although only two such parallel-connected EL segments 250₁ and 250_N are shown explicitly in FIG. 5, it should be appreciated that each parallel-connected EL segment 250_{1-N} can be identical. The parallel-connected EL segments 250_{1-N} can also be arranged physically within the EL display according to a grid or matrix distribution. For the sake of clarity, discussion of like elements or aspects of the two integrated drive circuits 100 and 200 may be abbreviated, while specific differences may be highlighted or emphasized.

Power supply 110 is coupled to the charge circuit 120 using isolation switch 160, which selectively connects and disconnects power supply 110 to the charge circuit 120 in response to the isolation switch control signal 190. Again the power supply 110 provides a supply voltage signal 115 to the charge circuit 120, which can be relatively low-voltage DC. The charge circuit 120 is coupled to each respective parallel-connected EL segment 250_{1-N} through corresponding diodes 257_{1-N}, which provide reverse isolation for each respective EL segment 250_{1-N}, not just from charge circuit 120, but also from other respective EL segments 250_{1-N}. The charge circuit 120 can have the same configuration as shown in FIG. 2 and, as described above, deliver energy to each corresponding EL segment 250_{1-N} in response to the charge control signal 160 provided by controller 240, by generating a discrete sequence of charge pulses 170.

A corresponding discharge circuit 230_{1-N}, each having the general configuration shown in FIG. 3, for example, is coupled across the parallel-connected EL segments 250_{1-N}. Each discharge circuit 230_{1-N} is independently controllable, using a corresponding discharge control signal 280_{1-N} generated and provided by the controller 240, to form corresponding shunt paths 235_{1-N} across the EL segments 250_{1-N}. As before the shunt paths 235_{1-N} can be controllably operated to dissipate corresponding voltages 255_{1-N} that accumulate across the EL segments 250_{1-N} when charged by the discrete sequence of charge pulses 170.

Referring now to FIGS. 5 and 6, the discharge circuits 230_{1-N} are independently controllable by the controller 240, so that each of the parallel-connected EL segments 250_{1-N} can produce generally different light intensities. By also controlling the respective illuminations of the parallel-connected EL segments 250_{1-N} as a function time, the electroluminescent display can produce pseudo-animations (i.e., in which the light intensity emitted by the electroluminescent display varies both spatially within the EL display, and as a function of time, according to a pre-programmed sequence).

As before, a charging phase 165 commences shortly after the controller 240 asserts the isolation switch control signal 190, thereby closing the isolation switch 160 and reconnecting the charge circuit 120 to the power supply 110. Shortly after the charging phase 165 commences, the controller 240 transmits a sequence of gating signals 162 to the charge circuit 120, in response to which the charge circuit 120 begins transmitting the sequence of charge pulses 170 to the parallel-connected EL segments 250_{1-N}. The controller 240 can generate the sequence of gating signals 162 (although not explicitly shown) according to a modulation scheme, such as PWM or PDM, so that each charge pulse in the sequence of charges pulses 170 delivers approximately the same incremental charge ΔQ to each of the parallel-connected EL segments 250_{1-N}. In this way, because each of the parallel-connected EL segments 250_{1-N} has the same effective capacitance, the voltages 255_{1-N} across the parallel-connected EL segments 250_{1-N} accumulate roughly in proportion to the number of charge pulses delivered.

However, unlike the integrated charge circuit 100 (FIG. 1), when the charging circuit 120 is delivering the sequence of charge pulses 170 to the EL segments 250_{1-N}, simultaneously during the charging phase 165, the controller 240 also generates respective gating signals 285_{1-N} for each corresponding discharge circuit 230_{1-N}. In response to the gating signals 285_{1-N}, the corresponding discharge circuits 230_{1-N} partially dissipate the voltages 255_{1-N} that have been accumulating across the EL segments 250_{1-N} during the charging phase 165 by draining sequences of partial discharge pulses 275_{1-N} from the EL segments 250_{1-N}. The controller 240 generates the gating signals 285_{1-N} to coincide with time intervals between consecutive charge pulses in the sequence of charge pulses 170, so that the control exerted over the charge circuit 120 is more or less decoupled from the control exerted over the discharge circuits 230_{1-N}.

Looking only at the EL segment 250₁ for the moment, the controller 240 determines the final voltage 255₁ to be accumulated across the EL segment 250₁ at the end of the charging cycle 165 based on the characterization of the EL segment 250₁ and the desired light intensity for the EL segment 250₁. As described above, the controller 240 can make this determination (or be pre-programmed) by characterizing the illumination response of the EL segment 250₁ for a range of different voltages. The controller 240 achieves the desired final voltage 255₁ by partially dissipating the total voltage accumulated during the charging phase 165 due to the sequence of charge pulses 170.

Assuming each of the charge pulse 170 roughly accumulates an incremental voltage ΔV across the EL segment 250₁, the controller 240 generates an estimate of the total accumulated voltage 255₁ at the end of the charging cycle 165 based on the number of individual pulses in the sequence of charge pulses 170. From the total accumulated voltage 255₁, the controller 240 subtracts the desired final voltage to determine how much of the total accumulated voltage 255₁ should be dissipated using the sequence of partial discharge pulses 275₁ during the charging phase 165. The controller 240 then determines how many partial discharge pulses 275 to drain from the EL segment 250₁ through the shunt path 235₁ to achieve the desired final voltage for the EL segment 250₁. As each partial discharge pulse also drains approximately the same incremental charge ΔQ from the EL segment 250₁, the controller 240 can determine the number of partial discharge pulses 275₁ that will achieve the desired final voltage based upon the number of charge pulses 170 delivered by the charge circuit 120. The controller 240 can perform these calculations dynamically or, alternatively, as will be appreciated, the relationship between the number of charge pulses and discharge pulses can be pre-programmed into the controller 240.

The controller 240 controls each of the EL segments 250_{1-N} in the manner described above for the EL segment 250₁ specifically. Accordingly, for each of EL segments 250_{1-N}, the controller 240 determines the corresponding number of partial discharge pulses 275_{1-N} based on the number of charge pulses 170, which will achieve a corresponding final voltage 255_{1-N} for that EL segment 250_{1-N}. As illustrated in FIG. 6, each corresponding sequence of partial discharge pulses 275_{1-N} can have a different number of pulses, so that each of the EL segments 250_{1-N} has a different final voltage at the end of the charging cycle 165. For example, the gating signals 285₁ provided to discharge circuit 230₁ has a number 287₁ of individual gating signals, which is not necessarily the same number 287_N of gating signals 285_N provided to discharge circuit 230_N. Due to the reverse isolation provided by the diodes 257_{1-N}, the control-

ler 240 can exert effectively independent control over each discharge circuit 230_{1-N}, thereby allowing each of the EL segments 250_{1-N} to produce different effective light intensities.

The charging phase 165 ends once the complete sequence of charging pulses 170 has been transmitted by the charging circuit 120, at which point each of the EL segments 250_{1-N} will be at corresponding final voltages 255_{1-N}. (Depending on upon how much of the accumulated voltage 255_{1-N} was partially dissipated during the charging phase 165, the corresponding final voltages 255_{1-N} can be arbitrarily different.) The discharging phase 185 again commences following the end of the charging phase 165. The isolation switch control signal 190 is again driven to the low-voltage state in order to disconnect the power supply 110. At or near the same time, the controller 240 also generates a complete discharge pulse 282_{1-N} for each corresponding discharge circuit 230_{1-N}, which is again of a suitably long duration to completely dissipate the final voltage 255_{1-N} that was accumulated across each EL segment 250_{1-N}. During discharge of the EL segments 250_{1-N}, re-polarization of the fields within the respective phosphor layers generates photoemission roughly in proportion to the final accumulated voltages 255_{1-N}. An optional idle phase 195 can again separate the end of the discharging phase 185 from the start of a new charging phase 165.

Referring now to FIG. 7, there is shown a flow chart illustrating a method 300 of supplying power to an electroluminescent display having multiple parallel-connected electroluminescent segments forming a grid or matrix of segments. The method 300 can be performed, for example, using the exemplary integrated drive circuit 200 (FIG. 5) in order to generate a pre-programmed, animated light sequence. For the sake of clarity, some details related to the integrated drive circuit 200 will not be repeated during discussion of the method 300, which may be abbreviated.

At 305, a discrete sequence of charge pulses is transmitted to each parallel-connected EL segment in the EL display to accumulate a corresponding voltage across each EL segment. The discrete sequence of charge pulses can be transmitted during a charging phase and contain a pre-determined number of individual charge pulses.

At 310, the voltage accumulated across one or more of at least one EL segment can be partially dissipated. In this way, the final voltage accumulated across each of the parallel-connected segments at the end of the charging cycle is controlled, i.e. as the difference between the total accumulated voltage and the partially dissipated voltage.

In one variation of the method 300, the EL segments are partially discharged by draining a discrete sequence of partial discharge pulses from respective EL segments during the charging phase. By controlling the incremental charge ΔQ accumulated or drained from the EL, to control the corresponding final voltage for a given EL segment, the number of partial discharge pulses to be drained is determined based upon the number of charge pulses in the discrete sequence of charge pulses. In some cases, the discrete sequence of partial discharge pulses is also timed to coincide with intervals between successive charge pulses in the discrete sequence of charge pulses, so that the charge and discharge pulses are non-overlapping in time.

At 315, each EL segment is completely discharged during a discharging phase following the charging phase. For example, a respective shunt path can be formed across each EL segment through which to dissipate whatever final voltage had accumulated across the EL segments during the charging phase. During discharge, the EL segments emit

light having an intensity that is varies approximately in proportion to their final accumulated voltages at the end of the charging phase.

At 320, it is checked whether the complete sequence has been performed. If the complete sequence has been performed, the method 300 branches to 325, the source of power for the EL display is disconnected and the method 300 ends. However, if at 320, it is determined that the sequence is not complete, the method 300 branches back to 305 and repeats until the complete sequence has been executed. During each successive iteration of the method 300, the different EL segments are controlled in the manner described to produce light intensities that vary both spatially within the EL display, and as a function of time, according to the pre-programmed sequence. In this way, rudimentary animations can be generated by following the method 300.

The present invention has been described herein by way of exemplary embodiments without limitation. Certain modifications and variations to these exemplary embodiments may be apparent without departing from the scope of the invention, which is limited only by the appended claims.

We claim:

1. An integrated drive circuit for an electroluminescent display comprising at least one electroluminescent segment, the integrated drive circuit comprising:

a charge circuit coupled to the at least one electroluminescent segment, wherein the charge circuit is configured to transmit energy received from a power supply to the at least one electroluminescent segment to accumulate an accumulated voltage across the at least one electroluminescent segment, and the charge circuit comprises a storage element coupled to the power supply and a gating switch controllable to release energy from the storage element to the at least one electroluminescent segment;

a discharge circuit coupled to the at least one electroluminescent segment and configured to dissipate the accumulated voltage by selectively forming a shunt path across the at least one electroluminescent segment to drain energy stored in the at least one electroluminescent segment, wherein the discharge circuit comprises a shunt switch connected across the at least one electroluminescent segment and is controllable to form the shunt path; and

a controller configured to control a final voltage of the accumulated voltage at an end of a charging phase by controlling the discharge circuit to at least partially discharge the accumulated voltage during the charging phase.

2. The integrated drive circuit of claim 1, wherein the controller is configured to control the voltage across the at least one electroluminescent segment by generating a charge control signal for the charge circuit and a discharge control signal for the discharge circuit.

3. The integrated drive circuit of claim 2, wherein the charge circuit is configured to generate and transmit a charging signal to the at least one electroluminescent segment in response to the charge control signal.

4. The integrated drive circuit of claim 2, wherein the discharge circuit is configured to selectively form the shunt path across the at least one electroluminescent segment in response to the discharge control signal.

5. The integrated drive circuit of claim 4, wherein the shunt switch is controllable by the discharge control signal to provide a short circuit across the at least one electroluminescent segment.

6. The integrated drive circuit of claim 2, wherein the controller is configured to reset the voltage across the at least one electroluminescent segment by controlling the discharge circuit to completely discharge the at least one electroluminescent segment during a discharging phase succeeding the charging phase.

7. The integrated drive circuit of claim 2, wherein the electroluminescent display comprises a plurality of parallel-connected electroluminescent segments;

the charge circuit is coupled to each electroluminescent segment and is configured to transmit a charging signal to the plurality of electroluminescent segments to accumulate a corresponding voltage across each electroluminescent segment;

a corresponding discharge circuit is coupled to each electroluminescent segment, each corresponding discharge circuit configured to selectively form a corresponding shunt path across that electroluminescent segment to dissipate the corresponding accumulated voltage; and

the controller is configured to control the corresponding voltage accumulated across each electroluminescent segment by generating a corresponding discharge control signal for each corresponding discharge circuit.

8. The integrated drive circuit of claim 7, wherein the controller is configured to control the corresponding final voltage accumulated by each electroluminescent segment at the end of the charging phase independently of other electroluminescent segments, and the controller is configured to generate different discharge control signals for at least two electroluminescent segments whereby the corresponding final voltages of the at least two electroluminescent segments differ.

9. The integrated drive circuit of claim 7, wherein the controller is configured to reset the voltage across each electroluminescent segment by controlling each corresponding discharge circuit to completely discharge that electroluminescent segment during a discharging phase succeeding the charging phase.

10. The integrated drive circuit of claim 1, further comprising an isolation switch for coupling the charge circuit to the power supply, the isolation switch controllable to selectively connect and disconnect the power supply to and from the charge circuit.

11. A method of supplying power to an electroluminescent display comprising at least one electroluminescent segment, the method comprising:

accumulating a voltage across the at least one electroluminescent segment during a charging phase by operating a charge circuit to transmit energy from a power supply to the at least one electroluminescent segment, wherein the charge circuit comprises a storage element coupled to the power supply and a gate switch controllable to release energy from the storage element to the at least one electroluminescent segment;

operating a discharge circuit coupled to the at least one electroluminescent segment to dissipate the voltage accumulated across the at least one electroluminescent segment during a discharging phase succeeding the charging phase by selectively forming a shunt path across the at least one electroluminescent segment, wherein the discharge circuit comprises a shunt switch connected across the at least one electroluminescent segment and is controllable to form the shunt path; and controlling, by a controller, a final voltage of the voltage accumulated across the at least one electroluminescent segment at an end of the charging phase by at least

15

partially discharging the voltage accumulated across the at least one electroluminescent segment during the charging phase.

12. The method of claim 11, wherein the electroluminescent display comprises a plurality of parallel-connected electroluminescent segments, and wherein the method further comprises:

accumulating a corresponding voltage across each electroluminescent segment during the charging phase by transmitting a charging signal to each electroluminescent segment; and

dissipating the corresponding voltage accumulated across each electroluminescent segment during the discharging phase by connecting a corresponding shunt path across that electroluminescent segment.

13. The method of claim 12, further comprising controlling a corresponding final voltage accumulated across each electroluminescent segment at the end of the charging phase by partially discharging the corresponding voltage accumulated across that electroluminescent segment during the charging phase.

14. The method of claim 13, further comprising controlling the corresponding final voltage accumulated by each electroluminescent segment at the end of the charging phase independently of other electroluminescent segments, wherein the method further comprises generating different discharge control signals for at least two electroluminescent segments whereby the corresponding final voltages of the at least two electroluminescent segments differ.

15. The method of claim 13, further comprising completely discharging each electroluminescent segment during the discharging phase.

16. The method of claim 11, wherein accumulating the voltage across the electroluminescent segment during the charging phase comprises:

transmitting a charging signal to the electroluminescent segment from the power supply.

17. An integrated drive circuit for an electroluminescent display comprising a plurality of parallel-connected electroluminescent segments, the integrated drive circuit comprising:

a charge circuit coupled to each electroluminescent segment, the charge circuit configured to transmit energy

16

received from a power supply to the plurality of electroluminescent segments to accumulate an accumulated voltage across each electroluminescent segment, wherein the charge circuit comprises a storage element coupled to the power supply and a gating switch controllable to release energy from the storage element to the respective electroluminescent segment;

a discharge circuit coupled to each electroluminescent segment, each discharge circuit is configured to dissipate the accumulated voltage at each electroluminescent segment by selectively forming a shunt path across that electroluminescent segment to drain energy stored in that electroluminescent segment, wherein the discharge circuit comprises a shunt switch connected across the respective electroluminescent segment and is controllable to form the respective shunt path; and

a controller configured to control a final voltage of the accumulated voltage of at least one electroluminescent segment at an end of a charging phase by controlling the corresponding discharge circuit to at least partially discharge the accumulated voltage of the at least one electroluminescent segment during the charging phase.

18. The integrated drive circuit of claim 17, wherein the controller is configured to control the corresponding final voltage accumulated by each electroluminescent segment at the end of the charging phase independently of other electroluminescent segments, and the controller is configured to generate different discharge control signals for at least two electroluminescent segments whereby the corresponding final voltages of the at least two electroluminescent segments differ.

19. The integrated drive circuit of claim 17, wherein: each charge circuit is configured to transmit a charging signal to the plurality of electroluminescent segments to accumulate the corresponding voltage across each electroluminescent segment.

20. The integrated drive circuit of claim 17, wherein the controller is configured to reset the voltage across each electroluminescent segment by controlling each corresponding discharge circuit to completely discharge that electroluminescent segment during a discharging phase succeeding the charging phase.

* * * * *

专利名称(译)	用于多段电致发光显示器的集成驱动电路		
公开(公告)号	US9916784	公开(公告)日	2018-03-13
申请号	US15/194615	申请日	2016-06-28
[标]申请(专利权)人(译)	SCOBIL IND		
申请(专利权)人(译)	SCOBIL INDUSTRIES CORP.		
当前申请(专利权)人(译)	SCOBIL INDUSTRIES CORP.		
[标]发明人	PIETRO PATRICK D PIETRO WILLIAM J SAVEL PAUL		
发明人	PIETRO, PATRICK D. PIETRO, WILLIAM J. SAVEL, PAUL		
IPC分类号	G09G3/30 G09G3/12 H05B33/08		
CPC分类号	G09G3/12 G09G3/30 H05B33/08 Y02B20/325 G09G2310/061 G09G2330/028 Y02B20/32		
优先权	61/391927 2010-10-11 US		
其他公开文献	US20160379536A1		
外部链接	Espacenet USPTO		

摘要(译)

提供了用于多段电致发光显示器的集成驱动电路。在充电阶段，电致发光部分通过公共充电电路充电，并且使用与各个电致发光部分相关联的单独放电电路部分放电。控制器提供对各个放电电路的基本上独立的控制，从而在充电阶段结束时，EL片段可以被充电到相应不同的最终电压。然后在充电阶段之后的放电阶段期间，电致发光段被完全放电，由此发射大致与最终累积电压成比例变化的光强度。控制器可以用空间 - 时间光模式预先编程，使得使用所公开的集成驱动电路可以操作电致发光显示器以生成基本动画。

