



US007003338B2

(12) **United States Patent**
Weber et al.

(10) **Patent No.:** **US 7,003,338 B2**
(45) **Date of Patent:** **Feb. 21, 2006**

(54) **METHOD AND APPARATUS FOR
REDUCING COUPLING BETWEEN SIGNALS**

(75) Inventors: **Walter M. Weber**, Laguna Hills, CA
(US); **Ammar Al-Ali**, Costa Mesa, CA
(US)

(73) Assignee: **Masimo Corporation**, Irvine, CA (US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 106 days.

(21) Appl. No.: **10/615,333**

(22) Filed: **Jul. 8, 2003**

(65) **Prior Publication Data**

US 2005/0010092 A1 Jan. 13, 2005

(51) **Int. Cl.**
A61B 5/00 (2006.01)

(52) **U.S. Cl.** **600/336; 600/323**

(58) **Field of Classification Search** **600/322-323,**
600/336

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,960,128 A	10/1990	Gordon et al.
5,163,438 A	11/1992	Gordon et al.
5,337,744 A	8/1994	Branigan
5,431,170 A	7/1995	Mathews
5,452,717 A	9/1995	Branigan et al.
5,482,036 A	1/1996	Diab et al.
5,490,505 A	2/1996	Diab et al.
5,494,043 A	2/1996	O'Sullivan et al.
5,533,511 A	7/1996	Kaspari et al.
5,590,649 A	1/1997	Caro et al.
5,632,272 A	5/1997	Diab et al.
5,638,816 A	6/1997	Kiani-Azarbayjany et al.
5,638,818 A	6/1997	Diab et al.
5,645,440 A	7/1997	Tobler et al.
5,685,299 A	11/1997	Diab et al.

D393,830 S	4/1998	Tobler et al.
5,743,262 A	4/1998	Lepper, Jr. et al.
5,758,644 A	6/1998	Diab et al.
5,760,910 A	6/1998	Lepper, Jr. et al.
5,769,785 A	6/1998	Diab et al.
5,782,757 A	7/1998	Diab et al.
5,785,659 A	7/1998	Caro et al.
5,791,347 A	8/1998	Flaherty et al.
5,810,734 A	9/1998	Caro et al.
5,823,950 A	10/1998	Diab et al.
5,830,131 A	11/1998	Caro et al.
5,833,618 A	11/1998	Caro et al.
5,860,919 A	1/1999	Kiani-Azarbayjany et al.
5,890,929 A	4/1999	Mills et al.
5,904,654 A	5/1999	Wohltmann et al.
5,919,134 A *	7/1999	Diab 600/323

(Continued)


Primary Examiner—Eric F. Winakur

(74) *Attorney, Agent, or Firm*—Knobbe Martens Olson &
Bear LLP

(57) **ABSTRACT**

A method and an apparatus for separating a composite signal into a plurality of signals is described. A signal processor receives a composite signal and separates a composite signal in to separate output signals. Feedback from one or more of the output signals is provided to a configuration module that configures the signal processor to improve a quality of the output signals. In one embodiment, the signal processor separates the composite signal by applying a first demodulation signal to the composite signal to generate a first output signal. In one embodiment, the signal processor also applies a second demodulation signal to the composite signal to generate a second output signal. In one embodiment, a phase and/or amplitude of the first demodulation signal and a phase and/or amplitude of the second demodulation signal are selected to reduce crosstalk. In one embodiment, the composite signal is obtained from a detector in a system for measuring one or more blood constituents.


11 Claims, 4 Drawing Sheets



U.S. PATENT DOCUMENTS

5,934,925 A	8/1999	Tobler et al.	6,501,975 B1	12/2002	Diab et al.
5,940,182 A	8/1999	Lepper, Jr. et al.	6,515,273 B1	2/2003	Al-Ali
5,995,855 A	11/1999	Kiani et al.	6,525,386 B1	2/2003	Mills et al.
5,995,858 A *	11/1999	Kinast 600/323	6,526,300 B1	2/2003	Kiani et al.
5,997,343 A	12/1999	Mills et al.	6,541,756 B1	4/2003	Schulz et al.
6,002,952 A	12/1999	Diab et al.	6,542,764 B1	4/2003	Al-Ali et al.
6,011,986 A	1/2000	Diab et al.	6,580,086 B1	6/2003	Schulz et al.
6,027,452 A	2/2000	Flaherty et al.	6,584,336 B1	6/2003	Ali et al.
6,036,642 A	3/2000	Diab et al.	6,597,933 B1	7/2003	Kiani et al.
6,045,509 A	4/2000	Caro et al.	6,606,511 B1	8/2003	Ali et al.
6,067,462 A	5/2000	Diab et al.	6,632,181 B1	10/2003	Flaherty et al.
6,081,735 A	6/2000	Diab et al.	6,640,116 B1	10/2003	Diab
6,088,607 A	7/2000	Diab et al.	6,643,530 B1	11/2003	Diab et al.
6,110,522 A	8/2000	Lepper, Jr. et al.	6,650,917 B1	11/2003	Diab et al.
6,151,516 A	11/2000	Kiani-Azarbayjany et al.	6,654,624 B1	11/2003	Diab et al.
6,152,754 A	11/2000	Gerhardt et al.	6,658,276 B1	12/2003	Kiani et al.
6,157,850 A	12/2000	Diab et al.	6,671,531 B1	12/2003	Al-Ali et al.
6,165,005 A	12/2000	Mills et al.	6,678,543 B1	1/2004	Diab et al.
6,184,521 B1	2/2001	Coffin, IV et al.	6,684,090 B1	1/2004	Ali et al.
6,206,830 B1	3/2001	Diab et al.	6,697,656 B1	2/2004	Al-Ali
6,229,856 B1	5/2001	Diab et al.	6,697,658 B1	2/2004	Al-Ali
6,236,872 B1	5/2001	Diab et al.	RE38,476 E	3/2004	Diab et al.
6,256,523 B1	7/2001	Diab et al.	6,699,194 B1	3/2004	Diab et al.
6,263,222 B1	7/2001	Diab et al.	6,714,804 B1	3/2004	Al-Ali et al.
6,278,522 B1	8/2001	Lepper, Jr. et al.	RE38,492 E	4/2004	Diab et al.
6,280,213 B1	8/2001	Tobler et al.	6,725,075 B1	4/2004	Al-Ali
6,285,896 B1	9/2001	Tobler et al.	6,745,060 B1	6/2004	Diab et al.
6,334,065 B1	12/2001	Al-Ali et al.	6,760,607 B1	7/2004	Al-Ali
6,349,228 B1	2/2002	Kiani et al.	6,770,028 B1	8/2004	Ali et al.
6,360,114 B1	3/2002	Diab et al.	6,771,994 B1	8/2004	Kiani et al.
6,371,921 B1	4/2002	Caro et al.	6,792,300 B1	9/2004	Diab et al.
6,377,829 B1	4/2002	Al-Ali	6,813,511 B1	11/2004	Diab et al.
6,388,240 B1	5/2002	Schulz et al.	6,816,741 B1	11/2004	Diab et al.
6,397,091 B1	5/2002	Diab et al.	6,822,564 B1	11/2004	Al-Ali
6,430,525 B1	8/2002	Weber et al.	6,826,419 B1	11/2004	Diab et al.
6,463,311 B1	10/2002	Diab	6,830,711 B1	12/2004	Mills et al.
6,470,199 B1	10/2002	Kopotic et al.			

* cited by examiner








FIG. 3





METHOD AND APPARATUS FOR REDUCING COUPLING BETWEEN SIGNALS

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to the field of signal processing, and, more particularly, relates to multi-channel demodulators for demodulating mixed signals, such as, for example, signals generated in a pulse oximetry system.

2. Description of the Related Art

In many multi-channel measurement and communication systems, crosstalk between channels and corruption of data within the channels are significant problems. Such problems can arise from variations in manufacturing tolerances, movement, propagation delays, phase shifts, temperature effects, degradation of components due to age or other factors, noise, etc.

A pulse oximetry system is one example of a system where the above-referenced problems are found. In a pulse oximetry system, blood oxygen saturation is determined by transmitting pulses of electromagnetic energy through a portion of a subject having blood flowing therein (e.g., through a finger, through an ear lobe, or other portion of the body where blood flows close to the skin). The pulses of electromagnetic energy comprise periodic pulses of red light having wavelengths of approximately 660 nanometers, for example, and periodic pulses of infrared light having wavelengths of approximately 905 nanometers.

After propagating through the portion of the subject, the red pulses and the infrared pulses are detected by a detector which is responsive to light at both wavelengths and which generates an electrical signal that has a relationship to the intensity of the electromagnetic energy incident on the detector. The detector output is a two-channel signal having a first signal component corresponding to the detected red pulses and a second signal component corresponding to the detected infrared pulses.

The two-channel signal is demodulated to recover separate signals corresponding to the first signal component and the second signal component. However, prior art demodulators are not sufficiently accurate enough to completely separate the two signal components in all cases. Thus, it is not uncommon for the first demodulator output signal (corresponding to the first signal component) to contain residual components of the second signal and vice versa. This crosstalk between the first and second signal components reduces the accuracy of the recovered first and second signals. In multi-channel systems with more than two channels, crosstalk can occur between all of the channels, again reducing accuracy.

SUMMARY OF THE INVENTION

The present invention solves these and other problems by separating a combined multi-channel signal into a plurality of output signals in a manner that reduces crosstalk and other contamination in the plurality of output signals. In one embodiment, the separator includes a multi-channel demodulator that is first configured using nominal values for the various components in the signal path. In one embodiment, the multi-channel demodulator is further configured using data obtained from calibration measurements. In one embodiment, the calibration measurements are made during an initialization period. In one embodiment, the calibration measurements are made frequently, continuously, or at selected intervals. In one embodiment, calibrations are per-

formed on at least one of, initialization, on command, on attachment of a new sensor, continuously, and/or interspersed with measurements. In one embodiment of a system for measuring one or more blood constituents, the calibration measurements are made when the system detects that a patient has been connected to the system. In one embodiment, the multi-channel demodulator is further configured at regular intervals by re-running the calibration measurements. In one embodiment, the multi-channel demodulator comprises an optimizing demodulator. In one embodiment, crosstalk in the multi-channel demodulator is reduced by computing an amplitude and/or phase adjustment of one or more demodulation signals that are provided respectively to one or more mixers.

In one embodiment, an apparatus for measuring blood oxygenation in a subject includes a first signal source which applies a first input signal during a first time interval. A second signal source applies a second input signal during a second time interval. A detector detects a first parametric signal responsive to the first input signal passing through a portion of the subject having blood therein and detects a second parametric signal responsive to the second input signal passing through the portion of the subject. The detector generates a detector output signal responsive to the first and second parametric signals. A signal processor receives the detector output signal and demodulates the detector output signal by applying a first demodulation signal to a signal responsive to the detector output signal to generate a first demodulator output signal and applying a second demodulation signal to the signal responsive to the detector output signal to generate a second demodulator output signal. In one embodiment, the first demodulation signal has at least one component comprising a first frequency, a first phase, and a first amplitude; and the second demodulation signal has at least one component comprising a second frequency, a second phase, and a second amplitude. In one embodiment, the first phase and the second phase are chosen to reduce crosstalk from the first parametric signal to the second demodulator output signal and to reduce crosstalk from the second parametric signal to the first demodulator output signal. In one embodiment, the first amplitude and the second amplitude are chosen to reduce crosstalk from the first parametric signal to the second demodulator output signal and to reduce crosstalk from the second parametric signal to the first demodulator output signal. In one embodiment, at least one of the first amplitude, the first phase, the second amplitude, and the second phase are chosen to reduce crosstalk from the first parametric signal to the second demodulator output signal and to reduce crosstalk from the second parametric signal to the first demodulator output signal.

In one embodiment, at least one of the first amplitude, the first phase, the second amplitude, and the second phase is determined by turning off one of the first and second signal sources and measuring the crosstalk between one of the parametric signals and the non-corresponding output signal.

One embodiment includes a method of reducing crosstalk between two signals generated by applying a first pulse and a second pulse to measure a parameter. The first pulse and the second pulse are applied periodically at a repetition rate defining a period. The first pulse is generated during a first interval in each period and the second pulse is generated during a second interval in each period. In one embodiment, the second interval is spaced apart from the first interval. In one embodiment, the second interval overlaps at least a portion of the first interval. The first and second pulses produce first and second parametric signals responsive to the

parameter. The first and second parametric signals are received by a detector which outputs a composite signal responsive to the first and second parametric signals. The method includes applying a first demodulation signal to the composite signal to generate a first demodulated output signal. The first demodulation signal includes at least one component having at least a first amplitude and a first phase. The method further includes applying a second demodulation signal to the composite signal to generate a second demodulated output signal. The second demodulation signal includes at least one component having at least a second amplitude and a second phase. The method further includes lowpass filtering the first demodulated output signal to generate a first recovered output signal responsive to the first parametric signal, and lowpass filtering the second demodulated output signal to generate a second recovered output signal responsive to the second parametric signal. The method also includes choosing at least one of the first phase, the first amplitude, the second phase, and the second amplitude to reduce crosstalk components in the first recovered output signal and the second recovered output signal. In one embodiment, the method also includes choosing the first phase and/or the second phase to reduce crosstalk components in the first recovered output signal and the second recovered output signal.

In one embodiment, the first phase and the second phase are chosen by applying a first light pulse pattern during a first time period and measuring the first recovered output during the first time period as a first calibration output, and measuring the second recovered output during the first time period as a second calibration output. The method includes applying a second light pulse pattern during a second time period and measuring the first recovered output during the first time period as a third calibration output and measuring the second recovered output during the second time period as a fourth calibration output. The method further includes computing the first phase and the second phase from at least the first calibration output, the second calibration output, the third calibration output, and the fourth calibration output.

In one embodiment the first phase is computed from a ratio of the first calibration output and the second calibration output.

In one embodiment, the first demodulation signal includes a sum of a first demodulation component having a first amplitude and a second demodulation component having a second amplitude. The second demodulation component is in quadrature with the first demodulation component and the act of choosing the first phase involves choosing the first amplitude and the second amplitude. In one embodiment the quadrature components are sinusoidal and cosinusoidal.

In one embodiment, the first demodulation signal includes a sum of a sinusoidal component having a first amplitude and a cosinusoidal component having a second amplitude. The first amplitude and the second amplitude are chosen by a least squares minimization of an error corresponding to the crosstalk. In one embodiment, the error is integrated over a time period corresponding to an integer number of cycles of the sinusoidal component.

In one embodiment, a first demodulation signal is applied to a composite signal having first and second coefficients to generate a first demodulated signal. The first demodulation signal includes a first component having a first amplitude and a second component having a second amplitude. The first and second components being in quadrature. The second amplitude has a predetermined relationship to the first amplitude. The predetermined relationship is selected to cause the first demodulated signal to have lower frequency components that include a primary component corresponding primarily to the first desired component and a residual

component corresponding to the second component. The first demodulated signal is lowpass filtered to generate a first output signal. At least one of the first amplitude and the second amplitude are adjusted to reduce the residual component with respect to the primary component.

In one embodiment, a pulse oximetry system includes a modulation signal generator. The modulation signal generator generates a first modulation signal including a first pulse at a repetition frequency having a first duty cycle. The modulation signal generator generates a second modulation signal including a second pulse which also repeats at the repetition frequency and having a second duty cycle. The second pulse can be non-overlapping with respect to the first pulse, or the second pulse can partially or completely overlap the first pulse. The first and second pulses include a plurality of components wherein a first component has a frequency corresponding to the repetition frequency and a second component has a second frequency corresponding to twice the first frequency. A first transmitter emits electromagnetic energy at a first wavelength in response to the first pulse. A second transmitter emits electromagnetic energy at a second wavelength in response to the second pulse. A detector receives electromagnetic energy at the first and second wavelengths after passing through a portion of a subject. The detector generates a detector output signal responsive to the received electromagnetic energy. The detector output signal includes a signal component responsive to attenuation of the electromagnetic energy at the first wavelength and a signal component responsive to attenuation of the electromagnetic energy at the second wavelength. A first demodulator multiplies the detector signal by a first demodulation signal and generates a first demodulated output signal. A second demodulator multiplies the detector signal by a second demodulation signal and generates a second demodulated output signal. A configuration module configures the first demodulation signal and the second demodulation signal to substantially separate the first demodulator output and the second demodulator output.

In one embodiment, the configuration module selects a phase relationship between the first demodulation signal and the second demodulation signal.

In one embodiment, the configuration module configures the first demodulation signal and the second demodulation signal using, at least in part, data obtained during a calibration period. In one embodiment, the calibration data includes first and second calibration data corresponding to the first and second demodulated output signals during a first time period, and third and fourth calibration data corresponding to the first and second demodulated output signals during a second time period. In one embodiment, the second transmitter is turned off during the first time period, and the first transmitter is turned off during the second time period.

In one embodiment, the configuration module configures the first demodulation signal and the second demodulation signal by adjusting initial parameters that define the first demodulation signal and the second demodulation signal. The configuration module adjusts the initial parameters using, at least in part, the calibration data obtained during a calibration period.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be described below in connection with the accompanying figures.

FIG. 1 is a block diagram of a multi-channel processing system that uses feedback from one or more outputs to configure the operation of a signal separator that separates a composite signal into a plurality of output signals.

FIG. 2 is a block diagram of a two-channel signal processing system to determine blood oxygen saturation in a

subject, wherein illumination is provided by back-to-back Light-Emitting Diodes (LEDs).

FIG. 3 is a block diagram of a multi-channel signal processing system to determine blood constituents (e.g., oxygen saturation) in a subject, wherein illumination is provided by N diodes or illumination sources.

FIG. 4 is a block diagram of a specific embodiment of the multi-channel processing system of FIG. 1.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

FIG. 1 shows a topology of a multi-channel measurement or communication system **100**. The system **100** has a signal combiner **103** for combining one or more input signals $S_1 \dots S_N$ into a composite signal and a signal separator **104** for separating the composite signal into one or more output signals $\hat{S}_1 \dots \hat{S}_M$. The output signals $\hat{S}_1 \dots \hat{S}_M$ can include estimates of the input signals $S_1 \dots S_N$. The input signals $S_1 \dots S_N$ are corrupted by pre-combination distortion **101–102** respectively, and, optionally, by combination distortion in the signal combiner **103**. The combiner **103** combines the N input signals into a composite signal (or composite signals). The combiner **401** can combine signals by addition, subtraction, multiplication, division, modulation, non-linear processes, linear processes, estimation, combinations thereof, etc. The composite signal is provided through a communication channel to the separator **104**. The composite signal is distorted by communication channel distortion **110**. The separator **104** separates the composite signal into M output signals, where M can be less than N, greater than N, or equal to N. In one embodiment, the separator also provides one or more additional output signals $\hat{n}_0 \dots \hat{n}_K$ corresponding to estimates of other signals, such as, for example, noise signals, error signals, etc.

Due to errors in the system **100**, the output signals $\hat{S}_1 \dots \hat{S}_M$ are typically not exact copies of the input signals, but rather are estimates of the input signals. The accuracy of these estimates is a measure of system performance. The pre-combination distortion **101–102**, the combiner distortion, and/or the channel distortion **110** tend to introduce crosstalk between the channels and thereby corrupt the output signals. The pre-combination distortion **101–102**, combiner distortion, and the channel distortion **110** can be caused by variations in manufacturing tolerances, delay, movement, temperature effects, degradation of components due to age or other factors, noise, etc.

A module **105** is provided to configure the separator **104** to improve the quality of the separation function and thereby improve the quality of the output signals. One or more of the output signals from the separator are provided to the module **105** to provide feedback regarding the quality of the output signals and/or feedback regarding the operation of the separator **104**. The module **105** uses feedback from one or more of the output signals $\hat{S}_1 \dots \hat{S}_M$ (and, optionally, the output signals $\hat{n}_0 \dots \hat{n}_K$) to monitor the quality of the separation function and to provide control information to control the operation of the separator. In one embodiment, the module **105** is configured by using configuration data obtained from the combiner **103**. Such configuration data can be obtained by calibration procedures that test the operation of the combiner **103** before or during system use.

In one embodiment, the module **105** configures demodulators in the signal separator **104** using, at least in part, calibration data obtained during a calibration period. For example, in one embodiment involving a two channel system, the calibration data includes first and second calibration

data corresponding to the first and second output signals during a first time period, and third and fourth calibration data corresponding to the first and second demodulated output signals during a second time period. In one embodiment, the second transmitter is turned off during the first time period, and the first transmitter is turned off during the second time period. In one embodiment, the module **105** configures the first demodulation signal and the second demodulation signal by adjusting initial parameters that define the first demodulation signal and the second demodulation signal. The configuration module adjusts the initial parameters using, at least in part, the calibration data obtained during a calibration period.

FIG. 2 is a block diagram of a two-channel signal processing system **200** that fits the general topology shown in FIG. 1. The system **200** is configured to determine one or more blood constituents in a subject, such as, for example, a human subject. In the example presented, the measurements are performed on a portion of the subject, such as a finger **202** illustrated in FIG. 2A. An LED modulation circuit **204** drives a pair of back-to-back light emitting diodes (LEDs) **206, 208** by applying a periodic signal to the two light emitting diodes **206, 208**. Light from the diodes **206, 208** passes through the finger **202** and is detected by a detector **250**. An output from the detector **250** is provided to a signal processing block **270**. A control output from the signal processing block **270** is provided to the LED modulation circuit **204**. The signal processing block **270** also provides outputs \hat{S}_1 and \hat{S}_2 corresponding to the light detected from the diodes **206, 208**, and, optionally, output signals $\hat{n}_0 \dots \hat{n}_K$ corresponding to estimates of noise or other signals.

In one embodiment, the LED **206** is selected to emit electromagnetic energy in the red visible light range, and has a wavelength of, for example, approximately 660 nanometers. The LED **208** is selected to emit electromagnetic energy in the infrared range, and has a wavelength of, for example, approximately 905 nanometers. The LED modulation circuit **204** supplies current to activate the LEDs **206** and **208**. Each LED is activated for a time period τ which can be different for the different LEDs. The pulses from the LEDs **206** and **208** repeat with a periodicity T .

FIG. 3 is a block diagram of a multi-channel signal processing system **300** that also fits the topology shown in FIG. 1. Like the system **200**, the system **300** is configured to determine blood oxygen saturation or other blood constituents in a subject, such as, for example, a human subject. In FIG. 3, an LED modulation circuit **314** drives N diodes, where N is two or greater, thus allowing greater flexibility than the system **200**. In FIG. 3, the diodes **206** and **208** are shown, along with an N'th diode **309**, it being understood that the diode **309** is omitted if $N=2$. The LED modulation circuit **314** is configured to allow the diodes **206, 208**, and **309** to be driven independently such that the diodes can be driven at separate times or in overlapping time periods if desired. Light from the diodes **206, 208, 309** passes through the finger **202** and is detected by the detector **250**. The output from the detector **250** is provided to a signal processing block **371**. A control output from the signal processing block **371** is provided to the LED modulation circuit **314**. The signal processing block **371** also provides outputs S_1 through S_M , where M is greater than or equal to one, but need not be equal to N.

FIG. 4 shows one embodiment of an adjustable multi-channel modulator/demodulator system **400**. The system **400** is based on the topology of the system **100** and can be used in a system for measuring blood constituents (e.g.,

pulse oximetry, carboxyhemoglobin, etc.) as shown in FIGS. 2 and 3. In the system 400, an input $S_1(t)$ and a modulation input $M_1(t)$ are provided to a first modulator 491. A signal input $S_N(t)$ and a modulation input $M_N(t)$ are provided to an N^{th} modulator 402.

The photodetector 250 is modeled as an adder 405. The outputs of the modulators 491 and 402 are added together in the adder 405, in the presence of noise $n(t)$ to generate a composite signal $M(t)$ where:

$$S(t) = S_1(t)M_1(t) + \dots + S_N(t)M_N(t) + n(t) \quad (1)$$

The $S(t)$ signal output of the adder 405 (i.e., the output of the detector 250) is applied to the input of a signal-processing block 410. Within the signal-processing block 410, the signal $S(t)$ is passed through an amplifier 497 and through an analog bandpass filter 498. The analog bandpass filter 498 provides anti-aliasing and removal of low frequency noise and DC. The desired signal components in the signals $S_i(t)$ are frequency shifted by the operation of the modulation signals $M_i(t)$ and are passed by the analog bandpass filter 498.

The output of the analog bandpass filter 498 is sampled by an analog-to-digital converter 499 and converted therein to digital signals and provided to an input of an optional decimation block 420.

The filtered (and, optionally, decimated) signal $S(t)$ is sampled to produce a sampled-data signal $S(k)$ that is provided to the first input of the first mixer 424, to the first input of the N^{th} mixer 412, and to the first input of a noise channel mixer 413. A first demodulating signal $D_1(k)$ is provided to a second input of a first mixer 424 from a signal generator 431. The N^{th} demodulating signal $D_N(k)$ is provided to an N^{th} mixer 412 from an output of a signal generator 432. The noise demodulating signal $D_0(k)$ is provided to the noise channel mixer 413 from an output of a signal generator 441. A control input to each of the signal generators 431, 432, and 441 is provided by the output of the adjuster algorithm 450. In yet another embodiment, the adjuster algorithm 450 may also be controlled by other signal processing elements downstream of the signal processor 400.

The outputs of the mixers 413, 424, and 412 are provided as respective inputs to decimation blocks 440, 430, and 434 respectively. Each of the decimation blocks 440, 430, and 434 has a control input provided by the output of the adjuster algorithm block 450. The output of the decimation block 440 is an estimate of the signal $n(t)$ and it is provided to an input of the adjuster algorithm block 450. In an alternate embodiment, the signal estimates $\hat{S}_i(k)$ are also provided to the adjuster algorithm block 450.

An output of the decimator 430 is a signal $\hat{S}_1(k)$, which, as discussed above, is an estimate of the signal $S_1(k)$ (where $S_1(k)$ corresponds to a sampled-data representation of $S_1(t)$). Likewise, the output of the decimation block 434 is an estimate of the signal $S_N(t)$. As shown above, the selection of the demodulating signals $D_i(t)$ for $i=0 \dots N$ in accordance with the present invention substantially reduces or eliminates the effects of noise in the output signals $\hat{S}_i(k)$ and $n(k)$, and also substantially reduces or eliminates crosstalk between the signals.

When the system 400 is used in connection with a blood constituent measurement system as shown in FIGS. 2 and 3 the red LED 206 provides a light intensity represented as I_{RD} , and the infrared LED 208 provides a light intensity represented as I_{IR} . The effects of turning the LEDs 206, 208 on and off on a periodic bases are modeled by the first multiplier or modulator 290 which applies a first modulation signal $M_1(t)$ to the red light intensity to generate a modulated red signal $I_{RDMOD}(t)$ and by a second multiplier the modulator 292 which applies a second modulation signal $M_2(t)$ to

the infrared light intensity to generate a modulated infrared signal $I_{IMOD}(t)$. The modulated light red signal and the modulated infrared signal are applied to the finger 202, or other body portion, as described above. The blood in the finger 202 has a volume and scattering components, which vary throughout each cardiac cycle. The blood carries oxygen and other materials therein. The oxygen content is a function of both the blood volume and the concentration of the oxygen in the blood volume. The concentration of the oxygen in the blood volume is generally measured as blood oxygen saturation for reasons which are described in full in U.S. Pat. Nos. 5,482,036 and 5,490,505, both of which are hereby incorporated by reference in their entirety. As further described in the two referenced patents, the blood oxygen saturation is determined by comparing the relative absorption of the red light and the infrared light in the finger 202. The comparison is complicated by the noise caused by movement, ambient light, light scattering, and other factors. The signals $S_1(t)$ and $S_2(t)$ represent the effect of the time-varying volume and scattering components of the blood in the finger 202 on the red light and the infrared light, respectively, passing through the finger 202 from the LEDs 206, 208 to the detector 250.

As shown in FIG. 4, a set of $N+1$ signals $S_i[k]$, $i=1 \dots N$, and $n(k)$ are sampled at a desired sample rate. The signals are combined according to the formula:

$$S(k) = M_1(k)S_1(k) + \dots + M_N(k)S_N(k) + n(k) \quad (2)$$

In one embodiment, each of the decimators 420, 440, 430, and 434 includes a digital lowpass filter and a sample rate compressor. In one embodiment, the characteristics of the digital lowpass filters (e.g., the number of filter coefficients and values of the filter coefficients) and the sample rate compression factor of each decimator are fixed. In one embodiment, the characteristics of the digital lowpass filters (e.g., the number of filter coefficients or values of the filter coefficients) and the sample rate compression factor of each decimator are provided by the adjustment algorithm 450. The signal generators 431, 432 and 441 generate the demodulation sequences for the demodulators 424, 412, and 413 respectively. The demodulation sequences produced by the signal generators 431, 432 and 441 are controlled by the adjuster algorithm 450.

In one embodiment, the adjuster algorithm 450 adjusts the pre-demodulation decimation rate R_1 (in the demodulator 420), and the post-demodulation decimation rate R_2 (in the demodulators 430, 434 and 440) according to the noise in the noise estimate $\hat{n}(k)$ and (optionally) according to the signals $\hat{S}_i(k)$. The product $R_1 R_2$ is the total decimation rate from the signal $S(k)$ at the output of the A/D converter 499 to the signals $\hat{S}_i(k)$ at the output of the signal processing block 400. The adjuster algorithm may adjust R_1 and R_2 such that the product $R_1 R_2$ varies, or the adjuster algorithm may adjust R_1 and R_2 such that the product $R_1 R_2$ is substantially constant. Typically, the adjuster algorithm will keep the $R_1 R_2$ product constant so that the signal processing blocks downstream of the signal processor 400 will operate at a substantially constant sample rate.

In one embodiment, the adjuster algorithm 450 adjusts the demodulation signals $D_i(k)$ to reduce or eliminate crosstalk. In one embodiment, the adjuster algorithm 450 reduces crosstalk by configuring the demodulators, as discussed in more detail below.

One skilled in the art will recognize that the lowpass filters provided in connection with the decimation blocks can provide other filter functions in addition to lowpass filtering. Thus, for example, the lowpass filters 420, 430, 440, and 450, and the decimators 420, 430, 434, and 440 can provide other filter functions (in addition to lowpass filtering) such as, for example, bandpass filtering, bandstop

filtering, etc. Moreover, the post-demodulation decimation rate R_2 need not be the same for each output channel. Thus, for example, in FIG. 4, the decimator 440 can have a first decimation rate $R_2=r_1$ while the decimators 430 and 434 have a second decimation rate $R_2=r_2$.

The demodulators above are described in terms of digital signal processing on sampled data. Thus, the demodulator signals are written $D_i(k)$. The demodulators and the filtering associated with the demodulators can be done in using analog processing (using time-domain demodulator signals $D_i(t)$) or on sampled data signals (using digital-domain demodulator signals $D_i(k)$). For convenience, the following development describes the demodulator signals primarily in the time domain, with the understanding that the modulators can be implemented using digital signal processing or analog processing.

The characteristics of the demodulation signals $D_1(t)$ and $D_2(t)$ affect how much crosstalk is seen in the output signals. In an diagonal system, that is, when the demodulator has been diagonalized, there is, ideally, no crosstalk. The first output signal $\hat{S}_1(t)$ is an estimate (or approximation) to the signal $S_1(t)$. Similarly, the second output signal $\hat{S}_2(t)$ is an estimate (or approximation) to the signal $S_2(t)$. When the composite signal $S(t)$ is a linear combination of the signals $S_i(t)$, then the relationship between the signals $S_i(t)$ and the signals $\hat{S}_i(t)$. When $M_1=\cos \omega t$, $M_2=\sin \omega t$, $n(t)=0$, and there is no distortion (e.g., no pre-combination, combiner, or channel distortion) then:

$$S(t)=S_1(t)\cos \omega t+S_2(t)\sin \omega t \quad (3) \quad 30$$

Then:

$$\hat{S}_1(t)=LP[D_1(t)S(t)] \quad (4)$$

$$\hat{S}_2(t)=LP[D_2(t)S(t)] \quad (5) \quad 35$$

If:

$$D_1(t)=2 \cos \omega t \quad (6)$$

$$D_2(t)=2 \sin \omega t \quad (7) \quad 40$$

then

$$\begin{aligned} D_1(t)S(t) &= 2S_1(t)\cos^2\omega t + 2S_2(t)\sin\omega\cos\omega t \\ &= S_1(t) - S_1(t)\cos 2\omega t + S_2(t)\sin 2\omega t \end{aligned} \quad (8) \quad 45$$

After lowpass filtering to remove the terms with a frequency of $2\omega t$ and higher 50

$$\hat{S}_1(t)=S_1(t) \quad (9)$$

Similarly for

$$\hat{S}_2(t)=LP[D_2(t)S(t)] \quad (10) \quad 55$$

then

$$\begin{aligned} D_2(t)S(t) &= 2S_1(t)\sin\omega\cos\omega t + 2S_2(t)\sin^2\omega t \\ &= S_2(t) - S_2(t)\cos 2\omega t + S_1(t)\sin 2\omega t \end{aligned} \quad (11) \quad 60$$

After lowpass filtering to remove the terms with a frequency of $2\omega t$ 65

$$\hat{S}_2(t)=S_2(t) \quad (12)$$

In the above analysis, it was assumed that there are no time delays or phase shifts in the signal $S(t)$, and thus, configuration is relatively straightforward

When an unknown delay (or phase error) is introduced, then the signals are no longer diagonal. Consider, for example, the situation when a delay Δ is introduced into the composite signal. Then:

$$S(t)=\cos \omega(t-\Delta)S_1(t-\Delta)+\sin \omega(t-\Delta)S_2(t-\Delta) \quad 10$$

It then follows that:

$$\begin{aligned} \hat{S}_1(t) &= LP[2\cos\omega t(\cos\omega(t-\Delta)S_1(t-\Delta) + \sin\omega(t-\Delta)S_2(t-\Delta))] = \\ &LP[2\cos\omega t(\cos\omega t\cos\omega\Delta + \sin\omega t\sin\omega\Delta)S_1(t-\Delta)] + \\ &LP[2\cos\omega t(\sin\omega t\cos\omega\Delta - \cos\omega t\sin\omega\Delta)S_2(t-\Delta)] = \\ &\cos\omega\Delta S_1(t-\Delta) - \sin\omega\Delta S_2(t-\Delta) \end{aligned} \quad 20$$

The above equations can be expressed in matrix form as:

$$\begin{bmatrix} \hat{S}_1(t) \\ \hat{S}_2(t) \end{bmatrix} = \begin{bmatrix} \cos\omega\Delta & -\sin\omega\Delta \\ \sin\omega\Delta & \cos\omega\Delta \end{bmatrix} \begin{bmatrix} S_1(t-\Delta) \\ S_2(t-\Delta) \end{bmatrix} \quad (13) \quad 25$$

Then

$$\begin{bmatrix} S_1(t-\Delta) \\ S_2(t-\Delta) \end{bmatrix} = \begin{bmatrix} \cos\omega\Delta & \sin\omega\Delta \\ -\sin\omega\Delta & \cos\omega\Delta \end{bmatrix} \begin{bmatrix} \hat{S}_1(t) \\ \hat{S}_2(t) \end{bmatrix} \quad (14) \quad 30$$

The above equation can be expressed as

$$\begin{aligned} \begin{bmatrix} S_1(t-\Delta) \\ S_2(t-\Delta) \end{bmatrix} &= \begin{bmatrix} \cos\omega\Delta & \sin\omega\Delta \\ -\sin\omega\Delta & \cos\omega\Delta \end{bmatrix} \cdot LP \begin{bmatrix} D_1(t)S(t) \\ D_2(t)S(t) \end{bmatrix} \\ &= LP \begin{bmatrix} \cos\omega\Delta & \sin\omega\Delta \\ -\sin\omega\Delta & \cos\omega\Delta \end{bmatrix} \begin{bmatrix} D_1(t) \\ D_2(t) \end{bmatrix} S(t) \\ &= LP \begin{bmatrix} D_1(t) \\ \bar{D}_2(t) \end{bmatrix} S(t) \end{aligned} \quad (15) \quad 40$$

where

$$\begin{aligned} \bar{D}_1(t) &= \cos\omega D_1(t) + \sin\omega\Delta D_2(t) \\ &= 2\cos\omega\Delta\cos\omega t + 2\sin\omega\Delta\sin\omega t \end{aligned}$$

and similarly for $\bar{D}_2(t)$. Thus the modified demodulation functions $\bar{D}_1(t)$ and $\bar{D}_2(t)$ can be expressed as a linear combination of basis functions. If the time delay Δ can be predicted, then the demodulator functions can be calculated and programmed into the communication system. However, in many cases the time delay Δ is not known or changes over time. As described below, the demodulator functions can be determined by system calibration procedures.

When an unknown phase shift (or phase error) is introduced, then there may be crosstalk in the system. Consider, for example, the situation when a phase error ϕ_1 occurs in the signal $S_1(t)$ and a phase error ϕ_2 occurs in the signal $S_2(t)$. The phase errors can be caused by intrinsic properties of the components, intrinsic properties of the system, component variations, time delays, etc. In the presence of the phase errors:

$$\begin{aligned}
D_1(t)S(t) &= 2A_1S_1(t)\sin(\omega t + \phi_1)\sin\omega t + 2A_2S_2(t)\cos(\omega t + \phi_2)\sin\omega t = \\
&2A_1S_1(t)\sin\omega t[\sin\omega t\cos\phi_1 + \cos\omega t\sin\phi_1] + \\
&2A_2S_2(t)\sin\omega t[\cos\omega t\cos\phi_2 + \sin\omega t\sin\phi_2] = \\
&A_1S_1(t)\cos\phi_1 - A_1S_1(t)\cos\phi_1\cos 2\omega t + A_1S_1(t)\sin\phi_1\sin 2\omega t + \\
&A_2S_2(t)\cos\phi_2\sin 2\omega t - A_2S_2(t)\sin\phi_2 + A_2S_2(t)\sin\phi_2\cos 2\omega t
\end{aligned} \quad (16)$$

Thus, after lowpass filtering

$$\hat{S}_1(t) = A_1S_1(t)\cos\phi_1 - A_2S_2(t)\sin\phi_2 \quad (17)$$

The above equation shows crosstalk because $\hat{S}_1(t)$ depends in part on components of $S_2(t)$ when $A_2 \neq 0$ and $\phi_2 \neq n\pi$ where $n=0, \pm 1, \pm 2, \dots$

Similarly,

$$\hat{S}_2(t) = A_1S_1(t)\sin\phi_1 + A_2S_2(t)\cos\phi_2 \quad (18)$$

The above equations can be expressed in matrix form as:

$$\begin{bmatrix} \hat{S}_1(t) \\ \hat{S}_2(t) \end{bmatrix} = \begin{bmatrix} A_1\cos\phi_1 & -A_2\sin\phi_2 \\ A_1\sin\phi_1 & A_2\cos\phi_2 \end{bmatrix} \begin{bmatrix} S_1(t) \\ S_2(t) \end{bmatrix} \quad (19)$$

After inversion

$$\begin{bmatrix} S_1(t) \\ S_2(t) \end{bmatrix} = \frac{1}{\cos(\phi_1 - \phi_2)} \begin{bmatrix} \frac{\cos\phi_2}{A_1} & \frac{\sin\phi_1}{A_1} \\ -\frac{\sin\phi_2}{A_2} & \frac{\cos\phi_1}{A_2} \end{bmatrix} \begin{bmatrix} \hat{S}_1(t) \\ \hat{S}_2(t) \end{bmatrix} \quad (20)$$

$$\begin{bmatrix} S_1(t) \\ S_2(t) \end{bmatrix} = \frac{1}{\cos(\phi_1 - \phi_2)} \begin{bmatrix} \frac{\cos\phi_2}{A_1} & \frac{\sin\phi_1}{A_1} \\ -\frac{\sin\phi_2}{A_2} & \frac{\cos\phi_1}{A_2} \end{bmatrix} \begin{bmatrix} D_1(t) \\ D_2(t) \end{bmatrix} S(t) \quad (21)$$

Then

$$\begin{bmatrix} S_1(t) \\ S_2(t) \end{bmatrix} = \begin{bmatrix} \bar{D}_1(t) \\ \bar{D}_2(t) \end{bmatrix} S(t) \quad (22)$$

Where $\bar{D}_i(t)$ are modified demodulation functions, given by:

$$\begin{bmatrix} \bar{D}_1(t) \\ \bar{D}_2(t) \end{bmatrix} = \frac{1}{\cos(\phi_1 - \phi_2)} \begin{bmatrix} \frac{\cos\phi_2\sin\omega t + \sin\phi_1\cos\omega t}{A_1} \\ \frac{-\sin\phi_2\sin\omega t + \cos\phi_1\cos\omega t}{A_2} \end{bmatrix} \quad (23)$$

The modified demodulation functions have the form

$$\bar{D}_i(t) = \sum_{j=1}^N \alpha_j \Phi_j(t) \quad (24)$$

Choosing the coefficients α_j to eliminate crosstalk configures the modulator.

In one embodiment, the coefficients α_j can be fixed coefficients computed using known properties of the system. However, as system properties change over time, such fixed coefficients may lead to unacceptably high levels of

crosstalk. Moreover, variations from device to device may cause the fixed coefficients to give unacceptably high levels of crosstalk.

Higher performance (that is, lower crosstalk) can be obtained by computing the coefficients as part of a system calibration or initialization procedure. Such calibration can be performed during system startup (e.g., when the system is turned on, or when the system begins processing data, etc.) and/or at regular intervals. In one embodiment, the adjuster algorithm 450 computes the coefficients α_j from the calibration data. In one embodiment, the coefficients α_j are chosen by making four calibration-type measurements to measure four parameters ξ_{11} , ξ_{12} , ξ_{21} , and ξ_{22} , where:

$$\xi_{11} = \hat{S}_1|_{S_1=A, S_2=0} = Aa_1 \cos\phi_1 \quad (25)$$

$$\xi_{12} = \hat{S}_1|_{S_1=0, S_2=B} = -Ba_2 \sin\phi_2 \quad (26)$$

$$\xi_{21} = \hat{S}_2|_{S_1=A, S_2=0} = Aa_1 \sin\phi_1 \quad (27)$$

$$\xi_{22} = \hat{S}_2|_{S_1=0, S_2=B} = Ba_2 \cos\phi_2 \quad (28)$$

where A and B are amplitudes. Then

$$a_1 = \frac{\sqrt{\xi_{11}^2 + \xi_{21}^2}}{A} \quad (29)$$

$$a_2 = \frac{\sqrt{\xi_{12}^2 + \xi_{22}^2}}{B} \quad (30)$$

$$\tan\phi_1 = \frac{\xi_{21}}{\xi_{11}} \quad (31)$$

$$\tan\phi_2 = -\frac{\xi_{12}}{\xi_{22}} \quad (32)$$

From the above equations, it is evident that crosstalk depends only on ϕ_1 and ϕ_2 . Moreover, ϕ_1 and ϕ_2 can be chosen to eliminate crosstalk without knowing A or B. This is useful for systems such as pulse oximetry systems where absolute measurements of a channel are difficult or impractical, but where relative measurements (e.g., channel-to-channel measurements) are practical.

The demodulation signals $D_i(t)$ can be generated using the values of ϕ_1 and ϕ_2 from the above equations. Alternatively, the demodulation signals $D_i(t)$ can be generated from quadrature components as:

$$D_1(t) = b_{11} \sin\omega t + b_{12} \cos\omega t \quad (33)$$

$$D_2(t) = b_{21} \sin\omega t + b_{22} \cos\omega t \quad (34)$$

where the coefficients b_{ij} are computed from ϕ_1 and ϕ_2 .

In one embodiment, the demodulation functions are adapted from baseline coefficients, which are then improved through a calibration or initialization procedure to produce actual coefficients. The baseline coefficients are typically obtained from known properties of the system. The actual coefficients are usually relatively close in value to the baseline coefficients. This provides one way to assess the operational status of the system and to evaluate the calibration procedure. In one embodiment, if the actual coefficients are too different from the baseline parameters then it is assumed that the calibration procedure failed in some manner or that the equipment has failed in some manner, and appropriate measures can be taken (e.g., alert the operator, sound a warning, etc.)

To find the actual coefficients, the demodulation functions are initially given by:

$$D_1(t) = \alpha_{11} \sin \omega t + \alpha_{12} \cos \omega t \quad (35)$$

$$D_2(t) = \alpha_{21} \sin \omega t + \alpha_{22} \cos \omega t \quad (36)$$

Where the coefficients α_{ij} are the baseline coefficients determined from known or assumed properties of the signal $S(t)$. For example, in one embodiment $\alpha_{ij} = \delta_{ij}$. In one embodiment, where initial estimates are available for ϕ_1 and ϕ_2 , then the values of α_{ij} can be computed as discussed above.

The crosstalk reduction obtained using demodulation functions based on the coefficients α_{ij} can often be improved by computing new coefficients $\bar{\alpha}_{ij}$ and corresponding new demodulation functions $\bar{D}_i(t)$ where:

$$\bar{D}_1(t) = \bar{\alpha}_{11} \sin \omega t + \bar{\alpha}_{12} \cos \omega t \quad (37)$$

$$\bar{D}_2(t) = \bar{\alpha}_{21} \sin \omega t + \bar{\alpha}_{22} \cos \omega t \quad (38)$$

The process of finding the coefficients $\bar{\alpha}_{ij}$ begins by measuring two data sets, $x_1(t)$ and $x_2(t)$, as follows:

$$x_1(t) = S(t)|_{S_1=A, S_2=0} \quad (39)$$

$$x_2(t) = S(t)|_{S_1=0, S_2=B} \quad (40)$$

The data sets $x_1(t)$ and $x_2(t)$ are used to enforce the following constraint:

$$\int_0^{nT} x_i(t) \bar{D}_i(t) dt = 0 \quad (41)$$

where $i=1, 2, n=1, 2, 3, \dots$, and T is a time period corresponding to one complete modulation cycle. From the above constraint and the definitions of the demodulation functions, it follows that:

$$\bar{\alpha}_{11} \int_0^{nT} x_1(t) \sin \omega t dt + \bar{\alpha}_{12} \int_0^{nT} x_1(t) \cos \omega t dt = 0 \quad (42)$$

$$\alpha_{21} \int_0^{nT} x_2(t) \sin \omega t dt + \bar{\alpha}_{22} \int_0^{nT} x_2(t) \cos \omega t dt = 0 \quad (43)$$

It is convenient to define

$$\gamma_{11} = \int_0^{nT} x_1(t) \sin \omega t dt \quad (44)$$

$$\gamma_{12} = \int_0^{nT} x_1(t) \cos \omega t dt \quad (45)$$

$$\gamma_{21} = \int_0^{nT} x_2(t) \sin \omega t dt \quad (46)$$

$$\gamma_{22} = \int_0^{nT} x_2(t) \cos \omega t dt \quad (47)$$

and to define

$$\beta_{ij} = \frac{\gamma_{ij}}{\left[\sum_k \gamma_{ik}^2 \right]^{1/2}} \quad (48)$$

where

$$\sum_k \beta_{ik}^2 = 1 \quad (49)$$

Then

$$\bar{\alpha}_{11} \beta_{11} + \bar{\alpha}_{12} \beta_{12} = 0 \quad (50)$$

$$\alpha_{21} \beta_{21} + \alpha_{22} \beta_{22} = 0 \quad (51)$$

In one embodiment, to reduce crosstalk, it is desired to find the coefficients $\bar{\alpha}_{ij}$ closest (in the sense of minimizing some specified error, such as, for example, a least squared error) to the coefficients α_{ij} such that the above constraints are satisfied. One solution, obtained by minimizing the least squared error is:

$$\bar{\alpha}_{ij} = \alpha_{ij} - \left(\sum_k \alpha_{ik} \beta_{ik} \right) \beta_{ij} \quad (52)$$

The term in parentheses can be described as the baseline crosstalk.

One of ordinary skill in the art will recognize that optimization methods other than least squares can be used. The solution methods for configuration are, for simplicity, described above in terms of a two-channel system. Using the above teachings, the extension to multi-channel systems is straightforward.

Although described above in connection with a particular embodiment of the present invention, it should be understood the description of the embodiment is illustrative of the invention and are not intended to be limiting. Although described above in connection with a pulse oximetry system wherein a parameter to be measured is the attenuation of red and infrared light passing through a portion of a subject's body, it should be understood that the method and apparatus described herein can also be used for other measurements where two or more signals are passed through a system to be analyzed. In particular, the present invention can be used to demodulate two combined parametric signals responsive to the system to be analyzed where the two parametric signals have a predetermined timing relationship between them, as described herein. The invention can be used in connection with various physiological parameter measurement systems, such as, for example, systems that measure blood constituents, blood oxygen carboxyhemoglobin, methemoglobin, glucose, etc. Various modifications and applications may occur to those skilled in the art without departing from the true spirit and scope of the invention as defined in the appended claims.

What is claimed is:

1. A method of reducing crosstalk between two signals generated by applying a first pulse and a second pulse to measure a parameter, wherein said first pulse and said second pulse are applied periodically at a first repetition rate defining a period, and wherein said first pulse is generated during a first interval in each period and said second pulse is generated during a second interval in each period, said

15

first and second pulses producing first and second parametric signals responsive to said parameter, said first and second parametric signals being received by a detector which outputs a composite signal responsive to said first and second parametric signals, said method comprising:

applying a first demodulation signal to said composite signal to generate a first demodulated output signal, said first demodulation signal comprising at least one component having at least a first amplitude and a first phase;

applying a second demodulation signal to said composite signal to generate a second demodulated output signal, said second demodulation signal comprising at least one component having at least a second amplitude and a second phase;

lowpass filtering said first demodulated output signal to generate a first recovered output signal responsive to said first parametric signal;

lowpass filtering said second demodulated output signal to generate a second recovered output signal responsive to said second parametric signal; and

choosing at least one of said first phase, said second phase, said first amplitude, and said second amplitude to reduce crosstalk components in said first recovered output signal and said second recovered output signal based at least in part on data obtained from said detector during a calibration procedure, wherein said choosing comprises:

applying said first light pulse during a first time period and measuring said first recovered output during said first time period as a first calibration output and measuring said second recovered output during said first time period as a second calibration output;

applying said second light pulse during a second time period and measuring said first recovered output during said first time period as a third calibration output and measuring said second recovered output during said second time period as a fourth calibration output; and

computing said first demodulation signal from at least said first calibration output, said second calibration output, said third calibration output, and said fourth calibration output.

2. The method of claim 1, wherein at least a portion of said first demodulation signal is computed from a ratio of said first calibration pulse and said second calibration pulse.

3. A method of reducing crosstalk between two signals generated by applying a first pulse and a second pulse to measure a parameter, wherein said first pulse and said second pulse are applied periodically at a first repetition rate defining a period, and wherein said first pulse is generated during a first interval in each period and said second pulse is generated during a second interval in each period, said first and second pulses producing first and second parametric signals responsive to said parameter, said first and second parametric signals being received by a detector which outputs a composite signal responsive to said first and second parametric signals, said method comprising:

applying a first demodulation signal to said composite signal to generate a first demodulated output signal, said first demodulation signal comprising at least one component having at least a first amplitude and a first phase;

applying a second demodulation signal to said composite signal to generate a second demodulated output signal, said second demodulation signal comprising at least one component having at least a second amplitude and a second phase;

16

lowpass filtering said first demodulated output signal to generate a first recovered output signal responsive to said first parametric signal;

lowpass filtering said second demodulated output signal to generate a second recovered output signal responsive to said second parametric signal; and

choosing at least one of said first phase, said second phase, said first amplitude, and said second amplitude to reduce crosstalk components in said first recovered output signal and said second recovered output signal based at least in part on data obtained from said detector during a calibration procedure, wherein said first demodulation signal comprises a sum of a first demodulation component having a first amplitude and a second demodulation component having a second amplitude, said second demodulation component in quadrature with said first demodulation component and wherein choosing said first phase comprises choosing said first amplitude and said second amplitude.

4. A method of reducing crosstalk between two signals generated by applying a first pulse and a second pulse to measure a parameter, wherein said first pulse and said second pulse are applied periodically at a first repetition rate defining a period, and wherein said first pulse is generated during a first interval in each period and said second pulse is generated during a second interval in each period, said first and second pulses producing first and second parametric signals responsive to said parameter, said first and second parametric signals being received by a detector which outputs a composite signal responsive to said first and second parametric signals, said method comprising:

applying a first demodulation signal to said composite signal to generate a first demodulated output signal, said first demodulation signal comprising at least one component having at least a first amplitude and a first phase;

applying a second demodulation signal to said composite signal to generate a second demodulated output signal, said second demodulation signal comprising at least one component having at least a second amplitude and a second phase;

lowpass filtering said first demodulated output signal to generate a first recovered output signal responsive to said first parametric signal;

lowpass filtering said second demodulated output signal to generate a second recovered output signal responsive to said second parametric signal; and

choosing at least one of said first phase, said second phase, said first amplitude, and said second amplitude to reduce crosstalk components in said first recovered output signal and said second recovered output signal based at least in part on data obtained from said detector during a calibration procedure, wherein said first demodulation signal comprises a sum of a sinusoidal component having a first amplitude and a cosinusoidal component having a second amplitude, and wherein choosing said first phase comprises choosing said first amplitude and said second amplitude by using a least squares minimization of an error corresponding to said crosstalk.

5. The method of claim 4, wherein said error is integrated over a time period.

6. The method of claim 4, wherein said error is integrated over a time period corresponding to an integer number of cycles of said sinusoidal component.

17

7. A pulse oximetry system, comprising:
 a modulation signal generator, said modulation signal
 generator generating a first modulation signal compris-
 ing a first pulse which repeats at a first repetition
 frequency, said first pulse having a duty cycle, said
 modulation signal generator generating a second modu- 5
 lation signal comprising a second pulse which also
 repeats at said first repetition frequency, said second
 pulse having a duty cycle, said second pulse occurring
 at non-overlapping times with respect to said first
 pulse, said first and second pulses comprising a plural- 10
 ity of components wherein a first component has a
 frequency corresponding to said repetition frequency
 and a second component has a second frequency cor-
 responding to twice said first frequency, said second 15
 component having an amplitude which has a first
 predetermined relationship to an amplitude of said first
 component;
 a first transmitter which emits electromagnetic energy at
 a first wavelength in response to said first pulse; 20
 a second transmitter which emits electromagnetic energy
 at a second wavelength in response to said second
 pulse;
 a detector which receives electromagnetic energy at said
 first and second wavelengths after passing through a 25
 portion of a subject and which generates a detector
 output signal responsive to the received electromag-
 netic energy, said detector output signal including a
 signal component responsive to attenuation of said
 electromagnetic energy at said first wavelength and a 30
 signal component responsive to attenuation of said
 electromagnetic energy at said second wavelength;
 a first demodulator which multiplies said detector signal
 by a first demodulation signal and generates a first 35
 demodulated output signal;
 a second demodulator which multiplies said detector
 signal by a second demodulation signal and generates
 a second demodulated output signal; and
 a configuration module to configure said first demodula-
 tion signal and said second demodulation signal to

18

substantially diagonalize said first demodulator and
 said second demodulator.

8. The pulse oximetry system of claim 7, wherein said
 configuration module selects a phase relationship between
 said first demodulation signal and said second demodulation
 signal.

9. The pulse oximetry system of claim 7, wherein said
 configuration module configures said first demodulation
 signal and said second demodulation signal using, at least in
 part, data obtained during a calibration period.

10. The pulse oximetry system of claim 7, wherein said
 configuration module configures said first demodulation
 signal and said second demodulation signal using, at least in
 part, calibration data obtained during a calibration period,
 said calibration data comprising first and second calibration
 data corresponding to said first and second demodulated
 output signals during a first time period and third and fourth
 calibration data corresponding to said first and second
 demodulated output signals during a second time period,
 said second transmitter turned off during said first time
 period, said first transmitter turned off during said second
 time period.

11. The pulse oximetry system of claim 7, wherein said
 configuration module configures said first demodulation
 signal and said second demodulation signal by adjusting
 initial parameters that define said first demodulation signal
 and said second demodulation signal, said configuration
 module adjusting said initial parameters using, at least in
 part, calibration data obtained during a calibration period,
 said calibration data comprising first and second calibration
 data corresponding to said first and second demodulated
 output signals during a first time period and third and fourth
 calibration data corresponding to said first and second
 demodulated output signals during a second time period,
 said second transmitter turned off during said first time
 period, said first transmitter turned off during said second
 time period.

* * * * *

专利名称(译)	用于减少信号之间的耦合的方法和设备		
公开(公告)号	US7003338	公开(公告)日	2006-02-21
申请号	US10/615333	申请日	2003-07-08
[标]申请(专利权)人(译)	WEBER WALTER中号 AL ALI AMMAR		
申请(专利权)人(译)	WEBER WALTER M. AL-ALI AMMAR		
当前申请(专利权)人(译)	CERCACOR LABORATORIES , INC.		
[标]发明人	WEBER WALTER M AL ALI AMMAR		
发明人	WEBER, WALTER M. AL-ALI, AMMAR		
IPC分类号	A61B5/00		
CPC分类号	A61B5/14551 A61B5/7203 A61B5/14552 A61B5/7228 A61B5/7221 A61B5/1495 A61B5/7214 A61B2562/0238		
其他公开文献	US20050010092A1		
外部链接	Espacenet USPTO		

摘要(译)

描述了一种用于将复合信号分离成多个信号的方法和装置。信号处理器接收复合信号并将复合信号分离成单独的输出信号。来自一个或多个输出信号的反馈被提供给配置模块，该配置模块配置信号处理器以改善输出信号的质量。在一个实施例中，信号处理器通过将第一解调信号应用于复合信号来分离复合信号，以产生第一输出信号。在一个实施例中，信号处理器还将第二解调信号应用于复合信号以产生第二输出信号。在一个实施例中，选择第一解调信号的相位和/或幅度以及第二解调信号的相位和/或幅度以减少串扰。在一个实施例中，复合信号从用于测量一种或多种血液成分的系统中的检测器获得。

