



US009351673B2

(12) **United States Patent**
Diab et al.

(10) **Patent No.:** **US 9,351,673 B2**
(45) **Date of Patent:** ***May 31, 2016**

(54) **METHOD AND APPARATUS FOR
DEMODULATING SIGNALS IN A PULSE
OXIMETRY SYSTEM**

(2013.01); *A61B 5/7228* (2013.01); *H04J 3/10*
(2013.01); *H04J 14/08* (2013.01); *A61B 5/7232*
(2013.01); *A61B 2560/0242* (2013.01)

(71) Applicant: **Masimo Corporation**, Irvine, CA (US)

(58) **Field of Classification Search**

CPC *A61B 5/14551*; *A61B 5/1455*; *A61B*
5/14552; *A61B 5/7228*; *A61B 5/7217*; *A61B*
5/7232; *A61B 2560/0242*

(72) Inventors: **Mohamed K. Diab**, Ladera Ranch, CA
(US); **Walter M. Weber**, Laguna Hills,
CA (US); **Ammar Al-Ali**, San Juan
Capistrano, CA (US)

See application file for complete search history.

(73) Assignee: **Masimo Corporation**, Irvine, CA (US)

(56) **References Cited**

U.S. PATENT DOCUMENTS

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 0 days.

3,638,640 A 2/1972 Shaw
3,704,706 A 12/1972 Herczfeld et al.
4,407,290 A 10/1983 Wilber

(Continued)

This patent is subject to a terminal dis-
claimer.

FOREIGN PATENT DOCUMENTS

(21) Appl. No.: **14/269,606**

DE 3328862 A1 2/1985
EP 0 335 357 3/1989

(22) Filed: **May 5, 2014**

(Continued)

(65) **Prior Publication Data**

US 2014/0243627 A1 Aug. 28, 2014

OTHER PUBLICATIONS

U.S. 8,845,543, 9/2014, Diab et al. (withdrawn).

Related U.S. Application Data

Primary Examiner — Eric Winakur

(60) Continuation of application No. 13/437,800, filed on
Apr. 2, 2012, now Pat. No. 8,718,737, which is a
continuation of application No. 11/750,930, filed on
May 18, 2007, now Pat. No. 8,150,487, which is a

(74) *Attorney, Agent, or Firm* — Knobbe, Martens, Olson &
Bear LLP

(Continued)

(57)

ABSTRACT

A method and an apparatus measure blood oxygenation in a
subject. A light source is activated to cause a first emission at
a first wavelength and a second emission at a second wave-
length. A detector detects a composite signal indicative of an
attenuation of the first and second wavelengths by tissue of a
patient. The composite signal is demodulated into a first
intensity signal and a second intensity signal. Blood oxygen-
ation in the subject is determined from the first and second
intensity signals.

(51) **Int. Cl.**

A61B 5/1455 (2006.01)

A61B 5/00 (2006.01)


H04J 3/10 (2006.01)

H04J 14/08 (2006.01)

(52) **U.S. Cl.**

CPC *A61B 5/14551* (2013.01); *A61B 5/7217*

16 Claims, 18 Drawing Sheets



Related U.S. Application Data

continuation of application No. 11/311,213, filed on Dec. 19, 2005, now Pat. No. 7,221,971, which is a continuation of application No. 10/700,324, filed on Nov. 3, 2003, now Pat. No. 7,003,339, which is a division of application No. 09/735,960, filed on Dec. 13, 2000, now Pat. No. 6,643,530, which is a division of application No. 09/058,799, filed on Apr. 10, 1998, now Pat. No. 6,229,856, which is a continuation-in-part of application No. 09/005,898, filed on Jan. 12, 1998, now Pat. No. 5,919,134.

- (60) Provisional application No. 60/043,620, filed on Apr. 14, 1997.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,773,422	A	9/1988	Isaacson et al.	5,800,348	A	9/1998	Kaestle
4,781,195	A	11/1988	Martin	5,810,734	A	9/1998	Caro et al.
4,785,463	A	11/1988	Janc et al.	5,823,950	A	10/1998	Diab et al.
4,824,242	A	4/1989	Frick et al.	5,830,131	A	11/1998	Caro et al.
4,848,901	A	7/1989	Hood, Jr.	5,833,618	A	11/1998	Caro et al.
4,863,265	A	9/1989	Flower et al.	5,860,919	A	1/1999	Kiani-Azarbayjany et al.
4,867,571	A	9/1989	Frick et al.	5,890,929	A	4/1999	Mills et al.
4,948,248	A	8/1990	Lehman	5,904,654	A	5/1999	Wohlmann et al.
4,960,128	A	10/1990	Gordon et al.	5,919,134	A	7/1999	Diab
4,964,408	A	10/1990	Hink et al.	5,921,921	A *	7/1999	Potratz et al. 600/323
5,041,187	A	8/1991	Hink et al.	5,934,925	A	8/1999	Tobler et al.
5,069,213	A	12/1991	Polczynski	5,940,182	A	8/1999	Lepper, Jr. et al.
5,163,438	A	11/1992	Gordon et al.	5,940,346	A	8/1999	Sadowsky et al.
5,193,543	A	3/1993	Yelderman	5,995,855	A	11/1999	Kiani et al.
5,276,705	A	1/1994	Higgins	5,997,343	A	12/1999	Mills et al.
5,319,355	A	6/1994	Russek	6,002,952	A	12/1999	Diab et al.
5,337,744	A	8/1994	Branigan	6,011,986	A	1/2000	Diab et al.
5,341,805	A	8/1994	Stavridi et al.	6,027,452	A	2/2000	Flaherty et al.
5,349,952	A	9/1994	McCarthy et al.	6,036,642	A	3/2000	Diab et al.
D353,195	S	12/1994	Savage et al.	6,045,509	A	4/2000	Caro et al.
D353,196	S	12/1994	Savage et al.	6,067,462	A	5/2000	Diab et al.
5,377,676	A	1/1995	Vari et al.	6,081,735	A	6/2000	Diab et al.
D359,546	S	6/1995	Savage et al.	6,088,607	A	7/2000	Diab et al.
5,431,170	A	7/1995	Mathews	6,110,522	A	8/2000	Lepper, Jr. et al.
D361,840	S	8/1995	Savage et al.	6,124,597	A	9/2000	Shehada et al.
D362,063	S	9/1995	Savage et al.	6,128,521	A	10/2000	Marro et al.
5,452,717	A	9/1995	Branigan et al.	6,129,675	A	10/2000	Jay
D363,120	S	10/1995	Savage et al.	6,144,868	A	11/2000	Parker
5,456,252	A	10/1995	Vari et al.	6,151,516	A	11/2000	Kiani-Azarbayjany et al.
RE35,122	E	12/1995	Corenman et al.	6,152,754	A	11/2000	Gerhardt et al.
5,479,934	A	1/1996	Imran	6,157,850	A	12/2000	Diab et al.
5,482,036	A	1/1996	Diab et al.	6,165,005	A	12/2000	Mills et al.
5,490,505	A	2/1996	Diab et al.	6,184,521	B1	2/2001	Coffin, IV et al.
5,494,043	A	2/1996	O'Sullivan et al.	6,206,830	B1	3/2001	Diab et al.
5,521,938	A	5/1996	Stewart et al.	6,229,856	B1	5/2001	Diab et al.
5,533,511	A	7/1996	Kaspari et al.	6,232,609	B1	5/2001	Snyder et al.
5,534,851	A	7/1996	Russek	6,236,872	B1	5/2001	Diab et al.
5,555,882	A	9/1996	Richardson et al.	6,241,683	B1	6/2001	Macklem et al.
5,561,275	A	10/1996	Savage et al.	6,253,097	B1	6/2001	Aronow et al.
5,562,002	A	10/1996	Lalin	6,256,523	B1	7/2001	Diab et al.
5,579,341	A	11/1996	Smith et al.	6,263,222	B1	7/2001	Diab et al.
5,590,649	A	1/1997	Caro et al.	6,278,522	B1	8/2001	Lepper, Jr. et al.
5,602,924	A	2/1997	Durand et al.	6,280,213	B1	8/2001	Tobler et al.
5,632,272	A	5/1997	Diab et al.	6,285,896	B1	9/2001	Tobler et al.
5,638,816	A	6/1997	Kiani-Azarbayjany et al.	6,301,493	B1	10/2001	Marro et al.
5,638,818	A	6/1997	Diab et al.	6,317,627	B1	11/2001	Ennen et al.
5,640,416	A	6/1997	Chalmers	6,321,100	B1	11/2001	Parker
5,645,440	A	7/1997	Tobler et al.	6,325,761	B1	12/2001	Jay
5,685,299	A	11/1997	Diab et al.	6,334,065	B1	12/2001	Al-Ali et al.
D393,830	S	4/1998	Tobler et al.	6,343,224	B1	1/2002	Parker
5,743,262	A	4/1998	Lepper, Jr. et al.	6,349,228	B1	2/2002	Kiani et al.
5,758,644	A	6/1998	Diab et al.	6,360,114	B1	3/2002	Diab et al.
5,760,910	A	6/1998	Lepper, Jr. et al.	6,368,283	B1	4/2002	Xu et al.
5,769,785	A	6/1998	Diab et al.	6,371,921	B1	4/2002	Caro et al.
5,782,757	A	7/1998	Diab et al.	6,377,829	B1	4/2002	Al-Ali
5,785,659	A	7/1998	Caro et al.	6,388,240	B2	5/2002	Schulz et al.
5,791,347	A	8/1998	Flaherty et al.	6,397,091	B2	5/2002	Diab et al.
				6,430,437	B1	8/2002	Marro
				6,430,525	B1	8/2002	Weber et al.
				6,463,311	B1	10/2002	Diab
				6,470,199	B1	10/2002	Kopotic et al.
				6,501,975	B2	12/2002	Diab et al.
				6,505,059	B1	1/2003	Kollias et al.
				6,515,273	B2	2/2003	Al-Ali
				6,519,487	B1	2/2003	Parker
				6,525,386	B1	2/2003	Mills et al.
				6,526,300	B1	2/2003	Kiani et al.
				6,541,756	B2	4/2003	Schulz et al.
				6,542,764	B1	4/2003	Al-Ali et al.
				6,580,086	B1	6/2003	Schulz et al.
				6,584,336	B1	6/2003	Ali et al.
				6,595,316	B2	7/2003	Cybulski et al.
				6,597,932	B2	7/2003	Tian et al.
				6,597,933	B2	7/2003	Kiani et al.
				6,606,511	B1	8/2003	Ali et al.
				6,632,181	B2	10/2003	Flaherty et al.
				6,639,668	B1	10/2003	Trepagnier
				6,640,116	B2	10/2003	Diab
				6,643,530	B2	11/2003	Diab et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

6,650,917	B2	11/2003	Diab et al.	7,254,433	B2	8/2007	Diab et al.
6,654,624	B2	11/2003	Diab et al.	7,254,434	B2	8/2007	Schulz et al.
6,658,276	B2	12/2003	Kiani et al.	7,272,425	B2	9/2007	Al-Ali
6,661,161	B1	12/2003	Lanzo et al.	7,274,955	B2	9/2007	Kiani et al.
6,671,531	B2	12/2003	Al-Ali et al.	D554,263	S	10/2007	Al-Ali
6,678,543	B2	1/2004	Diab et al.	7,280,858	B2	10/2007	Al-Ali et al.
6,684,090	B2	1/2004	Ali et al.	7,289,835	B2	10/2007	Mansfield et al.
6,684,091	B2	1/2004	Parker	7,292,883	B2	11/2007	De Felice et al.
6,697,656	B1	2/2004	Al-Ali	7,295,866	B2	11/2007	Al-Ali
6,697,657	B1	2/2004	Shehada et al.	7,328,053	B1	2/2008	Diab et al.
6,697,658	B2	2/2004	Al-Ali	7,332,784	B2	2/2008	Mills et al.
RE38,476	E	3/2004	Diab et al.	7,340,287	B2	3/2008	Mason et al.
6,699,194	B1	3/2004	Diab et al.	7,341,559	B2	3/2008	Schulz et al.
6,714,804	B2	3/2004	Al-Ali et al.	7,343,186	B2	3/2008	Lamego et al.
RE38,492	E	4/2004	Diab et al.	D566,282	S	4/2008	Al-Ali et al.
6,721,582	B2	4/2004	Trepagnier et al.	7,355,512	B1	4/2008	Al-Ali
6,721,585	B1	4/2004	Parker	7,356,365	B2	4/2008	Schurman
6,725,075	B2	4/2004	Al-Ali	7,371,981	B2	5/2008	Abdul-Hafiz
6,728,560	B2	4/2004	Kollias et al.	7,373,193	B2	5/2008	Al-Ali et al.
6,735,459	B2	5/2004	Parker	7,373,194	B2	5/2008	Weber et al.
6,745,060	B2	6/2004	Diab et al.	7,376,453	B1	5/2008	Diab et al.
6,760,607	B2	7/2004	Al-Ali	7,377,794	B2	5/2008	Al-Ali et al.
6,770,028	B1	8/2004	Ali et al.	7,377,899	B2	5/2008	Weber et al.
6,771,994	B2	8/2004	Kiani et al.	7,383,070	B2	6/2008	Diab et al.
6,792,300	B1	9/2004	Diab et al.	7,415,297	B2	8/2008	Al-Ali et al.
6,813,511	B2	11/2004	Diab et al.	7,428,432	B2	9/2008	Ali et al.
6,816,741	B2	11/2004	Diab	7,438,683	B2	10/2008	Al-Ali et al.
6,822,564	B2	11/2004	Al-Ali	7,440,787	B2	10/2008	Diab
6,826,419	B2	11/2004	Diab et al.	7,454,240	B2	11/2008	Diab et al.
6,830,711	B2	12/2004	Mills et al.	7,467,002	B2	12/2008	Weber et al.
6,850,787	B2	2/2005	Weber et al.	7,469,157	B2	12/2008	Diab et al.
6,850,788	B2	2/2005	Al-Ali	7,471,969	B2	12/2008	Diab et al.
6,852,083	B2	2/2005	Caro et al.	7,471,971	B2	12/2008	Diab et al.
6,861,639	B2	3/2005	Al-Ali	7,483,729	B2	1/2009	Al-Ali et al.
6,898,452	B2	5/2005	Al-Ali et al.	7,483,730	B2	1/2009	Diab et al.
6,920,345	B2	7/2005	Al-Ali et al.	7,489,958	B2	2/2009	Diab et al.
6,931,268	B1	8/2005	Kiani-Azarbayjany et al.	7,496,391	B2	2/2009	Diab et al.
6,934,570	B2	8/2005	Kiani et al.	7,496,393	B2	2/2009	Diab et al.
6,939,305	B2	9/2005	Flaherty et al.	D587,657	S	3/2009	Al-Ali et al.
6,943,348	B1	9/2005	Coffin, IV	7,499,741	B2	3/2009	Diab et al.
6,950,687	B2	9/2005	Al-Ali	7,499,835	B2	3/2009	Weber et al.
6,961,598	B2	11/2005	Diab	7,500,950	B2	3/2009	Al-Ali et al.
6,970,792	B1	11/2005	Diab	7,509,154	B2	3/2009	Diab et al.
6,979,812	B2	12/2005	Al-Ali	7,509,494	B2	3/2009	Al-Ali
6,985,764	B2	1/2006	Mason et al.	7,510,849	B2	3/2009	Schurman et al.
6,993,371	B2	1/2006	Kiani et al.	7,526,328	B2	4/2009	Diab et al.
6,996,427	B2	2/2006	Ali et al.	7,530,942	B1	5/2009	Diab
6,999,904	B2	2/2006	Weber et al.	7,530,949	B2	5/2009	Al-Ali et al.
7,003,338	B2	2/2006	Weber et al.	7,530,955	B2	5/2009	Diab et al.
7,003,339	B2	2/2006	Diab et al.	7,563,110	B2	7/2009	Al-Ali et al.
7,015,451	B2	3/2006	Dalke et al.	7,596,398	B2	9/2009	Al-Ali et al.
7,024,233	B2	4/2006	Ali et al.	7,618,375	B2	11/2009	Flaherty
7,027,849	B2	4/2006	Al-Ali	D606,659	S	12/2009	Kiani et al.
7,030,749	B2	4/2006	Al-Ali	7,647,083	B2	1/2010	Al-Ali et al.
7,039,449	B2	5/2006	Al-Ali	D609,193	S	2/2010	Al-Ali et al.
7,041,060	B2	5/2006	Flaherty et al.	D614,305	S	4/2010	Al-Ali et al.
7,044,918	B2	5/2006	Diab	RE41,317	E	5/2010	Parker
7,067,893	B2	6/2006	Mills et al.	7,729,733	B2	6/2010	Al-Ali et al.
7,096,052	B2	8/2006	Mason et al.	7,734,320	B2	6/2010	Al-Ali
7,096,054	B2	8/2006	Abdul-Hafiz et al.	7,761,127	B2	7/2010	Al-Ali et al.
7,132,641	B2	11/2006	Schulz et al.	7,761,128	B2	7/2010	Al-Ali et al.
7,142,901	B2	11/2006	Kiani et al.	7,764,982	B2	7/2010	Dalke et al.
7,149,561	B2	12/2006	Diab	D621,516	S	8/2010	Kiani et al.
7,186,966	B2	3/2007	Al-Ali	7,791,155	B2	9/2010	Diab
7,190,261	B2	3/2007	Al-Ali	7,801,581	B2	9/2010	Diab
7,215,984	B2	5/2007	Diab	7,822,452	B2	10/2010	Schurman et al.
7,215,986	B2	5/2007	Diab	RE41,912	E	11/2010	Parker
7,221,971	B2	5/2007	Diab	7,844,313	B2	11/2010	Kiani et al.
7,225,006	B2	5/2007	Al-Ali et al.	7,844,314	B2	11/2010	Al-Ali
7,225,007	B2	5/2007	Al-Ali	7,844,315	B2	11/2010	Al-Ali
RE39,672	E	6/2007	Shehada et al.	7,865,222	B2	1/2011	Weber et al.
7,239,905	B2	7/2007	Kiani-Azarbayjany et al.	7,873,497	B2	1/2011	Weber et al.
7,245,953	B1	7/2007	Parker	7,880,606	B2	2/2011	Al-Ali
7,254,429	B2	8/2007	Schurman et al.	7,880,626	B2	2/2011	Al-Ali et al.
7,254,431	B2	8/2007	Al-Ali	7,891,355	B2	2/2011	Al-Ali et al.
				7,894,868	B2	2/2011	Al-Ali et al.
				7,899,507	B2	3/2011	Al-Ali et al.
				7,899,518	B2	3/2011	Trepagnier et al.
				7,904,132	B2	3/2011	Weber et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

7,909,772	B2	3/2011	Popov et al.	8,430,817	B1	4/2013	Al-Ali et al.
7,910,875	B2	3/2011	Al-Ali	8,437,825	B2	5/2013	Dalvi et al.
7,919,713	B2	4/2011	Al-Ali et al.	8,455,290	B2	6/2013	Siskavich
7,937,128	B2	5/2011	Al-Ali	8,457,703	B2	6/2013	Al-Ali
7,937,129	B2	5/2011	Mason et al.	8,457,707	B2	6/2013	Kiani
7,937,130	B2	5/2011	Diab et al.	8,463,349	B2	6/2013	Diab et al.
7,941,199	B2	5/2011	Kiani	8,466,286	B2	6/2013	Bellot et al.
7,951,086	B2	5/2011	Flaherty et al.	8,471,713	B2	6/2013	Poeze et al.
7,957,780	B2	6/2011	Lamego et al.	8,473,020	B2	6/2013	Kiani et al.
7,962,188	B2	6/2011	Kiani et al.	8,483,787	B2	7/2013	Al-Ali et al.
7,962,190	B1	6/2011	Diab et al.	8,489,364	B2	7/2013	Weber et al.
7,976,472	B2	7/2011	Kiani	8,498,684	B2	7/2013	Weber et al.
7,988,637	B2	8/2011	Diab	8,509,867	B2	8/2013	Workman et al.
7,990,382	B2	8/2011	Kiani	8,515,509	B2	8/2013	Bruinsma et al.
7,991,446	B2	8/2011	Al-Ali et al.	8,523,781	B2	9/2013	Al-Ali
8,000,761	B2	8/2011	Al-Ali	8,529,301	B2	9/2013	Al-Ali et al.
8,008,088	B2	8/2011	Bellott et al.	8,532,727	B2	9/2013	Ali et al.
RE42,753	E	9/2011	Kiani-Azarbayjany et al.	8,532,728	B2	9/2013	Diab et al.
8,019,400	B2	9/2011	Diab et al.	D692,145	S	10/2013	Al-Ali et al.
8,028,701	B2	10/2011	Al-Ali et al.	8,547,209	B2	10/2013	Kiani et al.
8,029,765	B2	10/2011	Bellott et al.	8,548,548	B2	10/2013	Al-Ali
8,036,728	B2	10/2011	Diab et al.	8,548,550	B2	10/2013	Al-Ali et al.
8,046,040	B2	10/2011	Ali et al.	8,560,032	B2	10/2013	Al-Ali et al.
8,046,041	B2	10/2011	Diab et al.	8,560,034	B1	10/2013	Diab et al.
8,046,042	B2	10/2011	Diab et al.	8,570,167	B2	10/2013	Al-Ali
8,048,040	B2	11/2011	Kiani	8,570,503	B2	10/2013	Vo et al.
8,050,728	B2	11/2011	Al-Ali et al.	8,571,618	B1	10/2013	Lamego et al.
RE43,169	E	2/2012	Parker	8,571,619	B2	10/2013	Al-Ali et al.
8,118,620	B2	2/2012	Al-Ali et al.	8,577,431	B2	11/2013	Lamego et al.
8,126,528	B2	2/2012	Diab et al.	8,584,345	B2	11/2013	Al-Ali et al.
8,128,572	B2	3/2012	Diab et al.	8,588,880	B2	11/2013	Abdul-Hafiz et al.
8,130,105	B2	3/2012	Al-Ali et al.	8,600,467	B2	12/2013	Al-Ali et al.
8,145,287	B2	3/2012	Diab et al.	8,606,342	B2	12/2013	Diab
8,150,487	B2	4/2012	Diab et al.	8,626,255	B2	1/2014	Al-Ali et al.
8,175,672	B2	5/2012	Parker	8,630,691	B2	1/2014	Lamego et al.
8,180,420	B2	5/2012	Diab et al.	8,634,889	B2	1/2014	Al-Ali et al.
8,182,443	B1	5/2012	Kiani	8,641,631	B2	2/2014	Sierra et al.
8,185,180	B2	5/2012	Diab et al.	8,652,060	B2	2/2014	Al-Ali
8,190,223	B2	5/2012	Al-Ali et al.	8,663,107	B2	3/2014	Kiani
8,190,227	B2	5/2012	Diab et al.	8,666,468	B1	3/2014	Al-Ali
8,203,438	B2	6/2012	Kiani et al.	8,667,967	B2	3/2014	Al-Ali et al.
8,203,704	B2	6/2012	Merritt et al.	8,670,811	B2	3/2014	O'Reilly
8,224,411	B2	7/2012	Al-Ali et al.	8,670,814	B2	3/2014	Diab et al.
8,228,181	B2	7/2012	Al-Ali	8,676,286	B2	3/2014	Weber et al.
8,229,533	B2	7/2012	Diab et al.	8,682,407	B2	3/2014	Al-Ali
8,233,955	B2	7/2012	Al-Ali et al.	RE44,823	E	4/2014	Parker
8,244,325	B2	8/2012	Al-Ali et al.	8,690,799	B2	4/2014	Telfort et al.
8,255,026	B1	8/2012	Al-Ali	8,700,112	B2	4/2014	Kiani
8,255,027	B2	8/2012	Al-Ali et al.	8,702,627	B2	4/2014	Telfort et al.
8,255,028	B2	8/2012	Al-Ali et al.	8,706,179	B2	4/2014	Parker
8,260,577	B2	9/2012	Weber et al.	8,712,494	B1	4/2014	MacNeish, III et al.
8,265,723	B1	9/2012	McHale et al.	8,715,206	B2	5/2014	Telfort et al.
8,274,360	B2	9/2012	Sampath et al.	8,718,735	B2	5/2014	Lamego et al.
8,301,217	B2	10/2012	Al-Ali et al.	8,718,737	B2	5/2014	Diab et al.
8,310,336	B2	11/2012	Muhsin et al.	8,718,738	B2	5/2014	Blank et al.
8,315,683	B2	11/2012	Al-Ali et al.	8,720,249	B2	5/2014	Al-Ali
RE43,860	E	12/2012	Parker	8,721,541	B2	5/2014	Al-Ali et al.
8,337,403	B2	12/2012	Al-Ali et al.	8,721,542	B2	5/2014	Al-Ali et al.
8,346,330	B2	1/2013	Lamego	8,723,677	B1	5/2014	Kiani
8,353,842	B2	1/2013	Al-Ali et al.	8,740,792	B1	6/2014	Kiani et al.
8,355,766	B2	1/2013	MacNeish, III et al.	8,754,776	B2	6/2014	Poeze et al.
8,359,080	B2	1/2013	Diab et al.	8,755,535	B2	6/2014	Telfort et al.
8,364,223	B2	1/2013	Al-Ali et al.	8,755,856	B2	6/2014	Diab et al.
8,364,226	B2	1/2013	Diab et al.	8,755,872	B1	6/2014	Marinow
8,374,665	B2	2/2013	Lamego	8,761,850	B2	6/2014	Lamego
8,385,995	B2	2/2013	Al-Ali et al.	8,764,671	B2	7/2014	Kiani
8,385,996	B2	2/2013	Smith et al.	8,768,423	B2	7/2014	Shakespeare et al.
8,388,353	B2	3/2013	Kiani et al.	8,771,204	B2	7/2014	Telfort et al.
8,399,822	B2	3/2013	Al-Ali	8,777,634	B2	7/2014	Kiani et al.
8,401,602	B2	3/2013	Kiani	8,781,543	B2	7/2014	Diab et al.
8,405,608	B2	3/2013	Al-Ali et al.	8,781,544	B2	7/2014	Al-Ali et al.
8,414,499	B2	4/2013	Al-Ali et al.	8,781,549	B2	7/2014	Al-Ali et al.
8,418,524	B2	4/2013	Al-Ali	8,788,003	B2	7/2014	Schurman et al.
8,423,106	B2	4/2013	Lamego et al.	8,790,268	B2	7/2014	Al-Ali
8,428,967	B2	4/2013	Olsen et al.	8,801,613	B2	8/2014	Al-Ali et al.
				8,821,397	B2	9/2014	Al-Ali et al.
				8,821,415	B2	9/2014	Al-Ali et al.
				8,830,449	B1	9/2014	Lamego et al.
				8,831,700	B2	9/2014	Schurman et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

8,840,549 B2 9/2014 Al-Ali et al.
 8,847,740 B2 9/2014 Kiani et al.
 8,849,365 B2 9/2014 Smith et al.
 8,852,094 B2 10/2014 Al-Ali et al.
 8,852,994 B2 10/2014 Wojtczuk et al.
 8,868,147 B2 10/2014 Stippick et al.
 8,868,150 B2 10/2014 Al-Ali et al.
 8,870,792 B2 10/2014 Al-Ali et al.
 8,886,271 B2 11/2014 Kiani et al.
 8,888,539 B2 11/2014 Al-Ali et al.
 8,888,708 B2 11/2014 Diab et al.
 8,892,180 B2 11/2014 Weber et al.
 8,897,847 B2 11/2014 Al-Ali
 8,909,310 B2 12/2014 Lamego et al.
 8,911,377 B2 12/2014 Al-Ali
 8,912,909 B2 12/2014 Al-Ali et al.
 8,920,317 B2 12/2014 Al-Ali et al.
 8,921,699 B2 12/2014 Al-Ali et al.
 8,922,382 B2 12/2014 Al-Ali et al.
 8,929,964 B2 1/2015 Al-Ali et al.
 8,942,777 B2 1/2015 Diab et al.
 8,948,834 B2 2/2015 Diab et al.
 8,948,835 B2 2/2015 Diab
 8,965,471 B2 2/2015 Lamego
 8,983,564 B2 3/2015 Al-Ali
 8,989,831 B2 3/2015 Al-Ali et al.
 8,996,085 B2 3/2015 Kiani et al.
 8,998,809 B2 4/2015 Kiani
 9,028,429 B2 5/2015 Telfort et al.
 9,037,207 B2 5/2015 Al-Ali et al.
 9,060,721 B2 6/2015 Reichgott et al.
 9,066,666 B2 6/2015 Kiani
 9,066,680 B1 6/2015 Al-Ali et al.
 9,072,474 B2 7/2015 Al-Ali et al.
 9,078,560 B2 7/2015 Schurman et al.
 9,084,569 B2 7/2015 Weber et al.
 9,095,316 B2 8/2015 Welch et al.
 9,106,038 B2 8/2015 Telfort et al.
 9,107,625 B2 8/2015 Telfort et al.
 9,107,626 B2 8/2015 Al-Ali et al.
 9,113,831 B2 8/2015 Al-Ali
 9,113,832 B2 8/2015 Al-Ali
 9,119,595 B2 9/2015 Lamego
 9,131,881 B2 9/2015 Diab et al.
 9,131,882 B2 9/2015 Al-Ali et al.
 9,131,883 B2 9/2015 Al-Ali
 9,131,917 B2 9/2015 Telfort et al.
 9,138,180 B1 9/2015 Coverston et al.
 9,138,182 B2 9/2015 Al-Ali et al.
 9,138,192 B2 9/2015 Weber et al.
 9,142,117 B2 9/2015 Muhsin et al.
 9,153,112 B1 10/2015 Kiani et al.
 9,153,121 B2 10/2015 Kiani et al.
 9,161,696 B2 10/2015 Al-Ali et al.
 9,161,713 B2 10/2015 Al-Ali et al.
 9,167,995 B2 10/2015 Lamego et al.
 9,176,141 B2 11/2015 Al-Ali et al.
 9,186,102 B2 11/2015 Bruinsma et al.
 2009/0247984 A1 10/2009 Lamego et al.
 2009/0275844 A1 11/2009 Al-Ali
 2010/0004518 A1 1/2010 Vo et al.
 2010/0030040 A1 2/2010 Poeze et al.
 2011/0001605 A1 1/2011 Kiani et al.
 2011/0082711 A1 4/2011 Poeze et al.
 2011/0105854 A1 5/2011 Kiani et al.
 2011/0208015 A1 8/2011 Welch et al.
 2011/0213212 A1 9/2011 Al-Ali
 2011/0230733 A1 9/2011 Al-Ali
 2011/0237911 A1 9/2011 Lamego et al.
 2012/0059267 A1 3/2012 Lamego et al.
 2012/0179006 A1 7/2012 Jansen et al.
 2012/0209082 A1 8/2012 Al-Ali
 2012/0209084 A1 8/2012 Olsen et al.
 2012/0227739 A1 9/2012 Kiani

2012/0283524 A1 11/2012 Kiani et al.
 2012/0296178 A1 11/2012 Lamego et al.
 2012/0319816 A1 12/2012 Al-Ali
 2012/0330112 A1 12/2012 Lamego et al.
 2013/0023775 A1 1/2013 Lamego et al.
 2013/0041591 A1 2/2013 Lamego
 2013/0045685 A1 2/2013 Kiani
 2013/0046204 A1 2/2013 Lamego et al.
 2013/0060147 A1 3/2013 Welch et al.
 2013/0096405 A1 4/2013 Garfio
 2013/0096936 A1 4/2013 Sampath et al.
 2013/0190581 A1 7/2013 Al-Ali et al.
 2013/0197328 A1 8/2013 Diab et al.
 2013/0211214 A1 8/2013 Olsen
 2013/0243021 A1 9/2013 Siskavich
 2013/0253334 A1 9/2013 Al-Ali et al.
 2013/0296672 A1 11/2013 O'Neil et al.
 2013/0317370 A1 11/2013 Dalvi et al.
 2013/0324808 A1 12/2013 Al-Ali et al.
 2013/0331670 A1 12/2013 Kiani
 2013/0338461 A1 12/2013 Lamego et al.
 2014/0012100 A1 1/2014 Al-Ali et al.
 2014/0034353 A1 2/2014 Al-Ali et al.
 2014/0051953 A1 2/2014 Lamego et al.
 2014/0058230 A1 2/2014 Abdul-Hafiz et al.
 2014/0066783 A1 3/2014 Kiani et al.
 2014/0077956 A1 3/2014 Sampath et al.
 2014/0081100 A1 3/2014 Muhsin et al.
 2014/0081175 A1 3/2014 Telfort
 2014/0094667 A1 4/2014 Schurman et al.
 2014/0100434 A1 4/2014 Diab et al.
 2014/0114199 A1 4/2014 Lamego et al.
 2014/0120564 A1 5/2014 Workman et al.
 2014/0121482 A1 5/2014 Merritt et al.
 2014/0121483 A1 5/2014 Kiani
 2014/0127137 A1 5/2014 Bellott et al.
 2014/0129702 A1 5/2014 Lamego et al.
 2014/0135588 A1 5/2014 Al-Ali et al.
 2014/0142401 A1 5/2014 Al-Ali et al.
 2014/0163344 A1 6/2014 Al-Ali
 2014/0163402 A1 6/2014 Lamego et al.
 2014/0166076 A1 6/2014 Kiani et al.
 2014/0171763 A1 6/2014 Diab
 2014/0180038 A1 6/2014 Kiani
 2014/0180154 A1 6/2014 Sierra et al.
 2014/0194709 A1 7/2014 Al-Ali et al.
 2014/0194711 A1 7/2014 Al-Ali
 2014/0194766 A1 7/2014 Al-Ali et al.
 2014/0206963 A1 7/2014 Al-Ali
 2014/0213864 A1 7/2014 Abdul-Hafiz et al.
 2014/0243627 A1 8/2014 Diab et al.
 2014/0266790 A1 9/2014 Al-Ali et al.
 2014/0275808 A1 9/2014 Poeze et al.
 2014/0275835 A1 9/2014 Lamego et al.
 2014/0275871 A1 9/2014 Lamego et al.
 2014/0275872 A1 9/2014 Merritt et al.
 2014/0275881 A1 9/2014 Lamego et al.
 2014/0288400 A1 9/2014 Diab et al.
 2014/0303520 A1 10/2014 Telfort et al.
 2014/0316228 A1 10/2014 Blank et al.
 2014/0323825 A1 10/2014 Al-Ali et al.
 2014/0330092 A1 11/2014 Al-Ali et al.
 2014/0330098 A1 11/2014 Merritt et al.
 2014/0330099 A1 11/2014 Al-Ali et al.
 2014/0333440 A1 11/2014 Kiani
 2014/0336481 A1 11/2014 Shakespeare et al.
 2014/0343436 A1 11/2014 Kiani
 2015/0018650 A1 1/2015 Al-Ali et al.

FOREIGN PATENT DOCUMENTS

EP 0 761 159 A2 8/1996
 JP 2002-51129 4/2002
 WO WO 94/09698 9/1993
 WO WO 98/46125 4/1998
 WO WO 99/52420 10/1999

* cited by examiner





FIG. 1

FIG. 2






FIG. 3




FIG. 4




FIG. 5





FIG. 6






FIG. 8






FIG. 9






FIG. 12






FIG. 13

*FIG. 14*

*FIG. 15*




FIG. 16




FIG. 17





FIG. 18

*FIG. 19*




FIG. 20

1

METHOD AND APPARATUS FOR DEMODULATING SIGNALS IN A PULSE OXIMETRY SYSTEM

REFERENCE TO PRIOR RELATED APPLICATION

This application is a continuation of U.S. application Ser. No. 13/437,800, filed Apr. 2, 2012, entitled "Method and Apparatus for Demodulating Signals in a Pulse Oximetry System," which is a continuation of U.S. application Ser. No. 11/750,930 (now U.S. Pat. No. 8,150,487), filed May 18, 2007, entitled "Method And Apparatus for Demodulating Signals In A Pulse Oximetry System," which is a continuation of U.S. application Ser. No. 11/311,213 (now U.S. Pat. No. 7,221,971), filed Dec. 19, 2005, entitled "Method And Apparatus For Demodulating Signals In A Pulse Oximetry System," which is a continuation of U.S. application Ser. No. 10/700,324 (now U.S. Pat. No. 7,003,339), filed Nov. 3, 2003, entitled "Method And Apparatus For Demodulating Signals In A Pulse Oximetry System," which is a divisional of U.S. application Ser. No. 09/735,960 (now U.S. Pat. No. 6,643,530) filed Dec. 13, 2000, entitled "Method And Apparatus For Demodulating Signals In A Pulse Oximetry System," which is a divisional of U.S. application Ser. No. 09/058,799 (now U.S. Pat. No. 6,229,856) filed Apr. 10, 1998, entitled "Method And Apparatus For Demodulating Signals In A Pulse Oximetry System," which is a continuation-in-part of U.S. application Ser. No. 09/005,898 (now U.S. Pat. No. 5,919,134) filed Jan. 12, 1998, entitled "Method And Apparatus For Demodulating Signals In A Pulse Oximetry System," which claims priority from U.S. Provisional Application No. 60/043,620, filed Apr. 14, 1997. The foregoing are all incorporated by reference in their entirety.

FIELD OF THE INVENTION

The present invention relates to the field of signal processing, and, more particularly, relates to the field of processing of signals generated in a physiological monitoring system, such as, for example, in a system for measuring blood oxygen saturation using pulse oximetry.

BACKGROUND

The present invention will be described herein in connection with a pulse oximetry apparatus and a method, which are used to measure blood oxygen saturation in a subject, such as, for example, a human patient. The teachings of the present invention can be used in other applications wherein useable signal information is obtained in a noisy environment.

In an exemplary pulse oximetry apparatus and a corresponding method, blood oxygen saturation is determined by transmitting pulses of electromagnetic energy through a portion of a subject which has blood flowing therein (e.g., through a finger, through an ear lobe, or other portion of the body where blood flows close to the skin). In the examples described herein, the pulses of electromagnetic energy comprise periodic pulses of red light having wavelengths of approximately 660 nanometers, for example, and periodic pulses of infrared light having wavelengths of approximately 905 nanometers. As described, for example, in U.S. Pat. No. 5,482,036 and in U.S. Pat. No. 5,490,505 the pulses of red light and the pulses of infrared light are applied with the same periodicity but in an alternating and non-overlapping manner. In particular, in preferred embodiments, the red pulses are active for approximately 25% of each cycle and the infrared

2

pulses are also active for approximately 25% of each cycle. The red pulses are separated in time from the infrared pulses such that both pulses are inactive for approximately 25% of each cycle between a red pulse and the next infrared pulse and both pulses are inactive for approximately 25% of each cycle between an infrared pulse and the next red pulse. (Although described herein below in connection with pulses having 25% duty cycles, it should be understood by persons of skill in the art that the duty cycles of the pulses can be changed in some applications.) After propagating through the portion of the subject, the red pulses and the infrared pulses are detected by a detector which is responsive to light at both wavelengths and which generates an electrical signal which has a predictable relationship to the intensity of the electromagnetic energy incident on the detector. The electrical signal is processed in accordance with the present invention to provide a representation of the blood oxygen saturation of the subject. In conventional time division multiplexing (TDM) demodulation that uses rectangular waves to drive the red and infrared LEDs, the conventional process of demodulation using square waves can result in the aliasing of the ambient noise components that come close to the sidebands of harmonics and the fundamental frequency of the rectangular waves, and the noise components are thus collapsed into the output signal generated by the demodulation. In particular, it is very difficult to avoid including harmonics of the line frequency in the demodulated output signal.

In conventional time division multiplexing (TDM) demodulation that uses rectangular waves to drive the red and infrared LEDs, the conventional process of demodulation using square waves can result in the aliasing of the ambient noise components that come close to the sidebands of harmonics and the fundamental frequency of the rectangular waves, and the noise components are thus collapsed into the output signal generated by the demodulation. In particular, it is very difficult to avoid including harmonics of the line frequency in the demodulated output signal.

SUMMARY

The present invention avoids the problems associated with conventional demodulation and separation of TDM signals. In particular, the present invention avoids the problem of aliasing of the ambient noise into the passband of the system by selectively demodulating certain harmonics of the TDM signal. For example, in one embodiment, only two harmonics (e.g., the fundamental and the first harmonic) are demodulated. In resulting from demodulating with only certain harmonics instead of demodulating with all harmonics as is done using conventional square wave demodulation. In a digital implementation of the present, invention, the output of the photodetector is initially sampled at a very high frequency (e.g., 46,875 Hz), and the signals are decimated (where decimation is lowpass filtering followed by sample rate compression) such that the final output signals are generated at a relatively low sampling rate (e.g., 62.5 Hz) which provides increased resolution at the output. Thus, bandwidth is traded for resolution in the output signal, thus increasing the signal to noise ratio.

One aspect of the present invention is an apparatus for measuring blood oxygenation in a subject. The apparatus comprises a first signal source which applies a first input signal during a first time interval. A second signal source applies a second input signal during a second time interval. A detector detects a first parametric signal responsive to the first input signal passing through a portion of the subject having blood therein. The detector also detects a second parametric

signal responsive to the second input signal passing through the portion of the subject. The detector generates a detector output signal responsive to the first and second parametric signals. A signal processor receives the detector output signal. The signal processor demodulates the detector output signal by applying a first demodulation signal to a signal responsive to the detector output signal to generate a first output signal responsive to the first parametric signal and by applying a second demodulation signal to the signal responsive to the detector output signal to generate a second output signal responsive to the second parametric signal. Each of the first demodulation signal and the second demodulation signal comprises at least a first component having a first frequency and a first amplitude and a second component having a second frequency and a second amplitude. The second frequency is a harmonic of the first frequency. The second amplitude is selected to be related to the first amplitude to minimize crosstalk from the first parametric signal to the second output signal and to minimize crosstalk from the second parametric signal to the first output signal. In one embodiment, the second amplitude is determined by turning off one of the first and second signal sources and measuring the crosstalk between one of the parametric signals and the non-corresponding output signal while varying the second amplitude. A second amplitude is selected that minimizes the measured crosstalk.

Another aspect of the present invention is a method of minimizing crosstalk between two signals generated by applying a first pulse and a second pulse to measure a parameter. The first pulse and the second pulse are applied periodically at a first repetition rate defining a period. The first pulse is generated during a first interval in each period, and the second pulse is generated during a second interval in each period. The second interval is spaced, apart from the first interval. The first and second pulses produce first and second parametric signals responsive to the parameter. The first and second parametric signals are received by a single detector that outputs a composite signal responsive to the first and second parametric signals. The method comprises the step of applying a first demodulation signal to the composite signal to generate a first demodulated output signal wherein the first demodulation signal comprises at least a first component having a first frequency corresponding to the first repetition rate. The first component has a first amplitude. The first demodulation signal further comprises a second component having a second frequency that is a harmonic of the first frequency. The second component has a second amplitude which has a selected proportional relationship to the first amplitude. The method further includes the step of applying a second demodulation signal to the composite signal to generate a second demodulated output signal. The second demodulation signal comprises the first component at the first frequency and the first amplitude and further comprises the second component at the second frequency and the second amplitude. At least one of the first and second components of the second demodulation signal has a selected phase difference with respect to the corresponding one of the first and second components of the first demodulation signal. The method further includes the steps of lowpass filtering the first demodulated output signal to generate a first recovered output signal responsive to the first parametric signal; and lowpass filtering the second demodulated output signal to generate a second recovered output signal responsive to the second parametric signal.

Preferably, the selected phase difference is π . Also preferably, the first pulse and the second pulse are generally rectangular pulses having a respective duty cycle. The rectangular pulses comprise a plurality of sinusoidal components

including a fundamental component corresponding to the first frequency and a first harmonic component corresponding to the second frequency. The fundamental component has a fundamental component amplitude and the first harmonic component has a first harmonic component amplitude. The first harmonic component amplitude is related to the fundamental harmonic component amplitude by a first proportionality value. The second amplitude of the second component of the first demodulation signal is related to the first amplitude of the first component of the first demodulation signal by a second proportionality value which is approximately the inverse of the first proportionality value.

The method in accordance with this aspect of the invention preferably includes the further steps of sampling the composite signal when neither the first pulse nor the second pulse is active to obtain a sampled signal; and measuring the sampled signal to determine a noise level of the parametric signals.

In a further embodiment according to this aspect of the present invention, the method further includes the steps of performing a transform on the composite signal to generate a spectra of the composite signal; sampling the spectra at a plurality of frequencies other than at predetermined ranges of frequencies around the first frequency and around harmonics of the first frequency; determining an average of the magnitudes of the sampled plurality of frequencies; and comparing the average to a selected threshold to determine whether the average magnitude exceeds the selected threshold.

Another aspect of the present invention is a method of demodulating a composite signal generated by applying first and second periodic pulses of electromagnetic energy to a system having a parameter to be measured and by receiving signals responsive to the electromagnetic energy after having passed through the system and being affected by the parameter being measured. The signals are received as a composite signal having components responsive to the first and second pulses. The method comprises the step of applying a first demodulation signal to the composite signal to generate a first demodulated signal. The first demodulation signal comprises a first component having a first frequency corresponding to a repetition frequency of the first and second pulses and comprises a second component having a frequency that is a harmonic of the first frequency. The first component has a first amplitude and the second component has a second amplitude. The second amplitude has a predetermined relationship to the first amplitude. The predetermined relationship is selected to cause the first demodulated signal to have low frequency components responsive only to the first pulse. The method includes the further step of lowpass filtering the first demodulated signal to generate a first output signal. The first output signal varies in response to an effect of the parameter on the electromagnetic energy received from the first pulse.

Preferably, the method in accordance with this aspect of the invention includes the further step of applying a second demodulation signal to the composite signal to generate a second demodulated signal. The second demodulation signal has first and second components corresponding to the first and second components of the first demodulation signal. At least one of the first and second components of the second demodulation signal has a selected phase relationship with the corresponding one of the first and second components of the first demodulation signal. The method includes the further step of lowpass filtering the second demodulated signal to generate a second output signal. The second output signal varies in response to an effect of the parameter on the electromagnetic energy received from the second pulse.

Another aspect of the present invention is a pulse oximetry system that comprises a modulation signal generator. The

modulation signal generator generates a first modulation signal that comprises a first pulse that repeats at a first repetition frequency. The first pulse has a duty cycle of less than 50%. The modulation signal generator generates a second modulation signal comprising a second pulse that also repeats at the first repetition frequency. The second pulse has a duty cycle of less than 50%. The second pulse occurs at non-overlapping times with respect to the first pulse. Each of the first and second pulses comprises a plurality of components wherein a first component has a frequency corresponding to the repetition frequency and wherein a second component has a second frequency corresponding to twice the first frequency. The second component has an amplitude which has a first predetermined relationship to an amplitude of the first component. A first transmitter emits electromagnetic energy at a first wavelength in response to the first pulse; and a second transmitter emits electromagnetic energy at a second wavelength in response to the second pulse. A detector receives electromagnetic energy at the first and second wavelengths after passing through a portion of a subject and generates a detector output signal responsive to the received electromagnetic energy. The detector output signal includes a signal component responsive to attenuation of the electromagnetic energy at the first wavelength and a signal component responsive to attenuation of the electromagnetic energy at the second wavelength. A first demodulator multiplies the detector signal by a first demodulation signal and generates a first demodulated output signal. The first demodulation signal comprises a first component having the first frequency and having a first amplitude. The first demodulation signal also comprises a second component having the second frequency and having a second amplitude. The second amplitude has a second predetermined relationship to the first amplitude. The second predetermined relationship is approximately inversely proportional to the first predetermined relationship. A second demodulator multiplies the detector signal by a second demodulation signal and generates a second demodulated output signal. The second demodulation signal comprises a first component having the first frequency and having the first amplitude. The second demodulation signal further comprises a second component having the second frequency and having the second amplitude. At least one component of the second demodulation signal has a selected phase relationship with a corresponding one component of the first demodulation signal. Preferably, the selected phase relationship is a π phase difference.

Another embodiment incorporates declination before demodulation. In yet another embodiment, a multi-channel demodulator, with or without pre-demodulation decimation is disclosed.

In yet another embodiment, an adaptive algorithm is used to control the operation of pre-demodulation decimators and post-demodulation decimators. The adaptive algorithm may control both the characteristics of a lowpass filter in the decimator and the decimation rate provided by a signal rate compressor in the decimator.

Another embodiment of the invention is a method for selecting a sample rate that reduces the interference caused by ambient light.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be described below in connection with the accompanying drawing figures in which:

FIG. 1 illustrates an exemplary block diagram of a representation of a signal processing system in accordance with the present invention used to determine blood oxygen saturation in a subject;

FIG. 2 illustrates exemplary waveforms of the current through the LEDs in FIG. 1 and the resulting intensities of the red light and the infrared light generated by the LEDs;

FIG. 3 illustrates a block diagram of the overall processing system in accordance with the present invention;

FIG. 4 illustrates a frequency spectra of the first modulation signal $MI(t)$ for $n=0, 1, 2, \dots$, where the horizontal axis represents frequency and the vertical axis represents the energy in the DC and harmonic components of the signal;

FIG. 5 illustrates an exemplary spectrum of the first and second harmonics of the present invention when the fundamental frequency is selected to be 316.7 Hz in comparison to the fundamental and harmonics of conventional 60 Hz power;

FIG. 6 illustrates the effect of the value of B on the measured signal output $\hat{S}_2(t)$ responsive to the red modulation pulses as the value of B is varied while the infrared modulation pulses are off;

FIG. 7 illustrates a preferred embodiment of the present invention implemented in a digital processing system;

FIG. 8 illustrates a detailed block diagram of the demodulation portion of the present invention;

FIG. 9 illustrates a detailed block diagram of the modulation portion of the present invention;

FIG. 10 illustrates the red drive waveform and the infrared drive waveform generated by the modulation portion of FIG. 9;

FIG. 11 illustrates the demodulation waveforms generated by the demodulation portion of FIG. 8;

FIG. 12 illustrates a method of time domain sampling the digital detection signal during the times when both the red pulses and the infrared pulses are off to obtain information regarding the level of ambient noise;

FIG. 13 illustrates a block diagram of a system that performs the time domain sampling of FIG. 12;

FIG. 14 illustrates a method of frequency domain sampling to determine the noise floor at frequencies other than the signal frequencies;

FIG. 15 illustrates a block diagram of a system that performs the frequency domain sampling of FIG. 14;

FIG. 16 illustrates a block diagram of the overall processing system in accordance with a pre-demodulation decimation embodiment of the present invention;

FIG. 17 illustrates a block diagram of a multi-channel processing system in accordance with a pre-demodulation decimation embodiment of the present invention;

FIG. 18 illustrates a block diagram of an adaptive multi-channel processing system in accordance with a pre-demodulation decimation embodiment of the present invention;

FIG. 19 illustrates a flowchart of a method for choosing the modulation frequency and decimation rate in order to minimize the affects of ambient light; and

FIG. 20 is a graph to be used in connection with graphical method for designing a demodulation system to minimize interference due to ambient light.

DETAILED DESCRIPTION

FIG. 1 illustrates an exemplary block diagram of a representation of a signal presented, the measurements are performed on a portion of the subject, such as a finger 102 illustrated in FIG. 1. An LED modulation circuit 104 drives a pair of back-to-back light emitting diodes (LEDs) 106, 108 by applying a periodic signal to the two light emitting diodes

106, 108. The LED **106** is selected to emit electromagnetic energy in the red visible light range, and has a wavelength of, for example, approximately 660 nanometers. The LED **108** is selected to emit electromagnetic energy in the infrared range, and has a wavelength of, for example, approximately 905 nanometers. The LED modulation circuit **104** supplies current in alternating directions so that the two LEDs **106, 108** are activated one at a time. In particular, as illustrated by a current waveform **120** in FIG. 2, current is first applied in a forward direction with respect to the red LED **106** during a first time interval **122** having a duration τ . Thereafter, no current is applied to either LED during a second time interval **124** having a like duration τ . Then, current is applied in a forward direction with respect to the infrared LED **108** during a third time interval **126**, also having a duration τ . Then, no current is applied to either LED during a fourth time interval **128** having a like duration τ . Thereafter, the current is again applied in the forward direction for the red LED **106** during a fifth time interval **130** which corresponds to the first time interval **122**. It can be seen that the overall cycle repeats with a period of duration T equal to 4τ . The red LED **106** emits light only when the current is applied in the forward direction with respect to the red LED **106**. Thus, as illustrated by a red intensity waveform **132**, the red LED **106** emits light as a pulse **134** during the first time interval **122** and as a pulse **136** during the fifth time interval **130**, and so on. The red pulses repeat with a periodicity equal to T . Similarly, the infrared LED **108** emits infrared light only when the current is applied in the forward direction with respect to the infrared LED **108**. Thus, as illustrated by an infrared intensity waveform **140**, the infrared LED **108** emits infrared light as a pulse **142** during the third interval **126**. A next infrared pulse **144** occurs at an interval T after the infrared pulse **142**. Thus, the infrared pulses also repeat with a periodicity equal to T . It can be seen that the red pulses and the infrared pulses each have a duty cycle of 25%, and the red pulses and the infrared pulses are separated by intervals of one-fourth of each period T (i.e., the beginning of one pulse occurs an interval τ after the end of the previous pulse).

As further illustrated in FIG. 1, the electromagnetic energy pulses from the red LED **106** and the infrared LED **108** are applied to the finger **102**. A detector **150** is positioned to receive the electromagnetic energy after the energy has passed through a portion of the finger **102**. The detector **150** is selected to be responsive to both the red light and the infrared light and to generate an output signal responsive to the intensity of the energy received from each source. An exemplary current output signal from the detector **150** is represented by a waveform **152** in FIG. 2. As illustrated, the detector signal waveform **152** comprises a first pulse **154** responsive to the first red pulse **134**, a second pulse **156** responsive to the infrared pulse **142** and a third pulse **158** responsive to the second red pulse **136**. During the time between the first pulse **154** and the second pulse **156**, the detector signal waveform **152** comprises noise **160**, and during the time between the second pulse **156** and the third pulse **158**, the detector signal waveform **152** comprises noise **162**. The signal pulses **154, 156** and **158** also include noise superimposed thereon. Although shown as repeating noise, it should be understood that the noise varies with time. For example, noise caused by ambient light will vary with a periodicity corresponding to the 50 Hz or 60 Hz power frequency and their harmonics, particularly when the ambient light is provided by fluorescent lights which generate significant noise at the first harmonic (i.e., 100 Hz or 120 Hz) and the third harmonic (i.e., 200 Hz or 240 Hz).

The output of the detector **150** is applied as an input to a signal processor block **170** which processes the detector signal and generates a first signal $\hat{S}_1(t)$ responsive to the detected intensity of the red light incident on the detector **150** and generates a second signal $\hat{S}_2(t)$ responsive to the detected intensity of the infrared light incident on the detector **150**. As illustrated, the signal processing block **170** is synchronized with the LED modulator **104** via a set of control lines **180**. As will be discussed below, the control lines **180** advantageously communicate signals which provide timing information that determines when to activate the red LED **106** and when to activate the infrared LED **108**.

FIG. 3 is a pictorial representation of a model of an exemplary system which incorporates the present invention. The red LED **106** provides a light intensity represented as I_{RD} , and the infrared LED **108** provides a light intensity represented as I_{IR} . The effects of turning the LEDs **106, 108** on and off on periodic bases are modeled by a first multiplier or modulator **190** which applies a first modulation signal $M_1(t)$ to the red light intensity to generate a modulated red signal $I_{IRMOD}(t)$ and by a second multiplier or modulator **192** which applies a second modulation signal $M_2(t)$ to the infrared light intensity to generate a modulated infrared signal $I_{IRMOD}(t)$. The modulated light red signal and the modulated infrared signal are applied to the finger **102**, or other body portion, as described above. The finger **102** has blood flowing therein and is represented in FIG. 3 as a block **102**. The blood in the finger **102** has a volume and scattering components which vary throughout each cardiac cycle. The blood carries oxygen and other materials therein. The oxygen content is a function of both the blood volume and the concentration of the oxygen in the blood volume. The concentration of the oxygen in the blood volume is generally measured as blood oxygen saturation for reasons which are described in full in the above-identified issued U.S. Pat. Nos. 5,482,036 and 5,490,505. As further described in the two referenced patents, the blood oxygen saturation is determined by comparing the relative absorption of the red light and the infrared light in the finger **102**. The comparison is complicated by the noise caused by movement, ambient light, light scattering, and other factors.

In FIG. 3, a pair of signals $S_1(t)$ and $S_2(t)$ represent the effect of the time-varying volume and scattering components of the blood in the finger **102** on the red light and the infrared light, respectively, passing through the finger **102** from the LEDs **106, 108** to the detector **150**. The red light signal portion $S_1(t)$ is caused by the variable attenuation of the red light passing through the finger **102**. The infrared light signal portion $S_2(t)$ is caused by the variable attenuation of the infrared light passing through the finger **102**. To show the effect of the variable attenuations, the signal portion $S_1(t)$ is illustrated as being applied to a first attenuation modulator **191** which multiplies the signal $S_1(t)$ by the modulated red output $I_{IRMOD}(t)$ of the first modulator **190**. Similarly, the infrared light signal portion $S_2(t)$ is illustrated as being applied to a second attenuation modulator **193** which multiplies the signal $S_2(t)$ by the modulated infrared output $I_{IRMOD}(t)$ of the second modulator **192**. The outputs of the first and second attenuation modulators **191, 193** are provided to the receiving photodetector **150**. The photodetector **150** is modeled as adder **194** and an adder **196**. The outputs of the first and second attenuation modulators **191, 193** are provided to the adder **194** to generate a composite signal $M(t)$ where:

$$M(t) = S_1(t)M_1(t) + S_2(t)M_2(t). \quad (1)$$

The signal $M(t)$ from the adder **194** is provided to the adder **196** where the signal $M(t)$ is added to a signal $n(t)$ which represents a composite noise signal caused by ambient light,

electromagnetic pickup, and the like, which are also detected by the photodetector 150. The output of the adder 196 is a signal $M'(t) = M(t) + n(t)$ which includes noise components as well as the signal components. The noise components include DC components and harmonics of the power line frequency that appear in the ambient light. In addition, as will be discussed in more detail below, the signal $M'(t)$ may also include noise at higher frequencies caused, for example, by other devices such as electrocauterization equipment, or the like.

The $M'(t)$ signal output of the third adder 196 (i.e., the output of the detector 150) is applied to the input of the signal processing block 170. Within the signal processing block 170, the signal $M'(t)$ is first passed through a fixed gain amplifier 197 and then through an analog bandpass filter 198. The analog bandpass filter 198 has a passband selected to pass signals in the range of 20 Hz, to 10,000 Hz. Thus, the analog bandpass filter 198 removes a significant portion of the noise below 10 Hz. The signal components responsive to the blood oxygen saturation are frequency shifted by the operation of the two modulation signals $M_1(t)$ and $M_2(t)$ and are passed by the analog bandpass filter 198.

In the preferred embodiment, the output of the analog bandpass filter 198 is sampled by an analog-to-digital converter 199 and converted therein to digital signals. For example, the signals are preferably sampled at 46,875 samples per second. The output of the analog-to-digital converter 199 is a signal $MF(k)$.

The signal $MF(k)$ is provided as a first input to a first demodulating multiplier 210. The signal $MF(k)$ is also provided as a first input to a second demodulating multiplier 212. A first demodulating signal $D_1(k)$ is provided as a second input to the first demodulating multiplier 210, and a second demodulating signal $D_2(k)$ is provided as a second input to the second demodulating multiplier 212. The output of the first demodulating multiplier 210 is provided as an input to a first lowpass filter 220, and the output of the second demodulating multiplier is provided as an input to a second lowpass filter 222. The bandwidths of the lowpass filters 220, 222 are preferably approximately 10 Hz.

The output of the first lowpass filter 220 is a signal $\hat{S}_1(t)$, which, as discussed below, is an estimate of the signal $S_1(t)$. The output of the second lowpass filter 222 is a signal $\hat{S}_2(t)$, which, as discussed below, is an estimate of the signal $S_2(t)$. As will be shown below, the selection of the first demodulating signal $D_1(k)$ and the second demodulating signal $D_2(k)$ in accordance with the present invention substantially reduces or eliminates the effects of noise in the two output signals $\hat{S}_1(t)$ and $\hat{S}_2(t)$ and also substantially reduces or eliminates crosstalk between the two signals.

In the preferred embodiment of the present invention, the sample rates of the outputs of the lowpass filter 220 and the lowpass filter 222 are compressed by respective sample rate compressors 221 and 223. In particular, the sample rate compressors 221, 223 reduce the sample rate by 750 to a sample rate of, for example, 62.5 Hz to provide an output which can be further processed in accordance with the methods and apparatuses described in the above-referenced patents. The sample rate compressions which occur in the sample rate compressors 221, 223 reduce the rate at which the output signals $\hat{S}_1(t)$ and $\hat{S}_2(t)$ need to be processed while maintaining the sample rate well above the 0-10 Hz frequency content of the signals of interest. The outputs of the filters 220, 222, or the sample rate compressors 221, 223, if included, are provided on respective output lines 224 and 226.

In order to facilitate an understanding of how the present invention operates in demodulating the output signal $MF(k)$ from the analog-to-digital converter 199, the modulation sig-

nals $M_1(t)$ and $M_2(t)$ will first be described in terms of their frequency components. One skilled in the art will appreciate that the modulation signals $M_1(t)$ and $M_2(t)$ can each be represented as a Fourier cosine series expansion (e.g., $\sum_{n=0}^{\infty} a_n \cos(n\omega t)$, where $\omega = 2\pi/T$) representing the fundamental and harmonic frequencies of the rectangular signal pulses. One skilled in the art will understand that the Fourier series expansion includes phases; however, by suitably selecting the time origin, the phases are set to zero. A component which is 180° out of phase with a corresponding component will advantageously be represented by a minus sign before the coefficient.

FIG. 4 illustrates a frequency spectra of the first modulation signal $M_1(t)$ for $n=0, 1, 2, \dots$, where the horizontal axis represents frequency, with the energy in the DC component along the vertical axis and increasing harmonics of the fundamental frequency along the horizontal axis. The length of each component of $M_1(t)$ along the vertical axis represents the energy $E(n)$ in each component of the frequency spectra. The first component to the right of the vertical axis is at the fundamental frequency (i.e., $1/T$), which is designated herein as f_0 ; however, it should be understood that the fundamental frequency f_0 corresponds to $n=1$. The second component to the right of the vertical axis is the first harmonic f_1 (i.e., $n=2$), which has a frequency which is twice the fundamental frequency. The third component to the right of the vertical axis is the second harmonic f_2 (i.e., $n=3$), which has a frequency which is three times the fundamental frequency. The components to the right of the second harmonic are numbered accordingly. (Note, other conventions identify the fundamental frequency as the first harmonic, and designate the second harmonic as the frequency that is twice the fundamental frequency. The identification of the fundamental frequency as f_0 is used in the discussion that follows.)

In FIG. 4, a modulation envelope 230 is shown in dashed lines. The modulation envelope 230 represents the magnitudes of the fundamental and the harmonics of the signal $M_1(t)$. The shape of the envelope is determined by the modulation signal $M_1(t)$ which, for a repeating rectangular pulse train starting at time $t=0$ and having a normalized amplitude of 1, can be expressed as:

$$M_1(t) = \frac{\tau}{T} \sum_{n=0}^{\infty} \text{sinc}\left(\frac{n\tau}{T}\right) \cos\left(\frac{2\pi n t}{T}\right) \quad (2)$$

Where sinc is the function $(\sin \pi x)/\pi x$ (i.e., $\text{sinc}(\pi\tau/T) = \sin(\pi\tau/T)/(\pi\tau/T)$). In the example shown, $\tau = 1/4T$. (Note that for sampled signals, the envelope is more accurately represented as $\sin \alpha / \sin \beta$; however, as well known in the art, for the frequencies of interest, the sinc function is a suitable approximation.) Thus, the frequency spectra has nulls at $n=4, n=8, n=12$, and so on, corresponding to the third harmonic f_3 , the seventh harmonic f_7 , the eleventh harmonic f_{11} , and so on. Note that Equation 2 is an idealized form of the equation for $M_1(t)$, and that in general:

$$M_1(t) = \frac{\tau}{T} \sum_{n=0}^{\infty} a_n \text{sinc}\left(\frac{n\tau}{T}\right) e^{-j\omega_0 n t} \quad (3)$$

where a_n is a complex number. In the discussion that follows, the values of a_n are assumed to be real numbers only.

A similar frequency spectra (not shown) for the modulation signal $M_2(t)$ is determined by the expression:

11

$$M_2(t) = \frac{\tau}{T} \sum_{n=0}^{\infty} (-1)^n \text{sinc}\left(\frac{n\tau}{T}\right) \cos\left(\frac{2\pi n t}{T}\right) \quad (4)$$

An envelope for the frequency spectra of second modulation signal $M_2(t)$ will have the same magnitudes; however, it should be understood that because of the $(-1)^n$ term in the expression for $M_2(t)$, the fundamental f_0 and every even harmonic (i.e., f_2 , f_4 , etc.) are 180° out of phase with the corresponding harmonic of the first modulation signal $M_1(t)$.

In FIG. 3, the analog-to-digital converter **199** converts the signal $M'(t)$ to a sequence of sampled digital values $MF(k)$ at a sampling rate of, for example, 46,875 samples per second. As discussed above, the first demodulating multiplier **210** multiplies the output $MF(k)$ of the converter **199** by the first demodulating signal $D_1(k)$ to generate the first output sequence $\hat{S}_1(k)$, and the second demodulating multiplier **212** multiplies the output $MF(k)$ by the second demodulating signal $D_2(k)$ to generate the second output sequence $\hat{S}_2(k)$. The multiplication by the multipliers **210**, **212** can also be expressed as follows:

$$\hat{S}_2(k) = LP[MF(k)D_1(k)] \quad (5)$$

and

$$\hat{S}_2(k) = LP[MF(k)D_2(k)] \quad (6)$$

where LP is the transfer function of the lowpass filter **220** and of the lowpass filter **222**. If, for simplicity, the noise is assumed to be zero, then:

$$M'(t) = S_1(t)M_1(t) + S_2(t)M_2(t) \quad (7)$$

Therefore:

$$\hat{S}_1(k) = LP[[S_1(k)M_1(k) + S_2(k)M_2(k)]D_1(k)] \quad (8)$$

and thus

$$\hat{S}_1(k) = LP[[S_1(k)M_1(k)]D_1(k) + [S_2(k)M_2(k)]D_1(k)] \quad (9)$$

Similarly:

$$\hat{S}_2(k) = LP[[S_2(k)M_2(k)]D_2(k) + [S_1(k)M_1(k)]D_2(k)] \quad (10)$$

Since LP is a linear operator, the right-hand side of Equations 9 and 10 can be split into two terms. The first term on the right-hand side of each of Equations 9 and 10 above is the desired signal portion of the equation, and the second term on the right-hand side of each of the equations is the crosstalk portion. Thus, in order to reduce the crosstalk to zero, the second term of each of Equations 9 and 10 is set to zero:

$$LP[S_2(k)M_2(k)D_1(k)] = 0 \quad (11)$$

and

$$LP[S_1(k)M_1(k)D_2(k)] = 0 \quad (12)$$

By setting the second terms to zero, Equations 9 and 10 reduce to:

$$\hat{S}_1(k) = LP[S_1(k)M_1(k)D_1(k)] \quad (13)$$

and

$$\hat{S}_2(k) = LP[S_2(k)M_2(k)D_2(k)] \quad (14)$$

One goal of the present invention is to select the demodulating signals $D_1(k)$ and $D_2(k)$ to satisfy Equations 11 and 12 to thereby reduce Equations 9 and 10 to Equations 13 and 14. This is accomplished by utilizing Equations 2 and 3 to simplify the two equations by selectively using components of

12

the two modulating signals $M_1(t)$ and $M_2(t)$ to generate the demodulating sequences $D_1(k)$ and $D_2(k)$.

In order to simplify the discussion, Equation 2 can be rewritten as:

$$M_1(t) = \sum_{n=1}^{\infty} E(n) \cos(n\omega t) \quad (15)$$

where $E(n)$ is the sin c envelope for the fundamental frequency f_0 ($n=1$) and the harmonics f_1 ($n=2$), f_2 ($n=3$), and so on, where $\cos(n\omega t)$ represents the cosine term $\cos(2\pi n t/T)$, where $\omega = 2\pi/T$. (Note, as discussed above, for discrete sampled signals, the actual envelope of $E(n)$ is a sin α /sin β function; however, for the frequencies of interest, the sine function is a suitable representation.)

As discussed above, the DC term ($n=0$) does not need to be considered because of the operation of the filter **198**, and the analog-to-digital converter **199**, as well as the action of the demodulation, which shift any unwanted DC or low frequency signals having a frequency less than approximately 10 Hz (hereinafter near-DC signals) to higher frequencies before lowpass filtering. As a further simplification, the magnitude of the fundamental term in Equation 15 is normalized to a value of 1 (i.e., $E(1)=1$). Note that the normalization results in the need for a scale factor, which will be discussed below. Thus, Equation 15 becomes:

$$M_1(t) = \cos \omega t + a \cos 2\omega t + b \cos 3\omega t + c \cos 4\omega t + \dots \quad (16)$$

The demodulation signal $D_1(t)$ is defined as:

$$D_1(t) = \cos \omega t + B \cos 2\omega t \quad (17)$$

For reasons set forth below, only the first two cosine terms are needed.

Similarly, the second modulating signal $M_2(t)$ becomes:

$$M_2(t) = -\cos \omega t + a \cos 2\omega t - b \cos 3\omega t + c \cos 4\omega t + \dots \quad (18)$$

and the second demodulating signal $D_2(t)$ is defined as:

$$D_2(t) = -\cos \omega t + B \cos 2\omega t \quad (19)$$

Note that the signs of the fundamental and odd harmonics in Equation 18 are 180° out of phase with the corresponding terms in Equation 16.

Note, as will be developed more fully below, by including only the fundamental s ($\cos \omega t$) and the first harmonic ($\cos 2\omega t$) in each of the demodulation signals, only the signals proximate to the fundamental and first harmonic need to be considered. By eliminating higher harmonics, the effects of the higher harmonics of the power line frequency are also eliminated in the output signals generated by the present invention.

Assume that the filter **198** and the analog-to-digital converter **199** do not affect the magnitude of the signal $MF(k)$ with respect to $M'(t)$ for the frequencies having significant energy. Therefore, starting with Equation 7 above, $M'(t)$ can be written as:

$$M'(t) = S_1(t)[\cos \omega t + a \cos 2\omega t + b \cos 3\omega t + \dots] + S_2(t)[- \cos \omega t + a \cos 2\omega t - b \cos 3\omega t + \dots] \quad (20)$$

When the first demodulating multiplier **210** multiplies $M(t)$ by $D_1(t)$, the terms on the right-hand side of Equation 20 are multiplied by the terms on the right-hand side of Equation 17. Thus:

$$M'(t)D_1(t) = \quad (21)$$

$$S_1(t)[\cos \omega t + a \cos 2\omega t + b \cos 3\omega t + \dots][\cos \omega t + B \cos 2\omega t] + \\ S_2(t)[- \cos \omega t + a \cos 2\omega t - b \cos 3\omega t + \dots][\cos \omega t + B \cos 2\omega t]$$

The term $S_1(t)[\cos \omega t + a \cos 2\omega t + b \cos 3\omega t + \dots][\cos \omega t + B \cos 2\omega t]$ is the signal term which is to be preserved, and the term $S_2(t)[- \cos \omega t + a \cos 2\omega t - b \cos 3\omega t + \dots][\cos \omega t + B \cos 2\omega t]$ is the crosstalk term to be eliminated.

Expanding the crosstalk term from Equation 21, generates:

$$\text{crosstalk} = S_2(t)[- \cos^2 \omega t - B \cos \omega t \cos 2\omega t + a \cos 2\omega t \cos \omega t + \\ aB \cos^2 2\omega t - b \cos 3\omega t \cos \omega t - bB \cos 3\omega t \cos 2\omega t + \dots] \quad (22)$$

Using the identity, $\cos(x)\cos(y) = \frac{1}{2}[\cos(x+y) + \cos(x-y)]$, the crosstalk term from Equation 22 becomes:

$$\text{crosstalk} = S_2(t)[-1/2(\cos 2\omega t + 1) + \\ ((a-B)/2)[\cos 3\omega t + \cos \omega t] + (aB/2)[\cos 4\omega t + 1] - \\ (b/2)[\cos 4\omega t + \cos 2\omega t] - (bB/2)[\cos 5\omega t + \cos \omega t] + \dots] \quad (23)$$

The remaining terms in Equation 23 will all have a factor of \cos or higher. Thus, Equation 23, when fully expanded only includes near-DC terms:

$$\text{crosstalk}_{DC} = LP[S_2(t)[aB/2 - 1/2]] \quad (24)$$

where $S_2(t)$ corresponds to the infrared portion of the original plethysmograph signal which has a bandwidth of interest of approximately 0 to 10 Hz. Any components present above 10 Hz will be eliminated by the action of the lowpass filter 220. Thus, it can be seen that only the signals of interest are folded back to DC or near-DC. By using the lowpass filter 220, the DC terms and near-DC terms can be isolated so that only the DC terms and near-DC terms of the crosstalk are presented at the output of the lowpass filter 220. Thus, in order to eliminate the crosstalk, the crosstalk terms in Equation 24 need to be set to zero:

$$LP[S_2(t)[aB/2 - 1/2]] = 0 \quad (25)$$

Thus:

$$B = 1/a \quad (26)$$

The result in Equation 26 can also be expressed using a geometric interpretation of vector projection (i.e., dot products) of $S_2(t)$ and $S_1(t)$ wherein the projection of $S_2(t)$ onto $D_1(t)$ is equal to zero and the projection of $S_2(t)$ onto $D_2(t)$ is maximized. In other words, express $S_1(t)$, $S_2(t)$, $D_1(t)$ and $D_2(t)$ as vectors of samples in an n-dimensional sample space (e.g., $S_1(t)$ is represented as a vector S_1 of samples $S_1(k)$). For example, in a preferred embodiment, $n=148$, and thus S_1 , S_2 , D_1 and D_2 are vectors of 148 samples each. The first crosstalk term is $S_1 \cdot D_2$. The second crosstalk term is $S_2 \cdot D_1$. The first signal output is $S_1 \cdot D_1$. The second signal output is $S_2 \cdot D_2$. Select the vectors D_1 and D_2 to drive the crosstalk terms to zero.

The relationship in Equation 26 also works to preserve the signal term. In particular, the signal term in Equation 21 can be expanded and lowpass filtered in the same manner as the crosstalk term to obtain:

$$\text{signal} = \hat{S}_1(t) = LP[S_1(t)[(aB/2) + 1/2]] \quad (27)$$

Using the relationship from Equation 26, then Equation 27 becomes:

$$\text{signal} = \hat{S}_1(t) = LP[S_1(t)[(a/2a) + 1/2]] = LP[S_1(t)] = S_1(t) \quad (28)$$

It can be readily shown that the same relationship holds for the crosstalk term and the signal term for the signal $S_2(t)$ by defining the second demodulation signal $D_2(t)$ as:

$$D_2(t) = -\cos \omega t + B \cos 2\omega t \quad (29)$$

and multiplying $M_2(t)$ by $D_2(t)$. After expanding the crosstalk and signal terms and eliminating the terms above 10 Hz, it can be shown that by selecting $B=1/a$, the crosstalk term is canceled and the signal term $S_2(t)$ is recovered.

From the foregoing, it can be seen that by choosing the relationship between the magnitude of B as the reciprocal of a , then the crosstalk terms are eliminated and the signal terms are preserved. Note that neither A nor B is an absolute value. As set forth in Equation 16, a is the magnitude of the $\cos 2\omega t$ term of $M_1(t)$ when the magnitude of the $\cos \omega t$ term of $M_1(t)$ is normalized to 1. Similarly, from Equation 17, B is the magnitude of the $\cos 2\omega t$ term of $D_1(t)$ when the $\cos \omega t$ term of $D_1(t)$ is normalized to 1.

It should be understood that both $D_1(t)$ and $D_2(t)$ can include higher harmonic terms; however, such additional terms could result in increased sensitivity to the noise of fluorescent lights and the like because of the harmonics of the 60 Hz power line frequency (or the 50 Hz power line frequency in other countries). For example, FIG. 5 illustrates an exemplary spectrum of the first and second harmonics of the present invention when the fundamental frequency is selected to be 316.7 Hz. Thus, the first harmonic frequency is 633.4 Hz. Note that the variations in the signals caused by blood flow throughout a cardiac cycle causes the fundamental and harmonics of modulation frequency to be surrounded by sidebands representing the frequency content of the plethysmograph. For example, in FIG. 5, the first and second harmonics are at 316.7 Hz and 633.4 Hz, ± 10 Hz.

As further illustrated in FIG. 5, the conventional 60 Hz power line frequency has harmonics at 120 Hz, 180 Hz, 240, etc. Thus, the nearest harmonics of the power line frequency to the first harmonic of the present invention are at 300 Hz and 360 Hz, and the nearest harmonics of the power line frequency to the second harmonic of the present invention are 600 Hz and 660 Hz. Similarly, if used in a country having a 50 Hz power line frequency, the nearest harmonics to the first harmonic of the present invention are 300 Hz and 350 Hz, and the nearest harmonics to the second harmonic of the present invention are 600 Hz and 650 Hz. Even if the power frequency were to vary by up to 1.5 percent, the noise generated by the ambient light from fluorescent lamps, or the like, would not be at the first and second harmonic frequencies of the present invention. The fundamental frequency has thus been selected to avoid power line caused ambient noise at the first and second harmonic frequencies.

The foregoing discussion assumed that the filter 198 did not significantly affect the amplitude of the filtered signal. If the filter 198 does have an effect on the amplitude, then B will be a constant times the value of B determined above:

$$B = k/a \quad (30)$$

where k depends on the relative attenuation of the first harmonic and the second harmonic through the filter 198.

Although the value of the coefficient B can be calculated as set forth above, the calculations may be complicated if the filter 198 or the modulators 190, 192 introduce phase changes which cause the calculations to be performed on complex numbers. For example, if the modulation signals $M_1(t)$ and

$M_2(t)$ are not rectangular waves which have 25% duty cycles and which are precisely 180° out of phase, as illustrated herein, then the coefficients of the frequency components of the modulation signals may be complex to account for the phase relationships, and thus, the coefficients of the demodulation signals may be complex.

As illustrated in FIG. 6, the value of B can also be determined empirically by performing a initial measurement with one channel (i.e., either the red pulse or the infrared pulse turned off) and minimizing the crosstalk. In particular, during the initial measurement, the waveform **140** in FIG. 2 is set to a continuous zero value so that no infrared pulses are generated. Thus, the detector **150** (FIG. 1) receives only the light generated by the red LED **106**. Thus, $M_2(t)$ is set to zero, and Equation 10 for $\hat{S}_2(t)$ becomes:

$$\hat{S}_2(t) = LP[S_1(t)M_1(t)D_2(t)] \quad (31)$$

It can be seen that $\hat{S}_2(t)$ includes only a crosstalk portion, which can be measured on the output from the second low-pass filter **222**. Thus, by varying the value B while monitoring the magnitude or the RMS (root-mean-squared) value of the output signal $\hat{S}_2(t)$, a minimum magnitude $\hat{S}_2(t)_{min}$, for the output signal $\hat{S}_2(t)$ can be found which corresponds to the best value B_{BEST} for B. In an ideal system, the best value for B corresponds to a zero value for the output signal $\hat{S}_2(t)$; however, in a real environment, the best value of B may correspond to a non-zero value for $\hat{S}_2(t)$ (i.e., a minimum error for $\hat{S}_2(t)$). It should be understood that the value of B_{BEST} can also be determined by turning off the red LED **106** and varying B while monitoring $\hat{S}_1(t)$ until $\hat{S}_1(t)$ is minimized.

From the foregoing, it can be seen that the effect of the modulation signals $D_1(t)$ and $D_2(t)$ is to shift the DC or near-DC noise terms up in frequency while shifting the signals of interest at the harmonics back to DC or near-DC, which in effect interchanges the noise spectra and the signal spectra so that the noise spectra can be eliminated by the action of the lowpass filters **220**, **222**, leaving only the signals of interest.

FIG. 7 illustrates a preferred embodiment of the present invention which implements the functions described above in a digital system. Preferably, the digital system comprises a digital signal processor (not shown), and the blocks described herein comprise data structures within the digital signal processor and software routines that implement the processes described below. In particular, the present invention comprises an LED demodulation block **300** which receives a digital configuration signal on a bus **310**, a clock signal on a line **312** and a digital detector signal on a bus **314** as inputs. The digital configuration signal bus **310** provides a way to change the configuration of the LED demodulation block **300** to accommodate different LEDs and different detection algorithms. Preferably, the clock signal on the line **312** is a 46,875 Hz (46.875 kHz) square wave signal which is used to synchronize the timing functions of the present invention. The digital detector signal on the line **314** is the output of the analog-to-digital converter **199**. The analog-to-digital converter **199** is connected to the output of the detector **150** (via the amplifier **197** and the filter **198**) and samples the output of the detector **150** at 46,875 samples per second to provide a stream of sampled digital values of the red light and infrared light incident on the detector **150**.

The LED modulation block **300** generates a demodulated red signal output on a bus **340** and generates a demodulated infrared signal output on a bus **342**. The demodulated red signal output is passed through the low pass filter **220** and is output therefrom as the signal $\hat{S}_1(t)$. The demodulated infrared signal output is passed through the low pass filter **222** and

is output therefrom as the signal $\hat{S}_2(t)$. As further illustrated in FIG. 8, the LED demodulation block **300** comprises a modulo-M block **350**, an LED demodulation state table block **352**, the first demodulating multiplier **210** and the second demodulating multiplier **212**.

The modulo-M block **350** receives the main 46,875 Hz clock signal on the line **312** as one input and receives a MODULUS signal on a bus **354** as a second input. The bus **354** forms a portion of the configuration bus **310**. The modulo-M block **350** divides the clock signal by the MODULUS signal and generates a RESIDUE signal (described below) on a bus **356** which is provided as one input to the LED modulation state table block **352**. The LED modulation state table block **352** also receives the configuration signals on the configuration bus **310**.

The LED demodulation state table is responsive to the residue signal and the configuration signals to generate the first demodulating signal $D_1(t)$ on a bus **360** and to generate the second demodulating signal $D_2(t)$ on a bus **362**. The first demodulating signal $D_1(t)$ is provided as one input to the first demodulating multiplier **210**, as described above. The second demodulating signal $D_2(t)$ is provided as one input to the second demodulating multiplier **212**, as described above. The first demodulating multiplier **210** and the second demodulating multiplier **212** receive the digital detector signal on the line **314** as respective second inputs. The demodulating multipliers **210**, **212** multiply the digital detector signal by the first demodulating signal $D_1(t)$ and the second demodulating signal $D_2(t)$, respectively, to generate a demodulated red signal and a demodulated infrared signal on the buses **340** and **342**, respectively. Because the outputs of the two demodulating multipliers **210** and **212** include the terms $\cos \omega t$, $\cos 2\omega t$, and higher, the demodulated signals on the buses **340** and **342** are provided as respective inputs to the low pass filters **220** and **222** to pass only the near-DC terms, as discussed above. The outputs of the lowpass filters **220** and **222** on the buses **344** and **346**, respectively, are the $\hat{S}_1(t)$ signal and the $\hat{S}_2(t)$ signal which contain only the near-DC terms, which, in accordance with the discussion presented above represent the original input signals $S_1(t)$ and $S_2(t)$ with the unwanted noise substantially reduced or eliminated. The two signals $\hat{S}_1(t)$ and $\hat{S}_2(t)$ are then applied to computation circuitry (not shown) which computes the blood oxygen saturation and other cardiographic parameters in a manner described in the above-cited U.S. Pat. Nos. 5,482,036 and 5,490,505.

The residue signal generated as the output from the modulo-M block **350** is a multiple bit signal that counts from 0 to MODULUS-1. In the preferred embodiment described herein, MODULUS has a value of 148. Thus, the RESIDUE output of the modulo-M block **350** counts from 0 to 147. The RESIDUE output of the modulo-M block **350** is a number that is provided as the input to the LED demodulation state table block **352**. As illustrated in FIG. 9, the RESIDUE output on the bus **356** corresponds to the signal **180** in FIG. 1 and is also provided to the input of an LED modulation state table block **370** which, together with an LED driver circuit **372**, comprise the modulation block **104** (FIG. 1) which generates the drive signals to the red LED **106** and the infrared LED **108**. As described above, the red LED **106** and the infrared LED **108** generate the modulation signals $M_1(t)$ and $M_2(t)$, respectively, which effectively operate as carriers for the plethysmograph waveform to be measured. In particular, as illustrated by a red drive timing waveform **374** and by an infrared drive timing waveform **376** in FIG. 10, the modulation state table block **370** generates a red signal pulse **378** during the time when the RESIDUE signal increments from 0 to 36. Then, the modulation state table block **370** generates neither

a red signal pulse nor an infrared signal pulse during the time when the RESIDUE signal increments from 37 to 73. Then, the modulation state table block 370 generates the infrared signal pulse 380 during the time when the RESIDUE signal increments from 74 to 110. Then, the modulation state table block 370 again generates neither a red signal pulse nor an infrared signal pulse during the time when the RESIDUE signal, increments from 111 to 147. The RESIDUE signal then resets to 0 and the process repeats continuously.

The red signal pulse 378 and the infrared signal pulse 380 from the modulation state table block 370 are provided as inputs to the LED driver circuit 372 which turns on the red LED 106 when the red signal pulse 376 is active and turns on the infrared LED 108 when the infrared signal pulse 378 is active by generating the current waveform 120 illustrated in FIG. 2. The circuitry for converting the red signal pulse 376 and the infrared signal pulse 378 to the bi-directional current pulses of the waveform 120 is conventional and does not need to be described herein.

In the preferred embodiment, the LED demodulation state table block 352 implements demodulation equations which generally correspond to the Equations 17 and 19 described above. In particular, the LED demodulation state table block 352 receives the RESIDUE as one input to the state table and steps through the state table based upon the current value of the RESIDUE. The LED demodulation state table block 352 generates two output values for each value of the RESIDUE, wherein the first output value is the first demodulation signal $D_1(t)$ on the signal bus 360, and the second output value is the second demodulation signal $D_2(t)$ on the signal bus 362.

In particular, the LED demodulation state table block 352 implements the following forms of the demodulation signal $D_1(t)$ and the $D_2(t)$ equations:

$$D_1(t) = -SCL \left(\cos \left[2\pi t \left(\frac{R - 18.5 - HWD}{\text{Modulus}} \right) \right] + HWD \left(\cos \left[4\pi t \left(\frac{R - 185.5 - HWD}{\text{Modulus}} \right) \right] \right) \right) \quad (32)$$

and

$$D_2(t) = -SCL \left(\cos \left[2\pi t \left(\frac{R - 18.5 - HWD}{\text{Modulus}} \right) \right] - HWD \left(\cos \left[4\pi t \left(\frac{R - 185.5 - HWD}{\text{Modulus}} \right) \right] \right) \right) \quad (33)$$

In Equations 32 and 33, the value SCL is a scale factor which determines the magnitudes of the two demodulation signals and which is used to compensate for the normalization discussed above and to compensate for other factors; such as, for example, non-ideal rectangular pulses. The method of determining the scale factor will be set forth below. In one particularly preferred embodiment, the value of SCL is 2.221441469. The value HWD is a hardware distortion factor, which corresponds to the value of B discussed above. The determination of the value B was described above, and will be described again below in connection with this preferred embodiment. In one particularly preferred embodiment where the pulses applied to the red LED 106 and the infrared LED 108 are idealized rectangular waves having 25% duty cycles, the value of HWD can be calculated to be 1.414213562. This ideal value for HWD can be determined by recognizing that the value of the coefficient A for the $\cos 2\omega t$ terms in Equations 16 and 18 is determined by the sine function. When the coefficient of the $\cos \omega t$ term is normalized to 1, as in the two equations, then the value of the

coefficient a is equal to $\sqrt{2/2}$. Thus, the ideal value for B (i.e., HWD) is $\sqrt{2}$. Of course, the actual value of the coefficient B, and thus HWD, will vary when the red pulses and the infrared pulses are not true rectangular waves. Since, in actual embodiments, the pulses will have finite rise times and fall times, the optimum value of HWD is preferably found empirically in the manner described below.

The value 18.5 in Equations 32 and 33 is used to align the demodulation waveforms with the modulation waveforms so that the peak of the cosine functions corresponds to the mid-points of each of the modulation waveforms. The value HWD is a hardware delay factor which may be needed in certain embodiments to compensate for delays in the analog processing, the digital processing or both, which cause the demodulation signals $D_1(t)$ and $D_2(t)$ to be out of phase with the modulation signals $M_1(t)$ and $M_2(t)$. In an ideal environment, the value of the hardware delay factor is 0. However, in one particularly preferred embodiment, the value of the hardware delay factor is 39. The modulus was described above and is basically the number of steps in each period of the waveforms. In the embodiment described herein, the modulus is 148. The value R is the RESIDUE, which varies from 0 to modulus-1, and thus, in the preferred embodiment, R varies from 0 to 147.

In operation, the clock signal on the line 312 causes the modulo-M block 350 to generate the RESIDUE signal, as described above. The RESIDUE value is applied to the LED modulation block 104 which generates the modulation signals $M_1(t)$ and $M_2(t)$, as described above. The RESIDUE value is also applied to the LED demodulation state table block 352 which generates a new value for $D_1(t)$ and a new value for $D_2(t)$ for each new RESIDUE value. Thus, 148 values of $D_1(t)$ and $D_2(t)$ are generated for each complete cycle. Because the clock signal is operating at 46,875 Hz, the modulation signals $M_1(t)$ and $M_2(t)$ and the demodulation signals $D_1(t)$ and $D_2(t)$ have a fundamental frequency of 316.722973 Hz, which, as discussed above, does not correspond to any harmonic of conventional 50 Hz or 60 Hz power line frequencies.

The HWD (hardware delay factor) value, the HWD (hardware distortion factor) value and the SCL (scaling factor) value are found empirically as follows. First, the ideal values of the hardware delay factor, the hardware distortion factor and the scale factor are applied to the Equations 32 and 33 in the LED demodulation state table block 352 (i.e., $HWD=0$, $HWD=1.414213562$, and $SCL=2.221441469$). To determine the optimum value of the hardware delay factor, the second modulation signal $M_2(t)$ is set to a constant value of zero (i.e., the infrared LED is maintained in its OFF state). The red LED pulses are applied as set forth above, and the digital detector output signal from the analog-to-digital converter is monitored and compared to the modulation signal $M_1(t)$. The relative delay between the beginning of the modulation signal $M_1(t)$ and the detection of the beginning of the responsive output from the analog-to-digital converter is the optimum hardware delay factor (HWD) value. In one exemplary embodiment, the optimum value of the hardware delay factor is 39.

After determining the value of the hardware delay factor and applying it to Equations 32 and 33, the ideal value of the hardware distortion factor and the ideal value of the scale factor are applied to the two equations. Again, with the red LED pulses applied to the red LED 106 and no pulses applied to the infrared LED, the value of the hardware distortion factor is slowly varied from its ideal value while the DC component of the demodulated infrared signal output on the line 342 is monitored. The value of the hardware distortion

factor is varied until the measured DC component is minimized, and the value of the hardware distortion factor corresponding to the minimal DC component is selected as the optimum value for the hardware distortion factor.

Next, with the value of the hardware delay factor and the value of the hardware distortion factor set to their respective optimum values, as determined above, the value of the scale factor (SCL) is initially set to 1. Again, with the modulation system generating pulses only to the red LED 106, the DC component of the demodulated red signal output on the line 340 is measured. In addition, the difference in amplitude between the on state and the off state of the digital detector signal from the filter 198 is measured. The ratio of the measured amplitude difference to the measured DC component of the demodulated red signal output is selected as the optimum value for the scale factor.

An exemplary demodulation waveform $D_1(t)$ is illustrated by a waveform 400 in FIG. 11 and an exemplary demodulation waveform $D_2(t)$ is illustrated by a waveform 402 in FIG. 11. The demodulation waveforms in FIG. 11 are illustrated with the hardware delay factor set to 0 in order to align the waveforms with the modulation waveforms in FIG. 10. It should be understood that when the hardware delay factor is non-zero, the demodulation waveforms in FIG. 11 will be shifted in phase with respect to the modulation waveforms in FIG. 10.

Although described above in connection with the variation of the amplitude of the first harmonic component of the demodulation signals in order to minimize the crosstalk, it should be understood that the relative amplitude of the second harmonic component of the demodulation signals with respect to the amplitude of the fundamental component of the demodulation signals is determined by the relationship of the amplitude of the first harmonic component of the modulation signals to the amplitude of the fundamental component of the modulation signals. The relationship of the amplitude of the first harmonic component of the modulation signals depends in part upon the duty cycles of the modulation signals. If the modulation duty cycles are varied, the amplitude of the first harmonic component of the modulation signals changes. Thus, the crosstalk may also be minimized by holding the amplitudes of the components of the demodulation signals constant while varying the duty cycles of the modulation signals. One skilled in the art will appreciate that other variations in the modulation and demodulation signals may also be used to minimize the crosstalk between the two output signals.

A plurality of signals $S_1, S_2, S_3 \dots S_n$ can be demodulated and the crosstalk between signals reduced to a minimum by application of the foregoing invention to more than two signals.

Additional information can advantageously be derived from the digitized detection signal on the bus 314 and can be used to provide indications regarding the reliability of the demodulated signals generated as described above. In particular, although the present system is capable of demodulating the $\hat{S}_1(t)$ signal and the $\hat{S}_2(t)$ signal in the presence of significant ambient noise from light and other sources, it is possible that the level of the ambient noise is sufficiently high to affect the demodulated signals. FIGS. 12 and 13 illustrate a time domain method and system for determining the ambient noise level, and FIGS. 14 and 15 illustrate a frequency domain method and system for determining the ambient noise level.

As illustrated in FIG. 12, the digital detection signal 152 is sampled by a sample signal represented by a waveform 500, which comprises a plurality of sampling pulses 502. The

sampling pulses 502 are timed to occur during the intervals between the red pulses 134, 136 and the infrared pulses 142, 144 when no red light and no infrared light should be detected by the detector 150 (FIG. 1). Thus, any energy detected during the sample intervals is primarily caused by ambient light and other noise sources. As illustrated, the sampling pulses 502 preferably occur at the approximate midpoint of each interval between the red and infrared pulses.

As illustrated in FIG. 13, the digital detection signal bus 314 is provided as an input to a time domain sampler 520. The time domain sampler 520 also receives the RESIDUE signal on the bus 356 as a second input. The time domain sampler is responsive to the RESIDUE signal to sample the digital detection signal at times when the value of the RESIDUE signal corresponds to the quiescent times of the red pulses 134, 136 and the infrared pulses 142, 144. As described above, the red pulses 134, 136 are generated when the RESIDUE signal has values between 0 and 36, and the infrared pulses are generated when the RESIDUE signal has values between 74 and 110. Thus, assuming no hardware delay, the sampling pulses 502 are preferably generated, for example, when the RESIDUE signal has a value of 55 and when the RESIDUE signal has a value of 129, which positions the sampling pulses at the approximate midpoints of the quiescent intervals between the pulses. As discussed above, the actual system has a hardware delay caused by processing times. Thus, if the system has a hardware delay factor of, for example, 39, the sampling pulses 502 are shifted in time to occur when the RESIDUE signal has a value of 94 and a value of 20 (168 modulo 14 g). The sample times used by the time domain sampler 520 are advantageously determined by configuration signals received via the digital configuration bus 310, described above. For example, the time domain sampler 520 can be initially set to sample at RESIDUE signal values of 55 and 129, and the value of the hardware delay value factor (HWA) communicated by the digital configuration bus 310 is added to both values to shift the sample to the correct sample interval.

As illustrated in FIG. 14, a detection signal spectra 550 includes the two frequency components corresponding to the fundamental and first harmonic of the modulation signal at 316.7 Hz and 633.4 Hz, respectively. The spectra 550 further includes the fundamental and multiple harmonics of the 60 Hz power line frequency. In addition, the spectra 550 includes noise at a multitude of frequencies which may be caused by various sources. One particularly troublesome source of noise encountered in pulse oximetry systems is an electrocauterization device, which uses a high frequency electrical current to make surgical incisions and to cauterize the surrounding blood vessels at the same time. Although primarily high frequency noise sources, such devices also generate significant noise at lower frequencies because of arcing. When an electrocauterization device is operated close to a pulse oximeter detector, the noise generated by the device can overwhelm the signals generated by the pulse oximetry detector. In other words, the noise floor can be greater than the detectable signal from the pulse oximetry detector.

It is desirable to detect when the noise floor is too high so that the pulse oximetry system can indicate that the demodulated signals may not be reliable. In order to determine the level of the noise floor, the present invention samples the spectra 550 to determine the content of the frequency components detected at frequencies other than the fundamental and harmonic frequencies of the modulation signals. In particular, as illustrated by a sample control signal 560 in FIG. 14, the portions of the spectra 550 which do not include the fundamental and harmonics of the modulation signal are

sampled. Thus, in the preferred embodiment, the magnitudes of the spectra at 316.7 Hz, 633.4 Hz, 950.1 Hz, etc., are not sampled. Furthermore, because a band of frequencies around the fundamental and harmonics of the modulation signal also include significant information caused by the modulation of the red pulses and the infrared pulses by the changes in blood flow during each cardiac cycle. Thus, as illustrated in FIG. 14, in the preferred embodiment, a band of frequencies surrounding the fundamental and harmonic frequencies of the modulation signals (i.e., the sidebands discussed above) are not included in the samples. For example, a band of at least ± 10 Hz around each of the fundamental and harmonic frequencies is not included in the samples.

The intensities at the sampled frequencies are averaged, and an output signal is generated which represents the average intensity of the noise signals. Other portions (not shown) of the digital processing system advantageously monitor the average intensity of the noise signals, and, if the average intensity exceeds a selected threshold based upon the size of the measured plethysmograph, then the demodulated output signals from the system are considered as being unreliable and should not be used.

FIG. 15 illustrates a preferred embodiment of a system that determines the noise floor, as described above. The system of FIG. 15 includes a Fast Fourier Transform block 600 which receives a plurality of samples from the digitized detector bus 314 and generates a transformed output on a bus 610. The transformed output on the bus 610 represents the spectra of the samples. In the preferred embodiment, a sufficient number of samples are taken to represent approximately 44 milliseconds of data so that at least two cycles of the 60 Hz power are included within the samples. For example, approximately 1,024 samples can be taken during the 44-millisecond interval at a sample rate of approximately 23.4 kHz (e.g., one-half the system timing rate). The spectra for a 44-millisecond interval are provided as inputs to a spectral sampler 620 which eliminates the samples in the ± 10 Hz bands around the fundamental and harmonic frequencies of the modulation signals. The output of the spectral sampler 620 is provided on a bus 630 and is thereby provided as an input to an averager 640. The averager 640 averages the sampled noise (spectra which it receives and provides an averaged output on a bus 650. The averaged output on the bus 650 represents the noise floor and is provided to other portions of the digital processing system where it is compared to the selected threshold to determine whether the noise floor is excessive. The threshold is not necessarily fixed, but is dependent on the strength of the plethysmograph, which in turn depends upon the perfusion of blood in the body portion being measured.

The embodiment of FIG. 15 can also advantageously be used to determine whether the ambient noise is primarily at 60 Hz, corresponding to power line frequencies in the United States and Canada, or at 50 Hz, corresponding to power line frequencies in Europe. The foregoing modulation frequency of 316.7 Hz is selected to avoid the harmonics of the 60 Hz power line frequency as well as the 50 Hz power line frequency. If a significant shift in the power line frequency is detected such that aliasing of the ambient noise occurs at the frequencies of interest, then the modulation frequency can be changed to displace the modulation harmonics farther from the harmonics of the power line frequency, such as, for example, by changing the 46,875 Hz sampling frequency, or by changing the modulus.

Pre-Demodulation Decimation

For convenience, the previous embodiments do not show the signal MF(k) being decimated before demodulation. However, as discussed in more detail below, the signal MF(k)

can advantageously be decimated prior to demodulation. The pre-demodulation decimation technique can reduce the computational burden required to perform the demodulation operations, primarily because the decimated sample rate is lower than the original (undecimated) sample rate. Computation can also be reduced because, as will be seen, the numerical sequences used in the demodulator are, in some circumstances, shorter than the sequences given in Equations 32 and 33. Pre-demodulation decimation is a generalization of the previous embodiments and reduces to the previous embodiments when the pre-demodulation decimation rate is one.

FIG. 16 is a pictorial representation of a system that incorporates pre-demodulation filtering and decimation. FIG. 16 is similar to FIG. 3, and like numbers refer to like elements in the two figures. FIG. 16 shows the first modulator 191 having a signal input $S_1(t)$ and a modulation input $M_1(t)$. The second modulator 193 has a signal input $S_2(t)$ and a modulation input $M_2(t)$. The pair of signals $S_1(t)$ and $S_2(t)$ represent the effect of the time-varying volume and scattering components of the blood in a finger (or other body part) on the red light and the infrared light, respectively, passing through the finger. The red light signal portion $S_1(t)$ is caused by the variable attenuation of the red light passing through the finger 102 (shown in FIG. 1). The infrared light signal portion $S_2(t)$ is caused by the variable attenuation of the infrared light passing through the finger 102. The outputs of the first and second modulators 191, 193 are provided to the receiving photodetector 150. The photodetector 150 is modeled as an adder 194 and an adder 196. The outputs of the first and second modulators 191, 193 are provided to the adder 194 to generate a composite signal M(t) where:

$$M(t) = S_1(t)M_1(t) + S_2(t)M_2(t). \quad (34)$$

The output signal M(t) from the adder 194 is provided to an adder 196 where a signal n(t) is added to the signal M(t). The signal n(t) represents a composite noise signal caused by ambient light (including DC and harmonics of the power line frequency), electromagnetic pickup, and the like, which are also detected by the photodetector 150. In addition, the signal n(t) may also include noise at higher frequencies caused, for example, by other devices such as electrocauterization equipment, or the like. The output of the adder 196 is a signal M'(t) = M(t) + n(t) which includes noise components as well as the signal components.

The M'(t) signal output of the adder 196 (i.e., the output of the detector 150) is applied to the input of a signal processing block 1600. Within the signal processing block 1600, the signal M'(t) is first passed through the amplifier 197 and then through the analog bandpass filter 198. The analog bandpass filter 198 provides anti-aliasing and removal of low frequency noise and DC. The filter 198 has a passband selected to pass signals in the preferred range of 20 Hz to 10,000 Hz. The analog bandpass filter 198 removes a significant portion of the noise below 20 Hz. The signal components responsive to the blood oxygen saturation are frequency shifted by the operation of the two modulation signals $M_1(t)$ and $M_2(t)$ and are passed by the analog bandpass filter 198.

In one embodiment, the output of the analog bandpass filter 198 is sampled by the analog-to-digital converter 199 and converted therein to digital signals. In one embodiment, the signals are sampled at 46,875 samples per second. The digital signals from the analog-to-digital converter 199 are provided as inputs to a lowpass digital filter 1620. Output signals from the digital filter 1620 are provided to a sample rate compression block 1622 that reduces (compresses) the sample rate by a decimation rate R_1 . The lowpass digital filter 1620 and

sample rate compressor **1622** together comprise a decimator **1621** (decimation comprises lowpass filtering followed by sample rate compression). The digital filter **1620** provides anti-aliasing filtering and the sample rate compression block **1622** preferably operates at a sampling rate of at least twice the highest frequency of interest as determined by the digital filter **1.620**. In one embodiment, the sample rate compression block **1622** reduces the sample rate by a factor of $R_1=37$, corresponding to the number of samples during the period τ as illustrated in FIG. 10. The output of the sample rate compression block **1622** provides one sample per time period τ and thus four samples per time period T . The output of the sample rate compression block **1622** is a signal $MF(k)$ (where k is a discrete index) which comprises approximately 1,266 samples per second.

The signal $MF(k)$ is provided as a first input to a first mixer **1624**. The signal $MF(k)$ is also provided as a first input to a second mixer **1626**. A first demodulating signal $D_1(k)$ is provided as a second input to the first mixer **1624**, and a second demodulating signal $D_2(k)$ is provided as a second input to the second mixer **1626**. The output of the first mixer **1624** is provided as an input to a first lowpass filter **1630**, and the output of the second mixer is provided as an input to a second lowpass filter **1640**. The bandwidths of the lowpass filters **1630**, **1640** are preferably approximately 10 Hz. The signal $MF(k)$ is also provided as a first input to a noise channel mixer **1628**. A noise demodulating signal $D_0(k)$ is provided as a second input to the noise channel mixer **1628**. The output of the low pass filter **1650** is provided to a sample rate compression block **1652**. The output of the sample rate compression block **1652** is an estimate of the noise $n(t)$. The output of the lowpass filters **1630** is provided to an input of a sample rate compressor **1632** and the output of the lowpass filter **1640** is provided to an input of a sample rate compressor **1642**. The lowpass filter **1630** and the sample rate compressor **1632** together comprise a decimator **1631**. The lowpass filter **1640** and the sample rate compressor **1642** together comprise a decimator **1641**.

The output of the decimator **1631** is a signal $\hat{S}_1(k)$, which, as discussed below, is an estimate of the signal $S_1(k)$. The output of the decimator **1641** is a signal $\hat{S}_2(k)$, which, as discussed below, is an estimate of the signal $S_2(k)$. As will be shown below, the selection of the first demodulating signal $D_1(k)$ and the second demodulating signal $D_2(k)$ in accordance with the present invention can reduce or eliminate the effects of noise in the two output signals $\hat{S}_1(k)$ and $\hat{S}_2(k)$ and also reduce or eliminate crosstalk between the two signals.

The decimators **1632**, **1642** decimate by a decimation rate R_2 . In a preferred embodiment, the decimators **1632**, **1642** decimate by a decimation rate $R_2=20$ to a sample rate of, for example, 63.3 Hz to provide a decimated output which can be further processed in accordance with the methods and apparatuses described in the above-referenced patents. The decimations which occur in the decimators **1632**, **1642** reduce the rate at which the output signals $\hat{S}_1(k)$ and $\hat{S}_2(k)$ need to be processed while maintaining the sample rate well above the 10 Hz frequency content of the signals of interest. The outputs of the decimators **1632**, **1642** are provided on respective output lines **1634** and **1644**.

Decimating the signal $MF(k)$ prior to demodulation, although not an approximation technique, can be simplified by assuming that each desired signal $S_1(t)$ does not change appreciably during each period τ . In many applications it is reasonable to assume that the desired signals $S_1(t)$ and $S_2(t)$ will not change significantly during the time interval τ shown in FIG. 2. One skilled in the art will recognize that a sufficient condition for this assumption is that the highest significant

frequency components in $S_1(t)$ and $S_2(t)$ are much lower than the modulation frequency. In the pulse-oximetry application the highest frequency of interest is typically around 10 Hz, which is far below the 316.7 Hz fundamental of the modulation. Since $n(t)$ is not a desired signal, no such assumption is necessary for $n(t)$. Thus, while $n(t)$ may vary erratically over a modulation cycle, the signals $S_1(t)$ and $S_2(t)$ do not. Therefore, it is possible to perform pre-demodulation decimation that has little effect on $S_1(t)$ and $S_2(t)$ but may shape $n(t)$ into $n'(t)$. The measured signal is decimated by a factor $R_1=Q$ (where Q is the number of samples in a time period τ) and then demodulated.

Assuming $R_1=Q$, then the spectral domain representation of the signal $MF(k)$ at the output of the sample rate compression block **1622** is given by (approximately):

$$MF(f) = \quad (35)$$

$$\frac{1}{T} \sum_{n=-\infty}^{\infty} \left[S_1\left(f - \frac{n}{T}\right) + (-1)^n S_2\left(f - \frac{n}{T}\right) \right] + \frac{4}{T} \sum_{m=-\infty}^{\infty} n'\left(f - \frac{4m}{T}\right)$$

Since the sample rate compression block **1622** decimates at the same rate as the number of samples per period τ , the decimation removes any τ dependence in the expression for $MF(f)$. The frequency components indexed by m increase four times faster than the frequency components indexed by n . This occurs because the modulated signals $S_1(t)$ and $S_2(t)$, which are indexed by n , occur in only one fourth of the samples, but the noise $n(t)$, which is indexed by m , occurs in every sample.

The demodulation operation can be performed either in the frequency or the time domain. A method for frequency domain demodulation of the signal $MF(k)$ can be obtained by rewriting Equation 35 as:

$$MF(f) = \dots MF_{-2}(f) + MF_{-1}(f) + MF_0(f) + MF_1(f) + MF_2(f) + \dots \quad (36)$$

where

$$MF_{-2}(f) = [S_1(f) + S_2(f)]/T$$

$$MF_{-1}(f) = [S_1(f) - S_2(f)]/T$$

$$MF_0(f) = [S_1(f) + S_2(f) + S_2(f) + 4n'(f)]/T$$

$$MF_1(f) = [S_1(f) - S_2(f)]/T$$

$$MF_2(f) = [S_1(f) - S_2(f)]/T$$

$$MF_3(f) = [S_1(f) - S_2(f)]/T$$

$$MF_4(f) = [S_1(f) + S_2(f) + S_2(f) + 4n'(f)]/T \quad (37)$$

Where $n'(k)$ is the decimated noise signal $n(t)$. Estimates for the signal $S_1(f)$ can be obtained by shifting the spectra of $MF_1(f)$ and $MF_2(f)$ by $-1/T$ and $-2/T$, respectively, and then dividing the sum of the resultant by 2. Likewise, $S_2(f)$ can be obtained by dividing the difference of the resultant spectra by 2. In other words:

$$\hat{S}_1(f) = MF_1(f-1/T) + MF_2(f-2/T)$$

$$\hat{S}_2(f) = MF_1(f-1/T) - MF_2(f-2/T) \quad (38)$$

emodulation in the time domain is a more elegant method for obtaining $S_1(k)$ and $S_2(k)$. Time domain demodulation is obtained by using the frequency shift property of the Fourier transform given by:

$$F(\omega + \omega_0) \Leftrightarrow e^{-j\omega_0 t} f(t) \quad (39)$$

According to Equation 39, the frequency domain terms $MF_1(f)$ are related by a time shift in the time domain and this property can be used to generate the demodulation sequences D_0 - D_2 . A more complete development of this process (for the general case of N channels) is provided in Equations 42-50 below and in the text accompanying those equations. For the present case, where $N=2$, using equations 42-50 gives:

$$\begin{aligned} D_0(k) &= 0, 1, 0, 1, \dots \\ D_1(k) &= 1, -0.5, 0, -0.5, \dots \\ D_2(k) &= 0, -0.5, 1, -0.5, \dots \end{aligned} \quad (40)$$

The sequences shown in Equation 40 are repeating sequences of the four values shown. Thus, the demodulation waveforms are no more than short repeating sequences of simple coefficients. Since the samples $MF(k)$ are time domain sequences, demodulation simply involves multiplying the samples $MF(k)$ by the sequences in Equation 40. For example, the sequence of coefficients $D_0(k) = (0, 1, 0, 1, \dots)$ is provided to the multiplier **1628** to demodulate the signal $MF(k)$ and produce the estimate of $n(k)$. Similarly, the sequence of coefficients $D_1(k) = (1, -0.5, 0, -0.5, \dots)$ is provided to the multiplier **1624** to demodulate the signal $MF(k)$ and produce the estimate of $S_1(k)$.

Multiple Channel Modulation and Demodulation

The two-channel pre-demodulation decimation technique described in the previous section can be extended to multi-channel systems having more than two desired signals. FIG. 17 illustrates an expansion of the two-channel modulator into a multi-channel modulator/demodulator. FIG. 17 shows the first modulator **191** and the second modulator **193** as shown in FIG. 16. Further, FIG. 17 shows a third modulator **1701** and an N^{th} modulator **1702**. The signal input $S_1(t)$ and a modulation input $M_1(t)$ are provided to the first modulator **191**. The signal input $S_2(t)$ and a modulation input $M_2(t)$ are provided to the second modulator **193**. A signal input $S_3(t)$ and a modulation input $M_3(t)$ are provided to the third modulator **1701**. A signal input $S_N(t)$ and a modulation input $M_N(t)$ are provided to the N^{th} modulator **1702**.

The photodetector **150** is modeled as an adder **194** and an adder **196**. The outputs of the modulators **191**, **193**, **1701**, and **1703** are added together in the adder **194**, to generate a composite signal $M(t)$ where:

$$M(t) = S_1(t)M_1(t) + S_2(t)M_2(t) + S_3(t)M_3(t) + \dots + S_N(t)M_N(t) \quad (41)$$

The signal $M(t)$ from the adder **194** is provided to the adder **196** where the signal $M(t)$ is added to the signal $n(t)$ which represents a composite noise signal caused by ambient light, electromagnetic pickup, and the like, which are also detected by the photodetector **150**. The output of the adder **196** is the signal $M'(t) = M(t) + n(t)$, which includes the noise components as well as the signal components.

The $M'(t)$ signal output of the adder **196** (i.e., the output of the detector **150**) is applied to the input of the signal-processing block **1700**. Within the signal-processing block **1700**, the signal $M'(t)$ is first passed through an amplifier **197** and then through the analog bandpass filter **198**. The analog bandpass filter **198** provides anti-aliasing and removal of low frequency noise and DC. The desired signal components in the signals $S_1(t)$ are frequency shifted by the operation of the modulation signals $M_1(t)$ and are passed by the analog bandpass filter **198**.

The output of the analog bandpass filter **198** is sampled by the analog-to-digital converter **199** and converted therein to digital signals and provided to an input of the lowpass digital filter **1620**. Output signals from the digital filter **1620** are

provided to a sample rate compression block **1622**, which reduces the sample rate by a decimation factor R_1 . Together, the digital filter **1620** and the sample rate compression block **1622** comprise a decimator **1621**. The output of the sample rate compression block **1622** is a signal $MF(k)$. The signal $MF(k)$ is provided as: the first input to the first mixer **1624**; the first input to the second mixer **1626**; a first input to a third mixer **1710**; a first input to an N^{th} mixer **1712**; and a first input to a noise channel mixer **1713**. A first demodulating signal $D_1(k)$ is provided as a second input to the first mixer **1624**. A second demodulating signal $D_2(k)$ is provided as a second input to the second mixer **1626**. A third demodulating signal $D_3(k)$ is provided to the third mixer **1710**. A fourth demodulating signal $D_N(k)$ is provided to the N^{th} mixer **1712**. A noise demodulating signal $D_0(k)$ is provided to the noise channel mixer **1713**. The outputs of the mixers **1624**, **1626**, **1710**, **1712**, and **1713** are provided as respective inputs of the low-pass filters **1630**, **1640**, **1720**, **1730**, and **1740**. The outputs of the lowpass filters **1630**, **1640**, **1720**, **1730**, and **1740** are provided as respective inputs of the decimators **1632**, **1642**, **1721**, **1731** and **1741**. Each of the decimators **1632**, **1642**, **1721**, **1731** and **1741** reduces the sample rate by a decimation rate R_2 .

The output of the sample rate compressor **1632** is a signal $\hat{S}_1(k)$, which, as discussed below, is an estimate of the signal $S_1(k)$. Likewise, the output of the sample rate compressor **1642** is an estimate of $S_2(t)$, the output of the sample rate compressor **1721** is an estimate of the signal $S_3(t)$, the output of the sample rate compressor **1731** is an estimate of the signal $S_N(t)$, and the output of the sample rate compressor **1741** is an estimate of the signal $n(t)$.

As will be shown below, the selection of the demodulating signals $D_i(t)$ for $i=0 \dots N$ in accordance with the present invention can substantially reduce or eliminate the effects of noise in the output signals $\hat{S}_1(k)$ and $n(k)$, and can also substantially reduce or eliminate crosstalk between the signals.

As shown in FIG. 17, a set of $N+1$ signals $S_i[k]$ $i=1 \dots N$, and $n(k)$ are sampled at a rate T/QN , where T is a modulation period. For simplicity, the decimation rate R_1 is assumed to be the same as the factor Q . The assumption that $R_1=Q$ is not a necessary assumption, but rather is used here to simplify the mathematics. The signals are combined according to the formula:

$$S(k) = M_1(k)S_1(k) + M_2(k)S_2(k) + M_3(k)S_3(k) + \dots + M_N(k)S_N(k) + n(k) \quad (42)$$

Using the symbol $*$ to denote the convolution operator, the terms $M_i(k)$ are given by:

$$\begin{aligned} M_1(k) &= \Lambda(2Nt/T) * P_1(t) |_{t=kT/QN} \\ M_2(k) &= \Lambda(2Nt/T) * P_1(t) |_{t=kT/QN} \\ M_3(k) &= \Lambda(2Nt/T) * P_1(t) |_{t=kT/QN} \end{aligned} \quad (43)$$

where

$$\Delta(x) = \begin{cases} 1 & \text{if } |x| \leq 0.5 \\ 0 & \text{otherwise} \end{cases} \quad (44)$$

and

$$P_1(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT) \quad (45)$$

(where $\delta(k)$ is the Kronecker delta function, which is 1 for $k=0$, and 0 for all other values of k), and

$$P_1 = P_1 \left(t - \frac{(i-1)T}{N} \right) \text{ for } i = 2 \dots N \quad (46)$$

After the pre-demodulation and sample rate compression stage **1622**, which decimates by a factor Q, the signal in the frequency domain is given approximately by

$$MF(f) = \frac{1}{T} \sum_{n=-\infty}^{\infty} \left[S_1 \left(f - \frac{n}{T} \right) + \xi_1^n S_2 \left(f - \frac{2n}{T} \right) + \dots + \xi_N^n S_N \left(f - \frac{Nn}{T} \right) \right] + \frac{2N}{T} \sum_{m=-\infty}^{\infty} S_n \left(f - \frac{2Nm}{T} \right) \quad (47)$$

where

$$\xi_k^n = e^{\frac{j2\pi kn}{N}} \quad (48)$$

The demodulator sequences are then given by:

$$D_0(k) = \frac{(1 - (-1)^k)}{2} \quad (49)$$

$$D_1(k) = P_1(k) = \frac{D_0(k)}{N}$$

$$D_2(k) = P_2(k) = \frac{D_0(k)}{N}$$

$$D_N(k) = P_N(k) = \frac{D_0(k)}{N}$$

where

$$P_1(K) = P_1(t) \Big|_t = \frac{kT}{2N}, \quad P_2(K) = P_2(t) \Big|_t = \frac{kT}{2N}, \dots, P_N(K) = P_N(t) \Big|_t = \frac{kT}{2N} \quad (50)$$

The post demodulation lowpass filters **1630**, **1640**, **1720**, **1730** and **1740**, and the post demodulation sample rate compression stages **1632**, **1642**, **1721**, **1731** and **1741** suppress high frequency artifacts which are produced by the modulation/demodulation process. Note that Equation 49 reduces to Equation 40 for N=2.

Adaptive Demodulation

The multi-channel pre-demodulation decimation technique described in the previous section can be extended to an adaptive multi-channel system having an adjustable pre-demodulation decimation rate and an adjustable post-demodulation decimation rate. FIG. **18** illustrates an expansion of the multi-channel modulator into an adaptive multi-channel modulator/demodulator **1800**. FIG. **18** shows the first modulator **191** and the Nth modulator **1702** as shown in FIG. **17**. The signal input S₁(t) and a modulation input M₁(t) are provided to the first modulator **191**. A signal input S_N(t) and a modulation input M_N(t) are provided to the Nth modulator **1702**.

The photodetector **150** is modeled as an adder **194** and an adder **196**. The outputs of the modulators **191**, **193**, **1701**, and **1703** are added together in the adder **194**, to generate a composite signal M(t) where:

$$M(t) = S_1(t)M_1(t) + \dots + S_N(t)M_N(t) \quad (51)$$

The signal M(t) from the adder **194** is provided to the adder **196** where the signal M(t) is added to the signal n(t) which

represents a composite noise signal caused by ambient light, electromagnetic pickup, and the like, which are also detected by the photodetector **150**. The output of the adder **196** is the signal M'(t)=M(t)+n(t), which includes noise components as well as the signal components.

The M'(t) signal output of the adder **196** (i.e., the output of the detector **150**) is applied to the input of the signal processing block **1800**. Within the signal processing block **1800**, the signal M'(t) is first passed through the amplifier **197** and then through the analog bandpass filter **198**. The analog bandpass filter **198** provides anti-aliasing and removal of low frequency noise and DC. The desired signal components in the signals S₁(t) are frequency shifted by the operation of the modulation signals M₁(t) and are passed by the analog bandpass filter **198**.

The output of the analog bandpass filter **198** is sampled by the analog-to-digital converter **199** and converted therein to digital signals and provided to an input of a decimation block **1820**. The adaptive decimation block **1820** comprises a digital lowpass filter and a sample rate compressor that reduces the sample rate by the decimation rate R₁. The filter coefficients and decimation rate R₁ are provided to a control input of the adaptive decimation block **1820** by an output of an adaptive algorithm block **1850**. Equation 35 assumes that the decimation rate R₁ is equal to Q. However, in general, the value of Q may be different than the decimation rate R₁. The output of the adaptive decimation block **1820** is a signal MF(k).

The signal MF(k) is provided to the first input of the first mixer **1624**, to the first input of the Nth mixer **1712**, and to the first input of the noise channel mixer **1713**. A first demodulating signal D₁(k) is provided to a second input of the first mixer **1624** from a signal generator **1841**. The fourth demodulating signal D_N(k) is provided to the Nth mixer **1712** from an output of a signal generator **1831**. The noise demodulating signal D_N(k) is provided to the noise channel mixer **1713** from an output of a signal generator **1832**. A control input to each of the signal generators **1831**, **1832**, and **1841** is provided by the output of the adaptive algorithm **1850**. In yet another embodiment, the adaptive algorithm **1850** may also be controlled by other signal processing elements downstream of the signal processor **1800**.

The outputs of the mixers **1713**, **1624**, and **1712** are provided as respective inputs to adaptive decimation blocks **1840**, **1830**, and **1834** respectively. Each of the adaptive decimation blocks **1840**, **1830**, and **1834** has a control input provided by the output of the adaptive algorithm block **1850**. The output of the adaptive decimation block **1840** is an estimate of the signal n(t) and it is provided to an input of the adaptive algorithm block **1850**. In an alternate embodiment, the signal estimates $\hat{S}_i(k)$ are also provided to the adaptive algorithm block **1850**.

An output of the decimator **1830** is a signal $\hat{S}_1(k)$, which, as discussed above, is an estimate of the signal S₁(k). Likewise, the output of the decimation block **1834** is an estimate of the signal S_N(t). As shown above, the selection of the demodulating signals D_i(t) for i=0 . . . N in accordance with the present invention substantially reduces or eliminates the effects of noise in the output signals $\hat{S}_i(k)$ and n(k), and also substantially reduces or eliminates crosstalk between the signals.

As shown in FIG. **18**, a set of N+1 signals S_i[k] i=1 . . . N, and n(k) are sampled at a rate T/QN, where T is a modulation period, and R₁ is the decimation rate of the decimation block **1820**. The signals are combined according to the formula:

$$S(k) = M_1(k)S_1(k) + \dots + M_N(k)S_N(k) + n(k) \quad (52)$$

Each of the adaptive decimators **1820**, **1840**, **1830**, and **1834** comprises a digital **5** lowpass filter and a sample rate compressor. The characteristics of the digital lowpass filters (e.g., the number of filter coefficients and values of the filter coefficients) and the sample rate compression factor of each adaptive decimator is provided to a control input of the adaptive decimator. The control inputs are driven by an adaptive algorithm **1850**. The signal generators **1831**, **1832** and **1841** generate the demodulation sequences for the demodulators **1624**, **1712**, and **1713** respectively. The demodulation sequences produced by the signal generators **1831**, **1832** and **1841** are controlled by the adaptive algorithm **1850**.

The adaptive algorithm adjusts the pre-demodulation decimation rate R_1 (in the adaptive demodulator **1820**), and the post-demodulation decimation rate R_2 (in the adaptive demodulators **1830**, **1834** and **1840**) according to the noise in the noise estimate $n(k)$ **1746** and (optionally) according to the signals $\hat{S}_i(k)$. The product $R_1 R_2$ is the total decimation rate from the signal $S(k)$ at the output of the AID converter **199** to the signals (k) at the output of the signal processing block **1800**. The adaptive algorithm may adjust R_1 and R_2 such that the product $R_1 R_2$ varies, or the adaptive algorithm may adjust R_1 and R_2 such that the product $R_1 R_2$ is substantially constant. Typically, the adaptive algorithm will keep the $R_1 R_2$ product constant so that the signal processing blocks downstream of the signal processor **1800** will operate at a substantially constant sample rate.

Typically, each of the signal generators **1841**, **1831** and **1832** generates a repeating sequence of numbers. The number of elements in the sequence is a function of the decimation factor R_1 . As discussed above in connection with FIG. **3**, when $R_1=1$, there are preferably 148 values in each demodulation sequence. As discussed above in connection with FIG. **17**, when $R_1=37$, there are preferably only 4 values in the demodulation sequences.

The adaptive algorithm selects R_1 , R_2 , and the filter transfer functions in the adaptive decimators **1820**, **1830**, **1834**, and **1840** to improve the quality of the output signals $\hat{S}_i(k)$. For example, in high ambient noise environments, the higher order harmonics of the output signals are often contaminated by ambient noise (as discussed in connection with FIGS. **14** and **20**). Thus, the higher order harmonics are preferably not demodulated when ambient noise is present. To avoid demodulation of the higher order harmonics the adaptive demodulator **1850** can set $R_1=1$ and $R_2=37$, and thereby demodulate according to the method described in connection with FIGS. **3-14**. Alternatively, the adaptive demodulator **1850** can set $R_1=37$, set $R_2=1$, and set the transfer function of the lowpass filter in the adaptive decimator **1820** to provide a very fast rolloff (thereby filtering out the higher order harmonics).

Conversely, in low ambient noise environments, the higher order harmonics of the output signal are less contaminated by ambient noise, and thus the higher order harmonics may be demodulated. In one embodiment, to demodulate the higher order harmonics, the adaptive demodulator **1850** can set $R_1=37$ and set $R_2=1$, to demodulate according to the method described in connection with FIG. **17**. This is especially advantageous when perfusion is low, because, when perfusion is low the output signals $\hat{S}_i(k)$ are typically very weak and are contaminated by random noise. Demodulating more of the higher order harmonics increases the signal-to-noise ratio because it adds the harmonics (which are correlated) to the output signals, and tends to average out the noise (which is uncorrelated). Thus, the signal strength increases, and the noise is reduced.

One skilled in the art will recognize that the examples in the preceding two paragraphs are merely two points on a continuum and that the adaptive algorithm **1850** can generate many desirable solutions on the continuum.

5 Ambient Light Rejection

In the pulse oximeter, one of the major contributors to the noise signal $n(t)$ is ambient light that is detected by the photodetector **150**. One aspect of the present invention advantageously provides a method for choosing the modulation sampling rate f_s and the factor Q so that the effects of ambient light can be removed by the post demodulation filtering and decimation stages. Note that Q is the number of samples during the on period (i.e., modulation signal sample turn on time Q) and is preferably also the decimation rate R_1 for the pre-demodulation sample rate compressor **1622** (in general the values of Q and R_1 may be different). The particular embodiment described by Equation 35 assumes that the value Q is also used as decimation rate R_1 for the pre-demodulation decimator **1820**.

In the system shown in FIGS. **3** and **16**, which demodulates two harmonics, the period of a modulation cycle is given by:

$$T=4Q/f_s \quad (53)$$

where f is the sample rate. Defining the two line equations

$$y(f_a, n) = n f_a - \frac{1}{T} \quad (54)$$

where

$$f_a = \text{line frequencies of concern}$$

$$n = \text{line frequency harmonic numbers of concern} \quad (55)$$

then the effects due to ambient light will be minimized when

$$\begin{aligned} |y(f_a, n)| &\geq \text{SBF} \\ |z(f_a, n)| &\geq \text{SBF} \end{aligned} \quad (56)$$

where SBF is the stop band frequency of the post demodulation and decimation stages (e.g., the 10 Hz lowpass filter **1630** and the sample rate compressor **1632**, etc.).

FIG. **19** is a flowchart showing a method for selecting f_s and Q . The method begins at a process block **1902** wherein the ambient light frequencies f_a and important harmonic components n are identified. Important harmonics are defined as those harmonics that will degrade system performance below acceptable levels when detected by the detector **150**. The process then advances from the process block **1902** to a process block **1904**. In the process block **1904**, the values of f_a and n identified in the process block **1902** are used in conjunction with Equation 54 to identify a collection of acceptable values of T . Upon completion of the process block **1904**, the process advances to a process block **1906**. In the process **1906**, suitable values of f_s and Q are chosen using the values of T obtained in the process block **1904** and the equation $T=4Q/f_s$. One skilled in the art will recognize that, since T is proportional to the ratio of Q/f_s , knowing T will not uniquely determine either f_s or Q .

For example, given power line frequencies of 50 ± 1 Hz and 60 ± 1 Hz then the range of f_a is given by approximately the union of the interval 49-51 Hz and the interval 59-61 Hz, which can be expressed mathematically as:

$$f_a \approx [49, 51] \cup [59, 61] \quad (57)$$

Assuming that all harmonics up to the 18th harmonic are to be suppressed, then $n=1 \dots 18$. In a preferred embodiment,

using these values for f_a and n , application of the method in FIG. 19 results in $f_s=46,875$ Hz and acceptable Q values of 37 and 41.

The process leading to Equation 57 is illustrated graphically by FIG. 20, where the harmonics of the ambient light frequency f_a (in Hz) are plotted versus the plethysmograph signal frequency (also in Hz). FIG. 20 has an x-axis showing the ambient light frequency from 44 Hz to 64 Hz. The ambient light frequency will usually correspond to the frequency of the power lines, which is nominally 60 Hz (in the U.S.) and 50 Hz (outside the U.S.). However, power line frequency regulation typically varies somewhat, and thus FIG. 20 shows frequencies above and below the nominal frequencies.

FIG. 20 also shows a y-axis showing the plethysmograph signal frequency from -10 Hz to 10 Hz. One skilled in the art will recognize that negative frequencies occur in the mathematics described above. In particular, a signal that is modulated from baseband up to some carrier frequency will exhibit two sidebands, a sideband above the carrier frequency corresponding to the frequency of the baseband signal, and a sideband below the carrier frequency corresponding to the negative of the baseband frequency. Thus, when dealing with modulation and demodulation, it is convenient to deal with positive and negative frequencies.

FIG. 20 also shows harmonic lines corresponding to the 5th, 6th, 7th, 10th, 11th, 12th, 13th, and 14th harmonics of the ambient light frequency. The harmonic lines correspond to the harmonics produced in the plethysmograph signal by the demodulation (mixing down) of harmonics of the power line frequency. The lines in FIG. 20 are calculated using Equation 54 for $1/T=316.72$ Hz. Some of the harmonic lines correspond to $y(f_a, n)$ and some correspond to $z(f_a, n)$ from Equation 54. Harmonic lines that are not shown (e.g., the line corresponding to the 8th harmonic) fall outside the displayed limits of the x-axis and y-axis.

FIG. 20 can be used to determine the stop band frequencies as shown in Equation 56. For example, the harmonic lines in FIG. 20 show that for an ambient light frequency of 49 Hz, the 13th harmonic of the ambient light frequency will appear in the plethysmograph signal at approximately 3 Hz. Thus, FIG. 20 shows that for plethysmograph bandwidth of 10 Hz, none of the first 14 harmonics of the ambient light will appear in the plethysmograph signal for ambient light frequencies between approximately 612 Hz and approximately 58.5 Hz, which is consistent with Equation 57. The first ambient harmonics that do appear for a plethysmograph bandwidth of 10 Hz are the 5th harmonic and the 11 m harmonic.

Other Embodiments

In the preferred embodiment of the present invention, the hardware described above is implemented in a digital signal processor and associated circuitry. The LED modulation block 104 and the LED demodulation state table block 352 comprise algorithms implemented by program code executed by the digital signal processor. In addition, the configuration variables, such as for example, the hardware delay value, the hardware distortion value and the hardware scale value are provided as inputs to the digital signal processor when it is set up. For example, the main operating program of the digital signal processor may be stored in non-volatile ROM or PROM, and the variables may be stored in flash memory during a setup procedure. Techniques for communicating to and from a digital signal processor during such setup procedures are well known to persons of skill in the art, and will not be described in detail herein. For example, the configuration bus 310, discussed above, represents a communication path to the flash memory during such a setup procedure. The data provided to the configuration bus 310 may be provided by a

system operator (not shown) or the data may be provided from look-up tables (not shown) maintained for different embodiments of the LEDs 106, 108 and the detector 150.

Although described above in connection with a pulse oximetry system wherein a parameter to be measured is the attenuation of red and infrared light passing through a portion of a subject's body; it should be understood that the method and apparatus described herein can also be used for other measurements where two or more signals are passed through a system to be analyzed. In particular, the present invention can be used to demodulate two combined parametric signals responsive to the system to be analyzed where the two parametric signals have a predetermined timing relationship between them, as described herein.

One skilled in the art will recognize that the lowpass filters provided in connection with the decimation blocks may provide other filter functions in addition to lowpass filtering. Thus, for example, the lowpass filters 1620, 1622, 1630, 1640, 1650, 1720, 1730, and 1740, and the decimators 1820, 1830, 1834, and 1840 may provide other filter functions (in addition to lowpass filtering) such as, for example, bandpass filtering, bandstop filtering, etc. Moreover, the post-demodulation decimation rate R_2 need not be the same for each output channel. Thus, for example, in FIG. 18, the decimator 1840 may have a first decimation rate $R_2=r_1$ while the decimators 1830 and 1834 have a second decimation rate $R_2=r_2$.

Although described above in connection with a particular embodiment of the present invention, it should be understood the description of the embodiment is illustrative of the invention and are not intended to be limiting. Various modifications and applications may occur to those skilled in the art without departing from the true spirit and scope of the invention as defined in the appended claims.

What is claimed is:

1. A pulse oximeter configured to measure one or more physiological characteristics of a living subject non-invasively by measuring pulsing light of two or more wavelengths after attenuation by body tissue, the pulse oximeter comprising:

at least one emitter configured to emit light of at least two or more different wavelengths using a modulation scheme that cycles the at least two or more different wavelengths;

at least one detector configured to detect the light of the at least two or more different wavelengths emitted from the at least one emitter after the light has been attenuated by tissue of the living subject, the detector further configured to generate a detector signal representative of the emitted light;

at least one demodulation system configured to demodulate the detector signal and to generate a demodulated detector signal;

an adaptive algorithm processor configured to:

receive one or more inputs;

based, at least in part, on the one or more inputs, generate at least one control signal configured to reduce crosstalk; and

transmit at least one of the control signals to each of the demodulation systems;

wherein each of the demodulation systems is configured to adjust its demodulation based on the at least one control signal to reduce crosstalk;

at least one signal processor configured to use the demodulated detector signal to determine and display at least one physiological measurement; and

the one or more inputs to the adaptive algorithm processor include at least one of: detector configuration data, calibration data, or a noise demodulated signal.

2. The pulse oximeter of claim 1, wherein the at least one demodulation system is further configured to adjust the at least one demodulation in accordance with the control signal during a period where one or more of the at least two different wavelengths is turned off.

3. The pulse oximeter of claim 1, wherein the at least one demodulation system is further configured to adjust in accordance with the control signal during an initial calibration period.

4. The pulse oximeter of claim 3, wherein the adaptive algorithm processor is further configured to adjust the at least one demodulation system in accordance with the control signal during periodic calibration periods during measurement.

5. The pulse oximeter of claim 1, wherein the at least one demodulation system is further configured to utilize a plurality of demodulation coefficients to demodulate the detector signal.

6. The pulse oximeter of claim 5, wherein the at least one demodulation system is further configured to use at least one demodulation coefficient to demodulate each of the at least two or more different wavelengths.

7. The pulse oximeter of claim 1, wherein the at least one demodulation system is configured to use diagonalization.

8. A method of demodulating a composite signal generated by applying at least first and second periodic pulses of electromagnetic energy to a system having a physiological parameter to be measured and by non-invasively receiving signals responsive to the electromagnetic energy after attenuation by body tissue of a living subject, the signals received as a composite signal having at least first and second components responsive to the at least first and second pulses respectively, said method comprising:

receiving, at one or more signal processors, a composite signal responsive to electromagnetic energy of at least first and second periodic pulses of electromagnetic energy after attenuation by body tissue;

applying, using the one or more signal processors, a first demodulation scheme to the composite signal to generate at least a first demodulated signal;

generating, by an adaptive algorithm, at least one control signal;

automatically adjusting, using the one or more signal processors, the first demodulation scheme based, at least in part, by the at least one control signal;

using at least a second demodulated signal, obtained using the adjusted first demodulation scheme, to determine and display a physiological measurement; and

wherein the adaptive algorithm uses at least one of: detector configuration data, calibration data, or a noise demodulated signal to generate the control signal.

9. The method of claim 8, wherein the signal processor is further configured to adjust in order to reduce crosstalk.

10. The method of claim 8, further comprising applying a second demodulation scheme to the composite signal to generate a second demodulated signal and adjusting the second demodulation scheme based at least in part on the second demodulated signal.

11. The method of claim 10, wherein the signal processor is further configured to adjust at least one of the first and second demodulation schemes in the absence of at least one of the first and second periodic pulses of electromagnetic energy.

12. The method of claim 10, wherein the signal processor is further configured to adjust at least one of the first and second demodulation schemes based on the demodulated signals in order to further reduce crosstalk interspersed with measurements.

13. The method of claim 8, wherein the signal processor is further configured to adjust continuously.

14. A pulse oximeter for demodulating a composite signal generated by applying at least first and second periodic pulses of electromagnetic energy to a system having a physiological parameter to be measured and by non-invasively receiving signals responsive to the electromagnetic energy after attenuation by body tissue of a living subject, the signals received as a composite signal having at least first and second components responsive to the at least first and second pulses respectively, said pulse oximeter comprising:

means for receiving a composite signal responsive to electromagnetic energy of at least first and second periodic pulses of electromagnetic energy after attenuation by body tissue;

means for applying a first demodulation scheme to said composite signal to generate at least a first demodulated signal;

means for generating, by an adaptive algorithm, at least one control signal, the at least one control signal based at least in part on at least one of: detector configuration data, calibration data, or a noise demodulated signal;

means for automatically adjusting the first demodulation scheme by the at least one control signal;

means for determining a physiological measurement using a second demodulated signal obtained after adjusting the first demodulation scheme; and

means for displaying the physiological measurement.

15. The pulse oximeter of claim 14, further comprising applying a second demodulation scheme to the composite signal to generate a second demodulated signal and adjusting the second demodulation scheme based at least in part on the second demodulated signal.

16. The pulse oximeter of claim 15, wherein the means for automatically adjusting is further configured to adjust at least one of the first and second demodulation schemes in the absence of at least one of the first and second periodic pulses of electromagnetic energy.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 9,351,673 B2
APPLICATION NO. : 14/269606
DATED : May 31, 2016
INVENTOR(S) : Mohamed Kheir Diab

Page 1 of 3

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

In the Drawings

Sheet 8 of 18 (Reference Numeral 372, FIG. 9) at Line 3, Change "CURCUIT" to --CIRCUIT--.

In the Specification

In Column 6 at Line 11, Change "MI(t)" to --M₁(t)--.

In Column 9 at Line 33, Change "D₂(k)" to --D₂(k)--.

In Column 9 at Line 48, Change " $\hat{S}_1(t)$ and $\hat{S}_1(t)$ " to -- $\hat{S}_1(t)$ and $\hat{S}_2(t)$ --.

In Column 10 at Line 1, Change "M₂(t)" to --M₂(t)--.

In Column 12 at Line 46, Change "fundamental s" to --fundamentals--.

In Column 12 at Line 65, Change "DI(t)," to --D₁(t),--.

In Column 13 at Line 32, Change " $\text{crosstalk}_{DC} = \text{LP}[S_2(t)[aB/2]^{-1/2}]$ " to -- $\text{crosstalk}_{DC} = \text{LP}[S_2(t)[aB/2]^{-1/2}]$ --.


In Column 13 at Line 34, Change "S₂(t)" to --S₂(t)--.

In Column 13 at Line 59, Change "S₁-D₁." to --S₁·D₁.--.

In Column 14 at Line 10, Change "M₂(t)" to --M₂(t)--.

In Column 14 at Line 10, Change "D₂(t)." to --D₂(t).--.

Signed and Sealed this
Twenty-seventh Day of June, 2017



Joseph Matal
Performing the Functions and Duties of the
Under Secretary of Commerce for Intellectual Property and
Director of the United States Patent and Trademark Office

U.S. Pat. No. 9,351,673 B2

In Column 15 at Line 52, Change “a” to --a--.

In Column 17 at Line 24, Change “as.” to --as--.

In Column 18 at Line 48, Change “M₂(t)” to --M₂(t)--.

In Column 18 at Line 52, Change “MI(t).” to --M₁(t).--.

In Column 18 at Line 54, Change “MI(t)” to --M₁(t)--.

In Column 19 at Line 50, Change “more.” to --more--.

In Column 23 at Line 38, Change “1641,” to --1641.--.

In Column 23 at Line 50, Change “R₂=20” to --R₂=20--.

In Column 24 at Line 7, Change “S₁ (t)” to --S₁ (t)--.

In Column 26 at Line 33, Change “i=0” to --i=0--.

In Column 26 at Line 66, Change “Kroneker” to --Kronecker--.

In Column 28 at Line 9, Change “through.” to --through--.

In Column 31 at Line 26, Change “10t,” to --10th.--.

In Column 31 at Line 63, Change “axe” to --are--.

In the Claims

In Column 32 at Line 49, In Claim 1, change “the” to --a--.

In Column 32 at Lines 58-59, In Claim 1, after “signal” delete “configured to reduce crosstalk”.

In Column 32 at Line 66, In Claim 1, after “and” insert --to--.

In Column 33 at Line 6, In Claim 2, change “siganal” to --signal--.

In Column 33 at Line 11, In Claim 3, change “siganal” to --signal--.

In Column 33 at Lines 15-16, In Claim 4, change “siganal” to --signal--.

In Column 33 at Line 35, In Claim 8, change “said” to --the--.

CERTIFICATE OF CORRECTION (continued)

Page 3 of 3

U.S. Pat. No. 9,351,673 B2

In Column 34 at Line 27 (approx.), In Claim 14, change “said” to --the--.

In Column 34 at Line 33, In Claim 14, change “said” to --the--.

In Column 34 at Line 44, In Claim 14, change “measaurement.” to --measurement.--.

专利名称(译)	用于在脉搏血氧测定系统中解调信号的方法和装置		
公开(公告)号	US9351673	公开(公告)日	2016-05-31
申请号	US14/269606	申请日	2014-05-05
[标]申请(专利权)人(译)	梅西莫股份有限公司		
申请(专利权)人(译)	Masimo公司		
当前申请(专利权)人(译)	Masimo公司		
[标]发明人	DIAB MOHAMED K WEBER WALTER M AL ALI AMMAR		
发明人	DIAB, MOHAMED K. WEBER, WALTER M. AL-ALI, AMMAR		
IPC分类号	A61B5/1455 H04J14/08 H04J3/10 A61B5/00 A61B5/145		
CPC分类号	A61B5/14551 A61B5/7217 A61B5/7228 H04J3/10 H04J14/08 A61B5/7232 A61B2560/0242 A61B5/14552 A61B5/1495 A61B5/7203 A61B2562/0238		
代理机构(译)	KNOBBE , MARTENS , 奥尔森 & BEAR LLP		
优先权	11/750930 2012-04-03 US 11/311213 2007-05-22 US 10/700324 2006-02-21 US 09/735960 2003-11-04 US 09/058799 2001-05-08 US 09/005898 1999-07-06 US 60/043620 1997-04-14 US		
其他公开文献	US20140243627A1		
外部链接	Espacenet USPTO		

摘要(译)

一种测量受试者的血氧的方法和装置。激活光源以引起第一波长的第一发射和第二波长的第二发射。检测器检测指示患者组织对第一和第二波长的衰减的复合信号。复合信号被解调成第一强度信号和第二强度信号。从第一和第二强度信号确定受试者中的血液氧合。

