



(11) **EP 2 397 867 A1**

(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
21.12.2011 Bulletin 2011/51

(51) Int Cl.:
G01S 15/89 (2006.01) A61B 8/06 (2006.01)

(21) Application number: **11170018.3**

(22) Date of filing: **15.06.2011**

(84) Designated Contracting States:
AL AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL PT RO RS SE SI SK SM TR
Designated Extension States:
BA ME

(72) Inventors:
• **Kwak, Han**
135-851 Seoul (KR)
• **Lee, Jae Keun**
135-851 Seoul (KR)
• **Kim, Jong Sik**
135-851 Seoul (KR)

(30) Priority: **17.06.2010 KR 20100057426**

(71) Applicant: **Samsung Medison Co., Ltd.**
Nam-myun
Hongchun-gun
Kangwon do 250-875 (KR)


(74) Representative: **Schmid, Wolfgang**
Lorenz & Kollegen
Patentanwälte Partnerschaftsgesellschaft
Alte Ulmer Strasse 2
89522 Heidenheim (DE)

(54) **Adaptive clutter filtering in an ultrasound system**

(57) Embodiments for adaptively performing clutter filtering upon in an ultrasound system are disclosed. In one embodiment, the ultrasound system includes: an ultrasound data acquisition unit configured to transmit ultrasound signals to a target object and receive ultrasound echoes reflected from the target object to thereby acquire

ultrasound data; and a processing unit configured to form a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data, as well as to adjust coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

FIG. 1



EP 2 397 867 A1

Description

CROSS-REFERENCE TO RELATED APPLICATIONS

5 **[0001]** The present application claims priority from Korean Patent Application No. 10-2010-0057426 filed on June 17, 2010.

TECHNICAL FIELD

10 **[0002]** The present disclosure generally relates to ultrasound image processing, and more particularly to adaptive clutter filtering in an ultrasound system.

BACKGROUND

15 **[0003]** An ultrasound system has been extensively used in the medical field due to its non-invasive and non-destructive nature. Modern high-performance ultrasound imaging diagnostic systems and techniques are commonly used to produce two-dimensional or three-dimensional ultrasound images of internal features of patients.

[0004] The ultrasound system transmits ultrasound signals to the target objects, receives echo signals reflected from the target objects and provides a color Doppler mode image of the target object based on the echo signals. In the color Doppler mode image, velocities of the target object (e.g., blood flow), which flows toward an ultrasound probe, are indicated in a first color (e.g., red), while velocities of the target object, which flows away from an ultrasound probe, are indicated in a second color (e.g., blue).

20 **[0005]** The signal received by the ultrasound probe is converted into a digital signal at a front end. The digital signal is receive-focused to thereby obtain a receive-focused signal. The band of the receive-focused signal is modulated by a mixer and then the receive-focused signal is appropriately decimated so that In-phase/Quadrature (IQ) signal is obtained. This IQ signal is referred to as a baseband IQ signal. The IQ signal may be expressed by the following equation.

$$X_{IQ} = C + F + N \quad (1)$$

30 wherein X_{IQ} represents an IQ signal, C represents a clutter signal generated from a tissue, F represents a blood flow signal generated from blood flow, and N represents a noise signal generated from the system and exterior.

[0006] Essential information from Equation (1) is information on F, i.e., the blood flow signal. Color Doppler processing represents a process of extracting components on the blood flow signal from the IQ signal and processing the extracted components into data for display on a screen. Clutter filtering is an essential processing step in the color Doppler processing. The clutter filtering is performed to remove a low-band clutter signal from a Doppler signal to thereby extract only a blood flow signal and a noise signal. The filtered Doppler signal contains the blood flow signal and the noise, which are mixed with each other. The noise may be removed through signal processing. Then, the components on the blood flow signal are displayed on a screen.

40 **[0007]** Generally, the clutter signal is distributed at a low frequency band, whereas the blood flow signal is distributed at a high frequency band. Thus, a high pass filter should be designed to remove the clutter signal. However, the amplitude of the clutter signal is higher than that of the blood flow signal by 40 - 60 dB. As such, it is not easy to extract only the blood flow signal. Accordingly, a high performance of the high pass filter is required.

45 **[0008]** Further, since an effective clutter filtering may be limited due to a small ensemble number, various filtering techniques have been developed. The clutter filter may be classified into a finite impulse response (FIR), an infinite impulse response (IIR) and a Regression. In case of the IIR filter, various initializing techniques such as zero, step, exponential, projection, etc. have been developed to suppress the transient. The Regression-type filter is classified into a polynomial filter, a sinusoidal regression filter and the like.

50 **[0009]** Conventionally, a clutter filter is properly selected depending on the application of an ultrasound system and the clutter filtering is performed with only the selected clutter filter. In such a case, i.e., if an identical clutter filter is applied to entire regions within a region of interest, the quality of an ultrasound image may be degraded.

SUMMARY

55 **[0010]** Embodiments for adaptively performing clutter filtering in an ultrasound system are disclosed herein. In one embodiment, by way of non-limiting example, an ultrasound system comprises: an ultrasound data acquisition unit configured to transmit ultrasound signals to a target object and receive ultrasound echoes reflected from the target object

to thereby acquire ultrasound data; and a processing unit configured to form a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data, as well as to adjust coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

[0011] In another embodiment, a method of adaptively performing clutter filtering, comprises:

a) acquiring ultrasound data indicative of a target object; and b) forming a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data; and c) adjusting coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

[0012] In yet another embodiment, a computer-readable storage medium storing instructions that, when executed by a computer, cause the computer to provide a method of adaptively performing clutter filtering upon in an ultrasound system is provided, the method comprising: a) acquiring ultrasound data indicative of a target object; and b) forming a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data; and c) adjusting coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

[0013] The Summary is provided to introduce a selection of concepts in a simplified form that are further described below in the Detailed Description. This Summary is not intended to identify key or essential features of the claimed subject matter, nor is it intended to be used in determining the scope of the claimed subject matter.

BRIEF DESCRIPTION OF THE DRAWINGS

[0014]

FIG. 1 is a block diagram showing an illustrative embodiment of an ultrasound system.

FIG. 2 is a block diagram showing an illustrative embodiment of an ultrasound data acquisition unit.

FIG. 3 is a block diagram showing an illustrative embodiment of a processing unit.

FIG. 4 is a graph showing a relationship between stopband attenuation and stopband width in a clutter filter.

FIG. 5 is a graph showing a relationship between a cutoff frequency and stopband attenuation for setting coefficients of a clutter filter.

DETAILED DESCRIPTION

[0015] A detailed description may be provided with reference to the accompanying drawings. One of ordinary skill in the art may realize that the following description is illustrative only and is not in any way limiting. Other embodiments of the present invention may readily suggest themselves to such skilled persons having the benefit of this disclosure. The term "Doppler mode" described in the following embodiments includes a color Doppler mode, a spectral Doppler mode and the like.

[0016] Referring to FIG. 1, an ultrasound system constructed in accordance with one embodiment is shown therein. The ultrasound system 100 includes a user input unit 110, an ultrasound data acquisition unit 120, a processing unit 130 and a display unit 140.

[0017] The user input unit 110 receives a user request from a user. In one embodiment, the user request includes a first user request for setting a region of interest (ROI) on a brightness mode (B-mode) image. Also, the user request further includes a second user request for adjusting coefficients of a clutter filter to filter out a clutter signal from a Doppler signal for each of pixels constructing a Doppler mode image. The filter coefficients include a cutoff frequency, stopband attenuation and the like.

[0018] The ultrasound data acquisition unit 120 is configured to transmit ultrasound beams to a target object and receive ultrasound echoes reflected from the target object to thereby form ultrasound data representative of the target object. An operation of the ultrasound acquisition unit 120 will be described in detail by referring to FIG. 2.

[0019] FIG. 2 is a block diagram showing an illustrative embodiment of the ultrasound data acquisition unit 120. Referring to FIG. 2, the ultrasound data acquisition unit 120 includes a transmit (Tx) signal forming section 122. The Tx signal forming section 122 is configured to generate a plurality of Tx signals and apply delays to the Tx signals. The delays of the Tx signals may be controlled according to an image mode such as a brightness mode, a Doppler mode and the like, which may be provided in the ultrasound system. In one embodiment, the Tx signals include first Tx signals for the brightness mode and second Tx signals for the Doppler mode.

[0020] The ultrasound data acquisition unit 120 further includes an ultrasound probe 124, which is coupled to the Tx signal forming section 122. The ultrasound probe 124 may include an array transducer containing a plurality of transducer

elements for reciprocal conversion between electric signals and ultrasound signals. The ultrasound probe 124 is configured to transmit ultrasound signals in response to the Tx signals. The ultrasound probe 124 is further configured to receive ultrasound echoes reflected from the target object to thereby output receive signals. In one embodiment, the receive signals include first receive signals obtained in response to the first Tx signals and second receive signals obtained in response to the second Tx signals.

[0021] The ultrasound data acquisition unit 120 further includes a beam forming section 126, which is coupled to the ultrasound probe 124. The beam forming section 126 is configured to digitize the receive signals to obtain digital signals. The beam forming section 126 is further configured to apply delays to the digital signals in consideration of distances between the elements of the ultrasound probe 124 and focal points. Thereafter, the beam forming section 126 is further configured to sum the delayed digital signals to form receive-focused signals. In one embodiment, the beam forming section 126 forms a first receive-focused signal based on the first receive signals and a second receive-focused signal based on the second receive signals.

[0022] The ultrasound data acquisition unit 120 further includes an ultrasound data forming section 128, which is coupled to the beam forming section 126. The ultrasound data forming section 128 is configured to form ultrasound data based on the receive-focused signals. In one embodiment, the ultrasound data forming section 128 is configured to form first ultrasound data based on the first receive-focused signal. The first ultrasound data may include radio frequency data. However, the first ultrasound data may not be limited thereto. The ultrasound data forming section 128 may be configured to form second ultrasound data based on the second receive-focused signal. The second ultrasound data may include in-phase/quadrature data (i.e., ensemble data). However, the second ultrasound data may not be limited thereto.

[0023] Referring back to FIG. 1, the processing unit 130, which is coupled to the user input unit 110 and the ultrasound data acquisition unit 120, is configured to form a Doppler signal based on the second ultrasound data. The processing unit 130 is further configured to adaptively perform clutter filtering upon the Doppler signal for each of pixels constructing a Doppler mode image to filter out the clutter signal from the Doppler signal. The processing unit 130 is further configured to form a Doppler mode image based on the Doppler signal with the clutter signal filtered out. Also, the processing unit 130 is further configured to form a B-mode image based on the first ultrasound data.

[0024] FIG. 3 is a block diagram showing an illustrative embodiment of a processing unit. Referring to Fig. 3, the processing unit 130 includes a Doppler signal forming section 131, a coefficient adjusting section 132, a filtering section 133, a noise removing section 134 and an image forming section 135.

[0025] The Doppler signal forming section 131 is configured to perform signal processing such as decimation, modulation and the like, upon the second ultrasound data, which are provided from the ultrasound data acquisition unit 120, to thereby form a Doppler signal corresponding to a plurality of pixels of a Doppler mode image. The Doppler signal includes a blood flow signal caused by the blood flow, a clutter signal caused by the motion of tissues such as cardiac wall, cardiac valve and the like, and a noise signal.

[0026] The coefficient adjusting section 132 is configured to analyze the Doppler signal, which is provided from the Doppler signal forming section 131, to adjust coefficients of a clutter filter for clutter filtering upon the Doppler signal for each pixel.

[0027] The blood flow signal is a signal necessary for forming the Doppler mode image so that the clutter signal and the noise signal have to be removed from the Doppler signal. Amplitude has an order wherein clutter signal > blood flow signal > the noise signal. To efficiently remove the clutter signal, stopband attenuation and stopband width, which are coefficients of the clutter filter, should be appropriately determined. In one embodiment, the stopband attenuation and the stopband width may be determined according to characteristics of the clutter signal. The stopband width is determined by a bandwidth of the clutter signal and the stopband attenuation is determined by amplitude of the clutter signal. However, the stopband attenuation and the stopband width have a trade off in relation. That is, if the stopband attenuation is increased, then the stopband width is decreased. However, if the stopband attenuation is decreased, then the stopband width is increased.

[0028] FIG. 4 is a graph showing a relationship between the stopband attenuation and the stopband width in the clutter filter. As shown in FIG. 4, two curved lines represent frequency responses of different clutter filters having the same cutoff frequency of 0.16 pulse repetition frequency (prf). A solid line represents a frequency response of a clutter filter having stopband attenuation of 80 dB and a stopband width of 0.025 prf. Further, a dotted line represents a frequency response of a clutter filter having stop band attenuation of 50 dB and a stopband width of 0.055 prf.

[0029] Also, determining the cutoff frequency, which is another filter coefficient, is an essential process in designing the clutter filter. If the cutoff frequency is relatively low, then a blood flow signal corresponding to a slow speed may be preserved well. On the other hand, if the cutoff frequency is relatively high, then a wider stopband width may be secured while the blood flow signal corresponding to the slow speed is attenuated. This is so that clutter filter performance for removing the clutter signal may be improved. Thus, it is required to appropriately determine the cutoff frequency during the clutter filtering process.

[0030] FIG. 5 is a graph showing a relationship between a cutoff frequency and stopband attenuation for determining

coefficients of the clutter filter. The stopband attenuation is an independent variable and the cutoff frequency is a dependent variable determined according to the stopband attenuation. The coefficient adjusting section 132 is configured to determine the cutoff frequency and the stopband attenuation of the clutter filter as the following process.

[0031] The coefficient adjusting section 132 is configured to determine an upper limit and a lower limit of a threshold of the cutoff frequency in consideration of a range for removing the clutter signal. In one embodiment, the coefficient adjusting section 132 is configured to determine a maximum cutoff frequency $CF_{\max}$ for maximally removing the clutter signal as well as to determine a minimum cutoff frequency $CF_{\min}$ for minimally removing the clutter signal to show the blood flow of a relative slow speed, which is desired to observe, in the Doppler mode image, even if a large amount of the clutter signal remains. The maximum cutoff frequency $CF_{\max}$ represents the upper limit of the threshold of the cutoff frequency and the minimum cutoff frequency $CF_{\min}$ represents the lower limit of the threshold.

[0032] In one embodiment, a velocity v of the blood flow may be computed by the following equation.

$$v = \frac{c}{2 \cos \theta} \frac{f_d}{f_o} \quad (1)$$

wherein θ represents an angle between an ultrasound beam and a flowing direction of the blood flow, c is an acoustic velocity, f_d represent a Doppler shift frequency and f_o represents a transmit frequency.

[0033] Assuming that the cutoff frequency is CF_o , a detectable velocity of the blood flow may be computed as the following equation.

$$v = \frac{c}{2 \cos \theta} \frac{CF_o}{f_o} \quad (2)$$

[0034] Thus, if the minimum velocity $V_{\min}$ of the blood flow to be detected is determined, then the minimum cutoff frequency $CF_{\min}$ may be computed as the following equation.

$$CF_{\min} = 2 \cos \theta \cdot f_o \cdot \frac{v_{\min}}{c} \quad (3)$$

[0035] Further, as described above, the maximum cutoff frequency $CF_{\max}$ is determined to maximally remove the clutter signal based on Doppler signal distribution on a frequency domain. Also, the maximum cutoff frequency $CF_{\max}$ may be empirically determined by considering components on the clutter signal.

[0036] The coefficient adjusting section 132 is further configured to determine an upper limit and a lower limit of a threshold of the stopband attenuation according to a power of the Doppler signal. In one embodiment, the coefficient adjusting section 132 is configured to compute a power of the Doppler signal for each pixel. The coefficient adjusting section 132 is also configured to determine a maximum power as maximum stopband attenuation $SBA_{\max}$ and a minimum power as minimum stopband attenuation $SBA_{\min}$. The coefficient adjusting section 132 is configured to determine the maximum stopband attenuation $SBA_{\max}$ as an upper limit of the threshold of the stopband attenuation and to determine the minimum stopband attenuation $SBA_{\min}$ as a lower limit of the threshold of the stopband attenuation.

[0037] Further, the coefficient adjusting section 132 is configured to determine first coordinates and second coordinates on a coordinate system associating the cutoff frequency with the stopband attenuation. The first coordinates are determined by the lower limit of the threshold of the stopband attenuation and the lower limit of the threshold of the cutoff frequency, while the second coordinates are determined by the upper limit of the threshold of the stopband attenuation and the upper limit of the threshold of the cutoff frequency.

[0038] The coefficient adjusting section 132 is further configured to set a path between first and second coordinates ($SBA_{\min}$, $CF_{\min}$) and ($SBA_{\max}$, $CF_{\max}$). Referring to FIG. 5, if the path is set like path A, then the blood flow of weak amplitude may be more clearly indicated while the performance of removing the clutter signal is degraded. If the path is set like path C, then a high performance of removing the clutter signal is expected. However, the blood flow signal of weak amplitude may be attenuated so that loss of information on the blood flow may be increased. Thus, an appropriate path may be close to path B at which the cutoff frequency and the stopband attenuation are proportional to each other.

As for the path B, the stopband width may be a constant form at each cutoff frequency. Also, a more appropriate path may be set by using empirical methods.

[0039] The coefficient adjusting section 132 is configured to set the stopband attenuation for each pixel according to amplitude of the clutter signal contained in the Doppler signal, which is provided from the Doppler signal forming section 131. The coefficient adjusting section 132 is configured to compute the cutoff frequency for each pixel corresponding to the stopband attenuation for each pixel based on the proportional path set between the first coordinates (SBA_{min} , CF_{min}) and the second coordinates (SBA_{max} , CF_{max}). The coefficient adjusting section 132 is configured to adjust the cutoff frequency of the clutter filter based on the computed cutoff frequencies.

[0040] In one embodiment, the coefficient adjusting section 132 is configured to be at least one of the filter coefficients of the clutter filter such as cutoff frequency and stopband attenuation in response to the second user request, which is provided by the user input unit 110.

[0041] The filtering section 133 is configured to perform clutter filtering upon the Doppler signal for each pixel by using the stopband attenuation and the cutoff frequency, which have been adjusted for each pixel in the coefficient adjusting section 132, to remove the clutter signal therefrom.

[0042] The noise removing section 134 is configured to set a predetermined power threshold to remove a noise signal from the Doppler signal in which the clutter signal has been filtered out. In such a case, if the filtering section 133 is configured to decrease the amplitude of the clutter signal instead of completely removing the clutter signal during the clutter filter, then the clutter signal may be removed together with the noise signal in the noise removing section 134.

[0043] The image forming section 135 is configured to form a Doppler mode image by using the Doppler signal in which the clutter signal and the noise signal have been removed. The image forming section 135 may be configured to perform various processing such as scan conversion and the like to form the Doppler mode image.

[0044] Referring back to FIG. 1, the display unit 140, which is coupled to the processing unit 130, is configured to display the Doppler mode image. The display unit 140 may include at least one of a cathode ray tube display, a liquid crystal display, an organic light emit diode display and the like.

[0045] In another embodiment, there is provided a computer-readable storage medium storing instructions that, when executed by a computer, cause the computer to provide a method of spatially compounding ultrasound images based on a plurality of ultrasound frame data sets acquired from a target object and at different steering angles of scan lines in an ultrasound system, the method comprising: setting a plurality of masks corresponding to the respective frames based on the plurality of ultrasound frame data sets for removing seam artifact to form a plurality of mask images corresponding to the respective frames; forming a plurality of ultrasound images corresponding to the plurality of frames based on the plurality of frame data sets; and spatially compounding the plurality of ultrasound image based on the plurality of mask images to form an ultrasound spatial compound image.

[0046] Although embodiments have been described with reference to a number of illustrative embodiments thereof, it should be understood that numerous other modifications and embodiments can be devised by those skilled in the art that will fall within the scope of the principles of this disclosure. More particularly, numerous variations and modifications are possible in the component parts and/or arrangements of the subject combination arrangement within the scope of the disclosure, the drawings and the appended claims. In addition to variations and modifications in the component parts and/or arrangements, alternative uses will also be apparent to those skilled in the art.

Claims

1. An ultrasound system, comprising:

an ultrasound data acquisition unit configured to transmit ultrasound signals to a target object and receive ultrasound echoes reflected from the target object to thereby acquire ultrasound data; and
a processing unit configured to form a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data, the processing unit being further configured to adjust coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

2. The ultrasound system of Claim 1, wherein the processing unit includes:

a coefficient adjusting section configured to analyze the characteristics of the Doppler signal for each of the pixels to adjust the coefficients of the clutter filter;
a filtering section configured to perform the clutter filtering upon the Doppler signal for each of the pixels by using the adjusted coefficients to remove the clutter signal from the Doppler signal; and
a noise removing section configured to set a predetermined power threshold to remove a noise signal from the

Doppler signal with the clutter signal filtered out.

3. The ultrasound system of Claim 2, wherein the coefficients include a stopband attenuation and a cutoff frequency.

4. The ultrasound system of Claim 3, wherein the coefficient adjusting section is configured to set an upper limit and a lower limit of a threshold of the cutoff frequency based on a range for removing the clutter signal, and wherein the coefficient adjusting section is configured to set an upper limit and a lower limit of a threshold of the stopband attenuation based on a power of the Doppler signal.

5. The ultrasound system of Claim 4, wherein the coefficient adjusting section is configured to set a maximum cutoff frequency to filter out the clutter signal as the upper limit of the threshold of the cutoff frequency and a minimum cutoff frequency to filter out the clutter signal as the lower limit of the threshold of the cutoff frequency, and wherein the coefficient adjusting section is configured to set a maximum power of the Doppler signal as the upper limit of the threshold of the stopband attenuation and a minimum power of the Doppler signal as the lower limit the threshold of the stopband attenuation.

6. The ultrasound system of Claim 5, wherein the coefficient adjusting section is configured to determine first coordinates and second coordinates on a coordinate system associating the cutoff frequency with the stopband attenuation and set a proportional path between the first and second coordinates, wherein the stopband attenuation is an independent variable and the cutoff frequency is a dependent variable, and wherein the first coordinates are determined by the lower limit of the threshold of the stopband attenuation and the lower limit of the threshold of the cutoff frequency and the second coordinates are determined by the upper limit of the threshold of the stopband attenuation and the upper limit of the threshold of the cutoff frequency.

7. The ultrasound system of Claim 6, wherein the coefficient adjusting section is configured to determine the stopband attenuation based on amplitude of the clutter signal and to determine a cutoff frequency corresponding to the determined stopband attenuation on the proportional path to adjust the cutoff frequency of the clutter filter.

8. A method of adaptively performing clutter filtering, comprising:

- a) acquiring ultrasound data indicative of a target object; and
- b) forming a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data; and
- c) adjusting coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

9. The method of Claim 8, wherein the step c) includes:

- c1) analyzing the characteristics of the Doppler signal for each of the pixels to adjust the coefficients of the clutter filter;
- c2) performing the clutter filtering upon the Doppler signal for each of the pixels by using the adjusted coefficients to remove the clutter signal from the Doppler signal; and
- c3) setting a predetermined power threshold to remove a noise signal from the Doppler signal with the clutter signal filtered out.

10. The method of Claim 9, wherein the coefficients include a stopband attenuation and a cutoff frequency.

11. The method of Claim 10, wherein the step c1) includes:

- setting an upper limit and a lower limit of a threshold of the cutoff frequency based on a range for removing the clutter signal; and
- setting an upper limit and a lower limit of a threshold of the stopband attenuation based on a power of the Doppler signal.

12. The method of Claim 11, wherein the step c1) includes:

- determining a maximum cutoff frequency to filter out the clutter signal as the upper limit of the threshold of the cutoff frequency;

determining a minimum cutoff frequency to filter out the clutter signal as the lower limit of the threshold of the cutoff frequency;
determining a maximum power of the Doppler signal as the upper limit of the threshold of the stopband attenuation; and
5 determining a minimum power of the Doppler signal as the lower limit the threshold of the stopband attenuation.

13. The method of Claim 12, wherein the step c1) further includes:

10 determining first coordinates and second coordinates on a coordinate system associating the cutoff frequency with the stopband sttenuation; and
setting a proportional path between the first and second coordinates,
wherein the stopband attenuation is an independent variable and the cutoff frequency is a dependent variable, and
15 wherein the first coordinates are determined by the lower limit of the threshold of the stopband attenuation and the lower limit of the threshold of the cutoff frequency and the second coordinates are determined by the upper limit of the threshold of the stopband attenuation and the upper limit of the threshold of the cutoff frequency.

14. The method of Claim 14, wherein the step c1) further includes:

20 determining the stopband attenuation based on amplitude of the clutter signal; and
determining a cutoff frequency corresponding to the determined stopband attenuation on the proportional path to adjust the cutoff frequency of the clutter filter.

15. A computer-readable storage medium storing instructions that, when executed by a computer, cause the computer to provide a method of adaptively performing clutter filtering upon in an ultrasound system, the method comprising:

25 a) acquiring ultrasound data indicative of a target object; and
b) forming a Doppler signal corresponding to each of a plurality of pixels constructing a Doppler mode image based on the ultrasound data; and
30 c) adjusting coefficients of a clutter filter based on characteristics of the Doppler signal for each of the pixels for performing clutter filtering upon the Doppler signal.

FIG. 1




FIG. 2




FIG. 3




FIG. 4





FIG. 5





EUROPEAN SEARCH REPORT

Application Number
EP 11 17 0018

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
X	WO 99/58061 A1 (KONINKL PHILIPS ELECTRONICS NV [NL]; PHILIPS SVENSKA AB [SE]) 18 November 1999 (1999-11-18) * abstract * * page 3, line 10 - page 6, line 5; figures 1,4 * * page 2, line 13 - line 29 *	1-15	INV. G01S15/89 A61B8/06
X	YOO Y M ET AL: "Adaptive clutter filtering for ultrasound color flow imaging", ULTRASOUND IN MEDICINE AND BIOLOGY, NEW YORK, NY, US, vol. 29, no. 9, 1 September 2003 (2003-09-01), pages 1311-1320, XP004463713, ISSN: 0301-5629, DOI: 10.1016/S0301-5629(03)01014-7 * abstract * * page 1312, left-hand column, paragraph 3 * * page 1314, right-hand column, paragraph 2 - page 1316, left-hand column, paragraph 2; figure 5 *	1,2,8,9,15	TECHNICAL FIELDS SEARCHED (IPC) G01S A61B
X	EP 2 103 954 A1 (MEDISON CO LTD [KR]) 23 September 2009 (2009-09-23) * abstract * * paragraphs [0019] - [0021], [0028]; figures 3,4 *	1,8,15	
X	KR 2000 0073096 A (MEDISON CO LTD [KR]) 5 December 2000 (2000-12-05) * abstract *	1,8	
The present search report has been drawn up for all claims			
Place of search The Hague		Date of completion of the search 23 September 2011	Examiner Daoukou, Eleni
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

 1
EPO FORM 1503 03.82 (P04C01)



EUROPEAN SEARCH REPORT

Application Number
EP 11 17 0018

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
X	EP 0 316 200 A2 (HEWLETT PACKARD CO [US]) 17 May 1989 (1989-05-17) * column 6, line 2 - line 33; figures 3,4 * * column 6, line 57 - column 7, line 35; figures 2a,2b *	1-5,8-11	
A	EP 0 795 296 A1 (ADVANCED TECH LAB [US]) 17 September 1997 (1997-09-17) * page 4, line 12 - page 5, line 18; figures 4-7 *	1-15	
A	US 2003/073903 A1 (SATO TAKESHI [JP]) 17 April 2003 (2003-04-17) * paragraphs [0032], [0051] - [0056], [0112]; figures 2,3,6,10 *	1-15	
A	US 5 800 357 A (WITT JEROME F [US] ET AL) 1 September 1998 (1998-09-01) * column 3, line 41 - column 4, line 29; figures 2,3 *	6,7,13, 14	
A	HOEKS A P G ET AL: "An efficient algorithm to remove low frequency Doppler signals in digital Doppler systems", ULTRASONIC IMAGING, DYNAMEDIA INC., SILVER SPRING, MD, US, vol. 13, no. 2, 1 April 1991 (1991-04-01), pages 135-144, XP023046551, ISSN: 0161-7346, DOI: 10.1016/0161-7346(91)90080-2 [retrieved on 1991-04-01] * page 139, paragraph 3 - page 140, paragraph 1; figure 1 *	6,7,12, 13	
The present search report has been drawn up for all claims			TECHNICAL FIELDS SEARCHED (IPC)
Place of search The Hague		Date of completion of the search 23 September 2011	Examiner Daoukou, Eleni
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

 1
EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 11 17 0018

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

23-09-2011

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9958061	A1	18-11-1999	DE 69934649 T2 25-10-2007
		EP 0996364 A1 03-05-2000	
		JP 11342130 A 14-12-1999	
		NO 992323 A 15-11-1999	
		US 6036643 A 14-03-2000	
EP 2103954	A1	23-09-2009	JP 2009226218 A 08-10-2009
		KR 20090100657 A 24-09-2009	
		US 2009240153 A1 24-09-2009	
KR 20000073096	A	05-12-2000	NONE
EP 0316200	A2	17-05-1989	DE 3883484 D1 30-09-1993
		DE 3883484 T2 24-03-1994	
		JP 1164355 A 28-06-1989	
		JP 2738939 B2 08-04-1998	
		US 4850364 A 25-07-1989	
EP 0795296	A1	17-09-1997	AT 268570 T 15-06-2004
		DE 69729400 D1 15-07-2004	
		DE 69729400 T2 16-06-2005	
		JP 10005225 A 13-01-1998	
		NO 971106 A 15-09-1997	
		US 5669385 A 23-09-1997	
US 2003073903	A1	17-04-2003	JP 2003102726 A 08-04-2003
US 5800357	A	01-09-1998	NONE

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- KR 1020100057426 [0001]

专利名称(译)	超声系统中的自适应杂波滤波		
公开(公告)号	EP2397867A1	公开(公告)日	2011-12-21
申请号	EP2011170018	申请日	2011-06-15
[标]申请(专利权)人(译)	三星麦迪森株式会社		
申请(专利权)人(译)	三星MEDISON CO. , LTD.		
当前申请(专利权)人(译)	三星MEDISON CO. , LTD.		
[标]发明人	KWAK HAN LEE JAE KEUN KIM JONG SIK		
发明人	KWAK, HAN LEE, JAE KEUN KIM, JONG SIK		
IPC分类号	G01S15/89 A61B8/06		
CPC分类号	A61B8/06 G01S15/8981		
代理机构(译)	SCHMID , WOLFGANG		
优先权	1020100057426 2010-06-17 KR		
其他公开文献	EP2397867B1		
外部链接	Espacenet		

摘要(译)

公开了用于在超声系统中自适应地执行杂波滤波的实施例。在一个实施例中，超声系统包括：超声数据获取单元，被配置为将超声信号发送到目标对象并接收从目标对象反射的超声回波，从而获取超声数据；处理单元，被配置为基于超声数据形成与构成多普勒模式图像的多个像素中的每一个相对应的多普勒信号，以及基于多普勒信号的每个特性调整杂波滤波器的系数。用于对多普勒信号执行杂波滤波的像素。

FIG. 1

