



US007824334B2

(12) **United States Patent**
Sato

(10) **Patent No.:** **US 7,824,334 B2**
(45) **Date of Patent:** **Nov. 2, 2010**

(54) **ULTRASONOGRAPH AND METHOD AND PROGRAM FOR GENERATING ULTRASONOTOMOGRAPHIC IMAGE**

2002/0006230 A1 * 1/2002 Enomoto 382/261
2002/0094115 A1 * 7/2002 Ogawa 382/128
2002/0169377 A1 * 11/2002 Khairkahan et al. 600/433
2004/0073112 A1 4/2004 Azuma et al.

(75) Inventor: **Yoshiaki Sato**, Kanagawa (JP)

OTHER PUBLICATIONS

(73) Assignee: **FUJIFILM Corporation** (JP)

Hiroya Ozawa, "Staging of Esophagus Cancer With Fine Probe Ultrasonic Endoscope", Digestive Endoscopy, vol. 14, No. 5, 2002, pp. 583-588.

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 1350 days.

* cited by examiner

(21) Appl. No.: **11/312,466**

Primary Examiner—Long V Le

Assistant Examiner—Joel F Brutus

(22) Filed: **Dec. 21, 2005**

(74) *Attorney, Agent, or Firm*—Sughrue Mion, PLLC

(65) **Prior Publication Data**

US 2006/0140465 A1 Jun. 29, 2006

(30) **Foreign Application Priority Data**

Dec. 24, 2004 (JP) 2004-373947
Jun. 7, 2005 (JP) 2005-167145

(51) **Int. Cl.**
A61B 8/00 (2006.01)

(52) **U.S. Cl.** **600/437; 600/407**

(58) **Field of Classification Search** **600/437, 600/407**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,644,662 A * 7/1997 Vuylsteke 382/302
5,708,693 A 1/1998 Aach et al.

(57) **ABSTRACT**

An ultrasonograph is provided with a frequency component adjuster that adjusts spatial frequency components of original image data RAW_0 of an ultrasonotomographic image. The frequency component adjuster is constituted of an unsharp image data generator, a subtraction circuit, a weighting circuit, an integration circuit, a multiplication circuit and an addition circuit. The unsharp image data generator circuit generates unsharp image data RAW_i ($i=1$ to 5) by reducing the spatial frequency components of the original image data RAW_0 in five steps. The subtraction circuit generates differential image data ΔRAW_j ($j=1$ to 4) by subtracting the unsharp image data RAW_1 from RAW_{i-1} . The weighting circuit weights the differential image data ΔRAW_j by multiplying them by respective coefficients k_j ($-1 < k_j < 1$). The integration circuit integrates the differential image data ΔRAW_j to generate adjusted image data RAW_En . The addition circuit adds the adjusted image data RAW_En to the original image data RAW_0 to generate output image data RAW_out .

62 Claims, 10 Drawing Sheets




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 6




FIG. 5




FIG. 7




FIG.8




FIG.9




FIG. 10




FIG. 11





FIG. 12



1

ULTRASONOGRAPH AND METHOD AND PROGRAM FOR GENERATING ULTRASONOTOMOGRAPHIC IMAGE

FIELD OF THE INVENTION

The present invention relates to an ultrasonograph that generates ultrasonotomographic images from echo signals received on an ultrasonic probe and displays the ultrasonotomographic images. The present invention relates also to a method of generating ultrasonotomographic images from echo signals received on an ultrasonic probe, and to a generator program for generating ultrasonotomographic images.

BACKGROUND ARTS

Medical diagnosis that utilizes ultrasound imaging has recently been widely used in medical fields. The ultrasonic image is obtained by emitting ultrasonic wave from an ultrasonic probe toward a necessary body part and detecting ultrasonic echo from the body part as electric echo signals by use of an ultrasound observing device that is connected to the ultrasonic probe through a connector. It is also possible to obtain an ultrasonotomographic image by scanning with the ultrasonic wave.

As a concrete example of medical diagnosis utilizing ultrasound imaging, staging of esophagus cancer or stomach cancer based on ultrasonotomographic images has been disclosed, for example, from "Staging Of Esophagus Cancer With Fine Probe Ultrasonic Endoscope" by Hiroya OZAWA in DIGESTIVE ENDOSCOPE Vol. 14, No. 5, 2002. In this type of diagnosis, medical treatment for the patient is decided depending upon invasion degree of cancer especially into the sub mucous tissues, which are divided into three submucous tissue (sm) layers, as shown in FIG. 12.

However, because the mucosal (m) layer as laying on the muscularis mucosae (mm) and all the submucous tissue layers give rise to very strong high-echo that can often cause chroma clip in highlight range, that is, detail is lost or bleached out in high luminance range of subsequent ultrasonotomographic image. As a result, the muscularis mucosae and the three layered structure of the submucous tissues, which is referred to for checking if the cancer metastasizes to the lymph nodes or not, become indefinite on the image, so that it is hardly possible to make adequate diagnosis.

Meanwhile, an X-ray inspector has been suggested in U.S. Pat. No. 5,708,693 wherein an input image is decomposed into several images of different frequency bands. The images of different frequency bands are filtered through sequential statistic value filtering, and the filtered images are composed to obtain an output image. This is for the sake of reducing noises from the X-ray radiograph. Also an ultrasonic imaging device has been suggested in United States Patent Application Publication no. US2004/0073112, wherein structure-enhanced image data and texture-enhanced image data are extracted from an ultrasonotomographic image, and these image data are synthesized after being weighted respectively. In the structure-enhanced image data, the structure of living body tissues is enhanced. In the texture enhanced image data, texture pattern resulting from properties of living body tissues is enhanced.

Indeed the prior art disclosed in JP-A 10-505443 can reduce the noises from the X-ray radiograms, but data on details of the images, such as contours, remain as they are. The prior art disclosed in United States Patent Application Publication no. US2004/0073112 is designed to improve image quality by balancing in the image between the structure

2

of the living body tissues and the texture resulting from the properties of the living body tissues. Therefore, both of these prior arts cannot hold down the bleaching in images of the mucosal layer and the submucous tissue layer.

Ordinary image processing, such as gain control and contrast control, may be useful for holding down the occurrence of the chroma clip in highlight range to some extent. But with such ordinary image processing, images of deeper layers of the living body, which are originally darker than other portions, would be more darkened together with other portions, causing chroma clip in shadow range. As a result, details are lost or blacked out in low luminance range of the subsequent image, so that the ultrasonic image as the whole becomes difficult to diagnose.

SUMMARY OF THE INVENTION

In view of the foregoing, a primary object of the present invention is to provide an ultrasonograph that can prevent chroma clip in both highlight and shadow ranges of ultrasonotomographic images and thus allows accurate diagnosis.

To achieve the above and other objects, an ultrasonograph of the present invention comprises an ultrasonic probe that scans a living body with ultrasonic wave and receives ultrasonic echo to output echo signals; a device for generating original image data RAW_0 of an ultrasonotomographic image by digitalizing the echo signals; a frequency component adjusting device for adjusting spatial frequency components of the original image data so as to avoid chroma clip in both highlight and shadow ranges of the ultrasonotomographic image; and a displaying device for displaying the ultrasonotomographic image based on output image data from the frequency component adjusting device.

According to a preferred embodiment, the frequency component adjusting device divides the spatial frequency components of the original image data RAW_0 into low frequency components including direct current components and other alternating current components, and makes the adjustment on the alternating current components and/or the low frequency component including direct current components.

More specifically, the frequency component adjusting device comprises an unsharp image data generating device for generating unsharp image data RAW_i ($i=1$ to N , $N=a$ positive integer) by reducing the spatial frequency components of the original image data RAW_0 in N steps; a subtraction device subtracting the unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$); a weighting device for weighting the differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of the differential image data ΔRAW_j ; an integration device integrating the weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by the coefficients k_j ; and an addition device adding the adjusted image data RAW_En to the original image data RAW_0 to generate the output image data RAW_out .

Among the coefficients k_j , at least one represented by k_{N-1} has the smallest value and the values of the coefficients k_j increases linear-functionally as the number j decreases, and gradient of the linear-functional curve of the coefficients k_j is revisable. It is also possible to decide which of the coefficients k_j has to have the largest value, on the assumption that the coefficient k_{N-1} is the smallest.

According to another embodiment, the frequency component adjusting device comprises an unsharp image data generating device for generating unsharp image data RAW_1 by

reducing the spatial frequency components of the original image data RAW_0 ; a device for generating biased image data RAW_{img} from the unsharp image data RAW_1 with reference to a biasing table that extracts data of designated luminance ranges from the unsharp image data RAW_1 ; and a generating device adding said biased image data RAW_{img} to said original image data RAW_0 or subtracting said biased image data RAW_{img} from said original image data RAW_0 to generate said output image data RAW_{out} .

According to a further embodiment, the frequency component adjusting device comprises an unsharp image data generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of the original image data RAW_0 in N steps; a subtraction device subtracting the unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$); a weighting device for weighting the differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of the differential image data ΔRAW_j ; an integration device integrating the weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by the coefficients k_j ; a device for generating biased image data RAW_{img} from the unsharp image data RAW_i with reference to a biasing table that extracts data of designated luminance ranges from the unsharp image data RAW_i ; and an generating device adding said adjusted image data RAW_En to said original image data RAW_0 , and adding or subtracting said biased image data RAW_{img} to generate said output image data RAW_{out} that is finally output as said ultrasonotomographic image.

According to a preferred embodiment, the frequency component adjusting device further comprises a multiplication device for multiplying the adjusted image data RAW_En by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of the adjustment of the spatial frequency components of the original image data RAW_0 on the output image data RAW_{out} .

A method of generating an ultrasonotomographic image comprising steps of scanning a living body with ultrasonic wave to detect echo signals; generating original image data of an ultrasonotomographic image of the living body by digitalizing the echo signals; and adjusting spatial frequency components of the original image data so as to avoid chroma clip in both highlight and shadow ranges of the ultrasonotomographic image.

The adjusting step preferably comprises steps of dividing the spatial frequency components of the original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and adjusting the alternating current components and/or the low frequency components including direct current components.

Specifically, the adjusting step comprises steps of generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of the original image data RAW_0 in N steps; subtracting the unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$); weighting the differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of the differential image data ΔRAW_j ; integrating the weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by the coefficients k_j ; and adding the adjusted image data RAW_En to the original image data RAW_0 to generate output image data RAW_{out} that is finally output as the ultrasonotomographic image.

According to another embodiment, the adjusting step comprises steps of generating unsharp image data RAW_1 by reducing the spatial frequency components of the original image data RAW_0 ; generating biased image data RAW_{img} from the unsharp image data RAW_1 by extracting data of designated luminance ranges from the unsharp image data RAW_1 with reference to a biasing table; and adding said biased image data RAW_{img} to said original image data RAW_0 or subtracting the biased image data RAW_{img} from the original image data RAW_0 to generate the output image data RAW_{out} . In this embodiment, a high luminance range of the unsharp image data RAW_1 is enhanced and a middle luminance range thereof is held down by the biasing table.

According to another embodiment, the adjusting step comprises steps of generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of the original image data RAW_0 in N steps; a subtraction device subtracting the unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$); weighting the differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of the differential image data ΔRAW_j ; integrating the weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by the coefficients k_j ; generating biased image data RAW_{img} from the unsharp image data RAW_i with reference to a biasing table that extracts data of designated luminance ranges from the unsharp image data RAW_i ; and adding said adjusted image data RAW_En to said original image data RAW_0 , and adding or subtracting said biased image data RAW_{img} to generate output image data RAW_{out} that is finally output as said ultrasonotomographic image. In this embodiment, a high luminance range of the unsharp image data RAW_i is held down and a middle luminance range thereof is enhanced by the biasing table.

It is preferable to multiply the adjusted image data RAW_En by a coefficient Ka ($0 \leq Ka \leq 1$) to decide a degree of influence of the adjustment of the alternating current components of the spatial frequency components of the original image data RAW_0 .

It is more preferable to multiply the biased image data RAW_{img} by a second coefficient Kb ($0 \leq Kb \leq 1$) to decide a degree of influence of the adjustment of the low frequency components including the direct current components of the spatial frequency components of the original image data RAW_0 .

An ultrasonotomographic image generator program for a computer to generate an ultrasonotomographic image is configured to make the computer carry out the above mentioned steps of the inventive method.

Since the spatial frequency components of the original image data of the ultrasonotomographic image are so adjusted as to avoid chroma clip in both highlight and shadow ranges of the ultrasonotomographic image, accurate diagnosis is possible based on the displayed ultrasonotomographic image.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects and advantages will be more apparent from the following detailed description of the preferred embodiments when read in connection with the accompanied drawings, wherein like reference numerals designate like or corresponding parts throughout the several views, and wherein:

FIG. 1 is a schematic diagram illustrating an ultrasonograph according to an embodiment of the present invention;

FIG. 2 is a block diagram illustrating an interior of the ultrasonograph of FIG. 1;

FIG. 3 is a block diagram illustrating an interior of a frequency component adjuster of the ultrasonograph;

FIG. 4 is a graph illustrating variations in weighting coefficients for differential image data;

FIG. 5 is a flowchart illustrating an operation sequence of the ultrasonograph;

FIG. 6 is a graph illustrating another example of variations in weighting coefficients for differential image data;

FIG. 7 is a block diagram illustrating a frequency component adjuster according to another embodiment of the present invention;

FIG. 8 is a graph illustrating a content of a biasing table;

FIG. 9 is a graph illustrating a content of a biasing table according to another embodiment of the present invention;

FIG. 10 is a block diagram illustrating a frequency component adjuster according to still another embodiment of the present invention;

FIG. 11 is a block diagram illustrating an interior of the ultrasonograph according to another embodiment of the present invention; and

FIG. 12 is an enlarged sectional view illustrating tissues of stomach wall.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

FIG. 1 shows an ultrasonograph 2 that is mainly constituted of an ultrasonic endoscope 10, an ultrasonic observation device 11 and a not-shown light source. The ultrasonic endoscope 10 is provided with an inserting section 12 inserted into a living body, a handling section 13 coupled to a base end of the inserting portion 12, a connecting cord 14 connecting the ultrasonic endoscope 10 to the ultrasonic observation device 11, and an universal cord 15 connecting the ultrasonic endoscope 10 to the light source. The handling section 13 is provided with a clamping port 16 for accepting a tool for medical treatment. The inserting portion 12 has a tip portion 12a in which ultrasonic transducers 17 and imaging elements 18 of an imaging device are mounted, see FIG. 2.

The light source supplies illumination light through the universal cord 15 to the ultrasonic endoscope 10. The illumination light is projected toward a necessary part of the living body through an illumination window of the tip 12a. The tip 12a is provided with a not-shown observation window that has an objective optical system for forming an optical image of the body part to observe on the imaging device 18. The optical image taken through the imaging device 18 is displayed on a not-shown endoscope monitor that is specifically used for displaying optical images.

The ultrasonic endoscope 10 is a kind of intra-cavity diagnostic ultrasonic probe that scans the necessary part with ultrasonic wave from the ultrasonic transducer 17, to obtain an ultrasonotomographic image of the necessary part that is determined by observing the optical image of the internal body part on the not-shown endoscope monitor. For example, the ultrasonic endoscope 10 is of a linear scanning type, a convex scanning type, a sector scanning type or a radial scanning type. The ultrasonotomographic image obtained through the ultrasonic endoscope 10 is displayed on a monitor 19 of the ultrasonic observation device 11.

As shown in FIG. 2, the whole operation of the ultrasonic observation device 11 is controlled by a CPU 20. The CPU 20 is connected to an operating unit 21 having input devices such

as a jog dial 21a, a keyboard or a mouse, and a ROM 23 storing various programs and data, including a generation program 22 for generating the ultrasonotomographic images. As will be described later, the jog dial 21a is used for varying coefficients k_j and K . The CPU 20 controls operations of respective parts of the ultrasonic observation device 11 in response to operation signals entered through the operating unit 21, and executes processing of various kinds in accordance with the generation program 22 read out from the ROM 23.

Under the control of the CPU 20, a sender-receiver circuit 24 manages sending of drive signals to the ultrasonic transducer 17, which are voltage pulses for exiting the ultrasonic transducer 17, as well as receiving of echo signals that are obtained from the living body through the ultrasonic transducer 17. That is, the sender-receiver circuit 24 controls timing of switching of these signals and selects the ultrasonic transducer 17 to drive.

The echo signals received on the sender-receiver circuit 24 is fed to an A/D converter 25, which converts the echo signals into a digital form, and outputs them to a buffer memory 26. The buffer memory 26 temporarily stores the digitalized echo signals, i.e. original image data RAW_0 , see FIG. 3.

A frequency component adjuster 27 adjusts spatial frequency components of the original image data RAW_0 . As shown in FIG. 3, the frequency component adjuster 27 is constituted of an unsharp image data generator 40, a subtraction circuit 41, a weighting circuit 42, an integration circuit 43, a multiplication circuit 44 and an addition circuit 45.

The unsharp image data generator circuit 40 reads out the original image data RAW_0 from the buffer memory 26, and generates unsharp image data RAW_i ($i=1$ to 5) by reducing the spatial frequency components of the original image data RAW_0 in five steps. Concretely, the unsharp image data generator circuit 40 subjects the original image data RAW_0 to thinning or pixel-skipping and filtration through a Nyquist filter, to generate first unsharp image data RAW_1 whose resolution and size are half the original ones. Next, the first unsharp image data RAW_1 is subjected to the same processes as the original image data RAW_0 , to get second unsharp image data RAW_2 whose resolution and size are half the first unsharp image data RAW_1 . Repeating the same processes as above, third to fifth unsharp image data RAW_3 to RAW_5 are generated. Accordingly, the unsharp image data RAW_i become less sharper as the number "i" increases.

The subtraction circuit 41 generates differential image data ΔRAW_j ($j=1$ to 4). In the subtraction circuit 41, the unsharp image data RAW_i , which is generated from the unsharp image data generator circuit 40, is subjected to a smoothing process, whereby the unsharp image data RAW_i is interpolated with thinned data to recover the same size as the unsharp image data RAW_{i-1} , and then the data RAW_i is subtracted from the data RAW_{i-1} , to get the differential image data ΔRAW_j .

Provided that f_i represents the spatial frequency components of the respective image data RAW_i , including the original image data RAW_0 , spatial frequency components Δf_j of the differential image data ΔRAW_j can be held approximately equal to a value $(f_i - f_{i-1})$. Therefore, the differential image data ΔRAW_j can be held as data groups that are obtained by dividing the spatial frequency components of the original image data RAW_0 by a given frequency band width.

The weighting circuit 42 weights the differential image data ΔRAW_j by multiplying them by coefficients k_j ($-1 < k_j < 1$), which are prepared for the respective differential image data ΔRAW_j . As shown in FIG. 4, the coefficient k_4 for the fourth differential image data ΔRAW_4 is minus 0.80, that

is the smallest among the coefficients k_j , and the coefficients k_j increase linearly functionally as the number "j" decreases.

The gradient of the coefficients k_j can be modified by turning the jog dial **21a** of the operating unit **21**. By turning the jog dial **21a** clockwise, as shown by a chain-dotted line in FIG. 2, the coefficients k_0 to k_3 are shifted upward while keeping the coefficient k_4 as a reference point, so that the gradient of the coefficients k_j is made steeper as shown by a chain-dotted line in FIG. 4. As a result, a subsequent ultrasonotomographic image will become a hard gradation image whose luminance vary relatively largely.

On the contrary, by turning the jog dial **21a** counterclockwise, as shown by a phantom line in FIG. 2, the coefficients k_0 to k_3 are shifted downward while keeping the coefficient k_4 as the reference point, so that the gradient of the coefficients k_j is made gentler as shown by a phantom line in FIG. 4. As a result, a subsequent ultrasonotomographic image will become a soft gradation image whose luminance variations are relatively small.

Referring back to FIG. 3, the integration circuit **43** makes the differential image data ΔRAW_j as weighted by the weighting circuit **42** have the same size as the original image data RAW_0 , and then integrates the differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by the coefficients k_j .

The multiplication circuit **44** multiplies the adjusted image data RAW_En , as generated from the integration circuit **43**, by a coefficient K ($0 \leq K \leq 1$). The coefficient K is for deciding final degree of influence of the spatial frequency component adjustment on the original image data RAW_0 by the frequency component adjuster **27**. If the coefficient K is zero, the adjustment by the frequency component adjuster **27** results no effect, so the original image data RAW_0 is output as output image data RAW_out , which is output from the frequency component adjuster **27** as set forth in more detail below. If, on the other hand, the coefficient K is 1, the adjustment by the frequency component adjuster **27** is wholly reflected in the output image data RAW_out . The coefficient K has a value that is variable by turning the jog dial **21a**, like as the coefficients k_j .

The addition circuit **45** adds the original image data RAW_0 to the adjusted image data RAW_En after being multiplied by the coefficient K , to generate the output image data RAW_out , representative of a final ultrasonotomographic image.

Referring back to FIG. 2, a digital scan converter (DSC) **28** converts the output image data RAW_out , which is generated from the addition circuit **45** of the frequency component adjuster **27**, into an image signal of a TV signal scanning format, i.e. a NTSC signal, under the control of the CPU **20**. The NTSC signal is stored in an image memory **29**. A D/A converter **30** reads out the NTSC signal from the image memory **29**, and converts it again into an analog signal. Based on the analog signal from the D/A converter **30**, a monitor **10** displays an ultrasonotomographic image.

Now the operation of the ultrasonograph **2** configured as above will be described with reference to the flow chart of FIG. 5. After powering the ultrasonic observation device **11** on to activate the generator program **22**, the inserting portion **12** of the ultrasonic endoscope **10** is inserted into a living body, to search for a particular internal body part while observing images taken through the imaging device **18**. When the tip **12a** of the inserting portion **12** reaches the particular internal body part and the operating unit **21** is operated to unfreeze, the drive signals are sent from the sender-receiver circuit **24** to the ultrasonic transducer **17** under the control of

the CPU **20**. The drive signals excite the ultrasonic transducer **17** to emit ultrasonic wave toward the particular internal body part.

After sending the drive signals, the sender-receiver circuit **24** is switched over under the control of the CPU **20**, to receive echo signals that are obtained by the ultrasonic transducer **17** from the internal body part.

The echo signals received on the sender-receiver circuit **24** are digitalized through the A/D converter **25**, and are stored temporarily in the buffer memory **26**. The digitalized echo signals are read out from the buffer memory **26** by the frequency component adjuster **27**.

In the frequency component adjuster **27**, the unsharp image data generator circuit **40** generates the unsharp image data RAW_i by reducing the spatial frequency components of the original image data RAW_0 in five steps. Next, the subtraction circuit **41** makes the unsharp image data RAW_i have the same size as the unsharp image data RAW_{i-1} , and thereafter subtracts the unsharp image data RAW_i from the unsharp image data RAW_{i-1} to generate the differential image data ΔRAW_j .

The weighting circuit **42** weights the differential image data ΔRAW_j by multiplying them by the coefficients k_j . Next, the integration circuit **43** makes the weighted differential image data ΔRAW_j have the same size as the original image data RAW_0 , and then integrates the differential image data ΔRAW_j to generate the adjusted image data RAW_En .

Thereafter, the multiplication circuit **44** multiplies the adjusted image data RAW_En by the coefficient K . Finally, the addition circuit **45** adds the original image data RAW_0 to the adjusted image data RAW_En as being multiplied by the coefficient K , to generate the output image data RAW_out representative of the final ultrasonotomographic image.

The output image data RAW_out is converted into the NTSC signal through the DSC **28**, and is sent to the image memory **29**. Thereafter, the output image data RAW_out is converted again into the analog form through the D/A converter **30**, to be displayed as the ultrasonotomographic image on the monitor **19**.

When the jog dial **21a** is turned clockwise, the gradient of the coefficients k_j is made steeper to output a hard image. On the contrary, when the jog dial **21a** is turned counterclockwise, the gradient of the coefficient k_j is made gentler to output a soft image. When the coefficient K is set at zero by turning the jog dial **21a**, the original image data RAW_0 is output as the output image data RAW_out . On the contrary, when the coefficient K is set at 1, the output image data RAW_out reflects all the results of adjustment by the frequency component adjuster **27**.

According to another embodiment, the coefficients k_j may be variable not only in gradient but also in maximum value. In the embodiment shown in FIG. 6, the maximum value of the coefficients k_j is 0.2, and the coefficient k_j having the maximum value is shifted seriatim from k_0 to k_1 to k_2 as the jog dial **21a** turns. This embodiment is effective to prevent unnecessary enhancement of details of the ultrasonotomographic image if the display range is so narrow that the tissues of the particular internal body part can be seen in detail.

FIG. 7 shows another embodiment of a frequency component adjuster **50**, which is constituted of an unsharp image data generator circuit **51**, a biased image data generator circuit **52**, a multiplication circuit **53** and a subtraction circuit **54**. The frequency component adjuster **50** is designed to obtain ultrasonotomographic images whose low frequency components are held down in high luminance range by a well-known dynamic range compression that is disclosed for example in Japanese Laid-open Patent Application No. 10-75364.

The unsharp image data generator circuit 51 reads out the original image data RAW_0 from the buffer memory 26, to generate unsharp image data RAW_1 by reducing spatial frequency components from the original image data RAW_0 down to a data volume of $1/M$, e.g. $1/2$, of the original, using the same method as described with respect to the unsharp image data generator circuit 40 of FIG. 3.

The biased image data generator circuit 52 makes the unsharp image data RAW_1 recover the same size as the original image data RAW_0 and, thereafter, generates biased image data RAW_{img} with reference to a biasing table 52a. As shown in FIG. 8, the biasing table 52a is for extracting image data in a high luminance range from the unsharp image data RAW_1 , and is designed to output merely those input image data whose luminance is not less than a given threshold value Th.

Referring back to FIG. 7, the multiplication circuit 53 multiplies the biased image data RAW_{img} , which is generated from the biased image data generator circuit 52, by a coefficient K that decides final degree of influence of the adjustment of the spatial frequency components of the original image data RAW_0 by the frequency component adjuster 50, like the multiplication circuit 44 of FIG. 3. The subtraction circuit 54 subtracts the biased image data RAW_{img} as being multiplied by the coefficient K in the multiplication circuit 53, from the original image data RAW_0 to generate output image data RAW_{out} , which is output as a final ultrasonotomographic image from the frequency component adjuster 50.

Like the frequency component adjuster 27 of FIG. 3, the coefficient K has a value variable by turning the jog dial 21a. It is also possible to change the value M that decides the degree of data volume reduction on generating the unsharp image data RAW_1 from the original image data RAW_0 , and the biasing table 52a as well. It is possible to provide a specific operation member for changing the value M or one for changing the biasing table separately from the jog dial 21a.

Unlike the frequency component adjuster 27, the embodiment using the frequency component adjuster 50 does not need to generate five groups of unsharp image data, so that the following differential operation, the weighting with the coefficients k_j and the integration are omitted. Accordingly, the embodiment using the frequency component adjuster 50 simplifies the circuit structure and the processing in comparison with the embodiment using the frequency component adjuster 27. Note that the ultrasonograph 2 using the frequency component adjuster 50 operates fundamentally in the same sequence as shown in FIG. 2, except that the biased image data RAW_{img} is generated. Therefore, the description and illustration of the operation sequence of the embodiment of FIG. 7 will be omitted.

The biasing table 52a may have another characteristic curve as shown in FIG. 9. The curve shown in FIG. 9 is designed to enhance the unsharp image data RAW_1 in a high luminance range and hold it down in a middle luminance range. With the biasing table 52a having the curve shown in FIG. 8, the output image data RAW_{out} will be reduced in the high luminance range from the original image data RAW_0 , so the obtained image can be generally dark. On the other hand, where the biasing table 52a has the curve shown in FIG. 9, the output image data RAW_{out} will be reduced in the high luminance range but enhanced in the middle luminance range. Consequently, the luminance reduction of the output image data RAW_{out} is limited in total.

FIG. 10 shows a further embodiment of a frequency component adjuster 60, which is a combination of the frequency component adjuster 27 of FIG. 3 and the frequency component adjuster 50 of FIG. 7. In the frequency component

adjuster 60, a biased image data generator circuit 67 generates biased image data RAW_{img} from unsharp image data RAW_5 , and multiplication circuits 65 and 68 multiply adjusted image data RAW_{En} and the biased image data RAW_{img} by coefficients K_a and K_b respectively, which correspond to the coefficient K of the above embodiment. An addition circuit 66 adds the adjusted image data RAW_{En} , the biased image data RAW_{img} and original image data RAW_0 to generate output image data RAW_{out} .

Also in this embodiment, it is possible to change the coefficients k_j and K, the value M for data volume reduction, and a biasing table by operating the jog dial 21a, like in the frequency component adjuster 27 of FIG. 3 and the frequency component adjuster 50 of FIG. 7.

The frequency component adjuster 60 is more complicated in circuit structure and processing sequence, but it permits finer adjustment. Although the biased image data RAW_{img} is generated from the unsharp image data RAW_5 in the embodiment of FIG. 10, it is possible to generate the biased image data RAW_{img} from any of other unsharp image data RAW_1 to RAW_4 . Furthermore, the frequency component adjuster 60 adds the biased image data RAW_{img} to generate the output image data RAW_{out} , on the contrary to the frequency component adjuster 50 where the biased imaged data RAW_{img} is subtracted from the original image data RAW_0 to get the output image data RAW_{out} . Therefore, the biasing table used in the biased image data generator circuit 67 has a curve inverted to the curve shown in FIG. 8 or 9, in polarity of the luminance of the output data.

Generally, frequency components of signals consist of low frequency components, including direct current components, and other alternating current components. The same applies to the image signals. Assuming that I , I_{DC} and I_{AC} represent the total image signal, the low frequency components including the direct current components, and the alternating current components respectively, the total image signal I may be expressed as follows:

$$I = I_{DC} + I_{AC}$$

Since the frequency component adjuster 27 carries out the adjustment by weighting the band-divided differential image data ΔRAW_j by the respective coefficients k_j and adding them to the original image data RAW_0 , the low frequency components I_{DC} of the original image data RAW_0 , including the direct current components, are maintained unchanged, whereas other alternating current components I_{AC} are subjected to the adjustment. Accordingly, the adjustment by the frequency component adjuster 27 can be equivalently expressed by the following equation (1), provided that the output image signal obtained as the result of the adjustment is represented by I_{out} :

$$I_{out} = I_{DC} + \beta(I_{AC}) \quad (1)$$

$$\beta(I_{AC}) = \beta_0(I_{AC0}) + \beta_1(I_{AC1}) + \beta_2(I_{AC2}) + \beta_3(I_{AC3}) + \beta_4(I_{AC4}) \quad (2)$$

wherein $\beta(I_{AC})$ corresponds to the adjusted image data RAW_{En} , I_{AC0} to I_{AC4} correspond to the respective differential image data ΔRAW_0 to ΔRAW_4 , and $\beta(\)$ corresponds to the multiplication by the coefficients k_j and K.

Since the frequency component adjuster 50 of FIG. 7 carries out the adjustment by generating the biased image data RAW_{img} from the unsharp image data RAW_1 that has the flow frequency components including the direct current components I_{DC} , and adding it to the original image data RAW_0 , the alternating current components I_{AC} of the original image data RAW_0 are maintained unchanged, whereas the flow frequency components including the direct current components

11

I_{DC} are subjected to the adjustment. Accordingly, the adjustment by the frequency component adjuster 50 can be equivalently expressed by the following equation (3):

$$I_{out} = \alpha(I_{DC}) + I_{AC} \quad (3)$$

wherein $\alpha(I_{DC})$ corresponds to the biased image data RAW_{img} , I_{DC} corresponds to the unsharp image data RAW_1 , and $\alpha(\cdot)$ corresponds to the processing with the biasing table.

The adjustment by the frequency component adjuster 60 shown in FIG. 10 can be equivalently expressed by the following equation (4):

$$I_{out} = \alpha(I_{DC}) + \beta(I_{AC}) \quad (4)$$

It is to be noted that the processing expressed by $\alpha(\cdot)$ and $\beta(\cdot)$ in the equations (1) to (4) may be either the linear processing with the coefficients or the non-linear processing with the table.

Although the equation (1) does not directly express the adjustment by the frequency component adjuster 27, the combination of the equations (1) and (2) is equivalent to the adjustment by the frequency component adjuster 27:

$$I_{out} = I_{DC} + k'_0 \cdot I_{AC0} + k'_1 \cdot I_{AC1} + k'_2 \cdot I_{AC2} + k'_3 \cdot I_{AC3} + k'_4 \cdot I_{AC4}$$

$$I = I_{DC} + I_{AC}$$

$$\begin{aligned} I_{out} &= I - I_{AC} + k'_0 \cdot I_{AC0} + k'_1 \cdot I_{AC1} + k'_2 \cdot I_{AC2} + k'_3 \cdot I_{AC3} + k'_4 \cdot I_{AC4} \\ &= I + (k'_0 - 1) \cdot I_{AC0} + (k'_1 - 1) \cdot I_{AC1} + (k'_2 - 1) \cdot I_{AC2} + (k'_3 - 1) \cdot I_{AC3} + \\ &\quad (k'_4 - 1) \cdot I_{AC4} \\ &= I + k_0 \cdot I_{AC0} + k_1 \cdot I_{AC1} + k_2 \cdot I_{AC2} + k_3 \cdot I_{AC3} + k_4 \cdot I_{AC4} \end{aligned}$$

wherein "I" corresponds to the original image data RAW_0 , and $I_{out} = I$ when $k'_j = 1$ and $k_j = 0$.

In the same way, the equation (3) may be expressed as follows:

$$\begin{aligned} I_{out} &= \alpha(I_{DC}) + I - I_{DC} \\ &= \{\alpha(I_{DC}) - I_{DC}\} + I \\ &= LUT(I_{DC}) + I \end{aligned}$$

wherein $LUT(I_{DC})$ corresponds to the processing with the biasing table, so the equation (3) represents the adjustment by the frequency component adjuster 50.

As described so far, according to the present invention, the frequency component adjuster 27 or 50 or 60 adjusts the spatial frequency components of the original image data RAW_0 for the ultrasonotomographic image so as to avoid chroma clip in both highlight and shadow ranges of the ultrasonotomographic image, so that the ultrasonotomographic image shows details throughout the whole luminance ranges. Consequently, the ultrasonograph 2 of the present invention can extract the muscularis mucosae (mm layer) and the triple-layered structure of the submucous tissue layer (sm layer) of esophagus or stomach wall with higher probability, so it helps improving diagnostic exactness, for example, in examining the degree of invasion for the staging of esophagus cancer or stomach cancer.

In the frequency component adjuster 50 shown in FIG. 7, the biased imaged data RAW_{img} is generated by using the biasing table shown in FIGS. 8 and 9, and the biased imaged data RAW_{img} is subtracted from the original image data RAW_0 at the subtraction circuit 54 to generate output image data RAW_{out} . However, the present invention may be configured to use the biasing table having a curve inverted to the

12

curve shown in FIG. 8 or 9, in polarity of the luminance of the output data, and add the biased imaged data RAW_{img} to the original image data RAW_0 to generate output image data RAW_{out} . Moreover, in the frequency component adjuster 60 shown in FIG. 10, the biased imaged data RAW_{img} is generated by using the biasing table having a curve inverted to the curve shown in FIG. 8 or 9, in polarity of the luminance of the output data, and the biased imaged data RAW_{img} is added to the original image data RAW_0 at the addition circuit 66 to generate output image data RAW_{out} . However, the present invention may be configured to use the biasing table shown in FIGS. 8 & 9, and subtract the biased imaged data RAW_{img} from the original image data RAW_0 to generate output image data RAW_{out} . That is to say, the present invention may be configured to generate output image data RAW_{out} to hold down a high luminance range when the biasing table shown in FIG. 8 is used, or may be configured to generate output image RAW_{out} to hold down a high luminance range and enhance a middle luminance range when the biasing table shown in FIG. 9 is used.

As shown in FIG. 11, it is possible to provide an ultrasonograph 70 with a revising section 71 for revising at least one of the coefficients k_j and K , the value M and the biasing table, depending upon at least one of such data that represent the internal body part to observe, the frequency of the ultrasonic wave from an ultrasonic transducer 17, and a display depth of the ultrasonotomographic image. This embodiment permits obtaining proper ultrasonotomographic images automatically in accordance with conditions of usage of the ultrasonic endoscope 10.

Although the illustrated ultrasonic endoscope 10 is for intra-cavity diagnosis and has the imaging device 18 incorporated therein, the present invention is applicable to an ultrasonograph using a fine ultrasonic probe that has ultrasonic transducers alone, and is put into a clamping port of an electronic endoscope when the probe is used. The present invention is also applicable to a case using an extra-cavity diagnostic ultrasonic probe that is moved on a body surface for obtaining an ultrasonic image.

Thus, the present invention is not to be limited to the above embodiments but, on the contrary, various modifications will be possible without departing from the scope of claims appended hereto.

What is claimed is:

1. An ultrasonograph comprising:

an ultrasonic probe configured to scan a living body with ultrasonic wave and receives ultrasonic echo to output echo signals;

a device for generating original image data RAW_0 of an ultrasonotomographic image by digitalizing said echo signals;

a frequency component adjusting device for adjusting spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image; and

a displaying device for displaying said ultrasonotomographic image based on output image data from said frequency component adjusting device,

wherein said frequency component adjusting device comprises:

an unsharp image data generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_0 in N steps;

a subtraction device subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$);

13

a weighting device for weighting said differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data ΔRAW_j ;
 an integration device integrating said weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by said coefficients k_j ; and
 an addition device adding said adjusted image data RAW_En to said original image data RAW_0 to generate output image data RAW_out that is finally output as said ultrasonotomographic image.

2. An ultrasonograph as claimed in claim 1, wherein said frequency component adjusting device divides the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components and other alternating current components, and makes said adjustment on the alternating current components.

3. An ultrasonograph as claimed in claim 1, further comprising an operating unit that is manipulated to revise respective values of said coefficients k_j .

4. An ultrasonograph as claimed in claim 3, wherein among said coefficients k_j at least one represented by $kN-1$ has the smallest value and the values of said coefficients k_j increases linear-functionally as the number j decreases, and wherein said operating unit is manipulated to change gradient of the linear-functional curve of said coefficients k_j .

5. An ultrasonograph as claimed in claim 3, wherein among said coefficients k_j one represented by $kN-1$ has the smallest value and said operating unit is manipulated to decide which of said coefficients k_j has to have the largest value.

6. An ultrasonograph as claimed in claim 1, further comprising a revising device that revises the values of said coefficients k_j , depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

7. An ultrasonograph as claimed in claim 1, wherein said frequency component adjusting device further comprises a multiplication device for multiplying said adjusted image data RAW_En by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

8. An ultrasonograph as claimed in claim 7, further comprising an operating unit that is manipulated to revise said coefficient K .

9. An ultrasonograph as claimed in claim 7, further comprising a revising device that revises said coefficient K depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

10. An ultrasonograph as claimed in claim 1, wherein said frequency component adjusting device divides the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components and other alternating current components, and adjusts the low frequency components including the direct current components.

11. An ultrasonograph as claimed in claim 10, wherein said frequency component adjusting device holds down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

12. An ultrasonograph as claimed in claim 1, wherein said frequency component adjusting device divides the spatial

14

frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and makes said adjustment on both the low frequency components including the direct current components and the alternating current components.

13. An ultrasonograph as claimed in claim 12, wherein said frequency component adjusting device holds down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

14. An ultrasonograph as claimed in claim 1, wherein said frequency component adjusting device comprises:

an unsharp image data generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_0 in N steps;

a subtraction device subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$);

a weighting device for weighting said differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data ΔRAW_j ;

an integration device integrating said weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by said coefficients k_j ;

a device for generating biased image data RAW_{mg} from said unsharp image data RAW_i with reference to a biasing table that extracts data of designated luminance ranges from said unsharp image data RAW_i ; and

a generating device adding said adjusted image data RAW_En to said original image data RAW_0 , and adding or subtracting said biased image data RAW_{img} to generate said output image data RAW_out .

15. An ultrasonograph as claimed in claim 14, further comprising an operating unit that is manipulated to revise respective values of said coefficients k_j .

16. An ultrasonograph as claimed in claim 15, wherein among said coefficients k_j at least one represented by $kN-1$ has the smallest value and the values of said coefficients k_j increases linear-functionally as the number j decreases, and wherein said operating unit is manipulated to change gradient of the linear-functional curve of said coefficients k_j .

17. An ultrasonograph as claimed in claim 15, wherein among said coefficients k_j one represented by $kN-1$ has the smallest value and said operating unit is manipulated to decide which of said coefficients k_j has to have the largest value.

18. An ultrasonograph as claimed in claim 14, further comprising a revising device that revises the values of said coefficients k_j depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

19. An ultrasonograph as claimed in claim 14, wherein said frequency component adjusting device further comprises a multiplication device for multiplying said adjusted image data RAW_En by a coefficient Ka ($0 \leq Ka \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

20. An ultrasonograph as claimed in claim 19, further comprising an operating unit that is manipulated to revise said coefficient Ka .

15

21. An ultrasonograph as claimed in claim 19, further comprising a revising device that revises said coefficient Ka depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

22. An ultrasonograph as claimed in claim 14, wherein said biasing table is designed to generate output image data RAW_{out} to hold down a high luminance range and enhance a middle luminance range.

23. An ultrasonograph as claimed in claim 14, further comprising an operating unit for changing a volume of data reduction from said original image data RAW_o to generate said unsharp image data RAW_i.

24. An ultrasonograph as claimed in claim 14, further comprising a revising device that revises a volume of data reduction from said original image data RAW_o to generate said unsharp image data RAW_i, and/or said biasing table depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

25. An ultrasonograph as claimed in claim 14, further comprising a multiplication device for multiplying said biased image data RAW_{img} by a coefficient Kb ($0 \leq Kb \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_o on said output image data RAW_{out}.

26. An ultrasonograph as claimed in claim 25, further comprising an operating unit for revising said coefficient Kb.

27. An ultrasonograph as claimed in claim 25, further comprising a revising device that revises said coefficient Kb depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

28. An ultrasonograph as claimed in claim 1, wherein said ultrasonic probe is an intra-cavity diagnostic ultrasonic probe that has an imaging device built therein for taking an optical image of an internal body part.

29. An ultrasonograph comprising:

an ultrasonic probe configured to scan a living body with ultrasonic wave and receives ultrasonic echo to output echo signals;

a device for generating original image data RAW_o of an ultrasonotomographic image by digitalizing said echo signals;

a frequency component adjusting device for adjusting spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image; and

a displaying device for displaying said ultrasonotomographic image based on output image data from said frequency component adjusting device,

wherein said frequency component adjusting device comprises:

an unsharp image data generating device for generating unsharp image data RAW_i by reducing the spatial frequency components of said original image data RAW_o;

a device for generating biased image data RAW_{img} from said unsharp image data RAW_i with reference to a biasing table that extracts data of designated luminance ranges from said unsharp image data RAW_i; and

a generating device adding said biased image data RAW_{img} to said original image data RAW_o or subtracting said biased image data RAW_{img} from said original image

16

data RAW_o to generate said-output image data RAW_{out} that is finally output as said ultrasonotomographic image.

30. An ultrasonograph as claimed in claim 29, wherein said biasing table is designed to generate output image data RAW_{out} to hold down a high luminance range and enhance a middle luminance range.

31. An ultrasonograph as claimed in claim 29, further comprising an operating unit that is manipulated to revise a volume of data reduction from said original image data RAW_o to generate said unsharp image data RAW_i.

32. An ultrasonograph as claimed in claim 29, further comprising a revising device that revises a volume of data reduction from said original image data RAW_o to generate said unsharp image data RAW_i, and/or said biasing table, depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

33. An ultrasonograph as claimed in claim 29, wherein said frequency component adjusting device further comprises a multiplication device for multiplying said biased image data RAW_{img} by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_o on said output image data RAW_{out}.

34. An ultrasonograph as claimed in claim 33, further comprising an operating unit that is manipulated to revise said coefficient K.

35. An ultrasonograph as claimed in claim 33, further comprising a revising device that revises said coefficient K depending upon at least one of those data that represent a body part to observe, a frequency of said ultrasonic wave from said ultrasonic probe, and a display depth of said ultrasonotomographic image.

36. A method of generating an ultrasonotomographic image comprising the steps of:

scanning a living body with ultrasonic wave to detect echo signals;

generating original image data of an ultrasonotomographic image of said living body by digitalizing said echo signals; and

adjusting spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image, wherein said adjusting step comprises steps of:

generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_o in N steps;

subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data Δ RAW_j ($j=0$ to $N-1$);

weighting said differential image data Δ RAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data Δ RAW_j; integrating said weighted differential image data Δ RAW_j to generate adjusted image data RAW_{En} whose spatial frequency components are adjusted by said coefficients k_j ; and

adding said adjusted image data RAW_{En} to said original image data RAW_o to generate output image data RAW_{out} that is finally output as said ultrasonotomographic image.

37. A method as claimed in claim 36, wherein said adjusting step comprises steps of dividing the spatial frequency components of said original image data RAW_o into low frequency components including direct current components,

17

and other alternating current components, and adjusting the alternating current components.

38. A method as claimed in claim 36, wherein respective values of said coefficients k_j are revisable manually or automatically depending upon predetermined factors.

39. A method as claimed in claim 36, further comprising a step of

multiplying said adjusted image data RAW_En by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

40. A method as claimed in claim 36, wherein said adjusting step comprises steps of dividing the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and adjusting the low frequency components including the direct current components.

41. A method as claimed in claim 40, wherein said adjusting step comprises steps of:

generating unsharp image data RAW_1 by reducing the spatial frequency components of said original image data RAW_0 ;

generating biased image data RAW_{img} from said unsharp image data RAW_1 by extracting data of designated luminance ranges from said unsharp image data RAW_1 with reference to a biasing table; and

adding said biased image data RAW_{img} to said original image data RAW_0 or subtracting said biased image data RAW_{img} from said original image data RAW_0 to generate said output image data RAW_out that is finally output as said ultrasonotomographic image.

42. A method as claimed in claim 41, wherein output image data RAW_out to hold down a high luminance range and enhance a middle luminance range by said biasing table is generated.

43. A method as claimed in claim 41, further comprising a step of multiplying said biased image data RAW_{img} by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

44. A method as claimed in claim 40, wherein said adjustment is to hold down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

45. A method as claimed in claim 36, wherein said adjusting step comprises steps of dividing the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and adjusting both the low frequency components including the direct current components and the alternating current components.

46. A method as claimed in claim 45, wherein said frequency component adjusting device holds down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

47. A method of generating an ultrasonotomographic image comprising the steps of:

scanning a living body with ultrasonic wave to detect echo signals;

generating original image data of an ultrasonotomographic image of said living body by digitalizing said echo signals; and

18

adjusting spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image, wherein said adjusting step comprises steps of:

generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_0 in N steps;

a subtraction device subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$);

weighting said differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data ΔRAW_j ;

integrating said weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by said coefficients k_j ;

generating biased image data RAW_{img} from said unsharp image data RAW_i with reference to a biasing table that extracts data of designated luminance ranges from said unsharp image data RAW_i ; and

adding said adjusted image data RAW_En to said original image data RAW_0 , and adding or subtracting said biased image data RAW_{img} to generate output image data RAW_out that is finally output as said ultrasonotomographic image.

48. A method as claimed in claim 47,

wherein output image data RAW_out to hold down a high luminance range and enhance a middle luminance range by said biasing table is generated.

49. A method as claimed in claim 47, further comprising a step of multiplying said adjusted image data RAW_En by a coefficient K_a ($0 \leq K_a \leq 1$) to decide a degree of influence of said adjustment of the alternating current components of the spatial frequency components of said original image data RAW_0 .

50. A method as claimed in claim 47, further comprising a step of multiplying said biased image data RAW_{img} by a coefficient K_b ($0 \leq K_b \leq 1$) to decide a degree of influence of said adjustment of the low frequency components including the direct current components of the spatial frequency components of said original image data RAW_0 .

51. A non-transitory computer readable recording medium having embodied thereon an ultrasonotomographic image generator computer program for executing a method for generating an ultrasonotomographic image from echo signals received on an ultrasonic probe that scans a living body with ultrasonic wave, wherein said method comprises:

generating original image data RAW_0 of an ultrasonotomographic image of said living body by digitalizing said echo signals,

making adjustment on spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image;

generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_0 in N steps;

subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$);

weighting said differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data ΔRAW_j ;

19

integrating said weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by said coefficients k_j ; and

adding said adjusted image data RAW_En to said original image data RAW_0 to generate output image data RAW_out that is finally output as said final ultrasonotomographic image.

52. An ultrasonotomographic image generator program as claimed in claim 51, wherein said program makes said computer divide the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and carry out said adjustment on the alternating current components.

53. An ultrasonotomographic image generator program as claimed in claim 51, wherein said program makes said computer carry out a further step of multiplying said adjusted image data RAW_En by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

54. An ultrasonotomographic image generator program as claimed in claim 51, wherein said program makes said computer divide the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and carry out said adjustment on the low frequency components including the direct current components.

55. An ultrasonotomographic image generator program as claimed in claim 54, wherein said program makes said computer carry out a step of holding down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

56. An ultrasonotomographic image generator program as claimed in claim 51, wherein said program makes said computer divide the spatial frequency components of said original image data RAW_0 into low frequency components including direct current components, and other alternating current components, and carry out said adjustment on both the low frequency components including the direct current components and the alternating current components.

57. An ultrasonotomographic image generator program as claimed in claim 56, wherein said program makes said computer carry out steps of:

generating device for generating unsharp image data RAW_i ($i=1$ to N , N =a positive integer) by reducing the spatial frequency components of said original image data RAW_0 in N steps;

a subtraction device subtracting said unsharp image data RAW_i from one another RAW_{i-1} to generate differential image data ΔRAW_j ($j=0$ to $N-1$);

weighting said differential image data ΔRAW_j by multiplying them by coefficients k_j which are prepared for respective ones of said differential image data ΔRAW_j ; integrating said weighted differential image data ΔRAW_j to generate adjusted image data RAW_En whose spatial frequency components are adjusted by said coefficients k_j ;

generating biased image data RAW_{img} from said unsharp image data RAW_i by extracting data of designated lumi-

20

nance ranges from said unsharp image data RAW_i with reference to a biasing table; and

adding said adjusted image data RAW_En to said original image data RAW_0 , and adding or subtracting said biased image data RAW_{img} to generate output image data RAW_out that is finally output as said ultrasonotomographic image.

58. An ultrasonotomographic image generator program as claimed in claim 57, wherein said program makes said computer carry out a further step of multiplying said adjusted image data RAW_En by a coefficient Ka ($0 \leq Ka \leq 1$) to decide a degree of influence of said adjustment of the alternating current components of the spatial frequency components of said original image data RAW_0 .

59. An ultrasonotomographic image generator program as claimed in claim 57, wherein said program makes said computer carry out a further step of multiplying said biased image data RAW_{img} by a coefficient Kb ($0 \leq Kb \leq 1$) to decide a degree of influence of said adjustment of the low frequency components including the direct current components of the spatial frequency components of said original image data RAW_0 .

60. An ultrasonotomographic image generator program as claimed in claim 56, wherein said program makes said computer carry out a step of holding down variations in luminance totally with respect to the low frequency components including the direct current components of the spatial frequency components.

61. A non-transitory computer readable recording medium having embodied thereon an ultrasonotomographic image generator computer program for executing a method for generating an ultrasonotomographic image from echo signals received on an ultrasonic probe that scans a living body with ultrasonic wave, wherein said method comprises:

generating original image data RAW_0 of an ultrasonotomographic image of said living body by digitalizing said echo signals;

making adjustment on spatial frequency components of said original image data so as to avoid chroma clip in both highlight and shadow ranges of said ultrasonotomographic image,

generating unsharp image data RAW_1 by reducing the spatial frequency components of said original image data RAW_0 ;

generating biased image data RAW_{img} from said unsharp image data RAW_1 with reference to a biasing table that extracts data of designated luminance ranges from said unsharp image data RAW_1 ; and

adding said biased image data RAW_{img} to said original image data RAW_0 or subtracting said biased image data RAW_{img} from said original image data RAW_0 to generate output image data RAW_out that is finally output as said ultrasonotomographic image.

62. An ultrasonotomographic image generator program as claimed in claim 61, wherein said program makes said computer carry out a further step of multiplying said biased image data RAW_{img} by a coefficient K ($0 \leq K \leq 1$) to decide a degree of influence of said adjustment of the spatial frequency components of said original image data RAW_0 on said output image data RAW_out .

* * * * *

专利名称(译)	超声波图像和产生超声图像的方法和程序		
公开(公告)号	US7824334	公开(公告)日	2010-11-02
申请号	US11/312466	申请日	2005-12-21
[标]申请(专利权)人(译)	富士摄影胶片公司		
申请(专利权)人(译)	富士胶片有限公司		
当前申请(专利权)人(译)	富士胶片株式会社		
[标]发明人	SATO YOSHIAKI		
发明人	SATO, YOSHIAKI		
IPC分类号	A61B8/00		
CPC分类号	G06T5/004 G06T2207/10132 G06T2207/30004		
优先权	2004373947 2004-12-24 JP 2005167145 2005-06-07 JP		
其他公开文献	US20060140465A1		
外部链接	Espacenet USPTO		

摘要(译)

超声波检查仪具有频率分量调节器，该调节器调节超声波图像的原始图像数据RAW0的空间频率分量。频率分量调整器由非锐化图像数据发生器，减法电路，加权电路，积分电路，乘法电路和加法电路构成。非锐化图像数据生成器电路通过以五个步骤减小原始图像数据RAW0的空间频率分量来生成非锐化图像数据RAW_i (i = 1至5)。减法电路通过从RAW_{i-1}中减去非锐化图像数据RAW₁来产生差分图像数据ΔRAW_j (j = 1到4)。加权电路通过将差分图像数据ΔRAW_j乘以各自的系数k_j (-1 < k_j < 1) 来对差分图像数据ΔRAW_j进行加权。积分电路对差分图像数据ΔRAW_j进行积分以生成调整后的图像数据RAW_{En}。加法电路将调整后的图像数据RAW_{En}与原始图像数据RAW0相加以生成输出图像数据RAW_{out}。

