



US009066703B2

(12) **United States Patent**
Miller

(10) **Patent No.:** **US 9,066,703 B2**
(45) **Date of Patent:** **Jun. 30, 2015**

(54) **MEDICAL ULTRASOUND 2-D TRANSDUCER
ARRAY ARCHITECTURE: SPOT OF ARAGO**

(75) Inventor: **Gregg Miller**, Boulder, CO (US)

(73) Assignees: **Kabushiki Kaisha Toshiba**, Tokyo (JP);
Toshiba Medical Systems Corporation,
Otagawa-shi (JP)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 118 days.

(21) Appl. No.: **12/794,486**

(22) Filed: **Jun. 4, 2010**

(65) **Prior Publication Data**

US 2011/0301467 A1 Dec. 8, 2011

(51) **Int. Cl.**

A61B 8/14 (2006.01)

A61B 8/00 (2006.01)

G01S 7/52 (2006.01)

G01S 15/89 (2006.01)

(52) **U.S. Cl.**

CPC **A61B 8/4477** (2013.01); **A61B 8/4483**
(2013.01); **A61B 8/54** (2013.01); **G01S 7/52047**
(2013.01); **G01S 15/8913** (2013.01); **G01S**
15/8927 (2013.01)

(58) **Field of Classification Search**

USPC 600/437-472; 310/320, 321, 332
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,265,126 A * 5/1981 Papadofrangakis
et al. 73/861.25
4,523,471 A * 6/1985 Lee 73/626
5,398,216 A * 3/1995 Hall et al. 367/90
5,485,843 A * 1/1996 Greenstein et al. 600/455

5,522,393 A * 6/1996 Phillips et al. 600/455
5,893,832 A * 4/1999 Song 600/443
5,911,692 A * 6/1999 Hussain et al. 600/447
6,135,963 A * 10/2000 Haider 600/447
6,602,194 B2 * 8/2003 Roundhill et al. 600/443
6,783,497 B2 8/2004 Grenon et al.
7,559,897 B2 * 7/2009 Cerofolini 600/459
2003/0220554 A1 * 11/2003 Grenon et al. 600/407

FOREIGN PATENT DOCUMENTS

JP 6-181929 7/1994
JP 7-59773 3/1995

(Continued)

OTHER PUBLICATIONS

Office Action issued Feb. 17, 2015 in Japanese Patent Application
No. 2011-106478.

Primary Examiner — Long V. Le


Assistant Examiner — Lawrence Laryea

(74) *Attorney, Agent, or Firm* — Oblon, McClelland, Maier
& Neustadt, L.L.P.

(57) **ABSTRACT**

An ultrasound device including a main processing unit, a probe part, an array, and an apodization unit that receives an ultrasound signal from the array, the signal having multiple channels, that determines a weight for each channel based on an apodization profile being one of ring-centered and edge-centered, and that multiplies the received ultrasound signal by the determined weight for each channel. The array includes a first area including a first plurality of elements having a first functionality, a second area including a second plurality of elements having a second functionality, and a third area including a third plurality of elements having a third functionality different from the first functionality. The second area further includes a fourth area having a number of elements that are switchable between the second and third types of functionality. The array also includes a dynamic spot including the third and fourth areas.

33 Claims, 36 Drawing Sheets



US 9,066,703 B2

Page 2

(56) **References Cited**

FOREIGN PATENT DOCUMENTS

JP 8-500023 1/1996

JP	9-313487	12/1997
JP	2005-40376	2/2005
JP	2006-122657	5/2006
JP	2009-153945	7/2009

* cited by examiner





FIGURE 1A






FIGURE 1C




FIGURE 2A




FIGURE 2B




FIGURE 2C





FIGURE 3A






FIGURE 3C




FIGURE 4A





FIGURE 4B






FIGURE 5B




FIGURE 5C




FIGURE 6A




FIGURE 6B




FIGURE 6C






FIGURE 7A








FIGURE 9B





FIGURE 9C






FIGURE 10B





FIGURE 10C







FIGURE 11B







FIGURE 13






FIGURE 15




FIGURE 16




FIGURE 17




FIGURE 18




FIGURE 19A




FIGURE 19B

MEDICAL ULTRASOUND 2-D TRANSDUCER ARRAY ARCHITECTURE: SPOT OF ARAGO

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a system and method of producing ultrasound images using a reduced number of transducers elements.

2. Discussion of the Background

Conventionally, two dimensional 2-D ultrasound transducer arrays are formed by simultaneously transmitting and receiving using a plurality of individual transducer elements which act in concert as an array. When using a large number of individual transducer elements, the material cost and power required can be significant. U.S. Pat. No. 6,783,497 (herein Document 1) describes a sparse array that using only a portion of the full populated array. The sparse array consists of two or more separate zones for transmitting and receiving. However, since Document 1 is static in size and has a circular aperture shape, the device described in Document 1 is not sufficiently responsive.

SUMMARY OF THE INVENTION

Accordingly, an embodiment of the present invention provides, inter alia, an ultrasound device including a main processing unit, a probe part connected to the main processing unit, an apodization unit that receives an ultrasound signal from the array, the signal having multiple channels, that determines a weight for each channel based on an apodization profile, the apodization profile being one of ring-centered and/or edge-centered, and that multiplies the received ultrasound signal by the determined weight for each channel, and an array integral to the handle part of the probe. The array includes a first area including a first plurality of elements of a first type having a first functionality, a second area including a second plurality of elements of a second type having a second functionality, and a third area including a third plurality of elements of a third type having a third functionality different from the first functionality. The second area includes further area including a number of elements that are switchable between the second and third types of functionality.

An embodiment of the present invention also provides an ultrasound transducer having an array of elements arranged in an elliptical shape. The array includes a first area including a first plurality of elements of a first type having a first functionality, a second area including a second plurality of elements of a second type having a second functionality and a third area including a third plurality of elements of a third type having a third functionality.

Moreover, an embodiment of the present invention also provides for a method of processing an ultrasound signal obtained using an array including a first area including a first plurality of elements of a first type having a first functionality, a second area including a second plurality of elements of a second type having a second functionality, and a third area including a third plurality of elements of a third type having a third functionality different from the first functionality, wherein the second area further includes a fourth area having a number of elements that are switchable between the second and third types of functionality. The method includes the steps of receiving an ultrasound signal from the array, the signal having multiple channels, determining a weight for each channel based on an apodization profile, multiplying the received ultrasound signal by the determined weight for each channel and displaying the multiplied ultrasound signal as an

ultrasound image. In addition, the apodization profile is one of ring-centered and/or inner-edge centered.

It is to be understood that both the foregoing general description of the invention and the following detailed description are exemplary, but are not restrictive, of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

In the drawings like reference numbers designate identical or corresponding parts throughout the several views. Other objects, features and advantages of an embodiment of the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings, in which:

FIG. 1A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a receive only area, a transmit/receive area and a transmit only spot area;

FIG. 1B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a receive only area, a transmit/receive area and a receive only spot area;

FIG. 1C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a receive only area, a transmit/receive area and a disabled spot area;

FIG. 2A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a receive only area, a transmit/receive area and a transmit only spot area;

FIG. 2B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a receive only area, a transmit/receive area and a receive only spot area;

FIG. 2C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a receive only area, a transmit/receive area and a disabled spot area;

FIG. 3A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a dynamic spot and having a receive only area, a transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 3B illustrates an ultrasound transducer array according to an embodiment of the present invention having different spot sizes during receive and during transmit, the ultrasound transducer array having an elliptical aperture and a dynamic spot having a receive only area, a transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 3C illustrates a graph showing the size of the dynamic spot over time according to an embodiment of the present invention in which the size of the spot during transmit is different than the size of the spot during receive;

FIG. 4A illustrates graphs showing the size of the dynamic spot over time according to an embodiment of the present invention in which the size of the spot during transmit is different than the size of the spot during receive and the size of the spot during receive is dynamic;

FIG. 4B illustrates a graph showing the size of the dynamic spot over time according to an embodiment of the present

3

invention in which the size of the spot during transmit is different than the size of the spot during receive and the size of the spot for transmit and receive is dynamic from beam to beam;

FIG. 5A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a first transmit/receive area, a second transmit/receive area and a transmit only spot area;

FIG. 5B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a first transmit/receive area, a second transmit/receive area and a receive only spot area;

FIG. 5C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a first transmit/receive area, a second transmit/receive area and a disabled spot area;

FIG. 6A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a first transmit/receive area, a second transmit/receive area and an elliptical transmit only spot area;

FIG. 6B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a first transmit/receive area, a second transmit/receive area and an elliptical receive only spot area;

FIG. 6C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a first transmit/receive area, a second transmit/receive area and an elliptical disabled spot area;

FIG. 7A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a dynamic spot and having a first transmit/receive area, a second transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the second transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 8 illustrates an ultrasound transducer array according to an embodiment of the present invention having different dynamic spot sizes during receive and during transmit, the ultrasound transducer array having an elliptical aperture and a dynamic spot having a first transmit/receive area, a second transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the second transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 9A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a transmit only area, a transmit/receive area and a transmit only spot area;

FIG. 9B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a transmit only area, a transmit/receive area and a receive only spot area;

FIG. 9C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a circular spot and having a transmit only area, a transmit/receive area and a disabled spot area;

FIG. 10A illustrates an ultrasound transducer array according to an embodiment of the present invention having an

4

elliptical aperture and an elliptical spot and having a transmit only area, a transmit/receive area and a transmit only spot area;

FIG. 10B illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a transmit only area, a transmit/receive area and a receive only spot area;

FIG. 10C illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and an elliptical spot and having a transmit only area, a transmit/receive area and a disabled spot area;

FIG. 11A illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a dynamic spot and having a transmit only area, a transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 11B illustrates an ultrasound transducer array according to an embodiment of the present invention having different dynamic spot sizes during receive and during transmit, the ultrasound transducer array having an elliptical aperture and a dynamic spot having a transmit only area, a transmit/receive area, a disabled spot area, and a fourth area between the disabled spot area and the transmit/receive area which is switchable between being disabled and transmit/receive;

FIG. 12 illustrates an ultrasound transducer array according to an embodiment of the present invention for which a ring centered apodization graph is provided;

FIG. 13 illustrates an ultrasound transducer array according to an embodiment of the present invention for which an inner-edge centered apodization graph is provided;

FIG. 14 illustrates an ultrasound transducer array according to an embodiment of the present invention in which illustrates that the spot can be rotated in any combination of azimuth/elevation direction;

FIG. 15 illustrates an ultrasound transducer array according to an embodiment of the present invention having a polygonal aperture;

FIG. 16 illustrates an ultrasound transducer array according to an embodiment of the present invention having an elliptical aperture and a polygonal spot;

FIG. 17 illustrates a flow diagram illustrating a method according to an embodiment of the present invention;

FIG. 18 illustrates an ultrasound device according to an embodiment of the present invention having a main processing unit, a connector, a cable, a handle and a transducer array; and

FIG. 19A illustrates an exemplary structure of the main processing unit according to an embodiment of the present invention;

FIG. 19B illustrates an exemplary structure of the main processing unit according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTIONS

In an embodiment of the present invention there is described a transducer array such as an ultrasound transducer array. Embodiments of the present invention include transducer arrays of a two dimensional (2-D) type. These arrays can include piezoelectric transducers, CMUTs, PMUTs, or any other suitable type of transducer.

The architecture according to an embodiment of the present invention includes a spot on the transducer array which is not active during transmit and/or receive.

One advantage of this architecture is that the architecture results in a very narrow receive beam width are thereby enhancing near-field lateral resolution and the related imaging quality performance improvements. Moreover, the reduction in the number of elements coupled with similar superior resolution performance reduces power and electronics hardware requirements and saves related material cost.

As a result of the non-active elements in the array having no active transducers, the array has the potential to produce a higher quality near field image. This effect is produced as a result of Fresnel diffraction effects. [Note: Fresnel diffraction refers to near field effects, and Fraunhofer diffraction refers to far field effects.]

This improved signal quality in the near field is analogous to the “spot of Arago” or “Poisson’s spot” effect found in optics. The spot of Arago is a term used in optics diffraction theory to describe the result when an opaque circular disk having a size corresponding to a first Fresnel zone is substituted for the aperture of the first Fresnel zone. In such a situation, one would expect that the light amplitude would be reduced by a factor of 2 (for the 2 Fresnel ring case), but instead the irradiance at the center of the shadow is the same and more finely focused as compared with no opaque disk present.

In the case of the present architecture, the non-functioning elements in the spot area, correlate with the opaque optical disk which produces the spot of Arago, provide a focused beam in the near-field which improves image quality. Use of dedicated element clusters at the center of the array, which can be, for example, unused elements, lowers the required number of receive and/or transmit elements which, in turn, lowers the power and cost requirements for the electronics.

The spot noted above may be many different shapes. For instance, in the case of two dimensional (2D) externally utilized cardiac probes, the aperture is generally shaped as a rectangle. The overall probe shape is rectangular, but the spot will still be circular or elliptical in shape. Moreover, optics theory suggests that focusing provided by the Spot of Arago effect is typically realized with circular apertures. However, it has been discovered that an elliptically-shaped “hole” at the center of the aperture does not dramatically alter the beam characteristics when compared with a circular-shaped “hole.” Furthermore, elliptically shaped “spots” at the array center will look more circular when the beam is steered (from a point in line with the focus direction), and will therefore create a more focused near-field beam pattern than a circular “spot” under these circumstances.

The elliptical shaped spot is particularly helpful when steering due to the fact that, in the steering process, the ellipse collapses by the cosine of the interrogation angle to come closer to a circular aperture as seen from the line of steering, thereby compensating for this “stretching” of the non-transmitting/non-receiving aperture. Some compensative shaping of the spot can take place when steering (within a beam for receive, and from beam to beam as the line of sight changes, for both transmit and receive), such that it is more circular at receive (or transmit) angles closer to 0 degrees, and more elliptical at receive (or transmit) angles greater than or less than 0 degrees.

Shown below in Table I is a number of different embodiments of the present invention. The list of structures in Table I is not exhaustive.

1	2	3
1 RECEIVE ONLY	TRANSMIT/RECEIVE	TRANSMIT
2 RECEIVE ONLY	TRANSMIT/RECEIVE	RECEIVE
3 RECEIVE ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED)
4 RECEIVE ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE
5 RECEIVE ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC DURING A BEAM
6 RECEIVE ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC, DURING A BEAM TX AND RX SPOT SIZE CHANGE (OR NOT) FROM BEAM TO BEAM
7	TRANSMIT/RECEIVE	TRANSMIT
8	TRANSMIT/RECEIVE	RECEIVE
9	TRANSMIT/RECEIVE	SPOT (DISABLED)
10	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE
11	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC, DURING A BEAM TX AND RX SPOT SIZE CHANGE (OR NOT) FROM BEAM TO BEAM
12	TRANSMIT/RECEIVE	TRANSMIT
13 TRANSMIT ONLY	TRANSMIT/RECEIVE	RECEIVE
14 TRANSMIT ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED)
15 TRANSMIT ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE
16 TRANSMIT ONLY	TRANSMIT/RECEIVE	SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC, DURING A BEAM TX AND RX SPOT SIZE CHANGE (OR NOT) FROM BEAM TO BEAM
17 TRANSMIT ONLY	TRANSMIT/RECEIVE	TRANSMIT
18 TRANSMIT ONLY	TRANSMIT/RECEIVE	RECEIVE
		SPOT (DISABLED)
		SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE
		SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC SPOT (DISABLED), RX AND TX DIFFERENT SPOT SIZE, RX SPOT DYNAMIC, DURING A BEAM TX AND RX SPOT SIZE CHANGE (OR NOT) FROM BEAM TO BEAM

Embodiment 1

Circular Spot

FIG. 1A illustrates an ultrasound transducer array 20 having a circular spot 24 and that includes receive-only elements 21, transmit/receive elements 23 and transmit-only elements 25 in the spot area 24. The receive-only elements 21 are transducers that exclusively receive reflected ultrasound reverberations. The transmit-only elements 25 in the spot 24 exclusively transmit the ultrasonic waves and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched

such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 2A illustrates an ultrasound transducer array **20** having an elliptical spot **32** and that includes receive-only elements **21**, transmit/receive elements **23** and transmit-only elements **25** in the spot area **32**. The receive-only elements **21** are transducers that exclusively receive reflected ultrasound reverberations. The transmit-only elements **25** in the spot **32** exclusively transmit the ultrasonic waves and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Embodiment 2

Circular Spot

FIG. 1B illustrates an ultrasound transducer array **20** having a circular spot **24** and that includes receive-only elements **21**, transmit/receive elements **23** and receive-only elements **26** in the spot area **24**. The receive-only elements **21** are transducers that exclusively receive reflected ultrasound reverberations. The receive-only elements **26** in the spot **24** also exclusively receive reflected ultrasound reverberations and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 2B illustrates an ultrasound transducer array **20** having an elliptical spot **32** and that includes receive-only elements **21**, transmit/receive elements **23** and receive-only elements **26** in the spot area **32**. The receive-only elements **21** are transducers that exclusively receive reflected ultrasound reverberations. The receive-only elements **26** in the spot **32** also exclusively receive reflected ultrasound reverberations and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Embodiment 3

Circular Spot

FIG. 1C illustrates an ultrasound transducer array **20** having a circular spot **24** and that includes receive-only elements **21**, transmit/receive elements **23** and disabled elements **28** in the spot area **24**. The receive-only elements **21** are transducers that exclusively receive reflected ultrasound reverberations. The disabled elements **28** in the spot **24** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 2C illustrates an ultrasound transducer array **20** having an elliptical spot **32** and that includes receive-only elements **21**, transmit/receive elements **23** and disabled elements **28** in the spot area **32**. The receive-only elements **21** are

transducers that exclusively receive reflected ultrasound reverberations. The disabled elements **28** in the spot **32** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Dynamic Spot

FIG. 3A illustrates an ultrasound transducer array **20** having a dynamic spot **52** and that includes receive-only elements **21**, transmit/receive elements **23** and disabled elements **28**. The receive-only elements **21** are transducers that exclusively receive reflected ultrasound reverberations. The disabled elements **28** in the spot **52** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

The dynamic spot **52** has a maximum size **52B** and a minimum size **52A**, the maximum and minimum sizes shown in FIG. 3A are exemplary, the maximum and minimum sizes of the dynamic spot **52** can each be much larger or smaller.

The area between the maximum size **52B** and the minimum size **52A** includes elements **55** which a switchable between disabled transistors **28** and transmit/receive transistors **23**. The spot **52** can expand to the maximum size **52B** or shrink to the minimum size **52A** by using the switchable elements **55**. Thus, the dynamic spot **52** can grow smaller or larger or change shape (for example, from circle to ellipse, or larger and smaller) based on the needs of the focusing characteristics and image depth related requirements. Control of the switching of the switchable elements **55** can be performed by a main processing unit or by other electronic circuitry in the probe.

Thus, the enabling and disabling of elements can be performed using local enabling and disabling calculations performed locally to the array. Alternatively, the enabling and disabling of the switchable elements **55** can be performed in the main processing unit. Thus, the switching process takes into account the focus resulting from the execution of the function of the ultrasound transducer array and the shape of the spot **52**. For example, the present architecture can take into account image depth, transmit focus and other spot specific parameters to produce a certain sized/shaped spot by disabling elements accordingly. In addition, the switching logic can be updated while the beam is being dynamically focused from near to far field. Thus, the size and shape of the dynamic spot **52** can be precisely controlled to provide a more precise and accurate image in the near-field even during 2D scans.

Embodiment 4

FIG. 3B illustrates an ultrasound transducer array according to an embodiment of the present invention having different dynamic spot sizes during receive and during transmit. The transducer arrays shown in FIG. 3B have the structure as the transducer array in FIG. 3A. However, in the example shown in FIG. 3B, when the transducer array **20** is transmitting the ultrasound signal as is shown in FIG. 3B-(1), the receive transducers **21** are inactive, the receive/transmit transducers **23** are performing a transmit function, the transducers in the switchable area **55** are set to transmit, and the transducers in the spot area **28** are disabled. The dynamic spot **52B** thus has a first size during transmit which corresponds to the size of the disabled spot area **28**. In contrast, in FIG. 3B-(2)

there is shown an example corresponding to when the transducer array is in receive mode. In the example of receive mode, the receive transducers 21 are active, the receive/transmit transducers 23 are performing a receive function, the transducers in the switchable area 55 are set to disabled, and the transducers in the spot area 28 are disabled. Thus, the dynamic spot 52A has a second size during receive which corresponds to a combination of the size of the disabled spot area 28 and the switchable area 55. This example can also function when the spot area is transmit-only, receive-only and transmit/receive.

FIG. 3C illustrates a graph showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. As is shown in FIG. 3C, the size of the dynamic spot 52 changes when the transducer array is switched 39 from transmit to receive. It should be noted that the example shown in FIG. 3C illustrates that the size of the dynamic spot during transmit is smaller than the size of the dynamic spot during receive, however, the size of the dynamic spot during transmit can also be smaller than or equal to or larger than (in a different embodiment) the size of the dynamic spot during receive.

Embodiment 5

The ultrasound transducer array having the structure shown in FIG. 3A (dynamic spot 52 and that includes receive-only elements 21, transmit/receive elements 23 and disabled elements 28) can be used in the example shown in FIG. 4A. FIG. 4A illustrates graphs (1) and (2) showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. 4A illustrates that during receive the size of the dynamic spot 52A can change during the reception of the ultrasonic beam. As is shown in FIG. 4A, the size of the dynamic spot 52A changes when the transducer array is switched 39 from transmit to receive. In addition, as is shown in FIG. 4A-(1), the size of the dynamic spot 52A may increase as the reception of the ultrasonic beam is received. It should be noted that the dynamic spot 52A can also decrease during the reception of the ultrasonic beam as is shown in FIG. 4A-(2). In addition, the size of the dynamic spot 52A can increase and decrease or decrease and increase multiple times during the reception of the ultrasonic beam.

Embodiment 6

The ultrasound transducer array having the structure shown in FIG. 3A (dynamic spot 52 and that includes receive-only elements 21, transmit/receive elements 23 and disabled elements 28) can be used in the example shown in FIG. 4B. FIG. 4B illustrates a graph showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. 4B illustrates that during receive the size of the dynamic spot 52 can change during the reception of the ultrasonic beam. Moreover, FIG. 4B illustrates that the size of the dynamic spot 52 can change from beam to beam. As is shown in FIG. 4B, the size of the dynamic spot 52 changes when the transducer array is switched 39 from transmit to receive for each beam (first and second beam). The example shown in FIG. 4B illustrates two beams; however, the example shown in FIG. 4B is applicable to a plurality of beams. In addition, as is shown in FIG. 4B, the size of the dynamic spot 52 increases as the reception of the first ultrasonic beam is received. It should be noted that the dynamic spot 52 can increase or decrease or stay the same during the reception of the first

ultrasonic beam, second ultrasonic beam or any ultrasonic beam thereafter. In addition, the size of the dynamic spot can increase and decrease or decrease and increase multiple times during the reception of each of the ultrasonic beams. Furthermore, the size of the dynamic spot 52 during the transmit first beam and receive first beam can be different from the size of the dynamic spot 52 during the transmit second beam and receive second beam, respectively.

Embodiment 7

Circular Spot

FIG. 5A illustrates an ultrasound transducer array 20 having a circular spot 24 and that includes transmit/receive elements 29, transmit/receive elements 23 and transmit-only elements 25 in the spot area 24. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The transmit-only elements 25 in the spot 24 exclusively transmit the ultrasonic waves and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 6A illustrates an ultrasound transducer array 20 having an elliptical spot 32 and that includes transmit/receive elements 29, transmit/receive elements 23 and transmit-only elements 25 in the spot area 32. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The transmit-only elements 25 in the spot 32 exclusively transmit the ultrasonic waves and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

Embodiment 8

Circular Spot

FIG. 5B illustrates an ultrasound transducer array 20 having a circular spot 24 and that includes transmit/receive elements 29, transmit/receive elements 23 and receive-only elements 26 in the spot area 24. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The receive-only elements 26 in the spot 24 also exclusively receive reflected ultrasound reverberations and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 6B illustrates an ultrasound transducer array 20 having an elliptical spot 32 and that includes transmit/receive elements 29, transmit/receive elements 23 and receive-only elements 26 in the spot area 32. The transmit/receive elements 29 are transducers that can both transmit and receive the

11

ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The receive-only elements 26 in the spot 32 also exclusively receive reflected ultrasound reverberations and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

Embodiment 9

Circular Spot

FIG. 5C illustrates an ultrasound transducer array 20 having a circular spot 24 and that includes transmit/receive elements 29, transmit/receive elements 23 and disabled elements 28 in the spot area 24. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The disabled elements 28 in the spot 24 are unable to transmit or to receive and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. 6C illustrates an ultrasound transducer array 20 having an elliptical spot 32 and that includes transmit/receive elements 29, transmit/receive elements 23 and disabled elements 28 in the spot area 32. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The disabled elements 28 in the spot 32 are unable to transmit or to receive and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

Embodiment 10

FIG. 7A illustrates an ultrasound transducer array 20 having a dynamic spot 52 and that includes transmit/receive elements 29, transmit/receive elements 23 and disabled elements 28. The transmit/receive elements 29 are transducers that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 29 can perform the function of a transmit element or the function of a receive element. The disabled elements 28 in the spot 32 are unable to transmit or to receive and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements 23 can perform the function of a transmit element or the function of a receive element.

FIG. 8 illustrates an ultrasound transducer array according to an embodiment of the present invention having different dynamic spot sizes during receive and during transmit. The transducer arrays shown in FIG. 8 have the structure as the transducer array in FIG. 7A. However, in the example shown in FIG. 8, when the transducer array 20 is transmitting the ultrasound signal as is shown in FIG. 8-(1), the transmit/receive transducers 29 are set to transmit, the receive/transmit

12

transducers 23 are also set to transmit and are performing a transmit function, the transducers in the switchable area 55 are set to transmit, and the transducers in the spot area 28 are disabled. The dynamic spot 52B thus has a first size during transmit which corresponds to the size of the disabled spot area 28. In contrast, in FIG. 8-(2) there is shown an example corresponding to when the transducer array is in receive mode. In the example of receive mode, the transmit/receive transducers 29 are set to receive, the receive/transmit transducers 23 are also set to receive and are performing a receive function, the transducers in the switchable area 55A are set to disabled, and the transducers in the spot area 28 are disabled. Thus, the dynamic spot 52 has a second size during receive which corresponds to a combination of the size of the disabled spot area 28 and the switchable area 55. This example can also function when the spot area is transmit-only, receive-only and transmit/receive. Thus, as is shown in FIG. 3C, the dynamic spot 52 may have different sizes during transmit and receive.

Embodiment 11

The ultrasound transducer array having the structure shown in FIG. 7A (dynamic spot 52 and that includes transmit/receive elements 29, transmit/receive elements 23 and disabled elements 28) can be used in the example shown in FIG. 4A. As is noted above, FIG. 4A illustrates graphs (1) and (2) showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. 4A illustrates that during receive, the size of the dynamic spot 52A can change (is dynamic) during the reception of the ultrasonic beam. Thus, the dynamic spot 52A/B shown in FIG. 7A can have different sizes during transmit and receive and the size of the dynamic spot 52A can change during receive.

Embodiment 12

The ultrasound transducer array having the structure shown in FIG. 7A (dynamic spot 52 and that includes transmit/receive elements 29, transmit/receive elements 23 and disabled elements 28) can be used in the example shown in FIG. 4B. FIG. 4B illustrates a graph showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. 4B illustrates that during receive the size of the dynamic spot 52 can change during the reception of the ultrasonic beam. Moreover, FIG. 4B illustrates that the size of the dynamic spot 52 can change from beam to beam. Thus, the dynamic spot 52 shown in FIG. 7A can have different sizes during transmit and receive, the size of the dynamic spot 52 can change during receive, and the size of the dynamic spot 52 can change from beam to beam.

Embodiment 13

Circular Spot

FIG. 9A illustrates an ultrasound transducer array 20 having a circular spot 24 and that includes transmit-only elements 22, transmit/receive elements 23 and transmit-only elements 25 in the spot area 24. The transmit-only elements 22 are transducers that exclusively transmit the ultrasonic waves. The transmit-only elements 25 in the spot 24 also exclusively transmit the ultrasonic waves and the transmit/receive elements 23 are transducer elements that can both transmit and receive the ultrasonic waves and can be switched

13

such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. **10A** illustrates an ultrasound transducer array **20** having an elliptical spot **32** and that includes transmit-only elements **22**, transmit/receive elements **23** and transmit-only elements **25** in the spot area **32**. The transmit-only elements **22** are transducers that exclusively transmit the ultrasonic waves. The transmit-only elements **25** in the spot **32** also exclusively transmit the ultrasonic waves and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Embodiment 14

Circular Spot

FIG. **9B** illustrates an ultrasound transducer array **20** having a circular spot **24** and that includes transmit-only elements **22**, transmit/receive elements **23** and receive-only elements **26** in the spot area **24**. The transmit-only elements **22** are transducers that exclusively transmit the ultrasonic waves. The receive-only elements **26** in the spot **24** exclusively receive reflected ultrasound reverberations and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. **10B** illustrates an ultrasound transducer array **20** having an elliptical spot **32** that includes transmit-only elements **21**, transmit/receive elements **23** and receive-only elements **26** in the spot area **32**. The transmit-only elements **21** are transducers that exclusively transmit the ultrasonic waves. The receive-only elements **26** in the spot **32** exclusively receive reflected ultrasound reverberations and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Embodiment 15

Circular Spot

FIG. **9C** illustrates an ultrasound transducer array **20** having a circular spot **24** and that includes transmit-only elements **22**, transmit/receive elements **23** and disabled elements **28** in the spot area **24**. The transmit-only elements **22** are transducers that exclusively transmit the ultrasonic waves. The disabled elements **28** in the spot **24** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

(Elliptical Spot)

FIG. **10C** illustrates an ultrasound transducer array **20** having an elliptical spot **32** and that includes transmit-only elements **22**, transmit/receive elements **23** and disabled elements **28** in the spot area **32**. The transmit-only elements **22** are

14

transducers that exclusively transmit the ultrasonic waves. The disabled elements **28** in the spot **32** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

Embodiment 16

FIG. **11A** illustrates an ultrasound transducer array **20** having a dynamic spot **52** and that includes transmit-only elements **22**, transmit/receive elements **23** and disabled elements **28**. The transmit-only elements **22** are transducers that exclusively transmit the ultrasonic waves. The disabled elements **28** in the spot **32** are unable to transmit or to receive and the transmit/receive elements **23** are transducer elements that can both transmit and receive the ultrasonic waves and can be switched such that the transmit/receive elements **23** can perform the function of a transmit element or the function of a receive element.

FIG. **11B** illustrates an ultrasound transducer array according to an embodiment of the present invention having different dynamic spot sizes during receive and during transmit. The transducer arrays shown in FIG. **11B** have the structure as the transducer array in FIG. **11A**. However, in the example shown in FIG. **11B**, when the transducer array **20** is transmitting the ultrasound signal as is shown in FIG. **11B**-(1), the transmit transducers **22** are transmitting, the receive/transmit transducers **23** are set to transmit and are performing a transmit function, the transducers in the switchable area **55B** are set to transmit, and the transducers in the spot area **28** are disabled. The dynamic spot **52** thus has a first size during transmit which corresponds to the size of the disabled spot area **28**. In contrast, in FIG. **11B**-(2) there is shown an example corresponding to when the transducer array is in receive mode. In the example of receive mode, the transmit-only transducers **22** are inactive, the receive/transmit transducers **23** are set to receive and are performing a receive function, the transducers in the switchable area **55** are set to disabled, and the transducers in the spot area **28** are disabled. Thus, the dynamic spot **52A** has a second size during receive which corresponds to a combination of the size of the disabled spot area **28** and the switchable area **55**. This example can also function when the spot area is transmit-only, receive-only and transmit/receive. Thus, as is shown in FIG. **3C**, the dynamic spot **52** has different sizes during transmit and receive.

Embodiment 17

The ultrasound transducer array having the structure shown in FIG. **11A** (dynamic spot **52** and that includes transmit-only elements **22**, transmit/receive elements **23** and disabled elements **28**) can be used in the example shown in FIG. **4A**. As is noted above, FIG. **4A** illustrates graphs (1) and (2) showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. **4A** illustrates that during receive, the size of the dynamic spot **52A** can change (is dynamic) during the reception of the ultrasonic beam. Thus, the dynamic spot **52A/B** shown in FIG. **11A** can have different sizes during transmit and receive and the size of the dynamic spot **52A** can change during receive.

Embodiment 18

The ultrasound transducer array having the structure shown in FIG. **11A** (dynamic spot **52** and that includes trans-

mit-only elements **22**, transmit/receive elements **23** and disabled elements **28**) can be used in the example shown in FIG. **4B**. FIG. **4B** illustrates a graph showing the size of the dynamic spot over time when the size of the spot during transmit is different than the size of the spot during receive. In addition, FIG. **4B** illustrates that during receive the size of the dynamic spot **52** can change during the reception of the ultrasonic beam. Moreover, FIG. **4B** illustrates that the size of the dynamic spot **52** can change from beam to beam. Thus, the dynamic spot **52** shown in FIG. **11A** can have different sizes during transmit and receive, the size of the dynamic spot **52** can change during receive, and the size of the dynamic spot **52** can change from beam to beam.

FIGS. **12** and **13** relate to apodization. Apodization is generally applied in both 1-d and 2-d arrays so that the maximum signal is generated at the center of the array and the minimum signal, as defined by hamming/hanning/raised cosine/etc. apodization weighting, is applied at the elements farthest away from the active aperture center.

Standard Fresnel Lens Theory suggests that a sine-weighted apodization profile across each of the Fresnel rings will focus energy more finely at the designated focal point. In one embodiment, ring-centered apodization, similar to the optics theory mentioned above, and shown in the apodization graph **25** of FIG. **12**, is utilized in order to result in a similar imaging focus improvement. In addition, ring-centered apodization is used at one location in the image (the near and mid-field, for example) and inner-edge centered apodization (shown in FIG. **13**) is used in the mid-to-far field for highest sensitivity, and apodization flattening in the very far field. See apodization graph **25** of FIG. **12** which illustrates that the apodization is centered on the edge of the spot **22** and not in the middle of the aperture as is typical. Thus, whereas the ring-centered apodization is helpful in a number of instances, an apodization profile that changes for optimization of parameters other than focusing parameters may also be called for when optimizing an ultrasound image.

Different types of apodization can be used for an ultrasound system. Specifically, one type, transmit apodization, is performed by weighting the energy of the transmitting waveform. This can be accomplished by changing the amplitude of each of the waveforms across the transducer element array, or by changing the amount of energy available in the pulse through the use of pulse width modulation, for example. Transmit apodization can provide improvements in imaging performance. A second type, receive apodization, is applied by multiplying the incoming signal with a "weight" for that channel. For analog systems, this is accomplished through gain control associated with each channel, for digital systems that use analog to digital conversion before apodization processing, apodization is accomplished by multiplying the digital signal by a digital apodization weighting term within the beamformer.

In addition, apodization weighting can be applied to summed sub-array elements. When using sub-array elements, the summed receive signals from *n* elements, either directly summed, or summed after relative delay, are applied to each of the channels, before apodization is applied.

FIG. **14** illustrates that the spot **42** can be arranged in any combination of the elevation/azimuth direction. Although the examples of the transducer array noted above illustrate the spot in one configuration, as is shown in FIG. **14**, the spot whether it be a circle, an ellipse or some other shape, can be arranged in any direction. In addition, the spot can be arranged off-centered as well as centered on the array. In addition, the spot **42** can be used when steering beams for both transmit and receive apertures. Further, the spot can be

arranged such that it may be optimally used with steered beams in the azimuth direction, the elevation direction or in an elevation/azimuth direction.

In addition, for receive apertures, dynamic change of the spot **52** can occur on a depth basis, as well. For instance, the spot **52** can be dynamically updated with receive depth, in a similar way that present ultrasound systems perform aperture growth—including more channels, and increasing the receive aperture size, as the receive focusing depth is dynamically updated.

The embodiments noted above where described as having elliptical arrays, however, the present invention can also be implemented using a polygonal array. The polygonal array shown in FIG. **15** includes an array of transducer elements **60** which include transmit/receive *21* elements and a spot **62**. The polygonal array can be used with any of the embodiments noted above.

In addition the shape of the spot or the shape that the dynamic spot creates could be a polygonal shape **37**. This shape could be, for example, an irregular polygon. FIG. **16** illustrates an example of a spot which has a polygonal shape.

FIG. **17** shows a flow diagram indicating the process steps performed by the apodization in one embodiment of the present invention. In step **S1**, the incoming ultrasonic signal is received. The flow can either follow one of two paths. First if the summation of sub-arrays is not applied, the flow proceeds to step **S2**. However, if the summation of sub-arrays is applied, the summed receive signals from *n* elements, either directly summed, or summed after relative delay, are applied to each of the channels **S1B** before proceeding to step **S2**. In step **S2**, a weight for each incoming channel is determined based on an apodization profile (such as ring-centered or inner-edge centered). Once the weight for each channel has been determined, in step **S3**, the received signal for each channel is multiplied by the weight determined in step **S2**. As is noted above, this process can be performed using analog or digital signals and can be performed using both analog circuits or a digital computer based system.

FIG. **18** illustrates an exemplary ultrasound imaging device **89**. Included in the ultrasound imaging device **89** are a main processing unit **85**. This device could be connected to several input/output devices. Also connected to the main processing unit **85** is a connector **82** and a cable **83** which is connected to transducer array **81** via a handle **87**. The head of the handle **87** includes an array of elements **81** which can include a spot area as is described above. Processing necessary for performance of the ultrasonographic imaging process may be performed entirely or partly by the main processing unit **85** or alternatively partly or entirely in the probe—**82**, **83**, **87** and **81**. For example, the processing necessary to enable and disable elements in the spot area of the dynamic spot **52** can be performed by the main processing unit **85** (or within the probe, itself).

FIGS. **19A** and **19B** illustrate the structure of, for example, the main processing unit **85** according to an embodiment of the invention. The MPU **85** shown in FIGS. **19A** and **19B** are identical except for the inclusion in the MPU **85** in **19B** of a beamformer processing unit (BFPU) **1007**. In the embodiment shown in FIG. **19A**, the BFPU is not located in the MPU **85** but is instead located in an alternate location such as in the probe.

The main processing unit **85** includes a bus **B** or other communication mechanism for communicating information, and a processor/CPU **1004** coupled with the bus **B** for processing the information. The main processing unit **85** also includes a main memory/memory unit **1003**, such as a random access memory (RAM) or other dynamic storage device

(e.g., dynamic RAM (DRAM), static RAM (SRAM), and synchronous DRAM (SDRAM)), coupled to the bus B for storing information and instructions to be executed by processor/CPU **1004**. In addition, the memory unit **1003** may be used for storing temporary variables or other intermediate information during the execution of instructions by the CPU **1004**. The main processing unit **85** may also further include a read only memory (ROM) or other static storage device (e.g., programmable ROM (PROM), erasable PROM (EPROM), and electrically erasable PROM (EEPROM)) coupled to the bus B for storing static information and instructions for the CPU **1004**.

The main processing unit **85** may also include a disk controller coupled to the bus B to control one or more storage devices for storing information and instructions, such as mass storage **1002**, and drive device **1006** (e.g., floppy disk drive, read-only compact disc drive, read/write compact disc drive, compact disc jukebox, tape drive, and removable magneto-optical drive). The storage devices may be added to the main processing unit **85** using an appropriate device interface (e.g., small computer system interface (SCSI), integrated device electronics (IDE), enhanced-IDE (E-IDE), direct memory access (DMA), or ultra-DMA).

The main processing unit **85** may also include special purpose logic devices (e.g., application specific integrated circuits (ASICs)) or configurable logic devices (e.g., simple programmable logic devices (SPLDs), complex programmable logic devices (CPLDs), and field programmable gate arrays (FPGAs)).

The main processing unit **85** may also include a display controller coupled to the bus B to control a display, such as a cathode ray tube (CRT), for displaying information to a computer user. The computer system includes input devices, such as a keyboard and a pointing device, for interacting with a computer user and providing information to the processor. The pointing device, for example, may be a mouse, a trackball, or a pointing stick for communicating direction information and command selections to the processor and for controlling cursor movement on the display. In addition, a printer may provide printed listings of data stored and/or generated by the computer system.

The main processing unit **85** performs at least a portion of the processing steps of the invention in response to the CPU **1004** executing one or more sequences of one or more instructions contained in a memory, such as the memory unit **1003**. Such instructions may be read into the memory unit from another computer readable medium, such as the mass storage **1002** or a removable media **1001**. One or more processors in a multi-processing arrangement may also be employed to execute the sequences of instructions contained in memory unit **1003**. In alternative embodiments, hard-wired circuitry may be used in place of or in combination with software instructions. Thus, embodiments are not limited to any specific combination of hardware circuitry and software.

As stated above, the main processing unit **85** includes at least one computer readable medium **1001** or memory for holding instructions programmed according to the teachings of the invention and for containing data structures, tables, records, or other data described herein. Examples of computer readable media are compact discs, hard disks, floppy disks, tape, magneto-optical disks, PROMs (EPROM, EEPROM, flash EPROM), DRAM, SRAM, SDRAM, or any other magnetic medium, compact discs (e.g., CD-ROM), or any other medium from which a computer can read.

Stored on any one or on a combination of computer readable media, the present invention includes software for controlling the main processing unit **85**, for driving a device or

devices for implementing the invention, and for enabling the main processing unit **85** to interact with a human user. Such software may include, but is not limited to, device drivers, operating systems, development tools, and applications software. Such computer readable media further includes the computer program product of the present invention for performing all or a portion (if processing is distributed) of the processing performed in implementing the invention.

The computer code elements on the medium of the present invention may be any interpretable or executable code mechanism, including but not limited to scripts, interpretable programs, dynamic link libraries (DLLs), Java classes, and complete executable programs. Moreover, parts of the processing of the present invention may be distributed for better performance, reliability, and/or cost.

The term "computer readable medium" as used herein refers to any medium that participates in providing instructions to the CPU **1004** for execution. A computer readable medium may take many forms, including but not limited to, non-volatile media, and volatile media. Non-volatile media includes, for example, optical, magnetic disks, and magneto-optical disks, such as the mass storage **1002** or the removable media **1001**. Volatile media includes dynamic memory, such as the memory unit **1003**.

Various forms of computer readable media may be involved in carrying out one or more sequences of one or more instructions to the CPU **1004** for execution. For example, the instructions may initially be carried on a magnetic disk of a remote computer. An input coupled to the bus B can receive the data and place the data on the bus B. The bus B carries the data to the memory unit **1003**, from which the CPU **1004** retrieves and executes the instructions. The instructions received by the memory unit **1003** may optionally be stored on mass storage **1002** either before or after execution by the CPU **1004**.

The main processing unit **85** also includes a communication interface **1005** coupled to the bus B. The communication interface **1004** provides a two-way data communication coupling to a network that is connected to, for example, a local area network (LAN), or to another communications network such as the Internet. For example, the communication interface **1005** may be a network interface card to attach to any packet switched LAN. As another example, the communication interface **1005** may be an asymmetrical digital subscriber line (ADSL) card, an integrated services digital network (ISDN) card or a modem to provide a data communication connection to a corresponding type of communications line. Wireless links may also be implemented. In any such implementation, the communication interface **1005** sends and receives electrical, electromagnetic or optical signals that carry digital data streams representing various types of information.

The network typically provides data communication through one or more networks to other data devices. For example, the network may provide a connection to another computer through a local network (e.g., a LAN) or through equipment operated by a service provider, which provides communication services through a communications network. The local network and the communications network use, for example, electrical, electromagnetic, or optical signals that carry digital data streams, and the associated physical layer (e.g., CAT 5 cable, coaxial cable, optical fiber, etc). Moreover, the network may provide a connection to a mobile device such as a personal digital assistant (PDA) laptop computer, or cellular telephone.

Some of the advantages of embodiments of the present invention may be depending on the application: 1) power

requirements for 2D transducers can be lowered, 2) fewer elements are required for similar beam pattern response 3) lower cost requirements for the transducer, 4) reduced requirements for electronic focusing 5) spot shaping when steering creates a more uniform near-field beam formation across steering angles required for ultrasound imaging (0 to 45 degrees, for example) and, 6) for the same number of elements, larger apertures may be used to provide a larger aperture which results in finer focusing characteristics.

Modifications to embodiments of the invention described in the foregoing are susceptible to being implemented without departing from the scope of the invention as defined by the appended claims.

The invention claimed is:

1. An ultrasound device having an array of elements, the array comprising:

a first area including a first plurality of elements of a first type having a first functionality;

a second area including a second plurality of elements of a second type having a second functionality; and

a third area including a third plurality of elements of a third type having a third functionality different from the first functionality,

wherein the second area further includes therein a fourth area including a number of elements that are switchable between the second and third types of functionality.

2. The ultrasound device according to claim 1, wherein the array includes a dynamic spot comprising:

the fourth area including the number of elements that are switchable between the second and third types of functionality; and

the third area including the third plurality of elements of the third type having the third functionality different from the first functionality.

3. The ultrasound device according to claim 2, wherein a size or shape of the dynamic spot during a receive mode of a beam is different from a size or shape of the dynamic spot during a transmit mode of the beam.

4. The ultrasound device according to claim 3, wherein the size or shape of the dynamic spot during the receive mode is different from the size or shape of the dynamic spot during the transmit mode based on switching performed by the number of elements in the fourth area.

5. The ultrasound device according to claim 3, wherein the size or shape of the dynamic spot during the receive mode of the beam is dynamic.

6. The ultrasound device according to claim 5, wherein the size or shape of the dynamic spot during a receive mode or transmit mode of a first beam is different from the size or shape of the dynamic spot during a receive mode or transmit mode of a second beam.

7. The ultrasound device according to claim 2, wherein the second plurality of elements are transmit/receive elements and the second functionality is a transmit functionality during a transmit mode and a receive functionality during a receive mode.

8. The ultrasound device according to claim 7, wherein the first plurality of elements are receive-only elements and the first functionality is a receive functionality.

9. The ultrasound device according to claim 7, wherein the first plurality of elements are transmit/receive elements and the first functionality is the transmit functionality during the transmit mode and the receive functionality during the receive mode.

10. The ultrasound device according to claim 7, wherein the first plurality of elements are transmit-only elements and the first functionality is a transmit functionality.

11. The ultrasound device according to claim 8, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

12. The ultrasound device according to claim 10, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

13. The ultrasound device according to claim 9, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

14. The ultrasound device according to claim 7, wherein the dynamic spot has an elliptical, circular, or polygonal shape.

15. The ultrasound device according to claim 1, wherein the array has an elliptical shape or a polygonal shape.

16. An ultrasound device, comprising:

a main processing unit;

a probe part connected to the main processing unit;

the array according to claim 1 integral to a handle part of the probe part; and

an apodization unit configured to receive an ultrasound signal from the array, the signal having multiple channels, to determine a weight for each channel based on an apodization profile, wherein the apodization profile is one of ring-centered and edge-centered, and to multiply the received ultrasound signal by the determined weight for each channel.

17. An ultrasound device having an array of elements, the array comprising:

a first area including a first plurality of elements of a first type having a first functionality and which do not transmit ultrasound signals;

a second area including a second plurality of elements of a second type having a second functionality; and

a third area including a third plurality of elements of a third type having a third functionality,

wherein the array has an oblong ellipse shape, and wherein the first area is positioned inside the second area and the third area and the first area includes the center of the array.

18. The ultrasound device according to claim 17, wherein the second plurality of elements are transmit/receive elements and the second functionality is a transmit functionality during a transmit mode and a receive functionality during a receive mode.

19. The ultrasound device according to claim 18, wherein the first plurality of elements are receive-only elements and the first functionality is a receive functionality.

20. The ultrasound device according to claim 19, wherein the third plurality of elements are transmit-only elements and the third functionality is a transmit functionality.

21. The ultrasound device according to claim 19, wherein the third plurality of elements are receive-only elements and the third functionality is a receive functionality.

22. The ultrasound device according to claim 19, wherein the third plurality of elements are transmit/receive elements and the third functionality is the transmit functionality during the transmit mode and the receive functionality during the receive mode.

23. The ultrasound device according to claim 19, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

24. The ultrasound device according to claim 17, wherein the third plurality of elements are transmit-only elements and the third functionality is a transmit functionality.

25. The ultrasound device according to claim 17, wherein the third plurality of elements are receive-only elements and the third functionality is a receive functionality.

21

26. The ultrasound device according to claim 17, wherein the third plurality of elements are transmit/receive elements and the third functionality is the transmit functionality during the transmit mode and the receive functionality during the receive mode.

27. The ultrasound device according to claim 17, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

28. The ultrasound device according to claim 17, wherein the third plurality of elements are transmit-only elements and the third functionality is a transmit functionality.

29. The ultrasound device according to claim 17, wherein the third plurality of elements are receive-only elements and the third functionality is a receive functionality.

30. The ultrasound device according to claim 17, wherein the third plurality of elements are transmit/receive elements and the third functionality is the transmit functionality during the transmit mode and the receive functionality during the receive mode.

31. The ultrasound device according to claim 17, wherein the third plurality of elements are disabled elements and the third functionality is disabled.

32. A method of processing an ultrasound signal, the method comprising:

22

receiving the ultrasound signal from an array, the signal having multiple channels, wherein the array includes a first area including a first plurality of elements of a first type having a first functionality, a second area including a second plurality of elements of a second type having a second functionality, and a third area including a third plurality of elements of a third type having a third functionality different from the first functionality, wherein the second area further includes fourth area having a number of elements that are switchable between the second and third types of functionality;

determining a weight for each channel based on an apodization profile, wherein the apodization profile is one of ring-centered and edge-centered;

multiplying the received ultrasound signal by the determined weight for each channel; and

displaying the multiplied ultrasound signal as an ultrasound image.

33. The method according to claim 32, further comprising: summing a sub-array of elements of the array and applying the summation to each of the channels before the step of determining.

* * * * *

专利名称(译)	医用超声二维换能器阵列结构：arago现货		
公开(公告)号	US9066703	公开(公告)日	2015-06-30
申请号	US12/794486	申请日	2010-06-04
[标]申请(专利权)人(译)	东芝医疗系统株式会社 株式会社东芝		
申请(专利权)人(译)	东芝医疗系统公司 株式会社东芝		
当前申请(专利权)人(译)	株式会社东芝 东芝医疗系统公司		
[标]发明人	MILLER GREGG		
发明人	MILLER, GREGG		
IPC分类号	A61B8/14 G01S7/52 A61B8/00 G01S15/89		
CPC分类号	A61B8/4477 A61B8/4483 A61B8/54 G01S7/52047 G01S15/8913 G01S15/8927		
其他公开文献	US20110301467A1		
外部链接	Espacenet USPTO		

摘要(译)

一种超声装置，包括主处理单元，探针部分，阵列和变迹单元，其从阵列接收超声信号，该信号具有多个通道，其基于变迹轮廓确定每个通道的权重。以环为中心并以边缘为中心，并将接收的超声信号乘以每个通道的确定重量。该阵列包括第一区域和第三区域，第一区域包括具有第一功能的第一多个元件，第二区域包括具有第二功能的第二多个元件，第三区域包括具有与第一功能不同的第三功能的第三多个元件。第二区域还包括第四区域，该第四区域具有可在第二和第三类型功能之间切换的多个元件。阵列还包括包括第三和第四区域的动态点。

