



US 20030060709A1

(19) **United States**

(12) **Patent Application Publication**
Hashimoto et al.

(10) **Pub. No.: US 2003/0060709 A1**

(43) **Pub. Date: Mar. 27, 2003**

(54) **ULTRASONIC DIAGNOSTIC APPARATUS**

Publication Classification

(76) Inventors: **Hiroshi Hashimoto**, Tokyo (JP);
Shinichi Amemiya, Tokyo (JP)

(51) **Int. Cl.⁷** **A61B 8/00**

(52) **U.S. Cl.** **600/443**

Correspondence Address:

Patrick W. Rasche
Armstrong Teasdale LLP
Suite 2600
One Metropolitan Sq.
St. Louis, MO 63102 (US)

(57) **ABSTRACT**

For the purpose of eliminating a problem that a good harmonic image cannot be obtained due to the tail of a fundamental component of previous received data intruding into a fundamental component of current received data; in the operation in a harmonic mode according to a phase inversion technique, a first ultrasonic pulse is sequentially transmitted to a plurality of foci on the same acoustic line, and a second ultrasonic pulse of a phase opposite to that of the first ultrasonic pulse is sequentially transmitted to the plurality of foci on the same acoustic line.

(21) Appl. No.: **10/246,057**

(22) Filed: **Sep. 18, 2002**

(30) **Foreign Application Priority Data**

Sep. 21, 2001 (JP) 2001-287989




FIG. 1

Ultrasonic diagnostic
apparatus
10




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15





FIG. 16



ULTRASONIC DIAGNOSTIC APPARATUS

BACKGROUND OF THE INVENTION

[0001] The present invention relates to an ultrasonic imaging method and ultrasonic diagnostic apparatus, and more particularly to an ultrasonic imaging method and ultrasonic diagnostic apparatus that eliminate a problem that a good harmonic image cannot be obtained due to a fundamental component of received data for a previous ultrasonic pulse intruding into a fundamental component of received data for a current ultrasonic pulse at a considerable intensity.

[0002] FIG. 14 is an explanatory diagram showing timing of B-mode imaging in a conventional ultrasonic diagnostic apparatus. In FIG. 14, a fundamental component is indicated by a solid line and a harmonic component by a broken line because the fundamental component is principal and the harmonic component is subsidiary in the B mode.

[0003] When an ultrasonic pulse f_s with a relatively shallow (e.g., 5 cm) focus is transmitted at a time t_1 , the fundamental component of received data (i.e., a component of received data having the same frequency as the transmission frequency) indicated by the solid line in FIG. 14 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component (i.e., a component of received data having a frequency twice as high as the transmission frequency) of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0004] A time t_2 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_s transmitted at the time t_1 decreases to a negligible level (e.g., the component becomes smaller than a noise component or a detection sensitivity).

[0005] When an ultrasonic pulse f_m with a relatively intermediate (e.g., 10 cm) focus is transmitted at the time t_2 , the fundamental component of received data indicated by the solid line in FIG. 14 has an intensity decreasing over time with a maximum at the time t_2 . The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_2 .

[0006] A time t_3 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_m transmitted at the time t_2 decreases to a negligible level.

[0007] When an ultrasonic pulse f_d with a relatively deep (e.g., 15 cm) focus is transmitted at the time t_3 , the fundamental component of received data indicated by the solid line in FIG. 14 has an intensity decreasing over time with a maximum at the time t_3 . The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_3 .

[0008] A time t_4 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_d transmitted at the time t_3 decreases to a negligible level.

[0009] When an ultrasonic pulse f_s with a relatively shallow (e.g., 5 cm) focus is transmitted at the time t_4 , the fundamental component of received data indicated by the

solid line in FIG. 14 has an intensity decreasing over time with a maximum at the time t_4 . The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_4 .

[0010] A similar operation is repeated thereafter.

[0011] The frame rate is $1/(\tau_s + \tau_m + \tau_d) \times N$, where the interval between the times t_1 and t_2 is represented by τ_s , the interval between the times t_2 and t_3 is represented by τ_m , the interval between the times t_3 and t_4 is represented by τ_d , the ultrasonic pulses f_s , f_m and f_d gives one acoustic line, and the number of acoustic lines in one frame is N . Moreover, $\tau_s < \tau_m < \tau_d$.

[0012] If the transmission intervals for the ultrasonic pulses f_s , f_m and f_d are uniformly set to τ_s , the received data for the ultrasonic pulse f_m remains at a considerable intensity when reception of received data for the ultrasonic pulse f_d is started, compromising imaging. Moreover, the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0013] If the intervals are uniformly set to τ_m , the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0014] On the other hand, the intervals uniformly set to τ_d do no harm in imaging.

[0015] However, the frame rate is $1/(3 \times \tau_d) \times N$, which is lower than that in FIG. 14.

[0016] In other words, the ultrasonic pulses f_s , f_m and f_d are transmitted at timing as shown in FIG. 14 so that a higher frame rate can be achieved.

[0017] FIG. 15 is an explanatory diagram showing timing of harmonic-mode imaging according to a filtering technique in the conventional ultrasonic diagnostic apparatus.

[0018] In FIG. 15, a harmonic component is indicated by a solid line and a fundamental component by a broken line because the harmonic component is principal and the fundamental component is subsidiary in the harmonic mode. Moreover, the gain is increased to acquire large harmonic components that are inherently small, and accordingly, the fundamental components become larger.

[0019] The timing for transmitting the ultrasonic pulses in FIG. 15 is exactly the same as that in the B mode shown in FIG. 14.

[0020] FIG. 16 is an explanatory diagram showing timing of harmonic-mode imaging according to a phase inversion technique in the conventional ultrasonic diagnostic apparatus.

[0021] When a first ultrasonic pulse f_s with a relatively shallow focus is transmitted at a time t_1 , the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0022] When a second ultrasonic pulse $fs-$ with a relatively shallow focus and of a phase opposite to that of the first ultrasonic pulse $fs+$ is transmitted at a time $t2$ after a time period is from the time $t1$ as in the B mode, the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time $t2$. The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t2$.

[0023] Adding the first and second received data, the fundamental components are canceled out because their phases are opposite, and the harmonic components are doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0024] When a first ultrasonic pulse $fm+$ with a relatively intermediate focus is transmitted at a time $t3'$ after a time period τ_s from the time $t2$ as in the B mode, the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time $t3'$. The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t3'$.

[0025] When a second ultrasonic pulse $fm-$ with a relatively intermediate focus and of a phase opposite to that of the first ultrasonic pulse $fm+$ is transmitted at a time $t4'$ after a time period τ_m from the time $t3'$ as in the B mode, the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time $t4'$. The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t4'$.

[0026] Adding the first and second received data, the fundamental components are canceled out because their phases are opposite, and the harmonic components are doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0027] When a first ultrasonic pulse $fd+$ with a relatively deep focus is transmitted at a time $t5'$ after a time period τ_m from the time $t4'$ as in the B mode, the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time $t5'$. The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t5'$.

[0028] When a second ultrasonic pulse $fd-$ with a relatively deep focus and of a phase opposite to that of the first ultrasonic pulse $fd+$ is transmitted at a time $t6'$ after a time period i_d from the time $t5'$ as in the B mode, the fundamental component of received data indicated by the broken line in FIG. 16 has an intensity decreasing over time with a maximum at the time $t6'$. The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t6'$.

[0029] Adding the first and second received data, the fundamental components are canceled out because their phases are opposite, and the harmonic components are

doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0030] Then, a first ultrasonic pulse $fs+$ with a relatively shallow focus is transmitted at a time $t7'$ after a time period τ_d from the time $t6'$ as in the B mode.

[0031] A similar operation is repeated thereafter.

[0032] In the harmonic mode in the conventional ultrasonic diagnostic apparatus, transmission timing for the ultrasonic pulses is the same as that in the B mode.

[0033] However, the transmission timing for the ultrasonic pulses in the B mode is such that a next ultrasonic pulse is transmitted when the fundamental component of received data for a previous ultrasonic pulse decreases to a negligible level using a small gain. If the same timing is employed in the harmonic mode in which the gain is increased, the next ultrasonic pulse is transmitted when the fundamental component of received data for the previous ultrasonic pulse has not decreased to a negligible level.

[0034] Thus, the filtering technique has a problem that a good harmonic image cannot be obtained because the subsidiary fundamental component has a fundamental component of received data for a previous ultrasonic pulse intruding at a considerable intensity.

[0035] In the phase inversion technique, although the fundamental components are to be canceled out by addition, the fundamental component of received data for the ultrasonic pulse $fs-$ intrudes, for example, when the ultrasonic pulse $fm+$ is transmitted; and the fundamental component of received data for the ultrasonic pulse $fm+$ intrudes when the ultrasonic pulse $fm-$ is transmitted, as shown in FIG. 16. Thus, the intruding fundamental components cannot be canceled out because they are different, thereby also posing a problem that a good harmonic image cannot be obtained.

SUMMARY OF THE INVENTION

[0036] It is therefore an object of the present invention to provide an ultrasonic imaging method and ultrasonic diagnostic apparatus that eliminate a problem that a good harmonic image cannot be obtained due to a fundamental component of received data for a previous ultrasonic pulse intruding into a fundamental component of received data for a current ultrasonic pulse with a considerable intensity.

[0037] The present invention, in accordance with its first aspect, provides an ultrasonic imaging method for transmitting an ultrasonic pulse into a subject and receiving an ultrasonic echo from the subject corresponding to said ultrasonic pulse to generate received data, and acquiring harmonic-mode data employing a harmonic component from said received data, characterized in comprising: after transmitting an ultrasonic pulse to a focus on a certain acoustic line, transmitting a next ultrasonic pulse at a time interval such that no effect is received from an ultrasonic echo associated with said former ultrasonic pulse.

[0038] In the ultrasonic imaging method of the first aspect, since a next ultrasonic pulse is transmitted at a sufficient time interval after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a fundamental component of received data for a previous ultrasonic pulse is prevented from intruding into a fundamental component of received

data for a current ultrasonic pulse at a considerable intensity. Therefore, a good harmonic image can be obtained.

[0039] The present invention, in accordance with its second aspect, provides an ultrasonic imaging method for transmitting an ultrasonic pulse into a subject and receiving an ultrasonic echo from the subject corresponding to said ultrasonic pulse to generate received data, and acquiring harmonic-mode data employing a harmonic component from said received data, characterized in comprising: after transmitting an ultrasonic pulse to a focus on a certain acoustic line, transmitting a next ultrasonic pulse to a focus on an acoustic line spaced apart to a degree such that an ultrasonic pulse associated with said former ultrasonic pulse is negligible.

[0040] In the ultrasonic imaging method of the second aspect, since a next ultrasonic pulse is transmitted to a next focus sufficiently spaced apart after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a fundamental component of received data for a previous ultrasonic pulse is prevented from intruding into a fundamental component of received data for a current ultrasonic pulse at a considerable intensity. Therefore, a good harmonic image can be obtained.

[0041] The present invention, in accordance with its third aspect, provides an ultrasonic imaging method for transmitting a first ultrasonic pulse into a subject and receiving a first ultrasonic echo from the subject corresponding to said first ultrasonic pulse to generate first received data; next transmitting a second ultrasonic pulse of a phase opposite to that of said first ultrasonic pulse into the subject and receiving a second ultrasonic echo from the subject corresponding to said second ultrasonic pulse to generate second received data; and acquiring harmonic-mode data based on a sum of said first and second received data, characterized in comprising: after transmitting said first ultrasonic pulse, transmitting said second ultrasonic pulse at a time interval such that said second ultrasonic echo is not affected by said first ultrasonic pulse.

[0042] In the ultrasonic imaging method of the third aspect, since the second ultrasonic pulse is transmitted at a sufficient time interval after transmitting the first ultrasonic pulse, a fundamental component of received data for the first ultrasonic pulse is prevented from intruding into a fundamental component of received data for the second ultrasonic pulse at a considerable intensity. Therefore, a good harmonic image can be obtained.

[0043] The present invention, in accordance with its fourth aspect, provides an ultrasonic imaging method for transmitting a first ultrasonic pulse into a subject and receiving a first ultrasonic echo from the subject corresponding to said first ultrasonic pulse to generate first received data; next transmitting a second ultrasonic pulse of a phase opposite to that of said first ultrasonic pulse into the subject and receiving a second ultrasonic echo from the subject corresponding to said second ultrasonic pulse to generate second received data; and acquiring harmonic-mode data based on a sum of said first and second received data, characterized in comprising: sequentially transmitting said first ultrasonic pulse to a plurality of foci on the same acoustic line, and then sequentially transmitting said second ultrasonic pulse to the plurality of foci on the same acoustic line.

[0044] In the ultrasonic imaging method of the fourth aspect, since the fundamental component of received data

for an ultrasonic pulse transmitted before the first ultrasonic pulse, which component is to intrude into a fundamental component of received data for the first ultrasonic pulse, and the fundamental component of received data for an ultrasonic pulse transmitted before the second ultrasonic pulse, which component is to intrude into a fundamental component of received data for the second ultrasonic pulse, become identical, the intruding fundamental components are canceled out by addition. Therefore, a good harmonic image can be obtained.

[0045] The present invention, in accordance with its fifth aspect, provides an ultrasonic imaging method for transmitting a first ultrasonic pulse into a subject and receiving a first ultrasonic echo from the subject corresponding to said first ultrasonic pulse to generate first received data; next transmitting a second ultrasonic pulse of a phase opposite to that of said first ultrasonic pulse into the subject and receiving a second ultrasonic echo from the subject corresponding to said second ultrasonic pulse to generate second received data; and acquiring harmonic-mode data based on a sum of said first and second received data, characterized in comprising: between the transmission of said first ultrasonic pulse and the transmission of said second ultrasonic pulse to a certain focus, conducting transmission of said first or second ultrasonic pulse to one or more foci on one or more other acoustic lines.

[0046] In the ultrasonic imaging method of the fifth aspect, since, after transmitting the first ultrasonic pulse, the next ultrasonic pulse is transmitted to a next focus sufficiently spaced apart, and then the second ultrasonic pulse is transmitted, a fundamental component of received data for a previous ultrasonic pulse is prevented from intruding into fundamental components of received data for the first and second ultrasonic pulses at a considerable intensity. Therefore, the intruding fundamental component is prevented from obstructing obtainment of a good harmonic image.

[0047] The present invention, in accordance with its sixth aspect, provides the ultrasonic imaging method having the aforesaid configuration, characterized in that the time between transmission of an ultrasonic pulse and transmission of a next ultrasonic pulse is shortened as a corresponding focus is shallower.

[0048] In the ultrasonic imaging method of the sixth aspect, since the transmission interval for the ultrasonic pulses is shortened when the focus is shallower and an ultrasonic echo decays more rapidly, and the transmission interval for the ultrasonic pulses is lengthened when the focus is deeper and an ultrasonic echo decays more slowly, the frame rate can be increased without any harm in imaging.

[0049] The present invention, in accordance with its seventh aspect, provides the ultrasonic imaging method having the aforesaid configuration, characterized in that the transmission interval for the ultrasonic pulses in a B mode is shorter than the transmission interval for the ultrasonic pulses in a harmonic mode for the same focus.

[0050] In the ultrasonic imaging method of the seventh aspect, since the transmission interval for the ultrasonic pulses is longer in the harmonic mode in which the gain is larger, and the transmission interval for the ultrasonic pulses is shorter in the B mode in which the gain is smaller, the frame rate can be increased in the B mode without any harm in imaging.

[0051] The present invention, in accordance with its eighth aspect, provides the ultrasonic imaging method having the aforesaid configuration, characterized in that the transmission interval for the ultrasonic pulses in a harmonic mode is equal to the transmission interval for the ultrasonic pulses in a B mode for the same focus.

[0052] In the ultrasonic imaging method of the eighth aspect, since the transmission intervals for the ultrasonic pulses in the harmonic mode and in the B-mode are equal, the frame rate can be consistent.

[0053] The present invention, in accordance with its ninth aspect, provides an ultrasonic diagnostic apparatus comprising an ultrasonic probe; transmitting/receiving means for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data; harmonic-mode data generating means for acquiring harmonic-mode data employing a harmonic component from said received data; image producing means for producing a harmonic-mode image based on said harmonic-mode data; and display means for displaying said harmonic-mode image, characterized in that said transmitting/receiving means transmits, after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a next ultrasonic pulse at a time interval such that no effect is received from an ultrasonic echo associated with said former ultrasonic pulse.

[0054] In the ultrasonic diagnostic apparatus of the ninth aspect, the ultrasonic imaging method as described regarding the first aspect can be suitably implemented.

[0055] The present invention, in accordance with its tenth aspect, provides an ultrasonic diagnostic apparatus comprising an ultrasonic probe; transmitting/receiving means for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data; harmonic-mode data generating means for acquiring harmonic-mode data employing a harmonic component from said received data; image producing means for producing a harmonic-mode image based on said harmonic-mode data; and display means for displaying said harmonic-mode image, characterized in that said transmitting/receiving means transmits, after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a next ultrasonic pulse to a focus on an acoustic line spaced apart to a degree such that an ultrasonic pulse associated with said former ultrasonic pulse is negligible.

[0056] In the ultrasonic diagnostic apparatus of the tenth aspect, the ultrasonic imaging method as described regarding the second aspect can be suitably implemented.

[0057] The present invention, in accordance with its eleventh aspect, provides an ultrasonic diagnostic apparatus comprising an ultrasonic probe; transmitting/receiving means for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data; harmonic-mode data generating means for acquiring harmonic-mode data based on a sum of first received data corresponding to a first ultrasonic pulse and second received data corresponding to a second ultrasonic pulse of a phase opposite to said first ultrasonic pulse; image producing means for producing a harmonic-mode image based on said harmonic-mode data; and display means for displaying said harmonic-mode

image, characterized in that said transmitting/receiving means transmits, after transmitting said first ultrasonic pulse, said second ultrasonic pulse at a time interval such that said second ultrasonic echo is not affected by said first ultrasonic pulse.

[0058] In the ultrasonic diagnostic apparatus of the eleventh aspect, the ultrasonic imaging method as described regarding the third aspect can be suitably implemented.

[0059] The present invention, in accordance with its twelfth aspect, provides the ultrasonic diagnostic apparatus having the aforesaid configuration, characterized in that said transmitting/receiving means sequentially transmits said first ultrasonic pulse to a plurality of foci on the same acoustic line, and then sequentially transmits said second ultrasonic pulse to the plurality of foci on the same acoustic line.

[0060] In the ultrasonic diagnostic apparatus of the twelfth aspect, the ultrasonic imaging method as described regarding the fourth aspect can be suitably implemented.

[0061] The present invention, in accordance with its thirteenth aspect, provides the ultrasonic diagnostic apparatus having the aforesaid configuration, characterized in that said transmitting/receiving means conducts, between the transmission of said first ultrasonic pulse and the transmission of said second ultrasonic pulse to a certain focus, transmission of said first or second ultrasonic pulse to one or more foci on one or more other acoustic lines.

[0062] In the ultrasonic diagnostic apparatus of the thirteenth aspect, the ultrasonic imaging method as described regarding the fifth aspect can be suitably implemented.

[0063] The present invention, in accordance with its fourteenth aspect, provides the ultrasonic diagnostic apparatus having the aforesaid configuration, characterized in that said transmitting/receiving means shortens the time between transmission of an ultrasonic pulse and transmission of a next ultrasonic pulse as a corresponding focus is shallower.

[0064] In the ultrasonic diagnostic apparatus of the fourteenth aspect, the ultrasonic imaging method as described regarding the sixth aspect can be suitably implemented.

[0065] The present invention, in accordance with its fifteenth aspect, provides the ultrasonic diagnostic apparatus having the aforesaid configuration, characterized in that said transmitting/receiving means makes the transmission interval of ultrasonic pulses in a B mode shorter than the transmission interval of ultrasonic pulses in a harmonic mode for the same focus.

[0066] In the ultrasonic diagnostic apparatus of the fifteenth aspect, the ultrasonic imaging method as described regarding the seventh aspect can be suitably implemented.

[0067] The present invention, in accordance with its sixteenth aspect, provides the ultrasonic diagnostic apparatus having the aforesaid configuration, characterized in that said transmitting/receiving means makes the transmission interval of ultrasonic pulses in a harmonic mode equal to the transmission interval of ultrasonic pulses in a B mode for the same focus.

[0068] In the ultrasonic diagnostic apparatus of the sixteenth aspect, the ultrasonic imaging method as described regarding the eighth aspect can be suitably implemented.

[0069] According to the ultrasonic imaging method and ultrasonic diagnostic apparatus of the present invention, the intrusion of a fundamental component of received data for a previous ultrasonic pulse into a fundamental component of received data for a current ultrasonic pulse at a considerable intensity is prevented from obstructing obtainment of a good harmonic image, and hence, a good harmonic image can be obtained.

[0070] Further objects and advantages of the present invention will be apparent from the following description of the preferred embodiments of the invention as illustrated in the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0071] FIG. 1 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a first embodiment.

[0072] FIG. 2 is a timing chart showing the operation in a B mode in the ultrasonic diagnostic apparatus in accordance with the first embodiment.

[0073] FIG. 3 is a timing chart showing the operation in a harmonic mode in the ultrasonic diagnostic apparatus in accordance with the first embodiment.

[0074] FIG. 4 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a second embodiment.

[0075] FIG. 5 is a diagram for explaining acoustic lines constituting a frame and foci on the acoustic lines.

[0076] FIG. 6 is a timing chart showing the operation in a harmonic mode in the ultrasonic diagnostic apparatus in accordance with the second embodiment.

[0077] FIG. 7 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a third embodiment.

[0078] FIG. 8 is a timing chart showing the operation in a harmonic mode in the ultrasonic diagnostic apparatus in accordance with the third embodiment.

[0079] FIG. 9 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a fourth embodiment.

[0080] FIG. 10 is a timing chart showing the operation in a harmonic mode in the ultrasonic diagnostic apparatus in accordance with the fourth embodiment.

[0081] FIG. 11 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a fifth embodiment.

[0082] FIG. 12 is a diagram for explaining acoustic lines constituting a frame and foci on the acoustic lines.

[0083] FIG. 13 is a timing chart showing the operation in a harmonic mode in the ultrasonic diagnostic apparatus in accordance with the fifth embodiment.

[0084] FIG. 14 is a timing chart showing the operation in a B mode in a conventional ultrasonic diagnostic apparatus.

[0085] FIG. 15 is a timing chart showing the operation in a harmonic mode according to a filtering technique in the conventional ultrasonic diagnostic apparatus.

[0086] FIG. 16 is a timing chart showing the operation in a harmonic mode according to a phase inversion technique in the conventional ultrasonic diagnostic apparatus.

DETAILED DESCRIPTION OF THE INVENTION

[0087] The present invention will now be described in more detail with reference to several embodiments shown in the accompanying drawings.

[0088] First Embodiment

[0089] FIG. 1 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a first embodiment.

[0090] The ultrasonic diagnostic apparatus 10 comprises an ultrasonic probe 1, a transmitting/receiving section 12 for driving the ultrasonic probe 1 to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data, a filtering section 13 for acquiring harmonic-mode data employing a harmonic component from the received data, a mode switching section 4 for switching between a B mode and a harmonic mode, a B-mode processing section 5 for generating image data from the received data or harmonic-mode data, a DSC 6 for generating image display data, and a CRT 7 for displaying an image.

[0091] FIG. 2 is an explanatory diagram showing imaging timing when a B mode is selected at the mode switching section 4.

[0092] In FIG. 2, a fundamental component is indicated by a solid line and a harmonic component by a broken line because the fundamental component is principal and the harmonic component is subsidiary in the B mode.

[0093] When an ultrasonic pulse fs with a relatively shallow (e.g., 5 cm) focus is transmitted at a time t1, the fundamental component of received data (i.e., a component of received data having the same frequency as the transmission frequency) indicated by the solid line in FIG. 2 has an intensity decreasing over time with a maximum at the time t1. The harmonic component (i.e., a component of received data having a frequency twice as high as the transmission frequency) of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t1.

[0094] A time t2 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse fs transmitted at the time t1 decreases to a negligible level (e.g., the component becomes smaller than a noise component or a detection sensitivity).

[0095] When an ultrasonic pulse fm with a relatively intermediate (e.g., 10 cm) focus is transmitted at the time t2, the fundamental component of received data indicated by the solid line in FIG. 2 has an intensity decreasing over time with a maximum at the time t2. The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t2.

[0096] A time t3 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse fm transmitted at the time t2 decreases to a negligible level.

[0097] When an ultrasonic pulse f_d with a relatively deep (e.g., 15 cm) focus is transmitted at the time t_3 , the fundamental component of received data indicated by the solid line in FIG. 2 has an intensity decreasing over time with a maximum at the time t_3 . The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_3 .

[0098] A time t_4 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_d transmitted at the time t_3 decreases to a negligible level.

[0099] When an ultrasonic pulse f_s with a relatively shallow (e.g., 5 cm) focus is transmitted at the time t_4 , the fundamental component of received data indicated by the solid line in FIG. 2 has an intensity decreasing over time with a maximum at the time t_4 . The harmonic component of the received data indicated by the broken line has an intensity rapidly decreasing over time with a maximum slightly after the time t_4 .

[0100] A similar operation is repeated thereafter.

[0101] The frame rate is $1/(\tau_s + \tau_m + \tau_d) \cdot N$, where the interval between the times t_1 and t_2 is represented by τ_s , the interval between the times t_2 and t_3 is represented by τ_m , the interval between the times t_3 and t_4 is represented by τ_d , the ultrasonic pulses f_s , f_m and f_d gives one acoustic line, and the number of acoustic lines in one frame is N . Moreover, $\tau_s < \tau_m < \tau_d$.

[0102] If the transmission intervals for the ultrasonic pulses f_s , f_m and f_d are uniformly set to τ_s , the received data for the ultrasonic pulse f_m remains at a considerable intensity when reception of received data for the ultrasonic pulse f_d is started, compromising imaging. Moreover, the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0103] If the intervals are uniformly set to τ_m , the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0104] On the other hand, the intervals uniformly set to τ_d do no harm in imaging.

[0105] However, the frame rate is $1/(3 \cdot \tau_d) \cdot N$, which is lower than that in FIG. 2.

[0106] In other words, the ultrasonic pulses f_s , f_m and f_d are transmitted at timing as shown in FIG. 2 so that a higher frame rate can be achieved.

[0107] FIG. 3 is an explanatory diagram showing imaging timing when a harmonic mode is selected at the mode switching section 4.

[0108] In FIG. 3, a harmonic component is indicated by a solid line and a fundamental component by a broken line because the harmonic component is principal and the fundamental component is subsidiary in the harmonic mode. Moreover, the gain is increased to acquire large harmonic components that are inherently small, and accordingly, the fundamental components become larger.

[0109] When an ultrasonic pulse f_s with a relatively shallow focus is transmitted at a time t_1 , the fundamental component of received data indicated by the broken line in FIG. 3 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0110] A time T_2 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_s transmitted at the time t_1 decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_s + \Delta s)$ from the time t_1 to the time T_2 is longer than the time period τ_s in the B mode.

[0111] When an ultrasonic pulse f_m with a relatively intermediate focus is transmitted at the time T_2 , the fundamental component of received data indicated by the broken line in FIG. 3 has an intensity decreasing over time with a maximum at the time T_2 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_2 .

[0112] A time T_3 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_m transmitted at the time T_2 decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_m + \Delta m)$ from the time T_2 to the time T_3 is longer than the time period τ_m in the B mode.

[0113] When an ultrasonic pulse f_d with a relatively deep focus is transmitted at the time T_3 , the fundamental component of received data indicated by the broken line in FIG. 3 has an intensity decreasing over time with a maximum at the time T_3 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_3 .

[0114] A time T_4 is a time point when the intensity of the fundamental component of the received data for the ultrasonic pulse f_d transmitted at the time T_3 decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_d + \Delta d)$ from the time T_3 to the time T_4 is longer than the time period τ_d in the B mode.

[0115] When an ultrasonic pulse f_s with a relatively shallow focus is transmitted at the time T_4 , the fundamental component of received data indicated by the broken line in FIG. 3 has an intensity decreasing over time with a maximum at the time T_4 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_4 .

[0116] A similar operation is repeated thereafter.

[0117] The frame rate is $1/(\tau_s + \Delta s + \tau_m + \Delta m + \tau_d + \Delta d) \cdot N$, where the ultrasonic pulses f_s , f_m and f_d gives one acoustic line, and the number of acoustic lines in one frame is N . Moreover, $\tau_s + \Delta s < \tau_m + \Delta m < \tau_d + \Delta d$.

[0118] If the transmission intervals for the ultrasonic pulses f_s , f_m and f_d are uniformly set to $\tau_s + \Delta s$, the received data for the ultrasonic pulse f_m remains at a considerable

intensity when reception of received data for the ultrasonic pulse f_d is started, compromising imaging. Moreover, the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0119] If the intervals are uniformly set to $\tau_m + \Delta m$, the received data for the ultrasonic pulse f_d remains at a considerable intensity when reception of received data for the ultrasonic pulse f_s is started, compromising imaging.

[0120] On the other hand, the intervals uniformly set to $\tau_d + \Delta d$ do no harm in imaging.

[0121] However, the frame rate is $1/\{3 \cdot (\tau_d + \Delta d)\} \div N$, which is lower than that in FIG. 3.

[0122] In other words, by transmitting the ultrasonic pulses f_s , f_m and f_d at timing as shown in FIG. 3, a high frame rate can be achieved. Moreover, since a current ultrasonic pulse is transmitted after the fundamental component of received data for a previous ultrasonic pulse has decreased to a negligible intensity, harm due to intrusion is prevented, thus providing a good harmonic image.

[0123] Second Embodiment

[0124] FIG. 4 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a second embodiment.

[0125] The ultrasonic diagnostic apparatus 20 comprises an ultrasonic probe 1, a transmitting/receiving section 22 for driving the ultrasonic probe 1 to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data, a filtering section 13 for acquiring harmonic-mode data employing a harmonic component from the received data, a mode switching section 4 for switching between a B mode and a harmonic mode, a B-mode processing section 5 for generating image data from the received data or harmonic-mode data, a DSC 6 for generating image display data, and a CRT 7 for displaying an image.

[0126] The imaging timing when the B mode is selected at the mode switching section 4 is the same as that in FIG. 2 (first embodiment).

[0127] FIG. 5 is a conceptual diagram of acoustic lines constituting one frame.

[0128] It is assumed that one acoustic line is acquired by an ultrasonic pulse f_s with a shallow focus, an ultrasonic pulse f_m with an intermediate focus, and an ultrasonic pulse f_d with a deep focus, and one frame is formed by acoustic lines #0-#5 in different directions.

[0129] FIG. 6 is an explanatory diagram showing imaging timing when a harmonic mode is selected at the mode switching section 4.

[0130] When an ultrasonic pulse #0 f_s with a relatively shallow focus on the acoustic line #0 is transmitted at a time t_1 , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0131] A time t_2 is after a time period τ_s from the time t_1 as in the B mode.

[0132] When an ultrasonic pulse #3 f_s with a relatively shallow focus on the acoustic line #3 is transmitted at the time t_2 , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_2 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_2 .

[0133] The time period τ_s from the time t_1 to the time t_2 is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0 f_s intrudes into the fundamental component for the ultrasonic pulse #3 f_s , it is at a negligible degree.

[0134] A time t_3' is after a time period τ_s from the time t_2 .

[0135] When an ultrasonic pulse #0 f_m with a relatively intermediate focus on the acoustic line #0 is transmitted at the time t_3' , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_3' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_3' .

[0136] The time period τ_s from the time t_2 to the time t_3' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #3 f_s intrudes into the fundamental component for the ultrasonic pulse #0 f_m , it is at a negligible degree.

[0137] A time t_4' is after a time period τ_m from the time t_3' .

[0138] When an ultrasonic pulse #3 f_m with a relatively intermediate focus on the acoustic line #3 is transmitted at the time t_4' , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_4' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_4' .

[0139] The time period τ_m from the time t_3' to the time t_4' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0 f_m intrudes into the fundamental component for the ultrasonic pulse #3 f_m , it is at a negligible degree.

[0140] A time t_5' is after a time period τ_m from the time t_4' .

[0141] When an ultrasonic pulse #0 f_d with a relatively deep focus on the acoustic line #0 is transmitted at the time t_5' , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_5' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_5' .

[0142] The time period τ_m from the time t_4' to the time t_5' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #3fm intrudes into the fundamental component for the ultrasonic pulse #0fd, it is at a negligible degree.

[0143] A time t_6' is after a time period τ_d from the time t_5' .

[0144] When an ultrasonic pulse #3fd with a relatively deep focus on the acoustic line #3 is transmitted at the time t_6' , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_6' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_6' .

[0145] The time period τ_d from the time t_5' to the time t_6' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0fd intrudes into the fundamental component for the ultrasonic pulse #3fd, it is at a negligible degree.

[0146] A time t_7' is after a time period τ_d from the time t_6' .

[0147] When an ultrasonic pulse #1fs with a relatively shallow focus on the acoustic line #1 is transmitted at the time t_7' , the fundamental component of received data indicated by the broken line in FIG. 6 has an intensity decreasing over time with a maximum at the time t_7' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_7' .

[0148] The time period τ_d from the time t_6' to the time t_7' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #1 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #3fd intrudes into the fundamental component for the ultrasonic pulse #1fs, it is at a negligible degree.

[0149] A similar operation is repeated thereafter.

[0150] The frame rate is $1/(\tau_s + \tau_m + \tau_d) \times N$, i.e., a frame rate as high as that in the B-mode can be achieved. Moreover, since a current ultrasonic pulse is transmitted to a focus on an acoustic line in a different direction such that the fundamental component of received data for a previous ultrasonic pulse can be neglected, harm due to intrusion is prevented, thus providing a good harmonic image.

[0151] Third Embodiment

[0152] FIG. 7 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a third embodiment.

[0153] The ultrasonic diagnostic apparatus 30 comprises an ultrasonic probe 1, a transmitting/receiving section 32 for driving the ultrasonic probe 1 to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data, a memory 8 for storing first received data corresponding to a first ultrasonic pulse, an adder 9 for acquiring harmonic-mode data by adding second received data corresponding to a second ultrasonic pulse of a phase

opposite to the first ultrasonic pulse and the first received data stored in the memory 8, a mode switching section 4 for switching between a B mode and a harmonic mode, a B-mode processing section 5 for generating image data from the received data or harmonic-mode data, a DSC 6 for generating image display data, and a CRT 7 for displaying an image.

[0154] The imaging timing when the B mode is selected at the mode switching section 4 is the same as that in FIG. 2 (first embodiment).

[0155] FIG. 8 is an explanatory diagram showing imaging timing when a harmonic mode is selected at the mode switching section 4.

[0156] When a first ultrasonic pulse fs_+ with a relatively shallow focus is transmitted at a time t_1 , the fundamental component of first received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0157] A time t_2'' is a time point when the intensity of the fundamental component of the first received data for the first ultrasonic pulse fs_+ transmitted at the time t_1 decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_s + \delta_s)$ from the time t_1 to the time t_2'' is longer the time period τ_s in the B mode.

[0158] When a second ultrasonic pulse fs_- with a relatively shallow focus and of a phase opposite to that of the first ultrasonic pulse fs_+ is transmitted at the time t_2'' , the fundamental component of second received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time t_2'' . The harmonic component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_2'' .

[0159] A time t_3'' is a time point when the intensity of the fundamental component of the second received data for the second ultrasonic pulse fs_- transmitted at the time t_2'' decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_s + \delta_s)$ from the time t_2'' to the time t_3'' is longer the time period τ_s in the B mode.

[0160] When a first ultrasonic pulse fm_+ with a relatively intermediate focus is transmitted at the time t_3'' , the fundamental component of first received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time t_3'' . The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_3'' .

[0161] A time t_4'' is a time point when the intensity of the fundamental component of the first received data for the first ultrasonic pulse fm_+ transmitted at the time t_3'' decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau_m + \delta_m)$ from the time t_3'' to the time t_4'' is longer the time period τ_m in the B mode.

[0162] When a second ultrasonic pulse $fm-$ with a relatively intermediate focus and of a phase opposite to that of the first ultrasonic pulse $fm+$ is transmitted at the time $t4''$, the fundamental component of second received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time $t4''$. The harmonic component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t4''$.

[0163] A time $t5''$ is a time point when the intensity of the fundamental component of the second received data for the second ultrasonic pulse $fm-$ transmitted at the time $t4''$ decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau m + \delta m)$ from the time $t4''$ to the time $t5''$ is longer than the time period τm in the B mode.

[0164] When a first ultrasonic pulse $fd+$ with a relatively deep focus is transmitted at the time $t5''$, the fundamental component of first received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time $t5''$. The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t5''$.

[0165] A time $t6''$ is a time point when the intensity of the fundamental component of the first received data for the first ultrasonic pulse $fd+$ transmitted at the time $t5''$ decreases to a negligible level. Since the fundamental component is larger than that in the B mode as described above, the time period $(\tau d + \delta d)$ from the time $t5''$ to the time $t6''$ is longer than the time period τd in the B mode.

[0166] When a second ultrasonic pulse $fd-$ with a relatively deep focus and of a phase opposite to that of the first ultrasonic pulse $fd+$ is transmitted at the time $t6''$, the fundamental component of second received data indicated by the broken line in FIG. 8 has an intensity decreasing over time with a maximum at the time $t6''$. The harmonic component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t6''$.

[0167] A similar operation is repeated thereafter.

[0168] Adding the first and second received data at the adder 9, the fundamental components are canceled out because their phases are opposite, and the harmonic components are doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0169] In the phase inversion technique shown in FIG. 8, since the fundamental component of received data for a previous ultrasonic pulse is decreased to a negligible intensity when transmitting a certain ultrasonic pulse, the previous fundamental component is prevented from intruding, thus providing a good harmonic image.

[0170] Fourth Embodiment

[0171] FIG. 9 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a fourth embodiment.

[0172] The ultrasonic diagnostic apparatus 40 comprises an ultrasonic probe 1, a transmitting/receiving section 42 for driving the ultrasonic probe 1 to transmit an ultrasonic pulse

into a subject and receive an ultrasonic echo from the subject to output received data, a memory 8s for storing first received data corresponding to a first ultrasonic pulse with a relatively shallow focus, a memory 8m for storing first received data corresponding to a first ultrasonic pulse with a relatively intermediate focus, a memory 8d for storing first received data corresponding to a first ultrasonic pulse with a relatively deep focus, a selector 43 for selecting from among the memories 8s, 8m and 8d, an adder 9 for acquiring harmonic-mode data by adding second received data corresponding to a second ultrasonic pulse of a phase opposite to that of the first ultrasonic pulse and the first received data selected by the selector 43, a mode switching section 4 for switching between a B mode and a harmonic mode, a B-mode processing section 5 for generating image data from the received data or harmonic-mode data, a DSC 6 for generating image display data, and a CRT 7 for displaying an image.

[0173] The imaging timing when the B mode is selected at the mode switching section 4 is the same as that in FIG. 2 (first embodiment).

[0174] FIG. 10 is an explanatory diagram showing imaging timing when a harmonic mode is selected at the mode switching section 4.

[0175] When a first ultrasonic pulse $fs+$ with a relatively shallow focus is transmitted at a time $t1$, the fundamental component of first received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time $t1$. The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t1$.

[0176] A time $t2$ is after a time period τs from the time $t1$ as in the B mode.

[0177] When a first ultrasonic pulse $fm+$ with a relatively intermediate focus is transmitted at the time $t2$, the fundamental component of first received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time $t2$. The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t2$.

[0178] A time $t3$ is after a time period τm from the time $t2$ as in the B mode.

[0179] When a first ultrasonic pulse $fd+$ with a relatively deep focus is transmitted at the time $t3$, the fundamental component of first received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time $t3$. The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time $t3$.

[0180] A time $t4$ is after a time period τd from the time $t3$ as in the B mode.

[0181] When a second ultrasonic pulse $fs-$ with a relatively shallow focus and of a phase opposite to that of the first ultrasonic pulse $fs+$ is transmitted at the time $t4$, the fundamental component of second received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time $t4$. The harmonic

component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_4 .

[0182] A time t_5 is after a time period τ_s from the time t_4 as in the B mode.

[0183] When a second ultrasonic pulse $fm-$ with a relatively intermediate focus and of a phase opposite to that of the first ultrasonic pulse $fm+$ is transmitted at the time t_5 , the fundamental component of second received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time t_5 . The harmonic component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_5 .

[0184] A time t_6 is after a time period τ_m from the time t_5 as in the B mode.

[0185] When a second ultrasonic pulse $fd-$ with a relatively deep focus and of a phase opposite to that of the first ultrasonic pulse $fd+$ is transmitted at the time t_6 , the fundamental component of second received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time t_6 . The harmonic component of the second received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_6 .

[0186] A time t_7 is after a time period τ_d from the time t_6 as in the B mode.

[0187] When a first ultrasonic pulse $fs+$ with a relatively shallow focus on a next acoustic line is transmitted at the time t_7 , the fundamental component of first received data indicated by the broken line in FIG. 10 has an intensity decreasing over time with a maximum at the time t_7 . The harmonic component of the first received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_7 .

[0188] A similar operation is repeated thereafter.

[0189] Adding the first and second received data at the adder 9, the fundamental components are canceled out because their phases are opposite, and the harmonic components are doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0190] In the phase inversion technique shown in FIG. 10, the fundamental component of received data for the ultrasonic pulse $fs+$ intrudes when transmitting the first ultrasonic pulse $fm+$ at the time t_2 , for example, and the fundamental component of received data for the ultrasonic pulse $fs-$ intrudes when transmitting the second ultrasonic pulse $fm-$ at the time t_5 . Thus, since the intruding fundamental components are the same and of opposite phases, they are canceled out, thereby providing a good harmonic image.

[0191] Fifth Embodiment

[0192] FIG. 11 is a configuration diagram showing an ultrasonic diagnostic apparatus in accordance with a fifth embodiment.

[0193] The ultrasonic diagnostic apparatus 50 comprises an ultrasonic probe 1, a transmitting/receiving section 52 for driving the ultrasonic probe 1 to transmit an ultrasonic pulse

into a subject and receive an ultrasonic echo from the subject to output received data, a memory 8a for storing first received data corresponding to a first ultrasonic pulse for a certain acoustic line, a memory 8b for storing first received data corresponding to a first ultrasonic pulse for another acoustic line, a selector 53 for selecting from among the memories 8a and 8b, an adder for acquiring harmonic-mode data by adding second received data corresponding to a second ultrasonic pulse of a phase opposite to that of the first ultrasonic pulse, and a first received data selected by the selector 53, a mode switching section 4 for switching between a B mode and a harmonic mode, a B-mode processing section 5 for generating image data from the received data or harmonic-mode data, a DSC 6 for generating image display data, and a CRT 7 for displaying an image.

[0194] The imaging timing when the B mode is selected at the mode switching section 4 is the same as that in FIG. 2 (first embodiment).

[0195] FIG. 12 is a conceptual diagram of acoustic lines constituting one frame.

[0196] It is assumed that one acoustic line is acquired by an ultrasonic pulse fs with a shallow focus, an ultrasonic pulse fm with an intermediate focus, and an ultrasonic pulse fd with a deep focus, and one frame is formed by acoustic lines #0-#5 in different directions.

[0197] FIG. 13 is an explanatory diagram showing imaging timing when a harmonic mode is selected at the mode switching section 4.

[0198] When a first ultrasonic pulse #0 $fs+$ with a relatively shallow focus on the acoustic line #0 is transmitted at a time t_1 , the fundamental component of received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time t_1 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_1 .

[0199] A time t_2 is after a time period τ_s from the time t_1 as in the B mode.

[0200] When a first ultrasonic pulse #3 $fs+$ with a relatively shallow focus on the acoustic line #3 is transmitted at the time t_2 , the fundamental component of received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time t_2 . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_2 .

[0201] The time period τ_s from the time t_1 to the time t_2 is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0 $fs+$ intrudes into the fundamental component for the ultrasonic pulse #3 $fs+$, it is at a negligible degree.

[0202] A time t_3' is after a time period τ_s from the time t_2 .

[0203] When a second ultrasonic pulse #0 $fs-$ with a relatively shallow focus on the acoustic line #0 and of a phase opposite to that of the first ultrasonic pulse #0 $fs+$ is transmitted at the time t_3' , the fundamental component of

received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time t_3' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time t_3' .

[0204] The time period τ_s from the time t_2 to the time t_3' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #3fs+ intrudes into the fundamental component for the ultrasonic pulse #0fs-, it is at a negligible degree.

[0205] A time T_4' is after a time period τ_s from the time t_3' .

[0206] When a second ultrasonic pulse #3fs- with a relatively shallow focus on the acoustic line #3 and of a phase opposite to that of the first ultrasonic pulse #3fs+ is transmitted at the time T_4' , the fundamental component of received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time T_4' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_4' .

[0207] The time period τ_s from the time t_3' to the time T_4' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0fs- intrudes into the fundamental component for the ultrasonic pulse #3fs-, it is at a negligible degree.

[0208] A time T_5' is after a time period τ_s from the time T_4' .

[0209] When a first ultrasonic pulse #0fm+ with a relatively intermediate focus on the acoustic line #0 is transmitted at the time T_5' , the fundamental component of received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time T_5' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_5' .

[0210] The time period τ_s from the time T_4' to the time T_5' is the same as that in the B mode in spite of the larger fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #3fs- intrudes into the fundamental component for the ultrasonic pulse #0fm+, it is at a negligible degree.

[0211] A time T_6' is after a time period τ_m from the time T_5' .

[0212] When a first ultrasonic pulse #3fm+ with a relatively intermediate focus on the acoustic line #3 is transmitted at the time T_6' , the fundamental component of received data indicated by the broken line in FIG. 13 has an intensity decreasing over time with a maximum at the time T_6' . The harmonic component of the received data indicated by the solid line has an intensity rapidly decreasing over time with a maximum slightly after the time T_6' .

[0213] The time period τ_m from the time T_5' to the time T_6' is the same as that in the B mode in spite of the larger

fundamental component. However, since the acoustic lines #0 and #3 are in different directions, even if the fundamental component for the ultrasonic pulse #0fm+ intrudes into the fundamental component for the ultrasonic pulse #3fm+, it is at a negligible degree.

[0214] A similar operation is repeated thereafter.

[0215] Adding the first and second received data at the adder 9, the fundamental components are canceled out because their phases are opposite, and the harmonic components are doubled because they are in phase. That is, solely the harmonic components can be obtained.

[0216] In the phase inversion technique shown in FIG. 13, since a current ultrasonic pulse is transmitted to a focus on an acoustic line in a different direction such that the fundamental component of received data for a previous ultrasonic pulse can be neglected, harm due to intrusion is prevented, thus providing a good harmonic image.

[0217] Many widely different embodiments of the invention may be constructed without departing from the spirit and the scope of the present invention. It should be understood that the present invention is not limited to the specific embodiments described in the specification, except as defined in the appended claims.

1. An ultrasonic diagnostic apparatus comprising:

an ultrasonic probe;

a transmitting/receiving device for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data;

a harmonic-mode data generating device for acquiring harmonic-mode data employing a harmonic component from said received data;

an image producing device for producing a harmonic-mode image based on said harmonic-mode data; and

a display device for displaying said harmonic-mode image, wherein said transmitting/receiving device transmits, after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a next ultrasonic pulse at a time interval such that no effect is received from an ultrasonic echo associated with said former ultrasonic pulse.

2. An ultrasonic diagnostic apparatus comprising:

an ultrasonic probe;

a transmitting/receiving device for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data;

a harmonic-mode data generating device for acquiring harmonic-mode data employing a harmonic component from said received data;

an image producing device for producing a harmonic-mode image based on said harmonic-mode data; and

a display device for displaying said harmonic-mode image, wherein said transmitting/receiving device transmits, after transmitting an ultrasonic pulse to a focus on a certain acoustic line, a next ultrasonic pulse to a focus on an acoustic line spaced apart to a degree

such that an ultrasonic pulse associated with said former ultrasonic pulse is negligible.

3. An ultrasonic diagnostic apparatus comprising:

an ultrasonic probe;

a transmitting/receiving device for driving said ultrasonic probe to transmit an ultrasonic pulse into a subject and receive an ultrasonic echo from the subject to output received data;

a harmonic-mode data generating device for acquiring harmonic-mode data based on a sum of first received data corresponding to a first ultrasonic pulse and second received data corresponding to a second ultrasonic pulse of a phase opposite to said first ultrasonic pulse;

an image producing device for producing a harmonic-mode image based on said harmonic-mode data; and

a display device for displaying said harmonic-mode image,

wherein said transmitting/receiving device transmits, after transmitting said first ultrasonic pulse, said second ultrasonic pulse at a time interval such that said second ultrasonic echo is not affected by said first ultrasonic pulse.

4. The ultrasonic diagnostic apparatus of any one of claims **1** through **3**, wherein said transmitting/receiving device sequentially transmits said first ultrasonic pulse to a

plurality of foci on the same acoustic line, and then sequentially transmits said second ultrasonic pulse to the plurality of foci on the same acoustic line.

5. The ultrasonic diagnostic apparatus of any one of claims **1** through **3**, wherein said transmitting/receiving device conducts, between the transmission of said first ultrasonic pulse and the transmission of said second ultrasonic pulse to a certain focus, transmission of said first or second ultrasonic pulse to one or more foci on one or more other acoustic lines.

6. The ultrasonic diagnostic apparatus of any one of claims **1** through **3**, wherein said transmitting/receiving device shortens the time between transmission of an ultrasonic pulse and transmission of a next ultrasonic pulse as a corresponding focus is shallower.

7. The ultrasonic diagnostic apparatus of any one of claims **1** through **3**, wherein said transmitting/receiving device makes the transmission interval of ultrasonic pulses in a B mode shorter than the transmission interval of ultrasonic pulses in a harmonic mode for the same focus.

8. The ultrasonic diagnostic apparatus of any one of claims **1** through **3**, wherein said transmitting/receiving device makes the transmission interval of ultrasonic pulses in a harmonic mode equal to the transmission interval of ultrasonic pulses in a B mode for the same focus.

* * * * *

专利名称(译)	超声诊断设备		
公开(公告)号	US20030060709A1	公开(公告)日	2003-03-27
申请号	US10/246057	申请日	2002-09-18
[标]申请(专利权)人(译)	桥本HIROSHI 雨宫SHINICHI		
申请(专利权)人(译)	桥本HIROSHI 雨宫SHINICHI		
当前申请(专利权)人(译)	桥本HIROSHI 雨宫SHINICHI		
[标]发明人	HASHIMOTO HIROSHI AMEMIYA SHINICHI		
发明人	HASHIMOTO, HIROSHI AMEMIYA, SHINICHI		
IPC分类号	A61B8/14 A61B8/00 B06B1/02 G01S7/52		
CPC分类号	B06B1/0215 B06B2201/76 G01S7/52026 G01S7/52046 G01S7/5206 G01S15/8963 G01S7/52085		
优先权	2001287989 2001-09-21 JP		
其他公开文献	US6692440		
外部链接	Espacenet USPTO		

摘要(译)

为了消除由于先前接收的数据的基本分量的尾部侵入当前接收数据的基本分量而不能获得良好谐波图像的问题;在根据相位反转技术的谐波模式的操作中,第一超声波脉冲被顺序地发送到同一声线上的多个焦点,并且第二超声波脉冲的相位与第一超声波脉冲的相位相反。在同一声线上传输到多个焦点。

