



US009603580B2

(12) **United States Patent**
Chaggares et al.

(10) **Patent No.:** **US 9,603,580 B2**
(45) **Date of Patent:** **Mar. 28, 2017**

(54) **HIGH FREQUENCY ULTRASOUND PROBE**
(71) Applicant: **FUJIFILM Sonosite, Inc.**, Bothell, WA (US)
(72) Inventors: **Nicholas Christopher Chaggares**, Oshawa (CA); **Eric Rieder**, Ajax (CA)
(73) Assignee: **FUJIFILM SonoSite, Inc.**, Bothell, WA (US)
(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 165 days.

(21) Appl. No.: **14/286,918**
(22) Filed: **May 23, 2014**

(65) **Prior Publication Data**
US 2014/0350407 A1 Nov. 27, 2014

Related U.S. Application Data
(60) Provisional application No. 61/827,524, filed on May 24, 2013.
(51) **Int. Cl.**
A61B 8/14 (2006.01)
A61B 8/00 (2006.01)
B06B 1/06 (2006.01)
A61B 8/08 (2006.01)
(52) **U.S. Cl.**
CPC *A61B 8/4444* (2013.01); *A61B 8/4488* (2013.01); *B06B 1/0622* (2013.01); *A61B 8/5207* (2013.01)
(58) **Field of Classification Search**
USPC 600/459
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,223,741 A *	6/1993	Bechtel	H01L 23/057 257/678
8,316,518 B2	11/2012	Lukacs et al.	
2003/0018267 A1 *	1/2003	Erikson	A61B 8/4483 600/459
2007/0167820 A1	7/2007	Hirayama et al.	
2007/0293762 A1	12/2007	Sawada et al.	
2008/0002460 A1	1/2008	Tuckerman et al.	
2009/0108708 A1 *	4/2009	Jiang	B06B 1/0622 310/334
2009/0193874 A1	8/2009	Cobianu et al.	
2009/0278217 A1	11/2009	Laming et al.	
2012/0019106 A1 *	1/2012	Spigelmyer	B06B 1/0292 310/348
2012/0025335 A1 *	2/2012	Leclair	H01L 23/057 257/416


(Continued)

FOREIGN PATENT DOCUMENTS
WO WO-2007061216 5/2007

OTHER PUBLICATIONS
International Searching Authority, International Search Report and Written Opinion, PCT Patent Application PCT/US2014/039449, mailed Oct. 22, 2014, 8 pages.
Primary Examiner — Joel F Brutus
(74) *Attorney, Agent, or Firm* — Perkins Coie LLP

(57) **ABSTRACT**
A high frequency ultrasound probe includes a substrate having a number of transducer elements on it and a ground plane that is electrically coupled by one or more vias to a conductive frame that supports the substrate. The conductive frame is electrically coupled to a ground plane of a printed circuit having conductors that are coupled to the transducer elements.

13 Claims, 8 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

2012/0098625 A1 4/2012 Martin et al.
2012/0104629 A1* 5/2012 Bologna B81B 7/0064
257/774
2013/0019702 A1 1/2013 Oberdoerfer et al.

* cited by examiner




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12




Fig. 13




Fig. 14




Fig. 15

HIGH FREQUENCY ULTRASOUND PROBE**CROSS-REFERENCES TO RELATED APPLICATIONS**

This application claims benefit of and priority to U.S. Provisional Patent Application Ser. No. 61/827,524, filed on May 24, 2013, and entitled "HIGH FREQUENCY ULTRASOUND PROBE," which is hereby incorporated herein in its entirety by reference.

TECHNICAL FIELD

The disclosed technology generally relates to the fields of ultrasonic transducers and medical diagnostic imaging. More specifically, the disclosed technology relates to high frequency ultrasonic transducers and corresponding methods of assembly.

BACKGROUND

Ultrasonic transducers provide a means for converting electrical energy into acoustic energy and vice versa. When the electrical energy is in the form of an RF signal, a correctly designed transducer can produce ultrasonic signals with the same frequency characteristics as the driving electrical RF signal. Diagnostic ultrasound has traditionally been used at center frequencies ranging from less than 1 MHz to about 10 MHz. One skilled in the art will understand that this frequency spectrum provides a means of imaging biological tissue with resolution ranging from several mm to generally greater than 300 μ m and at depths from a few mm down to 10 s of cm.

High frequency ultrasonic transducers are generally ultrasonic transducers with center frequencies above 15 MHz and ranging to over 60 MHz. High frequency ultrasonic transducers provide higher resolution while limiting the maximum depth of penetration, and as such, provide a means of imaging biological tissue from a depth of a fraction of a mm to over 3 cm with resolutions in the 20 μ m to over 300 μ m range.

There are many challenges associated with fabricating high frequency ultrasonic transducers that do not arise when working with traditional clinical ultrasonic transducers that operate at frequencies below about 10 MHz. One skilled in the art will understand that structures generally scale down according to the inverse of the frequency, so that a 50 MHz transducer will have structures about 10 times smaller than a 5 MHz transducer. In some cases, materials or techniques cannot be scaled down to the required size or shape, or in doing so they lose their function and new technologies must be developed or adapted to allow high frequency ultrasonic transducers to be realized. In other cases, entirely new requirements exist when dealing with the higher radio frequency electronic and acoustic signals associated with HFUS transducers.

RF electrical interconnections require that some form of transmission line be employed to effectively contain the magnetic fields surrounding the signal and ground conductors. One skilled in the art will appreciate that depending on the frequencies being transmitted, and the length of the conductors, electrical impedance matching and shielding techniques must be employed for optimal performance. One skilled in the art will further appreciate that at lower clinical frequencies, such interconnections are highly developed and available in a wide variety of options to the ultrasound system and transducer designers and that such intercon-

nections typically consist of several components as follows: First, a connection to the ultrasound system, which typically consists of a zero insertion force (ZIF) type or other large format connector; second, the electrical cables running from the system connector toward the transducer (typically micro-coaxial transmission lines); third, an interface between the cables and the transducer usually including connectors and/or a printed circuit board; and finally, an interface from the connector or circuit board to each of the transducer elements. This typical set of components is readily available in the industry, with many variations being successfully employed for traditional clinical frequency US transducers.

One skilled in the art will appreciate that some of these components will readily scale to the higher frequencies associated with HFUS and other will not. Micro-coaxial transmission lines are well suited to the higher frequencies associated with HFUS, and many industry standard connector solutions are applicable at the system end as well. Furthermore, one skilled in the art will know that printed circuit boards can be designed to function at orders of magnitude higher frequencies than those required for HFUS. The challenge for electrically interconnecting HFUS transducers to the ultrasound system lies principally in the means of making electrical connections to the actual elements of the HFUS array. These elements are very small, fragile, and often limited to strict thermal budgets so that traditional micro electrical interconnection techniques are not suitable for HFUS transducers. Wire bonding, low temperature soldering, and ACF adhesives for example, are widely used technologies for making interconnections to traditional clinical frequency transducers. However, there are limitations to these techniques that make them generally unsuitable for use on HFUS transducers. For example, one skilled in the art will appreciate that wire bonding of interconnections at pitches less than about 100 μ m can be challenging, and at pitches below 50 μ m become nearly impossible. When process temperature are limited to less than about 100 degrees C., wire bonding is even more challenging. In addition, mechanical forces associated with wire bonding become problematic when substrate thickness is less than about 100 μ m. Typical piezoelectric materials suitable for making HFUS transducers must be thinned to about 100 μ m down to less than 30 μ m for transducers spanning the 15 MHz to 50 MHz center frequency range. These thin substrates tend to crack when wire bonding is attempted. ACF tape and other asymmetrical conductive adhesive systems are not suitable for high reliability connections at pitches below about 200 μ m, and also generally require a thermal budget in excess of 120 degrees Celsius, which one skilled in the art will understand, may be problematic for some materials associated with the fabrication of HFUS transducer materials.

Some HFUS transducers currently employ a grounding system that relies on a copper electrode made from thin conductive foil to be electrically attached to the front (lens side) ground plane of the transducer, and then exit the side of the stack and wrap around toward the flex circuits ground planes.

The primary challenge of this approach is related to the spacing of the lens to the ground plane of the piezoelectric material. In the conductive foil design, this space is equal to the thickness of the matching layers between the piezoelectric substrate and the lens, for example, in a three matching layer device, three quarter wave matching layers or about 30 μ m at 50 MHz up to about 70 μ m for 20 MHz (for reference, typical printer paper is 100 μ m thick). This necessitates the use of very thin foil attached to the array ground plane with

a very thin bond line of conductive epoxy. Preservation of the mechanical integrity of the foil during subsequent lapping and adhesive/cleaning procedures is very challenging. Other methods might be employed to allow the use of thicker foil, but a secondary limitation of the foil is the risk of causing a delamination of the lens due to forces associated with bending the conductive foil, which are increased as the foil becomes thicker.

Finally, one skilled in the art will recognize that the conductive foil technique requires that the ground electrode exits the stack structure along the edges, making electrical isolation of the device challenging especially when BF or CF medical device ratings are required. Given these problems, there is a need for improved techniques of making connections to high frequency ultrasound transducer elements.

SUMMARY

As will be discussed and illustrated below, the disclosed technology relates to a high frequency ultrasound probe for transmitting and receiving high frequency ultrasound signals and methods of assembling such a probe. The probe comprises a substrate with a plurality of high frequency transducers having a ground electrode on an outer face of the transducers and individually connected signal electrodes on an opposite, inner face of each of the transducers. The probe also includes a plurality of vias created around the perimeter of the transducer substrate material, which are electrically connected to the ground electrode on the front outer side of the substrate containing the arrayed transducers. The probe further includes a support structure of which at least a part is electrically conductive, and which exhibits a coefficient of thermal expansion (CTE) that is closely matched to that of the transducer substrate.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention may be more completely understood in consideration of the accompanying drawings, which are incorporated in and constitute a part of this specification, and together with the description, serve to illustrate the disclosed technology.

FIG. 1 is an isometric view of the complete assembly of the arrayed transducer labeled to illustrate the components of the grounding system in accordance with an embodiment of the disclosed technology;

FIG. 2 is a perspective view of the top of a conductive hybrid support structure in accordance with an embodiment of the disclosed technology;

FIG. 3 is a perspective view of the bottom of the conductive hybrid support structure in accordance with an embodiment of the disclosed technology;

FIG. 4 is a perspective view of the transducer substrate showing the pockets and metal film that will later form the vias in accordance with an embodiment of the disclosed technology;

FIG. 5 is a close up perspective view of the via pockets in accordance with an embodiment of the disclosed technology;

FIG. 6 is a perspective view of the via pockets filled with a conductive epoxy in accordance with an embodiment of the disclosed technology;

FIG. 7 is a perspective view looking down on the signal side of the transducer substrate that has been thinned to the final thickness and showing the final plated and filled vias as

they are exposed from the signal side of the substrate in accordance with an embodiment of the disclosed technology;

FIG. 8 illustrates the assembled components of the array transducer showing the ground planes of the flex, not yet connected to the conductive support structure in accordance with an embodiment of the disclosed technology;

FIG. 9 illustrates the fully assembled array transducer showing the ground path connected by conductive adhesive between the flex circuit ground plane and the conductive support structure in accordance with an embodiment of the disclosed technology;

FIG. 10 is a cross section perspective view fully labeled to illustrate the functional parts of the array transducer and the grounding system in accordance with an embodiment of the disclosed technology;

FIG. 11 is a cross section of the grounding system showing the direct path of ground conductors from the common ground plane of the arrayed transducers to the ground plane of the printed circuit board in accordance with an embodiment of the disclosed technology;

FIG. 12 is a perspective view showing signal interconnections, made using the laser etch laser process, in place in an array transducer in accordance with an embodiment of the disclosed technology;

FIG. 13 is a close up perspective view of the signal electrodes at one end of the array showing the need to isolate the signal electrodes from the conductive portion of the support structure used to conduct the ground currents to the ground plane of the flex; in accordance with an embodiment of the disclosed technology;

FIG. 14 shows a perspective view of the cross section of the array and signal electrodes in accordance with an embodiment of the disclosed technology; and

FIG. 15 shows a partial cross section of the arrayed transducer with both the signal electrodes and the ground system in place, illustrating the insulating function of the conductive hybrid support structure.

DETAILED DESCRIPTION

To address the above mentioned problems, the technology disclosed herein relates to high frequency ultrasound transducers. As will be discussed in further detail below, one embodiment of an ultrasound probe in accordance with the disclosed technology includes a hybrid support structure having an overall coefficient of thermal expansion that is closely matched to that of a substrate material used to make an array of transducer elements. This allows the support structure to be joined to the transducer substrate without inducing significant stress or strain over the thermal excursions routinely seen by ultrasound transducers.

In the embodiment shown in FIG. 1, a high frequency ultrasound transducer **100** includes a linear (or other shaped) array of transducer elements **102**, a cable bundle **104** containing a plurality of RF transmission lines for carrying RF electrical signals between an ultrasound system (not shown) and the arrayed ultrasound transducer elements, and a plurality of electrical interconnections lying between the RF transmission lines and the arrayed transducer elements. A mechanical housing (not shown) encapsulates some or all of the components included in the ultrasound probe assembly, such as the arrayed transducer elements, an acoustic stack and lens, and the electrical interconnections to the cable bundle.

In one embodiment the electrical interconnections made between the transducer elements **102** and the transmissions

lines of the cable bundle **104** are made according to a Laser Etch Laser (LEL) process as described in U.S. Pat. No. 8,316,518 and U.S. patent application Ser. No. 13/657,783 which are herein incorporated by reference in their entirety.

As described in the '518 patent, electrical connections are made between a transducer element and a conductor in a flexible circuit or cable bundle by coating the conductors and transducer elements with a particle (e.g. silica) filled epoxy. The area over the transducer elements is exposed and a low fluence laser is used to create trenches in the epoxy where conductors are desired. The number of laser pulses is increased over portions of the flex circuits in order to dig down to the copper conductors in the flex circuits. The channeled epoxy and the transducer elements are then sputter coated with a conductor such as gold. A resist is then placed over the gold. The resist is then removed with a low fluence laser in areas where the gold is to be removed. A wet etch process is then used to remove most of the gold conductor in the areas where it is not desired. A higher fluence laser is used to remove any remaining gold. The resist that is located over the areas where a conductor is desired is then chemically dissolved.

FUJIFILM Sonosite, Inc. (the assignee of the present applications) developed the Laser-Etch-Laser process (referred to as LEL), which is capable of connecting a standard flexible PCB to an ultrasonic array stack with pitches down to less than 10 μm , and within a thermal budget of <80 degrees C. LEL-based technology is currently used in all the VSI designed arrays ranging from 90 μm down to 38 μm in pitch, and has proven to be very reliable in the field.

In one embodiment, two flex circuits **104** are connected to either side of the transducer array. One circuit has conductors for the odd numbered transducer elements while the other printed circuit has conductors for the even numbered transducer elements. Each printed circuit has conductors with a pitch twice that of the array.

The techniques described in the '783 application are similar except that a stepped flex circuit is used where conductors in different layers of the flex circuit are spaced farther apart than the distance between adjacent electrode elements. The conductors of the flex circuits are interleaved so that connections can be made at a tighter pitch can be made with having all the conductors on the same layer of a printed circuit.

While the disclosed embodiment of the transducer probe includes electrical interconnections made using the LEL technique, one skilled in the art will recognize that electrical interconnections between the signal electrodes of the array and the transmission lines of the conductor bungle could be made by alternative methods if space and thermal budgets permit.

The exemplary high frequency ultrasound probe described herein is designed specifically to address one of the technical challenges specifically associated with making diagnostic images using high frequency ultrasound transducers having a center frequency in the range of at least about 15 MHz and up to about 50 MHz or higher. One skilled in the art will understand that while some state of the art techniques used for making traditional ultrasound probes, having center frequencies between about 1 MHz and 10 MHz, will scale to higher frequencies, others techniques will not. One skilled in the art will also understand that RF transmission lines and grounding techniques must be correctly designed for the frequencies and physical dimensions of a device to provide optimal function, such as minimization of unwanted electrical reflections, maximizing SNR, and providing RF shielding.

In addition to the challenges associated with electrically connecting each element to the conductor that will carry the driving signal to the transducer, there is a need for providing a good RF ground and adequate shielding to the array. One skilled in the art will understand that electrical grounding of an RF device containing many elements, such as an arrayed HFUS transducer, requires specific characteristics of the ground conductors to ensure low cross talk between elements, high SNR and good noise immunity, and broad band performance ensuring good signal integrity. Ground currents must be carried away from adjacent elements through low impedance conductive planes rather than wires, as inductance can cause unpredictable behavior and ground bounce can produce unwanted crosstalk between channels. In addition, one skilled in the art will recognize the need to account for controlled impedance transmission lines and impedance matching as well as EMI shielding, both of which influence good RF ground design.

In the exemplary embodiment described herein, micro machined vias and a ground plane are used to create a low impedance, high quality RF ground in a HF ultrasound transducer. A high frequency ultrasound probe constructed in accordance with the disclosed technology has a high quality, low impedance RF ground plane that is both electrically and spatially efficient and mechanically and thermally robust. One skilled in the art will recognize that each transducer in the scan head can comprise a substrate material consisting of a dielectric electromechanical driver, such as, but not limited to, a piezoelectric ceramic or a ferroelectric relaxor material, a ground electrode adjacent to one face of the driver, and a signal electrode adjacent the opposite face, thus allowing an electric field to be imposed or measured across the thickness of the electromechanical driver. One skilled in the art will also understand that the transducer substrate may also consist of a composite material based on a suitable electromechanical driver material arranged in an advantageous pattern within a matrix of passive dielectric material, such as a polymer, for example an epoxy, to produce an acoustic transducer having properties that are a composite of the driver and matrix materials. One skilled in the art will further understand that this method could readily be applied to any suitable transducer substrate consisting of a dielectric material and having a bounding region for creating vias, or being bounded by a dielectric or insulating material through which vias can be created.

In one preferred embodiment, the ground electrode is common to all the transducer elements in the array, and is located on the distal face of the transducers and the substrate from which they are formed. FIGS. 4 and 5 illustrate a transducer substrate **120** in which the transducer elements **102** are formed. One surface (e.g. the outer surface) of the substrate is covered with a conductive material **122** such as gold. The substrate **120** has a number of vias **124** surrounding the perimeter of the substrate. The vias are plated through in order to allow the conductive material **122** on the outer surface of the substrate to make electrical contact with a ground plane on the flex (or other) circuit that holds the transmission lines to drive the transducer elements.

The conductive material **122** forms a common ground electrode that is overlaid by an acoustic stack typically consisting of one or more matching layers and a lens. FIG. 15 shows a cross-section of an assembled ultrasound probe including substrate **120**, the vias **124**, a matching layer **126** positioned over the substrate and a lens **128** positioned over the matching layer **126** all of which are secured to a

conductive frame **130**. One skilled in the art will understand that a variety of acoustic stacks and or lens configurations are possible.

In the exemplary embodiment, the ground plane formed by the conductive material **122** is shown to be on the distal face of the arrayed transducers and to be a common ground plane across the complete array of transducers (See FIG. **4** and FIG. **10**). The common planar electrode provides a low impedance path to ground, and provides RF shielding for the signal electrodes located on the proximal face of the array. The ground plane located on the distal face of the transducer substrate is electrically connected to a conductive frame **130** (FIG. **3**) by the plurality of conductive vias **124** located along the perimeter of the substrate **120** as shown in FIGS. **4** through **7**.

The conductive vias **124** are created by making pockets in the transducer substrate **120** and then depositing an electrode material over the entire outer face of the arrayed transducers, and conformally coating the inner faces of the via pockets **124** as shown in FIGS. **4** and **5**. The pockets can be created by any means capable of micromachining ceramics, such as reactive ion etching, laser ablation, or conventional micromachining. In the exemplary embodiment, laser machined vias **124** have slightly tapered walls in the pockets to prevent shadowing during deposition of metal electrodes on the walls of the pockets. The pockets of the vias **124** are then filled with a conductive material, such as conductive epoxy, or any conductive matrix that will adhere to the inner faces of the pocket (see FIG. **6**). Finally, during the processing of the arrayed transducers, the transducer substrate **120** is thinned to the required dimension to achieve the required ultrasonic resonance in the transducers, for example, about 30 um for a 50 MHz transducer.

By ensuring that the pocket is deeper than the final thickness of the transducer substrate, the vias **124** are fully realized when the transducer substrate is thinned to the final dimension as shown in FIG. **7**. By metalizing the vias before filling them with a conductive material, one ensures that expansion/contraction of the conductive filler material does not result in micro cracking around the perimeter of the vias **124**.

The conductive frame **130** is then attached to the proximal face of the transducer substrate using a conductive adhesive, so that the exposed conductive bottom face of the hybrid tapered support overlays the exposed upper surface of the conductive vias **124** (see FIGS. **10**, **11**, and **15**). As can be seen in FIGS. **8**, **9** and **11**, the vias **124** provide a conductive path from the ground plane of the substrate **120** to the conductive frame **130**. A conductive adhesive **150** is then used to electrically couple the conductive frame to the ground plane **107** of the flexible printed circuit **104**. This ensures a very low inductance connection between the ground plane on the flexible printed circuit and the conductive frame **130** of the hybrid tapered support. It also ensures that the signal electrodes located on the inner surfaces of the transducer substrate, the hybrid tapered support, and the PCBs are completely surrounded by a ground electrode providing excellent shielding.

The conductive frame **130** is part of a hybrid support structure referred to as a hybrid tapered support herein. As shown in FIG. **2**, the hybrid tapered support consists of a conductive outer frame **130** and an insulating insert **140** that is secured to the outer frame by over-molding, adhesive or another technique. The insulating insert **140** includes guiding pockets **142** to assist in aligning the printed flexible circuit to the arrayed transducers (see FIGS. **2**, **3**, and **13**). The conductive frame **130** is designed to have a coefficient

of thermal expansion that closely matches that of the transducer substrate **120**. In an exemplary embodiment, in the case of a ceramic substrate, such as PZT or PMN-PT, molybdenum is chosen for the conductive frame, having a CTE of about 4.8 ppm/degree C. compared to 4.7 ppm/degree C. for PZT. Depending on the expected thermal perturbations that the arrayed transducers are to undergo, a closer CTE match may become more or less important, allowing the choice of different materials. For example, one might also choose engineered nickel iron alloys such as invar and its variants designed to match the CTE of specific materials. Other conductive materials such as graphite based materials, or plated ceramics could also be suitable so long as the CTE of the frame is closely matched to the transducer substrate over the expected thermal range.

As best shown in FIG. **10**, the ground electrode **122** is further extended through the conductive support frame **130** to the ground plane **107** of a flexible printed circuit board **104**. The connection to the ground plane is made over a large surface to ensure a low impedance connection to the ground plane. In the exemplary embodiment, conductive adhesive is used to connect the conductive support frame **130** to the ground plane **122** of the transducer substrate **120** (see FIGS. **8** through **10**), although one skilled in the art will understand that alternative methods of connecting the conductive frame to the ground plane could be used, such as soldering, conductive tapes, metallization etc.

As discussed above, a plurality of signal electrodes are deposited on the proximal face of each transducer, isolated from each other so that each individual transducer in the array can be independently connected to a transmitter/receiver. Each signal electrode is connected to a signal trace located on the signal layer of the flexible printed circuit board, as a means of providing an electrical interconnection between the transducer electrode, and the transmission line cables that carry electrical signals to and from the ultrasound system. As described above, the insulating insert **140** that is secured to the conductive frame **130** provides a non-conductive barrier between the transducer elements **102** and the conductive frame **130**.

Furthermore, in order to ensure that laser micromachining of the signal electrodes is possible without risk exposing sections of the conductive frame through the PCB during laser definition of the electrodes, a thin layer of a barrier strip formed of a ceramic insulator **160** such as alumina, is bonded to the back face of the PCB **104** before bonding the PCB **104** into the pocket on the hybrid tapered support (see FIGS. **10** and **11**). This insulator **160** serves to stiffen and flatten the flexible PCB prior to alignment in to the tapered support making alignment of signal electrodes in the PCB to the arrayed transducers more efficient and accurate. In addition, the ceramic insulator prevents the creation of short circuits between the traces of the printed flex circuit and the conductive frame **130**.

One skilled in the art will understand that a conductive frame surrounding the entire perimeter of the arrayed transducer structure will provide additional RF shielding. Furthermore, the use of a conductive ground structure with a high surface area to volume ratio ensures low inductance, and when it is placed in close proximity to all of the array signal conductors ensures minimal impedance for ground currents and therefore better noise rejection compared to using wires to connect the ground from the transducer to the printed circuit ground.

From the foregoing, it will be appreciated that specific embodiments of the invention have been described herein for purposes of illustration, but that various modifications

may be made without deviating from the spirit and scope of the invention. Accordingly, the invention is not limited except as by the appended claims.

We claim:

1. A high frequency ultrasound probe comprising:
 - a conductive frame;
 - a transducer substrate having an outer perimeter and a number of transducer elements formed therein that is secured to the conductive frame; and
 - a conductive ground plane on a distal surface of the transducer substrate that is electrically coupled to the conductive frame by one or more vias that are positioned around a perimeter of transducer elements on the transducer substrate and form conductive paths that are inside of the outer perimeter of the transducer substrate and extend between the distal surface of the transducer substrate and a proximal surface of the transducer substrate.
2. The high frequency ultrasound probe of claim 1, further comprising one or more printed flex circuits having conductors that are coupled to the transducer elements and a ground plane, wherein the ground plane of the one or more printed flex circuits is electrically coupled to the conductive frame.
3. The high frequency ultrasound probe of claim 2, wherein the ground plane of the one or more printed flex circuits is electrically coupled to the conductive frame with a conductive adhesive.
4. The high frequency ultrasound probe of claim 2, further comprising a non-conductive barrier strip positioned between the one or more printed flex circuits and the conductive frame.
5. The high frequency ultrasound probe of claim 2, wherein the conductive frame includes an insulating insert positioned between the conductive frame and the one or more printed flex circuits.
6. An ultrasound transducer, comprising:
 - a substrate having a number of transducer elements formed therein, wherein the substrate has a common ground electrode on a distal surface of the substrate and a number of vias filled with a conductive material positioned around a perimeter of the transducer elements, wherein the vias are directly connected to the common ground electrode and form conductive paths to a proximal surface of the substrate that are inside of an outer perimeter of the substrate;
 - a conductive frame secured to the proximal surface of the substrate, wherein the conductive frame is electrically connected to the common ground electrode on the substrate through the vias.

7. The ultrasound transducer of claim 6, wherein the substrate and the conductive frame have similar coefficients of thermal expansion.

8. The ultrasound transducer of claim 6, wherein the conductive frame has sloped walls configured to support conductors that are electrically coupled to individual transducer elements.

9. An ultrasound transducer, comprising:

a transducer substrate having an outer perimeter and a number of transducer elements formed therein, wherein the transducer substrate has a conductive common ground plane on a distal surface of the transducer substrate and a number of conductive vias positioned between the outer perimeter of the transducer substrate and the transducer elements and forming direct conductive paths from a proximal surface of the transducer substrate to the conductive common ground plane on the distal surface of the transducer substrate, wherein the direct conductive paths are positioned inside the outer perimeter of the transducer substrate;

a conductive frame configured to support one or more printed flex circuits, wherein the conductive frame is secured to the proximal surface of the transducer substrate and is electrically connected to the conductive vias so that the conductive frame is electrically connected to the conductive common ground plane through the conductive vias; and

one or more printed flex circuits having a number of conductors that are electrically connected to individual transducer elements in the transducer substrate and a ground plane that is electrically connected through the conductive frame to the conductive common ground plane on the distal surface of the transducer substrate.

10. The ultrasound transducer of claim 9, wherein the conductive frame has sloped sidewalls with respect to the transducer substrate and is configured to support the one or more printed flex circuits so that signal electrodes located on a proximal surface of the transducer substrate are surrounded by a ground electrode to provide shielding.

11. The ultrasound transducer of claim 9, wherein the conductive frame is made of molybdenum.

12. The ultrasound transducer of claim 9, wherein the transducer elements are sized to operate at a frequency of 15 MHz and higher.

13. The ultrasound transducer of claim 9, wherein the transducer elements are sized to operate at a center frequency between 15-50 MHz.

* * * * *

专利名称(译)	高频超声探头		
公开(公告)号	US9603580	公开(公告)日	2017-03-28
申请号	US14/286918	申请日	2014-05-23
[标]申请(专利权)人(译)	富士胶片索诺声公司		
申请(专利权)人(译)	FUJIFILM SONOSITE , INC.		
当前申请(专利权)人(译)	FUJIFILM SONOSITE , INC.		
[标]发明人	CHAGGARES NICHOLAS CHRISTOPHER RIEDER ERIC		
发明人	CHAGGARES, NICHOLAS CHRISTOPHER RIEDER, ERIC		
IPC分类号	A61B8/14 A61B8/00 B06B1/06 A61B8/08		
CPC分类号	A61B8/4444 A61B8/4488 B06B1/0622 A61B8/5207 A61B8/4494 B06B1/06		
代理机构(译)	博钦律师事务所		
优先权	61/827524 2013-05-24 US		
其他公开文献	US20140350407A1		
外部链接	Espacenet USPTO		

摘要(译)

高频超声探头包括其上具有多个换能器元件的基板和通过一个或多个通孔电耦合到支撑基板的导电框架的接地平面。导电框架电耦合到印刷电路的接地平面，该印刷电路具有耦合到换能器元件的导体。

