




US 20150182195A1

(19) **United States**(12) **Patent Application Publication**
LIU et al.(10) **Pub. No.: US 2015/0182195 A1**(43) **Pub. Date: Jul. 2, 2015**(54) **PROCESSING SYSTEM AND PROCESSING METHOD FOR CONFOCALLY EMITTING AND RECEIVING ULTRASOUND**(52) **U.S. CL.**CPC *A61B 8/4494* (2013.01); *A61B 8/52* (2013.01); *A61B 8/54* (2013.01); *A61B 8/0816* (2013.01); *A61B 8/0891* (2013.01)(71) Applicant: **CHANG GUNG UNIVERSITY,**
Tao-Yuan (TW)(72) Inventors: **Hao-Li LIU,** Tao-Yuan (TW);
Chih-Hung TSAI, Tao-Yuang (TW);
Kuo-Chen WEI, Taoyuan County (TW);
Pin-Yuan CHEN, Taipei City (TW)(73) Assignee: **CHANG GUNG UNIVERSITY,**
Tao-Yuan (TW)(21) Appl. No.: **14/289,393**(22) Filed: **May 28, 2014**(30) **Foreign Application Priority Data**

Dec. 27, 2013 (TW) 102148689

Publication Classification(51) **Int. Cl.***A61B 8/00* (2006.01)*A61B 8/08* (2006.01)(57) **ABSTRACT**

A processing system and a confocal processing method for confocally emitting and receiving ultrasound. Firstly, a first driving electrical signal is generated. Then, at least one first ultrasound signal having a main frequency is emitted to a reflection position according to the first driving electrical signal. With an object at the reflection position, the first ultrasound signal is reflected to form at least one second ultrasound signal. Then, a first analyzed signal whose frequency lower than the main frequency is retrieved from the second ultrasound signal, and other signals are eliminated from the second ultrasound signal, and the first analyzed signal is converted into at least one first analogous signal. Finally, first energy of a first fixed bandwidth of the first analyzed signal is retrieved by the first analogous signal. The method stops generating the first driving electrical signal when the first energy is larger than a predetermined value.






Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5(a)




Fig. 5(b)




Fig. 6(a)




Fig. 6(b)




Fig. 7(a)




Fig. 7(b)




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12




Fig. 13(a)



Fig. 13(b)




Fig. 14(a)




Fig. 14(b)




Fig. 15




Fig. 16




Fig. 17




Fig. 18




Fig. 19




Fig. 20




Fig. 21




Fig. 22

PROCESSING SYSTEM AND PROCESSING METHOD FOR CONFOCALLY EMITTING AND RECEIVING ULTRASOUND

[0001] This application claims priority for Taiwan patent application no. 102148689 filed at Dec. 27, 2013, the content of which is incorporated by reference in its entirety.

BACKGROUND OF THE INVENTION

[0002] 1. Field of the Invention

[0003] The present invention relates to a emitting and receiving process technology, particularly to a processing system and a processing method for receiving and exciting focused ultrasound.

[0004] 2. Description of the Related Art

[0005] The blood brain barrier (BBB) is a filter selectively retarding some materials from entering the brain, functioning like a brain health guard. The blood brain barrier of a healthy person can normally protect the brain strictly. If the brain of a person should be infected by viruses or bacteria, it indicates that the person has some problems in health and needs appropriate rest or even medical inspection. Since the blood brain barrier is very compact, medicine from external blood circulation cannot effectively enter into the local brain for therapy.

[0006] Nowadays, focused ultrasound (FUS) exposure with microbubbles can be used to temporarily enhance the permeability of central nervous system (CNS) capillary. Currently, the greatest limitation for the clinical translation of FUS induced local CNS capillary permeability increase is the lack of a real-time technique for monitoring the delivery of FUS to the subject. CNS Capillary permeability increase can be evaluated using contrast-enhanced magnetic resonance imaging (MRI). Such methods cannot control energy of ultrasound but only determine whether to enhance permeability of local CNS capillary. As a result, the backscattered ultrasound emission signals resulted from FUS exposures and circulating microbubbles are used to monitor a therapy behavior. The reflected harmonics formed by circulating microbubbles is proved to serve as a target of a therapy result. In the conventional technology, the harmonics or ultra-harmonics is used as an index to monitor a therapy behavior, namely a received signal whose frequency is higher than frequency of the delivered ultrasound. In order to receive the backscattered acoustic emissions with high frequency, the conventional technology almost uses a wideband hydrophone as a receiving terminal of ultrasound reflected. However, the hydrophone has a small receiving area and receives the backscattered acoustic emissions whose energy is limited and sensitivity to identify the emission source is low. Accordingly, the hydrophone is installed at a position of the acoustic reflection path, wherein the backscattered acoustic emissions has the strongest energy at the position. In order to receive and emit signals synchronously, a synchronization signal is added. The installation position of the hydrophone has to slightly be adjusted according to different therapy behaviors.

[0007] To overcome the abovementioned problems, the present invention provides a processing system and a processing method for confocally emitting and receiving ultrasound, so as to solve the afore-mentioned problems of the prior art.

SUMMARY OF THE INVENTION

[0008] A primary objective of the present invention is to provide a processing system and a processing method for confocally emitting and receiving ultrasound, which installs

an emitting terminal and a receiving terminal at the same side of an object such as a local brain. As a result, an ultrasound signal can be vertically emitted to reduce scattering. Since the receiving terminal has a larger area and the emitting and receiving terminals are confocally arranged with each other, the processing system receives a stronger and source-location-dependent signal and features more sensitivity and precision compared with a hydrophone. In addition, reflection waves are received without triggering an external synchronization signal via external extra devices. Control of the emitting and receiving sequence was united and designed in the same sequencing control panel to the same transducer.

[0009] To achieve the abovementioned objectives, the present invention provides a processing system for confocally emitting and receiving ultrasound, which comprises an electrical-signal emitting and receiving analytic device, coupled to at least one first ultrasound transducer and at least one second ultrasound transducer and generating a first driving electrical signal. The first and second ultrasound transducers are arranged on a curved surface and with a confocal arrangement, in order maximize the receiving acoustic emission originated from the FUS exposure target position. The first ultrasound transducer receives the first driving electrical signal, emits at least one first ultrasound signal having a main frequency to a reflection position according to the first driving electrical signal, and reflects the first ultrasound signal to form at least one second ultrasound signal by an object at the reflection position as a start point. The second ultrasound transducer retrieves a first analyzed signal whose frequency lower than the main frequency from the second ultrasound signal. The second ultrasound transducer eliminates other signals from the second ultrasound signal, converts the first analyzed signal into at least one first analogous signal, and transmits the first analogous signal to the electrical-signal emitting and receiving analytic device. The electrical-signal emitting and receiving analytic device retrieves first energy of a first fixed bandwidth of the first analyzed signal by the first analogous signal. The electrical-signal emitting and receiving analytic device stops generating the first driving electrical signal when the receiving analytic device receives a predetermined processed signal value.

[0010] The present invention also provides a processing method for confocally emitting and receiving ultrasound, which comprises steps of generating a first driving electrical signal; receiving the first driving electrical signal, emitting at least one first ultrasound signal having a main frequency to a reflection position according to the first driving electrical signal, and reflecting the first ultrasound signal to form at least one second ultrasound signal by an object at the reflection position as a start point; retrieving a first analyzed signal whose frequency lower than the main frequency from the second ultrasound signal, eliminating other signals from the second ultrasound signal, and converting the first analyzed signal into at least one first analogous signal; receiving the first analogous signal and retrieving first energy of a first fixed bandwidth of the first analyzed signal by the first analogous signal; and determining whether the first energy is larger than a predetermined value: if yes, stopping generating the first driving electrical signal; and if no, returning to the step of generating the first driving electrical signal.

[0011] Below, the embodiments are described in detail in cooperation with the drawings to make easily understood the technical contents, characteristics and accomplishments of the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] FIG. 1 is a block diagram showing a system according to the first embodiment of the present invention;

[0013] FIG. 2 and FIG. 3 are perspective views of spherically focused concentric circle structures formed by the first and second ultrasound confocal-arranged transducers according to an embodiment of the present invention;

[0014] FIG. 4 is a flowchart diagram showing a method according to the first embodiment of the present invention;

[0015] FIG. 5 (a) is a diagram showing a waveform of first energy with an average increased slope of 0.85 dB/s of the present invention;

[0016] FIG. 5 (b) is a diagram showing a tissue section corresponding to FIG. 5 (a);

[0017] FIG. 6 (a) is a diagram showing a waveform of first energy with an average increased slope of 2.2 dB/s of the present invention;

[0018] FIG. 6 (b) is a diagram showing a tissue section corresponding to FIG. 6 (a);

[0019] FIG. 7 (a) is a diagram showing a waveform of first energy with an average increased slope of 1.3 dB/s of the present invention;

[0020] FIG. 7 (b) is a diagram showing a tissue section corresponding to FIG. 7 (a);

[0021] FIG. 8 is a block diagram showing a system according to the second embodiment of the present invention;

[0022] FIG. 9 is perspective views of the plural first and plural second ultrasound transducers confocal-arranged into a diced array according to an embodiment of the present invention;

[0023] FIG. 10 is perspective views of the plural first and plural second ultrasound transducers confocal arranged into a strip-like linearity array according to an embodiment of the present invention;

[0024] FIG. 11 is a flowchart diagram showing a method according to the second embodiment of the present invention;

[0025] FIG. 12 is a diagram showing a waveform of the first and second ultrasound signals of the present invention;

[0026] FIG. 13 (a) is a diagram showing a spectrum of first energy of a first analyzed signal not higher than a given energy spectral density threshold (25 dB) of the present invention;

[0027] FIG. 13 (b) is a diagram showing a brain tissue section corresponding to FIG. 13 (a);

[0028] FIG. 14 (a) is a diagram showing a spectrum of first energy of a first analyzed signal higher than a given energy spectral density threshold (25 dB) of the present invention;

[0029] FIG. 14 (b) is a diagram showing a brain tissue section corresponding to FIG. 14 (a);

[0030] FIG. 15 is a diagram showing a comparison of a given bandwidth to prediction sensitivity and specificity of the present invention;

[0031] FIG. 16 is a diagram showing a comparison of a given bandwidth to sensitivity and specificity of the present invention;

[0032] FIG. 17 is a block diagram showing a system according to the third embodiment of the present invention;

[0033] FIG. 18 is a flowchart diagram showing a method according to the third embodiment of the present invention;

[0034] FIG. 19 is a flowchart diagram showing a first train process according to the third embodiment of the present invention;

[0035] FIG. 20 is a flowchart diagram showing a second train process according to the third embodiment of the present invention;

[0036] FIG. 21 is a diagram showing distribution of averaged accumulation and brain damage score for case 1 and case 2 of the present invention; and

[0037] FIG. 22 is a diagram showing tissue sections for case 1 and case 2 of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0038] The magnitude of sound pressure is one of factors to influence the local central nervous system (CNS) capillary permeability. For continuous waves, the relationship between electric power and sound pressure is observed by a power meter and a hydrophone. However, in therapy, burst waves with low energy have to be used to avoid hurting a brain. Besides, ultrasonic energy cannot be measured in the burst wave environment and threshold to individual treatment locations contains variety, making a fixed unturned ultrasonic energy to induce CNS capillary permeability increase becomes nearly impractical and impossible. As a result, in order to avoid hurting a tissue due to excessive electric power or excessive sound pressure, a method is found to monitor the ultrasonic energy or the ultrasonic pressure. Another problem is the therapy time. Less exposure time cannot effectively induce CNS capillary permeability change, and excessive exposure time might possibly induce potential damage. Accordingly, a method is found to decide the FUS exposure duration. Therefore, the present invention provides a processing system and a processing method for confocally emitting and receiving ultrasound, so as to solve the abovementioned problems.

[0039] Refer to FIG. 1. The first embodiment of the present invention comprises an electrical-signal emitting and receiving analytic device 10 generating a first driving electrical signal E1. The electrical-signal emitting and receiving analytic device 10 is coupled to at least one first ultrasound transducer 12 and at least one second ultrasound transducer 14. The amounts of the first and second ultrasound transducers 12 and 14 are respectively one and one, which is an example. The first ultrasound transducer 12 receives the first driving electrical signal E1, emits one first ultrasound signal US1 having a main frequency to a reflection position according to the first driving electrical signal E1, and reflects the first ultrasound signal US1 to form one second ultrasound signal US2 by an object at the reflection position as a start point, such as a blood vessel of a local brain. For example, the first and second ultrasound signals US1 and US2 are burst waves, and the main frequency is 1100 kHz in the present invention. The second ultrasound transducer 14, designed to have resonant frequency of 550 kHz, retrieves from the second ultrasound signal US2 a first analyzed signal whose frequency lower than the main frequency, eliminates other signals from the second ultrasound signal US2, converts the first analyzed signal into one first analogous signal A1, and transmits the first analogous signal A1 to the electrical-signal emitting and receiving analytic device 10. The electrical-signal emitting and receiving analytic device 10 retrieves first energy of a first fixed bandwidth of the first analyzed signal by the first analogous signal A1. The electrical-signal emitting and receiving analytic device 10 stops generating the first driving electrical signal E1 when the first energy is larger than a predetermined value. In the first embodiment, the main frequency is f , and the first analyzed signal has a frequency of $f/2$. For example,

the central frequency of the first analyzed signal is 550 kHz. The first fixed bandwidth is 5%–45% of the central frequency of the first analyzed signal, namely from 550±14 kHz to 550±124 kHz. The predetermined value is 25 dB. For example, the first analyzed signal has a frequency of 550 kHz, and the first fixed bandwidth is 40% of the frequency of the first analyzed signal, namely 440 kHz–660 kHz. The present invention mainly analyzes the first analyzed signal whose frequency lower than the main frequency since the transmittance of a low-frequency signal is greater than that of a high-frequency signal.

[0040] The electrical-signal emitting and receiving analytic device **10** further comprises an ultrasound emitting device **18** and coupled to an ultrasound analytic device **20**. The ultrasound emitting device **18** is coupled to the first ultrasound transducer **12** and generating the first driving electrical signal E1. The ultrasound analytic device **20** is coupled to the ultrasound emitting device **18** and the second ultrasound transducer **14**, retrieves the first energy by the first analogous signal A1, and controls the ultrasound emitting device **18** to stop generating the first driving electrical signal E1 when the first energy is larger than the predetermined value.

[0041] The ultrasound emitting device **18** further comprises a focused ultrasound controller **22** generating a first control signal C1 according to the main frequency. The focused ultrasound controller **22** is coupled to a phase generator **24**. The phase generator **24** receives the first control signal C1, and sets a phase of the first control signal C1 to generate a first focused electrical signal F1 according to the reflection position. The phase generator **24** and the first ultrasound transducer **12** are coupled to a power amplifier **26**. The power amplifier **26** receives the first focused electrical signal F1 and amplifies power of the first focused electrical signal F1 to generate the first driving electrical signal E1. The ultrasound analytic device **20** further comprises an analog to digital converter **28** coupled to the second ultrasound transducer **14** to receive the first analogous signal A1 and converting the first analogous signal A1 into a first digital signal D1. The analog to digital converter **28** and the focused ultrasound controller **22** are coupled to a processor **30**. The processor **30** receives the first digital signal D1, transforms the first digital signal D1 in time domain into a first spectrum signal in frequency domain by energy spectral density, and retrieves the first energy from the first spectrum signal. When the first energy is larger than the predetermined value, the processor **30** controls the focused ultrasound controller **22** to stop generating the first control signal C1, thereby stopping generating the first driving electrical signal E1.

[0042] The first ultrasound transducer **12** and the second ultrasound transducer **14** are arranged on a curved surface and the second ultrasound transducer **14** is confocally arranged with the first ultrasound transducer **12**. The first ultrasound transducer **12** and the second ultrasound transducer **14** have an identical focal position. The focal position is the above-mentioned reflection position. For example, as shown in FIG. 2 and FIG. 3, the first ultrasound transducer **12** and the second ultrasound transducer **14** form a concentric circle structure. The concentric circle structure has an inner circle structure and an outer circle structure. The inner circle structure and the outer circle structure are respectively the first ultrasound transducer **12** and the second ultrasound transducer **14**. Alternatively, the inner circle structure and the outer circle structure are respectively the second ultrasound transducer **14** and the first ultrasound transducer **12**. The present invention

installs an emitting terminal and a receiving terminal at the same side of an object **16** such as a local brain. As a result, an ultrasound signal can be vertically emitted to reduce side and un-specific scattering to the target position. Since the receiving terminal has a larger area and the emitting and receiving terminals have the same focus positions, the processing system receives an amplified backscattered acoustic emission signal and features more sensitivity and precision responding to the target location when compared with a hydrophonet. In addition, reflection waves are received without triggering an external synchronization signal. Installation of the processing system is simpler.

[0043] Below is the operation of the first embodiment. Refer to FIG. 1 and FIG. 4. Firstly, a first train process is performed one time, and the first train process comprises Steps S10–S22. In Step S10, the focused ultrasound controller **22** generates the first control signal C1 according to the main frequency. Then, in Step S12, the phase generator **24** receives the first control signal C1, and sets the phase of the first control signal C1 to generate the first focused electrical signal F1 according to a reflection position. Then, in Step S14, the power amplifier **26** receives the first focused electrical signal F1, and amplifies power of the first focused electrical signal F1 to generate the first driving electrical signal E1. Then, in Step S16, the first ultrasound transducer **12** receives the first driving electrical signal E1, emits the first ultrasound signal US1 having the main frequency to the reflection position according to the first driving electrical signal E1, and reflects the first ultrasound signal US1 to form the second ultrasound signal US2 by the object **16** at the reflection position as the start point. Then, in Step S18, the second ultrasound transducer **14** retrieves from the second ultrasound signal US2 the first analyzed signal whose frequency lower than the main frequency, eliminates other signals from the second ultrasound signal US2, and converts the first analyzed signal into the first analogous signal A1. Then, in Step S20, the analog to digital converter **28** receives the first analogous signal A1 and converts the first analogous signal A1 into the first digital signal D1. Then, in Step S22, the processor **30** receives the first digital signal D1, transforms the first digital signal D1 in time domain into the first spectrum signal in frequency domain by energy spectral density, and retrieves the first energy of the first fixed bandwidth of the first analyzed signal from the first spectrum signal. Finally, in Step S24, the processor **30** determines whether the first energy is larger than the predetermined value. If the answer is yes, the process proceeds to Step S26. In Step S26, the processor **30** controls the focused ultrasound controller **22** to stop generating the first control signal C1, thereby stopping generating the first driving electrical signal E1 and ending therapy. If the answer is no, the process returns to Step S10 and continues therapy.

[0044] Steps S10–S14 are replaced with a step of using the ultrasound emitting device **18** to generate the first driving electrical signal E1. Besides, Steps S20–S22 are also replaced with a step of using the ultrasound analytic device **20** to receive the first analogous signal A1 and retrieve the first energy of the first fixed bandwidth of the first analyzed signal by the first analogous signal A1.

[0045] Besides, the first embodiment of the present invention can deliver focused ultrasound targeting energy exposure to multiple points within a large range of a brain to enhance CNS blood-brain permeability with a large volume. In Step S16, the first ultrasound signal US1 whose first energy intensity increases with time is emitted. After Step S22, the pro-

processor 30 determines whether the retrieved first energy reaches a first threshold value, such as 6 dB. If the answer is yes, the processor 30 controls the focused ultrasound controller 22 to decrease the first energy intensity of the first ultrasound signals US1, and the process returns to Step S10, and the first ultrasound transducer 12 emits the first ultrasound signal US1 to another reflection position. If the answer is no, the process proceeds to Step S24.

[0046] In order to effectively enhance blood-brain permeability, an average increased slope of the retrieved first energy corresponding to the first threshold value is a second threshold value such as 1 dB/s when the first threshold value is reached at least two times.

[0047] The present invention uses four-point focused ultrasound to deliver medicine of $6 \times 6 \text{ mm}^2$. For example, the first threshold value is 6 dB, and the second threshold value is 1 dB/s. As shown in FIG. 5(a) and FIG. 5(b), the retrieved first energy does not reach 6 dB, and an average increased slope of the retrieved first energy is 0.85 dB/s. As a result, the blood-brain permeability is not enhanced. As shown in FIG. 6(a) and FIG. 6(b), the retrieved first energy reaches 6 dB, and an average increased slope of the retrieved first energy is 2.2 dB/s. As a result, the blood-brain permeability is uniformly enhanced. The slope threshold correlates with experiment setting and/or the specification of ultrasound instruments, such as emission numbers, frequency and energy. Accordingly, the slope threshold is not so limited.

[0048] However, as shown in FIG. 7(a) and FIG. 7(b), the present invention uses one-point focused ultrasound to deliver medicine of $6 \times 6 \text{ mm}^2$. For example, the first threshold value is 6 dB, and the second threshold value is 1 dB/s. Although the retrieved first energy reaches 6 dB and an average increased slope of the retrieved first energy is 1.3 dB/s, the blood-brain permeability is not uniformly distributed.

[0049] Refer to FIG. 8. The second embodiment is different from the first embodiment in that there are a plurality of first ultrasound transducers 12, a plurality of second ultrasound transducers 14, a plurality of first ultrasound signals US1, a plurality of second ultrasound signals US2, a plurality of first analogous signals A1, a plurality of first digital signals D1, and a plurality of first spectrum signals. In addition, the ultrasound analytic device 20 further comprises a time delayer 32 coupled to the second ultrasound transducers 14, the analog to digital converter 28 and the phase generator 24. The time delayer 32 receives the first focused electrical signal F1, and uses the first focused electrical signal F1 to delay time that the second ultrasound transducers 14 respectively retrieving the first analyzed signals, thereby delaying time points that the first analogous signals A1 are outputted to the analog to digital converter 28 through the time delayer 32. Since there are a plurality of first digital signals D1 and a plurality of first spectrum signals, the processor 30 retrieves the first energy from the first spectrum signals at least two adjacent time points. When an averaged value of the first energy is larger than the predetermined value, the processor 30 controls the focused ultrasound controller 22 to stop generating the first control signal C1, thereby stopping generating the first driving electrical signal E1.

[0050] The plural first ultrasound transducers 12 and the plural second ultrasound transducers 14 are confocal-arranged spherically on a curved surface and have identical focal distances and identical focus positions, wherein the focus position is the reflection position. For example, as shown in FIG. 9 and FIG. 10, the first and second ultrasound

transducers 12 and 14 are arranged into a dot-ring array or a linearity array on a curved surface.

[0051] Below is the operation of the second embodiment. Refer to FIG. 8 and FIG. 11. Firstly, a second train process is performed one time, and the second train process comprises Steps S28-S42. Steps S28-S32 are the same to Steps S10-S14 so will not be reiterated. After Step 32, as shown by Step S34, the first ultrasound transducers 12 receive the first driving electrical signals E1, emits the first ultrasound signals US1 having the main frequency to the reflection position according to the first driving electrical signals E1, and reflects the first ultrasound signals US1 to form the second ultrasound signals US2 by the object 16 at the reflection position as the start point. Then, in Step S36, the time delayer 32 receives the first focused electrical signal F1, uses the first focused electrical signal F1 to delay time that the second ultrasound transducers 14 respectively retrieving from the second ultrasound signals US2 the first analyzed signals whose frequency lower than the main frequency, eliminates other signals from the second ultrasound signals US2, and converts the first analyzed signals into the first analogous signals A1. Then, in Step S38, the time points that the first analogous signals A1 are outputted to the analog to digital converter 28 through the time delayer 32 are delayed. Afterwards, the analog to digital converter 28 receives the first analogous signals A1 and converts the first analogous signals A1 into the first digital signals D1. Then, in Step S42, the processor 30 receives the first digital signals D1, transforms the first digital signals D1 in time domain into the first spectrum signals in frequency domain by energy spectral density, and retrieves the first energy of the first fixed bandwidth of the first analyzed signal from the first spectrum signals at at least two adjacent time points. Finally, in Step S44, the processor 30 determines whether an average value of the first energy is larger than the predetermined value. If the answer is yes, the process proceeds to Step S46. In Step S46, the processor 30 controls the focused ultrasound controller 22 to stop generating the first control signals C1, thereby stopping generating the first driving electrical signals E1 and ending therapy. If the answer is no, the process returns to Step S28 and continues therapy.

[0052] Steps S28-S32 are replaced with a step of using the ultrasound emitting device 18 to generate the first driving electrical signals E1. Besides, Steps S38-S42 are also replaced with a step of using the ultrasound analytic device 20 to receive the first analogous signals A1 and retrieve the first energy of the first fixed bandwidth of the first analyzed signal by the first analogous signals A1.

[0053] Similarly, the second embodiment of the present invention can deliver drugs to multiple points within a large range of a brain to enhance blood-brain permeability. In Step S34, the first ultrasound signals US1 whose first energy intensity increases with time are emitted. After Step S42, the processor 30 determines whether the retrieved first energy reaches a first threshold value, such as 6 dB. If the answer is yes, the processor 30 controls the focused ultrasound controller 22 to decrease the first energy intensity of the first ultrasound signals US1, and the process returns to Step S28, and the first ultrasound transducer 12 emits the first ultrasound signals US1 to another reflection position. If the answer is no, the process proceeds to Step S44.

[0054] In order to effectively enhance blood-brain permeability, an average increased slope of the retrieved first energy corresponding to the first threshold value is a second threshold value such as 1 dB/s when the first threshold value is

reached at least two times. The slope threshold correlates with experiment setting and/or the specification of ultrasound instruments, such as emission numbers, frequency and energy. Accordingly, the slope threshold is not so limited.

[0055] Refer to FIG. 12 which is waveforms of the first and second ultrasound signals. The first ultrasound signal US1 comprises a plurality of long signal emission sets and a plurality of short signal emission sets which are respectively used for FUS energy exposure. At least one short signal set exists between the two adjacent long signal sets. Each long signal set comprises a plurality of long signals, and each short signal set comprises a plurality of short signals. For example, each long signal has 1-100 ms and each short signal has 1-100 μ s. The periods of the long and short signals are not so limited. Similarly, after the object 16 reflects the first ultrasound signal US1, a filter filters the long signal backscattered emissions but remains the short signal backscattered emission sets for energy analysis and detection. As a result, at least one short signal set is used to form the second ultrasound signal US2 retrieved by the second ultrasound transducer 14. Each long signal set comprises a plurality of long signals each having 1-100 ms, and each short signal set comprises a plurality of short signals each having 1-100 μ s. Analyzing the short signal of the second ultrasound signal can more precisely determine the therapy time of a brain.

[0056] The experiment of the present invention is applied to a rat. After ending the experiment, the rat is steeped in a stain (Evans Blue). After two hours, the experimentalist sacrifices the rat to obtain a brain tissue section, which determines whether the CNS capillary permeability of the local tissue is enhanced. In the experiment, the main FUS exposure frequency from the transducer 12 is 1100 kHz. As shown in FIG. 13 (a) and FIG. 14 (a), the first energy of the first analyzed signal with the center of receiving frequency band at 550 kHz is obtained. In FIG. 13 (a), the first energy of the first analyzed signal of 550 kHz is lower than the predetermined value of 25 dB, which implies that the permeability of the local blood brain is not enhanced. The tissue section diagram corresponding to FIG. 13 (a) is shown in FIG. 13 (b). In FIG. 14 (a), the first energy of the first analyzed signal of 550 kHz is higher than the predetermined value of 25 dB, which implies that the permeability of the local blood brain is enhanced. The tissue section diagram corresponding to FIG. 14 (a) is shown in FIG. 14 (b).

[0057] The experiment is analyzed within different bandwidths. The bandwidth of from 0% to 100% is divided into 20 units, wherein each unit is 5%. From FIG. 15, when the bandwidth is 10% or 15%, the sensitivity reaches to almost 100%, and the specificity reaches to almost 90%. When the bandwidth is 40% or 45%, the sensitivity and the specificity are higher than 90%. The higher specificity infers that the percentage that the first energy of first analyzed signals is lower than the predetermined value is higher when the blood brain barrier is not opened. The higher sensitivity infers that the percentage that the first energy of first analyzed signals is higher than the predetermined value is higher when the blood brain barrier is opened.

[0058] Refer to FIG. 16 which is a diagram showing comparison of the sensitivity and the specificity versus different frequencies of the present invention. In the experiment, the first fixed bandwidth is 20% and the first analyzed signal has a frequency of 550 kHz-1100 kHz or 1650 kHz. From FIG. 16, when the specificity is larger than 0.2, the sensitivity of the first analyzed signal of 550 kHz is the highest, indicating the

analyzed backscattered acoustic emission with the receiving bandwidth lower than the emitted frequency has highest detection performance

[0059] The third embodiment of the present invention is introduced below. Refer to FIG. 17, FIG. 18, FIG. 19 and FIG. 20. The system of the third embodiment is the same to the system of the first embodiment. The third embodiment not only detects the CNS capillary permeability change, but also to detect the possible brain damage occurrence caused by excessive power, more specifically the present invention detects the intracranial erythrocyte extravasations from the CNS capillary at the FUS exposure site in our practice. Firstly, in Step S48, a first train process is performed at least one time to obtain and record the first energy, and the first train process comprises Steps S481-S487. For example, the first train process is performed three times. In Step S481, the focused ultrasound controller 22 generates a first control signal C1 according to a main frequency. Then, in Step S482, the phase generator 24 receives the first control signal C1, and sets the phase of the first control signal C1 to generate a first focused electrical signal F1 according to a reflection position. Then, in Step S483, the power amplifier 26 receives the first focused electrical signal F1, and amplifies power of the first focused electrical signal F1 to generate a first driving electrical signal E1. Then, in Step S484, the first ultrasound transducer 12 receives the first driving electrical signal E1, emits at least one first ultrasound signal US1 having the main frequency to the reflection position according to the first driving electrical signal E1, and reflects the first ultrasound signal US1 to form at least one second ultrasound signal US2 by the object 16 at the reflection position as a start point. The first and second ultrasound signals US1 and US2 are burst waves. Then, in Step S485, the second ultrasound transducer 14 retrieves from the second ultrasound signal US2 a first analyzed signal whose frequency lower than the main frequency, eliminates other signals from the second ultrasound signal US2, and converts the first analyzed signal into a first analogous signal A1. For example, the frequency of the first analyzed signal is a half of the main frequency. Then, in Step S486, the analog to digital converter 28 receives the first analogous signal A1 and converts the first analogous signal A1 into a first digital signal D1. Then, in Step S487, the processor 30 receives the first digital signal D1, transforms the first digital signal D1 in time domain into a first spectrum signal in frequency domain by energy spectral density, and retrieves first energy of the first fixed bandwidth of the first analyzed signal from the first spectrum signal. The first fixed bandwidth is 5%-45% of the frequency of the first analyzed signal. Then, in Step S50, the processor 30 obtains and records a first averaged accumulation value AA1 according to all the identical first energy last recorded.

[0060] The first averaged accumulation value AA1 is expressed by an equation (1):

$$AA1 = \sqrt{(\sum_{i=1}^{N1} ESD_{i1}(w))^2 / N1} \quad (1)$$

[0061] Wherein $ESD_{i1}(w)$ is the i th one of all the identical first energy last recorded, w is angular frequency, and $N1$ is an amount of all the identical first energy last recorded.

[0062] Then, in Step S52, the processor 30 determines whether the first energy last recorded is larger than a predetermined value such as 25 dB. If the answer is yes, the process proceeds to Step S54. In Step S54, the processor 30 controls the focused ultrasound controller 22 to stop generating the first control signal C1, thereby stopping generating the first

driving electrical signal E1 and ending therapy. If the answer is no, the process returns to Step S481, increases energy of the next first ultrasound signal US1 and continues therapy. For example, the first ultrasound signal US1 is increased with the following adjustment:

$$E_{next} = E_{current} + \epsilon \cdot E_{current}$$

Where E_{next} is the exposure ultrasonic energy of the first ultrasound signal US1 for next time step, and $E_{current}$ is the exposure energy of the first ultrasound signal US1 at current time step; ϵ is a positive fraction value between [0,1].

[0063] After Step S54, the process proceeds to Step S56. In Step S56, the processor 30 determines whether the first averaged accumulation value AA1 is larger than an accumulation threshold. If the answer is yes, the process proceeds to Step S57. In Step S57, the operation of the third embodiment ends. If the answer is no, the process proceeds to Step S58. In Step S58, a second train process is performed to obtain and record the second energy, and the second train process comprises Steps S581-S587.

[0064] Firstly, in Step S581, the processor 30 controls the focused ultrasound controller 22 to generate a second control signal C2 according to the main frequency. Then, in Step S582, the phase generator 24 receives the second control signal C2, and sets the phase of the second control signal C2 to generate a second focused electrical signal F2 according to the reflection position. Then, in Step S583, the power amplifier 26 receives the second focused electrical signal F2, and amplifies power of the second focused electrical signal F2 to generate a second driving electrical signal E2. Then, in Step S584, the first ultrasound transducer 12 receives the second driving electrical signal E2, emits at least one third ultrasound signal US3 having the main frequency to the reflection position according to the second driving electrical signal E2, and reflects the third ultrasound signal US3 to form at least one fourth ultrasound signal US4 by the object 16 at the reflection position as a start point. The first and second ultrasound signals US3 and US4 are burst waves. Then, in Step S585, the second ultrasound transducer 14 retrieves from the second ultrasound signal US4 a second analyzed signal whose frequency lower than the main frequency, eliminates other signals from the fourth ultrasound signal US4, and converts the second analyzed signal into a second analogous signal A2. For example, the frequency of the second analyzed signal is a half of the main frequency. Then, in Step S586, the analog to digital converter 28 receives the second analogous signal A2 and converts the second analogous signal A2 into a second digital signal D2. Then, in Step S587, the processor 30 receives the second digital signal D2, transforms the second digital signal D2 in time domain into a second spectrum signal in frequency domain by energy spectral density, and retrieves second energy of the second fixed bandwidth of the second analyzed signal from the second spectrum signal. The second fixed bandwidth is 5%~45% of the frequency of the second analyzed signal. Then, in Step S60, the processor 30 obtains and records a second averaged accumulation value AA2 according to all the identical first energy last recorded and all the identical second energy last recorded.

[0065] The second averaged accumulation value AA2 is expressed by an equation (2):

$$AA2 = \sqrt{(\sum_{i=1}^{N1} ESD_{1i}(w) + \sum_{j=1}^{N2} ESD_{2j}(w))^2 / (N1 + N2)} \quad (2)$$

[0066] Wherein $ESD_{j2}(w)$ is the jth one of all the identical second energy last recorded, and N2 is an amount of all the identical second energy last recorded.

[0067] Then, in Step S64, the processor 30 determines whether the second averaged accumulation value is larger than the accumulation threshold. If the answer is yes, the process proceeds to Step 66. In Step S66, the processor 30 controls the focused ultrasound controller 22 to stop generating the second control signal C2, thereby stopping generating the second driving electrical signal E2 and ending therapy. If the answer is no, the process returns to Step S581.

[0068] Steps S481-S483 are replaced with a step of using the ultrasound emitting device 18 to generate the first driving electrical signal E1. Besides, Steps S486-S487 are also replaced with a step of using the ultrasound analytic device 20 to receive the first analogous signal A1, retrieve and record the first energy of the first fixed bandwidth of the first analyzed signal by the first analogous signal A1. Similarly, Steps S581-S583 are replaced with a step of using the ultrasound analytic device 20 to control the ultrasound emitting device 18 to generate the second driving electrical signal E2. Besides, Steps S586-S587 are also replaced with a step of using the ultrasound analytic device 20 to receive the second analogous signal A2, retrieve and record the second energy of the second fixed bandwidth of the second analyzed signal by the second analogous signal A2. In addition, Step S50 and Steps S56-S66 can be omitted. After Step S487, Step S52 can be directly performed.

[0069] The current exposure ultrasonic energy $E_{current}$ of the first ultrasound signal US1 or the third ultrasound signal US3 is expressed by an equation (3):

$$E_{current} = P \times T_e \quad (3)$$

[0070] Wherein P is the energy exposure level at the specific time point, and T_e is the burst time with energy delivery.

[0071] Refer to FIG. 21 and FIG. 22. The examples show the discriminating brain damage via the evaluation of averaged accumulation. In case 1, the brain tissue is not damaged by ultrasound. In case 2, the brain tissue is damaged by focused ultrasound. The following shows examples of determining the time to terminate the treatment session by using averaged accumulation. In these experiments, the ultrasound exposure was adjusted by using the exposure energy of 0.05 joule, with the burst length of 10 ms, with the delivered instantaneous power P ranging from 1-10 W was delivered. That is, the exposure energy ranging from 0.01 to 0.1 joule was delivered. The detected averaged accumulation among different animal experiments ranges from 2000 to 10000 u.i., and the brain tissue damage was scored from 0-12. Here, the damage score is defined by characterizing the observed grouped erythrocyte extravasations density. It can be observed that higher averaged accumulation level corresponds to denser grouped erythrocyte extravasations. With the score higher than 2, the present invention defined in our experiments that the brain damage is noticeable and the power energy should be terminated. The brain damage score locates at 6000 u.i. Therefore, for implementing the proposed algorithm, the present invention choose the accumulation threshold to be 6000 that can best discriminating the brain either been damaged or still intact.

[0072] In conclusion, the present invention installs an emitting terminal and a receiving terminal at the same side of an

object. As a result, an ultrasound signal with low frequency can be vertically emitted to reduce scattering and enhance detection sensitivity.

[0073] The embodiments described above are only to exemplify the present invention but not to limit the scope of the present invention. Therefore, any equivalent modification or variation according to the shapes, structures, features, or spirit disclosed by the present invention is to be also included within the scope of the present invention.

What is claimed is:

1. A processing system for confocally emitting and receiving ultrasound comprising:

an electrical-signal emitting and receiving analytic device generating a first driving electrical signal;

at least one first ultrasound transducer coupled to said electrical-signal emitting and receiving analytic device, receiving said first driving electrical signal, emitting at least one first ultrasound signal having a main frequency to a reflection position according to said first driving electrical signal, and reflecting said first ultrasound signal to form at least one second ultrasound signal by an object at said reflection position as a start point; and

at least one second ultrasound transducer coupled to said electrical-signal emitting and receiving analytic device, retrieving from said second ultrasound signal a first analyzed signal whose frequency lower than said main frequency, eliminating other signals from said second ultrasound signal, converting said first analyzed signal into at least one first analogous signal, and transmitting said first analogous signal to said electrical-signal emitting and receiving analytic device, and said at least one first ultrasound transducer and said at least one second ultrasound transducer are confocally arranged with each other and have an identical focal position as said reflection position, and said electrical-signal emitting and receiving analytic device retrieves first energy of a first fixed bandwidth of said first analyzed signal by said first analogous signal, and when said first energy is larger than a predetermined value, said electrical-signal emitting and receiving analytic device stops generating said first driving electrical signal.

2. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said electrical-signal emitting and receiving analytic device further comprises:

an ultrasound emitting device coupled to said first ultrasound transducer and generating said first driving electrical signal; and

an ultrasound analytic device coupled to said ultrasound emitting device and said second ultrasound transducer, retrieving said first energy by said first analogous signal, and controlling said ultrasound emitting device to stop generating said first driving electrical signal when said first energy is larger than said predetermined value.

3. The processing system for confocally emitting and receiving ultrasound according to claim 2, wherein said ultrasound emitting device further comprises:

a focused ultrasound controller generating a first control signal according to said main frequency;

a phase generator coupled to said focused ultrasound controller, receiving said first control signal, and setting a phase of said first control signal to generate a first focused electrical signal according to said reflection position; and

a power amplifier coupled to said phase generator and said first ultrasound transducer, receiving said first focused electrical signal, and amplifying power of said first focused electrical signal to generate said first driving electrical signal.

4. The processing system for confocally emitting and receiving ultrasound according to claim 3, wherein said ultrasound analytic device further comprises:

an analog to digital converter coupled to said second ultrasound transducer to receive said first analogous signal, and converting said first analogous signal into a first digital signal; and

a processor coupled to said analog to digital converter and said focused ultrasound controller, receiving said first digital signal, transforming said first digital signal in time domain into a first spectrum signal in frequency domain by energy spectral density, and retrieving said first energy from said first spectrum signal, and when said first energy is larger than said predetermined value, said processor controls said focused ultrasound controller to stop generating said first control signal, thereby stopping generating said first driving electrical signal.

5. The processing system for confocally emitting and receiving ultrasound according to claim 4, wherein said at least one first ultrasound transducer is a plurality of first ultrasound transducers, and said at least one second ultrasound transducer is a plurality of second ultrasound transducers, and said at least one first ultrasound signal is a plurality of first ultrasound signals, and said at least one second ultrasound signal is a plurality of second ultrasound signals, and said at least one first analogous signal is a plurality of first analogous signals, and said at least one first digital signal is a plurality of first digital signals, and said at least one first spectrum signal is a plurality of first spectrum signals.

6. The processing system for confocally emitting and receiving ultrasound according to claim 5, wherein said first and second ultrasound transducers are arranged into a diced array or a strip-type linear array on a curved surface.

7. The processing system for confocally emitting and receiving ultrasound according to claim 5, further comprising a time delayer coupled to said second ultrasound transducers, said analog to digital converter and said phase generator, receiving said first focused electrical signal, and using said first focused electrical signal to delay time that said second ultrasound transducers respectively retrieving said first analyzed signals, thereby delaying time points that said first analogous signals are outputted to said analog to digital converter through said time delayer.

8. The processing system for confocally emitting and receiving ultrasound according to claim 7, wherein said processor retrieves said first energy from said first spectrum signals at at least two adjacent time points, and when an average value of said first energy is larger than said predetermined value, said processor controls said focused ultrasound controller to stop generating said first control signal, thereby stopping generating said first driving electrical signal.

9. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said first and second ultrasound signals are burst waves.

10. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said first ultrasound signal comprises a plurality of long signal sets and a plurality of short signal sets, and at least one said short signal set exists between two adjacent said long signal sets,

and said second ultrasound transducer retrieves said second ultrasound signal formed by said short signal sets.

11. The processing system for confocally emitting and receiving ultrasound according to claim 10, wherein each said long signal set comprises a plurality of long signals each having 1 ms to 100 ms, and each said short signal set comprises a plurality of short signals each having 1 μ s to 100 μ s.

12. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said at least one first ultrasound transducer and said at least one second ultrasound transducer are arranged on a curved surface.

13. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said first ultrasound transducer and said second ultrasound transducer form a concentric circle structure, and said concentric circle structure has an inner circle structure and an outer circle structure, and said inner circle structure and said outer circle structure are respectively said first ultrasound transducer and said second ultrasound transducer, or said inner circle structure and said outer circle structure are respectively said second ultrasound transducer and said first ultrasound transducer.

14. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said main frequency is f , and said first analyzed signal has a receiving band with center frequency of $f/2$.

15. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said first fixed bandwidth is 5%–45% of a frequency of said first analyzed signal.

16. The processing system for confocally emitting and receiving ultrasound according to claim 1, wherein said predetermined value is 25 dB.

17. A processing method for confocally emitting and receiving ultrasound comprising steps of:

performing a first train process at least one time, and said first train process comprises steps of:

generating a first driving electrical signal;

at least one first ultrasound transducer receiving said first driving electrical signal, emitting at least one first ultrasound signal having a main frequency to a reflection position according to said first driving electrical signal, and reflecting said first ultrasound signal to form at least one second ultrasound signal by an object at said reflection position as a start point;

at least one second ultrasound transducer retrieving from said second ultrasound signal a first analyzed signal whose frequency lower than said main frequency, eliminating other signals from said second ultrasound signal, and converting said first analyzed signal into at least one first analogous signal, and said at least one first ultrasound transducer and said at least one second ultrasound transducer are confocally arranged with each other and have an identical focal position as said reflection position;

receiving said first analogous signal and retrieving first energy of a first fixed bandwidth of said first analyzed signal by said first analogous signal; and

determining whether said first energy is larger than a predetermined value:

if yes, stopping generating said first driving electrical signal; and

if no, returning to said step of generating said first driving electrical signal.

18. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said step of generating said first driving electrical signal further comprises steps of:

generating a first control signal according to said main frequency;

receiving said first control signal, and setting a phase of said first control signal to generate a first focused electrical signal according to said reflection position; and receiving said first focused electrical signal, and amplifying power of said first focused electrical signal to generate said first driving electrical signal.

19. The processing method for confocally emitting and receiving ultrasound according to claim 18, wherein said step of receiving said first analogous signal and retrieving said first energy by said first analogous signal further comprises steps of:

receiving said first analogous signal and converting said first analogous signal into a first digital signal; and

receiving said first digital signal, transforming said first digital signal in time domain into a first spectrum signal in frequency domain by energy spectral density, and retrieving said first energy from said first spectrum signal.

20. The processing method for confocally emitting and receiving ultrasound according to claim 19, wherein said at least one first ultrasound transducer is a plurality of first ultrasound transducers, and said at least one second ultrasound transducer is a plurality of second ultrasound transducers, said at least one first ultrasound signal is a plurality of first ultrasound signals, and said at least one second ultrasound signal is a plurality of second ultrasound signals, and said at least one first analogous signal is a plurality of first analogous signals, and said at least one first digital signal is a plurality of first digital signals, and said at least one first spectrum signal is a plurality of first spectrum signals.

21. The processing method for confocally emitting and receiving ultrasound according to claim 20, wherein in said step of retrieving said first analyzed signal, said first focused electrical signal is used to delay time that said first analyzed signals are respectively retrieved.

22. The processing method for confocally emitting and receiving ultrasound according to claim 21, wherein in said step of retrieving said first energy, said first energy is retrieved from said first spectrum signals at at least two adjacent time points; and in said step of determining whether said first energy is larger than said predetermined value, determining whether an average value of said first energy is larger than said predetermined value is executed.

23. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said first and second ultrasound signals are burst waves.

24. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said first ultrasound signal comprises a plurality of long signal sets and a plurality of short signal sets, and at least one said short signal set exists between two adjacent said long signal sets, and said second ultrasound transducer retrieves said second ultrasound signal formed by said short signal sets.

25. The processing method for confocally emitting and receiving ultrasound according to claim 24, wherein each said long signal set comprises a plurality of long signals each

having 1 ms to 100 ms, and each said short signal set comprises a plurality of short signals each having 1 μ s to 100 μ s.

26. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said main frequency is f , and said first analyzed signal has a receiving band with center frequency of $f/2$.

27. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said first fixed bandwidth is 5%–45% of a frequency of said first analyzed signal.

28. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein said predetermined value is 25 dB.

29. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein in said step of said first ultrasound transducer emitting said first ultrasound signal, said first ultrasound transducer emits said first ultrasound signal whose first energy intensity increases with time, and after said step of retrieving said first energy, determining whether said first energy reaches a first threshold value is executed: if yes, said first energy intensity is decreased and said method returns to execute said step of generating said first driving electrical signal; and if no, determining whether said first energy is larger than said predetermined value is executed.

30. The processing method for confocally emitting and receiving ultrasound according to claim 29, wherein said first threshold value is reached at least two times, and an average increased slope of said first energy corresponding to said first threshold value is a second threshold value.

31. The processing method for confocally emitting and receiving ultrasound according to claim 30, wherein said second threshold value is 1 dB/s.

32. The processing method for confocally emitting and receiving ultrasound according to claim 29, wherein said first threshold value is 6 dB/s.

33. The processing method for confocally emitting and receiving ultrasound according to claim 17, wherein in said step of receiving said first analogous signal and retrieving said first energy, said first analogous signal is received, said first energy is retrieved and recorded.

34. The processing method for confocally emitting and receiving ultrasound according to claim 33, wherein after said step of receiving said first analogous signal, retrieving and recording said first energy, a first averaged accumulation value is obtained and recorded according to all identical said first energy last recorded, and then said step of determining whether said first energy last recorded is larger than said predetermined value is performed, and when said first energy last recorded is not larger than said predetermined value, said method returns to said step of generating said first driving electrical signal and increases energy of next said first ultrasound signal, and after said step of stopping generating said first driving electrical signal, said method further comprises steps of:

determining whether said first averaged accumulation value is larger than an accumulation threshold:

if yes, ending; and

if no, executing a step of;

generating a second driving electrical signal;

said first ultrasound transducer receiving said second driving electrical signal, emitting at least one third ultrasound signal having said main frequency to said reflection position according to said second driving electrical

signal, and reflecting said third ultrasound signal to form at least one fourth ultrasound signal by said object at said reflection position as said start point;

said second ultrasound transducer retrieving from said fourth ultrasound signal a second analyzed signal whose frequency lower than said main frequency, eliminating other signals from said fourth ultrasound signal, and converting said second analyzed signal into at least one second analogous signal;

receiving said second analogous signal, retrieving and recording second energy of a second fixed bandwidth of said second analyzed signal by said second analogous signal;

obtaining and recording a second averaged accumulation value according to said all identical said first energy last recorded and all identical said second energy last recorded; and

determining whether said second averaged accumulation value is larger than said accumulation threshold;

if yes, stopping generating said third driving electrical signal; and

if no, returning to said step of generating said second driving electrical signal.

35. The processing method for confocally emitting and receiving ultrasound according to claim 34, wherein said step of generating said second driving electrical signal further comprises steps of:

generating a second control signal according to said main frequency;

receiving said second control signal, and setting a phase of said second control signal to generate a second focused electrical signal according to said reflection position; and

receiving said second focused electrical signal, and amplifying power of said second focused electrical signal to generate said second driving electrical signal.

36. The processing method for confocally emitting and receiving ultrasound according to claim 34, wherein said step of receiving said second analogous signal, retrieving and recording said second energy further comprises steps of:

receiving said second analogous signal and converting said second analogous signal into a second digital signal; and

receiving said second digital signal, transforming said second digital signal in time domain into a second spectrum signal in frequency domain by energy spectral density, and retrieving and recording said second energy from said second spectrum signal.

37. The processing method for confocally emitting and receiving ultrasound according to claim 34, wherein said first averaged accumulation value AA1 is expressed by an equation:

$$AA1 = \sqrt{(\sum_{i=1}^{N1} ESD_{i1}(w))^2 / N1}$$
, wherein $ESD_{i1}(w)$ is a i th one of said all identical said first energy last recorded, w is angular frequency, and $N1$ is an amount of said all identical said first energy last recorded.

38. The processing method for confocally emitting and receiving ultrasound according to claim 37, wherein said second averaged accumulation value AA2 is expressed by an equation:

$$AA2 = \sqrt{(\sum_{i=1}^{N1} ESD_{i1}(w) + \sum_{j=1}^{N2} ESD_{j2}(w))^2 / N1 + N2}$$
,

wherein $ESD_{j2}(w)$ is a j th one of said all identical said second energy last recorded, and $N2$ is an amount of said all identical said second energy last recorded.

* * * * *

专利名称(译)	超声发射和接收的处理系统及处理方法		
公开(公告)号	US20150182195A1	公开(公告)日	2015-07-02
申请号	US14/289393	申请日	2014-05-28
[标]申请(专利权)人(译)	长庚大学		
申请(专利权)人(译)	长庚大学		
当前申请(专利权)人(译)	长庚大学		
[标]发明人	LIU HAO LI TSAI CHIH HUNG WEI KUO CHEN CHEN PIN YUAN		
发明人	LIU, HAO-LI TSAI, CHIH-HUNG WEI, KUO-CHEN CHEN, PIN-YUAN		
IPC分类号	A61B8/00 A61B8/08		
CPC分类号	A61B8/4494 A61B8/52 A61B8/0891 A61B8/0816 A61B8/54 A61B8/0808 A61B8/4477 A61B8/5207 G01S7/5205 G01S15/8913 G01S15/8929		
优先权	102148689 2013-12-27 TW		
其他公开文献	US9743908		
外部链接	Espacenet USPTO		

摘要(译)

用于共焦发射和接收超声的处理系统和共焦处理方法。首先，产生第一驱动电信号。然后，根据第一驱动电信号将具有主频率的至少一个第一超声信号发射到反射位置。在物体处于反射位置的情况下，第一超声信号被反射以形成至少一个第二超声信号。然后，从第二超声信号中检索其频率低于主频率的第一分析信号，并从第二超声信号中消除其他信号，并且将第一分析信号转换为至少一个第一模拟信号。最后，第一分析信号的第一固定带宽的第一能量由第一模拟信号检索。当第一能量大于预定值时，该方法停止产生第一驱动电信号。

