



US 20160015988A1

(19) **United States**(12) **Patent Application Publication**
Perryman et al.(10) **Pub. No.: US 2016/0015988 A1**(43) **Pub. Date: Jan. 21, 2016**(54) **TREATING INFLAMMATION, CHRONIC PAIN AND OTHER DISORDERS WITH NEUROMODULATION****Publication Classification**(51) **Int. Cl.***A61N 1/378* (2006.01)*A61B 1/313* (2006.01)*A61B 19/00* (2006.01)*A61N 1/36* (2006.01)*A61N 1/372* (2006.01)(52) **U.S. Cl.**CPC *A61N 1/3787* (2013.01); *A61N 1/36071*(2013.01); *A61N 1/37229* (2013.01); *A61B**19/5244* (2013.01); *A61B 1/3132* (2013.01);*A61B 2019/5276* (2013.01); *A61B 2019/5238*

(2013.01)

(71) Applicants: **Laura Tyler PERRYMAN**, Scottsdale, AZ (US); **Chad ANDRESEN**, Chandler, AZ (US)(72) Inventors: **Laura Tyler Perryman**, Miami Beach, FL (US); **Chad Andresen**, Miami Beach, FL (US)(21) Appl. No.: **14/775,218**(22) PCT Filed: **Mar. 14, 2014**(86) PCT No.: **PCT/US14/29704**

§ 371 (c)(1),

(2) Date: **Sep. 11, 2015****Related U.S. Application Data**

(60) Provisional application No. 61/786,049, filed on Mar. 14, 2013.


(30) **Foreign Application Priority Data**

Dec. 5, 2013 (US) PCT/US2013/073326

(57)

ABSTRACT

Some implementations provide a method of treating chronic pain or inflammation with neural modulation, the method including: placing a surgical instrument to reach into a torso section of a patient's body, the patient suffering from chronic pain or inflammation in a primary area in the torso section; placing a wireless device into an opening on the surgical instrument, the wireless device suitable to fit into the opening and configured to receive electromagnetic energy non-inductively from a source located outside the patient's body; through the opening on the surgical instrument, positioning the wireless electrode lead adjacent to or near excitable tissue in the primary area in the torso section of the patient; and causing electrical pulses to be delivered to one or more electrodes on the wireless device such that neural modulation is applied to the excitable tissue in the primary area in the torso section.






FIG. 1A




FIG. 1B




FIG. 1C





FIG. 2






FIG. 3B




FIG. 4A





FIG. 4B






FIG. 5




FIG. 6A





FIG. 6B






FIG. 7B




FIG. 8A




FIG. 8B




FIG. 9A

Stimulation Section for
Various Receiver/Lead
Configurations




FIG. 9B




FIG. 10




FIG. 11






FIG. 12








FIG. 14A




FIG. 14B











FIG. 14C












FIG. 17B




FIG. 17C




FIG. 18





FIG. 19

FIG. 20



TREATING INFLAMMATION, CHRONIC PAIN AND OTHER DISORDERS WITH NEUROMODULATION

CROSS REFERENCE TO RELATED APPLICATIONS

[0001] This application claims benefit of U.S. provisional Patent Application 61/786,098, filed Mar. 14, 2013. Under 35 U.S.C. 365 and 120, this application claims the benefit of and is a continuation in part of PCT application PCT/US2013/073326, filed Dec. 5, 2013, U.S. patent application Ser. No. 13/551,050 filed Jul. 17, 2012, U.S. patent application Ser. No. 14/045,764 filed Oct. 3, 2013, U.S. patent application Ser. No. 13/562,221, filed Jul. 30, 2012, U.S. patent application Ser. No. 13/584,618, filed Aug. 13, 2012 and U.S. patent application Ser. No. 13/621,530, filed Sep. 17, 2012. The disclosures of all of these applications are incorporated by reference in their entirety for all purposes.

TECHNICAL FIELD

[0002] The present application relates to the delivery of energy impulses (and/or fields) to excitable tissues for therapeutic purposes.

BACKGROUND

[0003] Modulation of excitable tissue in the body by electrical stimulation has become an important type of therapy for patients with chronic disabling conditions, including chronic pain, pain associated with cancer, incontinence, problems of movement initiation and control, involuntary movements, vascular insufficiency, heart arrhythmias, obesity, diabetes, craniofacial pain and more. A variety of therapeutic intra-body electrical stimulation techniques can treat these conditions. Typically, such devices utilize a subcutaneous battery operated implantable pulse generator (IPG) to provide power or other charge storage mechanisms.

SUMMARY

[0004] In one aspect, a system for treating a variety of disorders, inflammation and/or chronic pain comprises one or more devices that have electrodes configured to apply one or more electrical impulses to excitable tissue, particularly nerves associated with pain, inflammation or disorders in the digestive track, heart, pancreas, spleen, kidneys and the like. The electrical impulses are sufficient to modulate the nerves to treat pain, inflammation and/or digestive disorders. The devices are coupled to a power supply and pulse generator for generating the electrical impulses.

[0005] In some implementations, the power supply and pulse generator are not directly attached to the device. Some implementations may use wireless devices that include a first antenna coupled for receiving an input signal from a second antenna, remote from the first antenna. The second antenna may be external to the patient's body or it may be positioned on the patient's body or implanted within the patient's body remotely from the first antenna. The power supply and pulse generator may be directly connected to the second antenna, or they may be physically separate from the second antenna. In this latter example, a relay remote antenna may be used to transmit the input signal from the pulse generator to the second antenna.

[0006] In some implementations, the second antenna is configured to transmit an input signal. The input signal may

include power and may define the electrical pulses for driving the electrodes. The first antenna is configured to receive the input signal non-inductively and without a wired connection. Electronic circuitry may be coupled to the first antenna and may extract the electrical power and electrical pulses from the input signal. The electronic circuitry may then send the electrical pulses to one or more electrodes. The one or more electrodes may modulate the targeted nerves using the electrical pulses. In one example, the one or more electrodes and the antenna are housed within an enclosure of the wireless device. The enclosure may be configured for subcutaneous placement on the patient's body or percutaneous placement within the patient's body.

[0007] In one aspect, some implementations provide a method of treating chronic pain or inflammation with neural modulation, the method including: placing a surgical instrument to reach into a torso section of a patient's body, the patient suffering from chronic pain or inflammation in a primary area in the torso section; placing a wireless device into an opening on the surgical instrument, the wireless device suitable to fit into the opening and configured to receive electromagnetic energy non-inductively from a source located outside the patient's body; through the opening on the surgical instrument, positioning the wireless electrode lead adjacent to or near excitable tissue in the primary area in the torso section of the patient; and causing electrical pulses to be delivered to one or more electrodes on the wireless device such that neural modulation is applied to the excitable tissue in the primary area in the torso section.

[0008] Implementations may include one or more of the following features. Placing the surgical instrument may include positioning a laparoscopic device into an abdominal region of the patient's body. Placing a wireless device into an opening on the surgical instrument may include placing the wireless device through a working channel or cannula of the laparoscopic device. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near branches of the splenic nerve of the patient. Positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near nerves within the spinal cord of the patient. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near branches of the splanchnic nerve of the patient. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near branches of the vagus nerve of the patient. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near the celiac ganglion of the patient. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near the phrenic nerve and the renal plexus of the patient. Placing the surgical instrument may include placing an endoscopic device into the torso section of the patient's body. Placing a wireless device into an opening on the surgical instrument may include placing the wireless device through a working channel or cannula of the endoscopic device. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device in a region in the gastro-intestinal tract or the respiratory tract of the patient. Placing the surgical instrument may include placing a catheter device into a thoracic region of the patient's body. Placing a wireless device into an opening on the surgical instrument may include placing the wireless

device through a working channel or cannula of the catheter device. Positioning the wireless device adjacent to or near excitable tissue may include positioning the wireless device adjacent to or near nerves on at least one of: stomach, heart, spleen, pancreas, diaphragm, liver, or kidney of the patient.

[0009] Positioning the wireless device adjacent to or near excitable tissue may further include positioning the device adjacent to or near the pancreas of the patient, and wherein causing neural modulation to be applied to the excitable tissue comprises causing sufficient neural modulation such that inflammation is reduced in the pancreas of the patient. Causing sufficient neural modulation may further include causing sufficient neural modulation to the TRPV1 and/or CGRP-containing neurons such that inflammation is reduced in the pancreas of the patient.

[0010] Causing neural modulation to be applied to the excitable tissue may further include causing neural modulation of the sympathetic nervous system of the patient. Causing neural modulation of the sympathetic nervous system of the patient may further include causing neural activation of the greater splanchnic nerve of the patient. Causing neural modulation of the sympathetic nervous system of the patient may further include causing neural inhibition of the greater splanchnic nerve of the patient.

[0011] The method may further include using X-Ray fluoroscopy to guide positioning the wireless device adjacent to or near one or more excitable tissue. The method may further include using ultrasound sonography to guide positioning the wireless electrode lead adjacent to or near one or more excitable tissue.

[0012] Placing a wireless device may further include placing a wireless device that includes one or more non-inductive antennas configured to receive electromagnetic energy radiated from a source located outside of the patient's body, electronic circuitry coupled to each of the one or more non-inductive antennas and configured to extract electric power and excitation pulses from the radiated electromagnetic energy as received by the one or more non-inductive antennas, and one or more electrodes configured to deliver the excitation pulses to the one or more excitable tissue to effectuate the neural modulation thereof.

[0013] In another aspect, a method for stimulating nerves leaving or within the spinal cord for treating chronic visceral pain (e.g., gastroparesis, IBS, mesenteric ischemia, epigastric abdominal pain, pelvic visceral pain, familial Mediterranean fever and chronic pancreatitis, post-gastric bypass chronic pain, mesenteric ischemia, abdominal adhesions and the like), visceral pelvic pain (e.g., anterograde implantation for posterior pelvic wall, post-hysterectomy, visceral pelvic adhesions, endometriosis remission and retrograde implantation for interstitial cystitis and pelvic floor issues), pain associated with cancer, such as pancreatic cancer, and intractable angina comprises advancing one or more devices with electrodes to a target site on or adjacent to nerves leaving or within the spinal cord. One or more electrical impulses are applied to the electrodes sufficient to modulate the nerves leaving or within the spinal cord. Some implementations employ a wireless device with electrodes and an input signal containing electrical energy is delivered to an antenna coupled to the electrodes. The input signal is converted to electrical impulses and applied to the electrodes for modulating the nerves.

[0014] In some cases, the input signal is delivered by an external antenna physically separate from one or more

antenna on the wireless device. The external antenna may be positioned either external to the patient's body or in a location on or in the patient's body separate from the electrodes and the one or more antennas on the wireless device. In some examples, the wireless device with electrodes is implanted at the target site. In other examples, the wireless device is percutaneously, laparoscopically or endoscopically advanced to the target site and withdrawn upon conclusion of the treatment.

[0015] In another aspect, a method for treating disorders, inflammation and/or pain comprises advancing a device into a patient's body and positioning the device adjacent to or near nerves within or leaving the spleen, stomach wall, pancreas, diaphragm or liver. In certain implementations, the device is secured to the wall of an organ to stimulate excitable tissue of the organ. In other implementations, the device is placed adjacent to or near the splenic nerve. The device may contain between one and 16 electrodes. Some implementations employ a wireless device that includes one or more antennas for receiving an input signal containing electrical energy. The input signal may be processed so that electrical pulses may be generated on the wireless device to drive power to the electrodes for modulating the nerves. The input signal may be delivered to the one or more antenna(s) on the wireless device by an external antenna positioned either external to the patient's body or in a location on or in the patient's body separate from the electrodes and the device antenna(s).

[0016] In yet another aspect, a method for treating pain and/or activating/deactivating organ functionality (e.g., kidneys, pancreas, spleen, bowel, stomach and/or liver) comprises positioning a device adjacent to or near branches of the splanchnic nerve, such as the greater, lesser or least splanchnic nerves or the celiac ganglion, particularly near the celiac artery. The positioning step may include advancing one or more devices with electrodes (e.g., through an open, endoscopic or percutaneous procedure) to a target site on or adjacent to the targeted nerves and an electrical impulse is applied to the electrodes sufficient to modulate the nerves. Some implementations may employ a wireless device and an input signal containing electrical energy may be delivered to one or more antennas coupled to the electrodes of the wireless device. The input signal may be processed by electronic circuitry on the wireless device such that electrical pulses are created on the wireless device to drive power to the electrodes for modulating the nerves. In one aspect, the input signal is delivered by an external antenna physically separate from the one or more antennas on the wireless device. The external antenna may be positioned either external to the patient's body or in a location on or in the patient's body separate from the electrodes and the first antenna. In certain configurations, the devices are implanted at the target site.

[0017] In yet another aspect, a device is positioned adjacent to or near the splenic nerve or the pancreas to treat pain and/or disorders of the spleen and pancreas. In one example, electrical pulses are applied to the device sufficient to modulate the targeted nerves and reduce inflammation (e.g., by depressing inflammatory-provoking upregulated TRPV1+Neurons) in or around the pancreas to thereby reduce pancreatic pain. Some implementations employ a wireless device.

[0018] In another aspect, a device is positioned adjacent to or near the celiac artery to modify the function of the small and/or large intestines. Some implementations employ a wireless device. In some implementations, an additional

wireless device is positioned adjacent to or near the inferior mesenteric ganglia for modifying the function of the ascending and descending colon.

[0019] In another aspect, a device, such as a wireless device, is positioned adjacent to or near vagal nerve branches on the anterior-superior surface of the stomach to treat digestive conditions, type II diabetes, nausea, obesity and/or pain or inflammation. In one example, the device is secured to the external wall of the stomach. In another example, the device is secured to the lateral anterior-superior surface of the stomach.

[0020] In another aspect, a device, such as a wireless device, is positioned adjacent to or near the phrenic nerve to treat pain arising from structures innervated by the phrenic nerve, such as Kehr's sign, hiccough reflex of the diaphragm and the like. In certain implementations, the device is positioned and secured on the surface of the diaphragm to provide electrical impulses to the phrenic nerve sufficient to modulate the nerve and treat pain or inflammation.

[0021] In another aspect, a device, such as a wireless device, is positioned adjacent to or near the renal nerve plexus to treat disorders and/or pain originating from the kidneys.

[0022] In another aspect, systems and methods are described for stimulating the sympathetic nervous system (e.g., sympathetic chain ganglia, splanchnic nerves (greater, lesser, least), splenic nerves, peripheral ganglia (celiac and superior mesenteric ganglia) to treat obesity, type II diabetes and/or other eating disorders.

[0023] In another aspect, a device, such as a wireless device, is positioned on either the inner or outer heart walls to treat refractory angina. In certain implementations, the device is advanced through a cardiac catheter introduced at the femoral vein and implanted in the interior heart tissue, such as the right or left atrium wall or the right or left ventricle.

[0024] The methods described above may include providing a wireless device including an enclosure that houses one or more electrodes; a first antenna configured to receive, from a second antenna and through electrical radiative coupling, an input signal containing electrical energy, the second antenna being physically separate from the wireless device; one or more flexible circuits electrically connected to the first antenna, the flexible circuits configured to create the one or more electrical pulses suitable to be applied at the electrodes using the electrical energy contained in the input signal; and supply the one or more electrical pulses to the one or more electrodes, and wireless device into a subject's body through an introducer or a needle.

[0025] In another aspect, a system for stimulating neural tissue comprises a controller module having a first antenna external to the patient's body and configured to send an input signal containing electrical energy to a second antenna through electrical radiative coupling. The second antenna is a dipole antenna and is located in an enclosure in a wireless device, such as those described above. The wireless device may not include an internal power source. The circuits of the device may include only passive components. The input signal has a carrier frequency in the range of about 300 MHz to about 8 GHz, preferably between about 750 MHz to about 2.5 GHz.

[0026] In another aspect, a wireless device configured for stimulating nerves, such as those described above, preferably comprises an enclosure shaped and configured for percutaneous delivery into a patient's body through an introducer or needle to a target site in the patient's body. The enclosure

houses one or more electrodes configured to apply one or more electrical pulses to a neural tissue. The enclosure preferably also houses a first antenna configured to receive, from a second antenna through electrical radiative coupling, an input signal containing electrical energy. In some embodiments, the second antenna is physically separate from the wireless device and may be positioned external to the patient's body. In certain exemplary embodiments, the first antenna is a dipole antenna. The enclosure further comprises one or more circuits electrically connected to the first antenna and configured to create the one or more electrical pulses suitable for stimulation of the neural tissue using the electrical energy contained in the input signal and to supply the one or more electrical pulses to the one or more electrodes.

[0027] In some embodiments, a portion of the enclosure may leave the electrodes in a non-direct contact with the neural tissue after the device has been delivered into the patient's body. The enclosure can be semi-cylindrical in shape and the device may include at least one directional electrode that directs a current path associated with the one or more electrical pulses to a direction that is substantially perpendicular to the neural tissue. The devices may include a semi-cylindrical array of electrodes. The electrodes may be made of at least one of platinum, platinum-iridium, gallium-nitride, titanium-nitride, iridium-oxide, or combinations thereof. The devices may include two to sixteen electrodes, each having a longitudinal length between about 0.25 and 6.0 mm and a diameter between about 0.1 and 0.8 mm. The electrodes are spaced between about 0.25 mm to 6 mm apart and have a combined surface area of between about 0.19 mm² to 250.0 mm².

BRIEF DESCRIPTION OF THE DRAWINGS

[0028] FIG. 1A illustrates a device placement at the spleen via laparoscopic operation.

[0029] FIG. 1B. illustrates a device placement at the splanchnic nerve bundle with affected organs.

[0030] FIG. 1C illustrates a device placement at the splanchnic nerve for spleen stimulation.

[0031] FIG. 2 illustrates a device placement at the pancreas via laparoscopic operation.

[0032] FIG. 3A illustrates a device placement in the abdomen for small intestine stimulation via laparoscopic operation.

[0033] FIG. 3B illustrates a device placement in the abdomen for large intestine stimulation via laparoscopic operation.

[0034] FIG. 4A illustrates a device placement at the gastro distribution of the glossopharyngeals.

[0035] FIG. 4B illustrates a device placement at the internal gastro wall via endoscopic operation.

[0036] FIG. 4C illustrates a device placement at the external gastro wall via laparoscopic operation.

[0037] FIG. 5 illustrates a device placement at the external diaphragm wall via laparoscopic operation.

[0038] FIG. 6 illustrates a renal device placement via laparoscopic operation.

[0039] FIG. 7A illustrates an external cardiac device placement via laparoscopic operation.

[0040] FIG. 7B illustrates an internal cardiac device placement via femoral catheter operation.

[0041] FIGS. 8A and 8B illustrate an example of a celiac cuff device.

[0042] FIG. 9A illustrates the anatomical placement of devices in dorsal column spinal cord stimulation for abdominal pain therapy.

[0043] FIG. 9B illustrates the distal tip of an example device.

[0044] FIG. 10 illustrates an example of a miniature implantable device including wireless power receiving electronics.

[0045] FIG. 11 shows three different sized miniature implantable devices.

[0046] FIG. 12 illustrates a miniature implantable device entering an introducer needle.

[0047] FIG. 13A shows a placement stylet capable of mating with a miniature implantable device.

[0048] FIG. 13B illustrates a miniature implantable device mated with a placement stylet.

[0049] FIG. 14A shows a miniature implantable device mated with a placement stylet entering a proximal opening of an introducer needle.

[0050] FIGS. 14B and 14C show a miniature implantable device mated with a placement stylet exiting a distal tip of an introducer needle.

[0051] FIG. 15 illustrates the anatomical placement of four miniature implantable devices in the forearm.

[0052] FIG. 16A illustrates an example suction stylet in zero pressure mode.

[0053] FIG. 16B illustrates the example suction stylet in first level of negative pressure mode.

[0054] FIG. 16C illustrates the example suction stylet in second level of negative pressure mode.

[0055] FIG. 16D illustrates an example miniature implantable device when the suction stylet is not active.

[0056] FIG. 16E illustrates an example miniature implantable device when the suction stylet is active.

[0057] FIG. 17A illustrates a miniature implantable device with multiple recording or stimulating cylindrical electrode pads (eight shown).

[0058] FIG. 17B illustrates various electrode configurations for stimulation and or recording electrodes on the miniature implantable device body, with various inter-electrode spacing options and mixture of recording and stimulation electrode assignments.

[0059] FIG. 17C is a cutout view of a miniature implantable device with stimulation or recording electrodes and the electronic circuitry and wireless power receiver.

[0060] FIG. 18 illustrates a view of a miniature implantable device and a plate electrode configuration for the stimulation or recording pads.

[0061] FIG. 19 depicts a high-level diagram of an example of a wireless neural stimulation system.

[0062] FIG. 20 depicts a detailed diagram of an example of a wireless neural stimulation system.

DETAILED DESCRIPTION

[0063] In various implementations, a neural stimulation system and method is disclosed for applying one or more electrical impulses to targeted nerves for treating chronic pain, inflammation and/or disorders, such as visceral pain (e.g., gastroparesis, IBS, mesenteric ischemia, epigastric abdominal pain, pelvic visceral pain, familial Mediterranean fever and chronic pancreatitis, post-gastric bypass chronic pain, mesenteric ischemia, abdominal adhesions and the like), visceral pelvic pain (e.g., antegrade implantation for posterior pelvic wall, post-hysterectomy, visceral pelvic

adhesions, endometriosis remission and retrograde implantation for interstitial cystitis and pelvic floor issues), inflammation and pain associated with cancer, such as pancreatic cancer, intractable and/or refractory angina, organ functionality, type II diabetes, eating disorders, motility, gastroparesis, reflux, obesity, nausea, and the like. The targeted nerves can include, but are not limited to, the spinal cord, nerves on the inner and outer walls of the stomach and heart, the sympathetic nervous system (e.g., sympathetic chain ganglia, splanchnic nerves (greater, lesser, least), splenic nerves, vagal nerves, the renal plexus, glossopharyngeal nerves, peripheral ganglia (celiac and superior mesenteric ganglia), nerves on the external diaphragm, stomach, heart, liver, kidneys, pancreas, spleen and the like.

[0064] Various embodiments can also include distinct advantages over wired leads with regard to ease of insertion, cross connections, elimination of extension wires, and no requirement for an implantable pulse generator in order to administer a chronic therapy. Various implementations also may have an associated lower overall cost compared to existing implantable neural modulation systems due to the elimination of the implantable pulse generator and this may lead to wider adoption of neural modulation therapy for patients as well as reduction in overall cost to the healthcare system.

[0065] Referring now to FIG. 1, a system and method for implanting a wireless device adjacent to or near the spleen is illustrated. As shown, the wireless device 102 is advanced into the abdominal cavity by laparoscopic placement 102 and through a laparoscopic incision on the patient's body. In some instances, a laparoscopic device, such as devices 102A, 102B, or 102C, may be placed at the incision site. For stimulation of the splenic nerves, the wireless device 104 may be traversed through a working channel or cannula of the laparoscopic device. Once inside the abdominal cavity of the patient's body, the device may be placed, for example, perpendicular to the lateral traversing splenic nerve. In another example, wireless device 104 may be placed in any 360° orientation relative to the splenic nerve. The device may be sutured to the serous coat of the spleen. In still other implementations, the device may be sutured or secured to alternate organs like the exterior stomach wall, pancreas, diaphragm, or liver. Rather than laparoscopic placement, the wireless device can be positioned through a variety of other approaches, including endoscopic or open surgical techniques. The placement procedure may be conducted under imaging guidance, such as X-Ray fluoroscopy or ultrasound sonography. Once wireless device 104 has been placed at the target location in the abdominal cavity, The wireless device 104 is anchored to nearby tissue, for example, anchor location 106, to stimulate excitable tissue near the spleen.

[0066] The device may contain, for example, at least two electrodes and be about 3 cm long with a feature for suturing the lead to surrounding tissue. The device may be used for visceral treatments and may contain between one and sixteen electrodes. The device and the electrodes thereon may have an outer diameter from between 0.1 mm to 1.35 mm. The length of the electrodes may be from between 0.5 mm to 6.0 mm. The total electrode lead length may be from between 10 mm and 600 mm. Internal to the device is one or more electronic circuits that receive power for stimulation from a wireless transmitter, as described above and below. The device may include, an anchoring feature to allow for suturing to tissues using a biocompatible nylon thread. The suture feature of the device may include a hole through the insulation mate-

rial with a diameter from between 0.1 mm and 1 mm. The device body insulation may include concave suture channels with a diameter from between 0.1 and 0.5 mm diameter smaller than the device body's outer diameter.

[0067] FIG. 1B illustrates the organs affected by stimulation of the splanchnic nerve bundle. As illustrated, the wireless device **104** can be implanted adjacent to or near the splanchnic nerve bundle to modulate one or more of the splanchnic nerves (including, for example, lesser, greater or least splanchnic nerves). The placement procedure may include a laparoscopic procedure, such as the procedure described above.

[0068] Nerves travelling from the spine to the celiac ganglion include the great splanchnic and the small splanchnic nerves (for example, at spinal levels T5-T12). The splanchnic branches from the spinal cord congregate to meet at the celiac ganglion before the nerves connect to the organs. Stimulation at the celiac ganglion may include one or more wireless devices that can be placed around the celiac artery, as illustrated in FIG. 1B. The celiac artery has been shown to have a diameter from between 6.0 mm to 8.0 mm. Stimulation at the celiac ganglion can affect, for example, the esophagus, the bowel, the stomach, the kidneys, pancreas, spleen, or liver neural pathways. This stimulation site may be applicable in a variety of indications such as pain, activating/deactivating organ functionality or obesity.

[0069] The sympathetic nervous system plays an important role in obesity. For example, drugs that activate the sympathetic nervous system are known to increase energy expenditure, which can result in weight loss. Similarly, electrical activation of the sympathetic nervous system can help to treat obesity. Electrical modulation (inhibition or activation) of the sympathetic nervous system can also be used to treat other eating disorders, such as anorexia or bulimia.

[0070] To treat obesity, some implementations may include electrical stimulation or activation of the greater splanchnic nerve. Typically, lower frequency (on the order of 1 to 50 Hz) stimulation may result in activation of the sympathetic nervous system and high frequency (greater than 100 Hz) stimulation may result in inhibition.

[0071] Electrical modulation of the sympathetic nerves may also be used to treat gastrointestinal diseases or disorders, such as type II diabetes, peptic ulcers, esophageal reflux, gastroparesis and Irritable Bowel Syndrome (IBS). Stimulation of the splanchnic nerves that innervate the large intestine may reduce symptoms of IBS, characterized by diarrhea.

[0072] The greater splanchnic nerve (GSN) is formed by efferent sympathetic neurons exiting the spinal cord at T4 or T5. Postganglionic neurons from the celiac ganglia that synapse with the GSN innervate primarily the upper digestive system, including the stomach, pylorus, duodenum, pancreas and liver. Postganglionic nerves of the mesenteric ganglia (supplied by nerves from the lesser and least splanchnic nerve), innervate primarily the lower intestine, colon, rectum, kidneys, bladder and sexual organs.

[0073] FIG. 1C illustrates a wireless device **104** implanted near or adjacent to the splenic nerve plexus for modulating such plexus to treat the spleen. In some implementations, a wireless device (such as a miniature device as described below with respect to FIGS. 10-23D) is implanted parallel with the splenic nerve plexus on top surface of the pancreas. The wireless device may be implanted through a laparoscopic procedure where the device is introduced to the body through a cannula or working channel, similar to the procedure

described above in association with FIG. 1A. As part of the operation, the laparoscopic instruments retract the liver and stomach laterally to gain direct access to the pancreas. Treatment of the splenic nerve plexus can affect the spleen and the pancreatic neural pathways. The wireless device may include a proximal tail of empty tubing that can be sutured to surrounding tissue or tunneled to a subcutaneous level for anchoring. Placement of the wireless device on the top surface of the pancreas may stimulate the splenic nerve bundles, which may broadly affect connected organs such as the pancreas, the spleen, and the vagus nerve.

[0074] Referring now to FIG. 2, another location for placing a wireless device may include the ventral surface of the pancreas. When the wireless device is placed on the ventral surface of the pancreas, the wireless device is in the space between the pancreas and the stomach. Placing the wireless device on the ventral aspect of the pancreas may deliver a targeted treatment focusing on stimulating solely the pancreas and stomach's neural pathways. A physician may insert a laparoscopic device, such as device **202A**, device **202B**, device **202C**, or device **202D**, into a patient's abdominal cavity through an incision site. Thereafter, the physician may advance wireless device **204** through a working channel or cannula of the laparoscopic device to reach a target area, for example, a location on the ventral surface of the pancreas. Once wireless device **204** has reached the target location, for example, a location on the ventral aspect of the pancreas, the physician may anchor the wireless device **204** at anchor location **206** (for example, on the pancreatic wall).

[0075] Pancreatic pain is a relatively common and disabling clinical condition usually caused by inflammation. Inflammation increases tissue temperature and promotes acidification of tissue; both stimuli excite TRPV1- and CGRP-containing neurons. This adverse milieu creates an environment due to up regulation of TRPV1 neurons leading to hyperalgesia and excessive blood flow. Both acute and chronic inflammation can cause these nerves to become sensitized so that more and more local cells (including dorsal horn neurons) express the TRPV1 receptor. Antagonists against TRPV1 and CGRP may be useful in attenuating the pain state. It is anticipated that physiological methods aimed at desensitizing TRPV1 neurons at or about the relevant thoracic dorsal horns, i.e., by epidural spinal cord stimulation, will effectively curtail the pain state. This therapy will be more functionally useful and certainly should cause fewer side effects than pharmacotherapies.

[0076] FIG. 3A illustrates a device placement in the abdomen adjacent to or near the celiac and superior mesenteric ganglia for treating the small intestine stimulation via laparoscopic operation. In this example, wireless device **304** is placed near the celiac ganglia through a laparoscopic procedure to target the function of the small intestine. A physician may insert a laparoscopic device, such as device **302A**, device **302B**, device **302C**, or device **302D**, into a patient's abdominal cavity through an incision site. Thereafter, the physician may advance wireless device **304** through a working channel or cannula of the laparoscopic device to reach a target area, for example, the celiac ganglia. Once wireless device **304** has reached the target location, the physician may anchor wireless device **304** by, for example, suturing wireless device **304** to the tissue surrounding celiac artery. In some instances, wireless device **304** includes a tail. The physician may route the tail to a subcutaneous level and suture the tail to a subcu-

aneous tissue. Placing the wireless device near the celiac ganglia can affect the neural pathways and tissue function of the small and large intestine.

[0077] Referring now to FIG. 3B, a wireless device 304 may be placed in the same celiac ganglion location with an additional wireless device 304 secured at the inferior mesenteric ganglia. The additional wireless device 304 may be placed by the physician during the same laparoscopic procedure or during a follow-up laparoscopic procedure, for example, when the patient has manifested a need for additional stimulation. The combination of the two wireless device 304 in FIG. 3B may produce a more targeted stimulation for the ascending and descending colon.

[0078] In FIG. 4A, a wireless device 402 is placed onto the vagal nerve branches on the anterior-superior surface of the stomach. Using laparoscopic procedures such as the ones described above, a physician may place wireless device 404 on a target location on the anterior-superior surface of the stomach. The physician may secure wireless device 402 in place by, for example, suturing the lead to the stomach's exterior surface. The wireless electrode lead 402 may include a tail. In some instances, the physician can route the tail to a surrounding organ before suturing the tail to the surrounding organ (e.g., the abdominal wall). In some instances, the treating physician may route the tail to the subcutaneous level and before suturing the tail at the subcutaneous level. Subcutaneous suture may enable easier removal of the implanted device.

[0079] In another implementation illustrated in FIG. 4B, the wireless device 404 may be placed on the lateral anterior-superior surface of the stomach. In this example, wireless device 404 is placed at the external wall of the stomach through a laparoscopic delivery approach, similar to the ones described above. With the wireless device placed laterally, the gastrointestinal mechanisms of the stomach can be affected. This placement may be common for treatment of obesity. The wireless device may be sutured directly to the exterior stomach wall. The wireless device 404 may also include tines that probe into the tissue wall when the wireless device 404 is pulled in the opposing direction of insertion.

[0080] FIG. 4C illustrates a wireless device 404 placed at the internal gastro wall through an endoscopic operation through the esophagus for treating digestive disorders or conditions, nausea, obesity, motility or pain symptoms. A physician may insert an endoscope with a working channel through the oral cavity (mouth) of the patient and push the endoscope to reach the stomach cavity of the patient. The physician may then advance wireless device 404 down the working channel of the endoscope to place the wireless device 404 in the target location inside the stomach. The physician may then suture the wireless device 404 to the interior stomach wall using a suturing tool. The wireless device 404, however, may be deployed using a variety of approaches (open, endoscopic, or laparoscopic).

[0081] FIG. 5 illustrates a wireless device 504 placed at the external diaphragm wall through laparoscopic surgery. The wireless device 504 may be placed ventral to the liver on the caudal concave surface of the diaphragm. In one example, the physician may use laparoscopic devices, for example, devices 502A, 502B, or 502C, to retract the liver caudally to gain workable space underneath the diaphragm. The physician may then advance wireless device 504 through a working channel or cannula of a laparoscopic device, for example, devices 502A, 502B, or 502C, to place wireless device 504 along the coronal plane of the diaphragm to target the phrenic

nerve. The physician may suture wireless device 504 directly to anchor location 506, for example, the diaphragm or the nearby exterior wall of the liver using standard laparoscopic instruments.

[0082] FIG. 6A-6B illustrate a wireless device 604 placed near the kidney to target the renal plexus stimulation through laparoscopic surgery. For the operation, the patient may be laid on his or her side for the physician to gain lateral access to the kidney. As illustrated in FIG. 6A, the laparoscopic surgery may use a variety of laparoscopic devices of different sizes. In one example, the physician may use the laparoscope to infiltrate the patient's body at the navel location. Thereafter, the physician may route the laparoscopic devices around and underneath the ribcage to reach the renal organs. The physician may then advance wireless device 604 along a working channel or cannula of a laparoscopic device to place wireless device 604 parallel with the renal artery to target the renal plexus, which travels along the artery. The physician then may secure wireless device 604 by suturing wireless device 604 to surrounding tissues in accordance with the descriptions herein.

[0083] FIG. 7A illustrates an external cardiac wireless device 704 placed near the vagus nerve through laparoscopic surgery. For the placement operation, the patient is laid on his or her side for a physician to gain direct access to his or her side. The physician may use laparoscopic device to infiltrate the patient's side. The physician may then pass laparoscopic instruments 702 through the ribcage of the patient to reach the exterior of the heart. The physician may then advance wireless electrode lead 704 along a working channel or cannula of a laparoscopic device to reach the exterior wall of the heart and place wireless device 704 parallel with the vagus nerve. The physician may then suture the wireless device 704 by suturing the device to surrounding tissue. In some instances, the wireless device 704 may include a tail and the physician may route the tail subcutaneously for suturing. The wireless device body may also contain cuff arms, which can secure the wireless device to the nerve, circumferentially, without puncture as seen in FIG. 8A-8B.

[0084] As illustrated in FIG. 7B, a wireless device 704 is secured into the cardiac muscle wall on the inside of a heart. The wireless device 704 can be placed through a cardiac catheter introduced at the femoral vein, a similar process to introducing pacing leads. The cardiac catheter may have a length from between 90 cm and 120 cm. The cardiac catheter may have an inner diameter from between 1.0 mm and 3.0 mm. The physician may advance wireless device 704 up the length of the catheter to reach a target site, for example, the inner wall of the left ventricle. The physician may then secure wireless device 704 into the muscular wall of the heart. The wireless device can be placed at various locations in the interior heart tissue, for example, the right atrium wall, right ventricle, left atrium, and left ventricle. For in-chamber placement, the wireless device may be advantageous because no obtruding connecting tube is routed through two or more chambers (for example, to an implantable battery). In other implementations, the wireless device 704 may have a tail attached which is left outside of the heart for retrieval of the wireless device. Wireless device 704, which may have a length from between 1 cm to 10 cm, is entirely implanted into one chamber. Wireless device 704 may contain tines that secure the wireless device in place without suture. Wireless

device **704** may contain suture ports for quick suturing of the device to the heart wall using a working instrument through the catheter channel.

[0085] FIG. 8A illustrates an example wireless device in the configuration of a stimulating cuff device **800**. The stimulating cuff device **800** includes distal end **802**, electrodes **804**, and suture arms **806**.

[0086] The body of the stimulating cuff device **800** can be made of a soft insulation material such as polyurethane or silicone. The total length of stimulating cuff device **800** may be from between 5.0 mm and 600 mm. The stimulating cuff device body may be ideal for stimulating nerve bundles around cylindrical anatomical bodies like the celiac artery.

[0087] The stimulating cuff device **800** may include suture arms **806** that extend off of the electrode body to wrap the device around a nerve. The suture arms may extend from between about 1.0 mm and about 8.0 mm from the device body. The suture arms may have length from between about 5.0 mm and about 100 mm. The suture arms may have a curvature radius from between about 0 degrees and about 30 degrees. The suture arms may have a thickness from between about 0.1 mm and about 1.0 mm. The suture arms may have suture ports with diameter from between about 0.1 mm and about 0.5 mm. For example, a physician may anchor stimulating cuff device **800** to a surrounding tissue by applying suture to suturing arms **806** and the surrounding tissue.

[0088] Electrodes **804** may deliver stimulation unidirectional to the nerve tissue. Examples of electrode **804** can be from between about 0.5 mm to about 2.0 mm wide and about 1.0 mm to about 10 mm long. Examples of electrodes **804** may be made of a biocompatible metal such as platinum, platinum-iridium, or titanium nitride.

[0089] One or more electronic circuits may be located within the stimulating cuff device **800**. The electronic circuits of stimulating cuff device **800** are not visible in FIG. 8A. However, FIG. 8B shows another example stimulating cuff device **810** with electronic circuits **808**, electronic circuits **808** may be coupled to electrodes **804**. Using internal antennas, stimulating cuff device **800** and **810** may receive electrical power for stimulation radiated from a wireless transmitter, as described above and below. The electronic circuit(s) may extract the electrical energy from the received input signal to provide power to the passive components and allow for stimulation of an excitable tissue. More examples of electrodes **804**, the electronic circuitry, and the internal antennas, as well as the detailed description of a non-inductive power reception mechanism are presented below in association with FIGS. 10 to 20.

[0090] Referring now to FIGS. 9A and 9B, a system and method for spinal cord stimulation are described. Spinal cord stimulation (SCS) has been used to treat a variety of disorders, such as the treatment of chronic pain of neuropathic or ischemic origin (e.g., refractory angina), chronic abdominal pain, chronic visceral pain and the like. Various types of SCS leads have been used to provide therapeutic pain relief. These lead configurations often include cylindrical percutaneous leads and paddle lead form factors. Cylindrical percutaneous leads typically have diameters in the range of about 1.3 mm and contain a number of circular electrodes. Paddle leads contain electrodes with a greater surface area directionally targeted for control over the excitation of the nerve bundles. The spinal cord stimulator exerts pulses electrical signals to the spinal cord to control the pain symptoms. The stimulating devices are typically implanted in the epidural space and the

electrical pulse generator and power supply are implanted in the lower abdominal area or gluteal region, with conducting wires connecting the electrodes to the generator. Complications with SCS range from simple easily correctable problems to devastating paralysis, nerve injury and death. The most common complications include lead migration, lead breakage, and infection. Other complications include hematomas (subcutaneous or epidural), cerebrospinal fluid (CSF) leak, post dural puncture headache, discomfort at pulse generator site, seroma and transient paraplegia. Hardware-related complications such as electrode migration, fractured electrodes, and rotation of pulse generator are also reported.

[0091] Implementations disclosed herein may solve many of the problems with existing SCS techniques because the lead can be connected to the neurostimulator or controller wirelessly. The wireless coupling feature may obviate the most invasive and expensive portion of the implantation procedure; namely, the incision in the upper buttock or abdomen and the connection of the controller to the neurostimulator. In addition, this allows for a significantly smaller electrode lead, thereby reducing the invasiveness of the procedure and increasing the options for percutaneous delivery of the electrode lead.

[0092] Some implementations may include an implantable wireless device. The wireless device may contain one or more electrodes adapted for stimulation of the nerves, passive circuitry and an antenna for receiving an input signal. Further examples of wireless devices are presented below in association with FIGS. 10 to 20.

[0093] FIG. 9A illustrates the anatomical placement of two wireless devices **910** in dorsal column spinal cord stimulation (as shown on a X-Ray image). Electrodes **904** of each wireless device **910** are shown as radio-opaque marks. Distal ends **902** are also visible. As indicated by FIG. 9A, the placement of the device may be accomplished by the use of an introducer. The placement of the device may be guided by fluoroscopy, including X-Ray and ultrasound, to verify that the device has been placed in the correct position.

[0094] FIG. 9B illustrates three example wireless devices. Wireless device **920** may have one electrode **924** located close to distal tip **922**. The length of electrode **924** may be about 12 mm. Wireless device **930** may include two electrodes **934** spaced apart and close to distal tip **932**. Electrodes **934** may be about 6 mm in length and spaced apart by about 4 mm. Wireless device **940** may include four electrodes **944** spaced apart and close to distal tip **942**. Electrodes **944** may be about 4 mm in length and spaced apart by about 4 mm.

[0095] During the surgical procedure, a wireless device may be advanced or delivered subcutaneously and positioned such that the electrodes are implanted on in the appropriate location in the epidural space of the patient's spinal cord. The example wireless device may communicate with an external controller to effectuate therapeutic effect.

[0096] The external controller may include electronic circuitry, a power source and a transmitting antenna. The external controller includes several predetermined programs that comprise combinations of pulse amplitude, pulse width, frequency, ON time and OFF time. The physician and/or patient may determine the particular program for therapy.

[0097] Once the program is determined, the external controller sends an input signal via a radio frequency carrier signal (as described above) to the antenna within the implantable wireless device. The internal antenna may receive the input signal. The internal circuitry on the wireless device then

may convert the received input signal to electrical pulses. The electrical pulses may be applied to the electrodes within the wireless electrode lead to modulate the nerves of the spinal cord and treat the chronic pain.

[0098] FIG. 10 illustrates an example miniature implantable device 1000. The implantable device 1000 includes a body 1016 with a distal end 1014 and a proximal end 1012.

[0099] The distal end 1014 includes a rounded tip 1002. The distal end 1014 of the miniature wireless device body 1016 may include a non-conductive tip 1002 that is rounded with a length of between about 0.5 mm and about 1.0 mm, with a smooth finish for navigating the device through tissue.

[0100] The device body 1006 includes electrodes 1004 and houses electronic circuitry 1006. In some implementations, the miniature implantable device may have between one and twenty-four cylindrical electrodes 1004 on its distal end 1014 with a diameter between about 0.1 mm and about 0.8 mm for stimulation applications. The diameters and other sizes may, of course, vary from one target treatment to another target treatment. The electrodes 1004 may have a longitudinal length of between about 0.25 mm and about 6.0 mm from the distal end 1014 toward the proximal end 1012. The spacing between the electrode contacts may be between about 0.25 mm and about 6.0 mm. The total electrode surface area of the cylindrical wireless lead body may be between about 0.06 mm² and about 250.0 mm².

[0101] The proximal end 1012 includes a suturing feature 1008 and a mating feature 1010. The suturing feature 1008 is a passage through the proximal end with a central axis that is parallel to a longitudinal axis of the device body 1006. Suturing feature 1008 may allow a clinician to suture and anchor implantable device 1000 during an implantation procedure. For instance, suture can be passed through the passage of suturing feature 1008 and tied to tissue. In some cases, the implantable device 1000 can be sutured to the surrounding tissue. Suturing the implantable device may reduce mobility and improve stability of the implanted device.

[0102] Mating feature 1010 may allow the device 1000 to be mechanically mated with a stylet, as disclosed herein. In one configuration, mating feature 1010 is a concave indentation that extends along a longitudinal axis of the device body 1006 from the proximal end 1012. The concave indentation mates with a corresponding feature on a placement stylet or suction stylet. The concave stylet-mating feature on the proximal end 1010 of implantable device 1000 can have, for example, a length of between about 0.1 mm and 1.0 mm. In other configurations, the stylet-mating feature 1010 may be semi-spherical or asymmetrical in shape for improved steerability of the device during implantation.

[0103] The various devices described herein, including device 1000, may include, for example, anywhere from one to twenty-four electrodes 1004, any of which can be designated by a programmer user as either a cathode or an anode. For example, electrodes 1004 can include multiple cathodes coupled to the targeted tissue as well as at least one anode. The electrode array can receive electrical stimulation pulses ranging from about 0 to about 10 V peak amplitude at a pulse width up to about 1 millisecond. Such stimulation pulses may be from a single receiver element within the device body. The polarity of the electrodes can produce various volume conduction distributions from the cathodes to the anodes to inhibit or excite surrounding excitable tissue, which may include A-δ and/or primary or secondary c-fiber afferents. To reduce electrode impedance, the electrodes may be made of a

conductive, corrosion resistant, biocompatible material such as, for example, platinum, platinum-iridium, gallium-nitride, titanium-nitride, or iridium-oxide.

[0104] The miniature implantable device 1000 may be 0.8 mm diameter or smaller. Miniature implantable device 1000 may receive microwave or RF energy from an external source non-inductively and without a wire. The miniature implantable 1000 device may contain the circuitry necessary to receive the pulse instructions from a source external to the body.

[0105] In particular, electronic circuitry 1006 of the miniature implantable device may convert an input signal received at the one or more antennas into an electrical energy and electrical pulses. In some implementations, extension tubing can provide an enclosure that houses, for example, flex circuitry. In some embodiments, the electronic circuitry 1006 may include one or a plurality of diodes that function to rectify the wireless signal, such as a sinusoidal signal, picked up by the non-inductive antenna(s). The diodes have a low threshold voltage to maximize the energy used for creating waveforms and power. Additionally, internal circuitry 1006 may include a charge balancing microelectronic component to reduce or prevent corrosion as well as a current limiter.

[0106] In certain embodiments, the electronic circuitry 1006 may include one or more non-inductive antennas, a rectifier, a charge balancer, a current limiter, a controller, and a device interface. In brief, the rectifier functions to rectify the signal received by the one or more non-inductive antennas. The rectified signal may provide power to electrodes 1004. The rectified signal may also be fed to a charge balance component that is configured to create one or more electrical pulses such that the one or more electrical pulses result in a substantially zero net charge (that is, the pulses are charge balanced). The charge balanced pulses are passed through the current limiter to the electrode interface, which applies the electrical pulses to electrodes 1004.

[0107] In some implementations, an internal dipole (or other) antenna configuration(s) may be used in lead 100 to receive RF power through electrical radiative coupling. This coupling mechanism can allow such devices to produce electrical currents capable of stimulating nerve bundles without a physical connection to an implantable pulse generator (IPG) or use of an inductive coil. In some implementations, between two to eight tissue-exposed-ring-antenna coupling contacts may be proximal to the electrodes. The tissue-exposed-ring-antenna coupling contacts may have a longitudinal length of between about 0.25 mm and about 6.0 mm from the distal end 1014 toward the proximal end 1010. The spacing between the tissue-exposed ring antenna coupling contacts may be between about 5 mm and about 80 mm. In certain implementations, tissue-exposed-small-antenna coupling contacts with a diameter between about 0.2 mm and about 0.6 mm may be used in lieu of the tissue-exposed-ring-antenna coupling contacts.

[0108] In some implementations, at least one of the antennas can be constructed as a conductive trace feature contained on one of the circuits. In other implementations, at least one of the antennas can be fabricated as a conductive wire connected to one of the circuits. In various implementations, implantable device 1000 may employ non-inductive, for example, dipole or other antenna configuration(s), to receive RF power through electrical radiative coupling.

[0109] For context, neural stimulating devices may utilize a battery-powered or charge-storage component. Such devices

are no longer functional once the battery cannot be recharged or charge cannot be stored. Consequently, for an implanted device, a patient would need to undergo a subsequent surgical procedure to obtain a functional replacement device.

[0110] In contrast, some implementations disclosed herein do not rely upon battery power or charge storage for operation. In some configurations, the implantable device can receive electrical power from radiated RF energy non-inductively and without a wired connection. As a result, the life of an implanted device is no longer limited by the life of the battery or ability to store charge.

[0111] Further, the electrical radiative coupling mechanism (for example, a dipole antenna) can be utilized to improve the form factor of the miniature implanted device and allow for miniature diameters. Electrical radiative coupling may also allow for the transmission and reception of energy at greater depths with less degradation in efficiency than inductive coil techniques. This electrical radiative coupling can provide an advantage over devices that employ inductive coupling where the efficiency of such implants may be highly dependent on the distance separating the external transmitter coil and the implanted receiver coil.

[0112] Accordingly, some implementations disclosed herein do not include inductive loops to receive RF energies in a wireless manner. Instead, some implementations disclosed herein use electric radiative coupling to receive RF energies. Such implementations facilitate a smaller form factor for a fully functional implantable electrical stimulation or recording device. The improved form factor may result in a less invasive surgical procedure for placement of the device. The improved form factor may also decrease scarring the amount of bodily tissue in contact with the implanted device is reduced.

[0113] A telemetry signal may be transmitted by the miniature implantable device **100** to deliver information to an external controller. The telemetry signal may be sent by modulation of a carrier signal. The telemetry signal does not interfere with the input received to power the miniature implantable device. In one example, the telemetry signal and powering signal are combined into one signal, where the RF telemetry signal is used to modulate the RF powering signal, and thus the implanted device is powered directly by the received telemetry signal; separate electronic subsystems harness the power contained in the signal and interpret the data content of the signal. In other embodiments, the telemetry output rate is at least 8 kilobits per second.

[0114] In other implementations, a RF pulse generator system, located externally to the miniature implanted device **1000**, may store parameters defining the excitation pulses to be applied at electrodes **1004**, which are transmitted via the second antenna.

[0115] FIG. 11 illustrates three examples of miniature implantable devices **1100A**, **1100B**, and **1100C** with various diameters. Miniature implantable device **1100A** is a miniature implantable device with a diameter of 0.8 mm. Miniature implantable device **1100A** includes a suturing feature **1108A** to allow a clinician to suture and anchor implantable miniature implantable device **1100A** during an implantation procedure. For instance, suture can be passed through the passage of suturing feature **1108A** and tied to tissue such that the mobility of the implanted device is reduced. As illustrated, implantable device **1100A** also includes an indentation **1110A** on the proximal end to allow for mating with a placement stylet during implantation.

[0116] Miniature implantable device **1100B** has a diameter of 0.4 mm and has a suturing feature **1108B** similar to **1108A**. Implantable device **1100B** also includes an indentation **1110B** on the proximal end to allow for mating with a placement stylet during implantation.

[0117] Miniature implantable device **1100C** has a diameter of 0.1 mm. Miniature implantable device **1100C** includes a suturing feature **1108C** in the form of ribs to aid suture in attaching to a surrounding tissue. Implantable device **1100C** also may include an indentation **1110C** to allow for mating with a placement stylet during implantation.

[0118] FIG. 12 illustrates the miniature wireless device **1000** (e.g., a 0.8 mm diameter) entering an 18 gauge needle **1200**. The distal end (not shown) of miniature implantable device is in position to enter the proximal opening **1202** of an 18-gauge needle **1200**. Miniature implantable device **1200** has a diameter small enough to fit into the inner lumen **1204** of the needle **1200**. The illustration may correspond to an implantation of a miniature implantable device with a diameter of 0.8 mm, shown as the implantable device **1100A** in FIG. 11. Notably, the middle and bottom devices (0.4 mm and 0.1 mm, respectively) shown in FIG. 11 are sized for advancement through introducer needles with even smaller sizes, (e.g., 22 gauge or smaller).

[0119] While it is possible to place the device **1000** directly into an introducer needle, doing so may not be desirable as the implantable device enclosure may not be as rigid as a guide wire and may not slide easily within the inner lumen of the introducer needle. Yet, a guide wire may not be used because the implantable device may not have a central void through which to mount the guide wire. To improve the ease of placement through an introducer needle, a stylet may be used to provide some rigidity to the miniature device.

[0120] FIG. 13A shows a placement stylet **1300** capable of mating with a miniature implantable device **1000** according to some implementations. Placement stylet **1300** includes a distal end **1308**, device body **1304**, and proximal end **1310**. Distal end **1308** includes a mating feature **1302** to allow the placement stylet **1300** to engage, for example, miniature implantable device **1000**. The mating feature **1302** is, for example, a convex protrusion that is shaped and sized to mate with the concave indentation **1010** of the lead **1000**. Proximal end **1306** includes handle **1306** for operator to hold placement stylet **1300**, for example, during an implantation procedure. Placement stylet **1300** can have a longitudinal length of between about 50 mm and about 177 mm. Placement stylet **1300** can have an outer diameter in the range from between about 0.1 mm and about 0.9 mm. Placement stylet **1300** may be made of a rigid biocompatible material such as stainless steel, titanium, nylon, or polyethylene.

[0121] FIG. 13B illustrates a miniature implantable device **1000** mated with a placement stylet **1300**. A clinician may mate the miniature implantable device **1000** onto the placement stylet **1300**. The mating feature **1302** on the distal end **1308** of the stylet may mate with mating feature **1010** on the proximal end **1012** of miniature implantable device **1000**. Mating feature **1302** on placement stylet **1300** may be semi-spherical in shape, and may provide mechanical gripping for placement stylet **1300** to engage the miniature implantable device **1000** during placement. Mating feature **1302** may be complementary in shape to the shape of mating feature **1012** on the proximal end **1010** of the device **1000**. In some configurations, mating feature **1302** may be convex in shape. In other configurations, mating feature **1302** may include

extruded shapes for mating the stylet **1200** to the miniature implantable device **1300** at mating feature **1012**, which may have a square, hexagon, star, or an asymmetrical shape. Mating feature **1302** may only protrude from the distal end **1308** of placement stylet **1300** from between 0.1 mm and 1.0 mm and may not fill the entirety of the device body **1006** (that is, the feature **1302** may only extend partially into device body **1006**). Mating feature **1302** may have a surface material that allows for increased friction to improve the mate between placement stylet **1300** and the miniature implantable device **1000**. Example materials may include silicon or polyurethane.

[10122] FIG. 14A illustrates a miniature implantable device **1000** mated with a placement stylet **1300** entering a proximal opening **1202** of needle **1200**. Miniature implantable device **1000** includes lead body **1016** that includes electrodes **1004** and houses electronic circuitry **1006**. The proximal end **1012** of miniature implantable device **1000** is now mated with the distal end **1308** of placement stylet **1300**. As illustrated, after the miniature implantable device **1000** has been mated to placement stylet **1300**, the subassembly of the device **1000** with the stylet **1300** can now be inserted into an 18 gauge needle **1200** or smaller. In particular, the miniature implantable device **1000** at the proximal opening **1202** of needle **1200** is being pushed into position with the placement stylet **1300**. In fact, the stylet/miniature device subassembly may now slide freely within the inner lumen **1204** of the needle **1200**. The free sliding motion may aid in the surgical placement of the miniature device **1000**.

[10123] FIGS. 14B and 14C show a miniature implantable device **1000** mated with a placement stylet **1300** exiting a distal end **1202** of needle **1200**. As discussed above, the miniature implantable device **1000** may freely traverse the inner lumen **1204** of needle **1200** with a size of 18 gauge or smaller. Once the traversal is completed, the miniature implantable device **1000** may exit the needle under the pushing force applied on the placement stylet **1300** mated to the device **1000**. As illustrated, rounded tip **1002** and body **1016** of miniature implantable **1000** have exited the distal end **1402** of needle **1200**. The portions of body **1016** that include electrodes **1004** and electronic circuitry **1006** are also shown on FIGS. 14B-14C. The proximal end **1012** of miniature implantable **1000** is mated to the distal end **1308** of placement stylet **1300**. After the implantable **1000** has been placed into a target region, the implantable device **1000** may be sutured or anchored in place. Thereafter, the placement stylet **1300** may be unmated from the implanted **1000**. A clinician may then withdraw the placement stylet **1300** by pulling the placement stylet **1300** out of the patient's body through the needle **1200**. The placement and withdrawal process may be performed under imaging guidance, such as, for example, X-Ray fluoroscopy, ultrasound fluoroscopy, etc. Once the procedure is completed, needle **1200** may be removed.

[10124] FIG. 15 demonstrates the feasibility of placing multiple miniature implantable devices in the anatomical positions of the forearm. The compact size of the miniature implantable device **1000** may allow minimally invasive placement procedure, thereby reducing complications during procedure and improving recovery time after procedure. Moreover, the compact size may allow multiple miniature implantable devices to be placed in nearby target areas. As shown in FIG. 15, four miniature implantable devices **1000** are placed into the forearm of a patient, one in the upper forearm area and three in the lower forearm area. Each

implanted lead may treat a specific nerve branch in the forearm region. Similarly, the miniature implantable devices **1000** also may be delivered to treat a neural tissue branching from the spinal column including but not limited to the dorsal root ganglia, traversing, or exiting nerve. The miniature implantable devices **1000** may also be delivered to treat peripheral nerve targets such as the radius, ulnar, sciatic, femoral, occipital, or brachial nerves. Given the compact size of the miniature leads, two or more such devices may be placed with pin-point precision to treat multiple nerve branches or peripheral nerve targets at the same time. In particular, two or more such devices may be placed with close proximity within a target area to provide pain-relief therapy to one or more excitable tissues within the target area. For instance, a patient may have one miniature implantable device **1000** implanted adjacent to or near a target area. If more therapeutic effect is desired, the patient may have additional miniature implantable devices **1000** implanted adjacent to or near the target area to enhance the therapeutic effect.

[10125] FIGS. 16A-16E illustrate a suction stylet **1600** in various modes of operation. The suction stylet **1600** is different from the placement stylet **1000** described above. As shown in FIG. 16A, the suction stylet **1600** is hollow inside and may have an outer diameter of between about 0.1 mm and 0.9 mm and may have a longitudinal length of between about 50 mm and 170 mm. The suction stylet **1600** may have an inner diameter between about 0.05 mm and 0.75 mm. The suction stylet **1600** includes distal end **1618**, stylet body **1614**, and proximal end **1616**.

[10126] The distal end **1618** may include a mating feature **1602**, chamber **1604**, and plunger tip **1606**. Mating feature **1602** also may be referred to as the suction tip. In some configurations, mating feature **1602** may be semi-spherical in shape and may have a diameter between about 0.05 mm and 0.08 mm. Mating feature **1602** on suction stylet **1600** may mate to mating feature **1010** on miniature wireless lead **1000**, in a manner similar to the mechanical mating described above. In some instances, a mating force may be provided by a negative air pressure created inside air chamber **1604** on suction stylet **1600**. In particular, by moving the plunger tip **1606** along the shaft for inner plunger **1608**, a negative air pressure may be created in chamber **1604**.

[10127] Stylet body **1614** may include inner plunger **1608** located inside shaft **1622**. The inner plunger shaft **1622** may have a diameter between about 0.05 mm and 0.75 mm, allowing the plunger **1608** to slide inside of the hollow suction stylet **1600**. The total length of the inner plunger including the inner plunger handle may be between about 50 mm and 170 mm. The inner plunger shaft, when installed, may not protrude beyond the suction tip.

[10128] The proximal end **1620** of suction stylet **1600** may include base **1616**, handle **1612**, and locking feature **1610**. Base **1616** may have a diameter of between about 0.1 mm and 0.9 mm depending on the outer diameter of the hollow stylet **1600** being utilized. Handle **1612** may include cap **1612a** and tip **1612b**. Cap **1612a** closes the tubing of suction stylet **1600**. Handle tip **1612b** may be pulled Out during a placement procedure. The pulling may cause sliding motion of the plunger **1608** inside shaft **1622**, which creates a negative air pressure in chamber **1604**. Suction force may be created on suction tip, mating feature **1602**, so that suction stylet **1600** is mated with miniature implantable device **1000**. Locking mechanism **1610** may include spike **1610a**, spike **1610b**, and

hinge **1610c**. Hinge **1610c** is mounted on base **1616** and may rotate to engage spikes **1610a** and **1610b** with cap **1612a**, as discussed below.

[0129] FIGS. **16A** to **16C** show the suction stylet without the mating miniature implantable device. As illustrated, the inner plunger **1608** may be slid in a translating motion inside shaft **1622** to different locations within the hollow stylet **1600**. Locking mechanism **1610** may be used to lock plunger **1608** into certain positions.

[0130] In particular, FIG. **16A** shows the inner plunger **1608** in a complete seated condition with respect to the distal end **1620** of stylet **1600**. In this position, no pressure differential may exist between the mating feature **1602** and plunger tip **1606**.

[0131] FIGS. **16B** and **16D** show the inner plunger **1608** at stage **1** position, which may be between about 1 mm and 10 mm from mating feature **1602** (suction tip) of the hollow stylet **1600**. FIG. **16B** shows suction stylet **1600** without the mated miniature implantable device **1000**, while FIG. **16D** shows suction stylet **1600** mated with miniature implantable device **1000**. By pulling the handle tip **1612b** away from the hollow stylet, a pressure differential may be generated to create a temporary mate between the miniature implantable device **1000** and the stylet **1600**. The mate is between mating feature **1002** on miniature implantable device **1000** and suction tip **1602** on suction stylet **1600**. Locking mechanism **1610**, as shown in FIG. **16B**, may lock the inner plunger **1608** in place by engaging spike **1610a** between base **1616** and cap **1612a**. Once locked, the pressure differential between suction tip (mating feature **1602**) and plunger tip **1606** may be maintained. This locking mechanism may be adjustable to allow for the inner plunger to be locked in a desired location.

[0132] FIGS. **16C** and **16E** illustrate the inner plunger **1608** being locked into a stage **2** location, which may be between about 2 mm and 30 mm from mating feature **1602** (suction tip) of the hollow stylet **1600**. FIG. **16C** shows suction stylet **1600** without the mated miniature implantable device **1000**, while FIG. **16E** shows suction stylet **1600** mated with miniature implantable device **1000**. This stage may have a greater pressure differential generated than the stage **1** location depicted in FIG. **16B**. In other examples, a suction stylet assembly may have one more locking stages depending on the locking mechanism utilized. An adjustable locking mechanism may allow for infinite locking distance locations.

[0133] The suction stylet design may provide the clinician the ability to install and remove the miniature implantable device **1000** from a patient. As discussed above, once suction stylet **1600** is activated to engage miniature implantable device **1000**, an assembly of miniature implantable device **1000** and suction stylet **1600** may be created. The clinician may push the suction stylet to advance the entire assembly, for example, down the inner lumen **1204** of needle **1200**, towards the target site. If the miniature implantable device **1000** is already implanted, the clinician can mate the miniature implantable device **1000** to the suction tip of the stylet **1600**, then pull on handle tip **1612b**. Plunger **1608** may slide inside shaft **1622**, thereby creating a pressure differential between suction tip **1602** and plunger tip **1606**. The pressure differential may engage the miniature implantable device **1000**, and the clinician may withdraw the suction stylet **1600** to take the implanted lead **600** from within the patient.

[0134] FIG. **17A** shows cylindrical electrodes **1704** (eight (8) shown) on the outside of a lead **1700**. The outer diameter of lead **1700** may be 0.8 cm or smaller. Each cylindrical

electrode **1704** may operate as a recording or stimulating electrode. A stimulating electrode may apply electric pulses to an excitable tissue to achieve therapeutic effect. A recording electrode may record or sense neural activity from surrounding tissue. In some instances, the electrodes may alternate between stimulating and recording electrodes. In the example shown, the miniature lead **1700** is not tethered and not connected to another structure or device for mechanical or electrical interface. One or more electrical flex circuitry may be internal to the miniature lead. The flex circuit may be inside gaps **1706**, in between electrodes **1704**. Lead **1700** may also include a rounded-tip **1702** for easy placement, as well as a mating feature to mate the lead **1700** with a stylet, such as those described above.

[0135] FIG. **17B** shows four example miniature implantable devices incorporating multiple recording and/or stimulating electrodes **1704**. The four example leads shown do not have an inner stylet lumen to mount a stylet or a guide wire, but may include a mating feature such as those described above. The recording and/or stimulating electrode pads **1704** may couple to a surrounding tissue for recording and/or stimulating. In a recording mode, neural activities of the surrounding tissue may be sensed and capture in electrical signals that encode such neural activities. In a stimulating mode, electric pulses may be applied to the surrounding tissue for pain relief. In some configurations, the electric circuitry may be spaced in between the recording and/or stimulating electrode pads, for example, in gaps **1706**. As illustrated, example miniature implantable devices **1700** may include rounded tip **1702** for easy placement.

[0136] FIG. **17C** illustrates a miniature implantable device **1700** with stimulating and/or recording electrodes **1704** located at the distal end of the lead, in the direction of the rounded tip **1702**. As illustrated, the electronic circuitry **1708** is located towards the proximal end of implantable device **1700**, rather than spaced between the electrodes **1702**.

[0137] For the configurations shown in FIGS. **17A** to **17C**, the electronic circuitry may provide power to drive the stimulating and/or recording electrodes. As described above, the electric pulses may be created by the electronic circuitry based on the input signal received at the antennas on the implantable devices. The electric pulses may be sent to a stimulating electrode to delivery pain-relief to an excitable tissue. As discussed above, a recording electrode may record neural activities of a surrounding tissue. The electronic circuitry also may route the recorded analog signal to the antennas on the implantable device which may in turn transmit the recorded analog signal to an external controller, located outside the patient body. In some implementations, the recorded analog signal may be processed and transmitted in a manner similar to the telemetry signal described above. For example, the transmission of the recorded analog signal, like the telemetry signal discussed herein, may be powered by the electrical power in the input signal.

[0138] FIG. **18** depicts an example of a lead **1800** with each electrode pad **1802** configured as a rectangular square. As illustrated, each rectangular square electrode pad **1802** may include an electrode **1806**. Electronic circuitry may be located on structures **1804**. Electrode **1806** may have a surface area of at least 0.06 mm². This implantable device **1800** may have a total width from between about 0.5 mm and 0.8 mm. The height of the implantable device **1800** may be from between about 0.1 mm and about 0.8 mm. The total length of the implantable device **1800** may be from between about 10

mm and about 600 mm. The rectangular electrode pads **1502** may have a length from between about 0.5 mm and about 6.0 mm and a width from between about 0.45 mm and about 0.75 mm. The inter-electrode spacing may be from between about 0.1 mm and about 6.0 mm. This implantable device **1800** may be suitable for stimulating a relatively large area.

[0139] FIGS. **19** and **20** illustrate an example of a neural stimulation system that may employ the implantable devices described above. These implantable devices may also be referred to as implantable leads.

[0140] In particular, FIG. **19** depicts a high-level diagram of an example of a neural stimulation system. The neural stimulation system may include four major components, namely, a programmer module **1902**, a RF pulse generator module **1906**, a transmit (TX) antenna **1910** (for example, a patch antenna, slot antenna, or a dipole antenna), and an implanted device **1914**, which may be a lead such as those described above. The programmer module **1902** may be a computer device, such as a smart phone, running a software application that supports a wireless connection **1914**, such as Bluetooth®. The application can enable the user to view the system status and diagnostics, change various parameters, increase/decrease the desired stimulus amplitude of the electrode pulses, and adjust feedback sensitivity of the RF pulse generator module **1906**, among other functions.

[0141] The RF pulse generator module **1906** may include communication electronics that support the wireless connection **1904**, the stimulation circuitry, and the battery to power the generator electronics. In some implementations, the RF pulse generator module **1906** includes the TX antenna embedded into its packaging form factor while, in other implementations, the TX antenna is connected to the RF pulse generator module **1906** through a wired connection **1908** or a wireless connection (not shown). The TX antenna **1910** may be coupled directly to tissue to create an electric field that powers the implanted device **1914**. The TX antenna **1910** communicates with the implanted device **1914** through an RF interface. For instance, the TX antenna **1910** radiates an RF transmission signal that is modulated and encoded by the RF pulse generator module **1910**. The implanted device **1914** contains one or more antennas, such as dipole antenna(s), to receive and transmit through RF interface **1912**. In particular, the coupling mechanism between antenna **1910** and the one or more antennas on the implanted device **1914** is electrical radiative coupling and not inductive coupling. In other words, the coupling is through an electric field rather than a magnetic field.

[0142] Through this electrical radiative coupling, the TX antenna **1910** can provide an input signal to the implanted device **1914**. This input signal contains energy and may contain information encoding stimulus waveforms to be applied at the electrodes of the implanted device **1914**. In some implementations, the power level of this input signal directly determines an applied amplitude (for example, power, current, or voltage) of the one or more electrical pulses created using the electrical energy contained in the input signal. Within the implanted device **1914** are components for demodulating the RF transmission signal, and electrodes to deliver the stimulation to surrounding neuronal tissue.

[0143] The RF pulse generator module **1906** can be implanted subcutaneously, or it can be worn external to the body. When external to the body, the RF generator module **1906** can be incorporated into a belt or harness design to allow for electric radiative coupling through the skin and underly-

ing tissue to transfer power and/or control parameters to the implanted device **1914**, which can be a passive stimulator. In either event, receiver circuit(s) internal to the device **1914** can capture the energy radiated by the TX antenna **1910** and convert this energy to an electrical waveform. The receiver circuit(s) may further modify the waveform to create an electrical pulse suitable for the stimulation of neural tissue, and this pulse may be delivered to the tissue via electrode pads.

[0144] In some implementations, the RF pulse generator module **1906** can remotely control the stimulus parameters (that is, the parameters of the electrical pulses applied to the neural tissue) and monitor feedback from the wireless device **1914** based on RF signals received from the implanted wireless device **1914**. A feedback detection algorithm implemented by the RF pulse generator module **1906** can monitor data sent wirelessly from the implanted wireless device **1914**, including information about the energy that the implanted wireless device **1914** is receiving from the RF pulse generator and information about the stimulus waveform being delivered to the electrode pads. In order to provide an effective therapy for a given medical condition, the system can be tuned to provide the optimal amount of excitation or inhibition to the nerve fibers by electrical stimulation. A closed loop feedback control method can be used in which the output signals from the implanted wireless device **1914** are monitored and used to determine the appropriate level of neural stimulation current for maintaining effective neuronal activation, or, in some cases, the patient can manually adjust the output signals in an open loop control method.

[0145] FIG. **20** depicts a detailed diagram of an example of the neural stimulation system. As depicted, the programming module **1902** may comprise user input system **2002** and communication subsystem **2008**. The user input system **2021** may allow various parameter settings to be adjusted (in some cases, in an open loop fashion) by the user in the form of instruction sets. The communication subsystem **2008** may transmit these instruction sets (and other information) via the wireless connection **1904**, such as Bluetooth or Wi-Fi, to the RF pulse generator module **1906**, as well as receive data from module **1906**.

[0146] For instance, the programmer module **1902**, which can be utilized for multiple users, such as a patient's control unit or clinician's programmer unit, can be used to send stimulation parameters to the RF pulse generator module **1906**. The stimulation parameters that can be controlled may include pulse amplitude, pulse frequency, and pulse width in the ranges shown in Table 1. In this context the term pulse refers to the phase of the waveform that directly produces stimulation of the tissue; the parameters of the charge-balancing phase (described below) can similarly be controlled. The patient and/or the clinician can also optionally control overall duration and pattern of treatment.

TABLE 1

Stimulation Parameter	
Pulse Amplitude:	0 to 20 mA
Pulse Frequency:	0 to 20,000 Hz
Pulse Width:	0 to 2 ms

[0147] The implantable device **1914** or RF pulse generator module **1914** (which may be a lead such as those described above) may be initially programmed to meet the specific parameter settings for each individual patient during the ini-

tial implantation procedure. Because medical conditions or the body itself can change over time, the ability to re-adjust the parameter settings may be beneficial to ensure ongoing efficacy of the neural modulation therapy.

[0148] The programmer module **1902** may be functionally a smart device and associated application. The smart device hardware may include a CPU **2006** and be used as a vehicle to handle touchscreen input on a graphical user interface (GUI) **2004**, for processing and storing data.

[0149] The RF pulse generator module **1906** may be connected via wired connection **1508** to an external TX antenna **1910**. Alternatively, both the antenna and the RF pulse generator are located subcutaneously (not shown).

[0150] The signals sent by RF pulse generator module **1906** to the implanted device **1914** may include both power and parameter-setting attributes in regards to stimulus waveform, amplitude, pulse width, and frequency. The RF pulse generator module **1906** can also function as a wireless receiving unit that receives feedback signals from the implanted device **1914**. To that end, the RF pulse generator module **1906** may contain microelectronics or other circuitry to handle the generation of the signals transmitted to the device **1914** as well as handle feedback signals, such as those from the device **1914**. For example, the RF pulse generator module **1906** may comprise controller subsystem **2014**, high-frequency oscillator **2018**, RF amplifier **2016**, a RF switch **2023**, and a feedback subsystem **2012**.

[0151] The controller subsystem **2014** may include a CPU **2030** to handle data processing, a memory subsystem **2028** such as a local memory, communication subsystem **2034** to communicate with programmer module **1902** (including receiving stimulation parameters from programmer module), pulse generator circuitry **2036**, and digital/analog (D/A) converters **2032**.

[0152] The controller subsystem **2014** may be used by the patient and/or the clinician to control the stimulation parameter settings (for example, by controlling the parameters of the signal sent from RF pulse generator module **1906** to device **1914**). These parameter settings can affect, for example, the power, current level, or shape of the one or more electrical pulses. The programming of the stimulation parameters can be performed using the programming module **1902**, as described above, to set the repetition rate, pulse width, amplitude, and waveform that will be transmitted by RF energy to the receive (RX) antenna **2038**, typically a dipole antenna (although other types may be used), in the wireless implanted device **1914**. The clinician may have the option of locking and/or hiding certain settings within the programmer interface, thus limiting the patient's ability to view or adjust certain parameters because adjustment of certain parameters may require detailed medical knowledge of neurophysiology, neuroanatomy, protocols for neural modulation, and safety limits of electrical stimulation.

[0153] The controller subsystem **2014** may store received parameter settings in the local memory subsystem **2028**, until the parameter settings are modified by new input data received from the programming module **1902**. The CPU **2006** may use the parameters stored in the local memory to control the pulse generator circuitry **2036** to generate a stimulus waveform that is modulated by a high frequency oscillator **2018** in the range from 300 MHz to 8 GHz. The resulting RF signal may then be amplified by RF amplifier **2026** and then sent through an RF switch **2023** to the TX antenna **1910** to reach through depths of tissue to the RX antenna **2038**.

[0154] In some implementations, the RF signal sent by TX antenna **1910** may simply be a power transmission signal used by the device **1914** to generate electric pulses. In other implementations, a telemetry signal may also be transmitted to the device **1914** to send instructions about the various operations of the device **1914**. The telemetry signal may be sent by the modulation of the carrier signal (through the skin if external, or through other body tissues if the pulse generator module **1906** is implanted subcutaneously). The telemetry signal is used to modulate the carrier signal (a high frequency signal) that is coupled onto the implanted antenna(s) **2038** and does not interfere with the input received on the same lead to power the implant. In one embodiment the telemetry signal and powering signal are combined into one signal, where the RF telemetry signal is used to modulate the RF powering signal, and thus the implanted stimulator is powered directly by the received telemetry signal; separate subsystems in the stimulator harness the power contained in the signal and interpret the data content of the signal.

[0155] The RF switch **2023** may be a multipurpose device such as a dual directional coupler, which passes the relatively high amplitude, extremely short duration RF pulse to the TX antenna **1910** with minimal insertion loss while simultaneously providing two low-level outputs to feedback subsystem **2012**; one output delivers a forward power signal to the feedback subsystem **2012**, where the forward power signal is an attenuated version of the RF pulse sent to the TX antenna **1910**, and the other output delivers a reverse power signal to a different port of the feedback subsystem **2012**, where reverse power is an attenuated version of the reflected RF energy from the TX Antenna **1910**.

[0156] During the on-cycle time (when an RF signal is being transmitted to the device **1914**), the RF switch **2023** is set to send the forward power signal to feedback subsystem. During the off-cycle time (when an RF signal is not being transmitted to the device **1914**), the RF switch **2023** can change to a receiving mode in which the reflected RF energy and/or RF signals from the device **1914** are received to be analyzed in the feedback subsystem **2012**.

[0157] The feedback subsystem **2012** of the RF pulse generator module **1906** may include reception circuitry to receive and extract telemetry or other feedback signals from the device **1914** and/or reflected RF energy from the signal sent by TX antenna **1910**. The feedback subsystem may include an amplifier **2026**, a filter **2024**, a demodulator **2022**, and an A/D converter **2020**.

[0158] The feedback subsystem **2012** receives the forward power signal and converts this high-frequency AC signal to a DC level that can be sampled and sent to the controller subsystem **2014**. In this way the characteristics of the generated RF pulse can be compared to a reference signal within the controller subsystem **2014**. If a disparity (error) exists in any parameter, the controller subsystem **2014** can adjust the output to the RF pulse generator **1906**. The nature of the adjustment can be, for example, proportional to the computed error. The controller subsystem **2014** can incorporate additional inputs and limits on its adjustment scheme such as the signal amplitude of the reverse power and any predetermined maximum or minimum values for various pulse parameters.

[0159] The reverse power signal can be used to detect fault conditions in the RF-power delivery system. In an ideal condition, when TX antenna **1910** has perfectly matched impedance to the tissue that it contacts, the electromagnetic waves generated from the RF pulse generator **1906** pass unimpeded

from the TX antenna 1910 into the body tissue. However, in real-world applications a large degree of variability may exist in the body types of users, types of clothing worn, and positioning of the antenna 1910 relative to the body surface. Since the impedance of the antenna 1610 depends on the relative permittivity of the underlying tissue and any intervening materials, and also depends on the overall separation distance of the antenna from the skin, in any given application there can be an impedance mismatch at the interface of the TX antenna 1910 with the body surface. When such a mismatch occurs, the electromagnetic waves sent from the RF pulse generator 1906 are partially reflected at this interface, and this reflected energy propagates backward through the antenna feed.

[0160] The dual directional coupler RF switch 2023 may prevent the reflected RF energy propagating back into the amplifier 2026, and may attenuate this reflected RF signal and send the attenuated signal as the reverse power signal to the feedback subsystem 2012. The feedback subsystem 2012 can convert this high-frequency AC signal to a DC level that can be sampled and sent to the controller subsystem 2014. The controller subsystem 2014 can then calculate the ratio of the amplitude of the reverse power signal to the amplitude of the forward power signal. The ratio of the amplitude of reverse power signal to the amplitude level of forward power may indicate severity of the impedance mismatch.

[0161] In order to sense impedance mismatch conditions, the controller subsystem 2014 can measure the reflected-power ratio in real time, and according to preset thresholds for this measurement, the controller subsystem 2014 can modify the level of RF power generated by the RF pulse generator 1906. For example, for a moderate degree of reflected power the course of action can be for the controller subsystem 2014 to increase the amplitude of RF power sent to the TX antenna 1910, as would be needed to compensate for slightly non-optimum but acceptable TX antenna coupling to the body. For higher ratios of reflected power, the course of action can be to prevent operation of the RF pulse generator 1906 and set a fault code to indicate that the TX antenna 1910 has little or no coupling with the body. This type of reflected-power fault condition can also be generated by a poor or broken connection to the TX antenna. In either case, it may be desirable to stop RF transmission when the reflected-power ratio is above a defined threshold, because internally reflected power can lead to unwanted heating of internal components, and this fault condition means the system cannot deliver sufficient power to the implanted wireless neural stimulator and thus cannot deliver therapy to the user.

[0162] The controller 2042 of the device 1914 may transmit informational signals, such as a telemetry signal, through the antenna 2038 to communicate with the RF pulse generator module 1906 during its receive cycle. For example, the telemetry signal from the device 1914 may be coupled to the modulated signal on the dipole antenna(s) 2038, during the on and off state of the transistor circuit to enable or disable a waveform that produces the corresponding RF bursts necessary to transmit to the external (or remotely implanted) pulse generator module 1906. The antenna(s) 2038 may be connected to electrodes 2054 in contact with tissue to provide a return path for the transmitted signal. An A/D (not shown) converter can be used to transfer stored data to a serialized pattern that can be transmitted on the pulse modulated signal from the internal antenna(s) 2038 of the neural stimulator.

[0163] A telemetry signal from the implanted wireless device 1914 may include stimulus parameters such as the power or the amplitude of the current that is delivered to the tissue from the electrodes. The feedback signal can be transmitted to the RF pulse generator module 1916 to indicate the strength of the stimulus at the nerve bundle by means of coupling the signal to the implanted RX antenna 2038, which radiates the telemetry signal to the external (or remotely implanted) RF pulse generator module 1906. The feedback signal can include either or both an analog and digital telemetry pulse modulated carrier signal. Data such as stimulation pulse parameters and measured characteristics of stimulator performance can be stored in an internal memory device within the implanted device 1914, and sent on the telemetry signal. The frequency of the carrier signal may be in the range of at 300 MHz to 8 GHz.

[0164] In the feedback subsystem 2012, the telemetry signal can be down modulated using demodulator 2022 and digitized by being processed through an analog to digital (A/D) converter 2020. The digital telemetry signal may then be routed to a CPU 2030 with embedded code, with the option to reprogram, to translate the signal into a corresponding current measurement in the tissue based on the amplitude of the received signal. The CPU 2030 of the controller subsystem 2014 can compare the reported stimulus parameters to those held in local memory 2028 to verify the stimulator(s) 1914 delivered the specified stimuli to tissue. For example, if the stimulator reports a lower current than was specified, the power level from the RF pulse generator module 1906 can be increased so that the implanted neural stimulator 1914 will have more available power for stimulation. The implanted neural stimulator 1914 can generate telemetry data in real time, for example, at a rate of 8 kbits per second. All feedback data received from the implanted lead module 1914 can be logged against time and sampled to be stored for retrieval to a remote monitoring system accessible by the health care professional for trending and statistical correlations.

[0165] The sequence of remotely programmable RF signals received by the internal antenna(s) 2038 may be conditioned into waveforms that are controlled within the implantable device 1914 by the control subsystem 2042 and routed to the appropriate electrodes 2054 that are placed in proximity to the tissue to be stimulated. For instance, the RF signal transmitted from the RF pulse generator module 1906 may be received by RX antenna 2038 and processed by circuitry, such as waveform conditioning circuitry 2040, within the implanted wireless device 1914 to be converted into electrical pulses applied to the electrodes 2054 through electrode interface 2052. In some implementations, the implanted device 1914 contains between two to sixteen electrodes 2054.

[0166] The waveform conditioning circuitry 2040 may include a rectifier 2044, which rectifies the signal received by the RX antenna 2038. The rectified signal may be fed to the controller 2042 for receiving encoded instructions from the RF pulse generator module 1906. The rectifier signal may also be fed to a charge balance component 2046 that is configured to create one or more electrical pulses based such that the one or more electrical pulses result in a substantially zero net charge at the one or more electrodes (that is, the pulses are charge balanced). The charge-balanced pulses are passed through the current limiter 2048 to the electrode interface 2052, which applies the pulses to the electrodes 2054 as appropriate.

[0167] The current limiter 2048 insures the current level of the pulses applied to the electrodes 2054 is not above a threshold current level. In some implementations, an amplitude (for example, current level, voltage level, or power level) of the received RF pulse directly determines the amplitude of the stimulus. In this case, it may be particularly beneficial to include current limiter 2048 to prevent excessive current or charge being delivered through the electrodes, although current limiter 2048 may be used in other implementations where this is not the case. Generally, for a given electrode having several square millimeters surface area, it is the charge per phase that should be limited for safety (where the charge delivered by a stimulus phase is the integral of the current). But, in some cases, the limit can instead be placed on the current, where the maximum current multiplied by the maximum possible pulse duration is less than or equal to the maximum safe charge. More generally, the limiter 2048 may act as a charge limiter that limits a characteristic (for example, current or duration) of the electrical pulses so that the charge per phase remains below a threshold level (typically, a safe-charge limit).

[0168] In the event the implanted wireless device 2014 receives a “strong” pulse of RF power sufficient to generate a stimulus that would exceed the predetermined safe-charge limit, the current limiter 2048 can automatically limit or “clip” the stimulus phase to maintain the total charge of the phase within the safety limit. The current limiter 2048 may be a passive current limiting component that cuts the signal to the electrodes 2054 once the safe current limit (the threshold current level) is reached. Alternatively, or additionally, the current limiter 2048 may communicate with the electrode interface 2052 to turn off all electrodes 2054 to prevent tissue damaging current levels.

[0169] A clipping event may trigger a current limiter feedback control mode. The action of clipping may cause the controller to send a threshold power data signal to the pulse generator 1906. The feedback subsystem 2012 detects the threshold power signal and demodulates the signal into data that is communicated to the controller subsystem 2014. The controller subsystem 2014 algorithms may act on this current-limiting condition by specifically reducing the RF power generated by the RF pulse generator, or cutting the power completely. In this way, the pulse generator 1906 can reduce the RF power delivered to the body if the implanted wireless neural stimulator 1914 reports is receiving excess RF power.

[0170] The controller 2050 of the device 2005 may communicate with the electrode interface 2052 to control various aspects of the electrode setup and pulses applied to the electrodes 2054. The electrode interface 2052 may act as a multiplex and control the polarity and switching of each of the electrodes 2054. For instance, in some implementations, the wireless stimulator 1906 has multiple electrodes 2054 in contact with tissue, and for a given stimulus the RF pulse generator module 1906 can arbitrarily assign one or more electrodes to 1) act as a stimulating electrode, 2) act as a return electrode, or 3) be inactive by communication of assignment sent wirelessly with the parameter instructions, which the controller 2050 uses to set electrode interface 2052 as appropriate. It may be physiologically advantageous to assign, for example, one or two electrodes as stimulating electrodes and to assign all remaining electrodes as return electrodes.

[0171] Also, in some implementations, for a given stimulus pulse, the controller 2050 may control the electrode interface 2052 to divide the current arbitrarily (or according to instruc-

tions from pulse generator module 1906) among the designated stimulating electrodes. This control over electrode assignment and current control can be advantageous because in practice the electrodes 2054 may be spatially distributed along various neural structures, and through strategic selection of the stimulating electrode location and the proportion of current specified for each location, the aggregate current distribution in tissue can be modified to selectively activate specific neural targets. This strategy of current steering can improve the therapeutic effect for the patient.

[0172] In another implementation, the time course of stimuli may be arbitrarily manipulated. A given stimulus waveform may be initiated at a time T_{start} and terminated at a time T_{final} , and this time course may be synchronized across all stimulating and return electrodes; further, the frequency of repetition of this stimulus cycle may be synchronous for all the electrodes. However, controller 2050, on its own or in response to instructions from pulse generator 1906, can control electrode interface 2052 to designate one or more subsets of electrodes to deliver stimulus waveforms with non-synchronous start and stop times, and the frequency of repetition of each stimulus cycle can be arbitrarily and independently specified.

[0173] For example, a stimulator having eight electrodes may be configured to have a subset of five electrodes, called set A, and a subset of three electrodes, called set B. Set A might be configured to use two of its electrodes as stimulating electrodes, with the remainder being return electrodes. Set B might be configured to have just one stimulating electrode. The controller 2050 could then specify that set A deliver a stimulus phase with 3 mA current for a duration of 200 us followed by a 400 us charge-balancing phase. This stimulus cycle could be specified to repeat at a rate of 60 cycles per second. Then, for set B, the controller 2050 could specify a stimulus phase with 1 mA current for duration of 500 us followed by a 800 us charge-balancing phase. The repetition rate for the set-B stimulus cycle can be set independently of set A, say for example it could be specified at 25 cycles per second. Or, if the controller 2050 was configured to match the repetition rate for set B to that of set A, for such a case the controller 2050 can specify the relative start times of the stimulus cycles to be coincident in time or to be arbitrarily offset from one another by some delay interval.

[0174] In some implementations, the controller 2050 can arbitrarily shape the stimulus waveform amplitude, and may do so in response to instructions from pulse generator 1506. The stimulus phase may be delivered by a constant-current source or a constant-voltage source, and this type of control may generate characteristic waveforms that are static, e.g. a constant-current source generates a characteristic rectangular pulse in which the current waveform has a very steep rise, a constant amplitude for the duration of the stimulus, and then a very steep return to baseline. Alternatively, or additionally, the controller 2050 can increase or decrease the level of current at any time during the stimulus phase and/or during the charge-balancing phase. Thus, in some implementations, the controller 2050 can deliver arbitrarily shaped stimulus waveforms such as a triangular pulse, sinusoidal pulse, or Gaussian pulse for example. Similarly, the charge-balancing phase can be arbitrarily amplitude-shaped, and similarly a leading anodic pulse (prior to the stimulus phase) may also be amplitude-shaped.

[0175] As described above, the device 1914 may include a charge-balancing component 2046. Generally, for constant

current stimulation pulses, pulses should be charge balanced by having the amount of cathodic current should equal the amount of anodic current, which is typically called biphasic stimulation. Charge density is the amount of current times the duration it is applied, and is typically expressed in the units of $\mu\text{C}/\text{cm}^2$. In order to avoid the irreversible electrochemical reactions such as pH change, electrode dissolution as well as tissue destruction, no net charge should appear at the electrode-electrolyte interface, and it is generally acceptable to have a charge density less than $30 \mu\text{C}/\text{cm}^2$. Biphasic stimulating current pulses ensure that no net charge appears at the electrode after each stimulation cycle and the electrochemical processes are balanced to prevent net de currents. The device 1914 may be designed to ensure that the resulting stimulus waveform has a net zero charge. Charge balanced stimuli are thought to have minimal damaging effects on tissue by reducing or eliminating electrochemical reaction products created at the electrode-tissue interface.

[0176] A stimulus pulse may have a negative-voltage or current, called the cathodic phase of the waveform. Stimulating electrodes may have both cathodic and anodic phases at different times during the stimulus cycle. An electrode that delivers a negative current with sufficient amplitude to stimulate adjacent neural tissue is called a “stimulating electrode.” During the stimulus phase the stimulating electrode acts as a current sink. One or more additional electrodes act as a current source and these electrodes are called “return electrodes.” Return electrodes are placed elsewhere in the tissue at some distance from the stimulating electrodes. When a typical negative stimulus phase is delivered to tissue at the stimulating electrode, the return electrode has a positive stimulus phase. During the subsequent charge-balancing phase, the polarities of each electrode are reversed.

[0177] In some implementations, the charge balance component 2046 uses a blocking capacitor(s) placed electrically in series with the stimulating electrodes and body tissue, between the point of stimulus generation within the stimulator circuitry and the point of stimulus delivery to tissue. In this manner, a resistor-capacitor (RC) network may be formed. In a multi-electrode stimulator, one charge-balance capacitor(s) may be used for each electrode or a centralized capacitor(s) may be used within the stimulator circuitry prior to the point of electrode selection. The RC network can block direct current (DC), however it can also prevent low-frequency alternating current (AC) from passing to the tissue. The frequency below which the series RC network essentially blocks signals is commonly referred to as the cutoff frequency, and in one embodiment the design of the stimulator system may ensure the cutoff frequency is not above the fundamental frequency of the stimulus waveform. In this embodiment of the present invention, the wireless stimulator may have a charge-balance capacitor with a value chosen according to the measured series resistance of the electrodes and the tissue environment in which the stimulator is implanted. By selecting a specific capacitance value the cutoff frequency of the RC network in this embodiment is at or below the fundamental frequency of the stimulus pulse.

[0178] In other implementations, the cutoff frequency may be chosen to be at or above the fundamental frequency of the stimulus, and in this scenario the stimulus waveform created prior to the charge-balance capacitor, called the drive waveform, may be designed to be non-stationary, where the envelope of the drive waveform is varied during the duration of the drive pulse. For example, in one embodiment, the initial

amplitude of the drive waveform is set at an initial amplitude V_i , and the amplitude is increased during the duration of the pulse until it reaches a final value $k \cdot V_i$. By changing the amplitude of the drive waveform over time, the shape of the stimulus waveform passed through the charge-balance capacitor is also modified. The shape of the stimulus waveform may be modified in this fashion to create a physiologically advantageous stimulus.

[0179] In some implementations, the wireless device 1914 may create a drive-waveform envelope that follows the envelope of the RF pulse received by the receiving dipole antenna (s) 2038. In this case, the RF pulse generator module 1906 can directly control the envelope of the drive waveform within the wireless device 1914, and thus no energy storage may be required inside the stimulator itself. In this implementation, the stimulator circuitry may modify the envelope of the drive waveform or may pass it directly to the charge-balance capacitor and/or electrode-selection stage.

[0180] In some implementations, the implanted device 1914 may deliver a single-phase drive waveform to the charge balance capacitor or it may deliver multiphase drive waveforms. In the case of a single-phase drive waveform, for example, a negative-going rectangular pulse, this pulse comprises the physiological stimulus phase, and the charge-balance capacitor is polarized (charged) during this phase. After the drive pulse is completed, the charge balancing function is performed solely by the passive discharge of the charge-balance capacitor, where it dissipates its charge through the tissue in an opposite polarity relative to the preceding stimulus. In one implementation, a resistor within the stimulator facilitates the discharge of the charge-balance capacitor. In some implementations, using a passive discharge phase, the capacitor may allow virtually complete discharge prior to the onset of the subsequent stimulus pulse.

[0181] In the case of multiphase drive waveforms the wireless stimulator may perform internal switching to pass negative-going or positive-going pulses (phases) to the charge-balance capacitor. These pulses may be delivered in any sequence and with varying amplitudes and waveform shapes to achieve a desired physiological effect. For example, the stimulus phase may be followed by an actively driven charge-balancing phase, and/or the stimulus phase may be preceded by an opposite phase. Preceding the stimulus with an opposite-polarity phase, for example, can have the advantage of reducing the amplitude of the stimulus phase required to excite tissue.

[0182] In some implementations, the amplitude and timing of stimulus and charge-balancing phases is controlled by the amplitude and timing of RF pulses from the RF pulse generator module 1906, and in others this control may be administered internally by circuitry onboard the wireless device 1914, such as controller 2050. In the case of onboard control, the amplitude and timing may be specified or modified by data commands delivered from the pulse generator module 1906.

[0183] A number of implementations have been described. Nevertheless, it will be understood that various modifications may be made. Accordingly, other implementations are within the scope of the following claims.

What is claimed is:

1. A method of treating chronic pain or inflammation with neural modulation, the method comprising:

placing a surgical instrument to reach into a torso section of a patient's body, the patient suffering from chronic pain or inflammation in a primary area in the torso section; placing a wireless device into an opening on the surgical instrument, the wireless device suitable to fit into the opening and configured to receive electromagnetic energy non-inductively from a source located outside the patient's body;

through the opening on the surgical instrument, positioning the wireless electrode lead adjacent to or near excitable tissue in the primary area in the torso section of the patient; and

causing electrical pulses to be delivered to one or more electrodes on the wireless device such that neural modulation is applied to the excitable tissue in the primary area in the torso section.

2. The method of claim 1, wherein placing the surgical instrument comprises positioning a laparoscopic device into an abdominal region of the patient's body.

3. The method of claim 2, wherein placing a wireless device into an opening on the surgical instrument comprises placing the wireless device through a working channel or cannula of the laparoscopic device.

4. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near branches of the splenic nerve of the patient.

5. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near nerves within the spinal cord of the patient.

6. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near branches of the splanchnic nerve of the patient.

7. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near branches of the vagus nerve of the patient.

8. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near the celiac ganglion of the patient.

9. The method of claim 3, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near the phrenic nerve and the renal plexus of the patient.

10. The method of claim 1, wherein placing the surgical instrument comprises placing an endoscopic device into the torso section of the patient's body.

11. The method of claim 10, wherein placing a wireless device into an opening on the surgical instrument comprises placing the wireless device through a working channel or cannula of the endoscopic device.

12. The method of claim 11, wherein positioning the wireless device adjacent to or near excitable tissue comprises

positioning the wireless device in a region in the gastrointestinal tract or the respiratory tract of the patient.

13. The method of claim 1, wherein placing the surgical instrument comprises placing a catheter device into a thoracic region of the patient's body.

14. The method of claim 13, wherein placing a wireless device into an opening on the surgical instrument comprises placing the wireless device through a working channel or cannula of the catheter device.

15. The method of claim 1, wherein positioning the wireless device adjacent to or near excitable tissue comprises positioning the wireless device adjacent to or near nerves on at least one of: stomach, heart, spleen, pancreas, diaphragm, liver, or kidney of the patient.

16. The method of 15, wherein positioning the wireless device adjacent to or near excitable tissue further comprises positioning the device adjacent to or near the pancreas of the patient, and wherein causing neural modulation to be applied to the excitable tissue comprises causing sufficient neural modulation such that inflammation is reduced in the pancreas of the patient.

17. The method of 15 wherein causing sufficient neural modulation further comprises causing sufficient neural modulation to the TRPV1 and/or CGRP-containing neurons such that inflammation is reduced in the pancreas of the patient.

18. The method of claim 1, wherein causing neural modulation to be applied to the excitable tissue further comprises causing neural modulation of the sympathetic nervous system of the patient.

19. The method of claim 18, wherein causing neural modulation of the sympathetic nervous system of the patient comprises causing neural activation of the greater splanchnic nerve of the patient.

20. The method of claim 19, wherein causing neural modulation of the sympathetic nervous system of the patient comprises causing neural inhibition of the greater splanchnic nerve of the patient.

21. The method of claim 1, further comprising using X-Ray fluoroscopy to guide positioning the wireless device adjacent to or near one or more excitable tissue.

22. The method of claim 1, further comprising using ultrasound sonography to guide positioning the wireless electrode lead adjacent to or near one or more excitable tissue.

23. The method of claim 1, wherein placing a wireless device further comprises placing a wireless device that includes one or more non-inductive antennas configured to receive electromagnetic energy radiated from a source located outside of the patient's body, electronic circuitry coupled to each of the one or more non-inductive antennas and configured to extract electric power and excitation pulses from the radiated electromagnetic energy as received by the one or more non-inductive antennas, and one or more electrodes configured to deliver the excitation pulses to the one or more excitable tissue to effectuate the neural modulation thereof.

* * * * *

专利名称(译)	用神经调节治疗炎症，慢性疼痛和其他疾病		
公开(公告)号	US20160015988A1	公开(公告)日	2016-01-21
申请号	US14/775218	申请日	2014-03-14
[标]申请(专利权)人(译)	佩里曼LAURA TYLER 安德烈森CHAD		
申请(专利权)人(译)	佩里曼，LAURA TYLER 安德烈森，乍得		
当前申请(专利权)人(译)	STIMWAVE技术公司		
[标]发明人	PERRYMAN LAURA TYLER ANDRESEN CHAD		
发明人	PERRYMAN, LAURA TYLER ANDRESEN, CHAD		
IPC分类号	A61N1/378 A61B1/313 A61N1/36 A61N1/372 A61B19/00		
CPC分类号	A61N1/3787 A61N1/36071 A61N1/37229 A61B2019/5238 A61B1/3132 A61B2019/5276 A61B19/5244 A61B34/20 A61B2090/376 A61B2090/378 A61N1/37205		
优先权	PCT/US2013/073326 2013-12-05 WO 61/786049 2013-03-14 US		
其他公开文献	US9717921		
外部链接	Espacenet USPTO		

摘要(译)

一些实施方式提供了一种通过神经调节来治疗慢性疼痛或炎症的方法，该方法包括：将外科器械放置到患者身体的躯干部分中，患者在躯干部分的主要区域中患有慢性疼痛或炎症；将无线设备放置在手术器械上的开口中，该无线设备适于装配到开口中并且被配置为从位于患者身体外部的源非感应地接收电磁能量；通过手术器械上的开口，将无线电极引线定位在患者躯干部分的主要区域中的可兴奋组织附近或附近；并且使电脉冲被传递到无线设备上的一个或多个电极，使得神经调制被应用于躯干部分中的主要区域中的可兴奋组织。

Some implementations provide a method of treating chronic pain or inflammation with neural modulation, the method including: placing a surgical instrument to reach into a torso