



US007746309B2

(12) **United States Patent**
Chen et al.

(10) **Patent No.:** **US 7,746,309 B2**
(45) **Date of Patent:** **Jun. 29, 2010**

(54) **DRIVING CIRCUIT HAVING STATIC
DISPLAY UNITS AND LIQUID CRYSTAL
DISPLAY DEVICE USING THE SAME**

(75) Inventors: **Eddy Giing-Lii Chen**, Miao-Li (TW);
Sz-Hsiao Chen, Miao-Li (TW)

(73) Assignee: **Innolux Display Corp.**, Miao-Li County
(TW)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 601 days.

(21) Appl. No.: **11/644,289**

(22) Filed: **Dec. 21, 2006**

(65) **Prior Publication Data**

US 2007/0139332 A1 Jun. 21, 2007

(30) **Foreign Application Priority Data**

Dec. 21, 2005 (CN) 2005 1 0121046

(51) **Int. Cl.**
G09G 3/36 (2006.01)

(52) **U.S. Cl.** **345/90; 345/87; 345/100**

(58) **Field of Classification Search** **345/87-100,**
345/204

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,359,343 A 10/1994 Nakamura
6,967,649 B2 11/2005 Sun
7,095,391 B2 * 8/2006 Lee 345/87

7,148,870 B2 * 12/2006 Tada 345/90
7,443,371 B2 * 10/2008 Fujikawa 345/96
2002/0118153 A1 8/2002 Kimura
2003/0142054 A1 7/2003 Tada
2003/0151582 A1 * 8/2003 Ishii 345/100
2003/0197673 A1 * 10/2003 Nakamura 345/99
2003/0227429 A1 12/2003 Shimoshikiryō
2008/0088552 A1 * 4/2008 Toya 345/84
2008/0238850 A1 * 10/2008 Watanabe 345/90

FOREIGN PATENT DOCUMENTS

CN 1365095 A 8/2002
CN 1437183 A 8/2003
CN 1482593 A 3/2004
TW 578125 B 3/2004

* cited by examiner


Primary Examiner—Nitin Patel

(74) Attorney, Agent, or Firm—Wei Te Chung

(57) **ABSTRACT**

An exemplary liquid crystal display device (1) includes a first substrate (3), a second substrate (2) facing the first substrate, and a liquid crystal layer (4) sandwiched between the first substrate and the second substrate. The first substrate includes a plurality of scan lines (11); a plurality of first and second parallel data lines (12, 22) orthogonal to the scan lines; a plurality of first and second thin film transistors (14, 24), positioned near a crossing of a corresponding scan line and a corresponding first data line, respectively; a plurality of first and second pixel electrodes (15, 25) electrically coupled to the first and second thin film transistors, respectively; a plurality of first and second static display units (19, 29) for providing voltage to the first and second pixel electrodes in a static display mode.

10 Claims, 8 Drawing Sheets






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6
(RELATED ART)




FIG. 7
(RELATED ART)




FIG. 8
(RELATED ART)

DRIVING CIRCUIT HAVING STATIC DISPLAY UNITS AND LIQUID CRYSTAL DISPLAY DEVICE USING THE SAME

FIELD OF THE INVENTION

The present invention relates to liquid crystal display (LCD) devices, and more particularly to a driving circuit having static display units and an LCD device using the same, such that the LCD device is capable of displaying 64 gray scale levels in a static display mode.

BACKGROUND

Nowadays, small LCD devices are more and more commonly used in portable electronic equipment, such as mobile phones, personal digital assistants (PDAs), and the like. Therefore, the issue of reducing power consumption of these kinds of LCD devices is becoming more important.

In order to reduce the power consumption of LCD devices, the LCD industry has developed a kind of technique in which the display status of an LCD device is divided into two modes. One of these is an active display mode, and the other is a static display mode. An example of the static display mode is the image shown on a mobile phone LCD when the mobile phone is in a call waiting status. In the active display mode, the operation of the LCD device is normal full operation. For example, the LCD device may be a thin-film transistor LCD (TFT-LCD) device. In the static display mode, the LCD device uses a static random access memory (SRAM) for supplying power to pixel regions, so as to reduce power consumption.

Referring to FIG. 6, this is a diagram of part of a driving circuit of a conventional active matrix LCD device. The LCD device 100 includes a plurality of parallel scan lines 101, and a plurality of parallel data lines 102 orthogonal to the scan lines 101 so as to define a plurality of single sub pixel units 500. The LCD device 100 also includes a common electrode 107.

Referring to FIG. 7, an enlarged circuit diagram of one of the sub pixel units 500 is shown. The sub pixel unit 500 includes a thin film transistor 104, a pixel electrode 105, and a static display unit 109. The thin film transistor (TFT) 104 is positioned near a crossing of a corresponding scan line 101 and a corresponding data line 102. A gate electrode 1040 of the first TFT 104 is electrically coupled to the corresponding scan line 101, and a source electrode 1041 of the first TFT 104 is electrically coupled to the corresponding data line 102. Further, a drain electrode 1042 of the first TFT 104 is electrically coupled to a corresponding pixel electrode 105. The pixel electrode 105 and the common electrode 107 cooperatively form a capacitor 108.

The static display unit 109 includes an SRAM 1094, a second TFT 1091, and a third TFT 1092. The SRAM 1094 includes four terminals: V_{dd} , V_{ss} , V_{in} , and V_{out} . The terminal V_{dd} is electrically coupled to a high voltage V_H , the terminal V_{ss} is electrically coupled to a low voltage V_L , the terminal V_{in} is electrically coupled to a drain electrode of the second TFT 1091, and the terminal V_{out} is electrically coupled to a source electrode of the third TFT 1092. A source electrode of the second TFT 1091 is electrically coupled to a drain electrode of the third TFT 1092, and these two electrodes cooperate with each other to form an output terminal of the static display unit 109. The output terminal is electrically coupled to the drain electrode 1042 of the first TFT 104. The gate electrodes of the second and third TFTs 1091 and 1092 are each electrically coupled to a time control register (Tcon, not

shown), which is used for controlling the second and third TFTs 1091 and 1092 to turn on or turn off.

The operational process of the SRAM 1094 is as follows. When a high voltage is transmitted into the SRAM 1094 via the terminal V_{in} , the terminal V_{in} and the terminal V_{out} output the voltage of the terminal V_{dd} and the terminal V_{ss} , respectively; and when a low voltage is transmitted into the SRAM 1094 via the terminal V_{in} , the terminal V_{in} and the terminal V_{out} output the voltage of the terminal V_{ss} and the terminal V_{dd} , respectively.

The LCD device 100 includes two display modes: active display mode and static display mode. In the active display mode, the operational process of the LCD device 100 is equal to a normal thin film transistor LCD (TFT-LCD) device. That is, each of the static display units 109 does not work, and gray scale voltage is supplied to the pixel electrodes 105 via the data lines 102 and the first TFTs 104 for displaying images.

Referring to FIG. 8, the operational process of the sub pixel unit 500 when in an on state is shown. Plot (A) represents a waveform diagram of scanning voltage supplied to the scan lines 101. Plot (B) represents a waveform diagram of voltage supplied to the data lines 102. Plot (C) represents a waveform diagram of voltage supplied to the gate electrode of the second TFT 1091. Plot (D) represents a waveform diagram of voltage supplied to the gate electrode of the third TFT 1092. Plot (E) represents a waveform diagram of voltage supplied to the pixel electrode 105. Plot (F) represents a waveform diagram of voltage supplied to the common electrode 107. Plot (G) represent a waveform diagram of a difference between voltages supplied to the pixel electrode 105 and the common electrode 107.

When the time t is equal to t_1 , a scanning voltage is supplied to the gate electrode 1040 of the first TFT 104 via the scan line 101, so as to turn on the first TFT 104. The Tcon turns on the second TFT 1091, while the third TFT 1092 is in an off state. At the same time, the data line 102 provides a high voltage for driving the SRAM 1094 via the first and second TFTs 104 and 1091. When the time t is equal to t_2 , the first TFT 104 is turned off until a next active display mode. At the same time, a high voltage V_H is outputted from the terminal V_{dd} , and is supplied to the pixel electrode 105 via the second TFT 1091. After that, the Tcon alternately turns on and turns off the second and third TFTs 1091 and 1092, and then the SRAM 1094 alternately supplies the voltage of the terminal V_{dd} and the terminal V_{ss} to the pixel electrode 105. When t is equal to t_3 , the second TFT 1091 is turned off, and the third TFT 1092 is turned on. At the same time, a low voltage V_L is outputted from the terminal V_{ss} , and is supplied to the pixel electrode 105 via the third TFT 1092. When the time t is equal to t_4 , the second TFT 1091 is turned on, and the third TFT 1092 is turned off. At the same time, a high voltage V_H is outputted from the terminal V_{dd} , and is supplied to the pixel electrode 105 via the second TFT 1091. The operational process complies with the circulation mentioned above. The common electrode 107 also meet with the circulation. That is, the common electrode 107 is V_H at time t_1 , varying to V_L at time t_3 , and returning to V_H at time t_4 . Therefore, the difference between the pixel electrode 105 and the common electrode 107 is maintained at zero, and the sub pixel unit 500 is in an on state (display white).

The sub pixel unit 500 has an operational process in an off state similar to that in an on state. In detail, a low voltage is provided by the data line 102 at an initial point in time. When the voltage of the data lines 102 is a high voltage V_H , the voltage of the pixel electrode 105 is a low voltage V_L . In addition, when the voltage of the common electrode 107 is a low voltage V_L , the voltage of the pixel electrode 105 is a high

voltage V_H . The difference between the common electrode **107** and the pixel electrode **105** is maintained at $V_H - V_L$, and so the sub pixel unit **500** is in an off state (display black).

While the LCD device **100** in the static display mode, voltage is supplied by the static display unit **109**. However, the static display unit **109** can only supplied two different voltages, and then each sub pixel unit **500** can only display a gray scale of 2 levels. Each pixel of the LCD device **100** includes three sub pixel units **500**, such as red, green and blue sub pixel units **500**. Therefore, each pixel of the LCD device **100** can display a gray scale of 8 levels in a static display mode. However, a gray scale of 8 levels is rather limited, and the LCD device **100** is not considered to be capable of displaying rich and colorful images.

It is desired to provide a driving circuit and an LCD device which can overcome the above-described deficiencies.

SUMMARY

A driving circuit of a liquid crystal display device includes: a plurality of parallel scan lines; a plurality of first parallel data lines orthogonal to the scan lines; a plurality of second parallel data lines orthogonal to the scan lines and parallel to the first data lines; a plurality of first thin film transistors, positioned near a crossing of a corresponding scan line and a corresponding first data line; a plurality of second thin film transistors, positioned near a crossing of a corresponding scan line and a corresponding second data line; a plurality of first pixel electrodes electrically coupled to the first thin film transistors; a plurality of second pixel electrodes electrically coupled to the second thin film transistors; a plurality of first static display unit having an output terminal electrically coupled to the first thin film transistor, and the first static display unit provides voltage to the first pixel electrode in a static display mode; and a plurality of second static display unit having an output terminal electrically coupled to the second thin film transistor, and the second static display unit provides voltage to the second pixel electrode in a static display mode.

A liquid crystal display device includes a first substrate, a second substrate facing the first substrate, and a liquid crystal layer sandwiched between the first substrate and the second substrate. The first substrate includes a plurality of parallel scan lines; a plurality of first parallel data lines orthogonal to the scan lines; a plurality of second parallel data lines orthogonal to the scan lines and parallel to the first data lines; a plurality of first thin film transistors, positioned near a crossing of a corresponding scan line and a corresponding first data line; a plurality of second thin film transistors, positioned near a crossing of a corresponding scan line and a corresponding second data line; a plurality of first pixel electrodes electrically coupled to the first thin film transistors; a plurality of second pixel electrodes electrically coupled to the second thin film transistors; a plurality of first static display unit having an output terminal electrically coupled to the first thin film transistor, and the first static display unit provides voltage to the first pixel electrode in a static display mode; and a plurality of second static display unit having an output terminal electrically coupled to the second thin film transistor, and the second static display unit provides voltage to the second pixel electrode in a static display mode.

Advantages and novel features of the driving circuit and liquid crystal display will become more apparent from the

following detailed description when taken in conjunction with the accompanying drawings, in which:

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic, abbreviated, isometric view of an LCD device according to an exemplary embodiment of the present invention;

FIG. 2 is a diagram of part of a driving circuit of the LCD device of FIG. 1;

FIG. 3 is an enlarged circuit diagram of one of sub pixels of the LCD device of FIG. 2;

FIG. 4 is a detailed circuit diagram of a first static display unit of the sub pixel shown in FIG. 3;

FIG. 5 is an enlarged circuit diagram of a static random access memory of the first static display unit of FIG. 4;

FIG. 6 is a diagram of part of a driving circuit of a conventional active matrix LCD device;

FIG. 7 is an enlarged circuit diagram of one of sub pixel units of the LCD device of FIG. 6; and

FIG. 8 shows waveform diagrams illustrating exemplary operation of the LCD device of FIG. 6.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Reference will now be made to the drawings to describe preferred and exemplary embodiments of the present invention in detail.

Referring to FIG. 1, this is a schematic, abbreviated, isometric view of an LCD device according to an exemplary embodiment of the present invention. The LCD device **1** includes a glass first substrate **2**, a glass second substrate **3** facing the first substrate **2**, and a liquid crystal layer **4** sandwiched between the first substrate **2** and the second substrate **3**. The first substrate **2** includes a common electrode **17** thereon, and the second substrate **3** includes a driving circuit **10** thereon.

Referring to FIG. 2, this is a diagram of part of the driving circuit **10**. The driving circuit **10** includes a plurality of parallel scan lines **11**, and a plurality of parallel first and second data lines **12** and **22** orthogonal to the scan lines **11** respectively, so as to define a plurality of single sub pixels **200**.

Referring to FIG. 3, this is an enlarged circuit diagram of an exemplary one of the sub pixels **200**. The sub pixel **200** includes a first sub pixel unit **201** and a second sub pixel unit **202** disposed at two sides of the scan line **11**, respectively. The first sub pixel unit **201** includes a first thin film transistor (TFT) **14**, a first pixel electrode **15**, a first capacitor **16**, and a first static display unit **19**. The second sub pixel unit **202** includes a second thin film transistor **24**, a second pixel electrode **25**, a second capacitor **26**, and a second static display unit **29**.

The first TFT **14** is positioned near a crossing of the scan line **11** and the data line **12**. A gate electrode **140** of the first TFT **14** is electrically coupled to the scan line **11**, and a source electrode **141** of the first TFT **14** is electrically coupled to the data line **12**. Further, a drain electrode **142** of the first TFT **14** is electrically coupled to the corresponding pixel electrode **15**. The pixel electrode **15** and the common electrode **17** cooperatively form a liquid crystal capacitor **18**. The first capacitor **16** is connected in parallel with the liquid crystal capacitor **18** for maintaining the voltage of the first sub pixel unit **201**. The first static display unit **19** is electrically coupled to the drain electrode **142** of the first TFT **14**.

The second TFT **24** is positioned near a crossing of the scan line **11** and the data line **22**. A gate electrode **240** of the second

TFT 24 is electrically coupled to the scan line 11, and a source electrode 241 of the second TFT 24 is electrically coupled to the data line 22. Further, a drain electrode 242 of the second TFT 24 is electrically coupled to the corresponding pixel electrode 25. The pixel electrode 25 and the common electrode 17 cooperatively form a liquid crystal capacitor 28. The second capacitor 26 is connected in parallel with the liquid crystal capacitor 28 for maintaining the voltage of the second sub pixel unit 202. The second static display unit 29 is electrically coupled to the drain electrode 242 of the second TFT 14.

An area of the first pixel electrode 15 may be different to or be equal to that of the second pixel electrode 25. In the illustrated embodiment, a ratio of the area of the first pixel electrode 15 to the second pixel electrode 25 is 1:2.

The first static display unit 19 is substantially the same as the second static display unit 29. Referring to FIG. 4, this is a detailed circuit diagram of the first static display unit 19. The first static display unit 19 includes an SRAM 194, a third TFT 191, and a fourth TFT 192. The SRAM 194 includes four terminals: V_{dd} , V_{ss} , V_{in} , and V_{out} . The terminal V_{dd} is electrically coupled to a high voltage V_H , the terminal V_{ss} is electrically coupled to a low voltage V_L , the terminal V_{in} is electrically coupled to a drain electrode of the third TFT 191, and the terminal V_{out} is electrically coupled to a source electrode of the fourth TFT 192. A source electrode of the third TFT 191 is electrically coupled to a drain electrode of the fourth TFT 192, and these two electrodes cooperate with each other to form an output terminal of the static display unit 19. The gate electrodes of the third and fourth TFTs 191 and 192 are each electrically coupled to a time control register (Tcon, not shown), which is used for controlling the third and fourth TFTs 191 and 192 to turn on or turn off.

Referring to FIG. 5, this is an enlarged circuit diagram of the SRAM 194. The SRAM 194 includes a fifth TFT 1941, a sixth TFT 1942, a seventh TFT 1943, and an eighth TFT 1944. The fifth and sixth TFTs 1941 and 1942 are positive thin film transistors, and the seventh and eighth TFTs 1943 and 1944 are negative thin film transistors. A gate electrode of the fifth TFT 1941 is electrically coupled to the terminal V_{in} , a source electrode of the fifth TFT 1941 is electrically coupled to the terminal V_{out} , and a drain electrode of the fifth TFT 1941 is electrically coupled to the terminal V_{dd} . A gate electrode of the sixth TFT 1942 is electrically coupled to the terminal V_{out} , a source electrode of the sixth TFT 1942 is electrically coupled to the terminal V_{in} , and a drain electrode of the sixth TFT 1942 is electrically coupled to the terminal V_{dd} . A gate electrode of the seventh TFT 1943 is electrically coupled to the terminal V_{in} , a source electrode of the seventh TFT 1943 is electrically coupled to the terminal V_{ss} , and a drain electrode of the seventh TFT 1943 is electrically coupled to the terminal V_{out} . A gate electrode of the eighth TFT 1944 is electrically coupled to the terminal V_{out} , a source electrode of the eighth TFT 1944 is electrically coupled to the terminal V_{ss} , and a drain electrode of the eighth TFT 1944 is electrically coupled to the terminal V_{in} .

The operation process of the SRAM 194 is that: when a high voltage is transmitted into the SRAM 194 via the terminal V_{in} , the terminal V_{in} and the terminal V_{out} outputs the voltage of the terminal V_{dd} and the terminal V_{ss} , respectively; when a low voltage is transmitted into the SRAM 194 via the terminal V_{in} , the terminal V_{in} and the terminal V_{out} outputs the voltage of the terminal V_{ss} and the terminal V_{dd} , respectively.

The LCD device 1 includes two display modes: active display mode and static display mode. In the active display mode, the operation process of the LCD device 1 is equal to a normal thin film transistor LCD device, that is, each of the

static display units 19 and 29 doesn't work, and gray scale voltage is supplied to the pixel electrodes 15 and 25 via the data lines 12 and 22 as well as the first and second TFTs 14 and 24 respectively, for displaying images.

In the static display mode, the first and second sub pixel units 201 and 202 have an operation process similar to that of the sub pixel unit 500 of the conventional LCD device 100. Wherein, the scan lines 11 drives the first and second TFTs 14 and 24, the first and second data lines 12 and 22 provides voltages to drive the first and second static display units 19 and 29, respectively. After that, the scan line 11 and the data lines 12 and 22 stop work, and the first and second static display units 19 and 29 respectively provides voltage to drive the first and second sub pixels units 201 and 202 to display images until next active display mode.

The first and second sub pixel units 201 and 202 can display a gray scale of 2 levels, respectively, then the sub pixel 200 can display a gray scale of 4 levels. That is, when the first and second sub pixel units 201 and 202 both in an off states, the sub pixel 200 displays a first gray scale; when the first sub pixel unit 201 is in an off state, and the second sub pixel unit 202 is in an on state, the sub pixel 200 displays a second gray scale; when the first sub pixel unit 201 is in an on state, and the second sub pixel unit 202 is in an off state, the sub pixel 200 displays a third gray scale; when the first and second sub pixel units 201 and 202 both in an on states, the sub pixel 200 displays a fourth gray scale.

Compared with the sub pixel unit 500 of the conventional LCD device 100, the sub pixel 200 of the driving circuit 10 can display a gray scale of 4 levels. Each of pixel units of the LCD device 1 includes three sub pixels 200, such as red, green, and blue sub pixels 200. Therefore, each pixel of the LCD device 1 can display a gray scale of 64 levels in a static display mode. Therefore, the LCD device 200 can display rich and colorful images.

It is to be further understood that even though numerous characteristics and advantages of preferred and exemplary embodiments have been set out in the foregoing description, together with details of structures and functions associated with the embodiments, the disclosure is illustrative only, and changes may be made in detail (including in matters of shape, size, and arrangement of parts) within the principles of the invention to the full extent indicated by the broad general meaning of the terms in which the appended claims are expressed.

What is claimed is:

1. A driving circuit of a liquid crystal display device, comprising:

- a plurality of parallel scan lines;
- a plurality of first parallel data lines substantially orthogonal to the scan lines;
- a plurality of second parallel data lines substantially orthogonal to the scan lines and parallel to the first data lines;
- a plurality of first thin film transistors, each positioned near a crossing of a corresponding one of the scan lines and a corresponding one of the first data lines;
- a plurality of second thin film transistors, each positioned near a crossing of a corresponding one of the scan lines and a corresponding one of the second data lines;
- a plurality of first pixel electrodes electrically coupled to the first thin film transistors;
- a plurality of second pixel electrodes electrically coupled to the second thin film transistors;
- a plurality of first static display units each comprising an output terminal electrically coupled to a corresponding one of the first thin film transistors, and each first static

7

display unit configured for providing voltage to a corresponding one of the first pixel electrodes in a static display mode of the liquid crystal display device; and
 a plurality of second static display units each comprising an output terminal electrically coupled to a corresponding one of the second thin film transistors, and each second static display unit configured for providing voltage to a corresponding one of the second pixel electrodes in the static display mode.

2. The driving circuit as claimed in claim 1, wherein an area of the first pixel electrode is equal to that of the second pixel electrode.

3. The driving circuit as claimed in claim 1, wherein an area of the first pixel electrode is different to that of the second pixel electrode.

4. The driving circuit as claimed in claim 1, wherein a ratio of an area of the first pixel electrode to that of the second pixel electrode is 1:2.

5. The driving circuit as claimed in claim 1, wherein each of the first and second static display units comprises a static random access memory, a third thin film transistor, a fourth thin film transistor, a drain electrode of the third thin film transistor is electrically coupled to a terminal of the static random access memory, and a source electrode of the third thin film transistor is electrically coupled to the output terminal of the static display unit, a source electrode of the fourth thin film transistor is electrically coupled to another terminal of the static random access memory, and a drain electrode of the third thin film transistor is electrically coupled to the output terminal of the static display unit.

6. A liquid crystal display device, comprising:

a first substrate comprising:

a plurality of parallel scan lines;

a plurality of first parallel data lines substantially orthogonal to the scan lines;

a plurality of second parallel data lines substantially orthogonal to the scan lines and parallel to the first data lines;

a plurality of first thin film transistors, each positioned near a crossing of a corresponding one of the scan lines and a corresponding one of the first data lines;

a plurality of second thin film transistors, each positioned near a crossing of a corresponding one of the scan lines and a corresponding one of the second data lines;

8

a plurality of first pixel electrodes electrically coupled to the first thin film transistors;

a plurality of second pixel electrodes electrically coupled to the second thin film transistors;

a plurality of first static display units each comprising an output terminal electrically coupled to a corresponding one of the first thin film transistors, and each first static display unit configured for providing voltage to a corresponding one of the first pixel electrodes in a static display mode of the liquid crystal display device; and

a plurality of second static display units each comprising an output terminal electrically coupled to a corresponding one of the second thin film transistors, and each second static display unit configured for providing voltage to a corresponding one of the second pixel electrodes in the static display mode;

a second substrate facing the first substrate; and

a liquid crystal layer sandwiched between the first substrate and the second substrate.

7. The liquid crystal display device as claimed in claim 6, wherein an area of the first pixel electrode is equal to that of the second pixel electrode.

8. The liquid crystal display device as claimed in claim 6, wherein an area of the first pixel electrode is different to that of the second pixel electrode.

9. The liquid crystal display device as claimed in claim 6, wherein a ratio of an area of the first pixel electrode to that of the second pixel electrode is 1:2.

10. The liquid crystal display device as claimed in claim 6, wherein each of the first and second static display units comprises a static random access memory, a third thin film transistor, a fourth thin film transistor, a drain electrode of the third thin film transistor is electrically coupled to a terminal of the static random access memory, a source electrode of the third thin film transistor is electrically coupled to the output terminal of the static display unit, a source electrode of the fourth thin film transistor is electrically coupled to another terminal of the static random access memory, and a drain electrode of the third thin film transistor is electrically coupled to the output terminal of the static display unit.

* * * * *

专利名称(译)	具有静态显示单元的驱动电路和使用该驱动电路的液晶显示装置		
公开(公告)号	US7746309	公开(公告)日	2010-06-29
申请号	US11/644289	申请日	2006-12-21
[标]申请(专利权)人(译)	群创光电股份有限公司		
申请(专利权)人(译)	群创光电股份有限公司.		
当前申请(专利权)人(译)	群创光电		
[标]发明人	CHEN EDDY GIING LII CHEN SZ HSIAO		
发明人	CHEN, EDDY GIING-LII CHEN, SZ-HSIAO		
IPC分类号	G09G3/36		
CPC分类号	G02F1/13624 G09G3/2074 G09G3/3648 G09G2300/0857 G09G2300/0443 G09G3/3614		
审查员(译)	帕特尔NITIN		
优先权	200510121046.X 2005-12-21 CN		
其他公开文献	US20070139332A1		
外部链接	Espacenet USPTO		

摘要(译)

示例性液晶显示装置(1)包括第一基板(3),面对第一基板的第二基板(2),以及夹在第一基板和第二基板之间的液晶层(4)。第一基板包括多条扫描线(11);多条与扫描线正交的第一和第二平行数据线(12,22);多个第一和第二薄膜晶体管(14,24),分别位于相应扫描线和相应第一数据线的交叉点附近;多个第一和第二像素电极(15,25)分别电连接到第一和第二薄膜晶体管;多个第一和第二静态显示单元(19,29),用于以静态显示模式向第一和第二像素电极提供电压。

