



(12) **Patent Application Publication**
Wu et al.

(43) **Pub. Date:** **Oct. 11, 2007**

Jan. 20, 2006 (TW)..... 095102160


Publication Classification

(52) **U.S. Cl.** 349/96; 349/114

(57) **ABSTRACT**

A transreflective liquid crystal display device includes a first and a second substrates, a liquid crystal layer, and a plurality of reflective electrodes and transparent electrodes. The liquid crystal layer is interposed between the first and the second substrates and functions in an OCB mode. The reflective electrode and the transparent electrode in one picture element are spaced apart from each other to produce a transverse electric field when a voltage is applied across the liquid crystal layer.

(22) Filed: **Oct. 6, 2006**






FIG. 1A (Prior Art)




FIG. 1B (Prior Art)




FIG. 1C (Prior Art)




FIG. 2




FIG. 3A




FIG. 3B




FIG. 3C




FIG. 4




FIG. 5A




FIG. 5B




FIG. 6




FIG. 7A




FIG. 7B




FIG. 8A




FIG. 8B




FIG. 8C




FIG. 9

TRANSFLECTIVE LIQUID CRYSTAL DISPLAY DEVICE

BACKGROUND OF THE INVENTION

[0001] (a) Field of the Invention

[0002] The invention relates to a transfective liquid crystal display device and, more particularly, to a transfective liquid crystal display device using an OCB (optically compensated birefringence) technique which realizes a wide view-field angle and high-speed response.

[0003] (b) Description of the Related Art

[0004] Twisted nematic (TN) cells, which at present are widely used in thin film transistor (TFT) liquid crystal display devices, have a small view-field angle and low-speed response. To solve this problem, studies on an OCB (optically compensated birefringence) technique have been made. Specifically, in case of displaying moving images, a response time is required in the order of ten milliseconds or even less, and the OCB technique is possible to obtain a high-speed response characteristic as well as a wide view-field angle. Hence, it is the best mode suitable for accommodating a recent trend of multimedia and motion picture processing that allows a vast amount of image data to be moved on the screen of a display device at high speed.

[0005] FIGS. 1A-1C show schematic diagrams illustrating the transformation of splay-bend alignment of liquid crystal molecules in an OCB cell 102.

[0006] Referring to FIG. 1A, the liquid crystal layer exhibits an initial splay-aligned state when no voltage is applied across it, where the liquid crystal molecules in the region A and region B tilt at a very small angle (compared with the later described angles shown in FIG. 1B and FIG. 1C) to the alignment films 104 and 106. Also, the liquid crystal molecules in the region C turn to nearly parallel to the alignment films 104 and 106.

[0007] Next, as shown in FIG. 1B, when a voltage is applied to the liquid crystal layer exhibiting splay alignment and gradually increased to approach a threshold voltage V_t , the splay alignment of liquid crystal molecules is deformed and transformed to a bend alignment, where the angle between the liquid crystal molecules and the alignment film 104 in the region A and the angle between the liquid crystal molecules and the alignment film 106 in the region B are both increased. Further, the liquid crystal molecules in the region C are almost perpendicular to the alignment films 104 and 106. At this time, the OCB cell is in a white state and has maximum brightness.

[0008] Then, when the voltage is continually increased to exceed a critical voltage V_c , the angle between the liquid crystal molecules and the alignment film 104 in the region A, and the angle between the liquid crystal molecules and the alignment film 106 in the region B are both increased to a maximum, about 80 degrees or more. Further, most of the liquid crystal molecules in the region C are perpendicular to the alignment films 104 and 106. At this time, the aligned direction of the liquid crystal molecules is almost perpendicular to the absorption axis of a polarizer (not shown), so the OCB cell is in a dark state. Thus, the OCB mode works when the applied voltage has a value between the threshold voltage V_t and the critical voltage V_c .

[0009] In the OCB cell, the liquid crystal molecules are well arranged to allow for a reduced friction during rotation, so that a wide view-field angle and high-speed response are realized. However, in order to operate an OCB mode LCD device, the applied voltage should be higher than the threshold voltage V_t . Thus, it may take much time to increase the applied voltage from zero to reach a threshold value once the threshold voltage V_t is high. More specifically, the threshold voltage V_t should be as low as possible to decrease the response time of the OCB mode LCD device and to prevent its thin film transistors from being damaged.

[0010] On the other hand, the OCB technique is typically used in either a transmission type or a reflection type LCD device. Though the transmission type LCD device uses backlight to obtain a bright display independent of surrounding environments, the panel brightness is often not sufficient when the device is exposed to direct sunlight. In comparison, a reflection type LCD device employs surrounding light to effect a display so that a backlight source is omitted; however, the reflection type LCD device is largely deteriorated in visibility in a dark surrounding. Hence, there has been a strong demand for designing an OCB mode LCD device that operates at a low threshold voltage and possesses good visibility in any environment.

BRIEF SUMMARY OF THE INVENTION

[0011] Hence, an object of the invention is to provide an optically compensated birefringence (OCB) mode transfective liquid crystal display device that operates at a low threshold voltage to realize a wide view-field angle and high-speed response and possesses good visibility in any environment.

[0012] According to the invention, a transfective liquid crystal display device includes a first and a second substrates, a liquid crystal layer, and a plurality of reflective electrodes and transparent electrodes. The liquid crystal layer is interposed between the first and the second substrates and functions in an OCB mode. Each reflective electrode is formed on the reflective region, and each transparent electrode is formed on the transmissive region of each picture element of the transfective LCD device. The reflective electrode and the transparent electrode in one picture element are spaced apart from each other to produce a transverse electric field between them when a voltage is applied across the liquid crystal layer.

[0013] Through the design of the invention, since the reflective electrode and the transparent electrode are spaced apart from each other, a transverse electric field applied in different horizontal directions is produced when a voltage difference exists between the two separate electrodes. Hence, in case of having splay alignment of liquid crystal molecules under the initial state of an OCB mode, the liquid crystal molecules will tilt toward different directions following the different horizontal directions of the transverse electric field to result in azimuthal disorder of tilt angle directions. Under the circumstance, it is easy to create a great number of transition nuclei that contribute to transform the splay alignment into the bend alignment due to the azimuthal disorder of tilt angle directions. Thereby, the OCB cell is quickly transformed into a bend-aligned state to effect a display device, and possible domain defects (non-transferred splay-aligned regions) are minimized as a result.

BRIEF DESCRIPTION OF THE DRAWINGS

[0014] FIGS. 1A-1C show schematic diagrams illustrating the transformation of splay-bend alignment of liquid crystal molecules in an OCB cell.

[0015] FIG. 2 shows a sectional schematic view illustrating a transfective LCD device according to an embodiment of the invention.

[0016] FIG. 3A shows a schematic diagram illustrating relative distributions of a reflective electrode and a transparent electrode according to an embodiment of the invention.

[0017] FIG. 3B shows a schematic diagram illustrating relative distributions of a reflective electrode and a transparent electrode according to another embodiment of the invention.

[0018] FIG. 3C shows a schematic diagram illustrating relative distributions of a reflective electrode and a transparent electrode according to another embodiment of the invention.

[0019] FIG. 4 shows a curve diagram illustrating examples of the calculation of Gibbs energy in relation to splay alignment and bend alignment.

[0020] FIG. 5A shows a curve diagram illustrating relationship between the phase difference $\cdot n \times dr$ and the intensity of reflected light in the reflective region of a transfective LCD.

[0021] FIG. 5B shows a curve diagram illustrating relationship between the phase difference $\cdot n \times dr$ and the intensity of transmission light in the transmissive region of a transfective LCD.

[0022] FIG. 6 shows a schematic diagram illustrating an OCB mode transfective LCD having optical phase compensators.

[0023] FIG. 7A shows a depiction of an output V-T curve according to the embodiment shown in FIG. 6.

[0024] FIG. 7B shows a depiction of an output V-R curve according to the embodiment shown in FIG. 6.

[0025] FIG. 8A-8C show schematic diagram illustrating another embodiments of the OCB mode transfective LCD having optical phase compensators.

[0026] FIG. 9 shows a sectional schematic view illustrating another transfective LCD device according to another embodiment of the invention.

DETAILED DESCRIPTION OF THE INVENTION

[0027] FIG. 2 shows a sectional schematic view illustrating a transfective liquid crystal display (LCD) device 10 according to an embodiment of the invention. Though the transfective LCD device 10 includes a plurality of picture elements, FIG. 2 simply illustrates one of them since all the picture elements have identical structures.

[0028] Referring to FIG. 2, a first substrate 12 and a second substrate 22 are placed to face with each other, and a liquid crystal layer 28 functioning in an optically compensated birefringence (OCB) mode is interposed between them. On the first substrate 12 a color filter 14, a common

electrode 16, and a first alignment film 18 are sequentially formed. The common electrode 16 is formed from indium tin oxide (ITO) or indium zinc oxide (IZO) transparent conductive films. On the second substrate 22 a pixel electrode 24 and a second alignment film 26 are formed. Further, a first biaxial film 30 and a first polarizer 32 are positioned in one side of the first substrate 12 opposite to the liquid crystal layer 28, and a second biaxial film 34 and a second polarizer 36 are positioned in one side of the second substrate 22 opposite to the liquid crystal layer 28.

[0029] According to the invention, each pixel electrode 24 provided in a picture element, such as provided corresponding to a red, green, or blue sub-pixel, is divided into two separate parts. As shown in FIG. 2, the isolated first and second parts of the pixel electrode 24 are spaced apart from each other by an interval d . In this embodiment, the first part of the pixel electrode 24 is a reflective electrode 24a made from film materials having high conductivity and reflectivity, such as aluminum, silver, or metal alloy, and the second part is a transparent electrode 24b made from transparent conductive films, such as indium tin oxide (ITO) or indium zinc oxide (IZO) films. Hence, each picture element of the transfective LCD device 10 is provided with a reflective region Re and a transmissive region Tr to make excellent use of both environmental light and backlight.

[0030] FIG. 3A shows a schematic diagram illustrating relative distributions of a reflective electrode and a transparent electrode according to an embodiment of the invention, on which the rubbing direction of polyimide (PI) of a liquid crystal cell (LC cell) is denoted as a reference direction. Referring to FIG. 3A, each pixel electrode 24 is divided into two separate parts, the reflective electrode 24a and the transparent electrode 24b, which are preferably formed in substantially the same plane. In this embodiment, the reflective electrode 24a has a concave portion, and the transparent electrode 24b has a convex portion complementary to the concave portion of the reflective electrode 24a. Hence, when a voltage difference exists between the two separate electrodes 24a and 24b, a traverse electric field EX applied in different horizontal directions (all parallel to the rubbing direction) is produced between the concave and convex structures. Hence, in case of having splay alignment of molecules under the initial state of an OCB mode, when a voltage is applied between the common electrode 16 and the pixel electrode 24, the liquid crystal molecules will tilt toward different horizontal directions following the different directions of the traverse electric field EX to result in azimuthal disorder of tilt angle directions. Under the circumstance, it is easy to create a great number of transition nucleuses that contribute to transform the splay alignment into the bend alignment due to the azimuthal disorder of tilt angle directions. This enables swift and reliable transformation from the splay alignment to the bend alignment.

[0031] FIG. 4 shows a curve diagram illustrating examples of the calculation of Gibbs energy, where a solid line indicates the calculation result in relation to the bend alignment, and dash lines indicates the calculation results in relation to the splay alignment. Referring to FIG. 4, in order to operate an OCB cell, the applied voltage should be higher than the threshold voltage V_t at which value the calculation of Gibbs energy under the bend alignment should equal to that under the splay alignment. According to the invention, since a transverse electric field is additionally provided as a

result of the division of a pixel electrode to cause azimuthal disorder of tilt angle directions, the calculation of Gibbs energy under splay alignment is raised and its depiction is shifted from curve P to curve Q, meaning the former threshold voltage V_t is decreased to a lower one V_t' . Thereby, the OCB cell is quickly transformed into a bend-aligned state to effect a display device, and possible domain defects (non-transferred splay-aligned regions) are minimized as a result.

[0032] Further, the division of a pixel electrode is not limited to a specific manner, as long as a transverse electric field is produced to result in azimuthal disorder of tilt angle directions. As shown in FIG. 3B, in an alternate embodiment the reflective electrode **24a** is provided with multiple convex portions **24a'** and concave portions **24a''**, and the transparent electrode **24b** is also provided with multiple convex portions **24b'** and concave portions **24b''** complementary to opposite concave or convex portions of the reflective electrode **24a**. Also, the configuration of these structures are not limited to a rectangular shape shown in FIG. 3B, but rather other shapes shown in FIG. 3C may also be used, such as an arc shape (concave portion **24a'**), a trapezoid shape (convex portion **24a'**), a triangular shape (convex portion **24b'**), or a shape combined from at least two of them.

[0033] Moreover, the respective areas of the reflective electrode **24a** and the transparent electrode **24b** can be arbitrary selected according to any design factor such as environmental brightness.

[0034] Referring back to FIG. 2 again, the separate reflective electrode **24a** and transparent electrode **24b** are electrically connected to a first and a second thin film transistors T1 and T2, respectively, to individually control the electric fields on the reflective region and the transmissive region.

[0035] Unavoidably, light propagates through a transmissive region achieves a phase difference different to another phase difference achieved by the light propagating through a reflective region. For instance, when a twist angle is made to be 0 degrees, and further when γ represents a wavelength of light, n the birefringence of liquid crystal, d_r the gap formed by the liquid crystal layer **28** in the reflective region, and d_t the gap formed by the liquid crystal layer **28** in the transmissive region, the intensity of reflected light in the reflective region becomes maximum when the product $n \times d_r$ (phase difference) equals $\lambda/4$. Relationship between the product $n \times d_r$ and the intensity of reflected light is shown in FIG. 5A. In comparison, the intensity of transmission light in the transmissive region becomes maximum when the product $n \times d_t$ equals $\lambda/2$. Relationship between the product $n \times d_t$ and the intensity of transmission light is shown in FIG. 5B. Hence, according to this embodiment, the reflective region and the transmissive region are respectively corrected by reflectance and transmittance gamma curves by means of the two transistors T1 and T2 to allow for a single cell-gap transfective LCD device.

[0036] Also, as shown in FIG. 2, in this embodiment, the two transistors T1 and T2 are both positioned underneath the reflective electrode **24a** to improve the aperture ratio of a transfective LCD device.

[0037] FIG. 6 shows a schematic diagram illustrating an OCB mode transfective LCD device **40** having optical phase compensators. Referring to FIG. 6, a first A-plate **44a** and a

first C-plate **46a** are provided between top of an OCB cell **42** and a polarizer **32**, and a second A-plate **44b** and a second C-plate **46b** are provided between the bottom of the OCB cell **42** and a polarizer **36**. In this embodiment, the OCB cell **42** achieves a phase difference of 1000 nm, and the A-plate and the C-plate both introduce a phase difference of 1000 nm in X-Y plane and a phase difference of 200 nm in Z-direction. The contrast ratio obtained by this embodiment is up to 16, and the output V-T (voltage-transmittance) curve and V-R (voltage-reflectance) curve of this embodiment are respectively depicted in FIGS. 7A and 7B. From FIGS. 7A and 7B, it is seen the threshold voltage V_t , at which value the splay-aligned liquid crystal molecules are transformed into bend-aligned liquid crystal molecules, is considerably decreased.

[0038] Further, the optical phase compensators used in an OCB mode transfective LCD are not limited to biaxial compensation films shown in FIG. 2, or the two sets of A-plates and C-plates shown in FIG. 6. In an alternate embodiment, only one set of A-plate and C-plate is used, as shown in FIG. 8A. Alternatively, a single A-plate and a combination of A-plate and C-plate are respectively provided on two sides of the OCB cell **42**, as shown in FIG. 8B.

[0039] Moreover, as shown in FIG. 8C, a first and a second quarter wavelength plates are provided between the polarizers and the OCB cell **42**, so that a linear polarized OCB cell is transformed into a circular polarized OCB cell to improve the light transmittance of an OCB mode transfective LCD device.

[0040] Besides, though the reflective electrode **24a** shown in FIG. 2 is a single-layer structure made from a reflective film having high conductivity, the formation of the reflective electrode **24a** is not limited to such manner. For instance, as shown in FIG. 9, the reflective electrode **24a** may be formed as a double-layer structure consisting of a transparent conductive film **37** and a reflective film **38** overlaying the transparent conductive film **37**.

[0041] While the invention has been described by way of examples and in terms of the preferred embodiments, it is to be understood that the invention is not limited to the disclosed embodiments. To the contrary, it is intended to cover various modifications and similar arrangements as would be apparent to those skilled in the art. Therefore, the scope of the appended claims should be accorded the broadest interpretation so as to encompass all such modifications and similar arrangements.

What is claimed is:

1. A transfective liquid crystal display device, comprising:

- a first substrate provided with a common electrode;
- a second substrate on which a plurality of pixel electrodes are formed, wherein each pixel electrode is positioned corresponding to a picture element of the transfective liquid crystal display device and divided into a reflective part and a transmissive part that are apart from each other; and
- a liquid crystal layer interposed between the first and the second substrates and functioning in an optically compensated birefringence (OCB) mode.

2. The transfective liquid crystal display device as claimed in claim 1, further comprising:

a plurality of first and second thin film transistors formed on the second substrate, each first thin film transistor being electrically connected to the reflective part, and each second thin film transistor being electrically connected to the transmissive part.

3. The transfective liquid crystal display device as claimed in claim 1, wherein the reflective part is a single-layer structure made from a reflective film.

4. The transfective liquid crystal display device as claimed in claim 1, wherein the reflective part is a double-layer structure made from a transparent conductive film and a reflective film overlaying the transparent conductive film.

5. The transfective liquid crystal display device as claimed in claim 1, wherein the reflective part and the transmissive part of each pixel electrode are formed at substantially the same plane.

6. The transfective liquid crystal display device as claimed in claim 1, wherein the reflective part has at least one convex portion and the transmissive part has at least one concave portion complementary to the convex portion.

7. The transfective liquid crystal display device as claimed in claim 1, wherein the reflective part has at least one concave portion and the transmissive part has at least one convex portion complementary to the concave portion.

8. The transfective liquid crystal display device as claimed in claim 1, further comprising:

a first polarizer positioned on one side of the first substrate opposite to the liquid crystal layer;

a second polarizer positioned on one side of the second substrate opposite to the liquid crystal layer;

a first optical phase compensator provided between the first polarizer and the first substrate; and

a second optical phase compensator provided between the second polarizer and the second substrate.

9. The transfective liquid crystal display device as claimed in claim 8, wherein the optical phase compensator comprises at least one biaxial film.

10. The transfective liquid crystal display device as claimed in claim 8, further comprising:

a first quarter wavelength plate provided between the first polarizer and the first substrate, and

a second quarter wavelength plate provided between the second polarizer and the second substrate.

11. A transfective liquid crystal display device having a plurality of picture elements, with each picture element having both a reflective region and a transmissive region, the display device comprising:

a first substrate provided with a common electrode;

a second substrate positioned facing the first substrate;

a liquid crystal layer interposed between the first and the second substrates and functioning in an optically compensated birefringence (OCB) mode;

a plurality of reflective electrodes, each of which is formed on the reflective region; and

a plurality of transparent electrodes, each of which is formed on the transmissive region;

wherein the reflective electrode and the transparent electrode in one picture element are spaced apart from each other to produce a transverse electric field between them when a voltage is applied across the liquid crystal layer.

12. The transfective liquid crystal display device as claimed in claim 11, further comprising:

a plurality of first and second thin film transistors formed on the second substrate to individually control electric fields on the reflective region and the transmissive region.

13. The transfective liquid crystal display device as claimed in claim 12, wherein each first thin film transistor is electrically connected to the reflective electrode, and each second thin film transistor is electrically connected to the transparent electrode.

14. The transfective liquid crystal display device as claimed in claim 12, wherein the first and second thin film transistors are positioned underneath the reflective electrode.

15. The transfective liquid crystal display device as claimed in claim 11, wherein the reflective electrode and the transparent electrode are formed at substantially the same plane.

16. The transfective liquid crystal display device as claimed in claim 11, wherein the reflective electrode is a single-layer structure made from a reflective film.

17. The transfective liquid crystal display device as claimed in claim 11, wherein the reflective electrode is a double-layer structure made from a transparent conductive film and a reflective film overlaying the transparent conductive film.

18. The transfective liquid crystal display device as claimed in claim 11, wherein the reflective electrode has at least one convex portion and the transmissive electrode has at least one concave portion complementary to the convex portion.

19. The transfective liquid crystal display device as claimed in claim 11, wherein the reflective electrode has at least one concave portion and the transmissive electrode has at least one convex portion complementary to the concave portion.

20. The transfective liquid crystal display device as claimed in claim 11, further comprising:

a first polarizer positioned on one side of the first substrate opposite to the liquid crystal layer;

a second polarizer positioned on one side of the second substrate opposite to the liquid crystal layer;

a first optical phase compensator provided between the first polarizer and the first substrate; and

a second optical phase compensator provided between the second polarizer and the second substrate.

21. The transfective liquid crystal display device as claimed in claim 20, further comprising:

a first quarter wavelength plate provided between the first polarizer and the first substrate, and

a second quarter wavelength plate provided between the second polarizer and the second substrate.

* * * * *

专利名称(译)	透反液晶显示装置		
公开(公告)号	US20070236629A1	公开(公告)日	2007-10-11
申请号	US11/543837	申请日	2006-10-06
[标]申请(专利权)人(译)	胜华科技股份有限公司		
申请(专利权)人(译)	胜华科技股份有限公司		
当前申请(专利权)人(译)	胜华科技股份有限公司		
[标]发明人	WU YI CHUN LIAO WEN JUI LIU CHIN CHANG LEE CHIAN CHANG		
发明人	WU, YI-CHUN LIAO, WEN-JUI LIU, CHIN-CHANG LEE, CHIAN-CHANG		
IPC分类号	G02F1/1335		
CPC分类号	G02F1/133555 G02F1/1395 G02F1/133707		
优先权	095102160 2006-01-20 TW		
其他公开文献	US7728929		
外部链接	Espacenet USPTO		

摘要(译)

一种半透半反液晶显示装置，包括第一和第二基板，液晶层，以及多个反射电极和透明电极。液晶层介于第一和第二基板之间，并以OCB模式工作。当在液晶层上施加电压时，一个像素中的反射电极和透明电极彼此间隔开以产生横向电场。

