



US006888585B2

(12) **United States Patent**  
**Kim**

(10) **Patent No.:** **US 6,888,585 B2**  
(45) **Date of Patent:** **May 3, 2005**

(54) **CONTROL SIGNAL UNIT FOR A LIQUID CRYSTAL DISPLAY**

(75) Inventor: **Dong-Gyu Kim, Suwon (KR)**  
(73) Assignee: **Samsung Electronics Co., Ltd., Suwon (KR)**  
(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 186 days.

(21) Appl. No.: **09/964,639**

(22) Filed: **Sep. 28, 2001**

(65) **Prior Publication Data**

US 2002/0051110 A1 May 2, 2002

(30) **Foreign Application Priority Data**

Oct. 31, 2000 (KR) ..... 2000-64396

(51) **Int. Cl.<sup>7</sup>** ..... **G02F 1/136; G02F 1/1345; H01L 29/04**

(52) **U.S. Cl.** ..... **349/43; 349/149; 349/152; 257/59; 257/72**

(58) **Field of Search** ..... **349/43, 149, 152; 257/59, 72**

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

5,148,301	A *	9/1992	Sawatsubashi et al. ....	349/153
5,208,690	A *	5/1993	Hayashi et al. ....	349/143
5,739,880	A *	4/1998	Suzuki et al. ....	349/110
5,909,035	A *	6/1999	Kim .....	257/59
5,914,758	A *	6/1999	Kishida et al. ....	349/51
6,097,457	A *	8/2000	Kim et al. ....	349/110
6,104,465	A *	8/2000	Na et al. ....	349/152
6,172,721	B1 *	1/2001	Murade et al. ....	349/43
6,580,486	B1 *	6/2003	Sekine .....	349/139
2001/0026345	A1 *	10/2001	Park et al. ....	349/149
2002/0093616	A1 *	7/2002	Park et al. ....	349/149

\* cited by examiner

*Primary Examiner*—Tarifur R. Chowdhury

(74) *Attorney, Agent, or Firm*—McGuireWoods LLP

(57) **ABSTRACT**

A control signal unit includes a substrate, a signal line formed on the substrate, and an insulating layer covering the signal line. A contact hole exposes the signal line with a predetermined width. The contact hole has a lateral side bordering on the signal line. The lateral side of the contact hole is longer than the width of the contact hole. A subsidiary signal pad is connected to the signal line through the contact hole.

**14 Claims, 55 Drawing Sheets**




FIG. 1




FIG. 2




FIG. 3




FIG. 4A




FIG. 4B




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9






FIG. 10A




FIG. 10B




FIG. 10C




FIG. 10D




FIG. 11A




FIG. 11B




FIG. 11C




FIG. 11D






FIG. 12A




FIG. 12B




FIG. 12C




FIG. 12D




FIG. 13A




FIG. 13B




FIG. 13C




FIG. 13D






FIG. 14A




FIG. 14B




FIG. 14C




FIG. 14D




FIG. 15





FIG. 16






FIG. 17




FIG. 18

FIG. 19






FIG. 20A




FIG. 20B




FIG. 20C




FIG. 20D




FIG. 20E




FIG. 21A




FIG. 21B




FIG. 21C




FIG. 21D





FIG. 21E










FIG. 22C








FIG. 23C








FIG.24C







FIG. 25C






FIG.26A




FIG. 26B




FIG. 26C




FIG. 26D




FIG. 26E




FIG. 27A




FIG.27B




FIG. 27C




FIG. 27D





FIG. 27E





## CONTROL SIGNAL UNIT FOR A LIQUID CRYSTAL DISPLAY

### BACKGROUND OF THE INVENTION

#### (a) Field of the Invention

The present invention relates to a control signal unit for a liquid crystal display and a method for fabricating the same and, more particularly, to a control signal unit for a liquid crystal display operating in a stable manner without line opening.

#### (b) Description of the Related Art

Generally, a liquid crystal display (LCD) has two glass substrates with electrodes, and a liquid crystal sandwiched between the substrates. When voltage is applied to the electrodes, the liquid crystal molecules are rearranged, thereby controlling light transmission.

One of the substrates has color filters, and the other substrate has thin film transistors (TFTs). The former substrate is usually called the "color filter substrate," and the latter substrate called the "TFT array substrate."

The display area is positioned at the center of the TFT array substrate. In the display area, a plurality of gate lines are formed in the horizontal direction, and a plurality of data lines cross over the gate lines to form pixel regions in a matrix type. The TFT is formed at each pixel region together with a pixel electrode such that it is electrically connected to the gate line and the data line. The TFT controls the data signals from the data line in accordance with the gate signals from the gate line, and sends the controlled signals to the pixel electrode.

A plurality of gate pads and data pads are formed externally to the display area such that they are connected, on the one hand, to the gate lines and the data lines, and on the other, directly to external driving ICs. The gate pad and the data pad receive the gate signal and the data signal respectively from the driving ICs, and send them to the gate line and the data line.

A gate printed circuit board, and a data printed circuit board are connected to the TFT array substrate to transmit the gate signal and the data signal thereto. Data signal transmission films interconnect the TFT array substrate and the data printed circuit board while mounting with data driving ICs for converting electrical signals into data signals and outputting the data signals to the data lines. Furthermore, gate signal transmission films interconnect the TFT array substrate and the gate printed circuit board while mounting with gate driving ICs for converting electrical signals into gate signals and outputting the gate signals to the gate lines.

Alternatively, without a gate printed circuit board, the data printed circuit board may output the gate control signals to the gate driving ICs of the gate signal transmission films via the TFT array substrate, thereby controlling the gate driving signals.

The gate control signals include various kinds of control signals such as gate on voltages (Von) and gate off voltages (Voff), and common voltages Vcom.

The control signal lines carrying such gate control signals are formed with a low resistance conductive material capable of rapidly carrying the signals. Aluminum is commonly used for that purpose, but bears unstable physical and chemical properties. Therefore, the control signal lines have a double or triple-layered structure with an aluminum-based layer and other layers based on metallic materials bearing relatively high resistance.

In case indium tin oxide (ITO) is used to form pixel electrodes and pads, since the aluminum-based material bears poor contact characteristic with respect to the ITO, the aluminum-based layer should be removed at the contact area.

The control signal lines may be processed in the following way. A metallic layer and an aluminum-based layer are sequentially deposited onto a substrate, and etched through photolithography to form a double-layered signal line. An insulating layer is then deposited onto the substrate such that it covers the double-layered signal lines. Contact holes are formed at the insulating layer, and the aluminum-based layer of the signal lines exposed through the contact holes are removed through etching. Subsidiary pads are formed on the exposed portions of the metallic layer. In the processing step where the exposed portion of the aluminum-based layer is completely removed, the non-exposed portion of the aluminum-based layer under the insulating layer is partially etched inside of the insulating layer while forming undercut regions.

Meanwhile, when strong static electricity is generated at the device, the static electricity is accumulated at the gate off voltage line and the common voltage line bearing relatively high capacity. In the process of discharging the static electricity, surge current accruing to the discharge of the static electricity is flown along the gate off voltage line and the common voltage line, and this generates Joule heat.

Particularly, the voltage drop is intensified at the undercut regions because an aluminum-based layer or other conductive layers capable of receiving the static electricity is absent at those regions. Accordingly, the voltage drop is focused at the undercut regions, and large amount of Joule heat is generated there. The Joule heat may melt the metallic layer and result in line opening.

### SUMMARY OF THE INVENTION

It is an object of the present invention to provide a liquid crystal display with a control signal unit which can prevent line opening due to the discharge of static electricity.

This and other objects may be achieved by a liquid crystal display having a control signal unit with the following features.

According to one aspect of the present invention, the control signal unit includes a substrate, a signal line formed on the substrate, and an insulating layer covering the signal line. A contact hole exposes the signal line with a predetermined width. The contact hole has a lateral side bordering on the signal line. The lateral side of the contact hole has a length greater than the width of the contact hole. A subsidiary signal pad is connected to the signal line through the contact hole. The lateral side of the contact hole has an inclined portion proceeding in the direction of the width. The contact hole has a protruded portion proceeding in the longitudinal direction of the signal line. At least one side of the protruded portion is overlapped with the signal line.

The signal line has a double-layered structure with an under-layer and an over-layer, and the contact hole is formed at the insulating layer, and the over-layer of the signal line. The over-layer of the signal line is formed with an aluminum-based metallic material.

According to another aspect of the present invention, the control signal unit includes a substrate, a plurality of signal lines formed on the substrate, an insulating layer covering the signal lines. Contact holes exposes the respective signal lines each with a predetermined width. The contact hole has a lateral side bordering on the signal line. The lateral side of

the contact hole has a length greater than the width of the contact hole. Subsidiary signal pads are connected to the respective signal lines through the respective contact holes.

The control signal unit further includes a signal transmission film with signal leads. The signal leads are connected to the signal lines in one to one correspondence. The signal leads of the signal transmission film include a first signal lead carrying high voltage signals and a second signal lead carrying low voltage signals, and a dummy lead is formed between the first and the second signal leads. The same voltage is applied to the dummy lead and the first signal lead. The dummy lead has a thickness of several to several tens micrometers.

A dummy line corresponding to the dummy lead is formed at the substrate. The dummy line is formed of a conductive material that is less oxidative than the signal line.

According to still another aspect of the present invention, the liquid crystal display with the control signal unit includes a substrate, and a gate line assembly and a plurality of signal lines formed on the substrate. The gate line assembly has gate electrodes and gate lines. A gate insulating layer covers the gate line assembly and the signal lines. Thin film transistor semiconductor patterns are formed on the gate insulating layer. A data line assembly has data lines crossing over the gate lines while being insulated from the gate lines, source electrodes extended from the data lines while contacting the semiconductor patterns, and drain electrodes contacting the semiconductor patterns in correspondence with the source electrodes. A protective layer covers the data line assembly and the semiconductor patterns. First contact holes expose the drain electrodes, and second contact holes expose the respective signal lines with a predetermined width. The second contact hole has a lateral side bordering on the signal line. The lateral side of the second contact hole has a length greater than the width of the second contact hole. Pixel electrodes and subsidiary signal pads are standing in the same plane. The pixel electrodes are connected to the drain electrodes, and the subsidiary signal pads are connected to the signal lines.

The gate line assembly and the signal lines have a double-layered structure with an aluminum-based layer. The second contact holes are formed at the gate insulating layer, the protective layer, and the aluminum-based layer of the signal lines. The liquid crystal display further includes a signal transmission film with signal leads. The signal leads are connected to the signal lines in one to one correspondence. The signal leads of the signal transmission film include a first signal lead carrying high voltage signals and a second signal lead carrying low voltage signals, and a dummy lead is formed between the first and the second signal leads. The same voltage is applied to the dummy lead and the first signal lead. The dummy lead is several to several tens micrometers thick. A dummy line corresponding to the dummy lead is formed at the substrate. The dummy line is formed with a conductive material that is less oxidative than the signal line. A gate pad is connected to each gate line as a component of the gate line assembly, and a data pad is connected to each data line as a component of the data line assembly. A third contact hole exposes the gate pad with a predetermined width, and a fourth contact hole exposes the data pad with a predetermined width. A subsidiary gate pad covers the gate pad at the first contact hole, and a subsidiary data pad covers the data pad at the fourth contact hole. Each of the third and the fourth contact holes has a lateral side bordering on the pad. The lateral side of the contact hole has a length greater than the width of the contact hole.

The liquid crystal display further includes common voltage pads formed at the substrate. The common voltage pads

are covered by one insulating layer among the gate insulating layer and the protective layer. Contact holes are formed at the insulating layer with a predetermined width while exposing the common voltage pads. Each contact hole has a lateral side bordering on the pad. The lateral side of the contact hole has a length greater than the width of the contact hole. Subsidiary common voltage pads are connected to the common voltage pads through the contact holes.

The liquid crystal display further includes a color filter substrate with a common electrode. The common electrode is connected to the subsidiary common voltage pads.

In a method for fabricating such a liquid crystal display, a gate line assembly and signal lines are formed on a substrate. The gate line assembly has gate electrodes and gate lines. A gate insulating layer is formed while covering the gate line assembly and the signal lines. Semiconductor patterns are formed on the gate insulating layer. A data line assembly comprises data lines crossing over the gate lines, source electrodes contacting the one-sided semiconductor patterns, and drain electrodes contacting the other-sided semiconductor patterns in correspondence with the source electrodes. A protective layer is formed while covering the data line assembly and the semiconductor patterns. First and second contact holes are formed with a predetermined width such that the first contact holes expose the drain electrodes, and the second contact holes expose the signal lines. Pixel electrodes and subsidiary signal pads are formed such that the pixel electrodes are connected to the drain electrodes through the first contact holes, and the subsidiary signal pads are connected to the signal lines through the second contact holes.

Each second contact hole has a lateral side bordering on the signal line. The lateral side of the contact hole has a length greater than the width of the contact hole. The signal lines have a double-lined structure with an aluminum-based layer. The second contact holes are formed through dry-etching the gate insulating layer and the protective layer covering the signal lines while exposing the aluminum-based layer, and wet-etching the exposed portions of the aluminum-based layer using an aluminum etching solution.

The gate line assembly further has gate pads connected to the gate lines, and the data line assembly further has data pads connected to the data lines. Third and fourth contact holes are formed with a predetermined width at the step of forming the first and the second contact holes such that the third contact holes expose the gate pads, and the fourth contact holes expose the data pads. Subsidiary gate pads and subsidiary data pads at the step of forming the drain electrodes and the subsidiary signal pads such that the subsidiary gate pads cover the gate pads, and the subsidiary data pads cover the data pads.

Each of the third and the fourth contact holes has a lateral side bordering on the pad. The lateral side of the contact hole has a length greater than the width of the contact hole.

The semiconductor patterns and the data line assembly are formed together using photoresist patterns having different thickness. The photoresist patterns include a first photoresist pattern placed over the data line assembly with a first thickness, and a second photoresist pattern placed over the channel portion between the source electrode and the drain electrode with a second thickness. The second thickness is smaller than the first thickness.

The formation of the semiconductor patterns and the data line assembly is made in the following way. A semiconductor layer and a conductive layer are deposited onto the gate

insulating layer, and the photoresist patterns are formed on the conductive layer. The conductive layer is etched using the photoresist patterns as a mask such that the semiconductor layer is partially exposed to the outside. The exposed portions of the semiconductor layer and the second photoresist pattern are removed to thereby complete the semiconductor patterns while exposing the portions of the conductive layer placed between the source electrode and the drain electrode. The exposed portions of the conductive layer is removed to thereby complete the data line assembly, and the first photoresist pattern is removed. The photoresist patterns are made using a mask with first to third regions. The first region of the mask has a light transmission higher than the second region but lower than the third region.

#### BRIEF DESCRIPTION OF THE DRAWINGS

A more complete appreciation of the invention, and many of the attendant advantages thereof, will be readily apparent as the same becomes better understood by reference to the following detailed description when considered in conjunction with the accompanying drawings in which like reference symbols indicate the same or the similar components, wherein:

FIG. 1 is a plan view of a control signal unit according to a first preferred embodiment of the present invention;

FIG. 2 is a cross sectional view of the control signal unit taken along the II-II' line of FIG. 1;

FIG. 3 is a cross sectional view of the control signal unit taken along the III-III' line of FIG. 1;

FIG. 4A illustrates a variation of the control signal unit shown in FIG. 1;

FIG. 4B illustrates another variation of the control signal unit shown in FIG. 1;

FIG. 5 is a schematic view of a liquid crystal display with a control signal unit according to a second preferred embodiment of the present invention;

FIG. 6 is a plan view of the liquid crystal display shown in FIG. 5 at a pixel region;

FIG. 7 is a plan view of the control signal unit shown in FIG. 5;

FIG. 8 is a cross sectional view of the liquid crystal display taken along the VIII-VIII' line of FIG. 6;

FIG. 9 is a cross sectional view of the liquid crystal display taken along the IX-IX' line of FIG. 7;

FIGS. 10A, 10B, 10C, 10D, 11A, 11B, 11C, 11D, 12A, 12B, 12C, 12D, 13A, 13B, 13C, 13D, 14A, 14B, 14C and 14D illustrate the steps of fabricating the liquid crystal display shown in FIG. 5;

FIG. 15 is a plan view of a liquid crystal display at a pixel region according to a third preferred embodiment of the present invention;

FIG. 16 is a plan view of a control signal unit for the liquid crystal display shown in FIG. 15;

FIG. 17 is a cross sectional view of the liquid crystal display taken along the XVII-XVII' line of FIG. 15;

FIG. 18 is a cross sectional view of the liquid crystal display taken along the XVIII-XVIII' line of FIG. 15;

FIG. 19 is a cross sectional view of the control unit taken along the XIX-XIX' line of FIG. 16; and

FIGS. 20A, 20B, 20C, 20D, 20E, 21A, 21B, 21C, 21D, 21E, 22A, 22B, 22C, 23A, 23B, 23C, 24A, 24B, 24C, 25A, 25B, 25C, 26A, 26B, 26C, 26D, 26E, 27A, 27B, 27C, 27D and 27E illustrate the steps of fabricating the liquid crystal display shown in FIG. 15.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of this invention will be explained with reference to the accompanying drawings.

FIG. 1 is a plan view of a control signal unit according to a first preferred embodiment of the present invention, and FIGS. 2 and 3 are cross sectional views of the control signal unit taken along the II-II' line and the III-III' line of FIG. 1, respectively.

A control signal line 220 for the control signal unit is formed on a substrate 10, and bears a double-layered structure with a chrome-based layer 201 and an aluminum-based layer 202. The chrome-based layer 201 is 500–1500Å thick, and the aluminum-based layer 202 is 2500–3500Å thick.

A first insulating layer 30 and a second insulating layer 70 are sequentially formed on the substrate 10 while covering the control signal line 220. A contact hole 270 is formed at the first and second insulating layers 30 and 70, and at the aluminum-based layer 202 of the control signal line 220 while exposing the chrome-based layer 201.

The contact hole 270 is roughly outlined along the shape of the control signal line 220 such that the length L of the lateral side of the contact hole 270 bordering on the control signal line 220 becomes to be greater than the width W of the contact hole 270. For instance, as shown in FIG. 1, one lateral side of the contact hole 270 is partially inclined in the direction of width such that the boundary between the contact hole 270 and the control signal line 220 is elongated.

In order to elongate the boundary between the contact hole 270 and the control signal line 220, the contact hole 270 may have a protruded portion. As shown in FIG. 1, the protruded portion of the contact hole 270 is positioned at the bottom of the control signal line 220. It is preferable that at least one side of the protruded portion is overlapped with the control signal line 220.

Alternatively, as shown in FIGS. 4A and 4B, the protruded portion of the contact hole 270 may be positioned at the top of the control signal line 220, or at the center thereof.

The contact hole 270 exposing the control signal line 220 is formed through dry-etching the first and second insulating layers 30 and 70 while exposing the underlying aluminum-based layer 202, and wet-etching the exposed portion of the aluminum-based layer 202. In the wet-etching process, the non-exposed portion of the aluminum-based layer 202 under the insulating layers 30 and 70 is also etched inside of the insulating layers 30 and 70 to thereby form undercut regions 200. Thereafter, a control signal subsidiary pad 280 is formed on the second insulating layer 70 such that it covers the chrome-based layer 201 exposed through the contact hole 270. The control signal subsidiary pad 280 may be formed with a transparent conductive material such as indium tin oxide (ITO) and indium zinc oxide (IZO).

The control signal line 220 is attached to a signal lead of a signal transmission film for signal communication.

Meanwhile, when strong static electricity is generated at the device, the static electricity is accumulated at the gate off voltage line and the common voltage line bearing relatively high capacity. In the process of discharging the static electricity, surge current accruing to the discharge of the static electricity is flown along the gate off voltage line and the common voltage line. This generates Joule heat.

Particularly, the portions of the chrome-based layer 201 placed at the undercut regions 200 significantly suffer voltage drop because the aluminum-based layer 202 capable of receiving the static electricity is absent at those portions. In

this case, large amount of Joule heat accruing to the voltage drop is generated there. However, in this preferred embodiment, the sufficiently elongated boundary between the chrome-based layer **201** and the control signal line **220** can significantly reduce the volume of voltage drop. Hence, the amount of Joule heat is also decreased, thereby preventing opening of the control signal line **220**.

The amount of Joule heat can be obtained by the following formula:

$$\text{Joule heat} \propto R$$

where  $R=D/L$ ,  $D$  indicates the vertical distance for the movement of the electric potential, that is, the width of the chrome-based layer at the undercut region, and  $L$  indicates the horizontal distance for the movement of the electric potential, that is, the boundary between the chrome-based layer and the aluminum-based layer at the undercut region, i.e., the lateral side of the contact hole bordering on the control signal line.

In the inventive control signal unit, since the boundary between the chrome-based layer and the aluminum-based layer at the undercut region **200** is elongated, the resistance of the metallic layer that becomes to be an obstacle to the movement of surge current is reduced, decreasing the amount of Joule heat.

For example, in case the width of the control signal line is  $23\mu\text{m}$ , and the lateral side of the contact hole **270** is elongated to be  $230\mu\text{m}$  while being inclined in the direction of width of the control signal line **220**, the amount of Joule heat per unit length occurred at the chrome-based layer **201** can be reduced at minimum by  $1/10$  compared to the case where the lateral side of the contact hole is formed in the same way as in the direction of width of the control signal line.

Alternatively, the contact hole **270** may be formed to be smaller than the control signal line **220** such that it is placed within the area of the control signal line **220**. Furthermore, the contact hole **270** may bear various shapes provided that the lateral side of the contact hole **270** bordering on the control signal line **220** is longer than the width of the contact hole **270**.

FIG. 5 is a schematic view of a liquid crystal display with a control signal unit according to a second preferred embodiment of the present invention.

As shown in FIG. 5, a plurality of gate lines **22** are formed on a substrate **10** in the horizontal direction. And a plurality of data lines **62** cross over the gate lines **22** while forming pixel regions  $P$  in a matrix type. The display area  $D$  is defined by the sum of the pixel regions  $P$ . The data lines **62** proceed in the vertical direction while being insulated from the gate lines **22**.

A thin film transistor (TFT) is formed at each pixel region  $P$  such that it is connected to the gate line **22** and the data line **62**. A pixel electrode (PE) is also formed at the pixel region  $P$  such that it is connected to the TFT. A black matrix **11** is formed at the outside of the display area (at the deviant lined area in the drawing) to prevent leakage of light.

A printed circuit board **100** is formed at the top of the substrate **10** to output gate signals and data signals. The substrate **10** is electrically connected to the printed circuit board **100** via data signal transmission films **300**.

A data driving IC **350** is mounted at each data signal transmission film **300** to output picture signals. Furthermore, a plurality of data signal leads **310** are formed at the data signal transmission film **300** to relay the picture signals from the data driving IC **350** to the data lines **62**. The data signal leads **310** and the data lines **62** are connected to each other at contact portions **C2**.

A plurality of gate signal transmission films **400** are mounted at the left side of the substrate **10** while being electrically connected thereto. A gate driving IC **450** is mounted at each gate signal transmission film **400** to output gate signals. A plurality of gate signal leads **410** are formed at the gate signal transmission film **400** to relay the gate signals from the gate driving IC **450** to the gate lines **22**. The gate signal leads **410** and the gate lines **22** are connected to each other at contact portions **C1**.

Gate signal control lines **220** are formed at the outside of the display area  $D$  while being connected to gate control signal leads **320** of the data signal transmission film **300** at contact portions **C3** and to gate control signal leads **420** at contact portions **C4**. As in the first preferred embodiment, the signal lines **220** are formed on the substrate **10**, and an insulating layer covers the control signal lines **220**. Contact holes **270** are formed at the insulating layer while exposing the control signal lines **220** such that the length  $L$  of the lateral side of the contact hole **270** bordering on the control signal line **220** is longer than the width  $W$  of the contact hole **270**. Subsidiary pads are connected to the control signal lines **220** through the contact holes **270**.

Such a line structure may be applied also to a common voltage signal unit of the TFT array substrate for transmitting common voltage signals to a common electrode of the color filter substrate. In this case, common voltage pads are formed on the substrate **10**, and an insulating layer covers the pads. Contact holes are formed at the insulating layer while exposing the common voltage pads such that the lateral side of each contact hole bordering on the pad has a length longer than the width of the contact hole. Subsidiary pads are connected to the common voltage pads through the contact holes. In the combination of the substrates, the common electrode of the color filter substrate contacts the common voltage pads of the TFT array substrate.

In the above-structured liquid crystal display, the gate control signals output from the printed circuit board **100** are transmitted to the gate control signal lines **220** via the gate control signal leads **320** of the data signal transmission film **300**, and input into the gate driving IC **450** via the gate control signal leads **420** of the gate signal transmission film **400**.

Upon receipt of the gate control signals, the gate driving IC **450** outputs gate signals to the gate lines **21** through the gate signal lead **410**.

In addition to the data signal transmission film **300**, a separate signal transmission film may be provided to interconnect the printed circuit board **100** and the substrate **10**.

FIG. 6 illustrates the liquid crystal display at a pixel region. FIG. 7 illustrates the control signal unit for the liquid crystal display. FIG. 8 is a cross sectional view of the liquid crystal display taken along the VIII-VIII' line of FIG. 6. FIG. 9 is a cross sectional view of the liquid crystal display taken along the IX-IX' line of FIG. 7. As the structure of the control signal unit at the contact portions **C4** is the same as that at the contact portions **C3**, explanation for the latter structure will be omitted.

A gate line assembly and gate control signal lines **223**, **224** and **225** are formed on an insulating substrate **10** with a double-layered structure where an under-layer **201**, and an over-layer **202** are present. The under-layer **201** is formed of a metallic material based on chrome or molybdenum while bearing a thickness of  $500\text{--}1000\text{\AA}$ . The over-layer **202** is formed of a low resistance metallic material based on aluminum while bearing a thickness of  $1500\text{--}2500\text{\AA}$ . Alternatively, the gate line assembly and the gate control signal lines **223**, **224** and **225** may be formed with a single or triple or more layered structure.

The gate line assembly includes gate lines **22** proceeding in the horizontal direction, gate electrodes **26** connected to the gate lines **22**, and gate pads **26** connected to the one-sided ends of the gate lines **22** to receive gate signals from the gate signal lead **410** of the gate signal transmission film **400** and send them to the gate lines **22**.

The gate control signal leads **223**, **224** and **225** proceeds perpendicular to the gate lines **22** at the top of the substrate **10** while proceeding parallel to the gate lines **22** at the left side of the substrate **10**. The gate control signal leads **223**, **224** and **225** shown in FIG. 7 are positioned at the top of the substrate **10** while being connected to the data signal transmission film **300** at the contact portions C3.

A gate insulating layer **30** covers the gate line assembly and the gate control signal lines **223**, **224** and **225**. The gate insulating layer **30** is formed of an insulating material such as silicon nitride.

A semiconductor pattern **42** is formed on the gate insulating layer **30** over each gate electrode **26** of amorphous silicon. Ohmic contact patterns **55** and **56** are formed on the semiconductor pattern **42** of impurities-doped amorphous silicon.

A data line assembly is formed on the ohmic contact patterns **55** and **56**, and the gate insulating layer **30** with a double-layered structure where an under-layer **601**, and an over-layer **602** are present. The under-layer **601** is formed of a metallic material based on molybdenum or chrome, and the over-layer **602** of a metallic material based on aluminum.

The data line assembly includes data lines **62** proceeding in the vertical direction, source electrodes **65** connected to the data lines **62**, drain electrodes **66** separated from the source electrodes **65**, and data pads **64** connected to the data lines **62** to relay picture signals from the data signal leads **310** of the data signal transmission film **300** to the data lines **62**.

The data line assembly may be formed with a single, triple or more layered structure as in the gate line assembly.

The TFT comprises the gate electrode **26**, the semiconductor pattern **42**, the source electrode **65**, and the drain electrode **66**.

A protective layer **70** is formed on the data line assembly, the semiconductor patterns **42** and the gate insulating layer **30** of silicon nitride, or organic insulating material.

In the area of pixel regions, contact holes **72** are formed at the protective layer **70** and the aluminum-based over-layer **602** of the drain electrodes **66** while exposing the under-layer **601** of the drain electrodes **66**. In the area of contact portions C1, contact holes **74** are formed at the protective layer **70**, the gate insulating layer **30** and the aluminum-based over-layer **202** of the gate pads **24** while exposing the under-layer **201** of the gate pads **24**. In the area of contact portions C2, contact holes **76** are formed at the protective layer **70** and the aluminum-based over-layer **602** of the data pads **64** while exposing the under-layer **601** of the data pads **64**. Furthermore, in the area of contact portions C4, contact holes **273** to **275** are formed at the protective layer **70**, the gate insulating layer **30** and the aluminum-based over-layer **202** of the gate control signal lines **223**, **224** and **225** while exposing the under-layer **201** of the gate control signal lines **223**, **224** and **225**.

The contact holes **273** to **275** exposing the gate control signal lines **223** to **225** are roughly outlined along the shape of the gate control signal lines **223** such that the lateral side of each contact hole bordering on the gate control signal line is longer than the width thereof. Furthermore, the contact holes **74** and **76** exposing the gate and data pads **24** and **64** are also outlined along the shape of the gate and data pads

**24** and **64** such that the lateral side of each contact hole bordering on the pad has a length longer than the width thereof. Each of the contact holes **74**, **76**, **273**, **274** and **275** has a lateral side bordering on the under-layers **201** and **601** that is partially inclined in the direction of width of the under-layers **201** and **601**.

Like the above, when the boundary between the contact holes and the control signal lines is elongated, the boundary between the over-layers **202** and **602** and the under-layers **201** and **601** at the contact holes is also elongated. Consequently, when static electricity is discharged from the over-layers **202** and **602** to the under-layers **201** and **601**, voltage drop can be reduced and the amount of Joule heat is decreased, thereby preventing opening of the control signal lines.

It is preferable that the contact hole **72** exposing the drain electrode **66** has a width at the protective layer **70** longer than that at the under-layer **601**. In this case, since the upper portion of the contact hole **72** is wider than the lower portion, a pixel electrode **82** can contact the under-layer **601** of the drain electrode **66** through the contact hole **72** in a stable manner. Since the contact hole **76** exposing the data pad **64** is formed together with the contact hole **72** exposing the drain electrode **66**, the contact holes **72** and **76** have the same sectional structure.

Pixel electrodes **82**, subsidiary gate pads **84**, subsidiary data pads **86**, and subsidiary gate control signal pads **283**, **284** and **285** are formed on the protective layer **70** with a transparent conductive material such as ITO.

The pixel electrode **82** is connected to the drain electrode **66** through the contact hole **72** to receive the picture signals. The subsidiary gate and data pads **84** and **86** are connected to the gate and data pads **24** and **64** through the contact holes **74** and **76** to reinforce adhesion between the pads **24** and **64** and the leads **310** and **410** of the data and gate signal transmission films **300** and **400**.

The subsidiary gate control signal pads **283**, **284** and **285** are connected to the gate control signal lines **223**, **224** and **225** through the contact holes **273**, **274** and **275**. Likewise, the subsidiary gate control signal pads **283**, **284** and **285** reinforce adhesion between the gate control signal lines **223**, **224** and **225** and the gate control signal leads **323**, **324** and **325**.

Meanwhile, the data and gate signal transmission films **300** and **400** are attached to the TFT array substrate **10** using an anisotropic conductive film **250** with conductive particles **251** and adhesives **252**.

The gate signal leads **410** of the gate signal transmission film **400** are electrically connected to the subsidiary gate pads **84** via the conductive particles **251** of the anisotropic conductive film **250** at the contact portions C1. Furthermore, the data signal leads **310** of the data signal transmission film **300** are electrically connected to the subsidiary data pads **86** via the conductive particles **251** of the anisotropic conductive film **250** at the contact portions C2. The data signal transmission film **300** is also provided with gate control signal leads **323**, **324** and **325**. The gate control signal leads **323**, **324** and **325** are electrically connected to the gate control signal lines **223**, **224** and **225** via the conductive particles **251** of the anisotropic conductive film **250** at the contact portions C3.

For instance, the gate control signal lead **323** carries gate on voltage Von of about 20V, the gate control signal lead **324** carries gate off voltage Voff of 0V or less, and the gate control signal lead **325** carries common voltage Vcom of about 7V. The gate control signal leads **323**, **324** and **325** are electrically connected to the gate control signal lines **223**, **224** and **225** to transmit gate control signals thereto.

The gate on voltage  $V_{on}$ , the gate off voltage  $V_{off}$ , and the common voltage  $V_{com}$  are transmitted to the signal lines **223**, **224** and **225** via the signal leads **323**, **324** and **325**. In this case potential difference is made between the signal line **223** carrying the gate on voltage and the signal line **224** carrying the gate off voltage. Furthermore, potential difference is also made between the signal line **224** carrying the gate off voltage and the signal line **225** carrying the common voltage. Likewise, potential difference is made between other signal lines not illustrated in the drawing.

Such a potential difference induces the phenomenon where negative ion particles in the moisture content intruded into the control signal unit during the operation electrochemically react with the signal lines **223**, **224** and **225**, and melt them.

In this connection, a thick dummy lead is formed between the high voltage signal line **223** carrying the gate on voltage and the low voltage signal line **224** carrying the gate off voltage. That is, a dummy lead of several to several tens micrometers is formed on the signal transmission film while being positioned between the high and low voltage signal lines **223** and **224** of several hundreds to several thousands angstroms.

When the data transmission film **300** and the substrate **10** are thermally compressed, and attached to each other via the anisotropic conductive film **500**, the adhesives **252** of the anisotropic conductive film **250** is compressed against the thick dummy lead while becoming so compact in structure as to obstruct the flowing of the negative ion particles. Therefore, the dummy lead functions as a barrier intercepting the flowing of the negative ions.

In this case, even though the moisture content is introduced into the control signal unit, the thick dummy lead prevents the negative ion particles of the moisture content from intruding into the high voltage signal line **223**.

When the voltage equivalent to the gate on voltage to be applied to the high voltage signal line **223** is applied to the dummy lead, equi-potential is formed between the high voltage signal line **223** and the dummy lead. In this case, even though negative ion particles intrude into the high voltage signal line **223**, equi-potential is formed around the high voltage signal line **223** so that the negative ion particles float about the high voltage signal line **223**.

Accordingly, the high voltage signal line does not react with the negative ion particles so that it does not suffer damage due to the negative ion particles.

When a dummy line electrically connected to the dummy lead of the data signal transmission film **300** is formed between the high voltage signal line **223** and the low voltage signal line **224**, large and stable equi-potential can be formed around the high voltage signal line **223**.

The signal line of the control signal unit may be formed with a common metallic material such as the conductive material for the gate or data line assembly. Furthermore, the signal line of the control signal unit may be formed of a less oxidative conductive material based on copper, silver, chrome, molybdenum, chrome nitride, or molybdenum nitride. Such a conductive material little influences electrolysis. Furthermore, in case the dummy line is formed with an oxidized conductive material such as ITO and IZO, reaction due to the negative ion particles can be reduced.

Meanwhile, the leads **310**, **410**, **323**, **324** and **325** of the data and gate signal transmission films **300** and **400** wholly cover the contact holes **74**, **76**, **273**, **274** and **275** in the longitudinal direction while covering only one side of the contact holes **74**, **76**, **273**, **274** and **275** in the direction of width.

In this structure, the anisotropic conductive film **500**, or the leads **310**, **410**, **323**, **324** and **325** of the data and gate signal transmission films **300** and **400** cover the substrate pads or the contact holes **74**, **76**, **273**, **274** and **275** over the lines **84**, **86**, **283**, **284** and **285** in order to prevent possible erosion at the contact portions **C1**, **C2**, **C3** and **C4**. This can reinforce adhesion at those portions, obtaining good contact characteristics.

A method for fabricating the liquid crystal display will be now explained with reference to FIGS. **10A** to **14D**.

As shown in FIGS. **10A** to **10D**, a metallic under-layer **201** is deposited onto a substrate **10**, and an aluminum-based over-layer **202** is deposited onto the under-layer **201**. The over-layer **202** and the under-layer **201** are etched to thereby form a gate line assembly and gate control signal lines **223**, **224** and **225** that have a double-layered structure. The gate line assembly includes gate lines **22**, gate pads **24**, and gate electrodes **26**.

Thereafter, as shown in FIGS. **11A** to **11D**, a gate insulating layer **30**, a semiconductor layer, and an impurities-doped semiconductor layer are sequentially deposited onto the substrate **10**. The impurities-doped semiconductor layer and the semiconductor layer are etched through photolithography to thereby form island-shaped semiconductor patterns **42** and island-shaped ohmic contact patterns **52**.

As shown in FIGS. **12A** to **12D**, a metallic under-layer **601** is deposited onto the substrate **10**, and an aluminum-based over-layer **602** is deposited onto the metallic under-layer **601**. The over-layer **602** and the under-layer **601** are etched through photolithography to thereby form a data line assembly. The data line assembly includes data lines **62**, data pads **64**, source electrodes **65**, and drain electrodes **66**.

The island-shaped ohmic contact patterns **52** are etched through the source electrodes **65** and the drain electrodes **66**, and separated into first ohmic contact patterns **55** contacting the source electrodes **65** and second ohmic contact patterns **56** contacting the drain electrodes **66**.

As shown in FIGS. **13A** to **13D**, an insulating material such as silicon nitride and organic insulating material is deposited onto the data line assembly to thereby form a protective layer **70**.

The protective layer **70** and the gate insulating layer **30** are dry-etched through photolithography to thereby expose the aluminum-based over-layer **202** and **602** of the drain electrodes **66**, the gate pads **24**, the data pads **74**, and the gate control signal lines **223**, **224** and **225**. The exposed portions of the aluminum-based over-layer **202** and **602** are removed using an aluminum etching solution.

In this way, the contact holes **74**, **273**, **274** and **275** exposing the chrome-based under-layers **201** and **601** of the gate pads **24** and the gate control signal lines **223**, **224** and **225** are completed.

Thereafter, the protective layer **70** over the drain electrodes **66** and the data pads **64** is side-etched such that the aluminum-based layer **602** thereof is exposed to the outside while making the contact holes **72** and **76** to be stepped. In this structure, a pixel electrode **82** contacts the drain electrode **66** through the contact hole **72** in a stable manner. At this time, the contact hole **72** has a top opening width larger than the bottom opening width.

The contact holes **273**, **274** and **275** exposing the signal lines **223**, **224** and **225** are longitudinally formed along the shape of the signal lines **223**, **224** and **225** such that the lateral side of each contact hole bordering on the gate control signal line has a length longer than the width thereof.

Thereafter, as shown in FIGS. **14A** to **14D**, a transparent conductive material such as ITO is deposited onto the

substrate **10**, and etched through photolithography to thereby form pixel electrodes **82** connected to the drain electrodes **66**, subsidiary gate pads **84** connected to the gate pads **24**, subsidiary data pads **86** connected to the data pads **64**, and subsidiary gate control signal pads **283**, **284** and **285** 5 connected to the gate control signal lines **223**, **224** and **225**. The pixel electrodes **82**, and the subsidiary pads **84**, **86**, **283** and **284** directly contact the chrome-based under-layer **201** and **601**.

After the TFT array substrate is completed, as shown in FIGS. **6** to **9**, data signal transmission films **300** and gate signal transmission films **400** are attached to the TFT array substrate using an anisotropic conductive film **500**.

At this time, the subsidiary gate pads **84**, the subsidiary data pads **86**, and the gate control signal lines **223**, **224** and **225** are electrically connected to the gate and data signal leads **410** and **310** of the gate and data signal transmission films **400** and **300**, and the gate control signal leads **323**, **324** and **325** in one to one correspondence.

FIG. **15** illustrates a liquid crystal display at a pixel region according to a third preferred embodiment of the present invention, and FIG. **16** illustrates a control signal unit for the liquid crystal display.

FIG. **17** is a cross sectional view of the liquid crystal display taken along the XVII–XVII' line of FIG. **15**, FIG. **18** is a cross sectional view of the liquid crystal display taken along the XVIII–XVIII' line of FIG. **15**, and FIG. **19** is a cross sectional view of the control unit taken along the XIX–XIX' line of FIG. **16**. As the structure of the control signal unit at the contact portions **C4** is the same as that at the contact portions **C3**, explanation for the latter structure will be omitted.

A metallic under-layer **201** is deposited onto an insulating substrate **10** with a conductive material based on chrome or molybdenum while bearing a thickness of 500–1000Å, and a metallic over-layer **202** is deposited onto the under-layer **201** with a low resistance material based on aluminum while bearing a thickness of 1500–2500Å. In this way, a double-layered gate line assembly, and double-layered gate control signal lines **223**, **224** and **225** are formed on the substrate **10**. Alternatively, the gate line assembly and the gate control signal lines may be formed with a single or triple or more layered structure.

The gate line assembly includes gate lines **22**, gate pads **24**, gate electrodes **26**, and storage capacitor electrodes **28** proceeding parallel to the gate lines **22** to receive common voltages from the outside.

The storage capacitor electrodes **28** are overlapped with storage capacitor conductive patterns **68** connected to pixel electrodes **82** to form storage capacitors for enhancing the storage capacity of each pixel. In case the overlapping of the pixel electrodes **82** and the gate lines **22** gives sufficient storage capacity, the storage capacitor electrodes **28** may be omitted.

The gate control signal lines **223**, **224** and **225** proceed perpendicular to the gate lines **22** at the top of the substrate **10** while being extended parallel to the gate lines at the left side of the substrate **10**.

A silicon nitride-based gate insulating layer **30** is formed at the substrate **10** with a thickness of 2500–4000Å while covering the gate line assembly, and the gate control signal lines **223**, **224** and **225**.

Semiconductor patterns **42** and **48** are formed on the gate insulating layer **30** with amorphous silicon while bearing a thickness of 800–1500Å. Ohmic contact patterns **55**, **56** and **58** are formed on the semiconductor patterns **42** and **48** with impurities-doped amorphous silicon while bearing a thickness of 500–800Å.

The semiconductor patterns are divided into the TFT semiconductor patterns **42** and the storage capacitor semiconductor patterns **48**, and have the same shape as the data line assembly and the ohmic contact patterns **55**, **56** and **58** except the TFT channel portions between the source electrodes **65** and the drain electrodes **66**. That is, the storage capacitor semiconductor patterns **48** have the same shape as the storage capacitor conductive patterns **68** and the storage capacitor ohmic contact patterns **58**. The TFT semiconductor patterns **42** has the same shape as the data line assembly except that they further include the TFT channel portions between the source and the drain electrodes **65** and **66**.

A data line assembly is formed on the ohmic contact patterns **55**, **56** and **58**. The data line assembly has a double-layered structure where a metallic under-layer **601** and a metallic over-layer **602** are present. The under-layer **601** is formed with a conductive material based on chrome or molybdenum while bearing a thickness of 500–1000Å, and the over-layer **602** is formed with a low resistance material based on aluminum while bearing a thickness of 1500–2500Å. As with the gate line assembly, the data line assembly may have a single or triple or more layered structure.

The data line assembly includes data lines **62** proceeding in the horizontal direction, data pads **64**, source and drain electrodes **65** and **66**, and storage capacitor conductive patterns **68** placed over the storage capacitor electrodes **28**.

The ohmic contact patterns **55**, **56** and **58** lower the contact resistance between the underlying semiconductor patterns **42** and **48** and the overlying data line assembly while bearing the same shape as the data line assembly. One of the ohmic contact patterns **55** contacts the data line **62**, the data pad **64** and the source electrode **65** being in a body, another ohmic contact pattern **56** contacts the drain electrode **66**, and still another ohmic contact pattern **58** contacts the storage capacitor conductive pattern **68**.

A protective layer **70** is formed at the substrate **10** while covering the data line assembly.

In the pixel regions, contact holes **72** and **78** are formed at the protective layer **70**, and the aluminum-based layer **602** of the drain electrodes **66** and the storage capacitor conductive patterns **68** while exposing the under-layer **601** of the drain electrodes **66** and the storage capacitor conductive patterns **68**. In the contact portions **C1**, contact holes **74** are formed at the protective layer **70**, and the aluminum-based layer **202** of the gate insulating layer **30** and the gate pads **24** while exposing the under-layer **201** of the gate pads **24**. In the contact portions **C2**, contact holes **76** are formed at the protective layer **70** and the aluminum-based layer **602** of the data pads **64** while exposing the under-layer **601** of the data pads **64**. In the contact portions **C4**, contact holes **273**, **274** and **275** are formed at the protective layer **70**, the gate insulating layer **30** and the aluminum-based layer **202** of the gate control signal lines **223**, **224** and **225** while exposing the under-layer **201** of the gate control signal lines **223**, **224** and **225**, respectively.

The contact holes **273**, **274** and **275** exposing the gate control signal lines **223**, **224** and **225** are outlined along the shape of the signal lines **223**, **224** and **225** such that the lateral side of each contact hole bordering on the gate control signal line has a length greater than the width thereof. Furthermore, the contact holes **74** and **76** exposing the gate pads **24** and the data pads **64** are also outlined along the shape of the gate pads **24** and the data pads **64** such that the lateral side of each contact hole bordering on the pad has a length longer than the width thereof. Each of the contact holes **74**, **76**, **273**, **274** and **275** has a lateral side bordering

on the under-layers **201** and **601** that is partially inclined in the direction of width of the under-layers **201** and **601**.

Since the boundary between the contact holes and the relevant lines **24**, **64**, **223**, **224** and **225** is elongated, the boundary between the aluminum-based over-layers **202** and **602** and the under-layers **201** and **601** is extended in a longitudinal direction. Therefore, the voltage drop occurred when the static electricity is discharged from the over-layers **202** and **602** to the under-layers **201** and **601** can be reduced, and accordingly, decreasing the amount of Joule heat, which in turn prevents opening of the lines.

The contact holes **74** and **76** exposing the gate and the data pads **24** and **64** are formed along the shape of the gate and data pads **24** and **64** such that the lateral side of each contact hole bordering on the pad has a length longer than the width thereof. Each of the contact holes **74** and **76** has a lateral side bordering on the under-layers **201** and **601** that is partially inclined in the direction of width of the under-layers **201** and **601**.

It is preferable that the contact holes **72** and **78** exposing the drain electrodes **66** and the storage capacitor conductive patterns **68** have a width at the protective layer **70** longer than that at the under-layer **601**. Since the top opening width of the contact holes **72** and **78** is longer than the bottom opening width thereof, pixel electrodes **82** can contact the under-layer **601** of the drain electrodes **66** and the storage capacitor conductive patterns **68** through the contact holes **72** and **78** in a stable manner. The contact hole **76** exposing the data pad **64**, and the contact holes **72** and **78** exposing the drain electrode **66** and the storage capacitor conductive pattern **68** are formed at the same time in the same shape.

Pixel electrodes **82**, subsidiary gate pads **84**, subsidiary data pads **86**, and subsidiary gate control signal pads **283**, **284** and **285** are formed on the protective layer **70** with a transparent conductive material such as ITO.

The pixel electrodes **82** are connected to the drain electrodes **66** and the storage capacitor conductive patterns **68** through the contact holes **72** and **78** to receive picture signals. The subsidiary gate and data pads **84** and **86** are connected to the gate and data pads **24** and **64** through the contact holes **74** and **76** to reinforce adhesion between the pads **24** and **64** and the leads **310** and **410** of the data and gate signal transmission films **300** and **400**.

The subsidiary gate control signal pads **283**, **284** and **285** are connected to the gate control signal lines **223**, **224** and **225** through the contact holes **273**, **274** and **275** to reinforce adhesion between the gate control signal lines **223**, **224** and **225** and the gate control signal leads **323**, **324** and **325** of the data signal transmission film **300**.

Meanwhile, gate signal transmission films **400** and data signal transmission films **300** are attached to the above-structured TFT array substrate via an anisotropic conductive film **500** with conductive particles **501** and adhesives **502**.

The gate signal leads **410** of the gate signal transmission films **400** are electrically connected to the subsidiary gate pads **84** at the contact portions C1 via the conductive particles **251** of the anisotropic conductive film **250**. Furthermore, the data signal leads **310** of the data signal transmission films **300** are electrically connected to the subsidiary data pads **86** at the contact portions C2 via the conductive particles **251** of the anisotropic conductive film **250**.

The gate control signal leads **323**, **324** and **325** are formed at the data signal transmission film **300**, and electrically connected to the gate control signal lines **223**, **224** and **225** at the contact portions C3 via the conductive particles **251** of the anisotropic conductive film **250**. The gate control signal

leads may be divided into a signal lead **323** carrying gate on voltage  $V_{on}$  of about 20V, a signal lead **324** carrying gate off voltage  $V_{off}$  of 0V or less, and a signal lead **325** carrying common voltage  $V_{com}$  of about 7V. The gate control signal leads **323**, **324** and **325** electrically contact the gate control signal lines **223**, **224** and **225** to transmit gate control signals thereto.

A method for fabricating the liquid crystal display will be now explained with reference to FIGS. **20A** to **27E**.

First, as shown in FIGS. **20A** to **20E**, a metallic under-layer **201** is deposited onto an insulating substrate **10** with a conductive material based on chrome or molybdenum, and a metallic over-layer **202** is deposited onto the under-layer **201** with a low resistance material based on aluminum.

The two metallic layers **201** and **202** are etched through photolithography to thereby form a double-layered gate line assembly and double-layered gate control signal lines **223**, **224** and **225**. The gate line assembly includes gate lines **22**, gate pads **24**, gate electrodes **26**, and storage capacitor electrodes **28**.

Thereafter, as shown in FIGS. **21A** to **21E**, a gate insulating layer **30** is formed on the substrate **10**, and semiconductor patterns **42** and **48**, ohmic contact patterns **55**, **56** and **58**, and a double-layered data line assembly are formed on the gate insulating layer **30**. The double-lined data line assembly is formed with a metallic under-layer **601** and an aluminum-based over-layer **602**.

The data line assembly includes data lines **62**, data pads **64**, source electrodes **65**, drain electrodes **66**, and storage capacitor electrodes **68**.

The semiconductor patterns are divided into TFT semiconductor patterns **42** and storage capacitor semiconductor patterns **48**. The TFT semiconductor patterns **42** have the same shape as the data lines **62**, the data pads **64** and the source and drain electrodes **65** and **66** except that they further include TFT channel portions between the source and the drain electrodes **65** and **66**.

The data line assembly, the ohmic contact patterns **55**, **56** and **58**, and the semiconductor patterns **42** and **48** may be formed using only one mask. This photolithography process will be now explained with reference to FIGS. **22A** to **25C**.

First, as shown in FIGS. **22A** to **22C**, a gate insulating layer **30**, a semiconductor layer **40**, and an impurities-doped semiconductor layer **50** are deposited onto the substrate **10** with the gate line assembly through chemical vapor deposition. A metallic under-layer **601**, and a metallic over-layer **602** are sequentially deposited onto the impurities-doped semiconductor layer **50**, and a photoresist film is coated onto the over-layer **602**.

Thereafter, the photoresist film is exposed to light, and developed to thereby form first and second photoresist patterns **112** and **114**. The first photoresist pattern **112** is positioned at the data line assembly portion A, and the second photoresist pattern **114** is positioned at the TFT channel portion C between the source and the drain electrodes **65** and **66**. The first photoresist pattern **112** is thicker than the second photoresist pattern **112**. The remaining portion B has no photoresist film. The thickness ratio of the second photoresist pattern **114** to the first photoresist pattern **112** should be adjusted depending upon the subsequent etching conditions. It is preferable that the thickness of the second photoresist pattern **114** is one half or less of the thickness of the first photoresist pattern **112**.

Such photoresist patterns of different thickness are made using a mask with different light transmission. In order to control light transmission, the mask is provided with slit or lattice patterns, or a semi-transparent film. It is preferable



that the slit width is smaller than the decomposition capacity of the light exposure. When using a semi-transparent film, thin films of different light transmission or of different thickness may be used to control the light transmission.

When the photoresist film is exposed to light through such a mask, the high molecules of the photoresist film directly exposed to light are completely decomposed, the high molecules of the photoresist film exposed to light through the slit-pattern or the semi-transparent film are slightly decomposed, and the high molecules of the photoresist film exposed to light through the opaque film are barely decomposed. At this time, the light exposing time should be controlled in an appropriate manner such that all of the molecules are not completely decomposed.

When the selectively exposed photoresist film is developed, the non-decomposed molecular portion with a large thickness and the slightly-decomposed molecular portion with a small thickness are left out.

Thereafter, as shown in FIGS. 23A to 23C, the over-layer 602 and the underlayer 601 at the B portion is removed using the photoresist patterns 112 and 114 as a mask while exposing the underlying impurities-doped semiconductor layer 50.

Consequently, the conductive patterns 67 and 68 at the channel portion C and the data line assembly portion A are left out, and the conductive layer at the remaining portion B is removed while exposing the impurities-doped semiconductor layer 50. One of the conductive patterns 68 is a storage capacitor conductive pattern, and the other pattern 67 is a metallic double-layered structure for the data line assembly where the source and the drain electrodes 65 and 66 are not yet separated.

Thereafter, as shown in FIGS. 24A to 24C, the impurities-doped semiconductor layer 50 exposed at the B portion and the underlying semiconductor layer 40 is removed together with the second photoresist pattern 114 through dry etching. The dry etching should be made in condition that the photoresist patterns 112 and 114, the impurities-doped semiconductor layer 50 and the semiconductor layer 40 are etched at the same time while not etching the gate insulating layer 30. Particularly, it is preferable that the photoresist patterns 112 and 114 and the semiconductor layer 40 bear the same etching ratio. For example, a mixture of SF<sub>6</sub> and HCl, or a mixture of SF<sub>6</sub> and O<sub>2</sub> can be used to etch the two layers by the same thickness.

In case the etching ratios with respect to the photoresist patterns 112 and 114 and the semiconductor layer 40 are the same, the thickness of the second photoresist pattern 114 should be the same as the sum in thickness of the semiconductor layer 40 and the impurities-doped semiconductor layer 50, or smaller than the sum.

Consequently, the second photoresist pattern 114 at the channel portion C is removed while exposing the conductive pattern 67, and the impurities-doped semiconductor layer 50 and the semiconductor layer 40 are removed while exposing the gate insulating layer 30. Meanwhile, the first photoresist pattern at the data line assembly portion A is also etched and the thickness becomes decreased.

In this step, the TFT semiconductor patterns 42 and the storage capacitor semiconductor patterns 48 are completed.

Ohmic contact patterns 57 are formed on the TFT semiconductor patterns 42 in the same shape, and ohmic contact patterns 58 are formed on the storage capacitor semiconductor patterns 48 in the same shape.

The photoresist residue on the conductive pattern 67 at the channel portion C is then removed through ashing.

Thereafter, as shown in FIGS. 25A to 25C, the conductive pattern 67 at the channel portion C and the underlying ohmic

contact pattern 57 are etched using the first photoresist pattern 112 as a mask, and removed.

At this time, the semiconductor pattern 42 may be reduced in thickness, and the first photoresist pattern 112 are also partially etched. The etching should be made in condition that the gate insulating layer 30 is not etched. Of course, it is preferable that the photoresist pattern is so thick that the photoresist pattern 112 is not completely removed while exposing the underlying data line assembly.

Consequently, the conductive pattern 67 is separated into a source electrode 65 and a drain electrode 66, and the underlying ohmic contact patterns 55, 56 and 58 are completed.

The first photoresist pattern at the data line assembly portion A is removed through ashing.

Thereafter, as shown in FIGS. 26A to 26E, silicon nitride is deposited onto the data line assembly to thereby form a protective layer 70. The protective layer 70, and the gate insulating layer 30 are dry-etched while exposing the aluminum-based over-layers 202 and 602 of the drain electrodes 66, the gate pads 24, the data pads 64, the storage capacitor conductive patterns 68, and the gate control signal lines 223, 224 and 225. The exposed portions of the aluminum-based layers 202 and 602 are wet-etched using an aluminum etching solution, and removed.

In this way, contact holes 74, 273, 274 and 275 exposing the chrome-based under-layers 201 and 601 of the gate pads 24 and the gate control signal lines 223, 224 and 225 are completed.

Thereafter, the protective layer 70 is side-etched while exposing the lateral side of the aluminum-based layer 602 of the drain electrodes 66, the storage capacitor conductive patterns, and the data pads 64, thereby forming stepped contact holes 72, 78 and 76 where the top opening width is larger than the bottom opening width. In this structure, pixel electrodes 82 can contact the drain electrodes 66 and the storage capacitor conductive patterns 68 through the contact holes 72 and 78 in a stable manner.

The contact holes 273, 274 and 275 exposing the signal lines 223, 224 and 225 are longitudinally formed along the shape of the signal lines 223, 224 and 225 such that the lateral side of each contact hole bordering on the gate control signal line has a length longer than the width thereof. Furthermore, the contact holes 74 and 76 exposing the gate and the data pads 24 and 64 are also longitudinally formed along the shape of the gate and data pads 24 and 64 such that the lateral side of each contact hole bordering on the pad has a length longer than the width thereof.

Thereafter, as shown in FIGS. 27A to 27E, an ITO-based transparent material is deposited onto the substrate 10, and etched through photolithography to thereby form pixel electrodes 82 connected to the drain electrodes 66, subsidiary gate and data pads 84 and 86 connected to the gate and data pads 24 and 64, and subsidiary gate control signal pads 273, 274 and 275 connected to the gate control signal lines 223, 224 and 225. The pixel electrodes 82, and the subsidiary pads 84, 86, 273, 274 and 275 directly contact the chrome-based under-layers 201 and 601.

After the TFT array substrate is completed, data and gate signal transmission films 300 and 400 are attached to the TFT array substrate using an anisotropic conductive film 250. At this time, the subsidiary gate pads 84, the subsidiary data pads 86, and the gate control signal lines 223, 224 and 225 are electrically connected to gate signal leads 410, data signal leads 310 and gate control signal leads 323, 324 and 325 of the data and gate signal transmission films 300 and 400 in one to one correspondence.

Alternatively, the contact holes may be structured to be smaller than the relevant lines or pads. That is, the contact hole may be positioned within the area of the relevant lines or pads. The shape of the contact holes may be altered in various manners provided that the lateral side of each contact hole bordering on the line or pad has a length longer than the width of the contact hole.

As described above, in the inventive liquid crystal display, the lateral side of each contact hole bordering on the gate control signal line has a length longer than the width thereof so that the amount of Joule heat due to the voltage drop at the boundary between the contact hole and the relevant line can be reduced, thereby preventing the line opening.

While the present invention has been described in detail with reference to the preferred embodiments, those skilled in the art will appreciate that various modifications and substitutions can be made thereto without departing from the spirit and scope of the present invention as set forth in the appended claims.

What is claimed is:

1. A liquid crystal display, comprising:

- a substrate;
- a gate line assembly and a plurality of signal lines formed on the substrate, the gate line assembly comprising gate electrodes and gate lines;
- a gate insulating layer covering the gate line assembly and the signal lines;
- thin film transistor semiconductor patterns formed on the gate insulating layer;
- a data line assembly comprising data lines crossing over the gate lines while being insulated from the gate lines, source electrodes extended from the data lines while contacting the semiconductor patterns, and drain electrodes contacting the semiconductor patterns in correspondence with the source electrodes;
- a protective layer covering the data line assembly and the semiconductor patterns;
- first contact holes exposing the drain electrodes;
- second contact holes exposing the respective signal lines with a predetermined width, the second contact holes having a lateral side bordering on the signal line, the lateral side of the second contact holes having a length greater than the width of the second contact holes; and
- pixel electrodes and subsidiary signal pads standing in the same plane, the pixel electrodes being connected to the drain electrodes, the subsidiary signal pads being connected to the signal lines.

2. The liquid crystal display of claim 1, wherein the gate line assembly and the signal lines have a double-layered structure with an aluminum-based layer.

3. The liquid crystal display of claim 2, wherein the second contact holes are formed at the gate insulating layer, the protective layer, and the aluminum-based layer of the signal lines.

4. The liquid crystal display of claim 1, further comprising a signal transmission film with signal leads, the signal leads connected to the signal lines in one to one correspondence.

5. The liquid crystal display of claim 4, wherein the signal leads of the signal transmission film comprise a first signal lead carrying high voltage signals and a second signal lead carrying low voltage signals, and a dummy lead is formed between the first signal lead and the second signal lead.

6. The liquid crystal display of claim 5, wherein a same voltage is applied to the dummy lead and the first signal lead.

7. The liquid crystal display of claim 5, wherein the dummy lead is several to several tens micrometers thick.

8. The liquid crystal display of claim 5, wherein a dummy line corresponding to the dummy lead is formed at the substrate.

9. The liquid crystal display of claim 8, wherein the dummy line is formed with a conductive material that is less oxidative than the signal line.

10. The liquid crystal display of claim 1, further comprising:

- a gate pad connected to each gate line as a component of the gate line assembly;
- a data pad connected to each data line as a component of the data line assembly;
- a third contact hole exposing said gate pad with a predetermined width;
- a fourth contact hole exposing said data pad with a predetermined width;
- a subsidiary gate pad covering said gate pad at the third contact hole; and
- a subsidiary data pad covering said data pad at the fourth contact hole.

11. The liquid crystal display of claim 10, wherein each of the third contact hole and the fourth contact hole has a lateral side bordering on the pad, the lateral side of the contact hole being longer than the width of the contact hole.

12. The liquid crystal display of claim 1, further comprising:

- common voltage pads formed at the substrate, the common voltage pads being covered by one insulating layer among the gate insulating layer and the protective layer;
- contact holes formed at the insulating layer with a predetermined width while exposing the common voltage pads, each contact hole having a lateral side bordering on the pad, the lateral side of the contact hole being longer than the width of the contact hole; and
- subsidiary common voltage pads connected to the common voltage pads through the contact holes.

13. The liquid crystal display of claim 12, further comprising a color filter substrate with a common electrode, the common electrode being connected to the subsidiary common voltage pads.

14. A display device, comprising:

- a first substrate having a plurality of gate lines and a plurality of data lines;
- a plurality of thin film transistors electrically connected to the gate lines and the data lines;
- a plurality of pixel electrodes electrically connected to the thin film transistors, respectively;
- a plurality of gate driving ICs to output gate signals to the gate lines;
- a plurality of data driving ICs to output data signals to the data lines;
- a plurality of interconnection lines for applying apply gate control signals to at least one of the gate driving ICs; and
- a black matrix overlapping at least one of the interconnection lines,

wherein one of the gate control signals is connected to at least one of the plurality of interconnection lines via a contact hole having a lateral side bordering the gate control signal and a length of the lateral side being longer than a width of the contact hole.

专利名称(译)	用于液晶显示器的控制信号单元		
公开(公告)号	<a href="#">US6888585</a>	公开(公告)日	2005-05-03
申请号	US09/964639	申请日	2001-09-28
[标]申请(专利权)人(译)	金东GYU		
申请(专利权)人(译)	金东GYU		
当前申请(专利权)人(译)	SAMSUNG ELECTRONICS CO. , LTD.		
[标]发明人	KIM DONG GYU		
发明人	KIM, DONG-GYU		
IPC分类号	G02F1/13 G02F1/1345 G02F1/1362 G02F1/133 G09F9/30 G09F9/35 H01L29/786 G02F1/136 H01L29/04		
CPC分类号	G02F1/1345 G02F1/13458 G02F1/136286 H01L27/1288 H01L27/124 H01L27/1244 G02F2001/13629		
优先权	1020000064396 2000-10-31 KR		
其他公开文献	US20020051110A1		
外部链接	<a href="#">Espacenet</a>	<a href="#">USPTO</a>	

摘要(译)

控制信号单元包括基板，形成在基板上的信号线，以及覆盖信号线的绝缘层。接触孔以预定宽度暴露信号线。接触孔具有与信号线接壤的侧面。接触孔的侧面比接触孔的宽度长。辅助信号焊盘通过接触孔连接到信号线。

