



US 20070013854A1

(19) **United States**

(12) **Patent Application Publication**

Yoo et al.

(10) **Pub. No.: US 2007/0013854 A1**

(43) **Pub. Date: Jan. 18, 2007**

(54) **LIQUID CRYSTAL DISPLAY**

(30) **Foreign Application Priority Data**

Jul. 15, 2005 (KR)..... 10-2005-0064488

(75) Inventors: **Seung-Hoo Yoo**, Seongnam-si (KR);
Jong-Ho Son, Seoul (KR); **Hee-Wook Do**, Suwon-si (KR); **Hyun-Wuk Kim**,
Yongin-si (KR); **Hak-Sun Chang**,
Yongin-si (KR); **Yoon-Sung Um**,
Yongin-si (KR)

Publication Classification

(51) **Int. Cl.**
G02F 1/1343 (2006.01)
(52) **U.S. Cl.** **349/143**

(57) **ABSTRACT**

A liquid crystal display includes: a substrate; a pixel electrode disposed on the substrate and having a first subpixel electrode and a second subpixel electrode; and a common electrode facing the pixel electrode, wherein the first subpixel electrode has a pair of bent edges substantially parallel to each other, the second subpixel electrode has a pair of bent edges substantially parallel to each other, and the second subpixel electrode has a height greater than a height of the first subpixel electrode.

Correspondence Address:
F. CHAU & ASSOCIATES, LLC
130 WOODBURY ROAD
WOODBURY, NY 11797 (US)

(73) Assignee: **Samsung Electronics Co., Ltd.**

(21) Appl. No.: **11/485,579**

(22) Filed: **Jul. 12, 2006**




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 21




FIG. 22





FIG. 23



LIQUID CRYSTAL DISPLAY

CROSS-REFERENCE TO RELATED APPLICATION

[0001] This Application claims priority from a Korean patent application number 10-2005-0064488 filed on Jul. 15, 2005, and all the benefits accruing therefrom under 35 U.S.C. §119, the contents of which are incorporated by reference herein in its entirety.

BACKGROUND OF THE INVENTION

[0002] (a) Technical Field

[0003] The present disclosure relates to a liquid crystal display.

[0004] (b) Discussion of Related Art

[0005] A liquid crystal display (LCD) is one of the most widely used flat panel display devices. The LCD includes a pair of panels including field-generating electrodes such as pixel electrodes and a common electrode, and a liquid crystal (LC) layer interposed between the panels. The LCD generates an electric field in the LC layer by applying voltages to the electrodes, and obtains desired images by controlling the strength of the electric field for determining orientations of LC molecules and polarization of light incident on the LC layer to vary the transmittance of light incident on the LC layer.

[0006] The LCD further includes switching elements connected to the pixel electrodes and signal lines such as gate lines and data lines, for applying signals to the switching elements, thereby applying voltages to the pixel electrodes.

[0007] Among the LCDs, a vertical alignment (VA) mode LCD, which aligns LC molecules such that the long axes of the LC molecules are perpendicular to the panels in the absence of an electric field, is spotlighted because of its high contrast ratio and wide reference viewing angle. The reference viewing angle means a viewing angle where the contrast ratio is 1:10 or the luminance sequence of grays starts to be reversed.

[0008] The wide viewing angle of the VA mode LCD can be realized by cutouts in the field-generating electrodes and protrusions on or under the field-generating electrodes. Since the cutouts and the protrusions can determine the tilt directions of the LC molecules, the tilt directions can be distributed into several directions by using the cutouts and the protrusions so to widen the reference viewing angle.

[0009] However, the protrusions and the cutouts obstruct the transmission of incident light and, thus, the light transmittance decreases as the number of the protrusions or the cutouts increases. In order to increase the light transmittance, the area of the pixel electrodes is suggested to be enlarged. However, the suggested configuration makes adjacent pixel electrodes close and makes the pixel electrodes and the data lines adjacent thereto close such that strong lateral electric fields are generated near the edges of the pixel electrodes. The lateral electric fields disorder the orientations of the LC molecules to generate visible texture in the image, as well as light leakage.

[0010] In addition, the VA mode LCD has poor lateral visibility as compared with front visibility. For example, in

a conventional LCD provided with cutouts, the image becomes brighter toward the lateral edges of the LCD and, in a severe case, the luminance difference between high grays vanishes to make the overall image dim.

[0011] To improve the lateral visibility, a pixel is divided into two subpixels capacitively coupled to each other. One of the two subpixels is directly supplied with a voltage, while the other is subjected to a voltage drop by the capacitive coupling, such that the two subpixels have different voltages to result in different light transmittances.

SUMMARY OF THE INVENTION

[0012] A liquid crystal display according to an exemplary embodiment of the present invention includes: a first substrate; a second substrate; a plurality of first signal lines formed at the first substrate; a plurality of second signal lines formed at the first substrate; a first subpixel electrode formed at the first substrate and having a bent edge; a second subpixel electrode formed at the first substrate, having a bent edge, and disposed adjacent to the first subpixel electrode in a first direction; a third subpixel electrode formed at the first substrate, having a bent edge, and disposed adjacent to the second subpixel electrode in a second direction; a fourth subpixel electrode formed at the first substrate, having a bent edge, and disposed adjacent to the third subpixel electrode in the first direction and to the first subpixel electrode in the second direction; a common electrode formed at the second substrate and facing the first to the fourth subpixel electrodes; and a plurality of switching elements, each of the switching elements coupled to one of the first signal lines, one of the second signal lines, and one of the first to the fourth subpixel electrodes, wherein the bent edge of the second subpixel electrode is longer than the bent edge of the first subpixel electrode, the bent edge of the fourth subpixel electrode is longer than the bent edge of the third subpixel electrode, and the fourth subpixel electrode has an edge contacting an edge of the second subpixel electrode.

[0013] First-directional lengths of the first to the fourth subpixel electrodes may be substantially equal to each other, and a length of the bent edge of each of the second and the fourth subpixel electrodes may be about twice a length of the bent edge of each of the first and the third subpixel electrodes.

[0014] The liquid crystal display may further include a tilt direction determining member formed at the common electrode. The tilt direction determining member may include a cutout having a bent portion passing through one of the first to the fourth subpixel electrodes and extending substantially parallel to the bent edge of the one of the first to the fourth subpixel electrodes. A distance between the bent portion of the cutout and the bent edge of the one of the first to the fourth subpixel electrodes may be equal to about 20-35 microns.

[0015] The first subpixel electrode and the second or the fourth subpixel electrode may be supplied with different voltages obtained from a single image information.

[0016] The switching elements may include a first thin film transistor coupled to the first subpixel electrode, and a second thin film transistor coupled to the second or the fourth subpixel electrode, and the first and the second thin film transistors may be connected to two different ones of the first signal lines and to a single one of the second signal lines.

[0017] The first and the second thin film transistors may turn on to transmit signals from the single one of the second signal lines in response to signals from the two different ones of the first signal lines, or may turn on to transmit signals from the different two of the first signal lines in response to a signal from the single one of the second signal lines.

[0018] A liquid crystal display according to an exemplary embodiment of the present invention includes: a substrate; a pixel electrode disposed on the substrate and comprising a first subpixel electrode and a second subpixel electrode; and a common electrode facing the pixel electrode, wherein the first subpixel electrode has a pair of bent edges substantially parallel to each other, the second subpixel electrode has a pair of bent edges substantially parallel to each other, and the second subpixel electrode has a height greater than a height of the first subpixel electrode.

[0019] The first subpixel electrode and the second subpixel electrode may be adjacent in a length direction or in a height direction. In the latter case, the convexity and the concavity of the bent edges of the first and the second subpixel electrodes may be reversed relative to each other.

[0020] The first subpixel electrode may have a length substantially equal to a length of the second subpixel electrode, and the height of the second subpixel electrode may be about twice the height of the first subpixel electrode.

[0021] Each of the bent edges may have a bent point, and each of the first and the second subpixel electrodes may have a symmetry with respect to a straight line connecting the bent points.

[0022] The pair of bent edges may include a concave edge and a convex edge.

[0023] The convex edge of the first subpixel electrode may be adjacent the concave edge of the second subpixel electrode or the concave edge of the first subpixel electrode may be adjacent the convex edge of the second subpixel electrode. Otherwise, the concave edge of the first subpixel electrode may be connected to the convex edge of the second subpixel electrode, and the convex edge of the first subpixel electrode may be connected to the concave edge of the second subpixel electrode.

[0024] The liquid crystal display may further include a tilt direction determining member formed at the common electrode. The tilt direction determining member may include a cutout including a bent portion passing through the first or the second subpixel electrode and extending substantially parallel to the bent edges of the first or the second subpixel electrode. A distance between the bent portion of the cutout and one of the bent edges of the first or the second subpixel electrodes adjacent the bent portion may be equal to about 20-35 microns.

[0025] The first subpixel electrode and the second subpixel electrode may have different voltages, and the first subpixel electrode and the second subpixel electrode may be supplied with different voltages obtained from a single image information.

[0026] The liquid crystal display may further include: a first thin film transistor coupled to the first subpixel electrode; a second thin film transistor coupled to the second subpixel electrode; a first signal line coupled to the first thin film transistor; a second signal line coupled to the second

thin film transistor; and a third signal line coupled to the first and the second thin film transistors and intersecting the first and the second signal lines.

[0027] The first thin film transistor may turn on to transmit a signal from the third signal line in response to a signal from the first signal line, and the second thin film transistor may turn on to transmit a signal from the third signal line in response to a signal from the second signal line. At this time, the first thin film transistor and the second thin film transistor may be disposed opposite each other with respect to the third signal line.

[0028] Otherwise, the first thin film transistor may turn on to transmit a signal from the first signal line in response to a signal from the third signal line, and the second thin film transistor may turn on to transmit a signal from the second signal line in response to a signal from the third signal line.

[0029] The liquid crystal display may further include a fourth signal line extending in a straight line connecting bent points of the bent edges of the first and the second subpixel electrodes. Each of the first and the second thin film transistors may include a drain electrode overlapping the fourth signal line.

[0030] The first subpixel electrode and the second subpixel electrode may be capacitively coupled to each other. The liquid crystal display may further include: a thin film transistor coupled to the first subpixel electrode; a first signal line coupled to the thin film transistor; and a second signal line coupled to the thin film transistor and intersecting the first signal line.

BRIEF DESCRIPTION OF THE DRAWINGS

[0031] Exemplary embodiments of the present invention can be understood in more detail from the following descriptions taken in conjunction with the accompanying drawings in which:

[0032] FIG. 1 is a block diagram of an LCD according to an exemplary embodiment of the present invention;

[0033] FIG. 2 is an equivalent circuit diagram of a pixel of an LCD according to an exemplary embodiment of the present invention;

[0034] FIGS. 3-5 are layout diagrams of pixel electrodes, common electrodes, and color filters in LC panel assemblies according to exemplary embodiments of the present invention;

[0035] FIG. 6 is a planar view of a subpixel electrode representing the subpixel electrodes shown in FIGS. 3-5;

[0036] FIG. 7 is an equivalent circuit diagram of signal lines and a pixel according to an exemplary embodiment of the present invention;

[0037] FIG. 8 is a layout view of a lower panel for an LC panel assembly according to an exemplary embodiment of the present invention;

[0038] FIG. 9 is a layout view of an upper panel for an LC panel assembly according to an exemplary embodiment of the present invention;

[0039] FIG. 10 is a layout view of an LC panel assembly including the lower panel shown in FIG. 8 and the upper panel shown in FIG. 9;

[0040] FIG. 11 is an exemplary sectional view of the LC panel assembly shown in FIG. 10 taken along line XI-XI;

[0041] FIG. 12 is another exemplary sectional view of the LC panel assembly shown in FIG. 10 taken along line XI-XI;

[0042] FIG. 13 is a layout view of a lower panel for an LC panel assembly according to an exemplary embodiment of the present invention;

[0043] FIG. 14 is a layout view of an upper panel for an LC panel assembly according to an exemplary embodiment of the present invention;

[0044] FIG. 15 is a layout view of an LC panel assembly including the lower panel shown in FIG. 13 and the upper panel shown in FIG. 14;

[0045] FIG. 16 is a sectional view of the LC panel assembly shown in FIG. 15 taken along lines XVI-XVI'-'XVI".

[0046] FIG. 17 is an equivalent circuit diagram of signal lines and a pixel according to an exemplary embodiment of the present invention;

[0047] FIG. 18 is a layout view of an LC panel assembly according to an exemplary embodiment of the present invention;

[0048] FIG. 19 is an equivalent circuit diagram of signal lines and a pixel according to an exemplary embodiment of the present invention.

[0049] FIG. 20 is a layout view of an LC panel assembly according to an exemplary embodiment of the present invention;

[0050] FIG. 21 is a sectional view of the LC panel assembly shown in FIG. 20 taken along line XXI-XXI;

[0051] FIG. 22 is a layout view of an LC panel assembly according to an exemplary embodiment of the present invention; and

[0052] FIG. 23 is a sectional view of the LC panel assembly shown in FIG. 22 taken along line XXIII-XXIII.

DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

[0053] Exemplary embodiments of the present invention now will be described more fully hereinafter with reference to the accompanying drawings. The present invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein.

[0054] An LCD according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 1 and 2.

[0055] FIG. 1 is a block diagram of an LCD according to an exemplary embodiment of the present invention, and FIG. 2 is an equivalent circuit diagram of a pixel of an LCD according to an exemplary embodiment of the present invention.

[0056] Referring to FIG. 1, an LCD according to an exemplary embodiment includes an LC panel assembly 300, a gate driver 400 and a data driver 500 that are connected to

the panel assembly 300, a gray voltage generator 800 connected to the data driver 500, and a signal controller 600 controlling the above elements.

[0057] Referring to FIG. 1, the panel assembly 300 includes a plurality of signal lines (not shown) and a plurality of pixels PX connected thereto and arranged substantially in a matrix. In a structural view shown in FIG. 2, the panel assembly 300 includes a lower panel 100, an upper panel 200, and an LC layer 3 interposed therebetween.

[0058] The signal lines, which are provided on the lower panel 100, include a plurality of gate lines (not shown) transmitting gate signals, also referred to as "scanning signals", and a plurality of data lines (not shown) transmitting data signals. The gate lines extend substantially in a row direction and are substantially parallel to each other, while the data lines extend substantially in a column direction and are substantially parallel to each other.

[0059] Referring to FIG. 2, each pixel PX includes a pair of subpixels and each subpixel includes a liquid crystal (LC) capacitor Clc1/Clc2. At least one of the two subpixels further includes a switching element (not shown) connected to a gate line, a data line, and an LC capacitor Clc1/Clc2.

[0060] The LC capacitor Clc1/Clc2 includes a subpixel electrode PE1/PE2 provided on the lower panel 100 and a common electrode CE provided on the upper panel 200 as two terminals. The LC layer 3 disposed between the electrodes PE1/PE2 and CE functions as the dielectric of the LC capacitor Clc1/Clc2. A pair of subpixel electrodes PE1 and PE2 are separated from each other and form a pixel electrode PE. The common electrode CE is supplied with a common voltage Vcom and covers an entire surface of the upper panel 200. The LC layer 3 has negative dielectric anisotropy, and LC molecules in the LC layer 3 may be oriented so that long axes of the LC molecules are perpendicular to the surfaces of the panels 100 and 200 in the absence of an electric field.

[0061] For a color display, each pixel PX uniquely represents one of the primary colors, that is, spatial division, or each pixel PX sequentially represents the primary colors in turn, that is, temporal division, such that the spatial or temporal sum of the three primary colors are recognized as a desired color. An example of a set of the primary colors includes red, green, and blue colors. FIG. 2 shows an example of spatial division in that each pixel PX includes a color filter CF representing one of the primary colors in an area of the upper panel 200 facing the pixel electrode PE. Alternatively, the color filter CF is provided on or under the subpixel electrode PE1 or PE2 on the lower panel 100.

[0062] A pair of polarizers (not shown) are attached to outer surfaces of the panels 100 and 200. The polarization axes of the two polarizers may be crossed such that the crossed polarizers block the light incident onto the LC layer 3. One of the polarizers may be omitted.

[0063] Detailed structures of pixel electrodes, common electrodes, and color filters in LC panel assemblies will be described in detail with reference to FIGS. 3, 4, 5 and 6.

[0064] FIGS. 3-5 are layout diagrams of pixel electrodes, common electrodes, and color filters in LC panel assemblies according to exemplary embodiments of the present inven-

tion, and FIG. 6 is a planar view of a subpixel electrode representing the subpixel electrodes shown in FIGS. 3-5.

[0065] Referring to FIGS. 3-5, each pixel electrode 191 of the LC panel assemblies according to exemplary embodiments of the present invention, which pixel electrode is shown enclosed by a dash-dot line, includes a first subpixel electrode 191a and a second subpixel electrode 191b that are separated from each other. The subpixel electrodes 191a and 191b have cutouts 92a and 92b, respectively, and a common electrode CE (shown in FIG. 2) has a plurality of cutouts 71a and 71b facing the subpixel electrodes 191a and 191b, respectively. Red color filters 230R, green color filters 230G, and blue color filters 230B extend along the pixel electrodes 191 adjacent to each other in a column direction.

[0066] Both of the first and the second subpixel electrodes 191a and 191b forming the pixel electrode 191 may be coupled to respective switching elements (not shown). On the other hand, the first subpixel electrode 191a is coupled to a switching element (not shown), while the second subpixel electrode 191b is capacitively coupled to the first subpixel electrode 191a.

[0067] The subpixel electrodes 191a and 191b have substantially the same or similar shapes, and the cutouts 71a and 71b of the common electrode CE also have substantially the same or similar shapes. FIG. 6 shows a subpixel electrode 193 representing the subpixel electrodes 191a and 191b shown in FIGS. 3-5 and a cutout 70 representing the cutouts 71a and 71b shown in FIGS. 3-5.

[0068] As shown in FIG. 6, the subpixel electrode 193 has a pair of bent edges 193o1 and 193o2 and a pair of transverse edges 193t and has the shape of a chevron. The bent edges 193o1 and 193o2 include the convex edge 193o1 meeting the transverse edges 193t at an obtuse angle, for example, about 135 degrees, and the concave edge 193o2 meeting the transverse edges 193t at an acute angle, for example, about 45 degrees. The bent edges 193o1 and 193o2, which are formed by the 90-degree meeting of a pair of oblique edges, has a bent angle of about a right angle. Each of the subpixel electrodes 193 has a cutout 90 that extends from a concave vertex CV on the concave edge 193o2 toward a convex vertex VV on the convex edge 193o1 and reaches near a center of the subpixel electrode 193.

[0069] The cutout 70 in the common electrode includes a bent portion 70o having a bent point CP, a center transverse portion 70t1 connected to the bent point CP of the bent portion 70o, and a pair of terminal transverse portions 70t2 connected to ends of the bent portion 70o. The bent portion 70o of the cutout 70 includes a pair of oblique portions meeting at about a right angle, extends substantially parallel to the bent edges 193o1 and 193o2 of the subpixel electrode 193, and bisects the subpixel electrode 193 into left and right halves. The center transverse portion 70t1 of the cutout 70 makes an obtuse angle, for example, about 135 degrees with the bent portion 70o, and extends toward the convex vertex VV of the subpixel electrode 193. The terminal transverse portions 70t2 are aligned with the transverse edges 193t of the subpixel electrode 193 and make an obtuse angle, for example, about 135 degrees with the bent portion 70o.

[0070] The subpixel electrode 193 is divided into four sub-areas S1, S2, S3 and S4 by the cutouts 70 and 90. Each of the sub-areas S1-S4 has two primary edges defined by a

bent portion 70o of the cutout 70 and by a bent edge 193o of the subpixel electrode 193. The distance between the primary edges, that is, the width of each sub-area S1-S4, may be equal to about 20-35 microns.

[0071] The subpixel electrode 193 and the cutout 70 has an inversion symmetry with respect to an imaginary straight line, referred to as a center transverse line, connecting the convex vertex VV and the concave vertex CV of the subpixel electrode 193.

[0072] Referring to FIG. 6, the length L of a transverse edge 193t of the subpixel electrode 193 is called the length of the subpixel electrode 193, and the distance H between the two transverse edges 193t of the subpixel electrode 193 is called the height of the subpixel electrode 193. In FIGS. 3-5, the length of the first subpixel electrode 191a is substantially equal to the length of the second subpixel electrode 191b, and the height of the second subpixel electrode 191b is about twice the height of the first subpixel electrode 191a. Accordingly, the area of the second subpixel electrode 191b is about twice the area of the first subpixel electrode 191a.

[0073] As shown in FIGS. 3-5, the first subpixel electrode 191a and the second subpixel electrode 191b are alternately arranged in the row and column directions. However, the convexity and the concavity of the subpixel electrodes 191a and 191b are fixed in the row direction, while the convexity and the concavity of the subpixel electrodes 191a and 191b are alternately reversed in the column direction. For example, the upper one of two rows shown in FIGS. 3-5 includes subpixel electrodes 191a and 191b having convex left edges and concave right edges, while the lower one of the two rows includes subpixel electrodes 191a and 191b having concave left edges and convex right edges. It is noted that the second subpixel electrodes 191b in adjacent rows have contacting edges or portions.

[0074] Regarding the arrangement of the subpixel electrodes 191a and 191b in the row direction, the center transverse line of the first subpixel electrode 191a coincides with the center transverse line of the second subpixel electrode 191b. In addition, the convex edge of the first subpixel electrode 191a is a neighbor of the concave edge of the second subpixel electrode 191b, and the concave edge of the first subpixel electrode 191a is a neighbor of the convex edge of the second subpixel electrode 191b. Regarding the arrangement in the column direction, the convex edge of the first subpixel electrode 191a is connected to the concave edge of the second subpixel electrode 191b, and the concave edge of the first subpixel electrode 191a is connected to the convex edge of the second subpixel electrode 191b.

[0075] The first and the second subpixel electrodes 191a and 191b of each pixel electrode 191 shown in FIGS. 3 and 4 are adjacent to each other in the row direction, while the first and the second subpixel electrodes 191a and 191b of each pixel electrode 191 shown in FIG. 5 are adjacent to each other in the column direction.

[0076] Referring to FIG. 3, the relative positions of the first subpixel electrode 191a and the second subpixel electrode 191b in each pixel electrode 191 are reversed between two adjacent rows. For example, the first subpixel electrode 191a of each pixel electrode 191 in the upper one of two rows shown in FIG. 3 is disposed to the right of the second

subpixel electrode **191b**, while the first subpixel electrode **191a** of each pixel electrode **191** in the lower one of two rows shown in FIG. 3 is disposed to the left of the second subpixel electrode **191b**.

[0077] On the contrary, the relative positions of the first subpixel electrode **191a** and the second subpixel electrode **191b** in each pixel electrode **191** shown in FIG. 4 are the same in all rows. For example, the first subpixel electrode **191a** of each pixel electrode **191** in all rows shown in FIG. 4 is disposed to the right of the second subpixel electrode **191b**. However, the first subpixel electrode **191a** may be disposed left to the second subpixel electrode **191b**. In this arrangement, the pixel electrodes **191** adjacent in the column direction form a straighter line than those shown in FIG. 3.

[0078] In the arrangement shown in FIG. 5, the relative (column directional) positions of the first subpixel electrode **191a** and the second subpixel electrode **191b** in each pixel electrode **191** are reversed in two adjacent rows. For example, in the pixel electrode **191** in the leftmost column among the four columns shown in FIG. 5, the first subpixel electrode **191a** is disposed down the second subpixel electrode **191b**, while the first subpixel electrode **191a** of the pixel electrode **191** in the next left column is disposed up the second subpixel electrode **191b**. The width of the color filters **230R**, **230G** and **230B** shown in FIG. 5 is a half of that shown in FIGS. 3 and 4.

[0079] In the above-described arrangements, the first and second subpixel electrodes **191a** and **191b** having an area ratio of about 1:2 are well organized without wasted space. The arrangements shown in FIGS. 3 and 4 may be suitable for large-pixel-size display devices, for example, for a large display device larger than about 32", in particular, for about 40" TV sets. On the contrary, the arrangement shown in FIG. 5 may be suitable for smaller-pixel-size display devices, for example, 17" or 19" monitors, etc.

[0080] In the meantime, since the color filters **230R**, **230G** and **230B** extend almost straight along the column direction, a single-colored line may be easily displayed. In particular, the pixel electrodes **191** in each column shown in FIG. 4 form a straighter line to be more advantageous in displaying a longitudinal line.

[0081] In addition, the color filters **230R**, **230G** and **230B** have equal areas to facilitate the balance of the colors.

[0082] Moreover, each of the pixel electrodes **191** is bent only once to give an increased aperture ratio as compared with pixel electrodes that are bent twice or more.

[0083] Referring to FIG. 1 again, the gray voltage generator **800** generates a plurality of gray voltages related to the light transmittance of the pixels PX. However, the gray voltage generator **800** may generate only a given number of gray voltages, referred to as reference gray voltages, instead of generating all of the gray voltages.

[0084] The gate driver **400** is connected to the gate lines of the panel assembly **300** and synthesizes the gate-on voltage V_{on} and the gate-off voltage V_{off} from an external device to generate gate signals V_g for application to the gate lines.

[0085] The data driver **500** is connected to the data lines of the panel assembly **300** and applies data voltages V_d , which are selected from the gray voltages supplied from the

gray voltage generator **800**, to the data lines. However, the data driver **500** may generate gray voltages for all of the gray voltages by dividing the reference gray voltages and selecting the data voltages V_d from the generated gray voltages when the gray voltage generator **800** generates the reference gray voltages.

[0086] The signal controller **600** controls the gate driver **400** and the data driver **500**, etc.

[0087] Each of the driving and processing units **400**, **500**, **600** and **800** may include at least one integrated circuit (IC) chip mounted on the LC panel assembly **300** or on a flexible printed circuit (FPC) film in a tape carrier package (TCP) arrangement, which are attached to the panel assembly **300**. Alternatively, at least one of the driving and processing units **400**, **500**, **600** and **800** may be integrated into the panel assembly **300** along with the signal lines and the switching elements. Alternatively, all the driving and processing units **400**, **500**, **600** and **800** may be integrated into a single IC chip, but at least one of the driving and processing units **400**, **500**, **600** and **800** or at least one circuit element in at least one of the driving and processing units **400**, **500**, **600** and **800** may be disposed on a single IC chip.

[0088] Now, the operation of the above-described LCD will be described in detail.

[0089] The signal controller **600** is supplied with input image signals R, G and B and with input control signals for controlling the display thereof from an external graphics controller (not shown). The input image signals R, G and B contain luminance information of each pixel PX, and the luminance has a predetermined number of, for example $1024(=2^{10})$, $256(=2^8)$ or $64(=2^6)$ grays. The input control signals include a vertical synchronization signal V_{sync} , a horizontal synchronization signal H_{sync} , a main clock MCLK, and a data enable signal DE, etc.

[0090] After generating gate control signals CONT1 and data control signals CONT2 and processing the input image signals R, G and B suitable for the operation of the panel assembly **300** and the data driver **500** on the basis of the input control signals and the input image signals R, G and B, the signal controller **600** transmits the gate control signals CONT1 to the gate driver **400**, and the processed image signals DAT and the data control signals CONT2 to the data driver **500**. The output image signals DAT are digital signals having a predetermined number of values or grays.

[0091] The gate control signals CONT1 include a scanning start signal STV for instructing a scanning start and at least a clock signal for controlling the output time of the gate-on voltage V_{on} . The gate control signals CONT1 may further include an output enable signal OE for defining the duration of the gate-on voltage V_{on} .

[0092] The data control signals CONT2 include a horizontal synchronization start signal STH for informing of the start of the data transmission for a group of subpixels, a load signal LOAD for instructing to apply the data voltages to the panel assembly **300**, and a data clock signal HCLK. The data control signal CONT2 may further include an inversion signal RVS for reversing the polarity of the data voltages, with respect to the common voltage V_{com} .

[0093] Responsive to the data control signals CONT2 from the signal controller **600**, the data driver **500** receives

a packet of the image signals DAT for the group of subpixels from the signal controller 600. The data driver 500 converts the image signals DAT into analog data signals selected from the gray voltages supplied from the gray voltage generator 800, and applies the data signals to the data lines.

[0094] The gate driver 400 applies the gate-on voltage Von to the gate line in response to the gate control signals CONTI from the signal controller 600, thereby turning on the switching elements connected thereto. The data voltages applied to the data lines are supplied to the subpixels through the activated switching elements.

[0095] Referring to FIGS. 3-5, when the first subpixel electrode 191a and the second subpixel electrode 191b forming a pixel electrode 191 are coupled to respective switching elements, that is, when each of the subpixels includes its own switching element, the two subpixels may be supplied with respective data voltages through the same data line at different times or through different data lines at the same time. However, when the first subpixel electrode 191a is coupled to a switching element (not shown) and the second subpixel electrode 191b is capacitively coupled to the first subpixel electrode 191a, one subpixel electrode including the first subpixel electrode 191a may be directly supplied with data voltages through the switching elements, while the other subpixel including the second subpixel electrode 191b may have a voltage that varies depending on the voltage of the first subpixel electrode 191a. At this time, the first subpixel electrode 191a having a relatively small area preferably has a voltage, relative to the common voltage, greater than the second subpixel electrode 191b having a relatively large area.

[0096] On the other hand, after two subpixel electrodes 191a and 191b are charged with the same voltage, the voltages of the subpixel electrodes 191a and 191b may be differentiated from each other by using storage capacitors (not shown), etc.

[0097] When the voltage difference is generated between two terminals of the LC capacitor Clc1/Clc2, a primary electric field substantially perpendicular to the surfaces of the panels 100 and 200 is generated in the LC layer 3 and both the pixel electrodes 191, PE and the common electrode CE are commonly referred to as field generating electrodes. The LC molecules in the LC capacitor clc1/Clc2 tend to change their orientations in response to the electric field so that their long axes may be perpendicular to the field direction. The molecular orientations determine the polarization of light passing through the LC layer 3. The polarizer(s) converts the light polarization into the light transmittance such that the pixels PX display the luminance represented by the image signal DAT.

[0098] The tilt angle of the LC molecules depends on the strength of the electric field. Since the voltages of the LC capacitors clc1 and Clc2 are different from each other, the tilt angles of the LC molecules in the subpixels are different from each other and thus the luminances of the two subpixels are different. Accordingly, the voltages of the two subpixels can be adjusted so that an image viewed from a lateral side is the closest to an image viewed from the front, that is, a lateral gamma curve is the closest to the front gamma curve, thereby improving the lateral visibility.

[0099] In addition, the area of the subpixel electrode 191a having a voltage, relative to the common voltage Vcom,

higher than that of the second subpixel electrode 191b may have an area smaller than that of the second subpixel electrode 191b, thereby making the lateral gamma curve further approach the front gamma curve. In particular, when the ratio of the areas of the first subpixel electrode 191a and the second subpixel electrode 191b is equal to about 1:2, the lateral gamma curve further approaches the front gamma curve to further improve the lateral visibility.

[0100] The tilt direction of the LC molecules is firstly determined by a horizontal field component. The horizontal field component is generated by the cutouts 71a, 71b, 92a and 92b of the field generating electrodes 191 and 270 CE and the edges of the subpixel electrodes 191a and 191b, which distort the primary electric field. The horizontal field component is substantially perpendicular to the edges of the cutouts 71a, 71b, 92a, 92b, and the edges of the first and second subpixel electrodes 191a and 191b.

[0101] Referring to FIGS. 3-5, since the LC molecules on each of the sub-areas divided by a set of the cutouts 71a, 71b, 92a, 92b tilt perpendicular to the major edges of the sub-area, the azimuthal distribution of the tilt directions are localized to four directions, thereby increasing the reference viewing angle of the LCD.

[0102] The width of the sub-areas, i.e., the distance between the bent portions of the cutouts of the common electrode CE and the bent edges of the subpixel electrodes 191a and 191b is preferably equal to about 20-35 microns as described above such that the horizontal component of the primary electric field can be suitably used and the decrease of the aperture ratio caused by the cutouts 71a, 71b, 92a, 92b can be reduced.

[0103] The direction of a secondary electric field due to the voltage difference between adjacent subpixel electrodes 191a and 191b is perpendicular to the major edges of the sub-areas. Accordingly, the field direction of the secondary electric field coincides with that of the horizontal component of the primary electric field. Consequently, the secondary electric field between the adjacent subpixel electrodes 191a and 191b enhances the determination of the tilt directions of the LC molecules.

[0104] By repeating this procedure by a unit of a horizontal period, which is denoted by "1H" and equal to one period of the horizontal synchronization signal Hsync or the data enable signal DE, all the pixels PX are supplied with data voltages.

[0105] When the next frame starts after one frame finishes, the inversion control-signal RVS applied to the data driver 500 is controlled such that the polarity of the data voltages is reversed, which is referred to as "frame inversion." The inversion control signal RVS may be also controlled such that the polarity of the data signals flowing in a data line are periodically reversed during one frame, for example, row inversion and dot inversion, or the polarity of the data signals in one packet are reversed, for example, column inversion and dot inversion.

[0106] The voltage across the LC capacitor clc1 or Clc2 forces the LC molecules in the LC layer 3 to be reoriented into a stable state corresponding to the voltage, and the reorientation of the LC molecules takes a time since the response time of the LC molecules is slow. The LC molecules continue to reorient themselves to vary the light

transmittance or the luminance until they reach the stable state on the condition that the application of the voltage across the LC capacitor clc1 or Clc2 is maintained. When the LC molecules reach the stable state and stop the reorientation, the light transmittance becomes fixed.

[0107] When a pixel voltage in such a stable state is referred to as a target pixel voltage and a light transmittance in the stable state is referred to as a target light transmittance, the target pixel voltage and the target light transmittance have one-to-one correspondence.

[0108] Since the time for turning on the switching element of each pixel PX to apply a data voltage to the pixel is limited, it is difficult for the LC molecules in the pixel PX to reach the stable state during the application of the data voltage. However, even though the switching element is turned off, the voltage across the LC capacitor clc1 or Clc2 still exists and thus the LC molecules continue the reorientation such that the capacitance of the LC capacitor clc1 or Clc2 changes. Ignoring leakage current, the total amount of electrical charges stored in the LC capacitor clc1 or Clc2 is kept constant when the switching element turns off, because one terminal of the LC capacitor clc1 or Clc2 is floating. Therefore, the variation of the capacitance of the LC capacitor clc1 or Clc2 results in the variation of the voltage across the LC capacitor clc1 or Clc2, that is, the pixel voltage.

[0109] Consequently, when a pixel PX is supplied with a data voltage corresponding to a target pixel voltage, referred to as a "target data voltage" hereinafter, which is determined in the stable state, an actual pixel voltage of the pixel PX may be different from the target pixel voltage such that the pixel PX may not reach a corresponding target light transmittance. The actual pixel voltage differs more from the target pixel voltage as the target transmittance differs more from a light transmittance that the subpixel initially has.

[0110] Accordingly, a data voltage applied to the pixel PX is required to be higher or lower than a target data voltage and for example, this can be realized by DCC (dynamic capacitance compensation).

[0111] DCC, which may be performed by the signal controller 600 or a separate image signal modifier, modifies an image signal of a frame, referred to as a "current image signal" hereinafter, for a subpixel to generate a modified current image signal referred to as a "modified (current) image signal" hereinafter based on an image signal of an immediately previous frame, referred to as a "previous image signal" hereinafter, for the subpixel. The modified image signal is basically obtained by experiments, and the difference between the modified current image signal and the previous image signal is usually larger than the difference between the current image signal before modification and the previous image signal. However, when the current image signal and the previous image signal are equal to each other or the difference therebetween is small, the modified image signal may be equal to the current image signal, that is, the current image signal may not, be modified.

[0112] In this way, the data voltages applied to the subpixels by the data driver 500 are higher or lower than the target data voltages.

[0113] However, the target transmittance may not be obtained by the above-described method. In this case, a predetermined voltage, referred to as a pre-tilt voltage

hereinafter, is pre-applied to the subpixel to pre-tilt the LC molecules and then, a primary voltage is applied to the subpixel.

[0114] For this purpose, the signal controller 600 or an image signal modifier modifies a current image signal in consideration of an image signal of the next frame, referred to as a "next image signal" hereinafter, as well as a previous image signal. For example, if the next image signal is very different from the current image signal, even though the current image signal is equal to the previous image signal, the current image signal is modified to prepare the next frame.

[0115] The modification of the image signals and the data voltages may or may not be performed for the highest gray or the lowest gray. In order to modify the highest gray or the lowest gray, the range of the gray voltages generated by the gray voltage generator 800 may be widened as compared with the range of the target data voltages required for obtaining the range of the target luminance, or the target transmittance, represented by the grays of the image signals.

[0116] Now, structures of LC panel assemblies according to exemplary embodiments of the present invention will be described in detail with reference to FIGS. 7, 8, 9, 10, 11, 12, 13, 14, 15, 16 and 17 as well as FIGS. 1-4.

[0117] FIG. 7 is an equivalent circuit diagram of signal lines and a pixel according to an exemplary embodiment of the present invention.

[0118] The LC panel assembly shown in FIG. 7 includes a plurality of signal lines and a plurality of pixels PX connected thereto. The signal lines include a plurality of pairs of gate lines GLa and GLb, a plurality of data lines DL, and a plurality of storage electrode lines SL extending substantially parallel to the gate lines GLa and GLb.

[0119] Each pixel PX includes a pair of subpixels PXa and PXb. Each subpixel PXa/PXb includes a switching element Qa/Qb connected to one of the gate lines GLa and GLb and one of the data lines DL, an LC capacitor Clca/Clcb coupled to the switching element Qa/Qb, and a storage capacitor Csta/Cstb connected between the switching element Qa/Qb and the storage electrode line SL.

[0120] The switching element Qa/Qb such as a thin film transistor (TFT) is provided on the lower panel 100 and has three terminals: a control terminal connected to a gate line GLa/GLb; an input terminal connected to a data line DL; and an output terminal connected to the LC capacitor Clca/Clcb and the storage capacitor Csta/Cstb.

[0121] The storage capacitor Csta/Cstb is an auxiliary capacitor for the LC capacitor Clca/Clcb. The storage capacitor Csta/Cstb includes a subpixel electrode and a separate signal line, which is provided on the lower panel 100, overlaps the subpixel electrode via an insulator, and is supplied with a predetermined voltage such as the common voltage Vcom. Alternatively, the storage capacitor Csta/Cstb includes the subpixel electrode and an adjacent gate line called a previous gate line, which overlaps the subpixel electrode via an insulator.

[0122] Since the LC capacitor Clca/Clcb and so on are described above with reference to FIG. 2, a detailed description thereof will be omitted.

[0123] In the LCD shown in FIG. 7, the signal controller 600 receives input image signals R, G and B and converts an input image signal R, G and B for each pixel PX into a pair of output image signals DAT for two subpixels PXa and PXb to be supplied to the data driver 500. Otherwise, the gray voltage generator 800 generates a pair of groups of gray voltages for respective subpixels PXa and PXb. The two groups of gray voltages are alternately supplied by the gray voltage generator 800 to the data driver 500 or alternately selected by the data driver 500, such that the two subpixels PXa and PXb are supplied with different voltages.

[0124] At this time, the values of the converted output image signals and the values of the gray voltages in each group are preferably determined such that the synthesis of gamma curves for the two subpixels PXa and PXb approaches a reference gamma curve at a front view. For example, the synthesized gamma curve at a front view coincides with the most suitable reference gamma curve at a front view, and the synthesized gamma curve at a lateral view is the most similar to the reference gamma curve at a front view.

[0125] An example of an LC panel assembly shown in FIG. 8 according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 8-11.

[0126] FIG. 8 is a layout view of a lower panel for an LC panel assembly according to an exemplary embodiment of the present invention, FIG. 9 is a layout view of an upper panel for an LC panel assembly according to an exemplary embodiment of the present invention, FIG. 10 is a layout view of an LC panel assembly including the lower panel shown in FIG. 8 and the upper panel shown in FIG. 9, and FIG. 11 is an exemplary sectional view of the LC panel assembly shown in FIG. 10 taken along line XI-XI.

[0127] Referring to FIGS. 8-11, an LC panel assembly according to an exemplary embodiment of the present invention includes a lower panel 100, an upper panel 200 facing the lower panel 100, and a liquid crystal layer 3 interposed between the panels 100 and 200.

[0128] First, the lower panel 100 will be described with reference to FIGS. 8, 10 and 11.

[0129] A plurality of gate conductors including a plurality of pairs of first and second gate lines 121a and 121b and a plurality of storage electrode lines 131 are formed on an insulating substrate 110 such as transparent glass or plastic.

[0130] The gate lines 121a and 121b transmit gate signals, extend substantially in a transverse direction, and are disposed at relatively upper and lower positions, respectively.

[0131] Each of the first gate lines 121a includes a plurality of first gate electrodes 124a projecting downwardly and an end portion 129a having a large area for contact with another layer or connection to an external driving circuit. Each of the second gate lines 121b includes a plurality of second gate electrodes 124b projecting upwardly toward and an end portion 129b having a large area for contact with another layer or connection to an external driving circuit. The first and second gate lines 121a and 121b may extend to be connected to a gate driver 400 that may be integrated on the substrate 110.

[0132] The storage electrode lines 131 are supplied with a predetermined voltage, such as the common voltage Vcom, and extend substantially parallel to the first and second gate lines 121a and 121b. Each of the storage electrode lines 131 is disposed between first and second gate lines 121a and 121b and it is nearly equidistant from the first gate line 121a and the second gate line 121b. The storage electrode lines 131 may have various shapes and arrangements. For example, each of the storage electrode lines 131 may include a plurality of expansions expanding upward and downward.

[0133] The first and second gate lines 121a, 121b and the storage electrode line 131 may be made of an Al containing metal such as Al and Al alloy, an Ag containing metal such as Ag and Ag alloy, a Cu containing metal such as Cu and Cu alloy, a Mo containing metal such as Mo and Mo alloy, Cr, Ta, or Ti. However, they may have a multi-layered structure including two conductive films (not shown) having different physical characteristics. One of the two films may be made of low resistivity metal including an Al containing metal, an Ag containing metal, and a Cu containing metal for reducing signal delay or voltage drop. The other film may be made of material such as an Mo containing metal, Cr, Ta, or Ti, which has good physical, chemical, and electrical contact characteristics with other materials such as indium tin oxide (ITO) or indium zinc oxide (IZO). Examples of the combination of the two films are a lower Cr film and an upper Al (alloy) film and a lower Al (alloy) film and an upper Mo (alloy) film. However, the first and second gate lines 121a, 121b and the storage electrode line 131 may be made of various metals or conductors.

[0134] The lateral sides of the first and second gate lines 121a, 121b and the storage electrode line 131 are inclined relative to a surface of the substrate, and the inclination angle thereof ranges about 30-80 degrees.

[0135] A gate insulating layer 140 that may be made of silicon nitride (SiNx) or silicon oxide (SiOx) is formed on the first and second gate lines 121a, 121b and the storage electrode line 131.

[0136] A plurality of first and second semiconductor islands 154a and 154b that may be made of hydrogenated amorphous silicon (abbreviated to "a-Si") or polysilicon are formed on the gate insulating layer 140. The first/second semiconductor islands 154a/154b are disposed on the first/second gate electrodes 124a/124b.

[0137] A plurality of pairs of ohmic contact islands 163b and 165b are formed on the semiconductor islands 154b, and a plurality of pairs of ohmic contact islands (not shown) are formed on the semiconductor islands 154a. The ohmic contact islands 163b and 165b may be made of n+ hydrogenated a-Si heavily doped with an n-type impurity such as phosphorous or they may be made of silicide.

[0138] The lateral sides of the semiconductor islands 154a and 154b and the ohmic contacts 163b and 165b are inclined relative to the surface of the substrate 110, and the inclination angles thereof may be in a range of about 30-80 degrees.

[0139] A plurality of data conductors including a plurality of data lines 171 and a plurality of pairs of first and second drain electrodes 175a and 175b are formed on the ohmic contacts 163b and 165b and the gate insulating layer 140.

[0140] The data lines 171 transmit data signals and extend substantially in the longitudinal direction to intersect the first

and second gate lines **121a** and **121b** and the storage electrode lines **131**. Each of the data lines **171** includes a plurality of bent portions projecting left or right near the intersections with the storage electrode lines **131**. Each of the bent portions includes a pair of oblique portions that are connected to each other to form a chevron and make an angle of about 45 degrees with the gate lines **121**.

[0141] Each data line **171** includes a plurality of first and second source electrodes **173a** and **173b** projecting toward the first and the second gate electrodes **124a** and **124b**, respectively, and an end portion **179** having a large area for contact with another layer or for connection to an external driving circuit. The data lines **171** may extend to be connected to a data driver **500** that may be integrated on the substrate **110**.

[0142] The first and the second drain electrodes **175a** and **175b** are separated from each other and separated from the data lines **171**. The first/second drain electrodes **175a/175b** are disposed opposite the first/second source electrodes **173a/173b** with respect to the first/second gate electrodes **124a/124b**. Each of the first/second drain electrodes **175a/175b** includes a wide end portion **177a/177b** and a narrow end portion. The wide end portion **177a/177b** overlaps a storage electrode line **131** and the narrow end portion partly enclosed by a first/second source electrode **173a/173b**.

[0143] A first/second gate electrode **124a/124b**, a first/second source electrode **173a/173b**, and a first/second drain electrode **175a/175b** along with a first/second semiconductor island **154a/154b** form a first/second TFT Qa/Qb having a channel formed in the first/second semiconductor island **154a/154b** disposed between the first/second source electrode **173a/173b** and the first/second drain electrode **175a/175b**.

[0144] The data conductors **171**, **175a** and **175b** may be made of refractory metal such as Cr, Mo, Ta, Ti, or alloys thereof. However, they may have a multilayered structure including a refractory metal film (not shown) and a low resistivity film (not shown). Good examples of the multilayered structure are a double-layered structure including a lower Cr/Mo (alloy) film and an upper Al (alloy) film and a triple-layered structure of a lower Mo (alloy) film, an intermediate Al (alloy) film, and an upper Mo (alloy) film. However, the data conductors **171**, **175a** and **175b** may be made of various metals or conductors.

[0145] The data conductors **171**, **175a** and **175b** have inclined edge profiles, and the inclination angles thereof range about 30-80 degrees.

[0146] The ohmic contacts **163b** and **165b** are interposed only between the underlying semiconductor islands **154a** and **154b** and the overlying data conductors **171**, **175a** and **175b** thereon and reduce the contact resistance therebetween. The semiconductor islands **154a** and **154b** include some exposed portions, which are not covered with the data conductors **171**, **175a** and **175b**, such as the portions located between the source electrodes **173** and the drain electrodes **175a** and **175b**.

[0147] A passivation layer **180** is formed on the data conductors **171**, **175a** and **175b** and the exposed portions of the semiconductor islands **154a** and **154b**. The passivation layer **180** may be made of inorganic or organic insulator and it may have a flat top surface. Examples of the inorganic

insulator include silicon nitride and silicon oxide. The organic insulator may have photosensitivity and a dielectric constant less than about 4.0. The passivation layer **180** may include a lower film of an inorganic insulator and an upper film of an organic insulator such that it provides the excellent insulating characteristics of the organic insulator while preventing the exposed portions of the semiconductor islands **154a** and **154b** from being damaged by the organic insulator.

[0148] The passivation layer **180** has a plurality of contact holes **182**, **185a** and **185b** exposing the end portions **179** of the data lines **171** and the first and the second drain electrodes **175a** and **175b**, respectively. The passivation layer **180** and the gate insulating layer **140** have a plurality of contact holes **181a** and **181b** exposing the end portions **129a** and **129b** of the gate lines **121a** and **121b**.

[0149] A plurality of pixel electrodes **191** and a plurality of contact assistants **81a**, **81b** and **82** are formed on the passivation layer **180**. They may be made of a transparent conductor such as ITO or IZO or a reflective conductor such as Ag, Al, Cr, or alloys thereof.

[0150] The pixel electrodes **191** have the structure shown in FIG. 3 and each pixel electrode **191** includes a pair of subpixel electrodes **191a** and **191b**. The subpixel electrodes **191a** and **191b** include cutouts **92a** and **92b**.

[0151] The data lines **171**, in particular, the bent portions of the data lines **171** extend along some of the bent edges of the pixel electrodes **191**. Therefore, the electric field generated between the data lines **171** and the subpixel electrodes **191a** and **191b** has a horizontal component substantially parallel to the horizontal component of the primary electric field such that the determination of the tilt direction of the LC molecules is enhanced. In addition, the aperture ratio is increased.

[0152] The storage electrode lines **131**, the expansions **177a** and **177b**, of the drain electrodes **175a** and **175b**, and the contact holes **185a** and **185b** lie on straight lines connecting bent points of the subpixel electrodes **191a** and **191b**. The straight lines connecting the bent points of the subpixel electrodes **191a** and **191b** form boundaries of the above-described sub-areas, and thus this configuration can cover texture that may be generated by the disorder of the LC molecules near the boundaries of the sub-areas, thereby improving the aperture ratio.

[0153] Since other features of the pixel **191** are described above with reference to FIG. 3, the detailed description thereof will be omitted.

[0154] The first/second subpixel electrodes **191a/191b** are physically and electrically connected to the first/second drain electrodes **175a/175b** through the contact holes **185a/185b** such that the first/second subpixel electrode **191a/191b** receives data voltages from the first/second drain electrodes **175a/175b**. A first/second subpixel electrode **191a/191b** and the common electrode **270** form a first/second LC capacitor C1ca/C1cb, which stores applied voltages after the TFT turns off.

[0155] A first/second storage capacitor Csta/Cstb for enhancing the charge storing capacity are formed by overlapping an expansion **177a/177b** of a first/second drain

electrode **175a/175b** connected to a first/second subpixel electrode **191a/191a** with a storage electrode line **131**.

[0156] The contact assistants **81a**, **81b** and **82** are connected to the end portions **129a** and **129b** of the gate lines **121a** and **121b** and the end portions **179** of the data lines **171** through the contact holes **181a**, **181b** and **182**, respectively. The contact assistants **81a**, **81b** and **82** protect the end portions **129a**, **129b** and **179** and enhance the adhesion between the end portions **129**, **129b** and **179** and external devices.

[0157] The description of the upper panel **200** follows with reference to FIGS. 9-11.

[0158] A light blocking member **220** referred to as a black matrix is formed on an insulating substrate **210** such as transparent glass or plastic. The light blocking member **220** includes a plurality of linear portions facing the boundaries of the pixel electrodes **191** on the lower panel **100** and a plurality of widened portions facing the TFTs **Qa** and **Qb** on the lower panel **100**. The light blocking member **220** blocks light leakage near the pixel electrodes **191** and the TFTs **Qa** and **Qb** and may have various shapes.

[0159] A plurality of color filters **230** are also formed on the substrate **210** and the light blocking member **220**. The color filters **230** are disposed substantially in the areas enclosed by the light blocking member **220** and the color filters **230** may extend substantially in the longitudinal direction along the pixel electrodes **191**. Each of the color filters **230R** represents one of the three primary colors, such as red, green, and blue.

[0160] An overcoat **250** is formed on the color filters **230** and the light blocking member **220**. The overcoat **250** may be made of an (organic) insulator, and it prevents the color filters **230** from being exposed and provides a flat surface. The overcoat **250** may be omitted.

[0161] A common electrode **270** is formed on the overcoat **250**. The common electrode **270** may be made of transparent conductive material such as ITO and IZO and has a plurality of sets of cutouts **71a** and **71b** that are described above with reference to FIG. 3.

[0162] The number of the cutouts **71a** and **71b** may be varied depending on the design factors, and the light blocking member **220** may also overlap the cutouts **71a** and **71b** to block the light leakage through the cutouts **71a** and **71b**.

[0163] Alignment layers **11** and **21** that may be homeotropic are coated on inner surfaces of the panels **100** and **200**.

[0164] Polarizers **12** and **22** are provided on outer surfaces of the panels **100** and **200** so that their polarization axes may be crossed and the polarization axes may make an angle of about 45 degrees with the bent edges of the subpixel electrodes **191a** and **191b** for increasing light efficiency. One of the polarizers **12** and **22** may be omitted when the LCD is a reflective LCD.

[0165] The LCD may further include at least one retardation film (not shown) for compensating the retardation of the LC layer **3**. The LCD may further include a backlight unit (not shown) supplying light to the LC layer **3** through the polarizers **12** and **22**, the retardation film, and the panels **100** and **200**.

[0166] It is preferable that the LC layer **3** has negative dielectric anisotropy and is subjected to a vertical alignment.

[0167] The shapes and the arrangements of the cutouts **71a**, **71b**, **92a** and **92b** may be modified.

[0168] At least one of the cutouts **71a**, **71b**, **92a** and **92b** can be substituted for by protrusions (not shown) or depressions (not shown). The protrusions may be made of organic or inorganic material and disposed on or under the field generating electrodes **191** or **270**.

[0169] Another example of an LC panel assembly shown in FIG. 10 will be described in detail with reference to FIG. 12.

[0170] FIG. 12 is another exemplary sectional view of the LC panel assembly shown in FIG. 10 taken along line XI-XI.

[0171] Referring to FIG. 12, an LC panel assembly according to this embodiment includes a lower panel **100**, an upper panel **200** facing the lower panel **100**, an LC layer **3**, and a pair of polarizers **12** and **22**.

[0172] Layered structures of the LC panel assembly according to this exemplary embodiment are similar to those shown in FIG. 11.

[0173] Regarding the lower panel **100**, gate conductors including a plurality of first and second gate lines **121a** and **121b** and a plurality of storage electrode lines **131** are formed on a substrate **110**. The first and the second gate lines **121a** and **121b** include first and second gate electrodes **124a** and **124b** and end portions **129a** and **129b**, respectively. A gate insulating layer **140**, a plurality of semiconductor islands **154a** and **154b**, and a plurality of ohmic contacts **163b** and **165b** are sequentially formed on the first and second gate lines **121a**, **121b** and the storage electrode lines **131**. Data conductors including a plurality of data lines **171** and a plurality of first and second drain electrodes **175a** and **175b** are formed on the ohmic contacts **163b** and **165b** and the gate insulating layer **140**. The data lines **171** include first and second source electrodes **173a** and **173b** and end portions **179**, and the drain electrodes **175a** and **175b** include wide end portions **177a** and **177b**. A passivation layer **180** is formed on the data conductors **171**, **175a** and **175b**, the gate insulating layer **140**, and exposed portions of the semiconductor islands **154a** and **154b**. A plurality of contact holes **181a**, **181b**, **182**, **185a** and **185b** are provided at the passivation layer **180** and the gate insulating layer **140**. A plurality of pixel electrodes **191** including subpixel electrodes **191a** and **191b** and having cutouts **92a** and **92b** and a plurality of contact assistants **81a**, **81b** and **82** are formed on the passivation layer **180**, and an alignment layer **11** is coated thereon.

[0174] Regarding the upper panel **200**, a light blocking member **220**, an overcoat **250**, a common electrode **270** having a plurality of cutouts **71a** and **71b**, and an alignment layer **21** are formed on an insulating substrate **210**.

[0175] Unlike the LC panel assembly shown in FIG. 11, the lower panel **100** shown in FIG. 12 includes a plurality of color filters **230** disposed under the passivation layer **180**, while the upper panel **200** has no color filter.

[0176] The color filters **230** extend along a longitudinal direction while being bent periodically and are not provided in peripheral areas where the end portions **129a** and **129b** of

the first and second gate lines **121a** and **121b** and the end portions **179** of the data lines **171** are disposed. The color filters **230** have through holes **235** larger than the contact holes **185a** so that the contact holes **185a** may pass through the through holes **235**.

[0177] Adjacent color filters **230** may overlap each other near the boundaries of the pixel electrodes **191** to block any light leakage therebetween, so as to act like the light blocking member **220**. In this case, the light blocking member **220** disposed on the upper panel **200** may be omitted to simplify the manufacturing process.

[0178] Another passivation layer (not shown) may be formed under the color filters **230**.

[0179] The overcoat **250** on the upper panel **200** may be omitted.

[0180] Many of the above-described features of the LC panel assembly shown in FIG. **11** may be applicable to the LC panel assembly shown in FIG. **12**.

[0181] Another example of an LC panel assembly shown in FIG. **7** will be described in detail with reference to FIGS. **13**, **14**, **15** and **16**.

[0182] FIG. **13** is a layout view of a lower panel for an LC panel assembly according to an exemplary embodiment of the present invention, FIG. **14** is a layout view of an upper panel for an LC panel assembly according to another embodiment of the present invention, FIG. **15** is a layout view of an LC panel assembly including the lower panel shown in FIG. **13** and the upper panel shown in FIG. **14**, and FIG. **16** is a sectional view of the LC panel assembly shown in FIG. **15** taken along lines XVI-XVII-XVI".

[0183] Referring to FIGS. **13-16**, an LC panel assembly according to this exemplary embodiment includes a lower panel **100**, an upper panel **200** facing the lower panel **100**, an LC layer **3**, and a pair of polarizers **12** and **22**.

[0184] Layered structures of the LC panel assembly according to this embodiment are similar to those shown in FIGS. **8-11**.

[0185] Regarding the lower panel **100**, gate conductors including a plurality of first and second gate lines **121a** and **121b** and a plurality of storage electrode lines **131** are formed on a substrate **110**. The first and the second gate lines **121a** and **121b** include first and second gate electrodes **124a** and **124b** and end portions **129a** and **129b**, respectively. A gate insulating layer **140**, a plurality of semiconductor members **154a** and **154b**, and a plurality of ohmic contacts **163b** and **165b** are sequentially formed on the first and second gate lines **121a**, **121b** and the storage electrode lines **131**. Data conductors including a plurality of data lines **171** and a plurality of first and second drain electrodes **175a** and **175b** are formed on the ohmic contacts **163b** and **165b**. The data lines **171** include first and second source electrodes **173a** and **173b** and end portions **179**, and the drain electrodes **175a** and **175b** include wide end portions **177a** and **177b**. A passivation layer **180** is formed on the data conductors **171**, **175a** and **175b**, the gate insulating layer **140**, and exposed portions of the semiconductor members **154a** and **154b**. A plurality of contact holes **181a**, **181b**, **182**, **185a** and **185b** are provided at the passivation layer **180** and the gate insulating layer **140**. A plurality of pixel electrodes **191** including subpixel electrodes **191a** and **191b** and having

cutouts **92a** and **92b** and a plurality of contact assistants **81a**, **81b** and **82** are formed on the passivation layer **180**, and an alignment layer **11** is formed thereon.

[0186] Regarding the upper panel **200**, a light blocking member **220**, a plurality of color filters **230**, an overcoat **250**, a common electrode **270** having a plurality of cutouts **71a** and **71b**, and an alignment layer **21** are formed on an insulating substrate **210**.

[0187] Unlike the LC panel assembly shown in FIGS. **8-11**, the arrangement of the pixel electrodes **191** and the subpixel electrodes **191a** and **191b** is substantially the same that shown in FIG. **4**. As described above, the pixel electrodes **191** adjacent in the column direction shown in FIG. **3** form a straighter line than those shown in FIG. **3**, and, thus, the configuration shown in FIGS. **13-16** is more advantageous in displaying a longitudinal line as compared with that shown in FIGS. **8-11**.

[0188] The data lines pass through about the center of a first or a second subpixel electrode **191a** or **191b**. In particular, bent portions of the data lines **171** overlap the cutouts **71a** and **71b** of the common electrode **270** instead of extending along the boundaries of the pixel electrodes **191**, and this configuration also gives substantially the same advantage as that in a case where the data lines **171** extend along the boundaries of the pixel electrodes **191**.

[0189] First/Second TFTs Qa/Qb are disposed right/left to the data lines **171**. This configuration shortens the length of the second drain electrodes **175b** as compared with that shown in FIGS. **8-12** to further increase the aperture ratio.

[0190] In addition, the semiconductor members **154a** and **154b** extend along the data lines **171** and the drain electrodes **175a** and **175b** to form semiconductor stripes **151**, and the ohmic contacts **163b** extend along the data lines **171** to form ohmic contact stripes **161**. The semiconductor stripes **151** have almost the same planar shapes as the data conductors **171**, **175a** and **175b** as well as the underlying ohmic contacts **161** and **165b**.

[0191] A manufacturing method of the lower panel according to an exemplary embodiment of the present invention simultaneously forms the data conductors **171**, **175a** and **175b**, the semiconductor members **151**, and the ohmic contacts **161** and **165b** using one photolithography process.

[0192] A photoresist pattern for the photolithography process has a position-dependent thickness, and in particular, it has first and second portions with a decreased thickness. The first portions are located on wire areas that will be occupied by the data conductors **171**, **175a** and **175b** and the second portions are located on channel areas of TFTs Qa and Qb.

[0193] The position-dependent thickness of the photoresist is obtained by several techniques, for example, by providing translucent areas on the exposure mask as well as light transmitting transparent areas and light blocking opaque areas. The translucent areas may have a slit pattern, a lattice pattern, or a thin film(s) with intermediate transmittance or intermediate thickness. When using a slit pattern, it is preferable that the width of the slits or the distance between the slits is smaller than the resolution of a light exposer used for the photolithography. Another example is to use reflowable photoresist. In detail, once a photoresist

pattern made of a reflowable material is formed by using a normal exposure mask with transparent areas and opaque areas, it is subject to reflow process to flow onto areas without the photoresist, thereby forming thin portions.

[0194] As a result, the manufacturing process is simplified by omitting a photolithography step.

[0195] Many of the above-described features of the LC panel assembly shown in FIGS. 8-11 may be applicable to the LC panel assembly shown in FIGS. 13-16.

[0196] A structure of an LC panel assembly according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 17 and 18 as well as FIGS. 1, 2 and 4.

[0197] FIG. 17 is an equivalent circuit diagram of signal lines and a pixel according to an exemplary embodiment of the present invention.

[0198] The LC panel assembly shown in FIG. 17 includes a plurality of signal lines and a plurality of pixels PX connected thereto. The signal lines include a plurality of gate lines GL, a plurality of pairs of data lines DL_a and DL_b, and a plurality of storage electrode lines SL.

[0199] Each pixel PX includes a pair of subpixels PX_c and PX_d. Each subpixel PX_c/PX_d includes a switching element Q_c/Q_d connected to one of the gate lines GL and one of the data lines DL_a and DL_b, an LC capacitor Cl_{cc}/Cl_{cd} coupled to the switching element Q_c/Q_d, and a storage capacitor C_{stc}/C_{std} connected between the switching element Q_c/Q_d and the storage electrode line SL.

[0200] The switching element Q_c/Q_d such as a thin film transistor (TFT) is provided on the lower panel 100 and has three terminals: a control terminal connected to a gate line GL; an input terminal connected to a data line DL_a/DL_b; and an output terminal connected to the LC capacitor Cl_{cc}/Cl_{cd}.

[0201] Since the LC capacitor Cl_{cc}/Cl_{cd}, the storage capacitors C_{stc} and C_{std}, and the operation of the LCD including the panel assembly shown in FIG. 17, etc., are substantially the same as those described above, a detailed description thereof will be omitted.

[0202] However, it is noted that the two pixels PX_c and PX_d forming a pixel PX shown in FIG. 17 are supplied with data voltages at the same time unlike those shown in FIG. 7. An example of an LC panel assembly shown in FIG. 17 according to an exemplary embodiment of the present invention will be described in detail with reference to FIG. 18.

[0203] FIG. 18 is a layout view of an LC panel assembly according to an embodiment of the present invention.

[0204] Referring to FIG. 18, an LC panel assembly according to an exemplary embodiment of the present invention includes a lower panel (not shown), an upper panel (not shown) facing the lower panel, and an LC layer (not shown).

[0205] Layered structures of the LC panel assembly according to this embodiment are almost the same as those shown in FIGS. 13-16.

[0206] Regarding the lower panel, gate conductors including a plurality of gate lines 121 and a plurality of storage electrode lines 131 are formed on a substrate (not shown).

Each of the gate lines 121 includes first and second gate electrodes 124_c 124_d and an end portion 129. A gate insulating layer (not shown) is formed on the gate conductors 121 and the storage electrode lines 131, and a plurality of pairs of semiconductor islands 154_c and 154_d are formed on the gate insulating layer. A plurality of ohmic contacts (not shown) are formed on the semiconductor islands 154_c and 154_d. Data conductors including a plurality of pairs of first and second data lines 171_a and 171_b and a plurality of pair of first and second drain electrodes 175_c and 175_d are formed on the ohmic contacts and the gate insulating layer. Each of the first/second data lines 171_a/171_b includes a plurality of first/second source electrodes 173_c/173_d and an end portion 179_a/179_b. Each of the first/second drain electrode 175_c/175_d includes a wide end portion 177_c/177_d. A passivation layer (not shown) is formed on the data conductors 171_a, 171_b, 175_c and 175_d, the gate insulating layer, and exposed portions of the semiconductor islands 154_c and 154_d. A plurality of contact holes 181, 182_a, 182_b, 185_c and 185_d are provided at the passivation layer and the gate insulating layer. A pixel electrode 191 including first and second subpixel electrodes 191_c and 191_d and a plurality of contact assistants 81, 82_a and 82_b are formed on the passivation layer. The first subpixel electrode 191_c has a cutout 92_c, and the second subpixel electrode 191_d has a cutout 92_d. An alignment layer (not shown) is formed on the pixel electrodes 191 and the passivation layer.

[0207] Regarding the upper panel, a light blocking member (not shown), a color filter (not shown), an overcoat (not shown), a common electrode (not shown) having a plurality of cutouts 71_c and 72_d, and an alignment layer (not shown) are formed on an insulating substrate (not shown).

[0208] However, the number of the gate lines 121 in the LC panel assembly shown in FIG. 18 is half that in the LC panel assembly shown in FIGS. 13-16, and the number of the data lines 171_a and 171_b in the LC panel assembly shown in FIG. 18 is twice that in the LC panel assembly shown in FIGS. 13-16. Furthermore, first and second TFTs Q_c and Q_d coupled to first and second subpixel electrodes 191_c and 191_d forming a pixel electrode 191 are connected to the same gate line 121 and different data lines 171_a and 171_b.

[0209] Curved portions of the data lines 171_a and 171_b are disposed near the boundaries between the first subpixel electrodes 191_c and the second subpixel electrodes 191_d. The first and the second TFTs Q_c and Q_d are disposed to the left of the first and the second data lines 171_a and 171_b, respectively.

[0210] Many of the above-described features of the LC panel assembly shown in FIGS. 13-16 may be applicable to the LC panel assembly shown in FIG. 18.

[0211] Now, structures of LC panel assemblies according to exemplary embodiments of the present invention will be described in detail with reference to FIGS. 19, 20, 21, 22 and 23 as well as FIGS. 1-3.

[0212] FIG. 19 is an equivalent circuit diagram of the signal lines and a pixel PX according to an exemplary embodiment of the present invention.

[0213] The LC panel assembly shown in FIG. 19 includes a plurality of signal lines and a plurality of pixels PX

connected thereto. The signal lines include a plurality of gate lines GL and a plurality of data lines DL.

[0214] Each pixel PX includes a pair of first and second subpixels PXe and PXf and a coupling capacitor Ccp connected between the first subpixel PXe and the second subpixel PXf.

[0215] The first subpixel PXe includes a switching element Q connected to one of the gate lines GL and one of the data lines DL, a first LC capacitor Clce coupled to the switching element Q, and a storage capacitor Cste connected to the switching element Q. The second subpixel PXf includes a second LC capacitor Clcf coupled to the coupling capacitor Ccp.

[0216] The switching element Q such as a thin film transistor (TFT) is provided on the lower panel 100 and has three terminals: a control terminal connected to a gate line GL; an input terminal connected to a data line DL; and an output terminal connected to the LC capacitor Clce, the storage capacitor Cste, and the coupling capacitor Ccp.

[0217] The switching element Q transmits data voltages from the data line DL in response to gate signals from the gate line GL to the first LC capacitor Clce and the coupling capacitor Ccp, and the coupling capacitor Ccp converts the magnitude of the data voltage and supplied to the second LC capacitor Clcf.

[0218] It is assumed that the common voltage Vcom is applied to the storage capacitor Cste and the capacitor Clce, Cste, Clcf or Ccp and the capacitance thereof are denoted by the same numerals, a voltage Ve stored in the first LC capacitor Clce and a voltage Vf stored in the second LC capacitor Clcf satisfies:

$$Vf = Vex \left[\frac{Ccp}{Ccp + Clcf} \right].$$

[0219] Since $Ccp / (Ccp + Clcf)$ is smaller than one, the voltage Vf stored in the second LC capacitor Clcf is smaller than the voltage Ve stored in the first LC capacitor Clce. The relation is also satisfied even though the voltage applied to the storage capacitor Cste is not the common voltage Vcom.

[0220] The desired ratio of the voltages Ve and Vf can be obtained by adjusting the capacitance of the coupling capacitor Ccp.

[0221] An example of an LC panel assembly shown in FIG. 19 according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 20 and 21.

[0222] FIG. 20 is a layout view of an LC panel assembly according to an exemplary embodiment of the present invention, and FIG. 21 is a sectional view of the LC panel assembly shown in FIG. 20 taken along line XXI-XXI.

[0223] An LC panel assembly includes a lower panel 100, an upper panel 200 facing the lower panel 100, a liquid crystal layer 3, and a pair of polarizers 12 and 22.

[0224] Layered structures of the LC panel assembly according to these embodiments are almost the same as those shown in FIGS. 8-11.

[0225] Regarding the lower panel 100, a plurality of gate lines 121 and a plurality of storage electrode lines 131 are formed on a substrate 110. Each of the gate lines 121 includes a plurality of gate electrodes 124 and an end portion

129. A gate insulating layer 140, a plurality of semiconductor islands 154, and a plurality of pairs of ohmic contacts 163 and 165 are sequentially formed on the gate lines 121. Data conductors including a plurality of data lines 171 and a plurality of drain electrodes 175 are formed on the ohmic contacts 163 and 165 and the gate insulating layer 140. Each of the data lines 171 includes a plurality of source electrodes 173 and an end portion 179, and each of the drain electrodes 175 includes an expansion 177. A passivation layer 180 is formed on the data conductors 171 and 175, the gate insulating layer 140, and exposed portions of the semiconductor islands 154. A plurality of contact holes 181, 182 and 185 are provided at the passivation layer 180 and the gate insulating layer 140. A plurality of pixel electrodes 191 including subpixel electrodes 191e and 191f having cutouts 92e and 92f are formed on the passivation layer 180. An alignment layer 11 is formed on the pixel electrodes 191 and the passivation layer 180.

[0226] Regarding the upper panel 200, a light blocking member 220, a plurality of color filters 230, an overcoat 250, a common electrode 270 having cutouts 71e and 71f, and an alignment layer 21 are formed on an insulating substrate 210.

[0227] Unlike the LC panel assembly shown in FIGS. 8-11, the second subpixel electrodes 191f are electrically floating, while the first subpixel electrodes 191e are connected to the drain electrodes 175.

[0228] Instead, each of the expansions 177 of the drain electrodes 175 extends along a storage electrode line 131 under a second subpixel electrode 191f to overlap the second subpixel electrode 191f. Therefore, the first subpixel electrode 191e and the second subpixel electrode 191f are capacitively coupled to each other to form a coupling capacitor Ccp.

[0229] The passivation layer 180 includes a lower film 180p and an upper film 180q. The lower film 180p may be made of an inorganic insulator such as silicon nitride or silicon oxide, and the upper film 180q may be made of an organic insulator. The organic insulator may have photosensitivity and a dielectric constant less than about 4.0 and may provide a flat surface. The passivation layer 180 may have a single layer structure that may be made of inorganic or organic insulator.

[0230] The upper film 180q has a plurality of openings 187 exposing the lower film 180p and disposed on the expansions 177 of the drain electrodes 175 under the second subpixel electrodes 191f. Therefore, the second subpixel electrodes 191f overlap the expansions 177 in the openings 187 with only the lower film 180p being interposed and, thus, the capacitance of the coupling capacitors Ccp is large as compared with a structure interposing both the lower film 180q and the upper film 180p, thereby increasing the aperture ratio.

[0231] Many of the above-described features of the LC panel assembly shown in FIGS. 8-11 may be applicable to the LC panel assembly shown in FIGS. 20 and 21.

[0232] Another example of an LC panel assembly shown in FIG. 19 according to an exemplary embodiment of the present invention will be described in detail with reference to FIGS. 22 and 23.

[0233] FIG. 22 is a layout view of an LC panel assembly according to an exemplary embodiment of the present invention, and FIG. 23 is a sectional view of the LC panel assembly shown in FIG. 22 taken along line XXIII-XXIII.

[0234] An LC panel assembly includes a lower panel 100, an upper panel 200 facing the lower panel 100, a liquid crystal layer 3, and a pair of polarizers 12 and 22.

[0235] Layered structures of the LC panel assembly according to these embodiments are almost the same as those shown in FIGS. 20 and 21.

[0236] Regarding the lower panel 100, a plurality of gate lines 121 and a plurality of storage electrode lines 131 are formed on a substrate 110. Each of the gate lines 121 includes a plurality of gate electrodes 124 and an end portion 129. A gate insulating layer 140, a plurality of semiconductor islands 154, and a plurality of pairs of ohmic contacts (not shown) are sequentially formed on the gate lines 121. Data conductors including a plurality of data lines 171 and a plurality of drain electrodes 175 are formed on the ohmic contacts and the gate insulating layer 140. Each of the data lines 171 includes a plurality of source electrodes 173 and an end portion 179. A passivation layer 180 including a lower film 180p and an upper film 180q is formed on the data conductors 171 and 175, the gate insulating layer 140, and exposed portions of the semiconductor islands 154. A plurality of contact holes 181, 182, 185 and 186 are provided at the passivation layer 180 and the gate insulating layer 140. A plurality of pixel electrodes 191 including subpixel electrodes 191e and 191f having cutouts 92e and 92f are formed on the passivation layer 180. An alignment layer 11 is formed on the pixel electrodes 191 and the passivation layer 180.

[0237] Regarding the upper panel 200, a light blocking member 220, a plurality of color filters 230, an overcoat 250, a common electrode 270 having cutouts 71e and 71f, and an alignment layer 21 are formed on an insulating substrate 210.

[0238] Unlike the LC panel assembly shown in FIGS. 20 and 21, a plurality of pairs of capacitive electrodes 136 are formed on the substrate 110. The capacitive electrodes 136 are made of the same layer as the gate lines 121 and the storage electrode lines 131 and are spaced apart from the gate lines 121 and the storage electrode lines 131. A pair of the capacitive electrodes 136 are symmetrically arranged with respect to a storage electrode line 131 and extend along a cutout 71f of the common electrode 270. The capacitive electrodes 136 are connected to the second subpixel electrodes 191f through the contact holes 186.

[0239] Each of the drain electrodes 175 includes an expansion 177 and a pair of branches 176 branching from the expansion 177. The expansion 177 extends along a storage electrode line 131 to a bent point of a cutout 71f, and the branches extend from an end of the expansion 177 along a pair of capacitive electrodes 136 to overlap the capacitive electrodes 136. The branches 176 have a plurality of through holes 176H larger than the contact holes 186 so that the contact holes 186 may pass through the through holes 176H.

[0240] The branches 176 and the capacitive electrodes 136 form a coupling capacitor Ccp, and a second subpixel electrode 191f and a portion of the expansion 177 disposed thereunder also contribute to the coupling capacitance.

[0241] Many of the above-described features of the LC panel assembly shown in FIGS. 20 and 21 may be applicable to the LC panel assembly shown in FIGS. 22 and 23.

[0242] As described above, the above-described exemplary embodiments of the present invention provide widths of the sub-areas suitable for various pixel sizes of the LCD. The exemplary embodiments give balanced color configuration and facilitate the display of longitudinal lines and oblique lines. In addition, the exemplary embodiments further improve the aperture ratio, the lateral visibility, and the reference viewing angle. While the present invention has been described in detail with reference to exemplary embodiments, those skilled in the art will appreciate that various modifications and substitutions can be made thereto without departing from the spirit and scope of the present invention as set forth in the appended claims.

What is claimed is:

1. A liquid crystal display comprising:

- a first substrate;
- a second substrate;
- a plurality of first signal lines formed on the first substrate;
- a plurality of second signal lines formed on the first substrate;
- a first subpixel electrode formed on the first substrate and having a bent edge;
- a second subpixel electrode formed on the first substrate, having a bent edge, and being disposed adjacent the first subpixel electrode in a first direction;
- a third subpixel electrode formed on the first substrate, having a bent edge, and being disposed adjacent the second subpixel electrode in a second direction;
- a fourth subpixel electrode formed on the first substrate, having a bent edge, and being disposed adjacent the third subpixel electrode in the first direction and adjacent the first subpixel electrode in the second direction;
- a common electrode formed on the second substrate and facing the first to the fourth subpixel electrodes on the first substrate; and
- a plurality of switching elements, each of the switching elements being coupled to one of the first signal lines, to one of the second signal lines, and to one of the first to the fourth subpixel electrodes,

wherein the bent edge of the second subpixel electrode is longer than the bent edge of the first subpixel electrode,

the bent edge of the fourth subpixel electrode is longer than the bent edge of the third subpixel electrode, and

the fourth subpixel electrode has an edge contacting an edge of the second subpixel electrode.

2. The liquid crystal display of claim 1, wherein first-directional lengths of the first to the fourth subpixel electrodes are substantially equal to each other.

3. The liquid crystal display of claim 2, wherein a length of the bent edge of each of the second and the fourth subpixel electrodes is about twice a length of the bent edge of each of the first and the third subpixel electrodes.

4. The liquid crystal display of claim 1, further comprising a tilt direction determining member formed at the common electrode.

5. The liquid crystal display of claim 4, wherein the tilt direction determining member comprises a cutout having a bent portion passing through one of the first to the fourth subpixel electrodes and extending substantially parallel to the bent edge of the one of the first to the fourth subpixel electrodes.

6. The liquid crystal display of claim 5, wherein a distance between the bent portion of the cutout and the bent edge of the one of the first to the fourth subpixel electrodes is equal to about 20-35 microns.

7. The liquid crystal display of claim 1, wherein the first subpixel electrode and the second subpixel electrode are supplied with different voltages obtained from a single image information.

8. The liquid crystal display of claim 1, wherein the first subpixel electrode and the fourth subpixel electrode are supplied with different voltages obtained from a single image information.

9. The liquid crystal display of claim 1, wherein the switching elements comprise a first thin film transistor coupled to the first subpixel electrode, and a second thin film transistor coupled to the second or the fourth subpixel electrode, and the first and the second thin film transistors are connected to two different ones of the first signal lines and to a single one of the second signal lines.

10. The liquid crystal display of claim 9, wherein the first and the second thin film transistors turn on to transmit signals from the single one of the second signal lines in response to the two different signals of the first signal lines.

11. The liquid crystal display of claim 9, wherein the first and the second thin film transistors turn on to transmit signals from the two different signals of the first signal lines in response to a signal from the single one of the second signal lines.

12. A liquid crystal display comprising:

a substrate;

a pixel electrode disposed on the substrate and including a first subpixel electrode and a second subpixel electrode; and

a common electrode facing the pixel electrode,

wherein the first subpixel electrode has a pair of bent edges substantially parallel to each other,

the second subpixel electrode has a pair of bent edges substantially parallel to each other, and

the second subpixel electrode has a height greater than a height of the first subpixel electrode.

13. The liquid crystal display of claim 12, wherein the first subpixel electrode and the second subpixel electrode are adjacent in a length direction.

14. The liquid crystal display of claim 12, wherein the first subpixel electrode and the second subpixel electrode are adjacent in a height direction.

15. The liquid crystal display of claim 14, wherein a convexity and a concavity of the bent edges of the first and the second subpixel electrodes are reversed relative to each other.

16. The liquid crystal display of claim 12, wherein the first subpixel electrode has a length substantially equal to a length of the second subpixel electrode.

17. The liquid crystal display of claim 16, wherein the height of the second subpixel electrode is about twice the height of the first subpixel electrode.

18. The liquid crystal display of claim 12, wherein each of the bent edges of the first and second subpixel electrodes has a bent point, and each of the first and the second subpixel electrodes has a symmetry with respect to a straight line connecting the bent points.

19. The liquid crystal display of claim 12, wherein each of the pairs of bent edges comprise a concave edge and a convex edge, and the convex edge of the first subpixel electrode is adjacent to the concave edge of the second subpixel electrode or the concave edge of the first subpixel electrode is adjacent the convex edge of the second subpixel electrode.

20. The liquid crystal display of claim 12, wherein each of the pairs of bent edges include a concave edge and a convex edge, the concave edge of the first subpixel electrode is connected to the convex edge of the second subpixel electrode, and the convex edge of the first subpixel electrode is connected to the concave edge of the second subpixel electrode.

21. The liquid crystal display of claim 12, further comprising a tilt direction determining member formed at the common electrode.

22. The liquid crystal display of claim 21, wherein the tilt direction determining member comprises a cutout comprising a bent portion passing through the first or the second subpixel electrode and extending substantially parallel to the bent edges of the first or the second subpixel electrode.

23. The liquid crystal display of claim 22, wherein a distance between the bent portion of the cutout and one of the bent edges of the first or the second subpixel electrodes adjacent to the bent portion is equal to about 20-35 microns.

24. The liquid crystal display of claim 12, wherein the first subpixel electrode and the second subpixel electrode have different respective voltages.

25. The liquid crystal display of claim 24, wherein the first subpixel electrode and the second subpixel electrode are supplied with different respective voltages obtained from a single image information.

26. The liquid crystal display of claim 24, further comprising:

a first thin film transistor coupled to the first subpixel electrode;

a second thin film transistor coupled to the second subpixel electrode;

a first signal line coupled to the first thin film transistor;

a second signal line coupled to the second thin film transistor; and

a third signal line coupled to the first and the second thin film transistors and intersecting the first and the second signal lines.

27. The liquid crystal display of claim 26, wherein the first thin film transistor turns on to transmit a signal from the third signal line in response to a signal from the first signal

line, and the second thin film transistor turns on to transmit a signal from the third signal line in response to a signal from the second signal line.

28. The liquid crystal display of claim 26, wherein the first thin film transistor and the second thin film transistor are disposed opposite each other with respect to the third signal line.

29. The liquid crystal display of claim 26, wherein the first thin film transistor turns on to transmit a signal from the first signal line in response to a signal from the third signal line, and the second thin film transistor turns on to transmit a signal from the second signal line in response to a signal from the third signal line.

30. The liquid crystal display of claim 26, further comprising a fourth signal line extending in a straight line connecting bent points of the bent edges of the first and the second subpixel electrodes.

31. The liquid crystal display of claim 30, wherein each of the first and the second thin film transistors comprises a drain electrode overlapping the fourth signal line.

32. The liquid crystal display of claim 12, wherein the first subpixel electrode and the second subpixel electrode are capacitively coupled to each other.

33. The liquid crystal display of claim 32, further comprising:

a thin film transistor coupled to the first subpixel electrode;

a first signal line coupled to the thin film transistor; and

a second signal line coupled to the thin film transistor and intersecting the first signal line.

* * * * *

专利名称(译)	液晶显示器		
公开(公告)号	US20070013854A1	公开(公告)日	2007-01-18
申请号	US11/485579	申请日	2006-07-12
[标]申请(专利权)人(译)	三星电子株式会社		
申请(专利权)人(译)	SAMSUNG ELECTRONICS CO. , LTD.		
当前申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
[标]发明人	YOO SEUNG HOO SON JONG HO DO HEE WOOK KIM HYUN WUK CHANG HAK SUN UM YOON SUNG		
发明人	YOO, SEUNG-HOO SON, JONG-HO DO, HEE-WOOK KIM, HYUN-WUK CHANG, HAK-SUN UM, YOON-SUNG		
IPC分类号	G02F1/1343		
CPC分类号	G02F1/134336 G02F2201/52 G02F2001/134345 G02F1/13624		
优先权	1020050064488 2005-07-15 KR		
其他公开文献	US7502089		
外部链接	Espacenet USPTO		

摘要(译)

液晶显示器包括：基板；像素电极，设置在基板上，具有第一子像素电极和第二子像素电极；面对像素电极的公共电极，其中第一子像素电极具有基本上彼此平行的一对弯曲边缘，第二子像素电极具有基本上彼此平行的一对弯曲边缘，第二子像素电极具有高度大于第一子像素电极的高度。

