



US008692750B2

(12) **United States Patent**
Lee

(10) **Patent No.:** **US 8,692,750 B2**
(45) **Date of Patent:** **Apr. 8, 2014**

(54) **LIQUID CRYSTAL DISPLAY DEVICE
HAVING GOLDD TYPE TFT AND LDD TYPE
TFT AND METHOD OF MAKING SAME**

(75) Inventor: **Seok-Woo Lee**, Gyeonggi-Do (KR)

(73) Assignee: **LG Display Co., Ltd.**, Seoul (KR)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 2139 days.

(21) Appl. No.: **11/139,980**

(22) Filed: **May 31, 2005**

(65) **Prior Publication Data**

US 2005/0266595 A1 Dec. 1, 2005

(30) **Foreign Application Priority Data**

May 31, 2004 (KR) 10-2004-0039340

(51) **Int. Cl.**
G09G 3/36 (2006.01)
G06F 3/041 (2006.01)

(52) **U.S. Cl.**
USPC **345/87**; 345/178

(58) **Field of Classification Search**
USPC 345/87, 88, 89, 90, 92, 94, 95, 96, 98,
345/99, 100, 103, 204, 205, 206, 207, 208,
345/209, 210, 211, 214, 690, 691, 692,
345/693; 349/33, 34, 36, 37, 38, 39, 41, 42,
349/43, 44, 45, 46, 47, 48, 49, 50, 51, 52,
349/53, 54, 55; 257/128, 333, 336, 344,
257/346, 366, 387, 388, 408, 900

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,198,379	A *	3/1993	Adan	438/151
5,485,019	A *	1/1996	Yamazaki et al.	257/57
5,521,107	A *	5/1996	Yamazaki et al.	438/303
5,821,559	A *	10/1998	Yamazaki et al.	257/57
5,949,107	A *	9/1999	Zhang	257/347
6,180,957	B1 *	1/2001	Miyasaka et al.	257/347
6,252,248	B1 *	6/2001	Sano et al.	257/59
6,330,044	B1 *	12/2001	Murade	349/44
6,362,507	B1 *	3/2002	Ogawa et al.	257/350
6,424,012	B1 *	7/2002	Kawasaki et al.	257/350
6,479,333	B1 *	11/2002	Takano et al.	438/159
6,512,504	B1 *	1/2003	Yamauchi et al.	345/87
6,603,453	B2 *	8/2003	Yamazaki et al.	345/92
6,603,455	B1	8/2003	Zhang et al.	
6,740,938	B2 *	5/2004	Tsunoda et al.	257/365
6,893,503	B1 *	5/2005	Ohnuma et al.	117/94
6,953,951	B2 *	10/2005	Yamazaki et al.	257/72
7,038,283	B2	5/2006	Yanai et al.	

(Continued)

FOREIGN PATENT DOCUMENTS

JP	11-133877	5/1996
JP	8-220505	8/1996

(Continued)


Primary Examiner — Michael Faragalla

(74) Attorney, Agent, or Firm — Morgan, Lewis & Bockius LLP

(57) **ABSTRACT**

A liquid crystal display device includes a display region having unit pixels arranged thereon in a matrix, and a driving circuit unit having at least a LDD (Lightly Doped Drain) type TFT and a GOLDD (Gate overlapped Lightly Doped Drain) type TFT.

6 Claims, 6 Drawing Sheets



(56)

References Cited

FOREIGN PATENT DOCUMENTS

U.S. PATENT DOCUMENTS

7,189,997	B2 *	3/2007	Tsunoda et al.	257/72
7,233,342	B1 *	6/2007	Yamazaki et al.	345/692
7,276,730	B2 *	10/2007	Yamazaki et al.	257/59
2001/0030722	A1 *	10/2001	Murade	349/110
2002/0014624	A1 *	2/2002	Yamazaki et al.	257/57
2002/0070382	A1 *	6/2002	Yamazaki et al.	257/72
2003/0057853	A1 *	3/2003	Ino	315/169.3
2004/0217354	A1 *	11/2004	Kamo et al.	257/72

JP	10-268254	10/1998
JP	2000-194014	7/2000
JP	2001-77373	3/2001
JP	2001-77374	3/2001
JP	2001-111060	4/2001
JP	2001-265243	9/2001
JP	2001-320053	11/2001
JP	2003-45892	2/2003

* cited by examiner

FIG. 1A
RELATED ART




FIG. 1B
RELATED ART




FIG. 1C
RELATED ART




FIG. 1D
RELATED ART




FIG. 1E
RELATED ART




FIG. 1F
RELATED ART




FIG. 2




FIG. 3A




FIG. 3B




FIG. 3C




FIG. 3D




FIG. 3E




FIG. 3F





FIG. 4



LIQUID CRYSTAL DISPLAY DEVICE HAVING GOLDD TYPE TFT AND LDD TYPE TFT AND METHOD OF MAKING SAME

This application claims the benefit of Korean Application No. 2004-39340 filed in Korea on May 31, 2004, which is hereby incorporated by reference in its entirety.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a liquid crystal display device and a fabrication method thereof, and particularly, to a liquid crystal display device having both GOLDD (Gate Overlapped Lightly Doped Drain) type and LDD (Lightly Doped Drain) type thin film transistors and a fabrication method thereof.

2. Description of the Related Art

Recently, research for lighter, more compact flat panel display devices have resulted in liquid crystal display (LCD) devices being mass-produced and widely used. LCD devices usually use thin film transistors (TFT). TFTs in a LCD device are used as switching devices to individually drive each respective pixel. A TFT includes a semiconductor layer having a channel formed therein through which a current flows, a gate electrode for controlling the current by applying a scanning signal to turn the current on and off, a source electrode for inputting data signals, and a drain electrode for outputting data signals.

The LCD includes a pixel region having a plurality of pixels therein for displaying real images, and a driving circuit unit for applying various signals to the pixel region. The TFT makes up all of the pixel region and the driving circuit unit. For Chip On Glass (COG) type LCD, which has the driving circuit unit and pixel region on the same substrate, research to form a compact LCD has been mainly achieved by providing the driving circuit unit with a polycrystalline TFT.

The TFT formed in the driving circuit unit has to have higher electric mobility as compared with the TFT formed in the pixel region. Accordingly, the polycrystalline TFT having high electric mobility is usually applied in the driving circuit unit.

Recently, attempts have been made to further minimize the LCD to form a lighter and more compact display apparatus. However, since the pixel region in which images are displayed cannot be further reduced, (the size of this pixel region has already been established), the size reduction of the LCD is substantially achieved by reducing the area of the driving circuit unit. Thus, when the area of the driving circuit unit is reduced, the size of the TFT arranged in the driving circuit unit is inevitably reduced as well. The reduction of the TFT is achieved by reducing the length of the channel. Reducing the length of the channel, however, make the channel layer prone to damage by generating hot carriers on the channel. The hot carriers trapped within the channel change the threshold voltage of a device creating a defect.

To solve this problem, a LDD (Lightly Doped drain) type TFT has been introduced. The LDD type TFT has a low concentration impurity region. The LDD region is formed adjacent to the channel layer and a high concentration impurity region is formed outside of the LDD region. Furthermore, since LDD type TFT hardly generates any off current, it may prevent leakage currents that cause degradation of image quality.

However, in the LDD type TFT, there is a limit on how much the channel length can be reduced. Reliability of the TFT declines as the channel length gets shorter. Therefore,

when the TFT having short channel length is applied to display apparatuses of high image qualities such as HDTV, the channel may be damaged due to hot carrier effects.

A TFT having a GOLDD (Gate Overlapped LDD) type is proposed to solve those problems. In the GOLDD type TFT, since a gate electrode is overlapped with an LDD region, it is possible to form a short channel. As a result, a small-sized TFT with reliability can be fabricated.

Hereinafter, a fabrication process for the GOLDD type TFT according to the related art is discussed with reference to FIGS. 1A through 1F.

First, as shown in FIG. 1A, a buffer layer **102** is formed on a substrate **101**, which is made of a transparent material like glass. Next, a semiconductor layer **103** is formed on the buffer layer **102** by depositing an amorphous semiconductor such as a silicon and patterning it. Thereafter, a photoresist pattern **104** is formed on the semiconductor layer **103** and then low concentration impurity ion (i.e., n- ion) is injected into the exposed region of the semiconductor layer **103** not blocked by the photoresist pattern. The result is the formation of a channel layer **103a** and low concentration impurity region **103b**, the n- region.

Next, as shown in FIG. 1B, after removing the photoresist pattern **104** on the channel layer **103a**, a laser beam is irradiated on the semiconductor layer **103** to crystallize the amorphous semiconductor layer. When the laser beam is irradiated on the semiconductor layer **103**, the impurity ion injected in the n- region **103b** is activated.

Next, as shown in FIG. 1C, a gate insulating layer **105** is formed on the semiconductor layer **103**. Thereafter, a metal layer **106** is formed on the gate insulating layer **105**.

Referring to FIG. 1D, a photoresist pattern **107** is formed on the metal layer **106** and photolithography process is performed to create gate electrode **106a**. The size of the gate electrode **106a** is greater than the channel layer **103a**.

Next, referring to FIG. 1E, high concentration impurity ion (n+ ion) is injected into the n- region **103b** by using the gate electrode **106a** as a mask. A part of each n- layer **103b** (i.e., regions where are not blocked by the gate electrode **106a**) becomes high concentration impurity region **103c** (n+ region). As a result, the gate electrode **106a** is overlapped with low concentration impurity regions **103b**.

After forming the high concentration impurity layer **103c**, as shown in FIG. 1F, a passivation layer **108** is formed on the gate electrode **106a**. A conductive layer is deposited on the passivation layer **108** and is etched to form a source electrode **109** and a drain electrode **110**.

The source electrode **109** and the drain electrode **110** are connected to the n+ region **103c** respectively through contact holes exposing the n+ region **103c**.

Accordingly, the GOLDD type TFT has low concentration impurity ion region and high concentration impurity ion region similar to that of LDD type TFT. The GOLDD type TFT has superior reliability but cannot readily be reduced in size. On the other hand, the LDD type TFT is advantageous for its small-size but its reliability is degraded due to minimization.

SUMMARY OF THE INVENTION

Accordingly, the present invention is directed to a liquid crystal display device that substantially obviates one or more of the problems due to limitations and disadvantages of the related art.

Therefore, an object of the present invention is to form a more compact liquid crystal display device by decreasing the area of a driving circuit unit in a substrate. More particularly,

an object of the present invention is to form an optimal driving circuit unit and a more compact liquid crystal display device by selectively applying LDD type TFT and GOLDD type TFT to various driving devices formed in the driving circuit unit according to driving voltages thereof.

Additional features and advantages of the invention will be set forth in the description which follows, and in part will be apparent from the description, or may be learned by practice of the invention. The objectives and other advantages of the invention will be realized and attained by the structure particularly pointed out in the written description and claims hereof as well as the appended drawings.

To achieve these and other advantages in accordance with the purpose of the present invention as embodied and broadly described herein, a liquid crystal display device includes a display region having unit pixels arranged thereon in a matrix, and a driving circuit unit having at least a LDD (Lightly Doped Drain) type TFT and a GOLDD (Gate overlapped Lightly Doped Drain) type TFT.

In another aspect, a liquid crystal display device includes an image display unit having unit pixels arranged thereon in a matrix, and a driving circuit unit formed by a first CMOS including LDD type TFT and a second CMOS including GOLDD type TFT according to a driving voltage.

In yet another aspect, a method for fabricating a driving circuit unit integrated liquid crystal display device includes the steps of designating a display region and a driving circuit region on a substrate, forming unit pixels in the display region in a matrix, forming at least one driving unit in the driving circuit region, the driving unit including a first driving section, a second driving section, and a third driving section, forming a LDD type NMOS in the first driving section, a GOLDD type TFT in the second driving section, and a PMOS in the third driving section, and simultaneously forming a first CMOS by pairing the LDD type NMOS with the PMOS and a second CMOS by pairing the GOLDD type TFT with the PMOS.

It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory and are intended to provide further explanation of the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this specification, illustrate embodiments of the invention and together with the description serve to explain the principles of the invention. In the drawings:

FIGS. 1A to 1F show procedures of fabricating a GOLDD type TFT according to the related art;

FIG. 2 is a plan view showing an array substrate according to the present invention;

FIGS. 3A to 3F show procedures of fabricating a GOLDD type TFT, an LDD type TFT, and a PMOS according to the present invention; and

FIG. 4 is a graph showing performance results illustrating variations of drain voltage and electric mobility of LDD type and GOLDD type TFTs according to the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the preferred embodiments of the present invention, examples of which are illustrated in the accompanying drawings.

In general, a liquid crystal display panel includes an array substrate having unit pixels arranged therein as a matrix and a color filter substrate facing the array substrate. Liquid crystal is filled in the gap between the array substrate and the color filter substrate. The array substrate may be divided into an image display unit having unit pixels formed therein and a driving circuit unit for applying a driving signal to the image display unit.

FIG. 2 shows a structure of an array substrate of a liquid crystal display device according to the present invention. As shown in FIG. 2, an image display unit **201** is formed at a predetermined position on substrate **200**, and driving circuit unit **202** equipped with various driving circuits is positioned outside of the image display unit **201**.

Particularly, SOG (Silicon on Glass) technique to form a driving circuit unit driving a display region and a display region displaying the image on the same substrate has been developed with creation of a polycrystalline silicon TFT. Accordingly, processes for fabricating a liquid crystal display panel has been simplified making it possible to make compact liquid crystal panels using the SOG technique. One of the main factors for this process is the use of polysilicon as a channel of TFT. Polysilicon has superior electric conductivity relative to amorphous silicon. Therefore, a driving circuit unit and a switching device of an display region are formed using polysilicon TFT in which the polysilicon is adopted as a channel.

A P-type TFT or an N-type TFT may selectively be used as the switching device of the display region. A CMOS (Complementary Metal Oxide Silicon) in which NMOS and PMOS make a pair is used as a driving device of the driving circuit unit. Specifically, the NMOS is an LDD type polysilicon TFT to control leakage current caused by carrier electrons.

A driving circuit unit can adopt the CMOS as a driving device. Here, the CMOS may be formed by using GOLDD type TFT instead of using LDD type NMOS. That is, the CMOS is configured in the driving circuit unit as a combination of LDD type TFT+PMOS and GOLDD type TFT+PMOS to prevent leakage current while optimizing a minimization of the driving circuit unit.

As shown in FIG. 2, the driving circuit unit **202** of the array substrate **200** includes gate driver **203** for supplying gate signals to gate lines of the display region **201** and data driver **204** for applying data signals to data lines. The data lines cross vertically to the gate lines, which are formed in the display region **201**. The two drivers **203** and **204** are adjacent to the display region **201**.

The driving circuit unit **202** further includes a timing controller **205** for generating control signals to be supplied to the gate driver and the data driver by receiving signals inputted from the exterior. To supply the generated control signals to the gate and data drivers, a DC-DC converter for converting a DC voltage input from the exterior into a DC voltage required for driving the liquid crystal display panel, a DA (Digital-to-Analog) converter for converting a digital signal inputted from the exterior into an analog signal, a gamma voltage generator and a common voltage (Vcom) driver for adjusting a common voltage are also included. Various devices in the driving circuit unit are formed by CMOS.

In forming the CMOS, driving devices operating at a relatively high voltage are formed by CMOS using GOLDD type TFT to prevent leakage currents usually generated during operation at high voltages. Driving devices operating at a relatively low voltage are configured by CMOS using LDD type NMOS. As a result, driving stability and area reduction are achieved.

For instance, an output buffer block within the gate driver, a level shifter in the driving circuit unit, a pixel switching TFT in the display region, and all other devices driven by high voltage more than 10V are formed by CMOS adopting GOLDD type TFT. On the other hand, a timing controller, a shift resistor within the data driver, a DC-DC converter, a Vcom driver, and all other devices driven by a low voltage less than 10V are formed by CMOS adopting LDD type TFT. Using these configurations, the driving circuit unit may be optimized for reliability and area reduction by utilizing both the LDD type TFT, which is capable of area reduction effect, and the GOLDD type TFT with superior reliability.

Hereinafter, the CMOS fabrication process for the driving circuit unit will be explained with reference to FIGS. 3A to 3F.

The driving circuit unit according to the present invention uses a CMOS having a pair of LDD type NMOS and PMOS and another CMOS having a pair of GOLDD type TFT and PMOS. For reference, the fabrication processes for LDD type NMOS, GOLDD type TFT and PMOS will be explained.

First, referring to FIG. 3A, active layers **302a**, **302b**, and **302c** are formed respectively on predetermined regions (i.e., LDD type TFT region L, GOLDD type TFT region G, and PMOS region P) of a transparent substrate **301**.

A process for forming the active layers **302a**, **302b**, and **302c** is achieved by forming an amorphous silicon layer on the substrate **301** using PECVD (Plasma Enhanced Chemical Vapor Deposition) method and patterning the amorphous silicon layer by a photomask process. In other words, the process for forming the active layers **302a**, **302b**, and **302c** includes the steps of depositing the amorphous silicon layer on the substrate **301** by the PECVD method, coating a photoresist (not shown) on the amorphous silicon layer, exposing and developing the photoresist by applying a mask, and patterning the amorphous silicon by using the developed photoresist pattern.

As shown in FIG. 3B, after forming the active layers **302a**, **302b**, and **302c**, photoresist patterns **304** are formed on the active layers **302a**, **302b**, and **302c** through a photomask process. The photoresist patterns **304** define channel regions for the active layers **302a** and **302b** on the LDD type TFT region L and the GOLDD type TFT region G, and cover the entire active layer **302c** on the PMOS region. The photoresist patterns **304** on the active layers **302a** and **302b** cover each channel region **303c** of the active layers **302a** and **302b** and expose the residual regions.

Afterwards, low concentration impurity ion is injected by using the photoresist pattern **304** as an impurity blocking mask. Group five element such as phosphorous (P) may be used as the impurity ion injected. According to the ion injection, low concentration impurity ion is injected into exposed parts of the active layers **302a** and **302b** on the LDD type TFT region L and the GOLDD type TFT region G, namely, regions which are not covered with the photoresist **304**. Accordingly, no impurity ion is injected into the active layer **302c** on the PMOS region P since it is covered with the photoresist pattern **304**.

Thereafter, as shown in FIG. 3C, a gate insulating layer **305** made of a silicon oxide film (SiO₂) is formed over the active layers **302a**, **302b**, and **302c** by the (PECVD) method. A metal layer, such as aluminum (Al) or the like, is formed on the gate insulating layer **305**. Through the photolithography process, gate electrodes **306**, **307**, and **308** are formed thereon. Gate electrode **307** formed on the GOLDD type TFT region G is bigger than the gate electrode **306** formed on the

LDD type TFT region L. This is to form low concentration impurity regions under the gate electrode **307** on the GOLDD type TFT region G.

Next, as shown in FIG. 3D, photoresist patterns **309a** and **309b** are formed on the gate electrodes **306** and **308**. Here, the photoresist pattern **309a** covers the entire gate electrode **306** and a part of the low concentration impurity region **303a** and **303b** of the LDD type TFT region L. The photoresist pattern **309b** is formed on the PMOS region P to cover the entire PMOS region. No photoresist pattern is formed on the GOLDD type TFT region G.

Next, high concentration impurity ion is injected into exposed low concentration impurity regions **303a** and **303b** of the LDD type TFT region L and the GOLDD type TFT region G. As a result, high concentration impurity regions **310b** and **310c**, the source and drain regions, respectively, are formed in the LDD type TFT region L. LDD region **310a** is defined at adjacent regions of the channel. Moreover, high concentration impurity regions **311b** and **311c**, the source and drain regions, respectively, are formed in low concentration impurity regions **303a** and **303b** of the GOLDD type TFT region G. Low concentration impurity region **311a** under the gate electrode **307** is defined as LDD region **311a**. The injected high concentration impurity ion may be group five element such as phosphorous (P). While the source and drain regions of the LDD type TFT region L and the GOLDD type TFT region G are formed by injecting the high concentration impurity ion, the active layer on the PMOS region P is covered with the photoresist to prevent the impurity from getting injected thereinto.

Next, as shown in FIG. 3E, both the LDD type TFT region L and the GOLDD type TFT region G are covered with photoresist pattern **312**. Here, the PMOS region P is not covered with the photoresist.

Next, a high concentration impurity ion of group three element such as boron (B) is injected into these regions using photoresist **312** as a blocking mask. At this time, the high concentration P type impurity ion is injected into source and drain regions **313a** and **313b** of the PMOS region P to thereby form a PMOS. As a result of these processes, LDD type NMOS, GOLDD type TFT, and PMOS are formed. As aforementioned, the LDD type NMOS is formed at low voltage driving device regions using less than 10V, and the GOLDD type TFT is formed at relatively high voltage driving device regions using more than 10V.

Next, as shown in FIG. 3F, a CMOS is formed by making the LDD type NMOS and the PMOS a pair while simultaneously another CMOS is formed by making the GOLDD type TFT and the PMOS a pair. FIG. 3F is an example of a configuration for the CMOS connecting the GOLDD type TFT and the PMOS.

After completing the TFT, an insulating layer **314** is formed over the entire substrate, and contact holes for exposing the source and drain regions of the TFT are formed on the insulating layer **314**.

Next, source electrode **320** and drain electrode **321** connected to the source and drain regions through the contact holes are formed. In this step of forming the source electrode **320** and the drain electrode **321**, a common drain electrode **315** is formed to connect the drain electrode **313b** on the PMOS and the drain electrode **311c** on the GOLDD type TFT.

Next, a passivation layer **317** is formed on the source and drain electrodes, and a drain connection terminal **316** connected to the common drain electrode **315** is formed. Meanwhile, the TFT as a switching device of the display region may be formed simultaneously with the above fabrication process for the CMOS in the driving circuit unit. The TFT in

the display region may be formed by selecting either the PMOS or the NMOS. Furthermore, when the switching device of the image display unit is driven at a high voltage, the GOLDD type TFT with superior reliability may be used as the switching device. As a result, the driving circuit unit integrated liquid crystal panel including both the LDD type TFT and the GOLDD type TFT may be achieved.

In fabricating the driving circuit unit integrated liquid crystal panel according to the present invention, the CMOS adopting the GOLDD type TFT is formed in devices driven by a relatively high driving voltage, while another CMOS adopting the LDD type TFT is formed in devices driven by a relatively low driving voltage. As a result, the driving circuit unit integrated liquid crystal panel which satisfy both an area reduction of the driving circuit unit and reliability thereof can be fabricated. Furthermore, since these processes are carried out without extraneous mask processes, efficiencies in fabrication of the liquid crystal panel is improved.

In accordance with an exemplary embodiment of the present invention, among TFTs positioned in the driving circuit unit, a GOLDD type TFT is driven by a high voltage more than 10V and an LDD type TFT is driven by a low voltage less than 10V. FIG. 4 is a graph showing an experimental result that illustrates variations of drain voltage and electric mobility of LDD type and GOLDD type TFTs for which width and length of a channel is 4 μm , respectively, and length of an LDD region is 1.5 μm . The graph illustrates the variations of electric mobility of the LDD type TFT as compared to that of the GOLDD type TFT.

As shown in FIG. 4, when the drain voltage V_d becomes greater than 10V, the electric mobility of the LDD type TFT having the above-described dimensions varies drastically while that of the GOLDD type TFT having the above-described dimensions remains relatively stable. This experimental result demonstrates that application of CMOS composed of the GOLDD type device is preferred for circuits requiring a high driving voltage to increase reliability. For circuits requiring a low driving voltage, application of CMOS composed of the LDD type device is preferred since LDD type devices are relatively smaller in size than the GOLDD type device while reliability is not affected.

The drain voltage at which the electric mobility becomes unstable varies based on the dimensions of the TFT devices. Considering these characteristics of the variations of the drain voltage and the electric mobility, the LDD type TFT is used when the variation of the electric mobility of the polysilicon TFT is less than 7% while the GOLDD type TFT is used when the variation of the electric mobility is more than 7%. Thus, a driving circuit integrated liquid crystal display panel, which simultaneously satisfies reduction of dimension and increase in reliability of the driving circuit unit can be fabricated.

It will be apparent to those skilled in the art that various modifications and variations can be made in the liquid crystal display device of the present invention and the method of fabricating the same without departing from the spirit or scope of the invention. Thus, it is intended that the present invention cover the modifications and variations of this invention provided they come within the scope of the appended claims and their equivalents.

What is claimed is:

1. A liquid crystal display device, comprising:

an image display unit having unit pixels arranged thereon in a matrix;

a driving circuit unit applying a driving signal to the image display unit, wherein the driving circuit unit includes,

a gate driver for supplying gate signals to gate lines of the display unit;

a data driver for applying data signals to data lines;

an output buffer block within the gate driver;

a level shifter in the driving circuit unit;

a timing controller for generating control signals to be supplied to the gate driver and the data driver by receiving signals inputted from an exterior;

a DC-DC (Direct Current-Direct Current) converter for converting a DC voltage input from the exterior into a DC voltage required for driving a liquid crystal display panel;

a DA (Digital-to-Analog) converter for converting a digital signal inputted from the exterior into an analog signal;

a gamma voltage generator;

a shift resistor for storing the control signals inputted from the timing controller; and

a common voltage driver for adjusting a common voltage;

a first CMOS by pairing a LDD TFT with a PMOS; and a second CMOS by pairing a GOLDD TFT with the PMOS,

wherein the output buffer block within the gate driver, the level shifter in the driving circuit unit, a pixel switching TFT in the display unit, and all other devices driven by high voltage more than 10V are formed by the second CMOS adopting the GOLDD TFT, and

wherein the timing controller, the shift resistor within the data driver, the DC-DC converter, the common voltage driver, and all other devices driven by a low voltage less than 10V are formed by the first CMOS adopting the LDD TFT.

2. The device of claim 1, wherein:

the data driver includes:

the shift resistor for storing the control signal inputted from the timing controller;

the digital-to-analog converter (DAC) for converting a control signal inputted from the shift resistor into an analog signal for the image display unit; and

a first output buffer block for applying a control signal inputted from the DAC to the data lines; and

the gate driver includes:

the shift resistor;

the level shifter for carrying the control signal inputted from the shift resistor to a specific level; and

a second output buffer block for applying a control signal inputted from the level shifter to the gate lines of the image display unit.

3. The device of claim 1, wherein the LDD TFT, the GOLDD TFT, and the PMOS comprise:

first, second and third active layers on a transparent substrate; a gate insulating layer over the active layers;

first, second and third gate electrodes on the gate insulating layer, wherein each of the gate electrodes is formed at the first, second and third active layers, respectively;

a first LDD region formed in the first active layer at sides of the first gate electrode, and a second LDD region formed in the second active layer under the second gate electrode; and

source and drain regions in the first, second and third active layer at sides of the first, second and third gate electrodes.

4. The device of claim 1, wherein the LDD TFT comprises:

a first active layer on a transparent substrate;

a gate insulating layer over the first active layer;

the first gate electrode on the gate insulating layer;

a first LDD region formed in the first active layer, wherein the first LDD region is formed in the first active layer at sides of the first gate electrode; and source and drain regions in the first active layer at the sides of the first gate electrode. 5

5. The device of claim 1, wherein the GOLDD TFT comprises:

a second active layer on a transparent substrate;
a gate insulating layer over the second active layer;
the second gate electrode on the gate insulating layer; a 10
second LDD region formed in the second active layer,
wherein the second LDD region is formed in the second active layer under the second gate electrode; and
source and drain regions in the second active layer at sides of the second gate electrode. 15

6. The device of claim 1, wherein the PMOS comprises:
a third active layer on a transparent substrate;
a gate insulating layer over the third active layer;
the third gate electrode on the gate insulating layer; and
source and drain regions in the third active layer at sides of 20
the third gate electrode.

* * * * *

专利名称(译)	具有GOLDD型TFT和LDD型TFT的液晶显示装置及其制造方法		
公开(公告)号	US8692750	公开(公告)日	2014-04-08
申请号	US11/139980	申请日	2005-05-31
[标]申请(专利权)人(译)	乐金显示有限公司		
申请(专利权)人(译)	LG.PHILIPS LCD CO. , LTD.		
当前申请(专利权)人(译)	LG DISPLAY CO. , LTD.		
[标]发明人	LEE SEOK WOO		
发明人	LEE, SEOK-WOO		
IPC分类号	G02F1/1345 G06F3/041 H01L21/00 G02F1/1368 H01L27/146 H01L29/786 G09G3/36 H01L21/77 G02F1/136 H01L21/84 G02F1/133 G02F1/1362 H01L21/336		
CPC分类号	H01L29/66757 H01L27/14643 H01L29/78627 G02F1/13454 H01L29/78621 H01L27/1214 H01L27/127		
优先权	1020040039340 2004-05-31 KR		
其他公开文献	US20050266595A1		
外部链接	Espacenet USPTO		

摘要(译)

一种液晶显示装置，包括：显示区域，具有以矩阵布置在其上的单位像素;以及驱动电路单元，至少具有LDD（轻掺杂漏极）型TFT和GOLDD（栅极重叠轻掺杂漏极）型TFT。

