



US006650312B2

(12) **United States Patent**
Tazuke

(10) **Patent No.:** **US 6,650,312 B2**
(45) **Date of Patent:** **Nov. 18, 2003**

(54) **LIQUID CRYSTAL DISPLAY MODULE
CAPABLE OF AVOIDING GENERATION OF
RIB-LIKE PATTERNS**

6,376,995 B1 * 4/2002 Kato et al. 315/169.3
6,528,952 B2 * 3/2003 Kato et al. 315/169.4
6,538,708 B2 * 3/2003 Zhang 349/40
6,552,710 B1 * 4/2003 Shimizu et al. 345/100

(75) Inventor: **Toshikazu Tazuke, Shiga (JP)**

* cited by examiner

(73) Assignee: **NEC Electronics Corporation,**
Kanagawa (JP)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 296 days.

Primary Examiner—Richard Hjerpe

Assistant Examiner—Ronald Laneau

(74) *Attorney, Agent, or Firm*—Choate, Hall & Stewart

(21) Appl. No.: **09/894,361**

(22) Filed: **Jun. 28, 2001**

(65) **Prior Publication Data**

US 2002/0008687 A1 Jan. 24, 2002

(30) **Foreign Application Priority Data**

Jun. 29, 2000 (JP) 2000-195540

(51) **Int. Cl.**⁷ **G09G 3/36**

(52) **U.S. Cl.** **345/96; 345/87**

(58) **Field of Search** 345/87, 88, 90,
345/92, 95, 96, 98, 99, 100, 211, 212, 213,
89

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,986,724 A * 11/1999 Akiyama et al. 349/41

(57) **ABSTRACT**

In an apparatus for driving data lines of a liquid crystal display panel, a plurality of voltage followers are provided, and a plurality of output pads are connected to the data lines. A plurality of first switches are connected between the voltage followers and the output pads, and a plurality of second switches are connected between the output pads. First and second charge neutralization pads are connected to a most-upstream one and a most-downstream one of the output pads. A third switch is connected between one, respectively, of the first and second charge neutralization pads and the most-upstream or most-downstream one of the output pads.

11 Claims, 13 Drawing Sheets





Fig. 1 PRIOR ART


Fig. 2 PRIOR ART

Fig. 3A PRIOR ART

POL="0"

+	-	+	-	+
-	+	-	+	-
+	-	+	-	+
-	+	-	+	-
+	-	+	-	+

Fig. 3B PRIOR ART

POL="1"

-	+	-	+	-
+	-	+	-	+
-	+	-	+	-
+	-	+	-	+
-	+	-	+	-

Fig. 4 PRIOR ART




Fig. 5 PRIOR ART





Fig. 6

Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12





Fig. 13



LIQUID CRYSTAL DISPLAY MODULE CAPABLE OF AVOIDING GENERATION OF RIB-LIKE PATTERNS

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a liquid crystal display (LCD) module, and more particularly, to the improvement of data line drive apparatuses thereof.

2. Description of the Related Art

A prior art LCD module is constructed by an LCD panel having data lines, gate lines and liquid crystal cells each connected to one of the data lines and one of the gate lines, a plurality of data line drive apparatuses provided at an edge of the LCD panel and connected by a cascade connection to each other for driving the data lines, and a plurality of gate line drive apparatuses provided at another edge of the LCD panel and connected by a cascade connection to each other. In this case, in view of power consumption, use is made of a dot inversion method rather than a frame inversion method.

Also, each of the data line drive apparatuses is formed by a plurality of voltage followers, a plurality of output pads each connected to one of the data lines, a plurality of first switches each connected between one of the voltage followers and one of the output pads, and a plurality of second switches each connected between two of the output pads.

The first and second switches are turned OFF and ON, respectively, by a first state of a strobe signal, and the first and second switches are turned ON, and OFF, respectively, by a second state of the strobe signal. Thus, the charges are neutralized among the data lines to salvage the charges, which further decreases the power consumption. This will be explained in detail later.

In the above-described prior art LCD module, however, since the neutralization of charges among the data lines is not carried out between the data line drive apparatuses, rib-like patterns are generated in the LCD panel in correspondence with the boundaries between the data line drive apparatuses.

SUMMARY OF THE INVENTION

It is an object of the present invention to provide an LCD module capable of avoiding the generation of rib-like patterns.

According to the present invention, in an LCD module including an LCD panel having data lines, gate lines and liquid crystal cells each connected to one of the data lines and one of the gate lines, and a plurality of data line drive apparatuses, provided at an edge of the LCD panel and connected by a cascade connection to each other, for driving the data lines, each of the data line drive apparatuses is formed by a plurality of voltage followers, a plurality of output pads each connected to one of the data lines, a plurality of first switches each connected between one of the voltage followers and one of the output pads, a plurality of second switches each connected between two of the output pads, first and second charge neutralization pads connected to a most-upstream one and a most-downstream one, respectively, of the output pads, and a third switch connected between one of the first and second charge neutralization pads and the most-upstream or most-downstream one of the output pads. The first, second and third switches are turned OFF, ON and ON, respectively, by a first state of a strobe

signal, and the first, second and third switches are turned ON, OFF and OFF, respectively, by a second state of the strobe signal. The first charge neutralization pads of one of the data line drive apparatuses is electrically connected to the second charge neutralization pad of another of the data line drive apparatuses upstream of the one of the data line drive apparatuses, and the second charge neutralization pad of one of the data line drive apparatuses is electrically connected to the second charge neutralization pad of another of the data line drive apparatuses downstream of the one of the data line drive apparatuses.

Also, in an LCD module including an LCD panel having data lines, gate lines and liquid crystal cells each connected to one of the data lines and one of the gate lines, and a plurality of data line drive apparatuses, provided at an edge of the LCD panel and connected by a cascade connection to each other, for driving the data lines, each of the data line drive apparatuses is formed by a plurality of voltage followers, a plurality of output pads each connected to one of the data lines, a plurality of first switches each connected between one of the voltage followers and one of the output pads, first and second charge neutralization pads, a common line connected between the first and second neutralization pad, and a plurality of second switches each connected between the common line and one of the output pads. The first and second switches are turned OFF and ON, respectively, by a first state of a strobe signal, and the first and second switches are turned ON and OFF, respectively, by a second state of the strobe signal. The first charge neutralization pad of one of the data line drive apparatuses is electrically connected to the second charge neutralization pad of another of said data line drive apparatuses upstream of the one of the data line drive apparatuses, and the second charge neutralization pad of one of the data line drive apparatuses is electrically connected to the second charge neutralization pad of another of the data line drive apparatuses downstream of the one of the data line drive apparatuses.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be more clearly understood from the description set forth below, as compared with the prior art, with reference to the accompanying drawings, wherein:

FIG. 1 is a plan view illustrating a prior art active matrix type LCD module;

FIG. 2 is a detailed block circuit diagram of the data line drive apparatus of FIG. 1;

FIGS. 3A and 3B are diagrams for explaining a dot inversion method by the polarity signal of FIG. 2;

FIG. 4 is a detailed circuit diagram of the driver circuit of FIG. 2;

FIG. 5 is a timing diagram for explaining the operation of the driver circuit of FIG. 4;

FIG. 6 is a plan view illustrating an embodiment of the LCD module according to the present invention;

FIG. 7 is a detailed block circuit diagram of the data line drive apparatus of FIG. 6;

FIG. 8 is a detailed circuit diagram of a first example of the driver circuit of FIG. 7;

FIG. 9 is a timing diagram for explaining the operation of the driver circuit of FIG. 8;

FIG. 10 is a detailed circuit diagram of a second example of the driver circuit of FIG. 7;

FIG. 11 is a detailed circuit diagram of a third example of the driver circuit of FIG. 7;

FIG. 12 is a detailed circuit diagram of a fourth example of the driver circuit of FIG. 7; and

FIG. 13 is a timing diagram for explaining the operation of the driver circuit of FIG. 12.

DESCRIPTION OF THE PREFERRED EMBODIMENT

Before the description of the preferred embodiment, a prior art active matrix type LCD module will be explained with reference to FIGS. 1 and 2.

In FIG. 1, reference numeral **100** designates an LCD panel having 1024×768 dots. In this case, each pixel is formed by three color elements, i.e., R(red), G(green) and B(blue), and therefore, the LCD panel **100** includes 3072 (1024×3) data lines (signal lines) DL and 768 gate lines (scan lines) GL. One pixel located at each intersection between the data lines DL and the gate lines GL is formed by one thin film transistor Q and one liquid crystal cell C.

In order to drive the 3072 data lines DL, eight data line drive apparatuses **201**, **202**, . . . , **208** each for driving 384 data lines are provided along a horizontal edge of the LCD panel **100**. In this case, the data line drive apparatuses **201**, **202**, . . . , **208** are arranged by a cascade connection method to transmit a horizontal start pulse signal STH therethrough.

On the other hand, in order to drive the 768 gate lines GL, four data line drive apparatuses **301**, **302**, **303** and **304** each for driving 192 gate lines are provided along a vertical edge of the LCD panel **100**. In this case, the gate line drive apparatuses **301**, **302**, **303** and **304** are arranged by a cascade connection method to transmit a vertical start pulse signal STV therethrough.

Note that the data line drive apparatuses **201**, **202**, . . . , **208** are mounted on a tape carrier package (TCP) and the gate line drive apparatuses **301**, **302**, **303** and **304** are mounted on another tape carrier package in advance. Then, the tape carrier packages are arranged on the edges of the LCD panel **100**.

The present invention relates to the data line drive apparatuses **201**, **202**, . . . , **208**.

The data line drive apparatus such as **202** of FIG. 1 is explained in detail next with reference to FIG. 2. Note that the data line drive apparatuses **201**, **202**, . . . , **208** have the same configuration.

In FIG. 2, reference numeral **401** designates a shift register circuit for shifting a horizontal start pulse signal STH in synchronization with a shift clock signal CLK. The shift register circuit **401** has 128 serially-connected D-type flip-flops clocked by the shift clock signal CLK to generate 128 output signals sequentially. Note that the horizontal start pulse signal STH is generated from a timing generating circuit (not shown) which receives a horizontal synchronization signal HSYNC. Note that such a timing generating circuit is provided commonly for all the data line drive apparatuses **201**, **202**, . . . , **208**.

A data register circuit **402** is formed by 384 D-type flip-flops for receiving 6-bit color video signals R, G and B and are triggered by the 128 output signals of the shift register circuit **401**. For example, the 1st, 2nd, and 3rd D-type flip-flops for receiving the color video signals R, G and B, respectively, are triggered by the 1st output signal of the shift register circuit **401**. Similarly, the 4th, 5th, and 6th D-type flip-flops for receiving the color video signals R, G and B, respectively, are triggered by the 2nd output signal of the shift register circuit **401**.

A data latch circuit **403** is formed by 384 registers for receiving output signals of the data register circuit **402** in

synchronization with a horizontal strobe signal STBH which is generated from the timing generating circuit. Also, the data latch circuit **403** receives a polarity signal POL which is also generated from the timing generating circuit. This polarity signal POL is used for carrying out a dot inversion method which is advantageous in power consumption. That is, if POL="0", the 1st output signal, the 3rd output signal, the 5th output signal, . . . of the data latch circuit **403** are made positive and the other signals are made negative as shown in FIG. 3A. On the other hand, if POL="1", the 2nd output signal, the 4th output signal, the 6th output signal, . . . of the data latch circuit **403** are made positive and the other signals are made negative as shown in FIG. 3B.

A decoder circuit **404** is formed by 384 digital/analog (D/A) converters powered by a positive power supply voltage VP and a negative power supply voltage VN. In this case, the decoder circuit **404** generates positive 64 gradation voltages by the positive power supply voltage VP and negative 64 gradation voltages by the negative power supply voltage VN therein. As a result, each of the 384 D/A converters converts one of the 384 output signals of the data latch circuit **403** into a positive or negative analog voltage.

A driver circuit **405** is driven by the horizontal strobe signal STBH to apply the 384 output signals of the decoder circuit **404** to the data lines DL of the LCD panel **100** of FIG. 1.

The driver circuit **405** of FIG. 2 is explained next in detail with reference to FIG. 4.

In FIG. 4, 384 output pads **501** are provided and will be connected to the data lines DL of the LCD panel **100** of FIG. 1. Also, 384 operational amplifiers **502** serving as voltage followers are provided to receive the 384 output signals of the decoder circuit **404**. Further, 384 switches **503** formed by transfer gates are provided between the operational amplifiers **502** and output pads **501**, and 383 switches **504** formed by transfer gates are provided between the output pads **501**. The switches **503** and **504** are controlled by the horizontal strobe signal STBH.

The operation of the driver circuit **405** of FIG. 4 is explained next with reference to FIG. 5.

First, the horizontal strobe signal STBH is made high, so that the switches **503** and **504** are turned OFF and ON, respectively. As a result, the operational amplifiers **502** are electrically isolated from the output pads **501** by the turned-OFF switches **503**, and all the output pads **501** are electrically connected by the turned-ON switches **504** to each other. Thus, the charges are neutralized among the data lines DL, which further decreases the power consumption. Then, the horizontal strobe signal STBH is made low, so that the switches **503** and **504** are turned ON and OFF, respectively. As a result, the operational amplifiers **502** are electrically connected to the output pads **501** by the turned-ON switches **503**, and the output pads **501** are electrically isolated by the turned-OFF switches **504**. Thus, the output signals of the operational amplifiers **502** are supplied to the data lines DL.

In the LCD module using the data line drive apparatuses **201** to **208** of FIG. 1 each including the driver circuit **405** of FIG. 2, however, since the neutralization of charges among the data lines DL is not carried out between the data line drive apparatuses **201** to **208**, seven rib-like patterns are generated in the LCD panel **100** in correspondence with the boundaries between the data line drive apparatuses **201** to **208**.

In FIG. 6, which illustrates an embodiment of the present invention, data line drive apparatuses **201'**, **202'**, . . . , **208'** are provided along the LCD panel **100** in the same way as the

5

data line drive apparatuses **201**, **202**, . . . , **208** of FIG. 1. Additionally, bonding wires **W1**, **W2**, . . . , **W7** are connected between the data line drive apparatuses **201'**, **202'**, . . . , **208'**, to carry out a charge neutralization between the data line drive apparatuses **201'**, **202'**, . . . , **208'**.

In FIG. 7, which is a detailed block circuit diagram of the data line drive apparatus such as **202'** of FIG. 6, the driver circuit **405** of FIG. 2 is modified into a driver circuit **405'** which further has a charge neutralization pad **PA** connected by a bonding wire such as **W1** to a driver circuit of an upstream data line drive apparatus such as **201'** and a charge neutralization pad **PB** connected by a bonding wire such as **W2** to a driver circuit of a downstream data line drive apparatus such as **203'**.

In FIG. 8, which is a detailed circuit diagram of a first example of the driver circuit **405'** of FIG. 7, switches **504A** and **504B** having the same configuration as the switches **504** are added to the elements of the driver circuit **405** of FIG. 4. In more detail, the switch **504A** is connected between the charge neutralization pad **PA** and the most-upstream one of the switches **504**, and the switch **504B** is connected between the charge neutralization pad **PB** and the most downstream one of the switches **504**. The switches **504A** and **504B** are controlled by the horizontal strobe signal **STBH** in the same way as the switches **504**.

The operation of the driver circuit **405'** of FIG. 8 is explained next with reference to FIG. 9.

First, the horizontal strobe signal **STBH** is made high, the switches **503** are turned OFF and the switches **504A** and **504B** as well as the switches **504** are turned ON. As a result, the operational amplifiers **502** are electrically isolated from the output pads **501** by the turned-OFF switches **503**. Also, all the output pads **501** are electrically connected by the turned-ON switches **504** to each other. Additionally, the output pads of all the data line drive apparatuses **201'** to **208'** are electrically connected by the turned-ON switches **504A** and **504B**. Thus, the charges are neutralized among the data lines **DL** of all the data line drive apparatuses **201'** to **208'**. Then, the horizontal strobe signal **STBH** is made low, the switches **503** are turned ON and the switches **504**, **504A** and **504B** are turned OFF. As a result, the operational amplifiers **502** are electrically connected to the output pads **501** by the turned-ON switches **503**, and the output pads **501** are electrically isolated by the turned-OFF switches **504**, **504A** and **504B**. Thus, the output signals of the operational amplifiers **502** are supplied to the data lines **DL**.

In the LCD module using the data line drive apparatuses **201'** to **208'** of FIG. 6 each including the driver circuit **405'** of FIG. 8, since the neutralization of charges among the data lines **DL** is carried out between the data line drive apparatuses **201'** to **208'**, no rib-like patterns are generated in the LCD panel **100**.

In FIG. 10, which is a detailed circuit diagram of a second example of the driver circuit **405'** of FIG. 7, the switch **504B** of FIG. 8 is not provided, and therefore, the most downstream output pad **501** is connected directly to the charge neutralization pad **PB**. In this case, when the switch **504A** of the downstream data line drive apparatus such as **203'** is turned ON by the horizontal strobe signal **STBH**, the output pads **501** of the data line drive apparatus **202'** are electrically connected to the output pads of the data line drive apparatus **203'**. Thus, the driver circuit **405'** of FIG. 10 operates in the same way as the driver circuit **405'** of FIG. 8.

In FIG. 11, which is a detailed circuit diagram of a third example of the driver circuit **405'** of FIG. 7, the switch **504A** of FIG. 8 is not provided, and therefore, the most upstream

6

output pad **501** is connected directly to the charge neutralization pad **PA**. In this case, when the switch **509B** of the upstream data line drive apparatus such as **201'** is turned ON by the horizontal strobe signal **STBH**, the output pads **501** of the data line drive apparatus **202'** are electrically connected to the output pads of the data line drive apparatus **201'**. Thus, the driver circuit **405'** of FIG. 11 operates in the same way as the driver circuit **405'** of FIG. 8.

In FIG. 12, which is a detailed circuit diagram of a fourth example of the driver circuit **405'** of FIG. 7, switches **505** formed by N-channel MOS transistors and a common line **CL** are provided instead of the switches **504**, **504A** and **504B** of FIG. 8. The common line **CL** is connected between the charge neutralization pads **PA** and **PB**. Also, each of the switches **505** is connected between the common line **CL** and one of the output pads **501**. The switches **505** are also controlled by the horizontal strobe signal **STBH**.

The operation of the driver circuit **405'** of FIG. 12 is explained next with reference to FIG. 13.

First, the horizontal strobe signal **STBH** is made high, so that the switches **503** and **505** are turned OFF and ON, respectively. As a result, the operational amplifiers **502** are electrically isolated from the output pads **501** by the turned-OFF switches **503**. Also, all the output pads **501** are electrically connected by the turned-ON switches **505** via the common line **CL** to each other. Additionally, the output pads of all the data line drive apparatuses **201'** to **208'** are electrically connected by the common line **CL**. Thus, the charges are neutralized among the data lines **DL** of all the data line drive apparatuses **201'** to **208'**. Then, the horizontal strobe signal **STBH** is made low, so that the switches **503** and **505** are turned ON and OFF, respectively. As a result, the operational amplifiers **502** are electrically connected to the output pads **501** by the turned-ON switches **503**, and the output pads **501** are electrically isolated by the turned-OFF switches **504**, **504A** and **504B**. Thus, the output signals of the operational amplifiers **502** are supplied to the data lines **DL**.

Even in the LCD module using the data line drive apparatuses **201'** to **208'** each including the driver circuit **405'** of FIG. 12, since the neutralization of charges among the data lines **DL** is carried out between the data line drive apparatuses **201'** to **208'**, no rib-like patterns are generated in the LCD panel **100**.

As explained hereinabove, according to the present invention, rib-like patterns can be prevented from being generated in an LCD panel.

What is claimed is:

1. A liquid crystal display module comprising:

a liquid crystal display panel having data lines, gate lines and liquid crystal cells each connected to one of said data lines and one of said gate lines; and

a plurality of data line drive apparatuses, provided at an edge of said liquid crystal display panel and connected by a cascade connection to each other, for driving said data lines,

each of said data line drive apparatuses comprising:

a plurality of voltage followers;

a plurality of output pads each connected to one of said data lines;

a plurality of first switches each connected between one of said voltage followers and one of said output pads;

a plurality of second switches each connected between two of said output pads;

first and second charge neutralization pads, said second charge neutralization pad being connected to a most-downstream one of said output pads; and

7

a third switch connected between said first charge neutralization pad and a most-upstream one of said output pads,
 said first, second and third switches being turned OFF, ON and ON, respectively, by a first state of a strobe signal,
 said first, second and third switches being turned ON, OFF and OFF, respectively, by a second state of said strobe signal,
 said first charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses upstream of said one of said data line drive apparatuses,
 said second charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses downstream of said one of said data line drive apparatuses.

2. The liquid crystal display module as set forth in claim 1, wherein each of said data line drive apparatuses further comprises a fourth switch connected between said second charge neutralization pad and the most-downstream one of said output pads,
 said fourth switch being turned ON and OFF by the first and second states, respectively, of said strobe signal.

3. The liquid crystal display module as set forth in claim 1, wherein said data line drive apparatuses carry out a dot inversion drive operation.

4. A liquid crystal display module comprising:
 a liquid crystal display panel having data lines, gate lines and liquid crystal cells each connected to one of said data lines and one of said gate lines; and
 a plurality of data line drive apparatuses, provided at an edge of said liquid crystal display panel and connected by a cascade connection to each other, for driving said data lines,
 each of said data line drive apparatuses comprising:
 a plurality of voltage followers;
 a plurality of output pads each connected to one of said data lines;
 a plurality of first switches each connected between one of said voltage followers and one of said output pads;
 a plurality of second switches each connected between two of said output pads;
 first and second charge neutralization pads, said first charge neutralization pad being connected to a most-upstream one of said output pads; and
 a third switch connected between said second charge neutralization pad and a most-downstream one of said output pads,
 said first, second and third switches being turned OFF, ON and ON, respectively, by a first state of a strobe signal,
 said first, second and third switches being turned ON, OFF and OFF, respectively, by a second state of said strobe signal,
 said first charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses upstream of said one of said data line drive apparatuses,
 said second charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses downstream of said one of said data line drive apparatuses.

8

5. The liquid crystal display module as set forth in claim 4, wherein said data line drive apparatuses carry out a dot inversion drive operation.

6. A liquid crystal display module comprising:
 a liquid crystal display panel having data lines, gate lines and liquid crystal cells each connected to one of said data lines and one of said gate lines; and
 a plurality of data line drive apparatuses, provided at an edge of said liquid crystal display panel and connected by a cascade connection to each other, for driving said data lines,
 each of said data line drive apparatuses comprising:
 a plurality of voltage followers;
 a plurality of output pads each connected to one of said data lines;
 a plurality of first switches each connected between one of said voltage followers and one of said output pads;
 first and second charge neutralization pad;
 a common line connected between said first and second charge neutralization pads; and
 a plurality of second switches each connected between said common line and one of said output pads,
 said first and second switches being turned OFF and ON, respectively, by a first state of a strobe signal,
 said first and second switches being turned ON and OFF, respectively, by a second state of said strobe signal,
 said first charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses upstream of said one of said data line drive apparatuses,
 said second charge neutralization pad of one of said data line drive apparatuses being electrically connected to said second charge neutralization pad of another of said data line drive apparatuses downstream of said one of said data line drive apparatuses.

7. The liquid crystal display module as set forth in claim 6, wherein said data line drive apparatuses carry out a dot inversion drive operation.

8. An apparatus for driving data lines of a liquid crystal display panel, comprising:
 a plurality of voltage followers;
 a plurality of output pads each connected to one of said data lines;
 a plurality of first switches each connected between one of said voltage followers and one of said output pads;
 a plurality of second switches each connected between two of said output pads;
 first and second charge neutralization pads, said second charge neutralization pad being connected to a most-downstream one of said output pads; and
 a third switch connected between said first charge neutralization pad and a most-upstream one of said output pads,
 said first, second and third switches being turned OFF, ON and ON, respectively, by a first state of a strobe signal,
 said first, second and third switches being turned ON, OFF and OFF, respectively, by a second state of said strobe signal.

9. The apparatus as set forth in claim 8, further comprising a fourth switch connected between said second charge neutralization pad and the most-downstream one of said output pads,
 said fourth switch being turned ON and OFF by the first and second states, respectively, of said strobe signal.

9

10. An apparatus for driving data lines of a liquid crystal display panel, comprising:

- a plurality of voltage followers;
- a plurality of output pads each connected to one of said data lines;
- a plurality of first switches each connected between one of said voltage followers and one of said output pads;
- a plurality of second switches each connected between two of said output pads;
- first and second charge neutralization pads, said first charge neutralization pad being connected to a most-downstream one of said output pads; and
- a third switch connected between said second charge neutralization pad and a most-upstream one of said output pads,
- said first, second and third switches being turned OFF, ON and ON, respectively, by a first state of a strobe signal,
- said first, second and third switches being turned ON, OFF and OFF, respectively, by a second state of said strobe signal.

10

11. An apparatus for driving data lines a liquid crystal display panel comprising:

- a plurality of voltage followers;
- a plurality of output pads each connected to one of said data lines;
- a plurality of first switches each connected between one of said voltage followers and one of said output pads;
- first and second charge neutralization pad;
- a common line connected between said first and second charge neutralization pads; and
- a plurality of second switches each connected between said common line and one of said output pads,
- said first and second switches being turned OFF and ON, respectively, by a first state of a strobe signal,
- said first and second switches being turned ON and OFF, respectively, by a second state of said strobe signal.

* * * * *

专利名称(译)	液晶显示模块能够避免产生肋状图案		
公开(公告)号	US6650312	公开(公告)日	2003-11-18
申请号	US09/894361	申请日	2001-06-28
申请(专利权)人(译)	NEC公司		
当前申请(专利权)人(译)	瑞萨电子公司		
[标]发明人	TAZUKE TOSHIKAZU		
发明人	TAZUKE, TOSHIKAZU		
IPC分类号	G09G3/36 G02F1/133 G09G3/20 H01L21/822 H01L27/04 H04N5/66		
CPC分类号	G09G3/3688 G09G3/3614 G09G2310/0248 H01L24/06 H01L2224/05554 H01L2924/14		
优先权	2000195540 2000-06-29 JP		
其他公开文献	US20020008687A1		
外部链接	Espacenet USPTO		

摘要(译)

在用于驱动液晶显示板的数据线的装置中，提供多个电压跟随器，并且多个输出焊盘连接到数据线。多个第一开关连接在电压跟随器和输出焊盘之间，多个第二开关连接在输出焊盘之间。第一和第二电荷中和垫连接到最上游的一个和最下游的一个输出垫。第三开关分别连接在第一和第二电荷中和垫的一个和输出垫的最上游或最下游的一个之间。

