



US 20100328592A1

(19) **United States**

(12) **Patent Application Publication**
Nagai et al.

(10) **Pub. No.: US 2010/0328592 A1**
(43) **Pub. Date: Dec. 30, 2010**

(54) **TRANSFLECTIVE
LIQUID-CRYSTAL-DISPLAY DEVICE**

(30) **Foreign Application Priority Data**

Mar. 7, 2006 (JP) 2006-061383

(76) Inventors: **Hiroshi Nagai**, Kanagawa (JP);
Michiaki Sakamoto, Kanagawa
(JP); **Kenichi Mori**, Kanagawa
(JP); **Kenichirou Naka**, Kanagawa
(JP); **Hidenori Ikeno**, Kanagawa
(JP)

Publication Classification

(51) **Int. Cl.**
G02F 1/1335 (2006.01)

(52) **U.S. Cl.** **349/114**

Correspondence Address:
HAYES SOLOWAY P.C.
3450 E. SUNRISE DRIVE, SUITE 140
TUCSON, AZ 85718 (US)

(57) **ABSTRACT**

A LCD device has a LC layer sandwiched between a TFT substrate and a counter substrate, first and second polarizing films, a first $\lambda/2$ film between the first polarizing film and the counter substrate, and a second $\lambda/2$ film between the second polarizing film and the TFT substrate. Angle θ_1 between the direction of the optical axis of the LC layer and the polarized direction of the light entering the LC layer satisfies the relationship: $0 \text{ degree} < \theta_1 < 45 \text{ degrees}$. The resultant LCD device has lower leakage light and coloring.

(21) Appl. No.: **12/873,108**

(22) Filed: **Aug. 31, 2010**

Related U.S. Application Data

(62) Division of application No. 11/682,646, filed on Mar. 6, 2007.

10C




FIG. 1A




FIG. 1B

10B




FIG. 1C




FIG. 2




FIG. 3A




FIG. 3B




FIG. 4A




FIG. 4B




FIG. 5A




FIG. 5B




FIG. 6A




FIG. 6B




FIG. 7A

FIG. 7B





FIG. 8A




FIG. 8B




FIG. 9




FIG. 10A




FIG. 10B




FIG. 10C




FIG. 10D




FIG. 11A




FIG. 11B




FIG. 12A




FIG. 12B




FIG. 12C




FIG. 12D




FIG. 13A




FIG. 13B




FIG. 13C




FIG. 13D




FIG. 14A




FIG. 14B




FIG. 14C




FIG. 14D




FIG. 15A




FIG. 15B




FIG. 15C




FIG. 15D




FIG. 16A




FIG. 16B




FIG. 17A




FIG. 17B




FIG. 17C




FIG. 17D




FIG. 18

10a




FIG. 19

		$Nz \leq 0.3$	$Nz \leq 1.0$
POLARIZING FILM	11	15	15
$\lambda/2$ WAVELENGTH FILE	18	97.5	97.5
LC LAYER	13	90	90
RETARDATION FILM	20	90.0	90.0
$\lambda/2$ WAVELENGTH FILE	19	82.5	82.5
POLARIZING FILM	15	75	75

FIG. 20




FIG. 21




FIG. 22A




FIG. 22B





FIG. 23



TRANSFLECTIVE LIQUID-CRYSTAL-DISPLAY DEVICE

BACKGROUND OF THE INVENTION

[0001] 1. Field of the Invention

[0002] The present invention relates to a transflective liquid-crystal-display (LCD) device and, more particularly, to a transflective LCD device having a transmissive area and a reflective area in each pixel of the LCD device.

[0003] 2. Description of the Related Art

[0004] LCD devices are roughly categorized into two types including a transmissive LCD device and a reflective LCD device. In general, the transmissive LCD device has a backlight unit and controls the transmission amount of light from the backlight unit to thereby represent an image on the screen. The reflective LCD device has a reflection film that reflects light incident from the outside and uses the light reflected by the reflection film as a light source to represent an image. That is, the reflective LCD device does not require the backlight unit, and is more advantageous than the transmissive LCD device in terms of a reduction in power dissipation, thickness, and weight. However, since the reflective LCD device uses the background light as the light source, visibility of the image is degraded if the background of the LCD device is dark.

[0005] As a LCD device having both advantages of the reflective LCD device and transmissive LCD device, a transflective LCD device is known (refer to, e.g., JP-2003-344837A, FIGS. 4 and 20, columns 0009 to 0019, columns 0045 to 0048). The transflective LCD device has a transmissive area and a reflective area in each pixel of the LCD device. The transmissive area transmits the light emitted from a backlight unit and uses the backlight unit as a light source for representing the image. The reflective area has a reflection film and uses the light incident thereto from the outside and reflected by the reflection film as the light source. In the transflective LCD device, if the background of the LCD device is light, the image is represented on the screen by using the reflective area, with the backlight unit being turned off, to thereby achieve a reduction in power dissipation. On the other hand, if the background of the LCD device is dark, the backlight unit is turned on to represent the image by using the transmissive area, thereby enabling the image to be represented on the screen even in a dark background.

[0006] A lateral electric-field LCD device such as an in-plane-switching mode (IPS mode) is known as a display mode of the LCD device. The LCD device has a pixel electrode and a common electrode formed in each pixel on the common substrate, and these electrodes apply therebetween a lateral electric field to a liquid crystal (LC) layer. The IPS-mode LCD device rotates the LC molecules in the LCD layer in the direction parallel to the surface of the substrate so as to represent the image, thereby achieving a wider viewing angle than a twisted-nematic(TN)-mode LCD device.

[0007] If the IPS mode is adopted in the transflective LCD device, a problem arises in that the black image and the white image are inverted between both the areas, as described in the technique of the above patent publication. More specifically, if the transmissive area is set at a normally-black mode, the reflective area will have a normally-white mode. The problem of the image inversion will be described hereinafter for a better understanding of the present invention.

[0008] FIG. 22A schematically shows the sectional view of the transflective LCD device, wherein a double-sided arrow

shows the direction of polarization axis of the polarizing film as viewed parallel to the substrate. FIG. 22B shows the polarized direction of light in both the reflective and transmissive areas **55** and **56** for the structure of FIG. 22A, upon emission of the light at the first polarizing film **51**, LC layer **53** and second polarizing film **52**. In FIG. 22B, the double-sided arrow depicts the linearly-polarized light, a thick arrow represents the traveling direction of the light, a circled "R" denotes a clockwise-circularly-polarized light, a circled "L" denotes a counterclockwise-circularly-polarized light, and a hollow bar denotes the direction of LC director (molecules). FIG. 22A shows the state of a single pixel including the reflective area **55** and the transmissive area **56**. The reflective area **55** uses the reflected light from a reflection film **54** as a light source, and the transmissive area **56** uses the backlight unit as a light source.

[0009] The polarizing film (first polarizing film) **51** on the light emitting side is a common polarizing film effecting on both the reflective and transmissive areas **55** and **56**, whereas the polarizing film (second polarizing film) **52** is a dedicated polarizing film effecting on the light incident side of the transmissive area **56**. These polarizing films **51** and **52** are arranged such that the polarizing axes thereof cross at right angles.

[0010] In the LC layer **53**, LC molecules are arranged such that the molecular direction upon absence of applied voltage is shifted by 90 degrees relative to direction of the polarization axis (optical transmission axis) of the second polarizing film **52**. Assuming that the direction of the polarization axis of the second polarizing film **52** shown in FIG. 22A is the reference direction, or at 0 degree, the direction of the polarization axis of the first polarizing film **51** is set at 90 degrees and the initial direction of the longitudinal axis of LC molecules in the LC layer **53** is set at 90 degrees, as shown in FIG. 22A.

[0011] In the transmissive area of the LC layer **53**, the cell gap of the LC layer **53** is adjusted such that the retardation $\Delta n d$ (Δn is the refractive index anisotropy of LC molecules and "d" is the cell gap) assumes $\lambda/2$ (λ is the wavelength of light; for example, in the case of green light, λ is 550 nm) and in the reflective area **55** of the LC layer **53**, the cell gap is adjusted such that the retardation assumes $\lambda/4$. The image represented on the screen of the LCD device will be described hereinafter in the case of absence and presence of applied voltage for the respective areas **55** and **56**.

<Reflective Area Upon Absence of Applied Voltage>

[0012] The image in the reflective area **55** upon absence of applied voltage (V_{off}) on the LC layer **53** will be described first with reference to the leftmost column of FIG. 22B. In the reflective area **55**, 90-degree linearly-polarized light passing through the first polarizing film **51** enters the LC layer **53**. The direction of the optical axis of the linearly-polarized light that has entered the LC layer **53** and direction of the longitudinal axis of LC molecules are aligned in this case, whereby the 90-degree linearly-polarized light is passed through the LC layer **53** without a change in the polarization and is reflected by the reflection film **54**. Thus, the 90-degree linearly-polarized light enters the LC layer **53** once again without a change. The 90-degree linearly-polarized light is thus emitted through the LC layer **53** and enters the first polarizing film **51**. Since the direction of the polarization axis of the first polarizing film **51** is set at 90 degrees, the linearly-polarized light is passed

through the first polarizing film **51**. As a result, a bright image (white image) is represented upon Voff of the LCD device.

<Reflective Area Upon Presence of Applied Voltage>

[0013] Next, the state in the reflective area **55** upon presence of applied voltage on the LC layer **53** will be described with reference to the second leftmost column in FIG. 22B. A 90-degree linearly-polarized light passing through the first polarizing film **51** enters the LC layer **53**. Here, the applied voltage causes the direction of the longitudinal axis of LC molecules in the LC layer **53** to be changed from 0 degree to 45 degrees with respect to the surface of the substrate. Since the polarized direction of the light that has entered the LC layer **53** is deviated by 45 degrees from the direction of the longitudinal axis of LC molecules and the retardation of the liquid crystal is set at $\lambda/4$, the 90-degree linearly-polarized light that has entered the LC layer **53** assumes a clockwise-circularly-polarized light, which enters the reflection film **54**. The clockwise-circularly-polarized light is reflected by the reflection film to be changed into a counterclockwise-circularly-polarized state. The counterclockwise-circularly-polarized light that has entered the LC layer **53** passes therethrough once again to be changed into a horizontal (0-degree) linearly-polarized light. The horizontal-linearly-polarized light then enters the first polarizing film **51**. Since the direction of the polarization axis of the first polarizing film **51** is at 90 degrees, the light reflected by the reflection film **54** cannot be passed through the first polarizing film **51**, with the result that a dark image (black) is represented on the screen.

[0014] As described above, the reflective area **55** assumes a normally white mode in which a bright image (white) is represented upon absence of applied voltage (Voff) and a dark image (black) is represented upon presence of applied voltage (Von).

<Transmissive Area Upon Absence of Applied Voltage>

[0015] Next, the state in the transmissive area **56** upon absence of applied voltage on the LC layer **53** will be described with reference to the second rightmost column in FIG. 22B. In the transmissive area **56**, a horizontal-linearly-polarized light passing through the second polarizing film **52** enters the LC layer **53**. The polarized direction of the incident light and longitudinal direction of LC molecules cross each other at right angles, whereby the horizontal-linearly-polarized light is passed through the LC layer **53** without a change in the polarization and enters the first polarizing film **51**. Since the direction of the polarization axis of the first polarizing film **51** is at 90 degrees, the transmitted light cannot be passed through the first polarizing film **51**, resulting in display of a dark image on the screen.

<Transmissive Area Upon Presence of Applied Voltage>

[0016] Next, the state in the transmissive area **56** upon presence of applied voltage on the LC layer **53** will be described with reference to the rightmost column in FIG. 22B. In the transmissive area **56**, a horizontal-linearly-polarized light passing through the second polarizing film **52** enters the LC layer **53**. Here, the applied voltage causes the direction of the longitudinal axis of LC molecules in the LC layer **53** to be changed from zero degree to 45 degrees with respect to the surface of the substrate. Thus, the polarized direction of the light that has entered the LC layer **53** is shifted to 45 degrees with respect to the direction of the longitudinal

axis of LC molecules. Since the retardation of the LC layer is set at $\lambda/2$, the horizontal-linearly-polarized light that has entered the LC layer **53** is changed into a vertical-linearly-polarized light and enters the first polarizing film **51**. As a result, in the transmissive area **56**, the first polarizing film **51** passes the backlight transmitted thereto through the second polarizing film **52**, resulting in representing a bright image on the screen.

[0017] As described above, the transmissive area **56** assumes a normally black mode in which a dark image is represented upon absence of applied voltage (Voff) and a bright image is represented upon presence of applied voltage (Von).

[0018] In the above configuration, the transmissive LCD device has a disadvantage in that a dark image and a bright image are inverted between the reflective area **55** and the transmissive area **56** upon both the presence and absence of the applied voltage on the LC layer **53**. A technique to solve this disadvantage is described in the above patent publication. FIG. 23 shows a sectional view of the LCD device described in the patent publication. In this technique, the direction of the polarization axis of the first polarizing film **51** is shifted by 45 degrees from the direction of the longitudinal axis of LC molecules in the LC layer **53**. The mere arrangement of the polarization axis of the first polarizing film **51** and the longitudinal axis of LC molecules in the LC layer **53** will cause the reflective area **55** using the reflection film **54** as the light source to assume a normally black mode and cause the transmissive area **56** using the backlight unit **57** as the light source to assume a normally white mode. In addition thereto, a $\lambda/2$ film **58** is inserted between the second polarizing film **52** and the LC layer **53** to thereby change the transmissive area **56** into a normally black mode, which accords the normally black mode of the reflective area **55**.

[0019] The direction of the optical axis of the $\lambda/2$ film **58** that crosses the direction of the longitudinal axis of the LC layer **53** at right angles is set at 135 degrees. Thus, in front view of the LCD device, optical compensation is achieved wherein the polarization effect that the LC layer **53** having a retardation of $\lambda/2$ exerts on the light compensates the polarization effect of the $\lambda/2$ film. The optical compensation achieves that the polarized state of light is not changed between the incidence and emission thereof, in consideration of the polarization of light effected by the LC layer **53** and $\lambda/2$ film **58** as a whole. Therefore, the light passing through the second polarizing film **52** to assume the horizontal-linearly-polarized light is passed through the LC layer **53** and $\lambda/2$ film **58** without a change in the polarization and cannot be passed through the first polarizing film **51** having an optical axis set at the vertical direction. That is, the insertion of the $\lambda/2$ film **58** between the LC layer **53** and the second polarizing film **52** causes the transmissive area **56** to assume also a normally black mode.

[0020] However, in the LCD device **50a** shown in FIG. 23, the polarized direction of the light that enters the LC layer **53** and direction of the longitudinal axis of the LC molecules in the LC layer **53** are not parallel or perpendicular to each other in the transmissive area **56**. This leads to a disadvantage in that leakage light cannot be suppressed sufficiently, upon display of a dark image, in the transmissive area **56** due to wavelength dispersion characteristics of retardation in the LC layer **53**. Further, the $\lambda/2$ film **58** also has wavelength dispersion characteristics, thereby causing leakage light due to the wavelength dispersion upon display of a dark image.

[0021] In order for solving the above problem, a configuration may be also considered wherein absence of applied voltage in the transmissive area **56** is achieved upon presence of applied voltage in the reflective area by inverting the voltage applied to the transmissive area to thereby apply the inverted voltage to the reflective area. However, such a device scheme or drive technique that can realize this configuration is not known in the art. In addition, problems encountered by this configuration as well as the countermeasures for solving the problems are not known in the art.

[0022] Next, in an IPS-mode transfective LCD device, a configuration will be considered in which a first polarizing film, a first $\lambda/2$ film, a first $\lambda/4$ film, a first LC-layer compensation film (positive or negative $\lambda/4$ film), an LC layer, a second LC-layer compensation film (positive or negative $\lambda/4$ film), a second $\lambda/4$ film, a second $\lambda/2$ film, and a second polarizing film are consecutively layered one on another from the light emitting side. In this configuration, each of the first polarizing film, $\lambda/2$ film, $\lambda/4$ film and second polarizing film, $\lambda/2$ film, $\lambda/4$ film are so arranged as a broadband $\lambda/4$ film.

[0023] If the first and second LC-layer compensation films each are a positive $\lambda/4$ film, these films are arranged such that the optical axes thereof cross the direction of the longitudinal axis of LC molecules at right angles. On the other hand, if the first and second LC-layer compensation films each are a negative $\lambda/4$ film, these films are arranged such that the optical axes thereof are parallel to the direction of the longitudinal axis of LC molecules. As a result, the LC layer is configured as a $\lambda/2$ film.

[0024] Accordingly, the effective retardation $\Delta n d$ of the first and second LC-layer compensation films and LC layer in total assumes 0 in the state of initial orientation of the LC molecules, thereby providing a dark image in a normally black mode in both the transmissive area and reflective area. However, in this configuration, it is impossible to completely perform phase compensation of the polarized light if the birefringence wavelength dispersion differs between the LC-layer compensation film and the LC layer. Further, it is difficult to perform a gap control for the LC layer. As a result, leakage light and/or coloring (chromaticity shift) occurs during display of a dark image. Therefore, the birefringence wavelength dispersion of a material used for the compensation layer and wavelength dispersion of the LC layer need to correspond to each other. Thus, there remains the problem that cannot be solved only by the device configuration.

SUMMARY OF THE INVENTION

[0025] It is an object of the present invention to provide a transfective LCD device capable of reducing coloring or leakage light, upon display of a dark image, due to wavelength dispersion of the LC layer.

[0026] It is another object of the present invention to provide a transfective LCD device capable of eliminating the problems related to inversion of bright and dark image between in the transmissive area and in the reflective area, without requiring a complicated structure in order for processing data signals in the LCD device.

[0027] The present invention provides a transfective liquid-crystal-display (LCD) device including: a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area; first and second polarizing films sandwiching therebetween the LC layer, the first polarizing film being effective common to the transmissive area and the reflective area, the second polarizing film being effective

to the transmissive area; and a retardation film sandwiched between the first polarizing film and the LC layer.

[0028] In accordance with the LCD device of the present invention, the retardation film provided between the first polarizing film and the LC layer compensates the wavelength dispersion of the LC layer upon display of a dark image, thereby suppressing the coloring and/or leakage light of the LCD device. The retardation film may act as a $\lambda/2$ -wavelength film (or $\lambda/2$ film) at a wavelength of 550 nm.

[0029] The above and other objects, features and advantages of the present invention will be more apparent from the following description, referring to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0030] FIG. 1A is a sectional view showing the structure of a transfective LCD device according to a first embodiment of the present invention, and FIGS. 1B and 1C are modification from the structure of FIG. 1A;

[0031] FIG. 2 is a top plan view showing the structure of the LCD device according to the first embodiment of the present invention;

[0032] FIGS. 3A and 3B are waveform diagrams each showing potential change of the pixel electrodes **35** and **36** after the pixel data signal has been supplied to the pixel electrodes **35** and **36**;

[0033] FIG. 4A is a waveform diagram showing a drive signal for the reflective area **21** in a specific stage, and FIG. 4B is a waveform diagram showing a drive signal for the transmissive area **22** in the same specific stage;

[0034] FIGS. 5A and 5B are schematic sectional views showing light polarization states in the reflective and transmissive areas when the signals shown in FIGS. 4A and 4B are applied;

[0035] FIG. 6A is a waveform diagram showing a drive signal for the reflective area **71** in a stage different from FIG. 4, and FIG. 6B is a waveform diagram showing a drive signal for the transmissive area **22** in the same phase as FIG. 6A;

[0036] FIGS. 7A and 7B are schematic sectional views showing light polarization states in the reflective and transmissive areas when the signals shown in FIGS. 6A and 6B are applied;

[0037] FIGS. 8A and 8B are diagrams each obtained by simulation and showing electric field distribution and light transmittance in a dark state;

[0038] FIG. 9 is a sectional view showing the structure of the reflection film **16** right under the pixel electrodes **35** and **36** and common electrode **37**;

[0039] FIGS. 10A to 10D show a fabrication step of process for manufacturing the TFT substrate, wherein FIG. 10A depicts a top plan view thereof, and FIGS. 10B to 10D depict sectional views taken along respective lines shown in FIG. 10A;

[0040] FIGS. 11A and 11B show a fabrication step subsequent to the step of FIGS. 10A to 10D, wherein FIG. 10A depicts a top plan view thereof, and FIG. 11B depicts a sectional view taken along line D-D' in FIG. 11B.

[0041] FIGS. 12A to 12D show a fabrication step subsequent to the step of FIGS. 11A and 11B, wherein FIG. 12A is a top plan view thereof, and FIGS. 10B to 10D depict sectional views taken along respective lines shown in FIG. 12A;

[0042] FIG. 13A to 13D show a fabrication step subsequent to the step of FIGS. 12A to 12D, wherein FIG. 13A is a top

plan view thereof, and FIGS. 13B to 13D depict sectional views taken along respective lines shown in FIG. 13A;

[0043] FIGS. 14A to 14D show a fabrication step subsequent to the step of FIGS. 13A to 13D, wherein FIG. 14A is a top plan view thereof, and FIGS. 14B to 14D depict sectional views taken along respective lines shown in FIG. 14A;

[0044] FIGS. 15A to 15D show a fabrication step subsequent to the step of FIGS. 14A to 14D, wherein FIG. 15A is a top plan view thereof, and FIGS. 15B to 15D depict sectional views taken along respective lines shown in FIG. 15A;

[0045] FIGS. 16A and 16B show a fabrication step subsequent to the step of FIGS. 15A to 15D, wherein FIG. 16A is a top plan view thereof, and FIG. 16B depicts a sectional view taken along line E-E' shown in FIG. 16A;

[0046] FIG. 17A to 17D show a fabrication step subsequent to the step of FIGS. 16A and 16B, wherein FIG. 17A is a top plan view thereof, and FIGS. 17B to 17D depict sectional views taken along respective lines shown in FIG. 17A;

[0047] FIG. 18 is a schematic sectional view showing the structure of a transfective LCD device according to a second embodiment of the present invention;

[0048] FIG. 19 is a table showing a suitable combination of the optical transmission axis of the polarizing films, direction of the longitudinal axis of LC molecules in the LC layer, direction of the optical axis of the $\lambda/2$ films with respect to the surface of the substrate;

[0049] FIG. 20 is a schematic view showing the polarized state of the light in the LCD device of the second embodiment;

[0050] FIG. 21 is a sectional view showing the reflection film 16 right under the pixel electrode 34 and common electrode 35;

[0051] FIG. 22A is a schematic sectional view showing a conventional transfective LCD device, and FIG. 22B is a schematic view showing the polarized state of light in the reflective and transmissive areas of the LCD device of FIG. 22A when the light is passed through the first polarizing film, LC layer, and second polarizing film; and

[0052] FIG. 23 is a sectional view showing the structure and polarized state of the light in the conventional transfective LCD device described in a patent publication.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0053] Embodiments of the present invention will be described below in detail with reference to the accompanying drawings. FIG. 1A shows the sectional structure of a LCD device according to a first embodiment of the present invention. The LCD device, generally designated at numeral 10, includes a first polarizing film 11, a first $\lambda/2$ film 18, a counter substrate 12, a LC layer 13, a TFT substrate 14, a second $\lambda/2$ film 19, and a second polarizing film 15, which are consecutively layered from the front side of the LCD device 10.

[0054] The LCD device 10 is configured as a transfective LCD device having a reflective area 21 and a transmissive area 22 in each pixel of the LCD device 10. In the reflective area 21, a reflection film 16 and an insulating film 17 are formed on the TFT substrate 14. The reflection film 16 reflects the incident light incident through the first polarizing film 11. In order to enhance light dispersion effect, the reflection film 16 typically has a rough surface.

[0055] A pixel electrode 35 for driving LC molecules and a common electrode 37 for supplying a reference potential are formed on the insulating film 17 in the reflective area 21. On

the other hand, a pixel electrode 36 and a common electrode 38 are formed on the TFT substrate 14 in the transmissive area 22. The reflective area 21 uses the light reflected by the reflection film 16 as the light source for representing the image on the screen. The LCD device 10 has a backlight unit (not shown in the figure) below the second polarizing film 15, and the transmissive area 22 uses the backlight unit as the light source for representing the image on the screen.

[0056] In the transmissive area 22, the cell gap of the LC layer 13 is adjusted such that the retardation of the LC layer 13 assumes nearly $\lambda/2$. The reason for setting the retardation to "nearly $\lambda/2$ " is to obtain an effective retardation of $\lambda/2$ by actually setting the retardation at $(\lambda/2)+\alpha$. This margin is necessary because, when the presence of applied voltage on the LC layer 13 rotates LC molecules, the LC molecules are rotated only in the central area of the cell gap, with the rotation of the LC molecules being suppressed near both the substrates. Assuming that retardation of the LC layer 13 is set at $\Delta n d = 300$ nm, the effective retardation upon presence of applied voltage assumes $\Delta n_{eff} d = \lambda/2 = 550/2 = 275$ nm. On the other hand, in the reflective area 21, the cell gap is adjusted such that the effective retardation of the LC layer 13 upon presence of applied voltage assumes $\lambda/4$ by setting a suitable thickness for the insulating film 17.

[0057] In the transmissive area 22, upon display of a dark image, the linearly-polarized light emitted from the backlight unit and passing through the second polarizing film 15 is passed through the second $\lambda/2$ film 19, LC layer 13, and first $\lambda/2$ film 18 and enters the first polarizing film 11. In the configuration of the LCD device 10, the angle of the polarization axis and direction of the longitudinal axis of LC molecules are set such that the light entering the first polarizing film 11 assumes a linearly-polarized light and the polarized direction thereof corresponds to the direction of the absorption axis of the first polarizing film 11. Further, angle θ_1 between the direction of the optical axis (or optical axis+90 degrees) of the LC layer 13 and the polarized direction of the light entering the LC layer 13 upon display of a dark image is set to satisfy the following relationship:

$$0 \text{ degree} < \theta_1 < 45 \text{ degrees,}$$

and preferably satisfy the following relationship:

$$0 \text{ degree} < \theta_1 \leq 22.5 \text{ degrees.}$$

[0058] In the description to follow, direction of the optical transmission axis of the first polarizing film 11 is set at 27 degrees, direction of the optical axis of the first $\lambda/2$ film 18 is set at 109.5 degrees, light transmission axis of the second polarizing film 15 is set at 63 degrees, direction of the optical axis of the second $\lambda/2$ film 19 is set at 70.5 degrees, direction of the longitudinal axis of LC molecules in the LC layer 13 upon absence of applied voltage is set at 90 degrees, and angle θ_1 between the linearly-polarized light entering the LC layer 13 from the second $\lambda/2$ film 19 and direction of the optical axis (direction of the longitudinal axis) of the LC molecules is set at 12 degrees.

[0059] FIGS. 1B and 1C show modifications from FIG. 1A. In FIG. 1B, the $\lambda/2$ film 18 is provided between the LC layer 13 and the counter substrate 12, in both the transmissive and reflective areas 21 and 22, whereas in FIG. 1C, a retardation film 18a acting as a $\lambda/4$ film in association with the LC layer 13 is provided between the LC layer 13 and the counter substrate 12 only in the reflective area. It is sufficient in the

LCD device of the present invention that the retardation film **18** or **18a** be provided between the first polarization film **11** and the LC layer **13**.

[0060] FIG. 2 shows a top plan view of the TFT substrate **14** of the LCD device **10** shown in FIG. 1A, depicting the configuration of a single pixel therein. A gate line **31** and a data line **32** that cross each other at right angles are formed on the substrate **14**. Near the intersection between the gate line **31** and the data line **32**, TFTs **33** and **34** are formed in the reflective area **21**, and transmissive area **22**, respectively. The gate of the TFTs **33** and **34** is connected to the gate line **31**, and one of the source and drain thereof are connected to the data line **32**. The other of the source and drain of the TFTs **33** and **34** are connected to the pixel electrode **35** in the reflective area **21** and pixel electrode **36** in the transmissive area **22**, respectively.

[0061] The first and second common electrodes **37** and **38** correspond to the reflective area **21** and transmissive area **22**, respectively, of each pixel and have a part that extends along the gate line **31** and a part that protrudes toward the display area of the pixel. The first common electrode **37** is formed in the reflective area **21** at the position opposite to the pixel electrode **35** within the substrate plane. The second common electrode **38** is formed in the transmissive area **22** at the position opposite to the pixel electrode **36** within the substrate plane. A signal having a predetermined signal waveform and common to the array of pixels in the LCD device **10** is supplied to the first and second common electrodes **37** and **38**. In the reflective area **21**, the orientation of the LC layer **13** is controlled by an electric field corresponding to the potential difference between the pixel electrode **35** and the first common electrode **37**. In the transmissive area **22**, the orientation of the LC layer **13** is controlled by an electric field corresponding to the potential difference between the pixel electrode **36** and the second common electrode **38**.

[0062] The pixel electrode **35** for the reflective area **21** and pixel electrode **36** for the transmissive area **22** are connected to the respective TFTs **33** and **34**. TFTs **33** and **34** are connected to a common gate line **31** and to a common data line **32**, whereby a common data signal is written in the pixel electrodes **35** and **36** when the TFTs **33** and **34** are turned on. The reason for the reflective area **21** and transmissive area **22** to use respective TFTs **33** and **34** and the respective pixel electrodes **35** and **36**, in spite of the common data signal being written in the pixel electrode **35** for the reflective area **21** and pixel electrode **36** for transmissive area **22**, is that the potential fluctuation is different between the pixel electrode **36** in the transmissive area **22** and the pixel electrode **35** in the reflective area **21**, after the TFTs **33** and **34** have been turned off.

[0063] FIGS. 3A and 3B show the potential profile of the pixel electrodes **35** and **36** after the common pixel signal has been supplied to the pixel electrodes **35** and **36**. For example, the polarity of the drive signal is inverted line by line in a gate-line-inversion drive scheme, whereby the potential of the first and second common electrodes **37** and **38** is iteratively inverted in accordance with the polarity inversion of each line during the time period between application of a gate signal pulse to the gate line **31** and another application of a gate signal pulse to the gate line **31** in the next frame.

[0064] Since the TFTs **33** and **34** are off at this stage, the pixel electrodes **35** and **36** are disconnected from the data line **32** to be in a floating state and, as shown in FIGS. 3A and 3B, the potential thereof is fluctuated in accordance with the

potential profile of the first and second common electrodes **37** and **38**, while keeping the potential difference upon the write of signal due to the coupling capacitance between the pixel electrode **35** and the first common electrode **37** and between the pixel electrode **36** and the second common electrode **38**. As described above, the potential profile of the pixel electrodes **35** and **36** after the supply of pixel signal differs between the reflective area **21** and transmissive area **22**. Thus, the pixel electrode should be separated between the reflective area **21** and transmissive area **22**.

[0065] FIG. 4A shows a drive signal waveform of the reflective area **21** in a specific stage, and FIG. 4B shows a drive signal waveform of the transmissive area **22** in the same specific stage. The LCD device **10** is driven by first and second common signals having an alternating voltage and, in each pixel, the potential (signal) applied to the first and second common electrodes **37** and **38** is inverted between, e.g., 0V and 5V in each frame, as shown in FIGS. 4A and 4B. Further, the inverted signal of the first common signal applied to the first common electrode **37** is applied to the second common electrode **38** as a second common signal.

[0066] A specific pixel signal ranging, e.g., between 0V and 5V is supplied to the pixel electrodes **35** and **36**. Since the TFTs **33** and **34** are connected to the common data line **32**, a common pixel signal is supplied to the pixel electrodes **35** and **36**. As shown in FIG. 4A, when a 0V data signal is supplied to the pixel electrode **35** and a 5V common signal is applied to the first common electrode **37** in the *i*-th frame ("*i*" is a natural number), the potential difference between the pixel electrode **35** and the first common electrode **37** assumes 5V. Thus, in the reflective area **21**, the LC layer **13** is driven by an electric field corresponding to a 5V potential difference. At this stage, a 0V signal is applied to the second common electrode **38**, whereby the potential difference between the pixel electrode **36** and the second common electrode **38** assumes 0V. Thus, the LC molecules in the LC layer **13** are not driven in the transmissive area **22**.

[0067] FIGS. 5A and 5B show polarization of the light in the reflective area **21** and transmissive area **22**, respectively, upon application of the signals shown in FIGS. 4A and 4B. When the signal shown in FIG. 4A is applied, the orientation direction of LC molecules in the LC layer **13** in the reflective area **21** is rotated by 33 degrees (=45 degrees- θ_1 (=12 degrees)) due to the electric field between the pixel electrode **35** and the first common electrode **37**. That is, the direction of the longitudinal axis of LC molecules is changed from 90 degrees to 57 degrees.

[0068] In the reflective area **21**, as shown in FIG. 5A, light that has entered the first polarizing film **11** from the outside of LCD device has been passed through the first polarizing film **11** to assume a 27-degree linearly-polarized light. The polarized direction of the 27-degree-linearly-polarized light is changed to 12 degrees after being passed through the first $\lambda/2$ film **18** and the 12-degree linearly-polarized light enters the LC layer **13** at an incident angle of 45 degrees with respect to the optical axis of the LC layer. The polarization of this incident light is changed upon being passed through the LC layer **13** to assume a counterclockwise-circularly-polarized light.

[0069] The counterclockwise-circularly-polarized light is then reflected by the reflection film **16** to be changed to a clockwise-circularly-polarized light. The clockwise-circularly-polarized light is passed through the LC layer **13** once again to assume a 102-degree linearly-polarized light, which

is then passed through the first $\lambda/2$ film 18 to assume a 117-degree linearly-polarized light. Therefore, the light reflected by the reflection film 16 cannot be passed through the first polarizing film 11, with the result that the reflective area 21 assumes a dark state.

[0070] Although the drive voltage for maintaining the LC molecules at a constant orientation angle is increased in the reflective area 21 due to the narrow gap on the LC layer 13, the orientation angle to which LC molecules are driven is reduced to 33 degrees due to the angle $\theta 1$ being set at 12 degrees. As a result, it is possible to reduce the drive voltage down to 0.9 times, compared to the case where the LC molecules are rotated by 45 degrees.

[0071] On the other hand, in the state where the signal shown in FIG. 4B is applied, an electric field is not generated between the pixel electrode 36 and the second common electrode 38, whereby the direction of orientation of LC molecules in the transmissive area 22 is kept at 90 degrees. In the transmissive area 22, as shown FIG. 5B, 63-degree linearly-polarized light passing through the second polarizing film 15 is changed to 78-degree linearly-polarized light after being passed through the second $\lambda/2$ film 19 and then enters the LC layer 13. The direction of the longitudinal axis of LC molecules in the LC layer is at 90 degrees. Accordingly, the 78-degree linearly-polarized light that has entered the LC layer 13 assumes a 102-degree linearly-polarized light after being passed through the LC layer 13. The 102-degree linearly-polarized light then assumes a 117-degree linearly-polarized light after being passed through the first $\lambda/2$ film 18, which cannot be passed through the first polarizing film 11 having an optical transmission axis at 27 degrees, with the result that the transmissive area 22 assumes a dark state.

[0072] As described above, by inverting the first common signal applied to the first common electrode 37 to apply the inverted common signal to the second common electrode 38, the direction of orientation of LC molecules in the LC layer 13 can be changed only in the reflective area 21 while the common pixel signal is being supplied to the pixel electrodes 35 and 36. As a result, a dark state can be achieved in the transmissive area 22 when the dark state is represented in the reflective area 21. Thus, it is possible to display the dark state both in the reflective and transmissive areas without the need to supply different pixel signals to the reflective and transmissive areas 21 and 22.

[0073] FIG. 6A shows a drive signal waveform of the reflective area 21 in a stage different from the stage shown in FIG. 4, and FIG. 6B shows another drive signal waveform of the transmissive area 22 in the same stage as that of FIG. 6A. FIGS. 7A and 7B show polarization of light in the reflective and transmissive areas 21 and 22 when the signals shown in FIGS. 6A and 6B are applied. In the state where the signal shown in FIG. 6A is applied, an electric field is not generated between the pixel electrode 35 and the first common electrode 37, whereby the direction of orientation of LC molecules in the reflective area 21 is kept at 90 degrees.

[0074] In the reflective area 21, as shown FIG. 7A, a 12-degree linearly-polarized light passing through the first polarizing film 11 and first $\lambda/2$ film 18 is passed through the LC layer 13, reflected by the reflection film 16, and passed once again through the LC layer 13 to assume a -12-degree linearly-polarized light. The -12-degree linearly-polarized light is passed through the first $\lambda/2$ film 18 to assume a 51-degree linearly-polarized light, which enters the first polarizing film 11. Since the direction of optical transmission axis of the first

polarizing film 11 is at 27 degrees, all the components of light assuming a 51-degree linearly-polarized light and reflected by the reflection film 16 travels toward the first polarizing film 11; however, cannot pass through the first polarizing film 11. In this state, a highest reflectivity achieving a highest luminance is obtained, whereby the reflective area 21 assumes a bright state.

[0075] The angle deviation between the polarized direction of light entering the first polarizing film 11 from the reflection film 16 in a bright state and the direction of the optical transmission axis of the first polarizing film 11 can be represented by $\theta 1 \times 2$. More specifically, if the angle $\theta 1$ is set at zero degree, the brightest image can be displayed and, for example, the reflectivity obtained when $\theta 1$ is set at 12 degrees assumes 0.9 times the case where $\theta 1$ is set at zero degree.

[0076] As described above, by increasing the angle $\theta 1$, the angle by which LC molecules are driven can be reduced to thereby reduce a drive voltage. However, there is a tradeoff in the relationship between the decrease in the drive voltage and increase in the reflectivity. In designing a LCD device, the angle $\theta 1$ should be set in consideration of a balance between the drive voltage and the reflectivity.

[0077] In a state where the signal shown in FIG. 6B is applied, the direction of orientation of LC molecules in the LC layer 13 in the transmissive area 22 is rotated by 45 degrees due to the electric field between the pixel electrode 36 and the second common electrode 38. Thus, in the transmissive area 22, as shown in FIG. 7B, a 78-degree linearly-polarized light passing through the second polarizing film 15 and second $\lambda/2$ film 19 is rotated by 90 degrees relative to the angle upon display of a dark image after being passed through the LC layer 13, to thereby assume a 12-degree linearly-polarized light. The 12-degree linearly-polarized light then enters the first $\lambda/2$ film 18 to assume a 27-degree linearly-polarized light, which enters the first polarizing film 11. As a result, the transmissive area 22 assumes a bright state.

[0078] As described above, by inverting the signal applied to the first common electrode 37 to apply the inverted signal to the second common electrode 38, a bright state can be achieved in the transmissive area 22 upon representing the bright image in the reflective area 21. Thus, it is possible to achieve the dark state both in the reflective and transmissive areas by using the signals shown in FIGS. 6A and 6B.

[0079] In the present embodiment, the common electrode is divided into the first and second common electrodes 37 and 38 so that the first and second common electrodes 37 and 38 correspond to the reflective area 21 and transmissive area 22, respectively. Opposite signals or inverted signals, which allow magnitude of the electric fields applied to the LC layer 13 to be reversed between the reflective area 21 and the transmissive area 22, are supplied to the first and second common electrodes 37 and 38. This enables the reflective area 21 and the transmissive area 22 of each pixel to provide the same image without the need to supply different pixel signals to the reflective area 21 and transmissive area 22, thereby eliminating the disadvantage that the inverted data signals must be applied between the reflective area and the transmissive area of each pixel in the IPS-mode transmissive LCD device.

[0080] In the structure of the LCD device 10C shown in FIG. 1C, the retardation film 18a provided only in the reflective area and acting as the $\lambda/4$ film in association with the LC

layer 13 has a function similar to that of the LC layer 13 described in the conventional structure. More specifically, a 90-degree linearly-polarized light passing through the first polarizing film 51 passes the LC layer 53 and the retardation film 18a. Since the polarized direction of the light that has passed the LC layer 53 and the retardation film 18a is deviated by 45 degrees from the direction of the longitudinal axis of LC molecules and the retardation of the liquid crystal and retardation film 18a in combination is set at $\lambda/4$, the 90-degree linearly-polarized light that passes the LC layer 53 and retardation film 18a assumes a clockwise-circularly-polarized light, which enters the reflection film 54. The clockwise-circularly-polarized light is reflected by the reflection film to be changed into a counterclockwise-circularly-polarized state. The counterclockwise-circularly-polarized light that has entered the LC layer 53 passes therethrough once again to be changed into a horizontal (0-degree) linearly-polarized light. The horizontal-linearly-polarized light then enters the first polarizing film 51. Since the direction of the polarization axis of the first polarizing film 51 is at 90 degrees, the light reflected by the reflection film 54 cannot be passed through the first polarizing film 51, with the result that a dark image (black) is represented on the screen. Thus, the configuration of FIG. 1C provides a function similar to the function obtained by the structure of FIG. 1A.

[0081] In the structure of FIG. 1A showing the present embodiment, the angle θ_1 between the direction of orientation of the LC layer 13 and the polarized direction of the light entering the LC layer 13 upon display of a dark image is set to satisfy the relationship;

$$0 \text{ degree} < \theta_1 < 45 \text{ degrees},$$

and preferably the relationship:

$$0 \text{ degree} < \theta_1 \leq 22.5 \text{ degrees}.$$

As a result, it is possible for the LCD device according to the present embodiment to reduce the adverse affect caused by wavelength dispersion characteristics of the LC layer 13 upon display of a dark image, as compared to the conventional transmissive LCD device 50a (FIG. 23), thereby preventing leakage light in a dark state.

[0082] In a typical TN-mode LCD device, a reflection film is configured by a reflection pixel electrode, to which a pixel signal for driving the LC layer in accordance with the desired gray-scale level is supplied. On the other hand, since the LC layer 13 is driven by the electric field generated between the pixel electrode 35 and the common electrode (first common electrode) 37 in the IPS mode, the potential to be applied to the reflection film 16 can arbitrarily be determined. In, the following description, the influence that the potential of the reflection film 16 exerts on the image in the reflective area 21 will be discussed.

[0083] FIGS. 8A and 8B, which are obtained by simulation, show the electric field distribution in the LC layer by using iso-electric lines and light transmittance by using iso-transmittance lines as well as gray scale levels, both in the case of a dark state. FIG. 8A shows the case wherein the pixel electrode 35 applied with a 5V signal and the common electrode 37 applied with a 0V signal maintain the potential of the reflection film, i.e., reflection electrode, 16 at an intermediate potential (2.5V) therebetween. FIG. 8B shows the case wherein the pixel electrode 35 is applied with a 5V signal and the common electrode 37 is applied with a 0V signal, and the potential of the reflection film 16 is maintained at the same potential (0V) as the common electrode 37.

[0084] If the potential of the reflection film 16 assumes an intermediate potential between the pixel electrode 35 and common electrode 37, as shown in FIG. 8A, although leakage light occurs on the pixel electrode 35 and common electrode 37 to increase the transmittance, the leakage light is suppressed at the portion between both the electrodes to reduce the light transmittance. On the other hand, if the potential of the reflection film 16 assumes the same potential as the common electrode 37, as shown in FIG. 8B, leakage light increases in the vicinity of the common electrode 37, as indicated by a thick arrow, to thereby increase the light transmittance in this area. This is considered due to the fact that the electric field between the pixel electrode 35 and the reflection film 16 is strong so that the electric lines of force, which are supposed to converge between the pixel electrode 35 and the common electrode 37, are directed to the reflection film 16, with the result that LC molecules in the vicinity of the common electrode 37 are not sufficiently driven.

[0085] The above simulation reveals that it is preferable that the potential of the reflection film 16 be an intermediate potential between the pixel electrode 35 and the common electrode 37. In this respect, it is possible to control the potential of the reflection film 16 by directly applying a desired potential to the reflection film 16. In an alternative, it is possible to control the potential of the reflection film 16 through capacitive coupling while adopting a floating state thereof. For example, if the floating potential is to be employed, an interconnect that can apply the potential of the pixel electrode 35 and another interconnect that can apply the potential of the common electrode 37 are formed right under the reflection film 16 such that the area ratio between the interconnects assumes 1:1, whereby the potential of the reflection film 16 is controlled at the intermediate potential between the pixel electrode 35 and the common electrode 37.

[0086] Since the leakage light occurs on the pixel electrode 35 and common electrode 37 as shown in FIG. 8A, the brightness upon display of a dark image cannot be sufficiently reduced without using a suitable countermeasure. In order to suppress the influence by the leakage light, patterning should be made such that the reflection film 16 is not formed right under the pixel electrode 35 or common electrode 37, as shown in FIG. 9. This reduces the brightness of reflected light observed at the positions on which the pixel electrode 35 and common electrode 37 are formed, thereby reducing the brightness upon display of a dark image.

[0087] Hereinafter, a fabrication process for the TFT substrate 14 shown in FIG. 1A will be described with reference to FIGS. 10A to 10D through FIGS. 17A to 17D showing respective steps of fabrication. In each of these drawings, the drawing having "A" character attached with the drawing number is a top plan view of the TFT substrate in a specific step, and other figures having the same drawing number attached with "B" to "D" are sectional views showing the same step as the drawing of the corresponding number and taken along lines A-A', B-B' and C-C', respectively, shown in FIG. 10A, unless otherwise specified,

[0088] Firstly, the gate line 31 shown in FIG. 2, a first common electrode line 37a, and a second common electrode line 38a are formed on a substrate body of the TFT substrate, in such patterns as shown in FIG. 10A. Sections of the reflective area 21, transmissive area 22, and the interface (step portion) between the reflective area 21 and the transmissive area 22 obtained at this step are shown in FIGS. 10B to 10D, respectively. In the reflective area 21, the first common elec-

trode line 37a is so formed as to project in the display area, thereby supplying a potential to the reflection film 16. Thereafter, the gate line 31, first common electrode line 37a, and second common electrode line 38a are covered by an insulating film.

[0089] Subsequently, as shown in FIG. 11A, a semiconductor layer 39 for forming thereon the TFT 33 is provided. As shown in FIG. 11B, the semiconductor layer 39 is formed so as to overlap the gate line or gate electrode 31. Thereafter, pixel electrode lines 35a and 36a are formed in such patterns as shown in figure FIG. 12A. The pixel electrode line 35a is connected to one of the ends of the source/drain path of the TFT 33, and the pixel electrode line 36a is connected to the other of the ends of the source/drain path of the TFT 34.

[0090] Sections of the reflective area 21, transmissive area 22, and interface between the reflective area 21 and the transmissive area 22 obtained at this step are shown in figures FIGS. 12B to 12D, respectively. In the reflective area 21, the first common electrode line 37a is formed between adjacent two of the pixel electrode lines 35a. The first common electrode line 37a is formed such that the area ratio between the pixel electrode line 35a and the first common electrode line 37a is 1:1 in the display area. With this configuration, the intermediate potential between the potentials of the pixel electrode 35 and the first common electrode 37 can be applied to the reflection film 16, which is to be formed later. After the formation of the first and second common electrode lines 37a and 38a, these lines are covered by an insulating film.

[0091] Subsequently, an overcoat (OC) layer 40 having a rough surface is formed thereon, as shown in FIGS. 13A to 13D. An aluminum (Al) layer is formed on the rough OC layer 40, and the reflection film 16 is formed thereon in the reflective area 21 in such a pattern as shown in FIG. 14A. Sections of the reflective area 21, transmissive area 22, and interface between the reflective area 21 and transmissive area 22 obtained at this stage are shown in FIGS. 14B to 14D, respectively. As shown in FIG. 14B, in the reflective area 21, the Al layer is selectively etched in the region right under the pixel electrode 35a and first common electrode 37a, to form a reflection film 16 having an opening therein.

[0092] After the formation of the reflection film 16, a flat OC layer 41 is formed in such a pattern as shown in FIG. 15A. The formation of the flat OC layer 41 causes a step difference on the interface between the reflective area 21 and the transmissive area 22 as shown in FIGS. 15B to 15D, with the result that the cell gap is adjusted in the respective areas. Thereafter, contact holes 42 are formed in the insulating 111111 that covers the pixel electrode lines 35a, 36a and first and second common electrode lines 37a, 38b at the portions shown in FIG. 16A to expose the pixel electrode lines 35a and 36a, and the first and second common electrode lines 37a and 38a (FIG. 16B).

[0093] After the formation of the contact holes, the pixel electrodes 35 and 36 and first and second common electrodes 37, 38 are formed on the flat OC layer 41 in such pattern as shown in FIG. 17A. Sections of the reflective area 21, transmissive area 22, and interface between the reflective area 21 and transmissive area 22 obtained at this stage are shown in FIGS. 17B to 17D, respectively. In this fabrication process, these electrodes are connected to the pixel electrode lines 35a, 36a and the first and second common electrode lines 37a, 38a through the contact holes 42. In this manner, the TFT substrate 14 used for the transfective LCD device 10 according to the present embodiment is obtained.

[0094] FIG. 18 shows the sectional structure of a transfective LCD device according to a second embodiment of the present invention. The LCD device, generally designated at numeral 10a, according the second embodiment is similar to the LCD device 10 of the first embodiment shown in FIG. 1A except that a retardation film 20 is disposed between the TFT substrate 14 and the second $\lambda/2$ film 19. In the present embodiment, the angle (31 between the polarized direction of the linearly-polarized light entering the LC layer 13 upon display of a dark image and the direction of the optical axis of the LC layer is set at zero degree in the transmissive area 22.

[0095] Assuming that the retardation film 20 has a refractive index of nx in the direction of the slow axis, a refractive index ny in the direction of the fast axis, a refractive index nz in the thickness direction, and a thickness of d, the following relationship:

$$(nx-nz)/(nx-ny)\leq 0.3; \text{ or}$$

$$(nx-nz)/(nx-ny)=1.0$$

is satisfied. Further, the value defined by:

$$(nx-ny)\times d$$

is set nearly equal to the retardation of the LC layer 13.

[0096] The retardation film 20 is disposed such that the direction of the longitudinal axis of LC molecules in the LC layer 13 and the direction of the fast axis of the retardation film 20 are parallel or perpendicular to each other. If the retardation film 20 satisfies the following relationship:

$$(nx-nz)/(nx-ny)=1.0$$

and is disposed in parallel to the optical axis of the LC layer, it is preferable to use the retardation film 20 having a configuration, wherein the wavelength dispersion of the birefringence is a reverse dispersion.

[0097] FIG. 19 shows a combination of polarizing films, LC layer and retardation films having a suitable relationship of the directions for the polarization axis and optical axis thereof. In this table, the values entered in the columns indicate the angles of the direction of the optical transmission axis of the polarizing films 11 and 15, direction of the longitudinal axis of the LC molecules in the LC layer 13, direction of the in-plane optical axis of the first and second $\lambda/2$ films 18, 19, and direction of the in-plane optical axis of the retardation film 20. In the combination shown in FIG. 19, the polarized direction of light passing through the second polarizing film 15, second $\lambda/2$ film 19 and retardation film 20 and entering the LC layer 13 is determined to be parallel or perpendicular to the direction of the longitudinal axis of LC molecules in the LC layer 13. This configuration is determined for the purpose of preventing the amount of leakage light upon display of a dark image in the transmissive area 22 from being increased, for each case of the refractive index Nz of the thickness direction of the retardation film being $Nz\leq 0.3$ and $Nz=0$.

[0098] The image obtained in the LCD device 10a adopting the combination shown in FIG. 19 will be described with reference to FIG. 20. Image of a dark image will be first described. Upon representing the dark state, the signals shown in FIGS. 4A and 4B may be applied, whereby the direction of the longitudinal axis of LC molecules in the LC layer 13 in the reflective area 21 is rotated to the direction of 45 degrees, whereas the direction of the longitudinal axis of LC molecules in the LC layer 13 in the transmissive area 22 is kept at 90 degrees.

[0099] In the transmissive area 22, the light emitted from the backlight unit is passed through the second polarizing film 15 having an optical transmission axis at 75 degrees, which is equal to the light absorption axis minus 15 degrees, to assume a 75-degree linearly-polarized light. The 75-degree linearly-polarized light is then passed through the second $\lambda/2$ film 19. At this stage, the polarized direction of the 75-degree linearly-polarized light is rotated by an angle equal to double the difference between the same and the direction of the optical axis, 825 degrees, of the second $\lambda/2$ film 19, thereby assuming a 90-degree or 270-degree linearly-polarized light.

[0100] The 90-degree linearly-polarized light is passed through the retardation film 20 and LC layer 13, with the polarized axis being maintained at 90 degrees. Then, the 90-degree linearly-polarized light is passed through the first $\lambda/2$ film 18 to assume a 105-degree linearly-polarized light, which enters the first polarizing film 11. Since the optical transmission axis of the first polarizing film 11 is at 15 degrees, the light transmitted from the backlight unit cannot be passed through the first polarizing film 11, resulting in display of a dark image.

[0101] Although components of the light entering the retardation film 20 and LC layer 13, other than the component having a wavelength of 550 nm, assume an elliptically-polarized light due to the wavelength dispersion by the first and second $\lambda/2$ films 18 and 19, the retardation film 20 compensates the wavelength dispersion of the components of the linearly-polarized light entering the LC layer 13, other than the component having a wavelength of 550 nm, to thereby suppress leakage light or coloring on the light emitting side.

[0102] In the reflective area 21, the 15-degree linearly-polarized light passing through the first polarizing film 11 having an optical transmission axis at 15 degrees is then passed through the first $\lambda/2$ film 18 to assume a 0-degree (or 180-degree) linearly-polarized light, which enters the LC layer 13. The 0-degree linearly-polarized light that has entered the LC layer 13 assumes a counterclockwise-circularly-polarized light upon being passed through the LC layer 13.

[0103] The counterclockwise-circularly-polarized light is then reflected by the reflection film 16 to assume a clockwise-circularly-polarized light. The clockwise-circularly-polarized light is passed through the LC layer 13 to assume a 90-degree linearly-polarized light, which enters the first $\lambda/2$ film 18. The 90-degree linearly-polarized light then assumes a 105-degree linearly-polarized light upon being passed through the first $\lambda/2$ film 18. The 105-degree linearly-polarized light cannot be passed through the first polarizing film 11, resulting in display of a dark image.

[0104] The description will next be given of a bright image. Upon representing a bright image, the signals shown in FIGS. 6A and 6B may be applied, whereby the direction of the longitudinal axis of LC molecules in the LC layer 13 in the transmissive area 22 is rotated to the direction of 45 degrees, whereas the direction of the longitudinal axis of LC molecules in the LC layer 13 in the reflective area 21 is kept at 90 degrees.

[0105] In the transmissive area 22, the light emitted from the backlight unit is passed through the second polarizing film 15 having an optical transmission axis at 75 degrees to assume a 75-degree linearly-polarized light. The 75-degree linearly-polarized light is then passed through the second $\lambda/2$ film 19 to assume a 90-degree (or 270-degree) linearly-polarized light, which enters the retardation film 20 and LC layer

13. Since the direction of the optical axis of the retardation film 20 and polarized direction of the light entering the retardation film 20 are parallel to each other, the 90-degree linearly-polarized light is passed through the retardation film 20 with the polarized axis thereof being kept at 90 degrees. The 90-degree linearly-polarized light then assumes a 0-degree linearly-polarized light upon being passed through the LC layer 13. The 0-degree linearly-polarized light is then passed through the first $\lambda/2$ film 18 to assume a 15-degree linearly-polarized light. The 15-degree linearly-polarized light is passed through the first polarizing film 11, resulting in representing a bright image.

[0106] In the reflective area 21, the 15-degree linearly-polarized light passing through the first polarizing film 11 having an optical transmission axis at 15 degrees is then passed through the first $\lambda/2$ film 18 to assume a 0-degree (180-degree) linearly-polarized light, which enters the LC layer 13. The 0-degree linearly-polarized light that has entered the LC layer 13 is passed through the LC layer 13, with the polarized axis thereof being kept at zero degree, reflected by the reflection film 16, and is passed through the LC layer 13 once again. The 0-degree linearly-polarized light passing through the LC layer 13 is passed through the first $\lambda/2$ film 18 to assume a 15-degree linearly-polarized light. The 15-degree linearly-polarized light is passed through the first polarizing film 11, resulting in representing a bright image.

[0107] In the first embodiment, the angle $\theta 1$ is set to satisfy the following relationship:

$$0 \text{ degree} < \theta 1 < 45 \text{ degrees,}$$

and preferably satisfy the following relationship:

$$0 \text{ degree} < \theta 1 \leq 22.5 \text{ degrees.}$$

[0108] Thus, it is possible to cancel the phase difference between the first $\lambda/2$ film and the second $\lambda/2$ film 19 by the retardation of the LC layer 13. However, in the present embodiment, the angle $\theta 1$ is set at zero degree, and thus coloring of the dark image toward blue color may be observed in the transmissive area 22 in some cases due to accumulation of the phase difference between the first $\lambda/2$ film 18 and the second $\lambda/2$ film 19. In the present embodiment, the retardation film 20 performs the optical compensation to thereby solve this problem.

[0109] Although, in the first embodiment, the reflection film 16 is not formed right under the pixel electrodes 35, 36 and first and second common electrodes 37 and 38 in the reflective area 21, the present invention is not limited to this configuration, so long as the portion right under these electrodes does not function as the light source. For is example, as shown in FIG. 21, part of the reflection film 16 that is located right under the electrode 35 or 37 can be formed flat. In this case, a scatter reflection will not occur in the portion right under the electrode, rendering the portion darker than the other portion. As a result, it is possible to reduce the influence by leakage light observed on the electrode. Further, although the angle $\theta 1$ is more than zero degree in the first embodiment, the angle $\theta 1$ may be set at zero degree.

[0110] In a LCD device, a wide wavelength range can be achieved by using a plurality of retardation films, which are layered one on another so that the slow axes thereof are not parallel or perpendicular to each other. This is described in, for example, "Retardation film and polarizer having a wider viewing angle and a large wavelength range" (Shingakugihō) written by Takahiro Ishinabe, Tetsuya Miyashita, and Tatsuo Uchida, January, 2001, pp. 56. The LC layer 13 can also be

considered as a kind of a retardation film. Thus, even if the second $\lambda/2$ film 19 is omitted, a wide wavelength range can be achieved by layering the first $\lambda/2$ film 18 and LC layer 13. In this case, the optical transmission axis of the second polarizing film 15 is set such that the angle between the direction of the optical axis of the LC layer 13 and the polarized direction of the incident light assumes θ_1 . More specifically, if the direction of the longitudinal axis of LC molecules is at 90 degrees and θ_1 is 12 degrees, the optical transmission axis of the second polarizing film 15 should be set at 78 degrees. It is to be noted however that the wavelength dispersion of the $\lambda/2$ film is generally smaller than the wavelength dispersion of the LC layer 13, and thus it is preferable to use a layer structure of the first and second $\lambda/2$ films 18 and 19 in order to achieve a wider wavelength range.

[0111] As described above, the transfective LCD device of the present invention achieves reduction of the coloring and/or leakage light especially upon display of a dark image.

[0112] As described above in connection with the LCD device of the above embodiments, each of the pixels may include a pixel electrode driven by a pixel data signal supplied common to the transmissive area and the reflective area, a first common electrode driven by a first common signal supplied common to the reflective areas of the plurality of pixels, and a second common electrode driven by a second common signal supplied common to the transmissive areas of the plurality of pixels.

[0113] In addition, the angle θ_1 between an optical axis of the LC layer in the transmissive area upon display of a dark image and a polarized direction of light incident onto the LC layer may satisfy the following relationship:

$$\text{zero degree} \leq \theta_1 < 45 \text{ degrees.}$$

[0114] Further, the angle θ_1 may satisfy the following relationship:

$$\text{zero degree} \leq \theta_1 \leq 22.5 \text{ degrees.}$$

[0115] Further, the angle θ_2 between an optical axis of the LC layer in the reflective area upon display of a dark image and a polarized direction of light incident onto the LC layer may satisfy the following relationship: $\theta_2 = 45$ degrees.

[0116] Further, a polarized direction of light incident onto the second polarizing film and an optical absorption axis of the second polarizing film may be aligned with each other upon display of a dark image.

[0117] Further, the LCD device may include another $\lambda/2$ wavelength film between the second polarizing film and the LC layer.

[0118] Further, the angle θ_1 between an optical axis of the LC layer in the transmissive area upon display of a dark image and a polarized direction of light incident onto the LC layer may be zero degree, and the LCD device may further include a retardation film sandwiched between the another $\lambda/2$ wavelength film and the LC layer.

[0119] Further, the retardation film may have an optical characteristic satisfying the following relationship:

$$-0.3 \leq (nx - nz)/(nx - ny) \leq 0.3; \text{ or}$$

$$(nx - nz)/(nx - ny) = 1.0,$$

where n_x , n_y , n_z and d are refractive index of a slow axis, refractive index of a fast axis, refractive index in a thickness direction and thickness of the retardation film, respectively, wherein the LC layer has a retardation substantially equal to

$(n_x - n_y) \times d$; and the fast axis of the retardation film is parallel or perpendicular to the optical axis of the LC layer.

[0120] Further, the LC layer may include homogeneously-oriented liquid crystal.

[0121] Further, the first and second common signals may be inverted in synchrony with a synchronizing signal, and the first common signal may be substantially an inverted signal of the second common signal, and vice versa.

[0122] Further, each of the pixels may include a first pixel electrode in the transmissive area, a second pixel electrode in the reflective area, a first switch for supplying a data signal to the first pixel electrode, and a second switch for supplying the data signal to the second pixel electrode.

[0123] Further, the reflective area may include a reflection film maintained at an intermediate potential between a potential of the pixel electrode and a potential of the first common electrode.

[0124] Further, the intermediate potential of the reflective film may be supplied by a capacitive coupling from the pixel electrode and the first common electrode.

[0125] Further, the intermediate potential of the reflective film may be provided by an intermediate-potential generator.

[0126] Further, the reflective film may have an opening right under the pixel electrode and the first common electrode.

[0127] Further, the reflective film may have a flat surface in a region right under the pixel electrode and the first common electrode, and a rough surface in the other region.

[0128] Further, each of said pixels may include a first pixel electrode in said transmissive area, a second pixel electrode in said reflective area, a first switching device for supplying a data signal to said first pixel electrode, and a second switch for supplying said data signal to said second pixel electrode.

[0129] Further, the transfective LCD device according to the present invention may include a first common electrode including a plurality of common electrodes connected in common and disposed in said reflective areas of a plurality of said pixels, and a second common electrode including a plurality of common electrodes connected in common and disposed in said transmissive areas of a plurality of said pixels.

[0130] Further, one of said first common electrode and said second common electrode may receive a common signal obtained by inversion of a common signal applied to the other of said first common electrode and said second common electrode.

[0131] Further, said first and second switching devices may be connected to a common data line, and driven by separate control lines.

[0132] Further, said first and second switching devices may be connected to a first data line and a second data line, respectively.

[0133] Further, one of said first and second common electrodes may be applied with a first data signal output from a voltage converter for converting a second data signal applied to the other of said first and second common electrodes.

[0134] Further, said voltage converter may include a data memory for storing said second data signal, and a gray-scale level converter for converting a gray-scale level of said second data signal to output said first data signal.

[0135] Further, said voltage converter includes a look-up table for converting said gray-scale level. The look-up may tabulate a maximum gray-scale level and a minimum gray-scale level in association. The look-up table may be configured by logic gates.

[0136] Further, the transfective LCD device may further include a first common electrode including a plurality of common electrodes connected in common and disposed in said reflective areas of a plurality of said pixels, and a second common electrode including a plurality of common electrodes connected in common and disposed in said transmissive areas of a plurality of said pixels.

[0137] Further, a potential to be written in said first and second common electrodes may be inverted at a timing of switching for writing data through said first switching device or said second switching device.

[0138] A method for driving the transfective LCD of the present invention may include the steps of: generating a first data signal and a second data signal having therebetween a specific potential relationship; and applying said first data signal and said second data signal to said reflective area and said transmissive area, respectively.

[0139] In the method of the present invention, said relationship between said first data signal and said second data signal may be such that said first data signal assumes a maximum gray-scale-level potential when is corresponding said second data signal assumes a minimum gray-scale-level potential.

[0140] The method of the present invention may further include the step of applying a first common electrode signal to a first common electrode disposed in said reflective areas of a plurality of said pixels and a second common electrode signal to a second common electrode disposed in said transmissive areas of a plurality of said pixels, said first common electrode signal having a potential different from a potential of said second common electrode signal.

[0141] The LCD device may include a first switching device for coupling a data line to said first pixel electrode and a second switching device for coupling said data line to said second pixel electrode, a first gate line for controlling said first switching device, a second gate line for controlling said second switching device, and said method may further include the steps of: turning ON said first and second switching devices in a time-division scheme, to apply a common data signal to said first and second pixel electrodes; applying a first common electrode signal to a common electrode during applying said common data signal to said first pixel electrode; and applying a second common electrode signal to said common electrode during applying said common data signal to said second pixel electrode, said first common electrode signal having a potential different from a potential of said second common electrode signal.

[0142] The LCD device may include a first switching device for coupling a first data line to said first pixel electrode, a second switching device for coupling a second data line to said second pixel electrode, and the method of the present invention may further include the step of: applying said first and second data signals to said first and second data lines, respectively.

[0143] In the method of the present invention, one of said first and second data signal may be supplied from outside of said LCD device, and the other of said first and second data signals has a gray-scale level converted from a grays-scale level of said one of said first and second data signals by using a look-up table.

[0144] In the method of the present invention, said look-up table may be such that similar γ -characteristics are obtained for both said reflective and transmissive areas.

[0145] The LCD device of the present invention may include a single common electrode for both said reflective

area and said transmissive area of a plurality of said pixels, and the method further of the present invention may include the steps of: applying said single common electrode with a first common electrode signal at the timing of writing said first data signal; and applying said single common electrode signal with a second common electrode signal at the timing of writing said second data signal.

[0146] Although the present invention has been described with reference to the preferred embodiment, the transfective LCD device according to the present invention is not limited to the above embodiments, and a transfective LCD device obtained by making various modifications and changes in the configurations of the above-described embodiments will fall within the scope of the present invention.

1. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer.

2. The transfective LCD device according to claim 1, wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels.

3-39. (canceled)

40. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein said retardation film acts as a $\frac{1}{2}$ -wavelength film at a wavelength of 550 nm.

41. The transfective LCD device according to claim 39, wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels.

42. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels,

wherein an angle $\theta 1$ between an optical axis of said LC layer in said transmissive area upon display of a dark image and a polarized direction of light incident onto said LC layer satisfies the following relationship:

$$\text{zero degree} < \theta 1 < 45 \text{ degrees.}$$

43. The transfective LCD device according to claim **42**, wherein said angle $\theta 1$ satisfies the following relationship:

$$\text{zero degree} < \theta 1 \leq 22.5 \text{ degrees.}$$

44. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels,

wherein an angle $\theta 2$ between an optical axis of said LC layer in said reflective area upon display of a dark image and a polarized direction of light incident onto said LC layer satisfies the following relationship: $\theta 2 = 45$ degrees.

45. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said

reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels,

wherein a polarized direction of light incident onto said second polarizing film and an optical absorption axis of said second polarizing film are aligned with each other upon display of a dark image.

46. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area;

a retardation film sandwiched between said first polarizing film and said LC layer; and

another $\frac{1}{2}$ wavelength film between said second polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels.

47. The transfective LCD device according to claim **46**, wherein an angle $\theta 1$ between an optical axis of said LC layer in said transmissive area upon display of a dark image and a polarized direction of light incident onto said LC layer is zero degree, further comprising a retardation film sandwiched between said another $\frac{1}{2}$ wavelength film and said LC layer.

48. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said reflective area, said second polarizing film being effective only to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second

common signal supplied in common to said transmissive areas of said plurality of pixels,
wherein said LC layer includes homogeneously-oriented liquid crystal.

49. A transfective liquid-crystal-display (LCD) device comprising:

a liquid crystal (LC) layer defining a plurality of pixels each having a transmissive area and a reflective area, at least said transmissive area operating in a lateral-electric-field mode;

first and second polarizing films sandwiching therebetween said LC layer, said first polarizing film being effective common to said transmissive area and said

reflective area, said second polarizing film being effective to said transmissive area; and

a retardation film sandwiched between said first polarizing film and said LC layer,

wherein each of said pixels includes a pixel electrode driven by a pixel data signal supplied in common to said transmissive area and said reflective area, a first common electrode driven by a first common signal supplied in common to said reflective areas of said plurality of pixels, and a second common electrode driven by a second common signal supplied in common to said transmissive areas of said plurality of pixels.

* * * * *

专利名称(译)	透反液晶显示装置		
公开(公告)号	US20100328592A1	公开(公告)日	2010-12-30
申请号	US12/873108	申请日	2010-08-31
[标]申请(专利权)人(译)	永井HIROSHI 坂本道明 森健一 NAKA KENICHIROU IKENO秀典		
申请(专利权)人(译)	永井HIROSHI 坂本道明 MORI KENICHI NAKA KENICHIROU IKENO秀典		
当前申请(专利权)人(译)	NLT科技有限公司.		
[标]发明人	NAGAI HIROSHI SAKAMOTO MICHIAKI MORI KENICHI NAKA KENICHIROU IKENO HIDENORI		
发明人	NAGAI, HIROSHI SAKAMOTO, MICHIAKI MORI, KENICHI NAKA, KENICHIROU IKENO, HIDENORI		
IPC分类号	G02F1/1335		
CPC分类号	G02F1/133528 G02F1/133555 G02F1/13363 G02F1/134363 G09G3/3607 G02F2001/133638 G02F2413/03 G02F2413/09 G02F2001/133565		
优先权	2006061383 2006-03-07 JP		
其他公开文献	US8502941		
外部链接	Espacenet USPTO		

摘要(译)

LCD装置具有夹在TFT基板和基板之间的LC层，第一和第二偏振膜，第一偏振膜和对基板之间的第一N/2膜，以及第二偏振膜之间的第二N/2膜薄膜和TFT基板。LC层的光轴方向与进入LC层的光的偏振方向之间的角度 θ_1 满足关系： $0^\circ < \theta_1 < 45^\circ$ 。所得到的LCD装置具有较低的漏光和着色。

