



US 20150042693A1

(19) **United States**(12) **Patent Application Publication**
Hirata(10) **Pub. No.: US 2015/0042693 A1**(43) **Pub. Date: Feb. 12, 2015**(54) **LIQUID CRYSTAL DISPLAY DEVICE AND
DRIVE METHOD FOR LIQUID CRYSTAL
PANEL**(75) Inventor: **Mitsuaki Hirata**, Osaka-shi (JP)(73) Assignee: **SHARP KABUSHIKI KAISHA**,
Osaka-shi, Osaka (JP)(21) Appl. No.: **14/345,010**(22) PCT Filed: **Sep. 13, 2012**(86) PCT No.: **PCT/JP2012/073531**

§ 371 (c)(1),

(2), (4) Date: **Mar. 14, 2014**(30) **Foreign Application Priority Data**

Sep. 20, 2011 (JP) 2011-205172

Publication Classification(51) **Int. Cl.**
G09G 3/36

(2006.01)

(52) **U.S. CL.**CPC **G09G 3/3659** (2013.01); **G09G 3/3607**
(2013.01); **G09G 2300/0439** (2013.01); **G09G**
2300/0478 (2013.01); **G09G 2300/0876**
(2013.01); **G09G 2310/0202** (2013.01); **G09G**
2320/0233 (2013.01)USPC **345/690**; 345/89(57) **ABSTRACT**

A liquid crystal display device of the present invention employs a liquid crystal panel of CS control pixel division, and is configured such that two adjacent pixel rows share one retention capacitor wire, and two adjacent scanning signal lines are simultaneously selected. In a case where two pixels ((Pn+1) and (Pn+2)) which are adjacent along a scanning direction but are not simultaneously selected are to have an identical predetermined luminance in two frames, a first signal potential is written to one pixel (Pn+1) in one of the two frames and a second signal potential having a polarity identical to that of the first signal potential is written to the other pixel (Pn+2) in the other of the two frames, the first and second signal potentials are different from each other. The present invention makes it possible to suppress transverse lines of display unevenness which occur in the liquid crystal display device.




FIG. 1




FIG. 2





FIG. 3



F I G. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9





FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16





FIG. 17



ODD-NUMBERED FRAMES
(SOLID-COLOR DISPLAY AT LUMINANCE LL)

EVEN-NUMBERED FRAMES
(SOLID-COLOR DISPLAY AT LUMINANCE LL)

CS CHANGE

SLa

SLb

CSLn-1

CSLn

CSLn+1

Gn

Gn+1

Gn+2

COM

Pn

Pn+1

Pn+2

LIGHT

DARK

Tn

Tn+1

Tn+2

Cn

Cn+1

Cn+2

X

Y

Z



A

B

Vs=VTM

Vs=VTP

FIG. 19



LIQUID CRYSTAL DISPLAY DEVICE AND DRIVE METHOD FOR LIQUID CRYSTAL PANEL

TECHNICAL FIELD

[0001] The present invention relates to a driving technique for a liquid crystal panel.

BACKGROUND ART

[0002] Patent literature 1 discloses the following technique (pixel division driving): two pixel electrodes are provided in one pixel (corresponding to one primary color) of a liquid crystal panel; and when halftone is displayed, these two pixel electrodes are caused to have respective different luminances by controlling potentials of CS wires. This pixel division driving improves viewing angle characteristics of the liquid crystal panel.

[0003] Patent Literature 1 also discloses the following technique (two-lines simultaneous selection driving): two signal potential lines are provided for one pixel column; and two adjacent scanning signal lines are simultaneously selected. This two-lines simultaneous selection driving allows fast scan of the liquid crystal panel.

CITATION LIST

Patent Literature

[0004] Patent Literature 1

[0005] PCT International Application Publication No. WO2009/084331 (A1)

SUMMARY OF INVENTION

Technical Problem

[0006] The inventor found that flicker and transverse lines of display unevenness are often perceivable if the pixel division driving and the two-lines simultaneous selection driving are employed in a liquid crystal panel in which one CS wire is shared by two adjacent pixel rows (see Patent Literature 1). One of objects of the present invention is to prevent such flicker and transverse lines of display unevenness.

Solution to Problem

[0007] A liquid crystal display device of the present invention includes: a first scanning signal line, a second scanning signal line, a third scanning signal line, and a fourth scanning signal line which are arranged in order; a first pixel, a second pixel, a third pixel, and a fourth pixel connected to the first scanning signal line, the second scanning signal line, the third scanning signal line, and the fourth scanning signal line, respectively; and a first retention capacitor wire and a second retention capacitor wire, wherein the first to fourth pixels each include a plurality of pixel electrodes, the first and second pixels with the first retention capacitor wire form capacitors, and the second and third pixels with the second retention capacitor wire form capacitors, the first and second scanning signal lines are simultaneously selected and thereafter the third and fourth scanning signal lines are simultaneously selected, potentials of the first and second retention capacitor wires are separately controlled, the second pixel and the third pixel have the same color, and in a case where the second and third pixels are to have an identical predetermined luminance

in two frames, a first signal potential is written to the second pixel in one of the two frames and a second signal potential having a polarity identical to that of the first signal potential is written to the third pixel in the other of the two frames, the first and second signal potentials being different from each other.

[0008] With this arrangement, signal potentials written to pixels compensate for a difference between the degrees of ripples which occur in the first and second retention capacitor wires. Accordingly, it is possible to suppress transverse lines of display unevenness.

Advantageous Effects of Invention

[0009] As described above, the present invention makes it possible to suppress transverse lines of display unevenness.

BRIEF DESCRIPTION OF DRAWINGS

[0010] FIG. 1 is a schematic view illustrating a signal potential V_s written to pixels P_{n+1} and P_{n+2} in Example 1.

[0011] FIG. 2 is a block diagram illustrating an example of a configuration of a liquid crystal display device of Example 1.

[0012] FIG. 3 is a schematic view illustrating an example of a configuration of a liquid crystal panel of Example 1.

[0013] FIG. 4 is a schematic view illustrating how retention capacitor wires are connected to stem wires.

[0014] FIG. 5 is a timing chart illustrating a relationship between (i) phases of the retention capacitor wires and (ii) scanning of scanning signal lines in odd-numbered frames.

[0015] FIG. 6 is a timing chart illustrating a relationship between (i) phases of the retention capacitor wires and (ii) scanning of the scanning signal lines in even-numbered frames.

[0016] FIG. 7 is a set of timing charts each showing a relationship between (i) a signal potential V_s which is written to a pixel electrode A in an odd-numbered frame and (ii) a signal potential V_s which is written to a pixel electrode B in an even-numbered frame in FIG. 1.

[0017] FIG. 8 is a set of graphs each showing (i) a relationship between luminance and gray level corresponding to the signal potential V_s (written potential) written to the pixel P_{n+1} (γ_1 characteristics) and (ii) a relationship between actual luminance and actual gray level of the pixel P_{n+1} (γ_2 characteristics).

[0018] FIG. 9 is a set of timing charts each showing a relationship between (i) the signal potential V_s which is written to the pixel electrode A in an even-numbered frame and (ii) the signal potential V_s which is written to the pixel electrode B in an odd-numbered frame in FIG. 1.

[0019] FIG. 10 is a set of timing charts each showing a relationship between (i) the signal potential V_s which is written to the pixel electrode A in an even-numbered frame and (ii) the signal potential V_s which is written to the pixel electrode A in an odd-numbered frame in FIG. 1.

[0020] FIG. 11 is a set of timing charts each showing a relationship between (i) the signal potential V_s which is written to the pixel electrode B in an even-numbered frame and (ii) the signal potential V_s which is written to the pixel electrode B in an odd-numbered frame in FIG. 1.

[0021] FIG. 12 is a graph showing a gray level range and the degree of display unevenness for each amplitude of a potential of a retention capacitor wire.

[0022] FIG. 13 is a schematic view illustrating an arrangement of two adjacent pixel columns and how to drive them (odd-numbered frames) in Example 1.

[0023] FIG. 14 is a schematic view illustrating an arrangement of two adjacent pixel columns and how to drive them (even-numbered frames) in Example 1.

[0024] FIG. 15 is a schematic view illustrating an arrangement of two adjacent pixel columns and how to drive them (odd-numbered frames) in Example 2.

[0025] FIG. 16 is a schematic view illustrating an arrangement of two adjacent pixel columns and how to drive them (even-numbered frames) in Example 2.

[0026] FIG. 17 is a schematic view illustrating how a liquid crystal display device of Example 3 is scanned.

[0027] FIG. 18 is a schematic view illustrating a signal potential V_s written to pixels P_{n+1} and P_{n+2} in Reference Example.

[0028] FIG. 19 is a set of timing charts each showing a relationship between (i) a signal potential V_s which is written to a pixel electrode A in an odd-numbered frame and (ii) a signal potential V_s which is written to a pixel electrode B in an even-numbered frame in FIG. 18.

DESCRIPTION OF EMBODIMENTS

Example 1

[0029] As illustrated in FIG. 2, a liquid crystal display device LCD of Example 1 includes (i) a liquid crystal panel LCP including signal potential lines, scanning signal lines, retention capacitor wires (CS wires), transistors and pixel electrodes, (ii) a backlight BL for irradiating the liquid crystal panel LCP with light, (iii) a gate driver GD for driving the scanning signal lines (supplying gate pulses to the scanning signal lines), (iv) a source driver SD for driving the signal potential lines (supplying signal potentials to the signal potential lines), (v) a CS driver CSD for driving the retention capacitor wires (CS wires) (supplying modulated signals to the retention capacitor wires), and (vi) a display control substrate DCS (timing controller substrate) for controlling the gate driver, the source driver and the CS driver.

[0030] The display control substrate DCS includes a timing controller Tcon and an image processing circuit IPC. The timing controller Tcon (i) generates display data, a source control signal, a gate control signal, and a CS control signal from image data IDA in cooperation with the image processing circuit IPC and (ii) supplies the display data and the source control signal to the source driver SD, supplies the gate control signal to the gate driver GD, and supplies the CS control signal to the CS driver CSD.

[0031] The liquid crystal display device of Example 1 is configured such that, as illustrated in FIG. 3, (i) two pixel electrodes are provided in one pixel (corresponding to one primary color) and (ii) two signal potential lines are provided in correspondence with one pixel column. For example, four scanning signal lines G_n to G_{n+3} which are adjacent to each other along a scanning direction (column direction) are selected such that (i) first, two scanning signal lines G_n and G_{n+1} are simultaneously selected and (ii) next, two scanning signal lines G_{n+2} and G_{n+3} are simultaneously selected.

[0032] Specifically, a pixel electrode A and a pixel electrode Y are provided in a pixel P_{n+1} , the pixel electrode A is connected to a signal potential line SL_b and the scanning signal line G_{n+1} via a transistor T_{n+1} , and the pixel electrode Y is connected to the signal potential line SL_b and the scan-

ning signal line G_{n+1} via a transistor t_{n+1} . A pixel electrode B and a pixel electrode Z are provided in a pixel P_{n+2} (pixel of the same color as the pixel P_{n+1}) which is adjacent to the pixel P_{n+1} along the column direction, the pixel electrode B is connected to a signal potential line SL_a and the scanning signal line G_{n+2} via a transistor T_{n+2} , and the pixel electrode Z is connected to the signal potential line SL_a and the scanning signal line G_{n+2} via a transistor t_{n+2} . Note that a pixel electrode X included in a pixel P_n is connected to the signal potential line SL_a and a scanning signal line G_n via a transistor t_n .

[0033] The liquid crystal display device LCD is configured such that two adjacent pixel rows share one retention capacitor wire. For example, a retention capacitor wire CSL_n , with the pixel electrode X of the pixel P_n and the pixel electrode A of the pixel P_{n+1} , forms retention capacitors, and a retention capacitor wire CSL_{n+1} , with the pixel electrode Y of the pixel P_{n+1} and the pixel electrode B of the pixel P_{n+2} , forms retention capacitors.

[0034] As illustrated in FIGS. 4 to 6, twelve stem wires M1 to M12 receive, from the CS driver CSD, modulated signals of first to twelfth phases. Each retention capacitor wire is connected to one of the stem wires M1 to M12. Note that the first to twelfth phases each have a cycle of 24 H (horizontal scanning periods), and the phase changes from "High" to "Low" or from "Low" to "High" every 12 H.

[0035] As illustrated in FIGS. 1 and 5, the liquid crystal display device of the present example is arranged as below. In odd-numbered frames (solid-color display at a luminance LL), while two scanning signal lines G_n and G_{n+1} are both in a selected state, a positive signal potential is written from the signal potential line SL_a to the pixel electrode X, and a negative signal potential V_{Tm} is written from the signal potential line SL_b to the pixel electrode A and the pixel electrode Y. Next, while two scanning signal lines G_{n+2} and G_{n+3} are both in the selected state, a positive signal potential V_{Tp} is written from the signal potential line SL_a to the pixel electrode B and the pixel electrode Z. After that, the retention capacitor wire CSL_n changes from "High" state to "Low" state while the retention capacitor wire CSL_{n+1} changes from "Low" state to "High" state. Accordingly, an effective potential of the pixel electrode A becomes lower than V_{Tm} (an effective voltage of a subpixel corresponding to the pixel electrode A increases), an effective potential of the pixel electrode Y becomes higher than V_{Tm} (an effective voltage of a subpixel corresponding to the pixel electrode Y decreases), and an effective potential of the pixel electrode B becomes higher than V_{Tp} (an effective voltage of a subpixel corresponding to the pixel electrode B increases).

[0036] Furthermore, as illustrated in FIGS. 1 and 6, in even-numbered frames (solid-color display at a luminance LL), while two scanning signal lines G_n and G_{n+1} are both in the selected state, a negative signal potential is written from the signal potential line SL_a to the pixel electrode X, and a positive signal potential V_{Tp} is written from the signal potential line SL_b to the pixel electrode A and the pixel electrode Y. Next, while two scanning signal lines G_{n+2} and G_{n+3} are both in the selected state, a negative signal potential V_{Tm} is written from the signal potential line SL_a to the pixel electrode B and the pixel electrode Z. After that, the retention capacitor wire CSL_n changes from "Low" state to "High" state while the retention capacitor wire CSL_{n+1} changes from "High" state to "Low" state. Accordingly, an effective potential of the pixel electrode A becomes higher than V_{Tp}

(an effective voltage of a subpixel corresponding to the pixel electrode A increases), an effective potential of the pixel electrode Y becomes lower than V_{Tp} (an effective voltage of a subpixel corresponding to the pixel electrode Y decreases), and an effective potential of the pixel electrode B becomes lower than V_{Tm} (an effective voltage of a subpixel corresponding to the pixel electrode B increases).

[0037] According to Example 1, the luminance LL is a low luminance corresponding to a gray level of 0 to 90 of 256 gray levels, and the signal potentials are set such that $V_{Tm} < V_{Tm}$ and $V_{Tp} < V_{Tp}$. The reason therefor is discussed below with reference to FIGS. 1, and 7 to 10, 18 and 19. Furthermore, the signal potentials are set such that $(V_{Tp} - V_{Tm}) > (V_{Tp} - V_{Tm})$. The reason therefor is discussed below with reference to FIGS. 1, 7 and 9 to 11.

[0038] The retention capacitor wire CSL_n is affected by both a feed-through voltage of the pixel electrode X connected to the transistor to and a feed-through voltage of the pixel electrode A connected to the transistor T_{n+1} when the potentials of the scanning signal lines G_n and G_{n+1} change from “active (High)” to “non-active (Low)” (when the transistors t_n and T_{n+1} are turned off) after the simultaneous selection of the scanning signal lines G_n and G_{n+1} . Therefore, a ripple (downward) which occurs in potential of the retention capacitor wire CSL_n when the transistors t_n and T_{n+1} are turned off is relatively large.

[0039] On the other hand, the retention capacitor wire CSL_{n+1} is affected only by a feed-through voltage of the pixel electrode B connected to the transistor T_{n+2} when the potentials of the scanning signal lines G_{n+2} and G_{n+3} change from “active (High)” to “non-active (Low)” (when the transistor T_{n+2} is turned off). Therefore, a ripple (downward) which occurs in potential of the retention capacitor wire CSL_{n+1} when the transistor T_{n+2} is turned off is relatively small.

[0040] Such a difference in magnitude of ripples causes two effects on the potentials of pixel electrodes.

[0041] One of the effects is as follows. As illustrated in FIGS. 1 and 19, a difference between the potential of the retention capacitor wire CSL_n and the High level when the transistors t_n and T_{n+1} are turned off in an odd-numbered frame is larger than a difference between the potential of the retention capacitor wire CSL_{n+1} and the High level when the transistor T_{n+2} is turned off in an even-numbered frame. Similarly, a difference between the potential of the retention capacitor wire CSL_n and a Low level when the transistors t_n and T_{n+1} are turned off in an even-numbered frame is larger than a difference between the potential of the retention capacitor wire CSL_{n+1} and the Low level when the transistor T_{n+2} is turned off in an odd-numbered frame.

[0042] As a result, a feed-through direct-current component of a pixel electrode relative to the common potential becomes different between pixels connected to the transistors t_n and T_{n+1} and pixels connected to the transistor T_{n+2} . Accordingly, effective values change at a frequency that is $\frac{1}{2}$ the frame frequency. This tends to cause flicker.

[0043] According to Example 1, as illustrated in FIGS. 1 and 7, when displaying a luminance LL (low luminance corresponding to a gray level of about 0 to 90 of the 256 gray levels) in pixels, it is possible to compensate for the difference between the degree of a ripple which occurs in the retention capacitor wire CSL_n and the degree of a ripple which occurs in the retention capacitor wire CSL_{n+1} because signal potentials are set such that V_{Tm} (negative signal potential) $< V_{Tp}$

(negative signal potential). Accordingly, it is possible to reduce the difference between the effective voltage across the subpixel corresponding to the pixel electrode A in odd-numbered frames and the effective voltage across the subpixel corresponding to the pixel electrode B in even-numbered frames. This makes it possible to prevent flicker which is caused when the effective values change every frame.

[0044] According to Example 1, as illustrated in FIGS. 1 and 9, when displaying a luminance LL (low luminance corresponding to a gray level of about 0 to 90 of the 256 gray levels) in pixels, it is possible to compensate for the difference between the degree of a ripple which occurs in the retention capacitor wire CSL_n and the degree of a ripple which occurs in the retention capacitor wire CSL_{n+1} because signal potentials are set such that V_{Tp} (positive signal potential) $< V_{Tp}$ (positive signal potential). Accordingly, it is possible to reduce the difference between the effective voltage across the subpixel corresponding to the pixel electrode A in even-numbered frames and the effective voltage across the subpixel corresponding to the pixel electrode B in odd-numbered frames. This makes it possible to prevent flicker which is caused when the effective values change every frame.

[0045] The other effect occurs when gate pulses (scanning signals) are turned off, because pixels (transistors provided in the pixels) are turned off at slightly different times depending on the polarities of the signal potentials. Specifically, pixels which have received a positive signal potential are turned off one to several microseconds earlier than transistors of pixels which have received a negative signal potential (see FIGS. 10 and 11).

[0046] Even during this period (from when the pixels which have received the positive signal potential are turned off to when the pixels which have received the negative signal potential are turned off), CS potentials change due to the effect of ripples. Therefore, the potentials of the pixel electrodes vary depending on the polarities of the signal potentials.

[0047] Specifically, when the following two differences are compared, i.e., when the difference between the potential of the retention capacitor wire CSL_n and the Low level when the transistor T_{n+1} is turned off in an even-numbered frame is compared with the difference between the potential of the retention capacitor wire CSL_n and the High level when the transistor T_{n+1} is turned off in an odd-numbered frame, the difference in the odd-numbered frame in which the signal potential is negative is larger (see FIG. 10). Furthermore, also when two differences are compared, i.e., when the difference between the potential of the retention capacitor wire CSL_n and the High level when the transistor T_{n+2} is turned off in an even-numbered frame is compared with the difference between the potential of the retention capacitor wire CSL_n and the Low level when the transistor T_{n+2} is turned off in an odd-numbered frame, the difference in the even-numbered frame in which the signal potential is negative is larger (see FIG. 11).

[0048] Note, here, that (the difference in an odd-numbered frame—the difference in an even-numbered frame) in the former in which a ripple is large (see FIG. 10) is larger than (the difference in an even-numbered frame—the difference in an odd-numbered frame) in the latter in which a ripple is small (see FIG. 11). Accordingly, for example, if the signal potentials are set such that “a difference between positive and negative signal potentials for the pixel electrode A (positive signal potential–negative signal potential)=a difference

between positive and negative signal potentials for the pixel electrode B (positive signal potential–negative signal potential)”, transverse lines of display unevenness are likely to occur. Such display unevenness is conspicuous when a low luminance corresponding to a gray level of about 0 to 90 of the 256 gray levels is displayed (luminance of dark subpixels is substantially 0) in pixels.

[0049] In view of the circumstances, according to Example 1, signal potentials are set such that “the difference between positive and negative signal potentials for the pixel electrode A ($V_{Tp}-V_{Tm}$)” > “the difference between positive and negative signal potentials for the pixel electrode B ($V_{Tp}-V_{Tm}$)” in the case where the luminance LL (low luminance corresponding to a gray level of about 0 to 90 of the 256 gray levels) is displayed in pixels (see FIGS. 1, 7, 9, 10 and 11). This compensates for the difference between the effect of a ripple which occurs in the retention capacitor wire CSL_n and the effect of a ripple which occurs in the retention capacitor wire CSL_{n+1}, and achieves substantially the same effective voltages across the subpixel corresponding to the pixel electrode A and across the subpixel corresponding to the pixel electrode B. This makes it possible to suppress transverse lines of display unevenness. Note that the difference between positive and negative signal potentials ($V_{Tp}-V_{Tm}$) for the pixel electrode A corresponds to luminance of γ_1 in FIG. 8, and the difference between positive and negative signal potentials ($V_{Tp}-V_{Tm}$) for the pixel electrode B corresponds to luminance of γ_2 in FIG. 8.

[0050] FIG. 12 is a graph showing a relationship between gray levels and degrees of transverse lines of unevenness for each amplitude (amplitude of a modulated signal) of a potential of a retention capacitor wire. It is preferable that signal potentials are set as shown FIG. 1 particularly in a gray level range (gray levels 10 to 64) where the degree of transverse lines of unevenness is 3 and 4.

[0051] According to Example 1, γ is set by digital gray level selection which is realized with the use of four LUTs, i.e., 2 (two types of polarity arrangements for dots in a check pattern) × 2 (positive and negative signal polarities which are reversed dot by dot).

[0052] Example 1 employs, as illustrated in FIGS. 13 and 14, an arrangement in which (i) data signal lines SL_a, SL_b, SL_A, and SL_B are arranged in this order and (ii) in a case where one of two pixels adjacent to each other along a row direction is connected to the data signal line SL_a via two transistors, the other is connected to the data signal line SL_A via two transistors, and, in a case where one of two pixels adjacent to each other along the row direction is connected to the data signal line SL_b via two transistors, the other is connected to the data signal line SL_B via two transistors. The data signal lines SL_a, SL_b, SL_A, and SL_B are supplied with positive, negative, negative, and positive signal potentials, respectively (see FIG. 13), or negative, positive, positive, and negative signal potentials, respectively (see FIG. 14).

Example 2

[0053] Example 1 employs, as illustrated in FIGS. 15 and 16, an arrangement in which (i) data signal lines SL_a, SL_b, SL_A, and SL_B are arranged in this order and (ii) in a case where one of two pixels adjacent to each other along a row direction is connected to the data signal line SL_a via two transistors, the other is connected to the data signal line SL_B via two transistors, and, in a case where one of two pixels adjacent to each other along the row direction is connected to

the data signal line SL_b via two transistors, the other is connected to the data signal line SL_A via two transistors. The data signal lines SL_a, SL_b, SL_A, and SL_B are supplied with positive, negative, positive, and negative signal potentials, respectively (see FIG. 15), or negative, positive, negative, and positive signal potentials, respectively (see FIG. 16).

Example 3

[0054] According to Example 3, a first half of the liquid crystal panel which is more upstream along the scanning direction and a second half which is more downstream along the scanning direction are scanned in parallel with each other. Specifically, as shown in FIG. 17, four data signal lines (e.g., data signal lines SL_a, SL_b, sL_a and sL_b) are provided for one pixel column, and two scanning signal lines in the first half and two scanning signal lines in the second half (four scanning signal lines in total) are simultaneously scanned. With this configuration, it is possible to perform more high-speed driving.

[0055] As has been described, a liquid crystal display device of the present invention is a liquid crystal display device including: a first scanning signal line, a second scanning signal line, a third scanning signal line, and a fourth scanning signal line which are arranged in order; a first pixel, a second pixel, a third pixel, and a fourth pixel connected to the first scanning signal line, the second scanning signal line, the third scanning signal line, and the fourth scanning signal line, respectively; and a first retention capacitor wire and a second retention capacitor wire, wherein the first to fourth pixels each include a plurality of pixel electrodes, the first and second pixels with the first retention capacitor wire form capacitors, and the second and third pixels with the second retention capacitor wire form capacitors, the first and second scanning signal lines are simultaneously selected and thereafter the third and fourth scanning signal lines are simultaneously selected, potentials of the first and second retention capacitor wires are separately controlled, the second pixel and the third pixel have the same color, and in a case where the second and third pixels are to have an identical predetermined luminance in two frames, a first signal potential is written to the second pixel in one of the two frames and a second signal potential having a polarity identical to that of the first signal potential is written to the third pixel in the other of the two frames, the first and second signal potentials being different from each other.

[0056] With this arrangement, signal potentials written to pixels compensate for a difference between the degrees of ripples which occur in the first and second retention capacitor wires. Accordingly, it is possible to suppress transverse lines of display unevenness.

[0057] The liquid crystal display device of the present invention can also be configured such that the first signal potential is smaller than the second signal potential.

[0058] The liquid crystal display device of the present invention can also be configured such that: a third signal potential is written to the third pixel in said one of the two frames; a fourth signal potential having a polarity identical to that of the third signal potential is written to the second pixel in said other of the two frames; and (i) an absolute value of a difference between the first signal potential and the fourth signal potential and (ii) an absolute value of a difference between the second signal potential and the third signal potential are different from each other.

[0059] The liquid crystal display device of the present invention can also be configured such that the absolute value of the difference between the first signal potential and the fourth signal potential is larger than the absolute value of the difference between the second signal potential and the third signal potential.

[0060] The liquid crystal display device of the present invention can also be configured such that, the predetermined luminance corresponds to a gray level included in a lower half of all gray levels.

[0061] The liquid crystal display device of the present invention can also be configured such that, in a case where the number of the all gray levels is 256, the predetermined luminance corresponds to any one of gray levels 5 to 80.

[0062] The liquid crystal display device of the present invention can also be configured such that: a potential of each of the first and second retention capacitor wires periodically switches between two levels; and the first changes in potentials of the first and second retention capacitor wires after the simultaneous selection of the first and second scanning signal lines are opposite to each other.

[0063] The liquid crystal display device of the present invention can further include: a first data signal line and a second data signal line; and a first transistor, a second transistor, a third transistor, a fourth transistor, a fifth transistor, and a sixth transistor, and can be configured such that: the first pixel includes a first pixel electrode and a second pixel electrode, the second pixel includes a third pixel electrode and a fourth pixel electrode, and the third pixel includes a fifth pixel electrode and a sixth pixel electrode; the first pixel electrode is connected to the first scanning signal line and the first data signal line via the first transistor, and the second pixel electrode is connected to the first scanning signal line and the first data signal line via the second transistor; the third pixel electrode is connected to the second scanning signal line and the second data signal line via the third transistor, and the fourth pixel electrode is connected to the second scanning signal line and the second data signal line via the fourth transistor; the fifth pixel electrode is connected to the third scanning signal line and the first data signal line via the fifth transistor, and the sixth pixel electrode is connected to the third scanning signal line and the first data signal line via the sixth transistor; and the first retention capacitor wire with the second and third pixel electrodes forms capacitors, and the second retention capacitor wire with the fourth and fifth pixel electrodes forms capacitors.

[0064] The liquid crystal display device of the present invention can also be configured such that, in one horizontal scanning period, a polarity of a signal potential supplied from the first data signal line and a polarity of a signal potential supplied from the second data signal line are different from each other.

[0065] A method for driving a liquid crystal panel in accordance with the present invention is a method for driving a liquid crystal panel including: a first scanning signal line, a second scanning signal line, a third scanning signal line, and a fourth scanning signal line which are arranged in order; a first pixel, a second pixel, a third pixel, and a fourth pixel connected to the first scanning signal line, the second scanning signal line, the third scanning signal line, and the fourth scanning signal line, respectively; and a first retention capacitor wire and a second retention capacitor wire, the first to fourth pixels each including a plurality of pixel electrodes, the first and second pixels with the first retention capacitor wire

forming capacitors, the second and third pixels with the second retention capacitor wire forming capacitors, and the second and third pixels having the same color, said method including: simultaneously selecting the first and second scanning signal lines and thereafter simultaneously selecting the third and fourth scanning signal lines; separately controlling potentials of the first and second retention capacitor wires; and in a case where the second and third pixels are to have an identical predetermined luminance in two frames, writing a first signal potential to the second pixel in one of the two frames and writing a second signal potential having a polarity identical to that of the first signal potential to the third pixel in the other of the two frames, the first and second signal potentials being different from each other.

[0066] The present invention is not limited to the descriptions of embodiments above, but may be altered by a skilled person within the scope of the claims. An embodiment based on a common general technical knowledge or a proper combination of such embodiments is encompassed in embodiments of the present invention.

INDUSTRIAL APPLICABILITY

[0067] The present invention is suitable for a liquid crystal TV and a liquid crystal display.

REFERENCE SIGNS LIST

- [0068]** Pn to Pn+2 Pixels
- [0069]** CSLn to CSLn+2 Retention capacitor wires
- [0070]** Gn to Gn+2 Scanning signal lines
- [0071]** VTm Signal potential (negative, first signal potential)
- [0072]** VTp Signal potential (positive, fourth signal potential)
- [0073]** VTM Signal potential (negative, second signal potential)
- [0074]** VTP Signal potential (positive, third signal potential)
- [0075]** Tn to Tn+2 Transistors
- [0076]** tn+2 Transistors
- [0077]** LCD Liquid crystal display device
- [0078]** LCP Liquid crystal panel

1: A liquid crystal display device comprising:

a first scanning signal line, a second scanning signal line, a third scanning signal line, and a fourth scanning signal line which are arranged in order;

a first pixel, a second pixel, a third pixel, and a fourth pixel connected to the first scanning signal line, the second scanning signal line, the third scanning signal line, and the fourth scanning signal line, respectively; and

a first retention capacitor wire and a second retention capacitor wire, wherein

the first to fourth pixels each include a plurality of pixel electrodes,

the first and second pixels with the first retention capacitor wire form capacitors, and the second and third pixels with the second retention capacitor wire form capacitors,

the first and second scanning signal lines are simultaneously selected and thereafter the third and fourth scanning signal lines are simultaneously selected,

potentials of the first and second retention capacitor wires are separately controlled,

the second pixel and the third pixel have the same color, and

in a case where the second and third pixels are to have an identical predetermined luminance in two frames, a first signal potential is written to the second pixel in one of the two frames and a second signal potential having a polarity identical to that of the first signal potential is written to the third pixel in the other of the two frames, the first and second signal potentials being different from each other.

2: The liquid crystal display device as set forth in claim 1, wherein the first signal potential is smaller than the second signal potential.

3: The liquid crystal display device as set forth in claim 1, wherein:

a third signal potential is written to the third pixel in said one of the two frames;

a fourth signal potential having a polarity identical to that of the third signal potential is written to the second pixel in said other of the two frames; and

(i) an absolute value of a difference between the first signal potential and the fourth signal potential and (ii) an absolute value of a difference between the second signal potential and the third signal potential are different from each other.

4: The liquid crystal display device as set forth in claim 3, wherein the absolute value of the difference between the first signal potential and the fourth signal potential is larger than the absolute value of the difference between the second signal potential and the third signal potential.

5: (canceled)

6: The liquid crystal display device as set forth in claim 1, wherein, in a case where the number of the all gray levels is 256, the predetermined luminance corresponds to any one of gray levels 5 to 80.

7: The liquid crystal display device as set forth in claim 1, wherein:

a potential of each of the first and second retention capacitor wires periodically switches between two levels; and the first changes in potentials of the first and second retention capacitor wires after the simultaneous selection of the first and second scanning signal lines are opposite to each other.

8: A liquid crystal display device as set forth in claim 1, further comprising: a first data signal line and a second data signal line; and a first transistor, a second transistor, a third transistor, a fourth transistor, a fifth transistor, and a sixth transistor, wherein:

the first pixel includes a first pixel electrode and a second pixel electrode, the second pixel includes a third pixel electrode and a fourth pixel electrode, and the third pixel includes a fifth pixel electrode and a sixth pixel electrode;

the first pixel electrode is connected to the first scanning signal line and the first data signal line via the first

transistor, and the second pixel electrode is connected to the first scanning signal line and the first data signal line via the second transistor;

the third pixel electrode is connected to the second scanning signal line and the second data signal line via the third transistor, and the fourth pixel electrode is connected to the second scanning signal line and the second data signal line via the fourth transistor;

the fifth pixel electrode is connected to the third scanning signal line and the first data signal line via the fifth transistor, and the sixth pixel electrode is connected to the third scanning signal line and the first data signal line via the sixth transistor; and

the first retention capacitor wire with the second and third pixel electrodes forms capacitors, and the second retention capacitor wire with the fourth and fifth pixel electrodes forms capacitors.

9: The liquid crystal display device as set forth in claim 8, wherein, in one horizontal scanning period, a polarity of a signal potential supplied from the first data signal line and a polarity of a signal potential supplied from the second data signal line are different from each other.

10: A method for driving a liquid crystal panel, the liquid crystal panel including: a first scanning signal line, a second scanning signal line, a third scanning signal line, and a fourth scanning signal line which are arranged in order; a first pixel, a second pixel, a third pixel, and a fourth pixel connected to the first scanning signal line, the second scanning signal line, the third scanning signal line, and the fourth scanning signal line, respectively; and a first retention capacitor wire and a second retention capacitor wire, the first to fourth pixels each including a plurality of pixel electrodes, the first and second pixels with the first retention capacitor wire forming capacitors, the second and third pixels with the second retention capacitor wire forming capacitors, and the second and third pixels having the same color,

said method comprising:

simultaneously selecting the first and second scanning signal lines and thereafter simultaneously selecting the third and fourth scanning signal lines;

separately controlling potentials of the first and second retention capacitor wires; and

in a case where the second and third pixels are to have an identical predetermined luminance in two frames, writing a first signal potential to the second pixel in one of the two frames and writing a second signal potential having a polarity identical to that of the first signal potential to the third pixel in the other of the two frames, the first and second signal potentials being different from each other.

11: The liquid crystal display device as set forth in claim 1, wherein the predetermined luminance corresponds to a gray level included in a lower half of all gray levels

* * * * *

专利名称(译)	液晶显示装置和液晶面板的驱动方法		
公开(公告)号	US20150042693A1	公开(公告)日	2015-02-12
申请号	US14/345010	申请日	2012-09-13
[标]申请(专利权)人(译)	夏普株式会社		
申请(专利权)人(译)	夏普株式会社		
当前申请(专利权)人(译)	夏普株式会社		
[标]发明人	HIRATA MITSUAKI		
发明人	HIRATA, MITSUAKI		
IPC分类号	G09G3/36		
CPC分类号	G09G3/3659 G09G3/3607 G09G2300/0439 G09G2320/0233 G09G2300/0876 G09G2310/0202 G09G2300/0478 G02F1/136286 G09G3/3614 G09G3/3666 G09G2300/0426 G09G2310/0221 G09G2320/0247		
优先权	2011205172 2011-09-20 JP		
其他公开文献	US9111505		
外部链接	Espacenet USPTO		

摘要(译)

本发明的液晶显示装置采用CS控制像素分割的液晶面板，并且被配置为使得两个相邻的像素行共用一个保持电容器线，并且同时选择两个相邻的扫描信号线。在沿扫描方向相邻但未同时选择的两个像素（ $(P_n + 1)$ ）和 $(P_n + 2)$ ）在两帧中具有相同的预定亮度的情况下，将第一信号电位写入一个两帧中的一帧中的像素 $(P_n + 1)$ 和具有与第一信号电位的极性相同的极性的第二信号电位被写入两帧中的另一帧中的另一像素 $(P_n + 2)$ ，第一和第二第二信号电位彼此不同。本发明使得可以抑制在液晶显示装置中出现的显示不均匀的横向线。

