



US 20150137099A1

(19) **United States**(12) **Patent Application Publication**
Choi(10) **Pub. No.: US 2015/0137099 A1**(43) **Pub. Date: May 21, 2015**(54) **ORGANIC LIGHT EMITTING DISPLAY
DEVICE**(52) **U.S. CL.**CPC **H01L 27/3248** (2013.01); **H01L 27/3269**
(2013.01); **H01L 51/52** (2013.01)(71) Applicant: **LG DISPLAY CO., LTD.**, Seoul (KR)(72) Inventor: **HeeDong Choi**, Seosan-si (KR)(21) Appl. No.: **14/537,740**(22) Filed: **Nov. 10, 2014**(30) **Foreign Application Priority Data**

Nov. 15, 2013 (KR) 10-2013-0138837

Publication Classification(51) **Int. Cl.****H01L 27/32**

(2006.01)

H01L 51/52

(2006.01)

(57) **ABSTRACT**

An organic light emitting display device comprises a driving transistor for driving an organic light emitting diode; a first transistor controlled by a scan signal and connected between a reference voltage line and a first node of the driving transistor; a second transistor controlled by the scan signal and connected between a data line and a second node of the driving transistor; a first plate with an improved conductive characteristic and connected to the semiconductor layer of the driving transistor and the semiconductor layer of the first transistor; a second plate positioned on the first plate, and connected to the semiconductor layer of the second transistor and a gate electrode of the driving transistor; and a pixel electrode of the organic light emitting diode, positioned on the second plate and connected to the first plate through a contact hole.




FIG. 2




FIG. 3A




FIG. 3B




FIG. 4




FIG. 5




FIG. 6A




FIG. 6B




FIG. 7




FIG. 8




FIG. 9A




FIG. 9B




FIG. 10




FIG. 11A




FIG. 11B





FIG. 12



**ORGANIC LIGHT EMITTING DISPLAY
DEVICE****CROSS-REFERENCE TO RELATED
APPLICATION**

[0001] This application claims priority from and the benefit under 35 U.S.C. §119(a) of Korean Patent Application No. 10-2013-0138837, filed on Nov. 15, 2013, which is hereby incorporated by reference for all purposes as if fully set forth herein.

BACKGROUND

[0002] 1. Technical Field

[0003] The present disclosure relates to an organic light emitting display device.

[0004] 2. Description of the Prior Art

[0005] Recently, organic light emitting display devices have been in the spotlight as being display devices having fast response rates, high light emitting efficiency, high luminance, and wide viewing angles. These advantages are due to the use of an organic light emitting diode, which is self-illuminating (emits light by itself).

[0006] Such an organic light emitting display device includes pixels arranged in a matrix form, the pixels including an organic light emitting diode. The display device controls brightness of pixels that are selected by a scan signal, according to a grayscale of data.

[0007] Each pixel of the organic light emitting display device includes, in addition to the organic light emitting diode, a data line and a gate line crossing each other, a transistor, and a storage capacitor connected to the data line and the gate line.

[0008] Each pixel may include a corresponding transistor in order to further perform various functions. Therefore, a number of signal lines for providing various signals to transistors increases, and thus a pixel structure becomes more complex. For example, when an internal or external compensation circuit for compensating for luminance non-uniformity between pixels is applied to a pixel structure, a transistor related to a sensing operation for a compensation may be added. This increases the number of necessary signal lines, and thus this causes complexity of the pixel structure.

[0009] In addition, according to a demand or design need for a larger size and a higher resolution, the number of signal lines may be increased, and thus a pixel structure becomes more complex.

[0010] As described above, the number of the signal lines is increased due to the increased number of design needs, such as additions of various functions such as sensing and compensation functions, need for larger size and the higher resolution. Therefore, the number of IC pads and the number of ICs are increased, and thus the pixel structure becomes more complex.

[0011] This may complicate the manufacturing process, increase the possibility of defects, remarkably reduce an opening ratio, and considerably reduce the lifespan of an organic light emitting diode. Ultimately, a high quality display panel may not be manufactured and thus the throughput may be reduced.

SUMMARY

[0012] Against this background, an aspect of the present disclosure is to provide an organic light emitting display device having a simple and compact structure.

[0013] Another aspect of the present disclosure is to provide an organic light emitting display device having a pixel structure with an improved opening ratio.

[0014] Another aspect of the present disclosure is to provide an organic light emitting display device having a pixel structure including a double capacitor in a pixel by a simplified process flow.

[0015] Another aspect of the present disclosure is to provide an organic light emitting display device having a pixel structure capable of preventing a short defect which may be caused by a step difference due to a contact hole.

[0016] In accordance with an aspect of the present disclosure, an organic light emitting display device comprises a driving transistor, including a semiconductor layer that includes an oxide semiconductor material, and for driving an organic light emitting diode. The display device further comprises a first transistor including a semiconductor layer including an oxide semiconductor material, controlled by a scan signal, and connected between a reference voltage line and a first node of the driving transistor. The display device further comprises a second transistor including a semiconductor layer including the oxide semiconductor material, controlled by the scan signal commonly provided from a gate line, and connected between a data line and a second node of the driving transistor. The display device also includes a first plate including the oxide semiconductor material of which conductive characteristic is improved, and connected to the semiconductor layer of the driving transistor and the semiconductor layer of the first transistor. The display device also includes a second plate positioned on the first plate, and connected to the semiconductor layer of the second transistor and a gate electrode of the driving transistor. The device further includes a pixel electrode of the organic light emitting diode, positioned on the second plate and connected to the first plate through a contact hole.

[0017] As described above, according to the present disclosure, an organic light emitting display device can provide a simple and compact structure.

[0018] In addition, according to the present disclosure, an organic light emitting display device can provide a pixel structure capable of increasing an opening ratio.

[0019] In addition, according to the present disclosure, an organic light emitting display device can include a double capacitor in a pixel by a simplified process flow.

[0020] In addition, according to the present disclosure, an organic light emitting display device can prevent a short defect, which may be caused by a step difference due to a contact hole.

[0021] Thus, a display panel having a good quality can be manufactured in a high throughput.

[0022] These structural improvements and resulting functional advantages are further emphasized when applied to a display panel having a high resolution and a large size.

BRIEF DESCRIPTION OF THE DRAWINGS

[0023] The above and other objects, features and advantages of the present disclosure will be more apparent from the following detailed description taken in conjunction with the accompanying drawings, in which:

[0024] FIG. 1 is an overall system construction diagram for an organic light emitting display device to which embodiments are applied.

[0025] FIG. 2 is an equivalent circuit diagram for a pixel in a display panel of the organic light emitting display device of FIG. 1, according to one or more embodiments.

[0026] FIG. 3A is a cross-sectional view schematically illustrating a portion of a display panel of an organic light emitting display device according to a first embodiment. FIG. 3B is an enlarged view of a portion A in FIG. 3A, according to the first embodiment.

[0027] FIG. 4 is a cross-sectional view taken along a cutting line I-I' of FIG. 3A, according to one or more embodiments.

[0028] FIG. 5 is a cross-sectional view taken along a cutting line II-II' of FIG. 3B, according to one or more embodiments.

[0029] FIG. 6A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a second embodiment. FIG. 6B is an enlarged view of a portion B in FIG. 6A, according to the second embodiment.

[0030] FIG. 7 is a cross-sectional view taken along a cutting line III-III' of FIG. 6A, according to one or more embodiments.

[0031] FIG. 8 is a cross-sectional view taken along a cutting line IV-IV' of FIG. 6B, according to one or more embodiments.

[0032] FIG. 9A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a third embodiment. FIG. 9B is an enlarged view of a portion C in FIG. 9A, according to the third embodiment.

[0033] FIG. 10 is a cross-sectional view taken along a cutting line V-V' of FIG. 9B, according to one or more embodiments.

[0034] FIG. 11A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a fourth embodiment. FIG. 11B is an enlarged view of a portion D in FIG. 11A, according to the fourth embodiment.

[0035] FIG. 12 is a cross-sectional view taken along a cutting line VI-VT' of FIG. 11B, according to one or more embodiments.

DETAILED DESCRIPTION OF THE EXEMPLARY EMBODIMENTS

[0036] Hereinafter, embodiments of the present disclosure will be described in detail with reference to the accompanying drawings. In the following description, the same elements will be designated by the same reference numerals although they are shown in different drawings. Further, in the following description of the present disclosure, a detailed description of known functions and configurations incorporated herein will be omitted when it may not provide additional clarity to the subject matter of the present disclosure.

[0037] In addition, terms, such as first, second, A, B, (a), (b) or the like may be used herein when describing components of the present disclosure. Each of these terminologies is not used to define an essence, order or sequence of a corresponding component but used merely to distinguish the corresponding component from other component(s). In the case that it is described that a certain structural element "is connected to", "is coupled to", or "is in contact with" another structural element, it should be interpreted that another structural element may "be connected to", "be coupled to", or "be in

contact with" the structural elements as well as that the certain structural element is directly connected to or is in direct contact with another structural element.

[0038] Embodiments of the present disclosure provide an organic light emitting display device having a panel structure with a simple and compact pixel structure, despite an increased number of signal lines connected to the pixel. In other words, positions of a transistor, a capacitor, an organic light emitting diode, and a signal line connection is simplified and compact in the pixel structure, according to some embodiments.

[0039] Therefore, an opening ratio can be increased, defect occurrence possibility can be reduced, manufacturing can be easier, and a panel having a good quality can be manufactured in a high throughput. Specifically, such an effect may become larger when an organic light emitting display device including a panel of a high resolution and a large size is manufactured.

[0040] FIG. 1 is an overall system construction diagram for an organic light emitting display device to which embodiments are applied.

[0041] Referring to FIG. 1, an organic light emitting display device 10, to which embodiments are applied, includes a display panel 11, a data driving unit 12, a gate driving unit 13 and a timing controller 14. The display panel 11 includes a plurality of pixels P disposed in areas where a data line DL (of a plurality of data lines DL formed in a direction) intersects with a gate line GL (of a plurality of gate lines GL formed in another direction). The data driving unit 12 provides a data voltage through the data line. The gate driving unit 13 provides a scan signal through the gate line. The timing controller 14 controls the driving timing of the data driving unit 12 and the gate driving unit 13.

[0042] Referring to FIG. 1, in the display panel 11, the plurality of data lines DL1, . . . , and DL4N are formed in a direction and the plurality of gate lines GL1, . . . , and GLM are formed in another direction, the gate lines GL1, . . . , and GLM intersecting the data lines DL1, . . . , and DL4N.

[0043] In the display panel 11, each pixel P is defined in an area where the data lines DL1, . . . , and DL4N and the M gate lines GL1, . . . , and GLM intersect. A pixel structure for each pixel P is described in more detail with reference to FIG. 2.

[0044] FIG. 2 is an equivalent circuit diagram for a pixel in the display panel of the organic light emitting display device of FIG. 1, according to one or more embodiments.

[0045] Referring to FIG. 2, each pixel P is connected to one data line DL, and receives only one scan signal SCAN through one gate line GL.

[0046] As shown in FIG. 2, each pixel includes an Organic Light Emitting Diode (OLED), a driving transistor DT, a first transistor T1, a second transistor T2, a storage capacitor Cst, and the like. As described above, each pixel includes three transistors DT, T1, and T2 and one storage capacitor Cst, and thus it is referred to that each pixel has a 3T(Transistor)1C (Capacitor) structure.

[0047] The driving transistor DT in each pixel receives a driving voltage EVDD provided through a driving voltage line DVL, and is a transistor driving the OLED under a control of a voltage (i.e., a data voltage) of a gate node N2, which is applied through the second transistor T2.

[0048] The driving transistor DT includes a first node N1, the second node N2, and a third node N3. The driving transistor DT is connected to the first transistor T1 through the

first node N1, the driving transistor DT is connected to the second node N2, and receives the driving voltage EVDD through the third node N3.

[0049] Here, for an example, the first node of the driving transistor DT may be a source node (may be referred to as a source electrode), the second node of the driving transistor DT may be a gate node (may be referred to as a gate electrode), and the third node of the driving transistor DT may be a drain node (may be referred to as a drain electrode). The first node, the second node, and the third node of the driving transistor DT may be changed according to a type change of a transistor, a circuit change, and the like.

[0050] In addition, the first transistor T1 is controlled by the scan signal SCAN provided from the gate line GL. The first transistor T1 is connected between the first node N1 of the driving transistor DT and a reference voltage line RVL providing a reference voltage Vref or a connection pattern CP connected to the reference voltage line RVL. The first transistor T1 may be referred to as a sensor transistor.

[0051] In addition, the second transistor T2 is controlled by the scan signal SCAN commonly provided through the gate line GL, and is connected between a corresponding data line DL and the second node N2 of the driving transistor DT. The second transistor T2 may be referred to as a switching transistor.

[0052] In addition, the storage capacitor Cst is connected between the first node N1 and the second node N2 of the driving transistor. The storage capacitor Cst may maintain a data voltage during one frame.

[0053] As described above, the first transistor T1 and the second transistor T2 are controlled by one scan signal provided through one gate line (i.e., a common gate line). As described above, since each pixel uses one scan signal, each pixel has a basic pixel structure of a "3T1C based 1 scan structure" in a first embodiment of the present disclosure.

[0054] Related to the 3T1C based 1 scan structure, the second transistor T2 basically is a transistor that serves a driving function which applies a data voltage to the gate node N2 of the driving transistor DT. The first transistor T1 may also be related to a driving function, however, the first transistor basically is a transistor that serves a sensing function which compensates for a luminance deviation between pixels. Since uses and functions of the two transistors T1 and T2 are different, controlling of the two transistors T1 and T2 using one scan signal has an effect on related operations (e.g., a driving operation and a sensing operation). Therefore, in order to properly perform a driving operation, a sensing operation and the like of a pixel, a separate device (e.g., a second switch and the like) and a change of an operation scheme (e.g., an operation timing and the like) may be necessary, and this will be described together with a compensation construction (function) described later.

[0055] As described above, each pixel according to the organic light emitting display device 10 of the first embodiment has the "3T1C based 1 scan structure (i.e., a common scan structure)" which receives one scan signal SCAN through one gate line GL under the 3T1C structure. That is, the scan signal (i.e., a common scan signal) provided through one gate line GL (e.g., a common gate line connected to both the first and second transistors) is commonly applied to the gate node of the first transistor and the gate node of the second transistor. Alternatively, different scan signals may be applied to the gate node of the first transistor and the gate node of the second transistor, respectively.

[0056] Meanwhile, the pixel structure of the organic light emitting display device 10, according to the first embodiment, includes a "signal line connection structure" related to a connection between each pixel and various signal lines, such as the data line, the gate line GL, the driving voltage line DVL, and the reference voltage line RVL, in addition to the "basic pixel structure (i.e., 3T1C based 1 scan structure)" described with reference to FIG. 2.

[0057] Here, the various signal lines further include the reference voltage line RVL for providing the reference voltage Vref to each pixel, the driving voltage line DVL for providing the driving voltage EVDD to each pixel, and the like, in addition to the data line for providing the data voltage to each pixel and the gate line for providing the scan signal to each pixel.

[0058] The above-mentioned reference voltage line RVL and the driving voltage line DVL are formed in parallel with the data line DL. The number of the reference voltage lines RVL and the number of the driving voltage lines DVL may be the same as the number of the data lines or may be different from the number of the data lines.

[0059] When the number of the reference voltage lines RVL and the number of the driving voltage lines DVL are the same as the number of the data lines, each pixel is connected to one data line DL and one gate line GL, and may be directly connected to one driving voltage line DVL and one reference voltage line RVL.

[0060] In this case, all of the signal line connection structures of each pixel may be the same. That is, a basic unit of the signal line connection structure is one pixel, and thus the signal line connection structure may be regular per one pixel (i.e., one pixel row).

[0061] In addition, in the present specification and drawings, the pixel connected to the data line DL may be, for example, an R (red) pixel, a G (green) pixel, a B (blue) pixel and a W (White) pixel.

[0062] When the number of the reference voltage lines RVL and the number of the driving voltage lines DVL are smaller than the number of the data lines, some pixels may be directly connected to the driving voltage line DVL and the reference voltage line RVL, and other pixels may be connected to each of the driving voltage line DVL and the reference voltage line RVL through the connection pattern CP (illustrated, for instance, in FIGS. 3A and 6A) instead the other pixels are directly connected to the driving voltage line DVL and the reference voltage line RVL.

[0063] In this case, the signal line connection structures of each pixel may be different. However, although the signal line connection structures of each pixel are different, the signal line connection structures may be the same per a plurality of pixels. That is, a unit of the signal line connection structure may be the plurality of pixels not one pixel P. The signal line connection structure may be repeatedly regular per the plurality of pixels (i.e., a plurality of pixel rows).

[0064] In addition, in the present specification and drawings, the transistors DT, T1 and T2 are N types, however, these are for convenience of description, and according to a circuit design change, all of the transistors DT, T1, and T2 may be changed to P types. Alternatively, some of the transistors DT, T1 and T2 may be implemented as N types and others of the transistors DT, T1 and T2 may be implemented as P types. In addition, the OLED may be changed to an inverted type.

[0065] In addition, the transistors DT, T1 and T2 described in the present specification may be referred to Thin Film Transistors (TFTs).

[0066] Aspects of a First Embodiment

[0067] FIG. 3A is a cross-sectional view schematically illustrating a portion of the display panel of the organic light emitting display device according to the first embodiment. FIG. 3B is an enlarged view of a portion A in FIG. 3A, according to the first embodiment.

[0068] Referring to FIGS. 3A and 3B, and as explained above with reference to FIG. 2, each pixel P connected to the data line DL includes the driving transistor DT receiving the driving voltage EVDD and driving the OLED, the first transistor T1 (see FIG. 3B) receiving the reference voltage Vref and transferring the reference voltage Vref to the first node N1 of the driving transistor DT (FIG. 3B), the second transistor T2 (FIG. 3B) receiving the data voltage Vdata and transferring the data voltage Vdata to the second node N2 of the driving transistor DT, the capacitor Cst (FIG. 3B) connected between the first node N1 and the second node N2 of the driving transistor DT, and the like. As described above, the pixel structure of such a pixel is referred to as the "3T1C based 1 scan structure".

[0069] As described above, since uses and functions of the two transistors T1 and T2 are different, controlling the two transistors T1 and T2 by applying the scan signal from one gate line may have a large effect on the driving operations and sensing operations related to the two transistors T1 and T2. Therefore, the first embodiment of the present disclosure needs a driving method and an additional construction (e.g., a second switch and the like) so as to normally perform a driving operation and a sensing operation of the pixel without problems, in implementing a simple and compact pixel structure, that is, the 3T1C based 1 scan structure.

[0070] The first transistor T1 is the sensor transistor which senses to compensate for a luminance deviation between the pixels, and the second transistor T2 is the switching transistor which selects the driving transistor.

[0071] A semiconductor layer 303a of each driving transistor DT, a semiconductor layer 303b of each first transistor T1 and a semiconductor layer 303c of each second transistor T2 are formed on a substrate 300.

[0072] The semiconductor layer 303a of each driving transistor DT is formed in correspondence to an area where a gate electrode 301a of each driving transistor DT is formed. The semiconductor layer 303b of each first transistor T1 is formed in correspondence to a portion playing a role of a gate electrode in a gate line 301b of each first transistor T1. The semiconductor layer 303c of each second transistor T2 is formed in correspondence to a portion playing a role of a gate electrode in a gate line 301b of each second transistor T2.

[0073] An area of the semiconductor layer 303a of each driving transistor DT, corresponding to the area where the gate electrode 301a is formed is a first area 303ab which is a channel area. An area of the semiconductor layer 303b of each first transistor T1, corresponding to the gate line 301b is a first area 303ba which is a channel area. An area of the semiconductor layer 303c of each second transistor T2, corresponding to the gate line 301b becomes a channel area. Both sides of each channel area become source-drain areas by an injection of impurities.

[0074] Next, the gate electrode 301a of each driving transistor DT, the gate line 301b for forming the gate electrodes of the first and second transistors T1 and T2, a connection pat-

tern 302a connected to each driving voltage line DVL, a connection pattern 302b connected to each reference voltage line RVL, and a first plate 302c for forming each storage capacitor Cst are formed, on the substrate 300 on which the semiconductor layer 303a of each driving transistor DT, the semiconductor layer 303b of each first transistor T1 and the semiconductor layer 303c of each second transistor T2 are formed.

[0075] Here, the gate line 301b is a common gate line for commonly applying the scan signal to the gate electrodes of the first and second transistors T1 and T2 included in the pixel, which are connected to the gate line 301b. Therefore, a portion where the gate electrode is formed in the gate line 301b is formed wider than other portions in consideration of a channel length L which is a designed value. In addition, a portion where a gate electrode is not formed in the gate line 301b may be narrowly formed in order to minimize a parasitic capacitance.

[0076] Next, the signal lines such as the driving voltage line 305 and the data lines 306 corresponding each pixel row are formed on the substrate 300.

[0077] A drain electrode 307a of the first transistor T1 connected to the connection pattern 302b (i.e., the connection pattern of the reference voltage line), which is formed on the substrate 300, through a contact hole, a drain electrode 307c of each driving transistor of all pixels, a second plate 307d playing a role of forming the storage capacitor by including a portion connected to the gate electrode 301a of the driving transistor DT of each pixel through a contact hole and a portion playing a role of the source electrode of the second transistor T2 of each pixel, a source electrode 307e of the first transistor T1 of each pixel, which is connected to the first plate 302c through a contact hole, and the like are further formed.

[0078] The first plate 302c connected to the source electrode 307c of the driving transistor DT of each pixel, and a pixel electrode 308 connected to the source electrode 307e of the first transistor T1 through the contact hole in each pixel are formed per each pixel.

[0079] A pixel defining film (referred to as a bank) 309 (illustrating in the cross sectional view of FIG. 4) which defines the pixel is formed. An organic layer (not shown) including a light emitting layer corresponding to each pixel may be laminated on the pixel defining film 309, and a common electrode for all pixels may be laminated on the organic layer. Meanwhile, in a case of a White Organic Light Emitting Diode (WOLED), an organic layer including the same light emitting layer may be laminated and a color filter may be formed in a light emitting direction in all pixels.

[0080] FIG. 4 is a cross-sectional view taken along a cutting line I-I' of FIG. 3A. FIG. 5 is a cross-sectional view taken along a cutting line II-II' of FIG. 3B.

[0081] Referring to FIGS. 3A to 5, a buffer layer 310 is formed on the substrate 300. The semiconductor layer 303a of the driving transistor DT and the semiconductor layer 303b of each first transistor T1 are formed on the substrate 300 on which the buffer layer 310 is formed. As described above, although not shown in FIG. 4, the semiconductor layer 303c of the second transistor T2 is formed on the substrate in a manner similar to the semiconductor layer 303a of the driving transistor DT and the semiconductor layer 303b of each first transistor T1. Each of the semiconductor layers 303a and 303b includes first areas 303aa and 303ba where a plasma is not processed in central areas thereof, and second areas 303ab

and 303bb which are conductive by a plasma process and positioned at both sides of the first areas 303aa and 303ba, respectively. Similarly, the semiconductor layer 303c of the second transistor T2 includes a first area where a plasma is not processed in a central area thereof, and second areas which become conductive by way of a plasma process and positioned at both sides of the first area.

[0082] Next, a gate insulating film 311 is formed in correspondence to the first area 303aa on the substrate 300 and the oxide semiconductor layer 303a including the first and second areas 303aa and 303ab. In addition, the gate insulating film 311 is formed in correspondence to the first area 303ba on the substrate 300 and the oxide semiconductor layer 303b including the first and second areas 303ba and 303bb. Additionally, the gate insulating film 311 is formed on the buffer layer 310 in correspondence to the first plate 302c for forming the storage capacitor Cst. Similarly, the gate insulating film 311 is formed in correspondence to the first area of the semiconductor layer 303c of the second transistor T2.

[0083] Next, the gate line 301b having a plane form equal to that of the gate insulating film 311 and extending in a direction on the gate insulating film 311 formed on the substrate 300 is formed. The gate line 301b formed on the first area 303ab plays the role of the gate electrode of the first transistor T1. The gate line 301b extends in a direction on the gate insulating film 311, which is formed in correspondence to the first area of the semiconductor layer 303c of the second transistor T2. The gate line 301b extending in correspondence to the first area of the semiconductor layer 303c of the second transistor T2 plays a role of the gate electrode of the second transistor T2.

[0084] In addition, the first plate 302c and the gate electrode 301a of the driving transistor DT are formed on the gate insulating film 311. The gate line 301b, the first plate 302c and the gate electrode 301a of the driving transistor DT are formed with the same gate electrode material by the same process.

[0085] An interlayer dielectric film 312 including an inorganic insulating material (e.g., oxide silicon (SiO₂) or nitride silicon (SiN_x)) or an organic insulating material is formed on the gate line 301b, the first plate 302c and the gate electrode 301a of the driving transistor DT and a whole surface of the substrate 300. The interlayer dielectric film 312 includes first and second contact holes 313a and 313b exposing the second areas 303ab positioned at the both sides of the first area 303aa of the semiconductor layer 303a of the driving transistor DT, respectively. In addition, the interlayer dielectric film 312 includes third and fourth contact holes 313c and 313d exposing the second areas 303bb positioned at both sides of the first area 303ba of the semiconductor layer 303b of the first transistor T1, respectively. In addition, the interlayer dielectric film 312 includes fifth and sixth contact holes 313e and 313f exposing the first plate 302c in an area adjacent to one of the second area 303ab of the semiconductor layer 303a of the driving transistor DT and one of the second area 303bb of the semiconductor layer 303b of the first transistor T1.

[0086] The driving voltage line 305, the data line 306 and the like defining the pixel area P by intersecting with the gate line 301b are formed on the interlayer dielectric film 312 including the first to sixth contact holes 313a to 313f.

[0087] In addition, the driving voltage line 305 connected to the second area 303ab of the semiconductor layer 303a of the driving transistor through the first contact hole 313a is

formed on the interlayer dielectric film 312 including the first to sixth contact holes 313a to 313f. A portion of the driving voltage line, which is connected to the second area 303ab of the semiconductor layer 303a of the driving transistor DT through the first contact hole 313a plays a role of the source electrode of the driving transistor DT.

[0088] In addition, the drain electrode 307c of the driving transistor DT, which is spaced apart from the driving voltage line 305, connected to the second area 303ab of the semiconductor layer 303a of the driving transistor DT through the second contact hole 313b, and connected to the first plate 302c through the fifth contact hole 313e is formed on the interlayer dielectric film 312.

[0089] In addition, the source electrode 307e of the first transistor T1, which is connected to the first plate 302c through the sixth contact hole 313f and connected to the second area 303bb of the semiconductor layer 303c of the second transistor T2 through the third contact hole 313c is formed on the interlayer dielectric film 312.

[0090] In addition, the drain electrode 307a of the first transistor T1, which is connected to the second area 303bb of the oxide semiconductor layer 303b through the fourth contact hole 313d, and connected to the connection pattern CP of FIG. 3 through another contact hole, is formed on the interlayer dielectric film 312.

[0091] In addition, the second plate 307d forming the storage capacitor Cst by including the portion connected to the gate electrode 301a of the driving transistor through the contact hole in a position corresponding to the first plate 302c and the portion playing a role of the source electrode of the second transistor T2 is formed on the interlayer dielectric film 312. That is, the gate electrode 301a of the driving transistor DT is connected to the second plate 307d through the contact hole, and the second plate 307d is connected to the second area 303cd of the semiconductor layer 303c through another contact hole.

[0092] The first plate 302c and the second plate 307d, which are sequentially laminated in the pixel area, play a role of forming the storage capacitor Cst.

[0093] The semiconductor layer 303a which is sequentially laminated in the pixel area, the gate electrode 301a formed on the gate insulating film, the portion formed on the interlayer dielectric film 312 and playing a role of the source electrode of the driving voltage line 305 connected to the second area 303ab of the oxide semiconductor layer 303a through first and second contact holes 313a and 313b, and the drain electrode 307c forms the driving transistor DT.

[0094] In addition, the oxide semiconductor layer 303b, which is sequentially laminated in the pixel area, the gate electrode 301b formed on the gate insulating film, and the source electrode 307e and the drain electrode 307a formed on the interlayer dielectric film 312 and connected to the second area 303bb of the oxide semiconductor layer 303b through the third and fourth contact holes 313c and 313d form the first transistor T1.

[0095] Next, a protection film 313 including an inorganic insulating material (e.g., oxide silicon (SiO₂) or nitride silicon (SiN_x)) or an organic insulating material (e.g., benzocyclobutene or photoacryl) is formed on a whole surface of the substrate 300 on which the driving transistor DT, the first transistor T1 and the storage capacitor Cst are formed. At this time, the protection film 313 includes a source contact hole 315 exposing the source electrode 307e.

[0096] In addition, the pixel electrode 308 connected to the source electrode 307e through the source contact hole 315 and extending up to a light emitting area is formed on the protection film 313 including the source contact hole 315. The pixel electrode 308 and the source electrode 307e which are sequentially laminated in the pixel area are connected through the source contact hole 315, and the first plate 302c and the source electrode 307e are connected through the source contact hole 315. The pixel electrode 308 and the first plate 302c form the double storage capacitor Cst together with the second plate 307d.

[0097] A planarization film 314 is formed on the protection film 313. The planarization film 314 is not formed between the pixel electrode 308 and the second plate 307d in order to form the storage capacitor Cst.

[0098] In a process for the display panel 11 of the organic light emitting display device 10, according to the first embodiment, a top gate in which the gate electrode 301a is positioned over the semiconductor layer 303b is described, but is an example for convenience of description. In an alternative process, a bottom gate in which the gate electrode 301a is positioned under the semiconductor layer 303b may be provided for the display panel 11 of the organic light emitting display device 10 according to the first embodiment. In the case of the bottom gate, the pixel structure may be changed in correspondence to the bottom gate. Meanwhile, semiconductor layers 303a, 303b and 303c may be, for example, oxide semiconductors, are not limited thereto, and may be amorphous silicon, poly silicon that is obtained by crystallizing amorphous silicon, organic semiconductors (hereinafter, it is the same as above).

[0099] Aspects of a Second Embodiment

[0100] FIG. 6A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a second embodiment. FIG. 6B is an enlarged view of a portion B in FIG. 6A, according to the second embodiment.

[0101] Referring to FIGS. 6A and 6B, each pixel of the second embodiment, which is connected to a driving voltage line DVL for providing a driving voltage EVDD and a data line DL analogous to the first embodiment, includes a 3T1C based scan structure in which a driving transistor DT, a first transistor T1, and a second transistor T2 are formed on a substrate 600. Some pixels may not be directly connected to the driving voltage line DVL and a reference voltage line RVL, and may be connected to each of the driving voltage line DVL and the reference voltage line

[0102] RVL through a connection pattern CP.

[0103] As shown in FIGS. 6A and 6B, a semiconductor layer 603a of each driving transistor DT, a semiconductor layer 603b of each first transistor T1 and a semiconductor layer 603c of each second transistor T2 are formed on the substrate 600.

[0104] The driving transistor DT includes the semiconductor layer formed with an oxide semiconductor material, and is for driving an OLED.

[0105] The first transistor T1 includes the semiconductor layer formed with an oxide semiconductor material, is controlled by a scan signal, and is connected between a first node of the driving transistor DT and the reference voltage line RVL.

[0106] The second transistor T2 includes the semiconductor layer formed with an oxide semiconductor material, is controlled by the scan signal commonly provided through a

gate line, and is connected between a second node of the driving transistor DT and data line DL.

[0107] A conductive characteristic of a portion of the semiconductor layer 603a of the driving transistor DT is improved, the portion of the semiconductor layer 603a of the driving transistor DT, of which the conductive characteristic is improved is connected to the driving voltage line DVL.

[0108] A conductive characteristic of a portion of the semiconductor layer 603b of the first transistor T1 is improved, the portion of the semiconductor layer 603b of the first transistor T1, of which the conductive characteristic is improved is connected to the reference voltage line RVL.

[0109] The semiconductor layer 603a of the driving transistor DT, the semiconductor layer 603b of the first transistor T1, the semiconductor layer 603c of the second transistor T2, and a first plate 607d are simultaneously formed in the same layer.

[0110] The first plate 607d connects the semiconductor layer 603a of the driving transistor DT with the semiconductor layer 603b of the first transistor T1, and is integrally formed.

[0111] The semiconductor layer 603a of the driving transistor DT, the semiconductor layer 603b of the first transistor T1, the semiconductor layer 603c of the second transistor T2, and a first plate 602c are formed with an oxide semiconductor material. In addition, the first plate 602c connects the semiconductor layer 603a of the driving transistor DT with the semiconductor layer 603b of the first transistor T1, and is integrally formed. The oxide semiconductor material may be zinc-oxide series material, and may be zinc-oxide series material including indium. Specifically, the oxide semiconductor material may be Indium Gallium Zinc Oxide (IGZO), Zinc Tin Oxide (ZTO), Zinc Indium Oxide (ZIO), and the like.

[0112] A conductive characteristic of the oxide semiconductor material may be improved, when the oxide semiconductor material is exposed to a plasma or impurities are added to the oxide semiconductor material.

[0113] Specifically, the semiconductor layer 603a of each driving transistor DT is formed in correspondence to an area where a gate electrode 601a of each driving transistor DT is formed. The semiconductor layer 603b of each first transistor T1 is formed in correspondence to a portion playing a role of a gate electrode in a gate line 601b of each first transistor T1. The semiconductor layer 603c of each second transistor T2 is formed in correspondence to a portion playing a role of a gate electrode in a gate line 601b of each second transistor T2.

[0114] Next, the gate electrode 601a of each driving transistor DT, the gate line 601b for forming the gate electrodes of the first and second transistors T1 and T2, a connection pattern 602a connected to each driving voltage line DVL, and a connection pattern 602b connected to each reference voltage line RVL are formed, on the substrate 600 on which the semiconductor layer 603a of each driving transistor DT, the semiconductor layer 603b of each first transistor T1 and the semiconductor layer 603c of each second transistor T2 are formed. Here, the gate line 601b is a common gate line for commonly applying the scan signal to the gate electrodes of the first and second transistors T1 and T2 included in each pixel, which are connected to the gate line 601b.

[0115] Next, signal lines such as the driving voltage line 605 and the data lines 606 corresponding each pixel row are formed on the substrate 600.

[0116] The the semiconductor layer **603a** of the driving transistor DT, the semiconductor layer **603b** of the first transistor T1, the semiconductor layer **603c** of the second transistor T2, and the first plate **602c** are conductive by a plasma process or impurities addition, except for a first area where the gate electrode **601a** and the gate line **601b** are covered.

[0117] A drain electrode **607a** of the first transistor T1, which is connected to the connection pattern **602b** (i.e., the connection pattern of the reference voltage line) formed on the substrate **600** through a contact hole, a second plate **607d** playing a role of forming a storage capacitor Cst by including a portion connected to the gate electrode **601a** of the driving transistor DT of each pixel through a contact hole and a portion playing a role of a source electrode of the second transistor T2 of each pixel, and the like are further formed.

[0118] The first plate **602c** connected to the semiconductor layer **603a** of the driving transistor DT, and a pixel electrode of the OLED connected to a pattern **607e** of the first transistor T1 through a contact hole in each pixel are formed in each pixel. The pixel electrode **608** is positioned on the first plate **602c** and the second plate **607d** and forms the storage capacitor. A protection film **613** is formed on the substrate **600** including the second plate **607d**. A planarization film **614** may be further formed. The planarization film **614** may not be formed in a portion of the storage capacitor Cst.

[0119] A pixel defining film (referred to as a bank) **609** which defines the pixel is formed. An organic layer (not shown) including a light emitting layer corresponding to each pixel may be laminated on the pixel defining film **609**, and a common electrode for all pixels may be laminated on the organic layer. Meanwhile, in a case of a White Organic Light Emitting Diode (WOLED), an organic layer including the same light emitting layer may be laminated and a color filter may be formed in a light emitting direction in all pixels.

[0120] FIG. 7 is a cross-sectional view taken along a cutting line III-III' of FIG. 6A. FIG. 8 is a cross-sectional view taken along a cutting line IV-IV' of FIG. 6B.

[0121] Referring to FIGS. 6A to 8, a buffer layer **610** is formed on the substrate **600**. The semiconductor layer **603a** of the driving transistor DT and the semiconductor layer **603b** of each first transistor T1 are formed on the substrate **600** on which the buffer layer **610** is formed. As described above, although not shown in FIG. 8, the semiconductor layer **603c** of the second transistor T2 is formed on the substrate equally to the semiconductor layer **603a** of the driving transistor DT and the semiconductor layer **603b** of each first transistor T1. In addition, the first plate **602c** connects the semiconductor layer **603b** of the first transistor T1 with the semiconductor layer **603c** of the second transistor T2, and is integrally formed.

[0122] Next, a gate insulating film **611** is formed on first areas **603aa** and **603ba** of the semiconductor layer **603b** of the first transistor T1 and the semiconductor layer **603c** of the second transistor T2. At this time, the gate insulating film **611** is formed in correspondence to a first area of the semiconductor layer **603c**.

[0123] Next, the gate line **601b** having a plane form equal to that of the gate insulating film **611** and extending in a direction on the gate insulating film **611** formed on the substrate **600** is formed. The gate line **601b** formed on a first area **603ab** plays a role of the gate electrode of the first transistor T1. The gate line **601b** extends in a direction on the gate insulating film **611** which is formed in correspondence to the first area of the semiconductor layer **603c**. The gate line **601b** extending

in correspondence to the first area of the semiconductor layer **603c** plays a role of the gate electrode of the second transistor T2.

[0124] The semiconductor layer **603b** of the first transistor T1, the semiconductor layer **603c** of the second transistor T2 and the first plate **602c** may be formed with oxide semiconductor material, and may be conductive by a plasma process or impurities addition.

[0125] Each of the semiconductor layers **603a** and **603b** includes first areas **603aa** and **603ba** where a plasma is not processed in central areas thereof, and second areas **603ab** and **603bb**, which are conductive and positioned at both sides of the first areas **603aa** and **603ba**. In addition, the first plate **602c** is also conductive.

[0126] The semiconductor layer **603c** of the second transistor T2 includes a first area where a plasma is not processed in a central area thereof, and second areas, which are conductive by a plasma process and positioned at both sides of the first area.

[0127] An interlayer dielectric film **612** including an inorganic insulating material (e.g., oxide silicon (SiO₂) or nitride silicon (SiN_x)) or an organic insulating material is formed on the the gate line **601b**, the first plate **602c** and the gate electrode **601a** of the driving transistor DT and a whole surface of the substrate **600**.

[0128] At this time, the interlayer dielectric **612** includes a first contact hole **613a** exposing the second area **603ab** of the semiconductor layer **603a** of the driving transistor DT, a fourth contact hole exposing the second area **603bb** of the first transistor T1, and a sixth contact hole **613f** exposing the first plate **602c** in a position adjacent to the first transistor T1.

[0129] It should be noted that, as illustrated in FIG. 7, the semiconductor layer **603b** of the first transistor T1, the semiconductor layer **603c** of the second transistor T2 and the first plate **602c** are integrally formed (e.g., directly connected or physically unified) in the second embodiment. Thus, in contrast to the first embodiment and the illustration of FIG. 4, where the contact holes **313b**, **313c** and **313e** that were provided in the first embodiment (see FIG. 4) in order to electrically connect the first plate **302c** with the gate electrode **301a** of the driving transistor and the first transistor T1, such contact holes are omitted in this second embodiment. Consequently, since some contact holes (such as **313b**, **313c**, and **313e** of FIG. 4) are omitted in the second embodiment, an opening ratio of a light emitting area of an organic light emitting device can be increased.

[0130] A driving voltage line **605** connected to the second area **603ab** of the oxide semiconductor layer **603a** through the first contact hole **613a** of the driving transistor DT is formed on the interlayer dielectric film **612**. A portion of the driving voltage line **605**, which is connected to the second area **603ab** of the semiconductor layer **603a** of the driving transistor DT through the first contact hole **613a** plays a role of the source electrode of the driving transistor DT.

[0131] In addition, a drain electrode **607a** of the driving transistor DT, which is connected to the second area **603bb** of the semiconductor layer **603b** of the first transistor T1 through the fourth contact hole **613d** and connected to the connection pattern CP of FIG. 6 is formed on the interlayer dielectric film **612**.

[0132] In addition, the pattern **607e** formed with source/drain electrode material is formed on the interlayer dielectric film **612**. The pattern **607e** connects the first plate **602c** with the pixel electrode **608**.

[0133] In addition, the second plate **607d** forming the storage capacitor Cst by including the portion connected to the gate electrode **601a** of the driving transistor through the contact hole in a position corresponding to the first plate **602c** and the portion playing a role of the source electrode of the second transistor **T2** is formed on the interlayer dielectric film **612**. That is, the gate electrode **601a** of the driving transistor DT is connected to the second plate **607d** through the contact hole, and the second plate **607d** is connected to the second area **603** of the semiconductor layer **903c** of the second transistor **T2** through another contact hole.

[0134] Next, a protection film **613** including an inorganic insulating material (e.g., oxide silicon (SiO₂) or nitride silicon (SiN_x)) or an organic insulating material (e.g., benzocyclobutene or photoacryl) is formed on a whole surface of the substrate **600** on which the driving transistor DT, the first transistor **T1** and the storage capacitor Cst are formed. The protection film **613** includes a source contact hole **615** exposing the pattern **607e**.

[0135] In addition, the pixel electrode **608** connected to the pattern **607e** through the source contact hole **615** and extending up to a light emitting area is formed on the protection film **613** including the source contact hole **615**. The pixel electrode **608** may be an anode electrode. The pixel electrode **608** and the pattern **607e** which are sequentially laminated in a pixel area are connected through the source contact hole **615**, and the first plate **602c** and the source electrode **607e** are connected through the source contact hole **615**. The pixel electrode **608** and the first plate **602c** form the double storage capacitor Cst together with the second plate **607d**.

[0136] Aspects of a Third Embodiment

[0137] FIG. 9A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a third embodiment. FIG. 9B is an enlarged view of a portion C in FIG. 9A, according to the third embodiment.

[0138] The third embodiment is analogous to the second embodiment except a pixel electrode **908** is formed a little larger than that of the second embodiment and some planarization film **914** is not formed between the pixel electrode **908** and a second plate **907d** and thus repetitive explanation will be omitted.

[0139] Referring to FIGS. 9A and 9B, in the organic light emitting display device, according to the third embodiment, each pixel connected to a driving voltage line DVL for providing a driving voltage EVDD and a data line DL equally to the second embodiment includes a 3T1C based scan structure in which a driving transistor DT, a first transistor **T1** and a second transistor **T2** are formed on a substrate **900**. At this time, some pixels may be connected to each of the driving voltage line DVL and a reference voltage line RVL through a connection pattern.

[0140] Next, various signal lines, such as a driving voltage line **905** and data lines **906** corresponding to each pixel row, are formed on the substrate **900**. A semiconductor layer **903a** of each driving transistor DT formed with an oxide semiconductor material, a semiconductor layer **903b** of the first transistor **T1**, a semiconductor layer **903c** of the second transistor **T2** and a first plate **902c** are formed on the substrate **900**. At this time, the semiconductor layer **903a** of the driving transistor DT, the semiconductor layer **903b** of the first transistor **T1** and the first plate **902c** are integrally formed analogously to the second embodiment.

[0141] Next, the gate electrode **901a** of each driving transistor DT, the gate line **901b** for forming the gate electrodes of the first and second transistors **T1** and **T2**, a connection pattern **902a** connected to each driving voltage line DVL, and a connection pattern **902b** connected to each reference voltage line RVL are formed, on the substrate **900** on which the semiconductor layer **903a** of each driving transistor DT, the semiconductor layer **903b** of each first transistor **T1** and the semiconductor layer **903c** of each second transistor **T2** are formed. Here, the gate line **901b** is a common gate line for commonly applying the scan signal to the gate electrodes of the first and second transistors **T1** and **T2** included in each pixel, which are connected to the gate line **901b**.

[0142] At this time, equally to the second embodiment, the first plate **902c** connects the driving transistor DT and the first transistor, is formed with an oxide semiconductor material, and is conductive.

[0143] The first plate **902c** and the second plate **907d** are formed, and an interlayer dielectric film **912** is between the first plate **902c** and the second plate **907d**. In addition, the second plate **907d** and the pixel electrode **908** are formed, and a protection film **913** is between the the second plate **907d** and the pixel electrode **908**.

[0144] A planarization film **914** is further formed between the protection film **913** and the pixel electrode **902**. However, the planarization film **914** is not formed in an area corresponding to the second plate **907d** in order to increase a capacitance of a double storage capacitor Cst. At this time, the planarization film **914** covers a portion of the second plate **907d** except for a portion of the driving transistor DT of the voltage pixel electrode **908**, and thus the capacitance of the storage capacitor can be maximized. In addition, the planarization film **914** is formed on the driving voltage line VDL too, and thus a defect between wires can be prevented.

[0145] FIG. 10 is a cross-sectional view taken along a cutting line V-V' of FIG. 9B.

[0146] Referring to FIG. 10, the semiconductor layer **903c** of the second transistor **T2** is formed on a buffer layer **910** of the substrate **900**.

[0147] The interlayer dielectric **912** includes a seventh contact hole **913h** exposing a portion of the semiconductor layer **903c** of the second transistor **T2**, and is formed on the second transistor **T2**.

[0148] The second plate **907d** is connected to the semiconductor layer **903c** of the second transistor **T2** through the seventh contact hole **913h**, and is connected to the gate electrode **901a** of the driving transistor DT through another contact hole.

[0149] In addition, the protection film **913** is formed on the substrate **900** on which the second plate **907d** is formed. The planarization film **914** is formed in a portion corresponding to the second plate **907d** on the protection film **913**. In addition, the pixel electrode **908** corresponding to the second plate **907d** is formed on the substrate **900**. The pixel electrode **908** corresponds to the second plate **907d**, and plays a role of the storage capacitor.

[0150] Thus, the organic light emitting display device according to the third embodiment includes the double storage capacitor Cst including the first plate **902c**, the second plate **907d** and the pixel electrode **908**.

[0151] At this time, the planarization film **914** is not formed on the second contact hole **913h**. Therefore, a short between the second plate **907d** and the pixel electrode **908** formed in correspondence to the seventh contact hole **913h** may occur

due to a step difference according to the seventh contact hole **913h**, and a fourth embodiment will be described as a method of enhancing this.

[0152] Aspects of a Fourth Embodiment

[0153] FIG. 11A is a plan view schematically illustrating a portion of a display panel of an organic light emitting display device according to a fourth embodiment. FIG. 11B is an enlarged view of a portion D in FIG. 11A, according to the fourth embodiment.

[0154] The fourth embodiment is substantially the same as the third embodiment except for a planarization film **1114** formed between a pixel electrode **1108** and a second plate **1107d** positioned on a seventh contact hole **1117h** of a second transistor **T2**.

[0155] Referring to aspects of the fourth embodiment (FIGS. 11A and 11B) that are analogous to the third embodiment (FIGS. 9A-9B), a 3T1C based 1 scan structure in which a driving transistor DT, a first transistor **T1** and the second transistor **T2** are formed is formed on a substrate **1100**. At this time, the driving transistor DT, the first transistor **T1** and the second transistor **T2** are connected to a driving voltage line DVL and a data line DL equally to the third embodiment. At this time, some pixels may not be directly connected to the driving voltage line DVL and a reference voltage line RVL, and may be connected to each of the driving voltage line DVL and the reference voltage line RVL through a connection pattern CP.

[0156] Next, various signal lines such as a driving voltage line **1105** and data lines **1106** corresponding to each pixel row are formed on the substrate **1100**. A semiconductor layer **1103a** of each driving transistor DT formed with an oxide semiconductor material, a semiconductor layer **1103b** of the first transistor **T1**, a semiconductor layer **1103c** of the second transistor **T2** and a first plate **1102c** are formed on the substrate **1100**. At this time, the semiconductor layer **1103a** of the driving transistor DT, the semiconductor layer **1103b** of the first transistor **T1** and the first plate **1102c** are integrally formed equally to the second embodiment.

[0157] Next, a gate electrode **1101a** of each driving transistor DT, a gate line **1101b** for forming gate electrodes of the first and second transistors **T1** and **T2**, a connection pattern **1102a** connected to each driving voltage line DVL, and a connection pattern **1102b** connected to each reference voltage line RVL are formed, on the substrate **1100** on which the semiconductor layer **1103a** of each driving transistor DT, the semiconductor layer **1103b** of each first transistor **T1** and the semiconductor layer **1103c** of each second transistor **T2** are formed. Here, the gate line **1101b** is a common gate line for commonly applying the scan signal to the gate electrodes of the first and second transistors **T1** and **T2** included in each pixel, which are connected to the gate line **1101b**.

[0158] As explained with reference to the second embodiment, the first plate **1102c** connects the driving transistor DT and the first transistor, is formed with an oxide semiconductor material, and is conductive.

[0159] The first plate **1102c** and the second plate **1107d** are formed, and an interlayer dielectric film **1112** is between the first plate **1102c** and the second plate **1107d**. In addition, the second plate **1107d** and a pixel electrode **1108** are formed, and a protection film **1113** is between the second plate **1107d** and the pixel electrode **1108**. A planarization film **1114** is further formed between the protection film **1113** and the pixel electrode **1108**. However, the planarization film **1114** is not formed in an area corresponding to the second plate **1107d**

in order to increase a capacitance of a double storage capacitor. The planarization film **1114** covers a portion of the second plate **1107d** except for a portion of the driving transistor DT of the pixel electrode **1108**, and thus a short between the second plate **1107d** and the pixel electrode **1108** can be prevented.

[0160] That is, a portion of the first plate **1102c** and a portion of the second plate **1107d** overlap, and the second plate **1107d** and a portion of the pixel electrode **1108** overlap to play a role of the storage capacitor Cst. The planarization film **1114** is not formed on the portion of the first plate **1102c**, the portion of the second plate **1107d** and the portion of the pixel electrode **1108** which are overlapped.

[0161] The second plate **1107d** is connected to the semiconductor layer **1103c** of the second transistor **T2** through a contact hole **1113h**. The planarization film **1114** is formed on the second plate **1107d** corresponding to the contact hole **1113h**. Therefore, a short between the pixel electrode **1108** and the second plate **1107d** due to a step difference according to a contact hole can be prevented.

[0162] FIG. 12 is a cross-sectional view taken along a cutting line VI-VI' of FIG. 11B.

[0163] Referring to FIG. 12, a buffer layer **1110** is formed on the substrate **1100**. The semiconductor layer **1103c** of the second transistor **T2** is formed on the buffer layer **1110**.

[0164] The interlayer dielectric film **1112** includes the seventh contact hole **1113h** exposing a portion of the semiconductor layer **1103c** of the second transistor **T2**, and is formed on the second transistor **T2**.

[0165] The second plate **1107d** is connected to the semiconductor layer **1103c** of the second transistor **T2** through the seventh contact hole **1113h**, and is connected to the gate electrode **1101a** of the driving transistor DT through another contact hole.

[0166] In addition, the protection film **1113** is formed on the substrate **1100** on which the second plate **1107d** is formed. The planarization film **1114** is formed in a portion corresponding to the second plate **1107d** on the protection film **1113**. In addition, the pixel electrode **1108** corresponding to the second plate **1107d** is formed on the substrate **1100**.

[0167] At this time, the planarization film **1114** is formed on a portion where the second transistor **1103c** and the second plate **1107d** are connected through the seventh contact hole **1113h**, and thus a short between the pixel electrode **1108** and the second plate **1107d** due to the seventh contact hole **1113h** can be prevented.

[0168] While the technical spirit of the present disclosure has been exemplarily described with reference to the accompanying drawings, it will be understood by a person skilled in the art that the present disclosure may be varied and modified in various forms without departing from the scope of the present disclosure. Accordingly, the embodiments disclosed in the present disclosure are merely to not limit but describe the technical spirit of the present disclosure. Further, the scope of the technical spirit of the present disclosure is limited by the embodiments. The scope of the present disclosure shall be construed on the basis of the accompanying claims in such a manner that all of the technical ideas included within the scope equivalent to the claims belong to the present disclosure.

What is claimed is:

1. An organic light emitting display device comprising:
 - a driving transistor including a semiconductor layer including an oxide semiconductor material, and for driving an organic light emitting diode;
 - a first transistor including a semiconductor layer including an oxide semiconductor material, controlled by a scan signal, and connected between a reference voltage line and a first node of the driving transistor;
 - a second transistor including a semiconductor layer including the oxide semiconductor material, controlled by the scan signal commonly provided from a gate line, and connected between a data line and a second node of the driving transistor;
 - a first plate including the oxide semiconductor material of which conductive characteristic is improved, and connected to the semiconductor layer of the driving transistor and the semiconductor layer of the first transistor;
 - a second plate positioned on the first plate, and connected to the semiconductor layer of the second transistor and a gate electrode of the driving transistor; and
 - a pixel electrode of the organic light emitting diode, positioned on the second plate and connected to the first plate through a contact hole.
2. The organic light emitting display device of claim 1, wherein the pixel electrode is connected to the first plate through the contact hole adjacent to the semiconductor layer of the first transistor.
3. The organic light emitting display device of claim 1, further comprising:
 - a planarization film formed on the second plate between the second plate and the pixel electrode,
 - wherein the second plate is connected to the semiconductor layer of the second transistor through a contact hole, and the planarization film is formed on the second plate corresponding to the contact hole.
4. The organic light emitting display device of claim 3, wherein a portion of the first plate overlaps a portion of the

second plate and the second plate overlaps a portion of the pixel electrode to play a role of a storage capacitor, wherein the planarization film is not formed on the overlapped portion of the first plate, the portion of the second plate, and the portion of the pixel electrode.

5. The organic light emitting display device of claim 1, wherein the conductive characteristic of the first plate is improved by exposing the oxide semiconductor material to a plasma or adding impurities to the oxide semiconductor material.

6. The organic light emitting display device of claim 1, wherein the oxide semiconductor material is zinc-oxide series material including indium.

7. The organic light emitting display device of claim 1, wherein the first transistor is a sensing transistor, which compensates a luminance deviation between pixels, and the second transistor is a switching transistor selecting the driving transistor.

8. The organic light emitting display device of claim 1, wherein the semiconductor layer of the driving transistor, the semiconductor layer of the second transistor and the first plate are simultaneously formed in the same layer, and the semiconductor layer of the driving transistor, the semiconductor layer of the second transistor and the first plate are integrally formed.

9. The organic light emitting display device of claim 1, wherein:

- a conductive characteristic of a portion of the semiconductor layer in the driving transistor is improved, the portion of the semiconductor layer in the driving transistor, of which the conductive characteristic is improved is connected to a driving voltage line,

- a conductive characteristic of a portion of the semiconductor layer in the first transistor is improved, and the portion of the semiconductor layer in the first transistor, of which the conductive characteristic is improved, is connected to a reference voltage line.

* * * * *

专利名称(译)	有机发光显示装置		
公开(公告)号	US20150137099A1	公开(公告)日	2015-05-21
申请号	US14/537740	申请日	2014-11-10
[标]申请(专利权)人(译)	乐金显示有限公司		
申请(专利权)人(译)	LG DISPLAY CO. , LTD.		
当前申请(专利权)人(译)	LG DISPLAY CO. , LTD.		
[标]发明人	CHOI HEEDONG		
发明人	CHOI, HEEDONG		
IPC分类号	H01L27/32 H01L51/52		
CPC分类号	H01L27/3248 H01L51/52 H01L27/3269 G09G3/3258 G09G2300/0465 G09G2300/0842 G09G2320/0233 H01L27/3265 H01L27/1225 H01L27/3262 H01L27/3276 H01L51/5237		
优先权	1020130138837 2013-11-15 KR		
其他公开文献	US9356081		
外部链接	Espacenet USPTO		

摘要(译)

有机发光显示装置包括用于驱动有机发光二极管的驱动晶体管;第一晶体管,由扫描信号控制,并连接在参考电压线和驱动晶体管的第一节点之间;第二晶体管,由扫描信号控制,并连接在驱动晶体管的数据线和第二节点之间;第一板,具有改善的导电特性,并连接到驱动晶体管的半导体层和第一晶体管的半导体层;第二板,位于第一板上,并连接第二晶体管的半导体层和驱动晶体管的栅极;所述有机发光二极管的像素电极位于所述第二板上,并通过接触孔与所述第一板连接。

