



US010580800B2

(12) **United States Patent**
Kim et al.

(10) **Patent No.:** **US 10,580,800 B2**
(45) **Date of Patent:** ***Mar. 3, 2020**

(54) **THIN FILM TRANSISTOR AND ORGANIC LIGHT EMITTING DIODE DISPLAY INCLUDING THE SAME**

(71) Applicant: **Samsung Display Co., Ltd.**, Yongin, Gyeonggi-Do (KR)

(72) Inventors: **Jung-Bae Kim**, Yongin (KR); **Bo-Yong Chung**, Yongin (KR); **Hai-Jung In**, Yongin (KR); **Dong-Gyu Kim**, Yongin (KR)

(73) Assignee: **SAMSUNG DISPLAY CO., LTD.**, Gyeonggi-Do (KR)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **15/791,492**

(22) Filed: **Oct. 24, 2017**

(65) **Prior Publication Data**

US 2018/0061860 A1 Mar. 1, 2018

Related U.S. Application Data

(63) Continuation of application No. 14/055,039, filed on Oct. 16, 2013, now Pat. No. 9,818,766.

(30) **Foreign Application Priority Data**

May 31, 2013 (KR) 10-2013-0062968

(51) **Int. Cl.**

H01L 27/12 (2006.01)

H01L 29/423 (2006.01)

(Continued)

(52) **U.S. Cl.**

CPC **H01L 27/124** (2013.01); **H01L 29/42384** (2013.01); **H01L 29/78645** (2013.01); **H01L 27/3262** (2013.01); **H01L 27/3265** (2013.01)

(58) **Field of Classification Search**

CPC H01L 27/124; H01L 27/3262; H01L 27/3265; H01L 29/42384; H01L 29/78645
(Continued)

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,672,888 A * 9/1997 Nakamura G02F 1/136213
257/408

7,667,287 B2 * 2/2010 You H01L 27/1214
257/439

(Continued)

FOREIGN PATENT DOCUMENTS

KR 1998-023376 A 7/1998

KR 1998-023377 A 7/1998

(Continued)


Primary Examiner — Mohammed Shamsuzzaman

(74) *Attorney, Agent, or Firm* — Cantor Colburn LLP

(57) **ABSTRACT**

A thin film transistor includes a substrate, a semiconductor layer on the substrate, a first insulating layer covering the substrate and the semiconductor layer, a first gate electrode on the first insulating layer and overlapping the semiconductor layer, a second insulating layer covering the first gate electrode and the first insulating layer, a second gate electrode on the second insulating layer and overlapping the semiconductor layer and the first gate electrode, a third insulating layer covering the second gate electrode, a first contact hole defined in the first insulating layer, the second insulating layer and the third insulating layer, and through which a portion of the semiconductor layer is exposed, and a source electrode and a drain electrode connected to the semiconductor layer through the first contact hole.

11 Claims, 6 Drawing Sheets



(51)	Int. Cl.		2005/0258423 A1* 11/2005 Kuwabara H01L 27/1214
	H01L 29/786	(2006.01)	257/66
	H01L 27/32	(2006.01)	2006/0097258 A1* 5/2006 Yamazaki H01L 29/42384
			257/59
(58)	Field of Classification Search		2007/0002195 A1* 1/2007 Cho G02F 1/136227
	USPC 257/40, 74, 66; 438/689, 222; 345/100		349/43
	See application file for complete search history.		2007/0117239 A1* 5/2007 Ishi H01L 27/1214
			438/30
(56)	References Cited		2007/0228426 A1* 10/2007 Iriguchi H01L 27/283
	U.S. PATENT DOCUMENTS		257/288
	9,318,513 B2* 4/2016 Nakano G02F 1/136209		2008/0018566 A1* 1/2008 Yamauchi H01L 27/1251
	2001/0009283 A1* 7/2001 Arao G02F 1/13454		345/76
			2008/0048189 A1* 2/2008 Yamazaki H01L 29/42384
	2002/0008240 A1 1/2002 Hirabayashi et al. 257/74		257/66
	2002/0142554 A1* 10/2002 Nakajima H01L 29/4908		2008/0062112 A1 3/2008 Umezaki 345/100
			2013/0021544 A1 1/2013 Fukuyama et al.
	2002/0145141 A1* 10/2002 Chen H01L 29/66757		
			FOREIGN PATENT DOCUMENTS
	2003/0132523 A1* 7/2003 Ohtani H01L 23/53223		KR 100186090 B1 3/1999
			KR 1020110103736 A 9/2011
	2004/0063270 A1* 4/2004 Ishikawa H01L 27/1214		TW 491985 B 6/2002
			TW 200518346 A 6/2005
	2004/0224514 A1 11/2004 Uehara et al. 438/689		WO 2011122352 A1 10/2011
	2004/0227195 A1* 11/2004 Chang H01L 29/66757		* cited by examiner
			257/408

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5





FIG. 6



THIN FILM TRANSISTOR AND ORGANIC LIGHT EMITTING DIODE DISPLAY INCLUDING THE SAME

This application is a continuation application of U.S. application Ser. No. 14/055,039 filed Oct. 16, 2013, which claims priority to Korean Patent Application No. 10-2013-0062968 filed on May 31, 2013, and all the benefits accruing therefrom under 35 U.S.C. § 119, the entire contents of which are incorporated herein by reference.

BACKGROUND

(a) Field

The invention relates to a thin film transistor and an organic light emitting diode display including the same.

(b) Description of the Related Art

An organic light emitting diode display includes two electrodes and an organic light emitting layer positioned therebetween. Electrons injected from a cathode that is one of the two electrodes and holes injected from an anode that is the other of the two electrodes are bonded to each other in the organic light emitting layer to form an exciton. Light is emitted while the exciton discharges energy.

The organic light emitting diode display includes a plurality of pixels each including an organic light emitting diode formed of the cathode, the anode and the organic light emitting layer. A plurality of thin film transistors ("TFTs") and capacitors for driving the organic light emitting diode are disposed in each pixel. The plurality of TFTs includes a switching TFT and a driving TFT.

SUMMARY

One or more exemplary embodiment provides a thin film transistor in which a leakage current is minimized, and an organic light emitting diode display including the same.

An exemplary embodiment provides a thin film transistor including a substrate. A semiconductor layer is on the substrate. A first insulating layer covers the substrate and the semiconductor layer. A first gate electrode is on the first insulating layer and overlaps the semiconductor layer. A second insulating layer covers the first gate electrode and the first insulating layer. A second gate electrode is on the second insulating layer and overlaps the semiconductor layer and the first gate electrode. A third insulating layer covers the second gate electrode. A first contact hole is defined in the first insulating layer, the second insulating layer and the third insulating layer, and exposes a portion of the semiconductor layer. A source electrode and a drain electrode are on the third insulating layer, and connected to the semiconductor layer through the first contact hole. An overall length of the second gate electrode is larger than an overall length of the first gate electrode.

The first gate electrode may be between the second gate electrode and the substrate.

The thin film transistor may further include a second contact hole defined in the second insulating layer, and through which a portion of the first gate electrode is exposed. The second gate electrode may be connected to the first gate electrode through the second contact hole.

The second gate electrode may include an overlapping second gate unit overlapping the first gate electrode, and a non-overlapping second gate unit exposed by the first gate electrode.

The semiconductor layer may include a source region in contact with the source electrode, a drain region in contact with the drain electrode, a channel region between the source region and the drain region, and a weak electric field region overlapping the non-overlapping second gate unit.

The weak electric field region may be between the source region and the channel region and between the drain region and the channel region.

The first gate electrode may include a first sub-gate electrode and a second sub-gate electrode spaced apart from each other.

Both the first sub-gate electrode and the second sub-gate electrode may be between the second gate electrode and the substrate.

The semiconductor layer may further include a central weak electric field region between the first sub-gate electrode and the second sub-gate electrode, in a plan view.

The thin film transistor may further include a third contact hole defined in the third insulating layer, and through which a portion of the second gate electrode is exposed, and a low resistance member on the third insulating layer, overlapping the second gate electrode and connected to the second gate electrode through the third contact hole.

Another exemplary embodiment provides a thin film transistor including a substrate. A semiconductor layer is on the substrate. A first insulating layer covers the substrate and the semiconductor layer. A first gate electrode is on the first insulating layer and overlaps the semiconductor layer. A second insulating layer covers the first gate electrode and the first insulating layer. A second gate electrode is on the second insulating layer and overlaps the semiconductor layer and the first gate electrode. A third insulating layer covers the second gate electrode. A first contact hole is defined in the first insulating layer, the second insulating layer and the third insulating layer, and exposes a portion of the semiconductor layer. A source electrode and a drain electrode are on the third insulating layer, and connected to the semiconductor layer through the first contact hole. The first gate electrode includes a first sub-gate electrode and a second sub-gate electrode spaced apart from each other. An overall length of the second gate electrode is smaller than an overall length of the first gate electrode.

The semiconductor layer may include a source region in contact with the source electrode, a drain region in contact with the drain electrode, a channel region between the source region and the drain region, and a central weak electric field region overlapping an interval between the first sub-gate electrode and the second sub-gate electrode, in a plan view.

The thin film transistor may further include a second contact hole defined in the second insulating layer, and through which a portion of the first gate electrode is exposed, and the second gate electrode may be connected to the first gate electrode through the second contact hole.

The thin film transistor may further include a third contact hole defined in the third insulating layer, and through which a portion of the second gate electrode is exposed, and a low resistance member on the third insulating layer, overlapping the second gate electrode and connected to the second gate electrode through the third contact hole.

Yet another exemplary embodiment provides an organic light emitting diode display including a substrate. A thin film transistor and a capacitor are on the substrate. An organic light emitting diode is connected to the thin film transistor.

The thin film transistor includes a semiconductor layer on the substrate. A first insulating layer covers the substrate and the semiconductor layer. A first gate electrode is on the first

3

insulating layer and overlaps the semiconductor layer. A second insulating layer covers the first gate electrode and the first insulating layer. A second gate electrode is on the second insulating layer and overlaps the semiconductor layer and the first gate electrode. A third insulating layer covers the second gate electrode. A first contact hole is defined in the first insulating layer, the second insulating layer and the third insulating layer, and exposes a portion of the semiconductor layer. A source electrode and a drain electrode are on the third insulating layer, and connected to the semiconductor layer through the first contact hole. An overall length of the second gate electrode is larger than an overall length of the first gate electrode.

The thin film transistor may further include a second contact hole defined in the second insulating layer, and through which a portion of the first gate electrode is exposed, and the second gate electrode may be connected to the first gate electrode through the second contact hole.

The second gate electrode may include an overlapping second gate unit overlapping the first gate electrode and a non-overlapping second gate unit exposed by the first gate electrode.

The semiconductor layer may include a source region in contact with the source electrode, a drain region in contact with the drain electrode, a channel region between the source region and the drain region, and a weak electric field region overlapping the non-overlapping second gate unit.

The weak electric field region may be between the source region and the channel region and between the drain region and the channel region.

The capacitor may include a first capacitor plate in a same layer as the first gate electrode, a second capacitor plate in a same layer as the second gate electrode, and a third capacitor plate in a same layer as the source electrode and the drain electrode. The first capacitor plate, the second capacitor plate and the third capacitor plate may overlap each other.

According to one or more exemplary embodiment, a second gate electrode includes a portion exposed by a first gate electrode, and a second gate electrode is connected to the first gate electrode through a contact hole defined in a second insulating layer. Accordingly, a weak electric field region of the semiconductor layer and overlapping the second gate electrode exhibits an effect similar to that of a lightly doped drain ("LDD") structure. Therefore, a leakage of electrical current and a hot electron effect can be reduced, and a breakdown voltage can be increased.

Further, an on-current is increased in a channel region of the thin film transistor where a strong electric field is formed. Therefore, a capacitor in a pixel of a large-area display device can be charged.

Further, the weak electric field region is included in the semiconductor layer of the organic light emitting diode display including the thin film transistor according to one or more exemplary embodiment. Therefore, the leakage of electrical current of the thin film transistor can be reduced to maintain a voltage applied to the capacitor connected to the thin film transistor, during one frame.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other features of this disclosure will become more apparent by describing in further detail exemplary embodiments thereof with reference to the accompanying drawings, in which:

FIG. 1 is a cross-sectional view of an exemplary embodiment of a thin film transistor according to the invention.

4

FIG. 2 is a cross-sectional view of an exemplary embodiment of an organic light emitting diode display including a thin film transistor according to the invention.

FIG. 3 is a cross-sectional view of another exemplary embodiment of a thin film transistor according to the invention.

FIG. 4 is a cross-sectional view of still another exemplary embodiment of a thin film transistor according to the invention.

FIG. 5 is a cross-sectional view of yet another exemplary embodiment of a thin film transistor according to the invention.

FIG. 6 is a cross-sectional view of yet another exemplary embodiment of a thin film transistor according to the invention.

DETAILED DESCRIPTION

Hereinafter, exemplary embodiments of the invention will be described in detail with reference to the accompanying drawings so that those skilled in the art may easily practice the invention. As those skilled in the art would realize, the described embodiments may be modified in various different ways, all without departing from the spirit or scope of the invention.

In addition, in various exemplary embodiments, the same reference numerals are used with respect to the constituent elements having the same constitution and illustrated in one exemplary embodiment, and in an alternative exemplary embodiment, only elements that are different from the one exemplary embodiment are illustrated.

In describing the disclosure, parts that are not related to the description will be omitted. Like reference numerals generally designate like elements throughout the specification.

In addition, the size and thickness of each element shown in the drawings are arbitrarily shown for understanding and ease of description, but the invention is not limited thereto. As used herein, the term "and/or" includes any and all combinations of one or more of the associated listed items.

In the drawings, the thickness of layers, films, panels, regions, etc., are exaggerated for clarity. In the drawings, for understanding and ease of description, the thicknesses of some layers and areas are exaggerated. It will be understood that when an element such as a layer, film, region, or substrate is referred to as being "on" another element, it can be directly on the other element or intervening elements may also be present.

It will be understood that, although the terms first, second, third, etc., may be used herein to describe various elements, components, regions, layers and/or sections, these elements, components, regions, layers and/or sections should not be limited by these terms. These terms are only used to distinguish one element, component, region, layer or section from another element, component, region, layer or section. Thus, a first element, component, region, layer or section discussed below could be termed a second element, component, region, layer or section without departing from the teachings of the invention.

The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting of the invention. As used herein, the singular forms "a," "an" and "the" are intended to include the plural forms as well, unless the context clearly indicates otherwise. It will be further understood that the terms "comprises," "comprising," "includes" and/or "including," when used in this specification, specify the presence of stated features, inte-

gers, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, integers, steps, operations, elements, components, and/or groups thereof.

Embodiments of the invention are described herein with reference to cross-section illustrations that are schematic illustrations of idealized embodiments (and intermediate structures) of the invention. As such, variations from the shapes of the illustrations as a result, for example, of manufacturing techniques and/or tolerances, are to be expected. Thus, embodiments of the invention should not be construed as limited to the particular shapes of regions illustrated herein but are to include deviations in shapes that result, for example, from manufacturing.

Unless otherwise defined, all terms (including technical and scientific terms) used herein have the same meaning as commonly understood by one of ordinary skill in the art to which this invention belongs. It will be further understood that terms, such as those defined in commonly used dictionaries, should be interpreted as having a meaning that is consistent with their meaning in the context of the relevant art and will not be interpreted in an idealized or overly formal sense unless expressly so defined herein.

When the organic light emitting diode display is driven, when leakage of electrical current is leaked associated with a capacitor connected to the switching thin film transistor ("TFT"), a size of the capacitor is increased to increase a capacity of the capacitor or a frame frequency is increased to reduce a time of one frame in order to maintain a constant voltage during the time of one frame. Thereby, a change in voltage due to the leakage current is relieved.

However, when the capacity of the capacitor is increased in order to maintain the constant voltage during the time of one frame, the increased capacity acts as a load during charging or discharging of the capacitor. Accordingly, it is difficult to ensure charging and discharging times, and an aperture ratio of the pixel is reduced. Further, when the frame frequency is increased in order to maintain the constant voltage during the time of one frame, input of data within a predetermined time due to a load connected to a data line and a scan line may be difficult.

As shown in a transfer curve of a typical P-type TFT, when a gate voltage (V_{GS}) is increased as a positive number, the leakage current is increased. When a drain voltage (V_{DS}) is increased as a negative number, the leakage current is further increased. Accordingly, in the switching TFT disposed in the pixel of the organic light emitting diode display, when the gate voltage V_{GS} is increased as the positive number and the switching TFT is in an off state, the drain voltage (V_{DS}) is increased as the negative number. Therefore, the leakage current is increased in a condition where a large voltage is applied, and thus a change in voltage applied to the capacitor is intensified.

In order to reduce the leakage current, a lightly doped drain ("LDD") structure where a lightly doped region (n-) is interposed between opposing highly doped source and drain regions (n+), and a channel is applied to the TFT of the organic light emitting diode display. In a process of providing a top gate type TFT, the LDD structure includes a gate electrode formed according to a self alignment method. The LDD structure provided in the top gate type TFT reduces the leakage current and a hot electron effect, and increases a breakdown voltage.

However, when the LDD structure is provided, an electrical on-current (I_{on}) is reduced and costs are increased due to use of an additional mask.

The top gate type TFT typically includes a semiconductor layer including polysilicon, a gate insulating layer covering the semiconductor layer, a gate electrode disposed on the gate insulating layer and partially overlapping the semiconductor layer, an interlayer insulating layer covering the gate electrode and the gate insulating layer, and source and drain electrodes connected to the semiconductor layer exposed through a contact hole defined in the interlayer insulating layer and the gate insulating layer. In the top gate TFT, when a cross-sectional thickness of the gate insulating layer is increased, an electric field respectively between the gate electrode, and the source and drain electrodes may be reduced to reduce the leakage current. However, the on-current may be reduced due to an increase in resistance, and thus a capacitor in a pixel of a large-area display device may not be charged.

Hereinafter, the invention will be described in detail with reference to the accompanying drawings.

Then, a TFT according to the invention will be described in detail with reference to FIG. 1.

FIG. 1 is a cross-sectional view of an exemplary embodiment of a TFT according to the invention.

As shown in FIG. 1, in the TFT, a semiconductor layer **130** is disposed on a substrate **110** including transparent glass or plastic. The semiconductor layer **130** may include a polysilicon (poly-Si) or oxide semiconductor. The oxide semiconductor may include an oxide including titanium (Ti), hafnium (Hf), zirconium (Zr), aluminum (Al), tantalum (Ta), germanium (Ge), zinc (Zn), gallium (Ga), tin (Sn), or indium (In) as a basis, and complex oxides thereof, such as zinc oxide ("ZnO"), indium-gallium-zinc oxide ("In-Ga-Zn-O"), indium-zinc oxide ("Zn-In-O"), zinc-tin oxide ("Zn-Sn-O"), indium-gallium oxide ("In-Ga-O"), indium-tin oxide ("In-Sn-O"), indium-zirconium oxide ("In-Zr-O"), indium-zirconium-zinc oxide ("In-Zr-Zn-O"), indium-zirconium-tin oxide ("In-Zr-Sn-O"), indium-zirconium-gallium oxide ("In-Zr-Ga-O"), indium-aluminum oxide ("In-Al-O"), indium-zinc-aluminum oxide ("In-Zn-Al-O"), indium-tin-aluminum oxide ("In-Sn-Al-O"), indium-aluminum-gallium oxide ("In-Al-Ga-O"), indium-tantalum oxide ("In-Ta-O"), indium-tantalum-zinc oxide ("In-Ta-Zn-O"), indium-tantalum-tin oxide ("In-Ta-Sn-O"), indium-tantalum-gallium oxide ("In-Ta-Ga-O"), indium-germanium oxide ("In-Ge-O"), indium-germanium-zinc oxide ("In-Ge-Zn-O"), indium-germanium-tin oxide ("In-Ge-Sn-O"), indium-germanium-gallium oxide ("In-Ge-Ga-O"), titanium-indium-zinc oxide ("Ti-In-Zn-O"), and hafnium-indium-zinc oxide ("Hf-In-Zn-O"). When the semiconductor layer **130** includes the oxide semiconductor, a separate protective layer (not shown) may be added to protect the oxide semiconductor that is weak to an external environment such as high temperatures.

The semiconductor layer **130** includes a source region **131**, a drain region **132**, a channel region **133** positioned between the source region **131** and the drain region **132**, and weak electric field regions **134** and **135** positioned between the source region **131** and the channel region **133** and between the drain region **132** and the channel region **133**.

The weak electric field regions **134** and **135** respectively separate the source region **131** and the channel region **133**, and the drain region **132** and the channel region **133**. As described above, the weak electric field regions **134** and **135** are disposed between the source region **131** and the channel region **133** and between the drain region **132** and the channel region **133**. Accordingly, when the TFT is in an off-state, an electron movement path in the semiconductor layer **130** may

be blocked to reduce or effectively prevent a leakage of electrical current from occurring.

A first insulating layer **141** including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the substrate **110** and the semiconductor layer **130**. A first gate electrode **125** is disposed on the first insulating layer **141**. The first gate electrode **125** is positioned to overlap the channel region **133**. The first gate electrode **125** is connected to a gate line (not shown) transmitting a gate signal.

A second insulating layer **142** including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the first gate electrode **125** and the first insulating layer **141**. The second insulating layer **142** covers the first gate electrode **125** to insulate the first gate electrode **125** from other elements of the TFT.

A second gate electrode **126** is disposed on the second insulating layer **142**. The second gate electrode **126** is positioned to overlap the first gate electrode **125** in a plan view. An overall length L2 of the second gate electrode **126** may be larger than an overall length L1 of the first gate electrode **125**. The first gate electrode **125** is disposed in an internal side of the second gate electrode **126**, where the internal side refers to a side closer to the substrate **110**. The second gate electrode **126** includes an overlapping second gate unit **126a** overlapping the first gate electrode **125** in the plan view, and a non-overlapping second gate unit **126b** not overlapping (e.g., exposed by) the first gate electrode **125** in the plan view. The weak electric field regions **134** and **135** of the semiconductor layer **130** are disposed at a position corresponding to a plurality of non-overlapping second gate units **126b**, respectively. A contact hole **43** is defined in the second insulating layer **142** and exposes the first gate electrode **125**. The second gate electrode **126** is physically and/or electrically connected to the first gate electrode **125** through the contact hole **43**, which extends completely through a cross-sectional thickness of the second insulating layer **142** and exposes the first gate electrode **125**.

Accordingly, when a scan signal is applied to the first gate electrode **125** and the second gate electrode **126**, only the first insulating layer **141** is disposed between the channel region **133** of the semiconductor layer **130**, and the first gate electrode **125** which overlaps both the overlapping second gate unit **126a** of the second gate electrode **126** and the channel region **133**. Therefore, a relatively strong electric field is formed between the first gate electrode **125** and the channel region **133** of the semiconductor layer **130**. The first insulating layer **141** and the second insulating layer **142** are disposed between the non-overlapping second gate unit **126b** of the second gate electrode **126**, and the weak electric field regions **134** and **135** of the semiconductor layer **130**. Therefore, a relatively weak electric field is formed between the non-overlapping second gate unit **126b** of the second gate electrode **126**, and the weak electric field regions **134** and **135** of the semiconductor layer **130**.

As described above, the weak electric field regions **134** and **135** exhibit an effect similar to that of an LDD structure. Accordingly, when the TFT is in an off-state, an electron movement path of the semiconductor layer **130** is blocked to reduce or effectively prevent a leakage of electrical current and a hot electron effect, and increase a breakdown voltage. Further, an on-current is increased in the channel region **133** of the TFT where the strong electric field is formed. Therefore, a capacitor in a pixel of a large-area display device can be effectively charged.

As described above, the second gate electrode **126** having a portion not overlapping (e.g., exposed by) the first gate electrode **125** is disposed in the TFT, and the second gate

electrode **126** is connected to the first gate electrode **125** through the contact hole **43** extended through the second insulating layer **142**. Accordingly, the weak electric field regions **134** and **135** may be disposed in the semiconductor layer **130** to exhibit the effect similar to that of the LDD structure, thus reducing the leakage current and the hot electron effect, and increasing the breakdown voltage.

A third insulating layer **143** including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the second gate electrode **126** and the second insulating layer **142**. The third insulating layer **143** covers the second gate electrode **126** to insulate the second gate electrode **126** from other elements of the TFT.

A source electrode **176** and a drain electrode **177** are disposed the third insulating layer **143**. Contact holes **41** and **42** are defined in the first insulating layer **141**, the second insulating layer **142**, and the third insulating layer **143**. The source electrode **176** and the drain electrode **177** are connected to the source region **131** and the drain region **132** of the semiconductor layer **130**, through the contact holes **41** and **42** which are extended completely through cross-sectional thicknesses of each of the first insulating layer **141**, the second insulating layer **142** and the third insulating layer **143**, through which the source region **131** and the drain region **132** of the semiconductor layer **130** are exposed, respectively.

An organic light emitting diode display including a TFT according to the invention will be described below in detail with reference to FIG. 2.

FIG. 2 is a cross-sectional view of an exemplary embodiment of an organic light emitting diode display including a TFT according to the invention.

As shown in FIG. 2, the first gate electrode **125** and a first capacitor plate **25** are disposed on the first insulating layer **141** of the TFT shown in FIG. 1, but the invention is not limited thereto. The first gate electrode **125** and the first capacitor plate **25** may be in and/or on a same layer of the organic light emitting diode display. The second insulating layer **142** is disposed on the first gate electrode **125**, the first capacitor plate **25** and the first insulating layer **141**. The second gate electrode **126** and a second capacitor plate **26** are disposed on the second insulating layer **142**. The second gate electrode **126** and the second capacitor plate **26** may be in and/or on a same layer of the organic light emitting diode display. The third insulating layer **143** is disposed on the second gate electrode **126**, the second capacitor plate **26** and the second insulating layer **142**. The source electrode **176**, the drain electrode **177** and a third capacitor plate **27** are disposed on the third insulating layer **143**. The source electrode **176**, the drain electrode **177** and the third capacitor plate **27** may be in and/or on a same layer of the organic light emitting diode display. The first capacitor plate **25**, the second capacitor plate **26** and the third capacitor plate **27** overlap each other to collectively form a capacitor Cst.

As described above, the organic light emitting diode display includes the capacitor Cst including the second capacitor plate **26** disposed in and/or on the same layer as the second gate electrode **126**. Accordingly, a capacity of the capacitor Cst may be increased to maintain a voltage applied to the capacitor Cst during one frame.

A protective layer **180** is disposed on the source electrode **176**, the drain electrode **177**, the third capacitor plate **27** and the third insulating layer **143**. A contact hole **81** is defined in the protective layer **180**. A pixel electrode **710** is disposed on the protective layer **180**. The pixel electrode **710** is physically and/or electrically connected to the drain electrode **177** through the contact hole **81** disposed extended completely

through the protective layer 180 to become an anode of an organic light emitting diode 70.

A pixel defining layer 350 is disposed on the protective layer 180 and an edge of the pixel electrode 710. A pixel opening 351 is defined in the pixel defining layer 350 and exposes the pixel electrode 710 therethrough. The pixel defining layer 350 may include resins such as polyacrylates or polyimides, and/or silica-based inorganic materials.

An organic light emitting layer 720 is disposed in the pixel opening 351 of the pixel defining layer 350. The organic light emitting layer 720 may be a monolayer, or a multi-layer structure. In one exemplary embodiment, for example, the organic light emitting layer 720 includes one or more of a light emitting layer, a hole injection layer ("HIL"), a hole transport layer ("HTL"), an electron transport layer ("ETL") and an electron injection layer ("EIL"). When the organic light emitting layer 720 includes all of the aforementioned layers, the HIL may be positioned on the pixel electrode 710 that functions as the anode of the organic light emitting diode 70. The HTL, the light emitting layer, the ETL and the EIL may be sequentially laminated thereon.

A common electrode 730 is disposed on the pixel defining layer 350 and the organic light emitting layer 720. The common electrode 730 may be a monolayer, or a multi-layer structure including a reflective layer including a reflective material or a semi-penetration layer. The common electrode 730 becomes a cathode of the organic light emitting diode 70. The pixel electrode 710, the organic light emitting layer 720 and the common electrode 730 collectively form the organic light emitting diode 70.

Only the second gate electrode connected to the first gate electrode is included the exemplary embodiment shown in FIG. 1. However, a further exemplary embodiment is feasible, in which a low resistance member connected to the second gate electrode is disposed at a position overlapping the second gate electrode on the third insulating layer.

Hereinafter, another exemplary embodiment of a TFT according to the invention will be described in detail with reference to FIG. 3.

FIG. 3 is a cross-sectional view of another exemplary embodiment of a TFT according to the invention.

The exemplary embodiment in FIG. 3 is substantially the same as the exemplary embodiment shown in FIG. 1, except that a low resistance member is further included. Accordingly, a repeated description thereof will be omitted.

As shown in FIG. 3, the third insulating layer 143 is disposed on the second gate electrode 126 and the second insulating layer 142 of the TFT. The third insulating layer 143 covers the second gate electrode 126 to insulate the second gate electrode 126.

The source electrode 176, the drain electrode 177 and a low resistance member 175 are disposed on the third insulating layer 143. The source electrode 176 and the drain electrode 177 are connected to the source region 131 and the drain region 132 of the semiconductor layer 130 through the contact holes 41 and 42 disposed extended through the first insulating layer 141, the second insulating layer 142 and the third insulating layer 143 and through which the source region 131 and the drain region 132 of the semiconductor layer 130 are exposed, respectively. In addition, the low resistance member 175 is disposed at a position overlapping the second gate electrode 126. A contact hole 44 is defined in the third insulating layer 143. The low resistance member 175 is physically and/or electrically connected to the second gate electrode 126 through the contact hole 44 disposed extended completely through a cross-sectional thickness of the third insulating layer 143.

Accordingly, the low resistance member 175, the second gate electrode 126 and the first gate electrode 125 may be connected to each other to reduce electrical resistance of the first gate electrode 125, thus preventing a resistive-capacitive ("RC") delay.

A further exemplary embodiment is feasible, in which the first gate electrode is divided into a first sub-gate electrode and a second sub-gate electrode spaced apart from each other.

Hereinafter, still another exemplary embodiment of a TFT according to the invention will be described in detail with reference to FIG. 4.

FIG. 4 is a cross-sectional view of still another exemplary embodiment of a TFT according to the invention.

The exemplary embodiment in FIG. 4 is substantially the same as the exemplary embodiment shown in FIG. 1, except that structures of the first gate electrodes are different. Accordingly, a repeated description thereof will be omitted.

As shown in FIG. 4, the semiconductor layer 130 of the TFT includes the source region 131, the drain region 132, the channel region 133 positioned between the source region 131 and the drain region 132, the weak electric field regions 134 and 135 positioned between the source region 131 and the channel region 133 and between the drain region 132 and the channel region 133, and a central weak electric field region 136 disposed at the center of opposing portions of the channel region 133.

The weak electric field regions 134 and 135 separate the source region 131 and the channel region 133, and the drain region 132 and the channel region 133, respectively. Reference numeral 133 may indicate an overall channel region or may indicate individual portions of an overall channel region. The central weak electric field region 136 divides the overall channel region 133 into two parts. As described above, the weak electric field regions 134 and 135 are disposed between the source region 131 and the channel region 133 and between the drain region 132 and the channel region 133, and the central weak electric field region 136 is disposed at the center of the overall channel region 133. Accordingly, when the TFT is in an off-state, an electron movement path in the semiconductor layer 130 may be blocked to further effectively prevent a leakage current from occurring.

The first insulating layer 141 including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the substrate 110 and the semiconductor layer 130. The first gate electrode 125 is disposed on the first insulating layer 141. The first gate electrode 125 includes a first sub-gate electrode 125a and a second sub-gate electrode 125b spaced apart from each other and electrically connected to each other. FIG. 4 does not show a connection portion between the first sub-gate electrode 125a and the second sub-gate electrode 125b, which electrically connects the first sub-gate electrode 125a and the second sub-gate electrode 125b. However, the first sub-gate electrode 125a and the second sub-gate electrode 125b are physically and/or electrically connected to each other.

The first sub-gate electrode 125a and the second sub-gate electrode 125b are positioned to overlap the individual channel regions 133, respectively. The central weak electric field region 136 is positioned corresponding to an interval between the first sub-gate electrode 125a and the second sub-gate electrode 125b in the plan view.

The second insulating layer 142 including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the first gate electrode 125 and the first insulating layer 141. The second insulating layer 142 covers the first sub-gate electrode 125a

and the second sub-gate electrode **125b** to insulate the first sub-gate electrode **125a** and the second sub-gate electrode **125b**.

The second gate electrode **126** is disposed on the second insulating layer **142**. The second gate electrode **126** is positioned to overlap both the first sub-gate electrode **125a** and the second sub-gate electrode **125b**. The overall length **L2** of the second gate electrode **126** may be larger than the overall length **L1** of the first gate electrode **125**. Both the first sub-gate electrode **125a** and the second sub-gate electrode **125b** are disposed at the internal side of the second gate electrode **126**. The second gate electrode **126** includes overlapping second gate units **126a** overlapping the first sub-gate electrode **125a** and the second sub-gate electrode **125b**, and non-overlapping second gate units **126b** not overlapping (e.g., exposed by) the first sub-gate electrode **125a** and the second sub-gate electrode **125b**. The weak electric field regions **134** and **135** and the central weak electric field region **136** of the semiconductor layer **130** are disposed at positions corresponding to the non-overlapping second gate units **126b**. The second gate electrode **126** is connected to the first sub-gate electrode **125a** and the second sub-gate electrode **125b** through the contact hole **43** disposed extended through the second insulating layer **142**.

Accordingly, when a scan signal is applied to the first gate electrode **125** and the second gate electrode **126**, only the first insulating layer **141** is disposed between the first sub-gate electrode **125a** connected to overlap the overlapping second gate unit **126a** and the second sub-gate electrode **125b**, and the channel regions **133**. Therefore, a strong electric field is formed between the first sub-gate electrode **125a** and the second sub-gate electrode **125b**, and the channel region **133**, respectively. The first insulating layer **141** and the second insulating layer **142** are disposed between the non-overlapping second gate units **126b**, and the weak electric field regions **134** and **135** and the central weak electric field region **136**. Therefore, a weak electric field is formed between the non-overlapping second gate units **126b**, and the weak electric field regions **134** and **135** and the central weak electric field region **136**.

As described above, when the TFT is in an off-state, the weak electric field regions **134** and **135** and the central weak electric field region **136** block an electron movement path of the semiconductor layer **130** to further reduce a leakage of an electrical current and a hot electron effect, and increase a breakdown voltage.

The overall length **L2** of the second gate electrode **126** is larger than the overall length **L1** of the first gate electrode **125** in the exemplary embodiment of FIG. 4. However, a further exemplary embodiment is feasible, in which the overall length of the second gate electrode is smaller than the overall length of the first gate electrode.

Hereinafter, yet another exemplary embodiment of a TFT according to the invention will be described in detail with reference to FIG. 5.

FIG. 5 is a cross-sectional view of yet another exemplary embodiment of a TFT according to the invention.

The exemplary embodiment in FIG. 5 is substantially the same as the exemplary embodiment shown in FIG. 4, except that the overall length of the second gate electrode is smaller than the overall length of the first gate electrode. Accordingly, a repeated description thereof will be omitted.

As shown in FIG. 5, the semiconductor layer **130** of the TFT includes the source region **131**, the drain region **132**, the channel region **133** positioned between the source region **131** and the drain region **132**, and the central weak electric field region **136** disposed at the center of the overall channel

region **133**. The central weak electric field region **136** divides the overall channel region **133** into two individual parts. As described above, the central weak electric field region **136** is disposed at the center of the channel region **133**. Accordingly, when the TFT is in an off-state, an electron movement path in the semiconductor layer **130** may be blocked to reduce or effectively prevent a leakage of electrical current from occurring.

The first insulating layer **141** including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the substrate **110** and the semiconductor layer **130**. The first gate electrode **125** is disposed on the first insulating layer **141**. The first gate electrode **125** includes the first sub-gate electrode **125a** and the second sub-gate electrode **125b** spaced apart from each other and electrically connected to each other. FIG. 5 does not show a connection portion between the first sub-gate electrode **125a** and the second sub-gate electrode **125b** for an electrical connection therebetween. However, the first sub-gate electrode **125a** and the second sub-gate electrode **125b** are physically and/or electrically connected to each other.

The first sub-gate electrode **125a** and the second sub-gate electrode **125b** are positioned to overlap the individual channel regions **133** of the overall channel region. The central weak electric field region **136** is positioned corresponding to an interval between the first sub-gate electrode **125a** and the second sub-gate electrode **125b**.

The second insulating layer **142** including silicon nitride (SiNx) or silicon oxide (SiOx) is disposed on the first gate electrode **125** and the first insulating layer **141**. The second insulating layer **142** covers the first sub-gate electrode **125a** and the second sub-gate electrode **125b** to insulate the first sub-gate electrode **125a** and the second sub-gate electrode **125b**.

The second gate electrode **126** is disposed on the second insulating layer **142**. The second gate electrode **126** is positioned to overlap the first sub-gate electrode **125a** and the second sub-gate electrode **125b**. The overall length **L2** of the second gate electrode **126** may be smaller than the overall length **L1** of the first gate electrode **125**. A portion of the first sub-gate electrode **125a** and the second sub-gate electrode **125b** is disposed at a position corresponding to an outside of the second gate electrode **126**, such that the second gate electrode **126** exposes portions of the first sub-gate electrode **125a** and the second sub-gate electrode **125b**. The second gate electrode **126** includes overlapping second gate units **126a** overlapping the first sub-gate electrode **125a** and the second sub-gate electrode **125b**, and the non-overlapping second gate unit **126b** not overlapping (e.g., exposed by) the first sub-gate electrode **125a** and the second sub-gate electrode **125b**. The central weak electric field region **136** of the semiconductor layer **130** is disposed at a position corresponding to the non-overlapping second gate unit **126b**. The second gate electrode **126** is connected to the first sub-gate electrode **125a** and the second sub-gate electrode **125b** through the contact hole **43** disposed extended through the second insulating layer **142**.

Accordingly, when a scan signal is applied to the first gate electrode **125** and the second gate electrode **126**, only the first insulating layer **141** is disposed between the first sub-gate electrode **125a** connected to overlap the overlapping second gate unit **126a** and the second sub-gate electrode **125b**, and the channel region **133**. Therefore, a strong electric field is formed between the first sub-gate electrode **125a** and the second sub-gate electrode **125b**, and the channel region **133**. The first insulating layer **141** and the second insulating layer **142** are disposed between the non-

13

overlapping second gate unit **126b** and the central weak electric field region **136**. Therefore, a weak electric field is formed between the non-overlapping second gate unit **126b** and the central weak electric field region **136**.

As described above, when the TFT is in an off-state, the central weak electric field region **136** blocks an electron movement path of the semiconductor layer **130** to further reduce a leakage of electrical current and a hot electron effect, and increase a breakdown voltage.

Only the second gate electrode connected to the first gate electrode is included in the exemplary embodiment shown in FIG. 5. However, a further exemplary embodiment is feasible, in which the low resistance member connected to the second gate electrode is disposed on the third insulating layer.

Hereinafter, yet another exemplary embodiment of a TFT according to the invention will be described in detail with reference to FIG. 6.

FIG. 6 is a cross-sectional view of yet another exemplary embodiment of a TFT according to the invention.

The exemplary embodiment of FIG. 6 is substantially the same as the exemplary embodiment shown in FIG. 5, except that the low resistance member is further included. Accordingly, a repeated description thereof will be omitted.

As shown in FIG. 6, the third insulating layer **143** is disposed on the second gate electrode **126** and the second insulating layer **142** of the TFT. The third insulating layer **143** covers the second gate electrode **126** to insulate the second gate electrode **126**.

The source electrode **176**, the drain electrode **177** and the low resistance member **175** are disposed on the third insulating layer **143**. The source electrode **176** and the drain electrode **177** are connected to the source region **131** and the drain region **132** of the semiconductor layer **130** through the contact holes **41** and **42** disposed extended through the first insulating layer **141**, the second insulating layer **142** and the third insulating layer **143**, and through which the source region **131** and the drain region **132** of the semiconductor layer **130** are exposed, respectively. In addition, the low resistance member **175** is disposed at a position overlapping the second gate electrode **126**. The low resistance member **175** is connected to the second gate electrode **126** through the contact hole **44** disposed extended through the third insulating layer **143**.

Accordingly, the low resistance member **175**, the second gate electrode **126** and the first gate electrode **125** may be connected to each other to reduce resistance of the first gate electrode **125**, thus preventing an RC delay.

While the invention has been described in connection with what is presently considered to be practical exemplary embodiments, it is to be understood that the invention is not limited to the disclosed exemplary embodiments, but, on the contrary, is intended to cover various modifications and equivalent arrangements included within the spirit and scope of the appended claims.

What is claimed is:

1. A thin film transistor comprising:

a substrate;

a semiconductor layer on the substrate;

a gate electrode overlapping the semiconductor layer while being insulated from the semiconductor layer;

a conductor layer comprising:

a source electrode and a drain electrode spaced apart from each other along a first direction, each of the source electrode and the drain electrode connected to the semiconductor layer while being insulated from the gate electrode, and

14

a first conductor electrically connected with the gate electrode and spaced apart from the source and drain electrodes along the first direction, while being insulated from the source and drain electrodes, and

a second conductor between the gate electrode and the first conductor, and connecting the gate electrode and the first conductor to each other; and

a first insulating layer respectively between the second conductor, and each of the source electrode, the drain electrode and the first conductor,

wherein along the first direction, a length of the first conductor and a length of the second conductor are both larger than a length of the gate electrode.

2. The thin film transistor of claim 1, wherein the first insulating layer extends from the conductor layer to be overlapped by each of the source electrode and the drain electrode.

3. The thin film transistor of claim 1, wherein the second conductor comprises an overlapping portion which overlaps the gate electrode and a non-overlapping portion which does not overlap the gate electrode.

4. The thin film transistor of claim 3, wherein the semiconductor layer comprises:

a source region which contacts the source electrode;

a drain region which contacts the drain electrode;

a channel region which is provided between the source region and the drain region; and

a weak electric field region which is disposed corresponding to the non-overlapping portion of the second conductor.

5. The thin film transistor of claim 4, wherein within the semiconductor layer, the weak electric field region is disposed between the source region and the channel region and between the drain region and the channel region.

6. The thin film transistor of claim 5, wherein

the source region in contact with the source electrode is disposed non-overlapping with both the overlapping portion and the non-overlapping portion of the second conductor,

the drain region in contact with the drain electrode is disposed non-overlapping with both the overlapping portion and the non-overlapping portion of the second conductor, and

the weak electric field region disposed corresponding to the non-overlapping portion of the second conductor extends from the channel region to an outer edge of the non-overlapping portion of the second conductor.

7. The thin film transistor of claim 1, wherein the first insulating layer defines a first contact hole at which the first conductor and the second conductor are connected to each other, the first insulating layer extending from the first contact hole to be overlapped by each of the source electrode and the drain electrode.

8. The thin film transistor of claim 7, further comprising a second insulating layer defining a second contact hole at which the second conductor and the gate electrode are connected to each other, the second insulating layer extending from the second contact hole to be overlapped by each of the source electrode and the drain electrode.

9. An organic light emitting diode display comprising:

the thin film transistor of claim 1;

a capacitor; and

an organic light emitting diode connected to the thin film transistor.

10. The thin film transistor of claim 1, wherein disposed along a thickness direction of the substrate are disposed

15

overlapping each other, in order: the gate electrode, the second conductor, the first insulating layer and the first conductor.

11. The thin film transistor of claim **1**, wherein a portion of the second conductor connecting the gate electrode to the first conductor, extends through a thickness of the first insulating layer to meet the first conductor within the first insulating layer.

* * * * *

16

专利名称(译)	薄膜晶体管和包括该薄膜晶体管的有机发光二极管显示器		
公开(公告)号	US10580800	公开(公告)日	2020-03-03
申请号	US15/791492	申请日	2017-10-24
[标]申请(专利权)人(译)	三星显示有限公司		
申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
当前申请(专利权)人(译)	三星DISPLAY CO. , LTD.		
[标]发明人	KIM JUNG BAE CHUNG BO YONG IN HAI JUNG KIM DONG GYU		
发明人	KIM, JUNG-BAE CHUNG, BO-YONG IN, HAI-JUNG KIM, DONG-GYU		
IPC分类号	H01L27/12 H01L29/423 H01L29/786 H01L27/32		
CPC分类号	H01L29/78645 H01L29/42384 H01L27/124 H01L27/3262 H01L27/3265 H01L27/1214 H01L27/1225 H01L27/1255		
代理机构(译)	康托科尔伯恩LLP		
优先权	1020130062968 2013-05-31 KR		
其他公开文献	US20180061860A1		
外部链接	Espacenet		

摘要(译)

薄膜晶体管包括：衬底；在衬底上的半导体层；覆盖衬底和半导体层的第一绝缘层；在第一绝缘层上并与半导体层重叠的第一栅电极；覆盖第一栅的第二绝缘层 电极和第一绝缘层，在第二绝缘层上并与半导体层和第一栅电极重叠的第二栅电极，覆盖第二栅电极的第三绝缘层，在第一绝缘层中限定的第一接触孔，绝缘层和第三绝缘层，通过其暴露一部分半导体层，以及通过第一接触孔连接到半导体层的源电极和漏电极。

