



US008536778B2

(12) **United States Patent**
Heo et al.

(10) **Patent No.:** **US 8,536,778 B2**
(45) **Date of Patent:** **Sep. 17, 2013**

(54) **DUAL PANEL TYPE ORGANIC
ELECTROLUMINESCENT DISPLAY DEVICE
AND METHOD OF FABRICATING THE SAME**

(75) Inventors: **Jung-Soo Heo**, Gyeongbuk (KR);
Jae-Hee Park, Daegu (KR); **Sang-Ho
Yu**, Seongnam-si (KR); **Kyung-Min
Park**, Gumi-si (KR); **Sung-Hoon Choi**,
Bucheon-si (KR); **Seok-Jong Lee**,
Gumi-si (KR)

(73) Assignee: **LG Display Co., Ltd.**, Seoul (KR)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 111 days.

(21) Appl. No.: **13/040,936**

(22) Filed: **Mar. 4, 2011**

(65) **Prior Publication Data**

US 2011/0156573 A1 Jun. 30, 2011

Related U.S. Application Data

(62) Division of application No. 11/639,310, filed on Dec.
15, 2006, now Pat. No. 7,923,916.

(30) **Foreign Application Priority Data**

Jun. 30, 2006 (KR) 10-2006-0060861

(51) **Int. Cl.**
H01L 51/52 (2006.01)

(52) **U.S. Cl.**
USPC **313/504**; 445/25; 313/506

(58) **Field of Classification Search**
USPC 313/504, 506; 445/24
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

6,046,543 A	4/2000	Bulovic et al.
6,366,017 B1	4/2002	Antoniadis et al.
6,876,406 B2	4/2005	Hwang
6,917,159 B2 *	7/2005	Tyan et al. 313/506
2002/0051894 A1 *	5/2002	Yoshikawa 428/690
2003/0052597 A1	3/2003	Sakurai
2003/0116772 A1	6/2003	Yamazaki et al.
2003/0127650 A1	7/2003	Park et al.
2003/0173564 A1 *	9/2003	Ko et al. 257/40
2003/0193284 A1 *	10/2003	Park et al. 313/504
2005/0051770 A1	3/2005	Ando et al.
2005/0110016 A1	5/2005	Yamazaki
2005/0140285 A1	6/2005	Park et al.
2005/0236956 A1	10/2005	Chung et al.
2006/0035015 A1	2/2006	Raychaudhuri et al.
2006/0102910 A1	5/2006	Yamazaki et al.

FOREIGN PATENT DOCUMENTS

CN	1623117 A	6/2005
DE	10 2004 031 109 A1	4/2006
JP	2004-048036 A	2/2004
JP	WO 2005-175248 A	6/2005
JP	2006-156369 A	6/2006
TW	200536434	11/2005
WO	2005/024956 A1	3/2005

* cited by examiner


Primary Examiner — Mary Ellen Bowman

(74) *Attorney, Agent, or Firm* — Birch, Stewart, Kolasch &
Birch, LLP

(57) **ABSTRACT**

An organic electroluminescent device including a switching
element and a driving element connected to the switching
element on a substrate including a pixel region, a cathode
connected to the driving element, in which the cathode
includes molybdenum (Mo), an emitting layer on the cathode,
and an anode on the emitting layer.

5 Claims, 22 Drawing Sheets



VIIIa

VIIIa

FIG. 1
Related Art





FIG. 2
Related Art






FIG. 4
Related Art




FIG. 5
Related Art





FIG. 6




FIG. 8A




FIG. 8B






FIG. 8C*FIG. 8D*

FIG. 9A




FIG. 9B




FIG. 9C




FIG. 9D




FIG. 9E




FIG. 9F




FIG. 9G




FIG. 10A






FIG. 10B*FIG. 10C*



FIG. 10D*FIG. 10E*



FIG. 10F*FIG. 10G*



FIG. 11A*FIG. 11B*



FIG. 11C*FIG. 11D*



FIG. 11E*FIG. 11F*



FIG. 11G*FIG. 12A*



FIG. 12B*FIG. 12C*





FIG. 12D*FIG. 12E*

FIG. 12F*FIG. 12G*

DUAL PANEL TYPE ORGANIC ELECTROLUMINESCENT DISPLAY DEVICE AND METHOD OF FABRICATING THE SAME

This application is a Divisional of application Ser. No. 11/639,310, filed on Dec. 15, 2006 now U.S. Pat. No. 7,923, 916, which claims priority to Korean Patent Application No. 10-2006-0060861 filed in Korea on Jun. 30, 2006. The entire contents of all of the above applications are hereby incorporated by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to an organic electroluminescent device (OELD), and more particularly to a top emission type OELD having a high brightness.

2. Discussion of the Related Art

In general, an OELD emits light by injecting electrons from a cathode and holes from an anode into an emission layer, combining the electrons with the holes, generating an exciton, and transitioning the exciton from an excited state to a ground state. In comparison to a liquid crystal display (LCD) device, an additional light source is not necessary for the OELD to emit light, because the transition of the exciton between the two states causes light to be emitted. Accordingly, the size and weight of the OELD are less than the LCD device.

The OELD has other excellent characteristics, such as a low power consumption, superior brightness, and a fast response time. Thus, the OELD is seen as the display for the next-generation of consumer electronic applications such as cellular phones, car navigation systems (CNSs), personal digital assistants (PDAs), camcorders, palmtop computers, etc. Moreover, because fabricating the organic ELD is performed with fewer processing steps, the OELD is less expensive to produce than the LCD device.

In addition, the two types of OELDs are a passive matrix OELD and an active matrix OELD. While both of the passive and active matrix OELDs have a simple structure and are formed by a simple fabricating process, the passive matrix OELD requires a relatively large amount of power to operate. In addition, the display size of the passive matrix OELD is limited by the width and thickness of conductive lines used in the structure. Further, as the number of conductive lines increases, the aperture ratio of the passive matrix OELD decreases. In contrast, the active matrix OELDs are highly efficient and can produce a high-quality image on a large display with a relatively low power.

Turning now to FIG. 1, which is a schematic cross-sectional view of an OELD 1 according to the related art. As shown, the OELD 1 includes first and second substrates 12 and 28 facing and being spaced apart from each other. Also included is an array element layer 14 formed on the first substrate 12. As shown, the array element layer 14 includes a thin film transistor "T." Although not shown, the array element layer 14 further includes a gate line, a data line crossing the gate line to define a pixel region "P," and a power line crossing one of the gate and data lines. In addition, the OELD 1 also includes a first electrode 16 on the array element layer 14, an organic electroluminescent (EL) layer 18 on the first electrode 16, and a second electrode 20 on the organic EL layer 18. In addition, the first electrode 16 is connected to the thin film transistor "T." Here, the organic EL layer 18 includes red (R), green (G) and blue (B) sub-organic EL layers in the pixel regions "P."

In addition, the second substrate 28 functions as an encapsulating panel having a recessed portion 21. A desiccant 22 is packaged in the recessed portion 21 to protect the OELD 1 from moisture. Further, a seal pattern 26 is formed between the first and second substrates 12 and 28 in a periphery thereof so as to attach the first and second substrates 12 and 28 to each other.

Next, FIG. 2 is an equivalent circuit diagram of the related art ELD shown in FIG. 1. As shown in FIG. 2, a pixel region "P" is defined by a gate line 42 and a data line 44 crossing the gate line 42 formed on a substrate 32. Also included is a power line 55 spaced parallel from the gate line 42 and crossing the data line 44.

In addition, a switching element "T_s" is connected to the gate and data lines 42 and 44 at an adjacent portion crossing the gate and data lines 42 and 44 and a driving element "T_D" is connected to the switching element "T_s." For example, the driving element "T_D" in FIG. 2 is a positive type thin film transistor. Further, a storage capacitor "C_{ST}" is formed between the switching element "T_s" and the driving element "T_D." Also, a drain electrode 63 of the driving element "T_D" is connected to a first electrode (not shown) of an organic EL diode "E." In addition, a source electrode 66 of the driving element "T_D" is connected to the power line 55 and a gate electrode 68 is connected to the capacitor Cst and switching element T_s.

Hereinafter, an operation of the OELD will be explained in detail. When a gate signal is applied to the gate electrode 46 of the switching element "T_s," a current signal applied to the data line 44 is changed into a voltage signal through the switching element "T_s" and is applied to the gate electrode 68 of the driving element "T_D."

Therefore, the driving element "T_D" is driven and the level of the current applied to the organic EL diode "E" is determined such that the organic EL diode "E" can embody a gray scale. Further, because the signal in the storage capacitor "Cst" functions to maintain the signal of the gate electrode 68 of the driving element "T_D," the current applied to the EL diode is maintained until the next signal is applied even if the switching element "T_s" is in an OFF state.

Next, FIG. 3 is a schematic plan view of a related art OELD with respect to one pixel. As shown, the switching element "T_s," the driving element "T_D" connected to the switching element "T_s," and the storage capacitor "Cst" are formed on the substrate 32 in the pixel region "P." Alternatively, the switching element "T_s" and the driving element "T_D" can be formed in multiple in the pixel region "P" in accordance with an operation characteristic thereof.

In addition, the substrate 32 includes a transparent insulating substrate such as glass or a plastic substrate. The gate line 42 is formed on the substrate 32 and the data line 44 crosses the gate line 42 to define the pixel region "P." In addition, in this example, a power line 55 is parallel to the data line 44.

Further, the switching element "T_s" includes the gate electrode 46 connected to a first gate line 42, a first semiconductor layer 50 over the first gate electrode 46, a first source electrode 56 connected to the data line 44, and a first drain electrode 60 spaced apart from the first source electrode 56. The driving element "T_D" includes the second gate electrode 68 connected to the drain electrode 60, a second semiconductor layer 62 over the second gate electrode 68, the second source electrode 66 connected to the power line 55, and the second drain electrode 63. Specifically, the first drain electrode 60 and the gate electrode 68 are connected to each other via a contact hole 64 of an insulating material layer (not shown).

Further, a first electrode 36 is connected to the first drain electrode 63 in the pixel region "P." Although not shown, the

storage capacitor "Cst" includes a first storage electrode of doped silicon, a second storage electrode occupying a portion of the power line 55, and an insulating material layer (not shown) between the first and second storage electrodes.

Turning now to FIG. 4, which is a schematic cross-sectional view of the related art OLED taken along the "IV-IV" line in FIG. 3. In FIG. 4, the second semiconductor layer 62 is formed on the substrate 32, a gate insulating layer "GI" is formed on the second semiconductor layer 62, the gate electrode 68 is formed on the gate insulating layer "GI" over the second semiconductor layer 62, and an interlayer insulating layer "IL" is formed on the gate electrode 68 and includes first and second contact holes "C1" and "C2" that expose both end portions of the second semiconductor layer 62. The source and drain electrodes 66 and 63 are formed on the interlayer insulating layer "IL" and are connected to the second semiconductor layer 62 via the first and second contact holes "C1" and "C2."

A passivation layer 68 is also formed on the second source and drain electrodes 66 and 63 and includes a drain contact hole "C3" that exposes a portion of the drain electrode 63. The first electrode 36 is connected to the drain electrode 63 via the drain contact hole "C3," the organic EL layer 38 is formed on the first electrode 36, and a second electrode 80 is formed on the organic EL layer 38. The first electrode 36, the organic EL layer 38, and the second electrode 80 constitute the organic EL diode "E." Further, the driving element "T_D" is a negative type TFT, and the first electrode 36 and the second electrode 80 are a cathode and an anode, respectively. Alternatively, the driving element "T_D" is a positive type TFT, and the first electrode 36 and the second electrode 80 are an anode and a cathode, respectively.

In addition, the storage capacitor "Cst" and the driving element "T_D" are disposed in a row. Here, the source electrode 66 is connected to the second storage electrode, and the first storage electrode 35 is disposed under the second storage electrode 34.

FIG. 5 is a schematic cross-sectional view of an emission region of the related art. In FIG. 5, the emission region of the OLED 1 includes the anode 36 on the substrate 32, a hole injection layer 38a on the anode 36, a hole transport layer 38b on the hole injection layer 38a, an emitting layer 38c on the hole transport layer 38b, an electron transport layer 38d on the emitting layer 38c, an electron injection layer 38e on the electron transport layer 38d, and the cathode 80 on the electron injection layer 38e. These layers are sequentially layered on the anode 36.

In addition, the hole transport layer 38b and the electron transport layer 38d function to transport a hole and electron to the emitting layer 38c to improve an emitting efficiency. Further, the hole injection layer 38a between the anode 36 and the hole transport layer 38b function to reduce a hole injecting energy, and the electron injection layer 38e between the cathode 80 and the electron transport layer 38d function to reduce an electron injecting energy, thereby increasing the emitting efficiency and reducing the driving voltage of the OLED.

Further, the cathode 80 is formed of a material including calcium (Ca), aluminum (Al), magnesium (Mg), silver (Ag) and lithium (Li). In addition, the anode 36 includes a transparent conductive material such as indium tin oxide (ITO). Thus, because the anode 36 formed with a transparent conductive material such as ITO is deposited by sputtering, layers under the anode 36 may be damaged. Therefore, to prevent damaging the emitting layer 38, the anode 36 is not formed on the emitting layer 38.

Accordingly, when light from the emitting layer 38 is emitted toward the anode 36 formed under the emitting layer 38,

the substantial aperture region is limited due to the array element (not shown) under the anode 36. Consequently, because the OLED related art is a bottom emission type OLED, the brightness is deteriorated due to the array element.

Further, to minimize the aperture region, the design of the array element is limited. Also, the driving element is selected from a positive type poly-silicon type in connection with the structure of the organic EL diode, the array process is complicated and the product yield is reduced.

SUMMARY OF THE INVENTION

Accordingly, one object of the present invention is to address the above-noted and other problems.

Another object of the present invention is to provide an OLED and a method of fabricating the same that can be driven as a top emission type OLED with an improved brightness.

Yet another object of the present invention is to provide an OLED and a method of fabricating the same that includes an array element formed through a simple process that reduces the product cost.

Another object of the present invention is to provide an OLED and a method of fabricating the same that prevents oxidation of the cathode to thereby prevent a driving defect of the OLED.

To achieve these and other advantages and in accordance with the purpose of the present invention, as embodied and broadly described herein, the present invention provides in one aspect an organic electroluminescent device including a switching element and a driving element connected to the switching element on a substrate including a pixel region, a cathode connected to the driving element, in which the cathode includes molybdenum (Mo), an emitting layer on the cathode, and an anode on the emitting layer.

In another aspect, the present invention provides a method of fabricating an organic electroluminescent device including forming a switching element and a driving element connected to the switching element on a substrate including a pixel region, forming and connecting a cathode to the driving element, in which the cathode includes molybdenum (Mo), forming an emitting layer on the cathode, and forming an anode on the emitting layer. The present invention also provides a method of fabrication OLED devices.

These and other objects of the present application will become more readily apparent from the detailed description given hereinafter. However, it should be understood that the detailed description and specific examples, while indicating preferred embodiments of the invention, are given by way of illustration only, since various changes and modifications within the spirit and scope of the invention will become apparent to those skilled in the art from this detailed description.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are included to provide a further understanding of the invention and are incorporated in and constitute a part of this specification, illustrate embodiments of the invention and together with the description serve to explain the principles of the invention. In the drawings:

FIG. 1 is a schematic cross-sectional view of a related art OLED;

FIG. 2 is an equivalent circuit diagram of the related art OLED;

FIG. 3 is a schematic plan view of the related art OLED with a respect to one pixel region;

FIG. 4 is a schematic cross-sectional view of the related art OLED taken along the “IV-IV” line in FIG. 3;

FIG. 5 is a schematic cross-sectional view of an emission region of the related art OLED;

FIG. 6 is a schematic cross-sectional view of an OLED according to an embodiment of the present invention;

FIG. 7 is a schematic plan view of an array substrate of an OLED according to an embodiment of the present invention;

FIGS. 8A, 8B, 8C and 8D are schematic cross-sectional views of an OLED taken along the “VIIIa-VIIIa,” “VIIIb-VIIIb,” “VIIIc-VIIIc,” and “VIId-VIId” lines in FIG. 7 according to an embodiment of the present invention;

FIGS. 9A to 9G are schematic cross-sectional views in accordance with a fabricating process of an OLED taken along the “VIIIa-VIIIa” line in FIG. 7 according to an embodiment of the present invention;

FIGS. 10A to 10G are schematic cross-sectional views in accordance with a fabricating process of an OLED taken along the “VIIIb-VIIIb” line in FIG. 7 according to an embodiment of the present invention;

FIGS. 11A to 11G are schematic cross-sectional views in accordance with a fabricating process of an OLED taken along the “VIIIc-VIIIc” line in FIG. 7 according to an embodiment of the present invention; and

FIGS. 12A to 12G are schematic cross-sectional views in accordance with a fabricating process of an OLED taken along the “VIId-VIId” line in FIG. 7 according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference will now be made in detail to the preferred embodiments, examples of which are illustrated in the accompanying drawings.

Turning first to FIG. 6, which is a schematic cross-sectional view of an OLED according to an embodiment of the present invention. As shown in FIG. 6, the OLED “EL” includes an array element (not shown) on a substrate 100, a cathode 200 on the array element, an electron injection layer 202 on the cathode 200, an electron transport layer 204 on the electron injection layer 202, an emitting layer 206 on the electron transport layer 204, a hole transport layer 208 on the emitting layer 206, a hole injection layer 210 on the hole transport layer 208, and an anode 214 over the hole injection layer 210.

Further, a buffer layer 212 may be disposed between the hole injection layer 210 and the anode 214 to prevent damage to the hole injection layer 210 during a deposition process by sputtering of the anode 214 of ITO or IZO. For example, the buffer layer 212 may include an organic molecular material for the hole injection layer. Specifically, the buffer layer 212 may be selected from one of an organic monomolecular material having a crystallinity and an oxide including vanadium pentoxide (V_2O_5). Also, the organic monomolecular material includes copper phthalocyanine (CuPc). Specifically, CuPc can be formed with a thin thickness and have a low threshold voltage and a high mobility.

In addition, the anode 214 includes a transparent conductive material such as ITO or IZO, and the cathode 200 includes molybdenum (Mo). Generally, although the cathode 200 is selected from a metallic material having a low work function such as calcium (Ca), aluminum (Al), magnesium (Mg), silver (Ag), or lithium (Li), the metallic material having a low work function is easily oxidized by being exposed to moisture and air during the mask process. Accordingly, the cathode 200 includes Mo having a non-oxidation characteristic or may further include a buffer layer between the cathode

200 and the electron injection layer 202. Specifically, the buffer layer may be etched when patterning a passivation layer (not shown) on the buffer layer to connect the cathode 200 and a drain electrode of the driving element “ T_D .”

As explained above, because the anode 214 is formed on top of the OLED, the OLED is a top emission type, thereby improving an aperture ratio. Also, although not shown, the cathode 200 is connected to a drain electrode of a driving element that is a negative type TFT, thereby reducing a number of manufacturing processing steps and thus the product cost. Furthermore, because the oxidation of the cathode 200 is prevented, process defects are prevented.

Next, FIG. 7 is a schematic plan view of an array substrate of an OLED “EL” according to an embodiment of the present invention. In FIG. 7, the switching element “Ts” and the driving element “ T_D ” connected the switching element “Ts” are formed on the substrate 100 in a pixel region “P.”

The switching element “Ts” may be a negative thin film transistor including a first gate electrode 102, a first semiconductor layer 118, a first source electrode 122a, and a first drain electrode 122b. In addition, the driving element “ T_D ” is a negative thin film transistor including a second gate electrode 104, a second semiconductor layer 120, a second source electrode 124a and a second drain electrode 124b. Specifically, the driving element “ T_D ” is connected to the switching element “Ts” by connecting the second gate electrode 104 to the first drain electrode 122b.

Here, the first semiconductor and second semiconductor layers 118 and 120 include amorphous silicon, and the switching element “Ts” and the driving element “ T_D ” are formed as a structure to improve an operation characteristic of the OLED. For example, the first source electrode 122a has a “U” shape and the first drain electrode 122b has a bar shape extending into the first source electrode 122a and being spaced apart from the electrode 122a. Also, the second source electrode 124a has a ring shape and the second drain electrode 124b has a circular shape contained within and separated from the second source electrode 124a.

By the channel structures of the switching element “Ts” and the driving element “ T_D ,” the channel length (not shown) is reduced and the channel width (not shown) is increased, thereby maximizing the channel width and minimizing the thermallization of the OLED.

In addition, a gate line 106 is formed on the substrate 100 along a first direction and is connected to the first gate electrode 102 to apply a scanning signal to the first gate electrode 102. A data line 126 crosses the gate line 106 to define the pixel region “P” and is connected to the first source electrode 122a to apply a data signal to the first source electrode 122a. In addition, a power line 110 is parallel to and is spaced apart from the gate line 106.

Further, a gate pad 108, a data pad 128 and a power pad 114 are formed at end portions of the gate line 106, the data line 126 and the power line 110, respectively. Furthermore, a gate pad terminal 138, a data pad terminal 142 and a power pad terminal 140 are connected to the gate pad 108, the data pad 128 and the power pad 114, respectively. For example, the gate pad terminal 138, the data pad terminal 142 and the power pad terminal 140 include a transparent conductive material such as indium tin oxide (ITO) or indium zinc oxide (IZO).

Meanwhile, although not shown, a storage capacitor “Cst” includes a first storage electrode extending from the first drain electrode 122b, a second storage electrode extending from the power line 110, and an insulating layer between the first storage electrode and the second storage electrode. In other

words, the first storage electrode, the insulating layer and the second storage electrode are sequentially layered.

In addition, a cathode **132** as a first electrode is connected to the second drain electrode **124b**. Although not shown, an emitting layer (not shown) is formed on the cathode **138** and an anode (not shown) is formed as a second electrode on the emitting layer.

Next, FIGS. **8A**, **8B**, **8C** and **8D** are schematic cross-sectional views of an organic ELD taken along the “VIIIa-VIIIa,” “VIIIb-VIIIb,” “VIIIc-VIIIc,” and “VIId-VIId” lines of FIG. **7** according to an embodiment of the present invention. In more detail, FIG. **8A** illustrates a switching region “S,” a driving region “D” and a storage region “C” defined on the substrate **100**. FIGS. **8B**, **8C** and **8D** illustrate a gate region “GA,” a power region “VA” parallel to the gate region “GA,” and a data region “DA” perpendicular to the gate region “GA” and the power region “VA,” respectively.

As shown in FIG. **8A**, the switching element “Ts” and the driving element “Td” connected to the switching element “Ts” are formed in the switching region “S” and the driving region “D,” respectively. Further, as discussed above with respect to FIG. **7** and as shown in FIG. **8A**, the switching element “Ts” includes the first gate electrode **102**, the first semiconductor layer **118**, the first source electrode **122a**, and the first drain electrode **122b**. Further, the driving element “Td” includes the second gate electrode **104**, the second semiconductor layer **120**, the second source electrode **124a**, and the second drain electrode **124b**. As shown in FIG. **7**, the gate line **106** is formed along a first direction on the substrate **100**, the power line **110** is parallel to and is spaced apart from the gate line **106**, and the data line **126** crosses the gate line **106** to define the pixel region “P.”

As not specifically shown in FIG. **8A**, in the storage region “C,” a first storage electrode extends from the first drain electrode **122b**, and a second storage electrode extends from the power line **110**. Further, a gate insulating layer **116** is disposed on the first storage electrode. In addition, as shown in FIG. **8A**, the cathode **132** is connected to the second drain electrode **124b**, an emitting layer **146** is formed on the cathode **132**, and an anode **150** is formed on the emitting layer **146**. In addition, the cathode **132** includes an opaque metallic material and the anode **150** includes a transparent conductive material. That is, the OLED “EL” is driven as a top emission type such that light from the emitting layer **146** is transmitted toward the anode **150**.

Also, the second gate electrode **104** is connected to the first drain electrode **122b** via a contact hole of the gate insulating layer **116**, and the second source electrode **124a** is connected to the power line **110** (shown in FIG. **7**). Furthermore, a passivation layer **144** is formed on the cathode **128** at a boundary between the pixel regions “P,” so the emitting layer **146** in each pixel region “P” is prevented from contacting each other.

Further, as shown in FIG. **7**, the gate pad **108**, the data pad **128** and the power pad **114** are formed at end portions of the gate line **106**, the data line **126** and the power line **110**, respectively. In addition, the gate pad terminal **138**, the data pad terminal **142** and the power pad terminal **140** are connected to the gate pad **108**, the data pad **128** and the power pad **114**, respectively. FIGS. **8B**, **8C** and **8D** illustrate in cross-sectional views the gate pad **108**, the power pad **114**, and the data pad **128**, respectively.

Further, the cathode **132** includes molybdenum (Mo). Alternatively, a buffer layer (not shown) may be formed between the cathode **132** of a metallic material having a low work function and the emitting layer **146** in which the buffer

layer includes molybdenum (Mo). In the latter case, the buffer layer is etched to expose the cathode **132** when the passivation layer **144** is patterned.

Turning next to FIGS. **9A-9G**, **10A-10G**, **11A-11G** and **12A-12G**, which are schematic cross-sectional views in accordance with a fabricating process of an OLED taken along the “VIIIa-VIIIa,” “VIIIb-VIIIb,” “VIIIc-VIIIc” and “VIId-VIId” lines in FIG. **7** according to an embodiment of the present invention. FIG. **7** will also be referred to in this description.

As shown in FIGS. **7** and **9A**, the pixel region “P,” the switching region “S,” the driving region “D,” and the storage region “C” are formed on the substrate **100**. FIGS. **10A**, **11A**, and **12A** illustrate the gate region “GA,” the power region “VA,” and the data region “DA,” respectively. The data region “DA” and the gate region “GA” define the pixel region “P,” and the power region “VA” is disposed at a region parallel to the gate region “GA.” Further, as shown in FIG. **9A**, the first and second gate electrodes **102** and **104** are formed by depositing and patterning a material including aluminum (Al), aluminum alloy such as aluminum neodymium (AlNd), chromium (Cr), Mo, copper (Cu), and titanium (Ti) in the switching region “S” and the driving region “D,” respectively. In the gate region “GA,” as shown in FIG. **7**, the gate line **106** is connected to the first gate electrode **102** and is formed on the substrate **100**, and the gate pad **108** is formed at end portion of the gate line **106**. Further, the power line **110** is formed in the power region “VA,” and the power pad **114** is formed at an end portion of the power line **110**. The first storage electrode **112** extending from the power line **110** is formed in the storage region “C.”

Next, as shown in FIGS. **9A**, **10A**, **11A** and **12A**, the gate insulating layer **116** is formed by depositing an inorganic insulating material such as silicon nitride (SiNx) or silicon oxide (SiOx) on the first gate electrode **102**, the second gate electrode **104** and the second storage electrode **112**. See also FIGS. **10B**, **11B** and **11C**.

Next, first active and second active layers **118a** and **120a** are formed by depositing an intrinsic amorphous silicon on the gate insulating layer **116** in the switching region “S” and the driving region “D,” respectively. Sequentially, first and second ohmic contact layers **118b** and **120b** are formed by depositing doped amorphous silicon on the first active and second active layers **118a** and **120a**, respectively. Here, the first active layer **118a** and the first ohmic contact layer **118b** constitute a first semiconductor layer **118**, and the second active layer **120a** and the second ohmic contact layer **120b** constitute a second semiconductor layer **120**.

Next, as shown in FIG. **9A**, first and second contact holes “CH1” “CH2” are formed by etching the gate insulating layer **116** to expose a portion of the second gate electrode **104** and a portion of the first storage electrode **112**. As shown in FIG. **9B**, the first source and first drain electrodes **122a** and **122b**, the second source and second drain electrodes **124a** and **124b**, and the data line **126** (of FIG. **7**) are formed by depositing a conductive metallic material such as the same material as the gate line **106** in the switching region “S,” the driving region “D” and the storage region “C,” respectively. Further, the second storage electrode **122c** extends from the first drain electrode **122b**, the second gate electrode **104** is connected to the first drain electrode **122b** via the first contact hole “CH1,” and the second drain electrode **124b** is connected to the second storage electrode **122c** via the second contact hole “CH2.”

Next, a portion of the first ohmic contact layer **118b** between the first source electrode **122a** and the first drain electrode **122b** is removed to expose a portion of the first

active layer **118a** corresponding to the portion of the first ohmic contact layer **118b**. Further, a portion of the second ohmic contact layer **120b** between the second source electrode **124a** and the second drain electrode **124b** is removed to expose a portion of the second active layer **120a** corresponding to the portion of the second ohmic contact layer **120b**. Here, the exposed first active and second active layers **118a** and **120a** function as an active channel (not shown). In addition, as shown in FIG. 7, to reduce a channel length and to increase a channel width, the first source electrode **122a** may have "U" shape and the first drain electrode **122b** may be a bar shape. Alternatively, the second source electrode **124a** may have a ring shape and the second drain electrode **124b** may have a circular shape.

In addition, the first gate electrode **102**, the first semiconductor layer **118**, the first source electrode **122a**, and the first drain electrode **122b** constitute the switching element "Ts." Also, the second gate electrode **104**, the second semiconductor layer **120**, the second source electrode **124a**, and the second drain electrode **124b** constitute the driving element "Td."

Next in FIG. 9C, the first passivation layer **130** is formed by depositing an inorganic insulating material on the switching element "Ts" and the driving element "Td." In this step, a third contact hole "CH3" is formed by etching the first passivation layer **130** to expose a portion of the second drain electrode **124b**. Simultaneously, fourth, fifth and sixth contact holes "CH4," "CH5," and "CH6" are formed by etching the first passivation layer **130** to expose portions of the gate pad **108**, the power pad **114**, and the data pad **128**, respectively (see also FIGS. 10B, 11C and 12C).

In FIG. 9D, the cathode **132** is formed by depositing one of calcium (Ca), aluminum (Al), magnesium (Mg), silver (Ag), and lithium (Li) on the driving element "Td." Specifically, the cathode **132** is connected to the second drain electrode **124b** via the third contact hole "CH3." In this step, the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142** are formed using the same material as that of the cathode **132** and the same material as that of the first buffer layer **134** on the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142**, respectively. See also FIG. 11C.

Next, in FIGS. 9D, 10D, 11D and 11C, first, second, third and fourth buffer layers **134**, **139**, **141** and **143** are formed by depositing molybdenum (Mo) on the cathode **132**, the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142**, respectively.

Because the second, third and fourth buffer layers **139**, **141** and **143** are etched through the fourth, fifth and sixth contact holes "CH4," "CH5," and "CH6," the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142** are connected to the gate pad **108**, the power pad **114** and the data pad **128** via the fourth contact hole "CH4," the fifth contact hole "CH5" and the sixth contact hole "CH6," respectively. In FIGS. 9E, 10E, 11E and 12E, the second passivation layer **144** is formed by depositing an inorganic insulating material on the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142**.

Next, in FIGS. 9F, 10F, 11F and 12F, the second passivation layer **144** is etched to expose the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142**. Through this step, the second passivation layer **144** is remained at boundary between the pixel regions "P." Thus, because the first buffer layer **134** covers the cathode **132**, oxidation reaction on the surface of the cathode **132** is not generated before patterning the second passivation layer **144**. Similarly, the second, third and fourth buffer layers **139**, **141**

and **143** cover the gate pad terminal **138**, the power pad terminal **140**, and the data pad terminal **142**, respectively. Therefore, the oxidation reaction is prevented.

In FIGS. 9G, 10G, 11G and 12G, the emitting layer **146** is formed over the cathode **132**. Further, as shown in FIG. 9G, the OLED includes the electron injection layer "EIL" on the cathode **132**, the electron transport layer "ETL" on the electron injection layer "EIL," the hole transport layer "HTL" on the emitting layer **146**, the hole injection layer "HIL" on the hole transport layer "HTL," and the second buffer layer **148** on the hole the injection layer "HIL." In addition, the emitting layer **146** includes red (R), green (G), and blue (B) sub-emitting layers. In each example, the emitting layer **146** is disposed in each pixel region "P."

Next, as shown in FIG. 9G, the anode **150** is formed by depositing and patterning a transparent conductive material such as indium tin oxide (ITO) or indium zinc oxide (IZO) on the second buffer layer **148**. Thus, through the above-noted processes, the top emission type organic ELD is manufactured.

In addition, the OLED according to the present invention is an inverted structure such that a cathode of an opaque material is disposed as a lower electrode and an anode of a transparent conductive material is disposed as an upper electrode to form a top emission type OLED, thereby obtaining an improved aperture ratio without affecting the design of the array element. Further, the switching and driving elements are negative types, thereby reducing a number of processes, product cost, and increasing the stability of the circuit. More particularly, because the oxidation reaction of the cathode is prevented, a driving defect is also prevented.

As the present invention may be embodied in several forms without departing from the spirit or essential characteristics thereof, it should also be understood that the above-described embodiments are not limited by any of the details of the foregoing description, unless otherwise specified, but rather should be construed broadly within its spirit and scope as defined in the appended claims, and therefore all changes and modifications that fall within the metes and bounds of the claims, or equivalence of such metes and bounds are therefore intended to be embraced by the appended claims.

What is claimed is:

1. An organic electroluminescent device, comprising:

- a gate line on a substrate including a pixel region;
- a power line parallel to and spaced apart from the gate line, the power line being formed at a same layer and of a same material as the gate line;
- a data line crossing the gate line to define the pixel region;
- a switching element and a driving element connected to the switching element, the switching element being connected to the gate and data lines, and the driving element being connected to the power line;
- a cathode connected to the driving element;
- a buffer layer on the cathode;
- a passivation layer on the buffer layer, the passivation layer and the buffer layer having a contact hole that exposes a portion of the cathode;
- an emitting layer on the passivation layer, the emitting layer contacting the cathode via the contact hole; and
- an anode on the emitting layer,

wherein the buffer layer includes molybdenum (Mo).

2. The device according to claim 1, wherein the cathode includes a material selected from one of calcium (Ca), aluminum (Al), magnesium (Mg), silver (Ag), and lithium (Li).

3. A method of fabricating an organic electroluminescent device, comprising:

forming a gate line and a power line on a substrate including a pixel region, the power line being parallel to and spaced apart from the gate line, and the power line being formed at a same layer and of a same material as the gate line;

forming a data line crossing the gate line to define the pixel region;

forming a switching element and a driving element connected to the switching element, the switching element being connected to the gate and data lines, and the driving element being connected to the power line;

forming a cathode connected to the driving element after the step of forming the switching element and the driving element;

forming a buffer layer on the cathode;

forming a passivation layer on the buffer layer;

forming an emitting layer on the passivation layer, the emitting layer contacting the cathode via the contact hole that exposes a portion of the cathode; and

forming an anode on the emitting layer.

4. The method according to claim 3, wherein the cathode includes a material selected from one of calcium (Ca), aluminum (Al), magnesium (Mg), silver (Ag), and lithium (Li).


5. The method according to claim 3, wherein the buffer layer includes molybdenum (Mo).

* * * * *

专利名称(译)	双面板型有机电致发光显示装置及其制造方法		
公开(公告)号	US8536778	公开(公告)日	2013-09-17
申请号	US13/040936	申请日	2011-03-04
[标]申请(专利权)人(译)	HEO JUNG SOO 朴在熙 俞桑HO 朴敬MIN LEE JONG SEOK		
申请(专利权)人(译)	HEO JUNG-SOO 公园jae-hee YU SANG-HO PARK KYUNG-MIN 崔成勋 李硕JONG		
当前申请(专利权)人(译)	LG DISPLAY CO. , LTD.		
[标]发明人	HEO JUNG SOO PARK JAE HEE YU SANG HO PARK KYUNG MIN CHOI SUNG HOON LEE SEOK JONG		
发明人	HEO, JUNG-SOO PARK, JAE-HEE YU, SANG-HO PARK, KYUNG-MIN CHOI, SUNG-HOON LEE, SEOK-JONG		
IPC分类号	H01L51/52		
CPC分类号	H01L27/3244 H01L27/3248 H01L51/5221 H01L2251/5315 H01L51/5088 H01L27/3262		
代理机构(译)	桦木, STEWART, KOLASCH与桦木, LLP		
优先权	1020060060861 2006-06-30 KR		
其他公开文献	US20110156573A1		
外部链接	Espacenet USPTO		

摘要(译)

一种有机电致发光器件，包括开关元件和连接到包括像素区域的基板上的开关元件的驱动元件，连接到驱动元件的阴极，其中阴极包括钼 (Mo) ，阴极上的发光层，和发光层上的阳极。



VIIIa

VIIIa