




US 20030135099A1

(19) **United States**(12) **Patent Application Publication**
Al-Ali(10) **Pub. No.: US 2003/0135099 A1**(43) **Pub. Date: Jul. 17, 2003**(54) **ISOLATION AND COMMUNICATION
ELEMENT FOR A RESPOSABLE PULSE
OXIMETRY SENSOR**(60) Provisional application No. 60/351,784, filed on Jan.
25, 2002.(76) Inventor: **Ammar Al-Ali, Tustin, CA (US)**

Correspondence Address:

**KNOBBE MARTENS OLSON & BEAR LLP
2040 MAIN STREET
FOURTEENTH FLOOR
IRVINE, CA 92614 (US)****Publication Classification**(51) **Int. Cl.⁷** **A61B 5/00**(52) **U.S. Cl.** **600/323**(21) Appl. No.: **10/351,643**(22) Filed: **Jan. 24, 2003****Related U.S. Application Data**(63) Continuation-in-part of application No. 10/128,721,
filed on Apr. 23, 2002, which is a continuation of
application No. 09/456,666, filed on Dec. 9, 1999,
now Pat. No. 6,377,829.(57) **ABSTRACT**

A sensor has a connector adapted to electrically communicate with a physiological measurement instrument. A breakable conductor incorporated by the sensor transitions from a continuity state to a discontinuity state as the result of sensor wear. An isolation and communications element (ICE) has an instrument port and an electrically isolated loop port. The instrument port is in communications with the connector and the loop port is in communications with the breakable conductor. The ICE generates a control output responsive to the discontinuity state to render the sensor inoperable.







FIG. 1






FIG. 2B
(PRIOR ART)




FIG. 3




FIG. 4




FIG. 5




FIG. 6A




FIG. 6B




FIG. 7




FIG. 8A




FIG. 8B




FIG. 9A




FIG. 9B




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14

ISOLATION AND COMMUNICATION ELEMENT FOR A RESPONSABLE PULSE OXIMETRY SENSOR

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] The present application claims priority benefit under 35 U.S.C. §120 to and is a continuation-in-part of U.S. patent application Ser. No. 10/128,721, filed Apr. 23, 2002, entitled "Responsible Pulse Oximetry Sensor," which is a continuation of U.S. patent application Ser. No. 09/456,666 filed Dec. 9, 1999, now U.S. Pat. No. 6,377,829, entitled "Responsible Pulse Oximetry Sensor." Moreover, the present application claims priority benefit under 35 U.S.C. §119(e) to U.S. Provisional Patent Application Serial No. 60/351,784, filed Jan. 25, 2002, entitled "Isolation and Communication Element for a Responsible Pulse Oximetry Sensor." The present application incorporates the foregoing disclosures herein by reference.

BACKGROUND OF THE INVENTION

[0002] Early detection of low blood oxygen is critical in a wide variety of medical applications. For example, when a patient receives an insufficient supply of oxygen in critical care and surgical applications, brain damage and death can result in just a matter of minutes. Because of this danger, the medical industry developed oximetry, a study and measurement of the oxygen status of blood. One particular type of oximetry, pulse oximetry, is a widely accepted noninvasive procedure for measuring the oxygen saturation level of arterial blood, an indicator of the oxygen status of the blood. A pulse oximeter relies on a sensor attached to a patient in order to measure the blood oxygen saturation.

[0003] Conventionally, a pulse oximeter sensor has a red emitter, an infrared emitter, and a photodiode detector. The sensor is typically attached to a patient's finger, earlobe, or foot. For a finger, the sensor is configured so that the emitters project light through the outer tissue of the finger and into the blood vessels and capillaries contained inside. The photodiode is positioned at the opposite side of the finger to detect the emitted light as it emerges from the outer tissues of the finger. The photodiode generates a signal based on the emitted light and relays that signal to a pulse oximeter. The pulse oximeter determines blood oxygen saturation by computing the differential absorption by the arterial blood of the two wavelengths (red and infrared) emitted by the sensor.

[0004] Conventional sensors are either disposable or reusable. A disposable sensor is typically attached to the patient with an adhesive wrap, providing a secure contact between the patient's skin and the sensor components. A reusable sensor is typically a clip that is easily attached and removed, or reusable circuitry that employs a disposable attachment mechanism, such as an adhesive tape or bandage.

[0005] The disposable sensor has the advantage of superior performance due to conformance of the sensor to the skin and the rejection of ambient light. However, repeated removal and reattachment of the adhesive tape results in deterioration of the adhesive properties and tearing of the tape. Further, the tape eventually becomes soiled and is a potential source of cross-patient contamination. The disposable sensor must then be thrown away, wasting the long-lived emitters, photodiode and related circuitry.

[0006] On the other hand, the clip-type reusable sensor has the advantage of superior cost savings in that the reusable pulse sensor does not waste the long-lived and expensive sensor circuitry. However, as mentioned above, the clip-type reusable sensor does not conform as easily to differing patient skin shape, resulting in diminished sensitivity and increased ambient light.

[0007] Similar to the clip-type reusable sensor, the circuit-type reusable sensor advantageously does not waste the sensor circuitry. On the other hand, the circuit-type reusable sensor fails to provide quality control over the attachment mechanism. Much like the disposable sensors, the attachment mechanism for the circuit-type reusable sensor may become soiled or damaged, thereby leading to cross-patient contamination or improper attachment. Moreover, because the reusable circuit is severable from the attachment mechanism, operators are free to use attachment mechanisms that are either unsafe or improper with regard to a particular type of reusable circuitry.

[0008] Based on the foregoing, significant and costly drawbacks exist in conventional disposable and reusable oximetry sensors. Thus, a need exists for a pulse oximetry sensor that incorporates the advantages found in the disposable and reusable sensors, without the respective disadvantages.

SUMMARY OF THE INVENTION

[0009] A reusable sensor with the performance features of a disposable may incorporate a disposable adhesive tape component that can be removed from other reusable sensor components. The disposable tape may include a mechanism for the electrical connection of an information element to the emitters, where the information element provides an indication to an attached pulse oximeter of various aspects of the sensor and also insures the sensor is from an authorized supplier. The information element electrical connection mechanism may be a breakable conductor located within the disposable component such that excessive wear of the disposable component prevents connection of the information element to an attached pulse oximeter, thereby indicating that the disposable component should be replaced. There are some drawbacks to this approach, however, including patient-instrument electrical isolation and electromagnetic interference (EMI).

[0010] Electrical isolation between an electrical source and a patient needs to be 4,000V. A pulse oximeter instrument typically provides 2,500V of isolation and a pulse oximeter sensor another 1,500V. The 1,500V sensor isolation is difficult to achieve with a breakable conductor located within the tape used for patient sensor attachment. Further, a breakable conductor formed as a loop around the periphery of the disposable attachment tape, although advantageous for wear detection, creates an antenna that receives EMI, which can be conducted directly into the sensor circuitry.

[0011] A sensor incorporating an isolation and communications element (ICE) that reduces or eliminates the aforementioned drawbacks has a connector adapted to electrically communicate with a physiological measurement instrument, such as a pulse oximeter. A breakable conductor incorporated by the sensor transitions from a continuity state to a discontinuity state as the result of sensor wear. An isolation and communications element (ICE) has an instrument port

and an electrically isolated loop port. The instrument port is in communications with the connector and the loop port is in communications with the breakable conductor. The ICE generates a control output responsive to the discontinuity state to render the sensor inoperable.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] **FIG. 1** illustrates a circuit diagram of a conventional disposable sensor having an information element.

[0013] **FIGS. 2A and 2B** illustrate perspective views of the conventional disposable sensor.

[0014] **FIG. 3** illustrates an exploded view of a resposable sensor having two disposable tape layers, according to one embodiment of the invention.

[0015] **FIG. 4** illustrates a top view of one of the disposable tape layers of **FIG. 3** incorporating an information element.

[0016] **FIG. 5** illustrates a top view of one of the disposable tape layers of **FIG. 3** incorporating a breakable conductor.

[0017] **FIGS. 6A and 6B** illustrate cross-sectional views of a portion of the disposable tape layer of **FIG. 5**.

[0018] **FIG. 7** illustrates a top view of one of the disposable tape layers of **FIG. 3** incorporating the information element with a breakable conductor.

[0019] **FIGS. 8A and 8B** illustrate a top view and a side view, respectively, of one of the disposable layers of **FIG. 3** configured as a fold-over tape.

[0020] **FIG. 9A** illustrates a perspective view of a resposable sensor having a disposable portion configured as a tape sleeve and a reusable portion directly attached to a patient cable, according to another embodiment of the invention.

[0021] **FIG. 9B** illustrates a perspective view of a resposable sensor having a reusable portion removably attached to a patient cable, according to another embodiment of the invention.

[0022] **FIG. 10** is a schematic of a sensor circuit incorporating a breakable conductor.

[0023] **FIG. 11** is a schematic of a sensor circuit incorporating an embodiment of an isolation and communications element (ICE).

[0024] **FIG. 12** is a block diagram of an ICE embodiment.

[0025] **FIG. 13** is a schematic of a sensor circuit incorporating an alternative embodiment of an isolation and communications element (ICE).

[0026] **FIG. 14** is a block diagram of an alternative ICE embodiment.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

[0027] **Resposable Pulse Oximeter Sensor**

[0028] The configuration of an information element for an oximeter sensor and method of reading an information element with an attached oximeter is described in U.S. Pat. No. 5,758,644 entitled "Manual And Automatic Probe Calibration," assigned to Masimo Corporation, Irvine, Calif. and

incorporated by reference herein. Accordingly, the configuration and the implementation of an information element will be greatly summarized as follows.

[0029] **FIG. 1** illustrates a conventional oximeter sensor circuit **100**. The oximeter sensor circuit **100** includes an emitter **105** comprising a first LED **107** and a second LED **110**. The oximeter sensor circuit further includes an information element comprising a resistor **115**. The first LED **107**, the second LED **110** and the resistor **115** are connected in parallel. The parallel connection has a common input electrical connection **120** and a common return **125**. The oximeter sensor circuit **100** also includes a photodetector **130** having an input electrical connection **135** connected to one end and having the common return **125** connected to the other end.

[0030] As mentioned, the resistor **115** is provided as an information element that can be read by an attached oximeter. In order to read the resistor **115**, the oximeter drives the oximeter sensor circuit **100** at a level where the emitter **105** draws effectively insignificant current. As is well understood in the art, the emitter **105** becomes active only if driven at a voltage above a threshold level. Thus, at this low level, significantly all of the current through the input electrical connection **120** flows through the resistor **115**. By reducing the drive voltage across the input electrical connection **120** and common return **125** to a low enough level to not activate the emitter **105**, the emitter **105** is effectively removed from the oximeter sensor circuit **100**. Thus, the oximeter can determine the value of the resistor **115**.

[0031] The value of the resistor **115** can be preselected to indicate, for example, the type of sensor (e.g., adult, pediatric, or neonatal), the operating wavelength, or other parameters about the sensor. The resistor **115** may also be utilized for security and quality control purposes. For example, the resistor **115** may be used to ensure that the oximeter sensor circuit **100** is configured properly for a given oximeter. For instance, the resistor **115** may be utilized to indicate that the oximeter sensor circuit **100** is from an authorized supplier.

[0032] An information element other than the resistor **115** may also be utilized. The information element need not be a passive device. Coding information may also be provided through an active circuit, such as a transistor network, memory chip, or other identification device.

[0033] Furthermore, it will be understood by a skilled artisan that a number of different circuit configurations can be implemented that allow the oximeter sensor circuit **100** to include an information element. For example, the emitter **105** and the information element may each have individual electrical connections.

[0034] As mentioned above, the resistor **115** is preselected such that at low drive voltages, it is the only circuit element sensed by the oximeter. On the other hand, the resistor **115** can also be preselected be of a sufficiently high value that when the drive voltage rises to a level sufficient to drive the emitter **105**, the resistor **115** is effectively removed from the oximeter sensor circuit **100**. Thus, the resistor **115** does not affect normal operations of the emitter **105**. In summary, an information element may form an integral part of the oximeter sensor circuit **100** by providing valuable information to the attached oximeter.

[0035] **FIGS. 2A and 2B** illustrate a conventional disposable sensor **200**. The disposable sensor **200** includes an

adhesive substrate **205** having an elongated center portion **210** with front and rear flaps, **215** and **220**, extending outward from the elongated center portion **210**. The adhesive substrate **205** may also have an image **225** superimposed on the adhesive substrate **205** so as to indicate proper use.

[0036] The elongated center portion **210** includes the oximeter sensor circuit **100** of FIG. 1. For example, the emitter **105** is housed on an underside of the elongated center portion **210** approximately beneath the superimposed image **225**. Thus, as shown in FIG. 2A, the emitter **105** may be housed approximately beneath the asterisk superimposed on the image of a fingernail. On the other hand, the photodetector **130** is housed on the topside of the elongated center portion **210** in proximity with the rear flaps **220**.

[0037] The elongated center portion **210** further includes an electrical connector **230** to drive the emitter **105** and to receive an output from the photodetector **130**. The electrical connector **230** is preferably configured to attach to a connector cable **235** via a sensor connector **240**. Also, the connector cable **235** attaches to or connects with an oximeter via an oximeter connector **245**.

[0038] FIG. 2B illustrates an example of how the disposable sensor **200** wraps the front and rear flaps **215** and **220** around a finger such that the adhesive substrate **205** provides a secure contact between the patient's skin, the emitter **105** and the photodetector **130**. FIG. 2B also illustrates an example of the sensor connector **240** (shown in broken lines) encompassing the electrical connector **230**.

[0039] As shown in FIGS. 1-2B, the conventional disposable sensor **200** integrates the components of the conventional oximeter sensor circuit **100** such that disposal of the disposable sensor **200** includes disposal of the longer lasting, expensive circuitry found therein.

[0040] FIG. 3 illustrates an exploded view of one embodiment of a resposable (reusable/disposable) sensor **300**. In this embodiment, the resposable sensor **300** includes a reusable portion **305** having an emitter **306**, a photodetector **307** and an electrical connector **308**. The resposable sensor also includes a disposable portion **310** having a face tape layer **315** and a clear base tape layer **320**. As shown in FIG. 3, the disposable portion **310** attaches to the reusable portion **305** by sandwiching the reusable portion **305** between a face tape layer **315** and a clear base tape layer **320**.

[0041] According to this embodiment, conventional adhesives or other attaching methodology may be used to removably attach the face tape layer **315** to the clear base tape layer **320**. Furthermore, the adhesive properties associated with the base of the conventional disposable sensor **200** may be the same as the adhesive properties on the base of the clear base tape layer **320**, as both portions are provided to attach to the patient's skin.

[0042] As mentioned, the disposable portion **310** removably attaches to the reusable portion **305** in, for example, a sandwich or layered style. After removably attaching the disposable portion **310** to the reusable portion **305**, the resposable sensor **300** functions similar to the disposable sensor **200**, i.e., the resposable sensor **300** wraps flaps around a patient's tissue such that the emitter **306** and the photodetector **307** align on opposite sides of the tissue. However, in contrast to the disposable sensor **200**, the

resposable sensor **300** provides for reuse of the reusable portion **305**. For example, when the disposable portion **310** becomes contaminated, worn, or defective, rather than discarding the entire resposable sensor **300**, the disposable portion **310** is removed such that the reusable portion **305** may be re-removably attached to a new disposable portion **310**. The discarding of the disposable portion **310** completely avoids cross-contamination through the reuse of adhesive tapes between patients without wasting the more costly and longer lasting sensor circuitry of the resposable portion **305**. Note that optional sterilization procedures may be advantageously performed on the reusable portion **305** before reattachment to either the new disposable portion **310** or to the patient, in order to further ensure patient safety.

[0043] FIG. 4 illustrates a top view of an embodiment of the face tape layer **315** of the disposable portion **310** of the resposable sensor **300**. According to this embodiment, the face tape layer **315** further includes an information element **405** as an integral part of the face tape layer **315**. In this embodiment, the information element **405** is a resistive element made by depositing a conductive ink trace having a predetermined length and width. As is known in the art, the length, width and conductivity of the conductive ink trace determines the resistance of the resistive element. The information element **405** is deposited between contacts **410** that are also implemented with conductive ink. It will be understood by a skilled artisan that a variety of methods can be used for mating the contacts **410** with the electrical circuitry of the reusable portion **305**. For example, the contacts **410** may advantageously physically touch the leads or the electrical connector **308** such that the reusable portion **305** is electrically configured to include the information element **405**. Such a configuration employs the oximeter sensor circuit **100** of FIG. 1, having elements thereof distributed in both the reusable portion **305** and the disposable portion **310** of the resposable sensor **300**.

[0044] In the foregoing embodiment, the disposable portion **310** comprises the information element **405** along with the face tape layer **315** and the clear base layer **320**. As mentioned, the disposable portion **310** is removably attached to the reusable portion **305** and is employed in a similar manner as the disposable sensor **200**. In contrast to the disposable sensor **200**, when the disposable portion **310** of the resposable sensor **300** becomes worn, the disposable portion **310** and the information element **405** are discarded and the reusable portion **305** is saved. By discarding the information element, the attached oximeter can perform quality control. For example, if the reusable portion **305** is reattached to a patient using either a simple adhesive or any other non-authorized disposable mechanism, the resposable sensor **300** will not include the information element **405**. As mentioned above, an attached oximeter can recognize the absence of the information element **405** and create an appropriate response indicating inappropriate use of the reusable portion **305** of the resposable sensor **300**.

[0045] FIG. 5 illustrates a top view of yet another embodiment of the face tape layer **315** of the disposable portion **310** of the resposable sensor **300**. In this embodiment, the face tape layer **315** includes a breakable conductor **505** comprising a conductive ink trace located approximately along the periphery of the face tape layer **315**. This location ensures that a tear along the periphery of the face tape layer **315** results in a tear, or electrical discontinuity, in the breakable

conductor **505**. For example, **FIGS. 6A and 6B** illustrate the face tape layer **315** in which the breakable conductor **505** is layered between a tape stock **605** and a tape base **610**. The reusable portion **305** of the resposable sensor **300** then attaches to the tape base **610** through a pressure sensitive adhesive (PSA) **615**. The PSA **615**, the conductor **505** and the tape base **610** include a score **620** such that multiple attachment and removal of the resposable sensor **300** will result in a peripheral tear, or electrical discontinuity, in the breakable conductor **505**, as illustrated in **FIG. 6B**.

[0046] Thus, like the information element **405**, the breakable conductor **505** also provides security and quality control functions. In particular, repeated use of the disposable portion **305** of the resposable sensor **300** advantageously severs at least one part of the breakable conductor **505**. An attached oximeter can detect such severance and initiate an appropriate notification to, for example, monitoring medical personnel. Providing security and quality control through a breakable conductor advantageously assists in controlling problems with patient contamination or improper attachment due to weakened adhesives.

[0047] **FIG. 7** illustrates yet another embodiment of the face tape layer **315**. In this embodiment, the face tape layer **315** combines the breakable conductor **505** and the information element **405**. In this embodiment, the breakable conductor **505** is printed in a serpentine pattern to further increase the probability of a discontinuity upon the tearing of any portion of the face tape layer **315**. This combination of the information element **405** and the breakable conductor **505** advantageously adds significant safety features. For example, in this embodiment, the information element **405** is connected serially with the breakable conductor **505** and in parallel with the emitter **306** of the reusable portion **305**. Therefore, any discontinuity or tear in the breakable conductor **505** separates the information element **405** from the circuitry of the reusable portion **305**.

[0048] According to the foregoing embodiment, the attached oximeter receives an indication of both overuse and misuse of the resposable sensor **300**. For example, overuse is detected through the tearing and breaking of the breakable conductor **505**, thereby removing the information element **405** from the resposable sensor **300** circuitry. In addition, misuse through employment of disposable portions **310** from unauthorized vendors is detected through the absence of the information element **405**. Moreover, misuse from purposeful shorting of the contacts **410** is detected by effectively removing the emitter **306** from the circuit, thereby rendering the resposable sensor **300** inoperative. Therefore, the resposable sensor **300** of this embodiment advantageously provides a multitude of problem indicators to the attached oximeter. By doing so, the resposable sensor **300** advantageously prevents the likelihood of contamination, adhesive failure, and misuse. The resposable sensor **300** also advantageously maintains the likelihood of quality control.

[0049] A skilled artisan will recognize that the concepts of **FIGS. 3-7** may be combined in total or in part in a wide variety of devices. For example, either or both of the breakable conductor **505** and the information element **405** may advantageously be traced into the clear base tape layer **320** rather than into the face tape layer **315**.

[0050] **FIGS. 8A and 8B** illustrate yet another embodiment of the disposable portion **310** of the resposable sensor

300. As shown in this embodiment, the disposable portion **310** includes a face tape layer **805** and a clear base tape layer **810**. According to this embodiment, the clear base tape layer **810** includes a preattached section **815** and a fold over section **820**. The preattached section **815** attaches approximately one third of the face tape layer **805** to the clear base tape layer **810**. On the other hand, the fold over section **820** forms a flap configured to create a cavity between the face tape layer **805** and the clear base tape layer **810**. The cavity is configured to receive the reusable portion **305** of the resposable sensor **300**. According to one embodiment, a release liner **825** fills the cavity and separates the face tape layer **805** from the clear base tape layer **810**. When the release liner **825** is removed, newly exposed adhesive on the fold over section **820** and the face tape layer **805** removably attaches the reusable portion **305** between the face tape layer **805** and fold over section **820** of the clear base tape layer **810**.

[0051] According to another embodiment, the cavity is so formed that adhesive is not needed. For example, the fold over section **820** may comprise resilient material that can form a friction fit relationship so as to fix the reusable portion **305** in an appropriate position relative to the disposable portion **310**. On the other hand, the fold over section **820** may also comprise material having other than resilient or adhesive properties, but still allow for proper placement of the reusable portion **305** and disposable portion **310** on the patient. For example, hook-and-loop type materials like VELCRO® may be used.

[0052] It will be understood that a skilled artisan would recognize that the fold over embodiment of the resposable sensor **300** may employ the properties discussed in relation to **FIGS. 3-7**, such as the information element **405** and the breakable wire **505**.

[0053] **FIG. 9A** illustrates an embodiment of a resposable sensor **900** integrated with an attached patient cable **905**, according to another embodiment of the invention. In this embodiment, a disposable portion **910** is attached to a reusable portion **915** by removably inserting the reusable portion **915** into a tape envelope **920** formed in the disposable portion **910**.

[0054] A skilled artisan will recognize that the disposable portion **910** may include the information element **405**, the breakable wire **505**, or both. Inclusion of one or both of these electronic components in the resposable sensor **900** advantageously provides the security, quality control, and safety features described in the foregoing embodiments.

[0055] **FIG. 9B** illustrates an embodiment of a resposable sensor **300** of **FIG. 3**, according to another embodiment of the invention. According to this embodiment, the resposable sensor **300** removably attaches to the patient cable **905** via a sensor connector **925**. The patient cable **905** then attaches to an oximeter via an oximeter connector **930**. Use of the sensor connector **925** enables the replacement of both the reusable portion **305** of the resposable sensor **300** without replacement of the sensor connector **925** or patient cable **905**. In such an embodiment, the disposable portion **310** would follow a different, more frequent, replacement schedule than that of the reusable portion **305**.

[0056] A skilled artisan will recognize that the variety of configurations described above that include the information

element **405**, the breakable wire **505**, or both, may be incorporated into the embodiment of **FIG. 9B**.

[0057] Although the foregoing invention has been described in terms of certain preferred embodiments, other embodiments will be apparent to those of ordinary skill in the art. For example, select aspects of **FIGS. 3-9B** may be combined. For example, the envelope configured disposable portion **910** of **FIG. 9A** may be combined with the reusable portion **305** of **FIG. 3**. A responsible sensor is described in U.S. patent application Ser. No. 09/456,666 filed Dec. 9, 1999 entitled "Responsible Pulse Oximetry Sensor," assigned to Masimo Corporation, Irvine, Calif. and incorporated by reference herein.

[0058] Isolation And Communications Element

[0059] **FIG. 10** illustrates a sensor circuit **1000** incorporating a breakable conductor, as described above. The sensor circuit **1000** has emitters **107, 110**, a corresponding detector **130**, and an information element **115**, as described with respect to **FIG. 1**. The sensor circuitry **1000** also has a breakable conductor **505**, as described with respect to **FIG. 5**. Further, the sensor circuit **1000** has an emitter input **1010** and a detector output port **1020**, which are both accessible via a connector **308** (**FIG. 3**). A pulse oximeter (not shown) attached to the connector **308** (**FIG. 3**) outputs emitter drive current to the emitter input **1010** and inputs a resulting detector current from the output port **1020**, as described with respect to **FIG. 1**. The pulse oximeter also reads the information element **115** via the emitter input **1010**, as described with respect to **FIG. 1**. Excessive wear results in a discontinuity in the breakable conductor **505**, as described above. There are drawbacks, however, to this circuit configuration. If routed within the sensor face tape layer **315** (**FIG. 5**), as described with respect to **FIGS. 5-7**, the breakable conductor **505** reduces patient electrical isolation from the pulse oximeter. Further, the breakable conductor may act as an antenna for EMI and conduct the resulting electrical noise into the sensor circuitry.

[0060] **FIG. 11** illustrates a sensor circuit **1100** incorporating one embodiment of an isolation and communications element (ICE) **1200**. In addition to the ICE **1200**, the sensor circuit **1100** has a breakable conductor **505**, an emitter input **1010**, a detector output **1020**, one or more switches **1110**, emitters **107, 110**, a detector **130** and an information element **115**. The emitters **107, 110**, detector **130** and information element **115** are described above. The ICE senses a discontinuity in the breakable conductor **505** and renders the sensor inoperable accordingly. The ICE is configured to optically isolate the breakable conductor **505** from the remainder of the sensor circuitry **1100** so as to improve electrical isolation of the patient from the pulse oximeter electrical supply and prevent electromagnetic interference (EMI) inductively coupled into the breakable conductor **505** from being conducted into the sensor circuitry **1100**. Further, the ICE provides a communication feature, described below, that allows bi-directional data transfers between a pulse oximeter and the sensor, advantageously utilizing the emitter input **1010**.

[0061] As shown in **FIG. 11**, this embodiment of the ICE **1200** is connected in parallel with the input **1010**, and the switches **1110** are external to the ICE **1200**. The ICE **1200** has an instrument port **1201**, a loop port **1203** and a control port **1205**. The instrument port **1201** connects in parallel to

the emitter input **1010**. The loop port **1203** provides a current loop that connects to the breakable conductor **505**. The control port **1205** actuates the switches **1110**, which connect the emitters **107, 110** to the emitter input **1010**. The switches **1110** may be normally open or normally closed and actuated accordingly. Further, the switches may be electromechanical or purely electrical devices.

[0062] Also shown in **FIG. 11**, the instrument port **1201** taps current from the modulated signal which drives the emitters **107, 110**, in order to supply power to the ICE **1200**. The instrument port **1201** also provides bi-directional communications between the ICE **1200** and a pulse oximeter attached to the sensor connector **308** (**FIG. 3**). Advantageously, this bi-directional communications is conducted via the emitter input **1010**, eliminating the need for additional connector pinouts. The loop port **1203** provides a current loop so as to detect discontinuities in the attached breakable conductor **505**. In response to a breakable conductor discontinuity, the control port **1205** actuates one or more of the switches **1110** to an open position so as to disconnect the information element **115** or emitters **107, 110** from the emitter input **1010**. In this manner, an attached pulse oximeter is unable to read the information element **115** and/or the sensor is otherwise rendered inoperable when the breakable conductor is broken.

[0063] **FIG. 12** illustrates one embodiment of an isolation and communications element **1200**. The ICE **1200** has a processor **1210**, a memory **1220**, an opto-isolator driver/receiver **1230**, a serial transceiver **1240**, and a power converter **1250**. The opto-isolator **1230** detects an open circuit at the loop port **1203** and asserts a logic output OC **1232** in response, indicating a discontinuity in the breakable conductor. The opto-isolator **1230** electrically isolates the loop port **1203** utilizing LED and photodiode pairs (not shown), as is well-known in the art. One pair drives the current loop created by the breakable conductor **505** (**FIG. 11**). Another pair detects an open-circuit, for example by measuring the voltage across a sampling resistor in series with the breakable conductor **505** (**FIG. 11**) and generating the OC logic output **1232** accordingly. The processor **1210** reads the OC output **1232** and, in response, generates a control output **1212** to the control port **1205**, which actuates the switches **1110** (**FIG. 11**).

[0064] The power converter **1250** is an AC-to-DC converter that taps a portion of the modulated emitter drive current at the emitter input **1201** and provides one or more DC voltage outputs **1252** to power the remainder of the ICE **1200**. The memory **1220** is connected to the processor **1210** with a bi-directional bus **1222** for transferring instructions and data. The memory **1220** may be volatile RAM or nonvolatile programmable ROM or a combination of RAM and PROM. The memory **1220** stores a variety of sensor information downloaded at the time of manufacture or during communications with a pulse oximeter, as described below.

[0065] As shown in **FIG. 11**, a modulated waveform applied to the emitter input **1201** for driving the emitters **107, 110** is described in U.S. Pat. No. 6,229,856 entitled "Method and Apparatus for Demodulating Signals in a Pulse Oximetry System" assigned to the assignee of the present application and incorporated by reference herein. In particular, a current is first applied in a forward direction with

respect to one LED 107 during a first time interval. Thereafter, no current is applied to either LED 107, 110 during a second time interval. Then, current is applied in a forward direction with respect to the other LED 110 during a third time interval. Then, no current is applied to either LED 107, 110 during a fourth time interval. Thereafter, the current is again applied in the forward direction for one LED 107 during a fifth time interval that corresponds to the first time interval. Typically, each emitter 107, 110 is active for a duty cycle of 25%, and an inactive period having a 25% duty cycle separates each active period.

[0066] As shown in FIG. 12, the serial transceiver 1240 is connected to the emitter input 1201 and provides a bi-directional data bus 1242 to the processor 1210. During a start-up, calibration, initialization or re-initialization period, an attached instrument, such as a pulse oximeter or testing device, may alter the modulated waveform described above for the purpose of transmitting information to the sensor processor 1210. That is, the emitter drive current applied to the emitter input 1201 may be modulated in a manner other than a constant 25% on and 25% off cycle so as to convey information. For example, the current waveform may be pulse position modulated (PPM) or pulse width modulated (PWM) with a bit pattern, as is well known in the art. Transmitted bit patterns may contain information such as calibration data, emitter specifications, and/or manufacturing data to name a few. The serial transceiver 1240 demodulates this data, which is then transferred over the data bus 1242 to the processor 1210, either as serial or parallel data. The processor 1210 may in turn store this information in memory 1220.

[0067] Further, the serial transceiver 1240 may also transfer data from the processor 1210 to an attached instrument. A data upload may occur during emitter "off" periods, described above, which may be the 25% duty off-cycles or specifically designated off periods timed so that the power converter 1250 is still operational. The upload may be at a voltage that is less than the turn-on voltage of either emitter 107, 110 so as to limit the required output power from the ICE 1200. Alternatively, the emitters may be disconnected during data uploads by the switches 1110 (FIG. 11). The data upload may be accomplished by any of a number of conventional serial data transfer waveforms, such as PPM or PWM to name a few.

[0068] FIG. 13 illustrates a sensor circuit 1300 incorporating an alternative embodiment of an isolation and communications element 1400. The sensor circuit 1300 has a breakable conductor 505, an emitter input 1010, a detector output port 1020, emitters 107, 110 and a detector 130 as described with respect to FIG. 11, above. In this embodiment, the ICE 1400 is connected in series between the emitter input 1010 and the emitters 107, 110 and utilizes internal switches 1420 (FIG. 14). The ICE 1400 has an instrument port 1401 and a loop port 1403, also as described with respect to FIG. 11, above. Further, the ICE 1400 has a component port 1405 that connects to the emitters 107, 110. The ICE 1400 decouples the breakable conductor 505 from the emitter input 1010 and other portions of the sensor circuit 1300, such as the detector 130, as described with respect to FIG. 11, above. The instrument port 1401 taps power from the modulated drive signal on the emitter input 1010 and provides bi-directional communications between the ICE 1400 and an attached pulse oximeter, also as described with respect to FIG. 11, above.

[0069] FIG. 14 illustrates a block diagram of an alternative embodiment of an isolation and communications ele-

ment 1400. The ICE 1400 has a processor 1210, a memory 1220, an opto-isolator driver/receiver 1230, a serial transceiver 1240, and a power converter 1250, as described with respect to FIG. 12, above. The ICE also has an internal information element 1410 and one or more internal switches 1420. In response to a breakable conductor discontinuity as signaled by the OC logic output 1232 of the optoisolator 1230, the processor 1210 generates a control output 1430 that activates the switches 1420. When activated, the switches 1420 disconnect the component port 1405 from the emitter input 1010. In this manner, the information element 1410 cannot be read by an attached pulse oximeter and/or the sensor is rendered otherwise inoperable when the breakable conductor is broken.

[0070] Other combinations, omissions, substitutions and modifications of the ICE embodiments and the ICE-sensor circuit configurations will be apparent to the skilled artisan in view of the disclosure herein. For example, the sensor circuit was described as having back-to-back emitters and a parallel connected information element all sharing a pair of connector pinouts. The ICE, however, can also be configured with a sensor circuit having emitters and an information element with only partially shared pinouts, such as common cathode or common anode configurations, or with unshared pinouts. As another example, the sensor circuit was described with switches actuated to disconnect sensor components from the sensor connector. Other devices that can be actuated to decouple one or more sensor components from the sensor connector may be used, such as high impedance capable series devices or low impedance capable parallel devices. Further, the isolation and communications element (ICE) is described in the conjunctive, it is understood that a sensor may be configured with either an isolation function or a communications element or both.

What is claimed is:

1. A sensor comprising:

a connector adapted to electrically communicate with a physiological measurement instrument;

a breakable conductor that transitions from a continuity state to a discontinuity state as the result of sensor wear; and

an isolation and communications element (ICE) having an instrument port and an electrically isolated loop port, said instrument port in communications with said connector and said loop port in communications with said breakable conductor.

2. The sensor according to claim 1 wherein:

said ICE further comprises a control output responsive to said discontinuity state,

said sensor further comprises an electrical component,

said ICE being connected in parallel with said connector and said electrical component, and

said component being operable from said instrument via said connector according to said control output.

3. The sensor according to claim 2 further comprising a switch in series between said component and said connector, said switch responsive to said control output so as to disconnect said component from said connector.

4. The sensor according to claim 3 wherein said ICE further comprises a converter which supplies DC power to

said ICE, said converter connected to said instrument port so as to draw modulated power from said instrument.

5. The sensor according to claim 3 wherein said ICE further comprises:

a processor having an input indicating said discontinuity state and providing said control output in response;

a transceiver in communications with said processor and said instrument port and adapted to transfer a plurality of data items between said instrument and said processor; and

a memory readable and writeable by said processor and adapted to store and retrieve said data items.

6. The sensor according to claim 3 wherein said ICE further comprises:

an opto-isolator driver connected to said loop port and adapted to supply a current to said breakable conductor; and

an opto-isolator receiver connected to said loop port and adapted to receive said current so as to detect said discontinuity state.

7. The sensor according to claim 1 wherein said sensor further comprises an electrical component and said ICE further comprises:

a component port in communications with said electrical component,

said ICE being connected in series between said connector and said electrical component so that said component is operable from said instrument via said connector according to said control output.

8. The sensor according to claim 6 wherein said ICE further comprises:

a switch in series between said instrument port and said component port, said switch responsive to a control signal so as to disconnect said component from said connector.

9. The sensor according to claim 7 wherein said ICE further comprises an information element, said switch connected between said instrument port and said information element so as to disconnect said information element from said connector.

10. A sensor comprising:

a connector adapted to electrically communicate with a physiological measurement instrument;

a breakable conductor configured as a current loop that becomes an open circuit as the result of sensor wear, said conductor electrically isolated from said connector; and

an electrical component operable from said instrument via said connector said electrical component rendered inoperable in response to said open circuit.

11. A sensor according to claim 9 further comprising:

a driver configured to provide a current to said breakable conductor; and

a receiver responsive to said current so as to provide a control output indicating said open circuit,

said driver and said receiver adapted to provide electrical isolation between said conductor and said connector.

12. The sensor according to claim 10 further comprising switch between said component and said connector, said switch actuated by said control output so as to disconnect said component from said connector.

13. The sensor according to claim 11 wherein said component is an information element readable by said instrument so as to activate said sensor, said switch rendering said information element unreadable when said control output indicates said open circuit.

14. A sensor method comprising the steps of:

incorporating a breakable conductor within a sensor to indicate sensor wear;

isolating said conductor from a measurement connector; and

disabling a sensor circuit in response to a discontinuity in said breakable conductor.

15. The sensor method according to claim 13 wherein said isolating step comprises the substeps of:

providing a current for said conductor from an optically isolated driver; and

detecting said current in said conductor by an optically isolated receiver.

16. The sensor method according to claim 14 wherein said disabling step comprises the substeps of:

generating an open circuit output from said receiver when said current is disrupted; and

actuating a switch in response to said open circuit output to disconnect said sensor circuit from said connector.

17. The sensor method according to claim 14 comprising the further steps of:

detecting a communications request at said connector;

actuating said switch in response to said communications request; and

downloading data from said connector to a sensor memory.

18. The sensor method according to claim 13 comprising the further step of converting a modulated drive signal to said sensor circuit into a DC supply voltage.

19. A sensor configured to connect to a measurement instrument comprising:

a conductive means for indicating sensor wear;

an optical means for isolating said conductive means from said instrument; and

a switching means for disabling a circuit portion of said sensor in response to a discontinuity in said conductive means.

20. The sensor according to claim 18 further comprising a communications means for the transfer of data between said instrument and said sensor.

21. The sensor according to claim 19 further comprising a converter means for drawing power from said instrument and supplying power to said sensor.

* * * * *

专利名称(译)	用于可重复使用的脉搏血氧饱和度传感器的隔离和通信元件		
公开(公告)号	US20030135099A1	公开(公告)日	2003-07-17
申请号	US10/351643	申请日	2003-01-24
[标]申请(专利权)人(译)	AL ALI AMMAR		
申请(专利权)人(译)	AL-ALI AMMAR		
当前申请(专利权)人(译)	摩根大通银行，NATIONAL ASSOCIATION		
[标]发明人	AL ALI AMMAR		
发明人	AL-ALI, AMMAR		
IPC分类号	A61B5/00		
CPC分类号	A61B5/14552 A61B5/6826 A61B2562/182 A61B2560/0276 A61B5/6838		
优先权	60/351784 2002-01-25 US		
其他公开文献	US6950687		
外部链接	Espacenet USPTO		

摘要(译)

传感器具有适于与生理测量仪器电连通的连接器。由传感器磨损导致由传感器结合的可破坏导体从连续状态转变为不连续状态。隔离和通信元件 (ICE) 具有仪器端口和电隔离环路端口。仪器端口与连接器通信，并且环路端口与可断裂导体通信。ICE响应于不连续状态产生控制输出，以使传感器不可操作。

