



US009956414B2

(12) **United States Patent**
Kane et al.

(10) **Patent No.:** **US 9,956,414 B2**
(45) **Date of Patent:** **May 1, 2018**

(54) **TEMPORAL CONFIGURATION OF A
MOTION SENSOR IN AN IMPLANTABLE
MEDICAL DEVICE**

(71) Applicant: **CARDIAC PACEMAKERS, INC.**, St.
Paul, MN (US)

(72) Inventors: **Michael J. Kane**, Roseville, MN (US);
William J. Linder, Golden Valley, MN
(US); **Benjamin J. Haasl**, Forest Lake,
MN (US); **Paul Huelskamp**, St. Paul,
MN (US); **Keith R. Maile**, New
Brighton, MN (US); **Ron A.
Balczewski**, Bloomington, MN (US);
Bin Mi, Plymouth, MN (US); **John D.
Hatlestad**, Maplewood, MN (US);
Allan Charles Shuros, St. Paul, MN
(US)

(73) Assignee: **CARDIAC PACEMAKERS, INC.**, St.
Paul

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 0 days. days.

(21) Appl. No.: **15/243,524**

(22) Filed: **Aug. 22, 2016**

(65) **Prior Publication Data**

US 2017/0056665 A1 Mar. 2, 2017

Related U.S. Application Data

(60) Provisional application No. 62/210,882, filed on Aug.
27, 2015.

(51) **Int. Cl.**
A61N 1/365 (2006.01)
A61N 1/368 (2006.01)

(Continued)

(52) **U.S. Cl.**
CPC **A61N 1/36542** (2013.01); **A61B 5/0452**
(2013.01); **A61B 5/1118** (2013.01);
(Continued)

(58) **Field of Classification Search**
None
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,835,864 A 9/1974 Rasor et al.
3,943,936 A 3/1976 Rasor et al.
(Continued)

FOREIGN PATENT DOCUMENTS

AU 2008279789 B2 10/2011
AU 2008329620 B2 5/2014
(Continued)

OTHER PUBLICATIONS

US 8,886,318, 11/2014, Jacobson et al. (withdrawn)
(Continued)


Primary Examiner — Brian T Gedeon

(74) *Attorney, Agent, or Firm* — Seager, Tufte &
Wickhem LLP

(57) **ABSTRACT**

Methods and devices for configuring the use of a motion
sensor in an implantable cardiac device. The electrical
signals of the patient's heart are observed and may be
correlated to the physical motion of the heart as detected by
the motion sensor of the implantable cardiac device in order
to facilitate temporal configuration of motion sensor data
collection that avoids detecting cardiac motion in favor of
overall motion of the patient.

20 Claims, 12 Drawing Sheets



- (51) **Int. Cl.**
A61N 1/375 (2006.01)
A61N 1/37 (2006.01)
A61B 5/0452 (2006.01)
A61B 5/11 (2006.01)
A61B 5/00 (2006.01)
A61N 1/372 (2006.01)
- (52) **U.S. Cl.**
 CPC *A61B 5/686* (2013.01); *A61B 5/6869* (2013.01); *A61N 1/3684* (2013.01); *A61N 1/371* (2013.01); *A61N 1/3756* (2013.01); *A61B 5/1107* (2013.01); *A61B 2562/0219* (2013.01); *A61N 1/36578* (2013.01); *A61N 1/37205* (2013.01)
- (56) **References Cited**
 U.S. PATENT DOCUMENTS
- | | | | | | |
|-------------|---------|---------------------|--------------|---------|-------------------|
| 4,142,530 A | 3/1979 | Wittkamp | 5,314,459 A | 5/1994 | Swanson et al. |
| 4,151,513 A | 4/1979 | Menken et al. | 5,318,597 A | 6/1994 | Hauck et al. |
| 4,157,720 A | 6/1979 | Greatbatch | 5,324,316 A | 6/1994 | Schulman et al. |
| RE30,366 E | 8/1980 | Rasor et al. | 5,331,966 A | 7/1994 | Bennett et al. |
| 4,250,884 A | 2/1981 | Hartlaub et al. | 5,334,222 A | 8/1994 | Salo et al. |
| 4,256,115 A | 3/1981 | Bilitch | 5,342,408 A | 8/1994 | Decoriolis et al. |
| 4,263,919 A | 4/1981 | Levin | 5,372,606 A | 12/1994 | Lang et al. |
| 4,310,000 A | 1/1982 | Lindemans | 5,376,106 A | 12/1994 | Stahmann et al. |
| 4,312,354 A | 1/1982 | Walters | 5,383,915 A | 1/1995 | Adams |
| 4,323,081 A | 4/1982 | Wiebusch | 5,388,578 A | 2/1995 | Yomtov et al. |
| 4,357,946 A | 11/1982 | Dutcher et al. | 5,404,877 A | 4/1995 | Nolan et al. |
| 4,365,639 A | 12/1982 | Goldreyer | 5,405,367 A | 4/1995 | Schulman et al. |
| 4,440,173 A | 4/1984 | Hudziak et al. | 5,411,031 A | 5/1995 | Yomtov |
| 4,476,868 A | 10/1984 | Thompson | 5,411,525 A | 5/1995 | Swanson et al. |
| 4,522,208 A | 6/1985 | Buffet | 5,411,535 A | 5/1995 | Fujii et al. |
| 4,556,063 A | 12/1985 | Thompson et al. | 5,456,691 A | 10/1995 | Snell |
| 4,562,841 A | 1/1986 | Brockway et al. | 5,466,246 A | 11/1995 | Silvian |
| 4,593,702 A | 6/1986 | Kepski et al. | 5,468,254 A | 11/1995 | Hahn et al. |
| 4,593,955 A | 6/1986 | Leiber | 5,522,866 A | 6/1996 | Fernald |
| 4,630,611 A | 12/1986 | King | 5,540,727 A | 7/1996 | Tockman et al. |
| 4,635,639 A | 1/1987 | Hakala et al. | 5,545,186 A | 8/1996 | Olson et al. |
| 4,674,508 A | 6/1987 | DeCote | 5,545,202 A | 8/1996 | Dahl et al. |
| 4,712,554 A | 12/1987 | Garson | 5,591,214 A | 1/1997 | Lu |
| 4,729,376 A | 3/1988 | DeCote | 5,620,466 A | 4/1997 | Haefner et al. |
| 4,754,753 A | 7/1988 | King | 5,634,938 A | 6/1997 | Swanson et al. |
| 4,759,366 A | 7/1988 | Callaghan | 5,662,688 A | 9/1997 | Haefner et al. |
| 4,787,389 A | 11/1988 | Tarjan | 5,674,259 A | 10/1997 | Gray |
| 4,793,353 A | 12/1988 | Borkan | 5,683,426 A | 11/1997 | Greenhut et al. |
| 4,819,662 A | 4/1989 | Heil et al. | 5,683,432 A | 11/1997 | Goedeke et al. |
| 4,858,610 A | 8/1989 | Callaghan et al. | 5,720,770 A | 2/1998 | Nappholz et al. |
| 4,886,064 A | 12/1989 | Strandberg | 5,728,154 A | 3/1998 | Crossett et al. |
| 4,928,688 A | 5/1990 | Mower | 5,741,314 A | 4/1998 | Daly et al. |
| 4,967,746 A | 11/1990 | Vandegriff | 5,741,315 A | 4/1998 | Lee et al. |
| 4,987,897 A | 1/1991 | Funke | 5,752,976 A | 5/1998 | Duffin et al. |
| 4,989,602 A | 2/1991 | Sholder et al. | 5,752,977 A | 5/1998 | Grevious et al. |
| 5,012,806 A | 5/1991 | De Bellis | 5,755,736 A | 5/1998 | Gillberg et al. |
| 5,036,849 A | 8/1991 | Hauck et al. | 5,759,199 A | 6/1998 | Snell et al. |
| 5,058,581 A | 10/1991 | Silvian | 5,774,501 A | 6/1998 | Halpern et al. |
| 5,078,134 A | 1/1992 | Heilman et al. | 5,792,202 A | 8/1998 | Rueter |
| 5,109,845 A | 5/1992 | Yuuchi et al. | 5,792,203 A | 8/1998 | Schroepel |
| 5,113,859 A | 5/1992 | Funke | 5,792,205 A | 8/1998 | Alt et al. |
| 5,117,824 A | 6/1992 | Keimel et al. | 5,792,208 A | 8/1998 | Gray |
| 5,127,401 A | 7/1992 | Grevious et al. | 5,814,089 A | 9/1998 | Stokes et al. |
| 5,133,353 A | 7/1992 | Hauser | 5,827,216 A | 10/1998 | Igo et al. |
| 5,144,950 A | 9/1992 | Stoop et al. | 5,836,985 A | 11/1998 | Goyal et al. |
| 5,170,784 A | 12/1992 | Ramon et al. | 5,836,987 A | 11/1998 | Baumann et al. |
| 5,179,945 A | 1/1993 | Van Hofwegen et al. | 5,842,977 A | 12/1998 | Lesho et al. |
| 5,193,539 A | 3/1993 | Schulman et al. | 5,855,593 A | 1/1999 | Olson et al. |
| 5,193,540 A | 3/1993 | Schulman et al. | 5,873,894 A | 2/1999 | Vandegriff et al. |
| 5,241,961 A | 9/1993 | Henry | 5,891,184 A | 4/1999 | Lee et al. |
| 5,243,977 A | 9/1993 | Trabucco et al. | 5,897,586 A | 4/1999 | Molina |
| 5,269,326 A | 12/1993 | Verrier | 5,899,876 A | 5/1999 | Flower |
| 5,284,136 A | 2/1994 | Hauck et al. | 5,899,928 A | 5/1999 | Sholder et al. |
| 5,300,107 A | 4/1994 | Stokes et al. | 5,919,214 A | 7/1999 | Ciciarelli et al. |
| 5,301,677 A | 4/1994 | Hsung | 5,935,078 A | 8/1999 | Feierbach |
| 5,312,439 A | 5/1994 | Loeb | 5,941,906 A | 8/1999 | Barreras et al. |
| 5,313,953 A | 5/1994 | Yomtov et al. | 5,954,757 A | 9/1999 | Gray |
| | | | 5,978,713 A | 11/1999 | Prutchi et al. |
| | | | 5,991,660 A | 11/1999 | Goyal |
| | | | 5,999,848 A | 12/1999 | Gord et al. |
| | | | 5,999,857 A | 12/1999 | Weijand et al. |
| | | | 6,026,320 A | 2/2000 | Carlson et al. |
| | | | 6,044,298 A | 3/2000 | Salo et al. |
| | | | 6,044,300 A | 3/2000 | Gray |
| | | | 6,055,454 A | 4/2000 | Heemels |
| | | | 6,073,050 A | 6/2000 | Griffith |
| | | | 6,076,016 A | 6/2000 | Feierbach |
| | | | 6,080,187 A | 6/2000 | Alt et al. |
| | | | 6,083,248 A | 7/2000 | Thompson |
| | | | 6,106,551 A | 8/2000 | Crossett et al. |
| | | | 6,115,636 A | 9/2000 | Ryan |
| | | | 6,141,581 A | 10/2000 | Olson et al. |
| | | | 6,141,588 A | 10/2000 | Cox et al. |
| | | | 6,141,592 A | 10/2000 | Pauly |
| | | | 6,144,879 A | 11/2000 | Gray |
| | | | 6,162,195 A | 12/2000 | Igo et al. |
| | | | 6,164,284 A | 12/2000 | Schulman et al. |
| | | | 6,167,310 A | 12/2000 | Grevious |
| | | | 6,208,894 B1 | 3/2001 | Schulman et al. |

(56)

References Cited

U.S. PATENT DOCUMENTS

6,211,799	B1	4/2001	Post et al.	6,763,269	B2	7/2004	Cox
6,221,011	B1	4/2001	Bardy	6,778,860	B2	8/2004	Ostroff et al.
6,240,316	B1	5/2001	Richmond et al.	6,788,971	B1	9/2004	Sloman et al.
6,240,317	B1	5/2001	Villaseca et al.	6,788,974	B2	9/2004	Bardy et al.
6,256,534	B1	7/2001	Dahl	6,804,558	B2	10/2004	Haller et al.
6,259,947	B1	7/2001	Olson et al.	6,847,844	B2	1/2005	Sun et al.
6,266,558	B1	7/2001	Gozani et al.	6,871,095	B2	3/2005	Stahmann et al.
6,266,567	B1	7/2001	Ishikawa et al.	6,878,112	B2	4/2005	Linberg et al.
6,270,457	B1	8/2001	Bardy	6,885,889	B2	4/2005	Chinchoy
6,272,377	B1	8/2001	Sweeney et al.	6,892,094	B2	5/2005	Ousdigian et al.
6,277,072	B1	8/2001	Bardy	6,897,788	B2	5/2005	Khair et al.
6,280,380	B1	8/2001	Bardy	6,904,315	B2	6/2005	Panken et al.
6,285,907	B1	9/2001	Kramer et al.	6,922,592	B2	7/2005	Thompson et al.
6,292,698	B1	9/2001	Duffin et al.	6,931,282	B2	8/2005	Esler
6,295,473	B1	9/2001	Rosar	6,934,585	B1	8/2005	Schloss et al.
6,298,271	B1	10/2001	Weijand	6,957,107	B2	10/2005	Rogers et al.
6,312,378	B1	11/2001	Bardy	6,978,176	B2	12/2005	Lattouf
6,315,721	B2	11/2001	Schulman et al.	6,985,773	B2	1/2006	Von Arx et al.
6,336,903	B1	1/2002	Bardy	7,003,350	B2	2/2006	Denker et al.
6,345,202	B2	2/2002	Richmond et al.	7,006,864	B2	2/2006	Echt et al.
6,351,667	B1	2/2002	Godie	7,013,178	B2	3/2006	Reinke et al.
6,351,669	B1	2/2002	Hartley et al.	7,027,871	B2	4/2006	Burnes et al.
6,353,759	B1	3/2002	Hartley et al.	7,050,849	B2	5/2006	Echt et al.
6,358,203	B2	3/2002	Bardy	7,060,031	B2	6/2006	Webb et al.
6,361,780	B1	3/2002	Ley et al.	7,063,693	B2	6/2006	Guenst
6,368,284	B1	4/2002	Bardy	7,082,336	B2	7/2006	Ransbury et al.
6,371,922	B1	4/2002	Baummann et al.	7,085,606	B2	8/2006	Flach et al.
6,398,728	B1	6/2002	Bardy	7,110,824	B2	9/2006	Amundson et al.
6,400,982	B2	6/2002	Sweeney et al.	7,120,504	B2	10/2006	Osypka
6,400,990	B1	6/2002	Silvian	7,139,613	B2	11/2006	Reinke et al.
6,409,674	B1	6/2002	Brockway et al.	7,142,912	B2	11/2006	Wagner et al.
6,411,848	B2	6/2002	Kramer et al.	7,146,225	B2	12/2006	Guenst et al.
6,424,865	B1	7/2002	Ding	7,146,226	B2	12/2006	Lau et al.
6,434,429	B1	8/2002	Kraus et al.	7,149,581	B2	12/2006	Goedeke
6,438,410	B2	8/2002	Hsu et al.	7,149,588	B2	12/2006	Lau et al.
6,438,417	B1	8/2002	Rockwell et al.	7,158,839	B2	1/2007	Lau
6,438,421	B1	8/2002	Stahmann et al.	7,162,307	B2	1/2007	Patrias
6,440,066	B1	8/2002	Bardy	7,164,952	B2	1/2007	Lau et al.
6,441,747	B1	8/2002	Khair et al.	7,177,700	B1	2/2007	Cox
6,442,426	B1	8/2002	Kroll	7,181,505	B2	2/2007	Haller et al.
6,442,432	B2	8/2002	Lee	7,184,830	B2	2/2007	Echt et al.
6,443,891	B1	9/2002	Grevious	7,186,214	B2	3/2007	Ness
6,445,953	B1	9/2002	Bulkes et al.	7,191,015	B2	3/2007	Lamson et al.
6,453,200	B1	9/2002	Koslar	7,200,437	B1	4/2007	Nabutovsky et al.
6,459,929	B1	10/2002	Hopper et al.	7,200,439	B2	4/2007	Zdeblick et al.
6,470,215	B1	10/2002	Kraus et al.	7,206,423	B1	4/2007	Feng et al.
6,471,645	B1	10/2002	Warkentin et al.	7,209,790	B2	4/2007	Thompson et al.
6,480,745	B2	11/2002	Nelson et al.	7,212,871	B1	5/2007	Morgan
6,487,443	B2	11/2002	Olson et al.	7,226,440	B2	6/2007	Gelfand et al.
6,490,487	B1	12/2002	Kraus et al.	7,228,183	B2	6/2007	Sun et al.
6,507,755	B1	1/2003	Gozani et al.	7,236,821	B2	6/2007	Cates et al.
6,507,759	B1	1/2003	Prutchi et al.	7,236,829	B1	6/2007	Farazi et al.
6,512,940	B1	1/2003	Brabec et al.	7,254,448	B2	8/2007	Almendinger et al.
6,522,915	B1	2/2003	Ceballos et al.	7,260,436	B2	8/2007	Kilgore et al.
6,526,311	B2	2/2003	Begemann	7,270,669	B1	9/2007	Sra
6,542,775	B2	4/2003	Ding et al.	7,272,448	B1	9/2007	Morgan et al.
6,553,258	B2	4/2003	Stahmann et al.	7,277,755	B1	10/2007	Falkenberg et al.
6,561,975	B1	5/2003	Pool et al.	7,280,872	B1	10/2007	Mosesov et al.
6,564,807	B1	5/2003	Schulman et al.	7,288,096	B2	10/2007	Chin
6,574,506	B2	6/2003	Kramer et al.	7,289,847	B1	10/2007	Gill et al.
6,584,352	B2	6/2003	Combs et al.	7,289,852	B2	10/2007	Helfinstine et al.
6,597,948	B1	7/2003	Rockwell et al.	7,289,853	B1	10/2007	Campbell et al.
6,597,951	B2	7/2003	Kramer et al.	7,289,855	B2	10/2007	Nghiem et al.
6,622,046	B2	9/2003	Fraley et al.	7,302,294	B2	11/2007	Kamath et al.
6,628,985	B2	9/2003	Sweeney et al.	7,305,266	B1	12/2007	Kroll
6,647,292	B1	11/2003	Bardy et al.	7,310,556	B2	12/2007	Bulkes
6,666,844	B1	12/2003	Igo et al.	7,319,905	B1	1/2008	Morgan et al.
6,689,117	B2	2/2004	Sweeney et al.	7,333,853	B2	2/2008	Mazar et al.
6,690,959	B2	2/2004	Thompson	7,336,994	B2	2/2008	Hettrick et al.
6,704,602	B2	3/2004	Berg et al.	7,347,819	B2	3/2008	Lebel et al.
6,718,212	B2	4/2004	Parry et al.	7,366,572	B2	4/2008	Heruth et al.
6,721,597	B1	4/2004	Bardy et al.	7,373,207	B2	5/2008	Lattouf
6,738,670	B1	5/2004	Almendinger et al.	7,384,403	B2	6/2008	Sherman
6,749,566	B2	6/2004	Russ	7,386,342	B1	6/2008	Falkenberg et al.
6,758,810	B2	7/2004	Lebel et al.	7,392,090	B2	6/2008	Sweeney et al.
				7,406,105	B2	7/2008	DelMain et al.
				7,406,349	B2	7/2008	Seeberger et al.
				7,410,497	B2	8/2008	Hastings et al.
				7,425,200	B2	9/2008	Brockway et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

7,433,739 B1	10/2008	Salys et al.	7,894,915 B1	2/2011	Chitre et al.
7,496,409 B2	2/2009	Greenhut et al.	7,899,537 B1	3/2011	Kroll et al.
7,496,410 B2	2/2009	Heil	7,899,541 B2	3/2011	Cowan et al.
7,502,652 B2	3/2009	Gaunt et al.	7,899,542 B2	3/2011	Cowan et al.
7,512,448 B2	3/2009	Malick et al.	7,899,554 B2	3/2011	Williams et al.
7,515,969 B2	4/2009	Tockman et al.	7,901,360 B1	3/2011	Yang et al.
7,526,342 B2	4/2009	Chin et al.	7,904,170 B2	3/2011	Harding
7,529,589 B2	5/2009	Williams et al.	7,907,993 B2	3/2011	Ghanem et al.
7,532,933 B2	5/2009	Hastings et al.	7,920,928 B1	4/2011	Yang et al.
7,536,222 B2	5/2009	Bardy et al.	7,925,343 B1	4/2011	Min et al.
7,539,541 B2	5/2009	Quiles et al.	7,930,040 B1	4/2011	Kelsch et al.
7,544,197 B2	6/2009	Kelsch et al.	7,937,135 B2	5/2011	Ghanem et al.
7,558,631 B2	7/2009	Cowan et al.	7,937,148 B2	5/2011	Jacobson
7,565,195 B1	7/2009	Kroll et al.	7,937,161 B2	5/2011	Hastings et al.
7,584,002 B2	9/2009	Burnes et al.	7,941,214 B2	5/2011	Kleckner et al.
7,590,455 B2	9/2009	Heruth et al.	7,945,333 B2	5/2011	Jacobson
7,606,621 B2	10/2009	Briskin et al.	7,946,997 B2	5/2011	Hübinette
7,610,088 B2	10/2009	Chinchoy	7,949,404 B2	5/2011	Hill
7,610,092 B2	10/2009	Cowan et al.	7,949,405 B2	5/2011	Feher
7,610,099 B2	10/2009	Almendinger et al.	7,953,493 B2	5/2011	Fowler et al.
7,610,104 B2	10/2009	Kaplan et al.	7,962,202 B2	6/2011	Bhunja
7,616,991 B2	11/2009	Mann et al.	7,974,702 B1	7/2011	Fain et al.
7,617,001 B2	11/2009	Penner et al.	7,979,136 B2	7/2011	Young et al.
7,617,007 B2	11/2009	Williams et al.	7,983,753 B2	7/2011	Severin
7,630,767 B1	12/2009	Poore et al.	3,010,209 A1	8/2011	Jacobson
7,634,313 B1	12/2009	Kroll et al.	7,991,467 B2	8/2011	Markowitz et al.
7,637,867 B2	12/2009	Zdeblick	7,991,471 B2	8/2011	Ghanem et al.
7,640,060 B2	12/2009	Zdeblick	7,996,087 B2	8/2011	Cowan et al.
7,647,109 B2	1/2010	Hastings et al.	8,000,791 B2	8/2011	Sunagawa et al.
7,650,186 B2	1/2010	Hastings et al.	8,000,807 B2	8/2011	Morris et al.
7,657,311 B2	2/2010	Bardy et al.	8,001,975 B2	8/2011	DiSilvestro et al.
7,668,596 B2	2/2010	Von Arx et al.	8,002,700 B2	8/2011	Ferek-Petric et al.
7,691,047 B2	4/2010	Ferrari	8,019,419 B1	9/2011	Panescu et al.
7,702,392 B2	4/2010	Echt et al.	8,019,434 B2	9/2011	Quiles et al.
7,713,194 B2	5/2010	Zdeblick	8,027,727 B2	9/2011	Freeberg
7,713,195 B2	5/2010	Zdeblick	8,027,729 B2	9/2011	Sunagawa et al.
7,729,783 B2	6/2010	Michels et al.	8,032,219 B2	10/2011	Neumann et al.
7,734,333 B2	6/2010	Ghanem et al.	8,036,743 B2	10/2011	Savage et al.
7,734,343 B2	6/2010	Ransbury et al.	8,046,079 B2	10/2011	Bange et al.
7,738,958 B2	6/2010	Zdeblick et al.	8,046,080 B2	10/2011	Von Arx et al.
7,738,964 B2	6/2010	Von Arx et al.	8,050,297 B2	11/2011	Delmain et al.
7,742,812 B2	6/2010	Ghanem et al.	8,050,759 B2	11/2011	Stegemann et al.
7,742,816 B2	6/2010	Masoud et al.	8,050,774 B2	11/2011	Kveen et al.
7,742,822 B2	6/2010	Masoud et al.	8,055,345 B2	11/2011	Li et al.
7,743,151 B2	6/2010	Vallapureddy et al.	8,055,350 B2	11/2011	Roberts
7,747,335 B2	6/2010	Williams	8,060,212 B1	11/2011	Rios et al.
7,751,881 B2	7/2010	Cowan et al.	8,065,018 B2	11/2011	Haubrich et al.
7,758,521 B2	7/2010	Morris et al.	8,073,542 B2	12/2011	Doerr
7,761,150 B2	7/2010	Ghanem et al.	8,078,278 B2	12/2011	Penner
7,761,164 B2	7/2010	Verhoef et al.	8,078,283 B2	12/2011	Cowan et al.
7,765,001 B2	7/2010	Echt et al.	8,095,123 B2	1/2012	Gray
7,769,452 B2	8/2010	Ghanem et al.	8,102,789 B2	1/2012	Rosar et al.
7,778,699 B1 *	8/2010	Ferrise	8,103,359 B2	1/2012	Reddy
		A61B 5/0432	8,103,361 B2	1/2012	Moser
		600/513	8,112,148 B2	2/2012	Giftakis et al.
7,792,588 B2	9/2010	Harding	8,114,021 B2	2/2012	Robertson et al.
7,797,059 B1	9/2010	Bornzin et al.	8,121,680 B2	2/2012	Falkenberg et al.
7,801,596 B2	9/2010	Fischell et al.	8,123,684 B2	2/2012	Zdeblick
7,809,438 B2	10/2010	Echt et al.	8,126,545 B2	2/2012	Flach et al.
7,840,281 B2	11/2010	Kveen et al.	8,131,334 B2	3/2012	Lu et al.
7,844,348 B2	11/2010	Swoyer et al.	8,140,161 B2	3/2012	Willerton et al.
7,846,088 B2	12/2010	Ness	8,150,521 B2	4/2012	Crowley et al.
7,848,815 B2	12/2010	Briskin et al.	8,160,672 B2	4/2012	Kim et al.
7,848,823 B2	12/2010	Drasler et al.	8,160,702 B2	4/2012	Mann et al.
7,860,455 B2	12/2010	Fukumoto et al.	8,160,704 B2	4/2012	Freeberg
7,871,433 B2	1/2011	Lattouf	8,165,694 B2	4/2012	Carbanaru et al.
7,877,136 B1	1/2011	Moffitt et al.	8,175,715 B1	5/2012	Cox
7,877,142 B2	1/2011	Moaddeb et al.	8,180,451 B2	5/2012	Hickman et al.
7,881,798 B2	2/2011	Miesel et al.	8,185,213 B2	5/2012	Kveen et al.
7,881,810 B1	2/2011	Chitre et al.	8,187,161 B2	5/2012	Li et al.
7,890,173 B2	2/2011	Briskin et al.	8,204,595 B2	6/2012	Pianca et al.
7,890,181 B2	2/2011	Denzene et al.	8,204,605 B2	6/2012	Hastings et al.
7,890,192 B1	2/2011	Kelsch et al.	8,209,014 B2	6/2012	Doerr
7,894,894 B2	2/2011	Stadler et al.	8,214,043 B2	7/2012	Matos
7,894,907 B2	2/2011	Cowan et al.	8,224,244 B2	7/2012	Kim et al.
7,894,910 B2	2/2011	Cowan et al.	8,233,985 B2	7/2012	Bulkes et al.
			8,265,748 B2	9/2012	Liu et al.
			8,265,757 B2	9/2012	Mass et al.
			8,280,521 B2	10/2012	Haubrich et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

8,285,387	B2	10/2012	Utsi et al.	8,738,147	B2	5/2014	Hastings et al.
8,290,598	B2	10/2012	Boon et al.	8,744,572	B1	6/2014	Greenhut et al.
8,290,600	B2	10/2012	Hastings et al.	8,747,314	B2	6/2014	Stahmann et al.
8,295,939	B2	10/2012	Jacobson	8,755,884	B2	6/2014	Demmer et al.
8,301,254	B2	10/2012	Mosesov et al.	8,758,365	B2	6/2014	Bonner et al.
8,315,701	B2	11/2012	Cowan et al.	8,774,572	B2	7/2014	Hamamoto
8,315,708	B2	11/2012	Berthelsdorf et al.	8,781,605	B2	7/2014	Bornzin et al.
8,321,021	B2	11/2012	Kisker et al.	8,788,035	B2	7/2014	Jacobson
8,321,036	B2	11/2012	Brockway et al.	8,788,053	B2	7/2014	Jacobson
8,332,036	B2	12/2012	Hastings et al.	8,798,740	B2	8/2014	Samade et al.
8,335,563	B2	12/2012	Stessman	8,798,745	B2	8/2014	Jacobson
8,335,568	B2	12/2012	Heruth et al.	8,798,762	B2	8/2014	Fain et al.
8,340,750	B2	12/2012	Prakash et al.	8,798,770	B2	8/2014	Reddy
8,340,780	B2	12/2012	Hastings et al.	8,805,505	B1	8/2014	Roberts
8,352,025	B2	1/2013	Jacobson	8,805,528	B2	8/2014	Corndorf
8,352,028	B2	1/2013	Wenger	8,812,109	B2	8/2014	Blomqvist et al.
8,352,038	B2	1/2013	Mao et al.	8,818,504	B2	8/2014	Bodner et al.
8,359,098	B2	1/2013	Lund et al.	8,831,747	B1	9/2014	Min et al.
8,364,276	B2	1/2013	Willis	8,855,789	B2	10/2014	Jacobson
8,369,959	B2	2/2013	Meskens	8,868,186	B2	10/2014	Kroll
8,369,962	B2	2/2013	Abrahamson	8,886,339	B2	11/2014	Faltys et al.
8,380,320	B2	2/2013	Spital	8,903,500	B2	12/2014	Smith et al.
8,386,051	B2	2/2013	Rys	8,903,513	B2	12/2014	Ollivier
8,391,981	B2	3/2013	Mosesov	8,914,131	B2	12/2014	Bornzin et al.
8,391,990	B2	3/2013	Smith et al.	8,923,795	B2	12/2014	Makdissi et al.
8,406,874	B2	3/2013	Liu et al.	8,923,963	B2	12/2014	Bonner et al.
8,406,886	B2	3/2013	Gaunt et al.	8,938,300	B2	1/2015	Rosero
8,412,352	B2	4/2013	Griswold et al.	8,942,806	B2	1/2015	Sheldon et al.
8,417,340	B2	4/2013	Goossen	8,958,892	B2	2/2015	Khairkhahan et al.
8,417,341	B2	4/2013	Freeberg	8,977,358	B2	3/2015	Ewert et al.
8,423,149	B2	4/2013	Hennig	8,989,873	B2	3/2015	Locsin
8,428,722	B2	4/2013	Verhoef et al.	8,996,109	B2	3/2015	Karst et al.
8,433,402	B2	4/2013	Ruben et al.	9,002,467	B2	4/2015	Smith et al.
8,433,409	B2	4/2013	Johnson et al.	9,008,776	B2	4/2015	Cowan et al.
8,433,420	B2	4/2013	Bange et al.	9,008,777	B2	4/2015	Dianaty et al.
8,447,412	B2	5/2013	Dal Molin et al.	9,014,818	B2	4/2015	Deterre et al.
8,452,413	B2	5/2013	Young et al.	9,017,341	B2	4/2015	Bornzin et al.
8,457,740	B2	6/2013	Osche	9,020,611	B2	4/2015	Khairkhahan et al.
8,457,742	B2	6/2013	Jacobson	9,037,262	B2	5/2015	Regnier et al.
8,457,761	B2	6/2013	Wariar	9,042,984	B2	5/2015	Demmer et al.
8,478,407	B2	7/2013	Demmer et al.	9,072,911	B2	7/2015	Hastings et al.
8,478,408	B2	7/2013	Hastings et al.	9,072,913	B2	7/2015	Jacobson
8,478,431	B2	7/2013	Griswold et al.	9,155,882	B2	10/2015	Grubac et al.
8,504,156	B2	8/2013	Bonner et al.	9,168,372	B2	10/2015	Fain
8,509,910	B2	8/2013	Sowder et al.	9,168,380	B1	10/2015	Greenhut et al.
8,515,559	B2	8/2013	Roberts et al.	9,168,383	B2	10/2015	Jacobson et al.
8,527,068	B2	9/2013	Ostroff	9,180,285	B2	11/2015	Moore et al.
8,532,790	B2	9/2013	Griswold	9,192,774	B2	11/2015	Jacobson
8,541,131	B2	9/2013	Lund et al.	9,205,225	B2	12/2015	Khairkhahan et al.
8,543,205	B2	9/2013	Ostroff	9,216,285	B1	12/2015	Boling et al.
8,547,248	B2	10/2013	Zdeblick et al.	9,216,293	B2	12/2015	Berthiaume et al.
8,548,605	B2	10/2013	Ollivier	9,216,298	B2	12/2015	Jacobson
8,554,333	B2	10/2013	Wu et al.	9,227,077	B2	1/2016	Jacobson
8,565,878	B2	10/2013	Allavatam et al.	9,238,145	B2	1/2016	Wenzel et al.
8,565,882	B2	10/2013	Matos	9,242,102	B2	1/2016	Khairkhahan et al.
8,565,897	B2	10/2013	Regnier et al.	9,242,113	B2	1/2016	Smith et al.
8,571,678	B2	10/2013	Wang	9,248,300	B2	2/2016	Rys et al.
8,577,327	B2	11/2013	Makdissi et al.	9,265,436	B2	2/2016	Min et al.
8,588,926	B2	11/2013	Moore et al.	9,265,962	B2	2/2016	Dianaty et al.
8,612,002	B2	12/2013	Faltys et al.	9,272,155	B2	3/2016	Ostroff
8,615,310	B2	12/2013	Khairkhahan et al.	9,278,218	B2	3/2016	Karst et al.
8,626,294	B2	1/2014	Sheldon et al.	9,278,229	B1	3/2016	Reinke et al.
8,634,908	B2	1/2014	Cowan	9,283,381	B2	3/2016	Grubac et al.
8,634,912	B2	1/2014	Bornzin et al.	9,283,382	B2	3/2016	Berthiaume et al.
8,634,919	B1	1/2014	Hou et al.	9,289,612	B1	3/2016	Sambelashvili et al.
8,639,335	B2	1/2014	Peichel et al.	9,302,115	B2	4/2016	Molin et al.
8,644,934	B2	2/2014	Hastings et al.	9,333,364	B2	5/2016	Echt et al.
8,649,859	B2	2/2014	Smith et al.	9,358,387	B2	6/2016	Suwito et al.
8,670,842	B1	3/2014	Bornzin et al.	9,358,400	B2	6/2016	Jacobson
8,676,319	B2	3/2014	Knoll	9,364,675	B2	6/2016	Deterre et al.
8,676,335	B2	3/2014	Katoozi et al.	9,370,663	B2	6/2016	Moulder
8,700,173	B2	4/2014	Edlund	9,375,580	B2	6/2016	Bonner et al.
8,700,181	B2	4/2014	Bornzin et al.	9,375,581	B2	6/2016	Baru et al.
8,705,599	B2	4/2014	dal Molin et al.	9,381,365	B2	7/2016	Kibler et al.
8,718,773	B2	5/2014	Willis et al.	9,393,424	B2	7/2016	Demmer et al.
				9,393,436	B2	7/2016	Doerr
				9,399,139	B2	7/2016	Demmer et al.
				9,399,140	B2	7/2016	Cho et al.
				9,409,033	B2	8/2016	Jacobson

(56)

References Cited

U.S. PATENT DOCUMENTS

9,427,594 B1	8/2016	Bornzin et al.	2006/0064149 A1	3/2006	Belacazar et al.
9,433,368 B2	9/2016	Stahmann et al.	2006/0085039 A1	4/2006	Hastings et al.
9,433,780 B2	9/2016	R�gnier et al.	2006/0085041 A1	4/2006	Hastings et al.
2002/0032470 A1	3/2002	Linberg	2006/0085042 A1	4/2006	Hastings et al.
2002/0035376 A1	3/2002	Bardy et al.	2006/0095078 A1	5/2006	Tronnes
2002/0035377 A1	3/2002	Bardy et al.	2006/0106442 A1	5/2006	Richardson et al.
2002/0035378 A1	3/2002	Bardy et al.	2006/0116746 A1	6/2006	Chin
2002/0035380 A1	3/2002	Rissmann et al.	2006/0135999 A1	6/2006	Bodner et al.
2002/0035381 A1	3/2002	Bardy et al.	2006/0136004 A1	6/2006	Cowan et al.
2002/0042629 A1	4/2002	Bardy et al.	2006/0161061 A1	7/2006	Echt et al.
2002/0042630 A1	4/2002	Bardy et al.	2006/0200002 A1	9/2006	Guenst
2002/0042634 A1	4/2002	Bardy et al.	2006/0206151 A1	9/2006	Lu
2002/0049475 A1	4/2002	Bardy et al.	2006/0212079 A1	9/2006	Routh et al.
2002/0052636 A1	5/2002	Bardy et al.	2006/0241701 A1	10/2006	Markowitz et al.
2002/0068958 A1	6/2002	Bardy et al.	2006/0241705 A1	10/2006	Neumann et al.
2002/0072773 A1	6/2002	Bardy et al.	2006/0247672 A1	11/2006	Vidlund et al.
2002/0082665 A1	6/2002	Haller et al.	2006/0259088 A1	11/2006	Pastore et al.
2002/0091414 A1	7/2002	Bardy et al.	2006/0265018 A1	11/2006	Smith et al.
2002/0095196 A1	7/2002	Linberg	2007/0004979 A1	1/2007	Wojciechowicz et al.
2002/0099423 A1	7/2002	Berg et al.	2007/0027508 A1	2/2007	Cowan
2002/0103510 A1	8/2002	Bardy et al.	2007/0078490 A1	4/2007	Cowan et al.
2002/0107545 A1	8/2002	Rissmann et al.	2007/0088394 A1	4/2007	Jacobson
2002/0107546 A1	8/2002	Ostroff et al.	2007/0088396 A1	4/2007	Jacobson
2002/0107547 A1	8/2002	Erlinger et al.	2007/0088397 A1	4/2007	Jacobson
2002/0107548 A1	8/2002	Bardy et al.	2007/0088398 A1	4/2007	Jacobson
2002/0107549 A1	8/2002	Bardy et al.	2007/0088405 A1	4/2007	Jacobson
2002/0107559 A1	8/2002	Sanders et al.	2007/0118054 A1 *	5/2007	Pinhas A61B 5/1104
2002/0120299 A1	8/2002	Ostroff et al.			600/587
2002/0173830 A1	11/2002	Starkweather et al.	2007/0135882 A1	6/2007	Drasler et al.
2002/0193846 A1	12/2002	Pool et al.	2007/0135883 A1	6/2007	Drasler et al.
2003/0009203 A1	1/2003	Lebel et al.	2007/0150037 A1	6/2007	Hastings et al.
2003/0028082 A1	2/2003	Thompson	2007/0150038 A1	6/2007	Hastings et al.
2003/0041866 A1	3/2003	Linberg et al.	2007/0156190 A1	7/2007	Cinbis
2003/0088278 A1	5/2003	Bardy et al.	2007/0219525 A1	9/2007	Gelfand et al.
2003/0097153 A1	5/2003	Bardy et al.	2007/0219590 A1	9/2007	Hastings et al.
2003/0114908 A1	6/2003	Flach	2007/0225545 A1	9/2007	Ferrari
2003/0144701 A1	7/2003	Mehra et al.	2007/0233206 A1	10/2007	Frikart et al.
2003/0187460 A1	10/2003	Chin et al.	2007/0239244 A1	10/2007	Morgan et al.
2003/0187461 A1	10/2003	Chin	2007/0255327 A1	11/2007	Cho et al.
2004/0024435 A1	2/2004	Leckrone et al.	2007/0255376 A1	11/2007	Michels et al.
2004/0087938 A1	5/2004	Leckrone et al.	2007/0276444 A1	11/2007	Gelbart et al.
2004/0088035 A1	5/2004	Guenst et al.	2007/0293900 A1	12/2007	Sheldon et al.
2004/0102830 A1	5/2004	Williams	2007/0293904 A1	12/2007	Gelbart et al.
2004/0127959 A1	7/2004	Amundson et al.	2008/0004663 A1	1/2008	Jorgenson
2004/0147969 A1	7/2004	Mann et al.	2008/0021505 A1	1/2008	Hastings et al.
2004/0147973 A1	7/2004	Hauser	2008/0021519 A1	1/2008	De Geest et al.
2004/0167558 A1	8/2004	Igo et al.	2008/0021532 A1	1/2008	Kveen et al.
2004/0167587 A1	8/2004	Thompson	2008/0065185 A1	3/2008	Worley
2004/0172071 A1	9/2004	Bardy et al.	2008/0071318 A1	3/2008	Brooke et al.
2004/0172077 A1	9/2004	Chinchoy	2008/0109054 A1	5/2008	Hastings et al.
2004/0172104 A1	9/2004	Berg et al.	2008/0119911 A1	5/2008	Rosero
2004/0176817 A1	9/2004	Wahlstrand et al.	2008/0130670 A1	6/2008	Kim et al.
2004/0176818 A1	9/2004	Wahlstrand et al.	2008/0154322 A1	6/2008	Jackson et al.
2004/0176830 A1	9/2004	Fang	2008/0228234 A1	9/2008	Stancer
2004/0186529 A1	9/2004	Bardy et al.	2008/0234771 A1	9/2008	Chinchoy et al.
2004/0204673 A1	10/2004	Flaherty	2008/0243217 A1	10/2008	Wildon
2004/0210292 A1	10/2004	Bardy et al.	2008/0269814 A1	10/2008	Rosero
2004/0210293 A1	10/2004	Bardy et al.	2008/0269825 A1	10/2008	Chinchoy et al.
2004/0210294 A1	10/2004	Bardy et al.	2008/0275518 A1	11/2008	Ghanem et al.
2004/0215308 A1	10/2004	Bardy et al.	2008/0275519 A1	11/2008	Ghanem et al.
2004/0220626 A1	11/2004	Wagner	2008/0288039 A1	11/2008	Reddy
2004/0220639 A1	11/2004	Mulligan et al.	2008/0294208 A1	11/2008	Willis et al.
2004/0249431 A1	12/2004	Ransbury et al.	2008/0294210 A1	11/2008	Rosero
2004/0267303 A1	12/2004	Guenst	2008/0306359 A1	12/2008	Zdeblick et al.
2005/0061320 A1	3/2005	Lee et al.	2009/0018599 A1	1/2009	Hastings et al.
2005/0070962 A1	3/2005	Echt et al.	2009/0024180 A1	1/2009	Kisker et al.
2005/0102003 A1	5/2005	Grabek et al.	2009/0036941 A1	2/2009	Corbucci
2005/0149138 A1	7/2005	Min et al.	2009/0048646 A1	2/2009	Katoozi et al.
2005/0165466 A1	7/2005	Morris et al.	2009/0062895 A1	3/2009	Stahmann et al.
2005/0182465 A1	8/2005	Ness	2009/0082827 A1	3/2009	Kveen et al.
2005/0203410 A1	9/2005	Jenkins	2009/0082828 A1	3/2009	Ostroff
2005/0283208 A1	12/2005	Von Arx et al.	2009/0088813 A1	4/2009	Brockway et al.
2006/0052829 A1	3/2006	Sun et al.	2009/0131907 A1	5/2009	Chin et al.
2006/0052830 A1	3/2006	Spinelli et al.	2009/0135886 A1	5/2009	Robertson et al.
2006/0064135 A1	3/2006	Brockway	2009/0143835 A1	6/2009	Pastore et al.
			2009/0171408 A1	7/2009	Solem
			2009/0171414 A1	7/2009	Kelly et al.
			2009/0204170 A1	8/2009	Hastings et al.
			2009/0210024 A1	8/2009	M

(56)

References Cited

U.S. PATENT DOCUMENTS

2009/0216292 A1	8/2009	Pless et al.	2012/0158111 A1	6/2012	Khairkhahan et al.
2009/0234407 A1	9/2009	Hastings et al.	2012/0165827 A1	6/2012	Khairkhahan et al.
2009/0234411 A1	9/2009	Sambelashvili et al.	2012/0172690 A1	7/2012	Anderson et al.
2009/0275998 A1	11/2009	Burnes et al.	2012/0172891 A1	7/2012	Lee
2009/0275999 A1	11/2009	Burnes et al.	2012/0172892 A1	7/2012	Grubac et al.
2009/0299447 A1	12/2009	Jensen et al.	2012/0172942 A1	7/2012	Berg
2010/0013668 A1	1/2010	Kantervik	2012/0197350 A1	8/2012	Roberts et al.
2010/0016911 A1	1/2010	Willis et al.	2012/0197373 A1	8/2012	Khairkhahan et al.
2010/0023085 A1	1/2010	Wu et al.	2012/0215285 A1	8/2012	Tahmasian et al.
2010/0030061 A1	2/2010	Canfield et al.	2012/0232565 A1	9/2012	Kveen et al.
2010/0030327 A1	2/2010	Chatel	2012/0277600 A1	11/2012	Greenhut
2010/0042108 A1	2/2010	Hibino	2012/0277606 A1	11/2012	Ellingson et al.
2010/0056871 A1	3/2010	Govari et al.	2012/0283795 A1	11/2012	Stancer et al.
2010/0063375 A1	3/2010	Kassab et al.	2012/0283807 A1	11/2012	Deterre et al.
2010/0063562 A1	3/2010	Cowan et al.	2012/0290025 A1	11/2012	Keimel
2010/0094367 A1	4/2010	Sen	2012/0296381 A1	11/2012	Matos
2010/0114209 A1	5/2010	Krause et al.	2012/0303082 A1	11/2012	Dong et al.
2010/0125281 A1	5/2010	Jacobson et al.	2012/0316613 A1	12/2012	Keefe et al.
2010/0168761 A1	7/2010	Kassab et al.	2013/0012151 A1	1/2013	Hankins
2010/0168819 A1	7/2010	Freeberg	2013/0023975 A1	1/2013	Locsin
2010/0198288 A1	8/2010	Ostroff	2013/0035748 A1	2/2013	Bonner et al.
2010/0198304 A1	8/2010	Wang	2013/0041422 A1	2/2013	Jacobson
2010/0217367 A1	8/2010	Belson	2013/0053908 A1	2/2013	Smith et al.
2010/0228308 A1	9/2010	Cowan et al.	2013/0053915 A1	2/2013	Holmstrom et al.
2010/0234924 A1	9/2010	Willis	2013/0053921 A1	2/2013	Bonner et al.
2010/0241185 A1	9/2010	Mahapatra et al.	2013/0060298 A1	3/2013	Splett et al.
2010/0249729 A1	9/2010	Morris et al.	2013/0066169 A1	3/2013	Rys et al.
2010/0286744 A1	11/2010	Echt et al.	2013/0072770 A1	3/2013	Rao et al.
2010/0312309 A1	12/2010	Harding	2013/0079798 A1	3/2013	Tran et al.
2011/0022113 A1	1/2011	Zdeblick et al.	2013/0079861 A1	3/2013	Reinert et al.
2011/0071586 A1	3/2011	Jacobson	2013/0085350 A1	4/2013	Schugt et al.
2011/0077708 A1	3/2011	Ostroff	2013/0085403 A1	4/2013	Gunderson et al.
2011/0112600 A1	5/2011	Cowan et al.	2013/0085550 A1	4/2013	Polefko et al.
2011/0118588 A1	5/2011	Komblau et al.	2013/0096649 A1	4/2013	Martin et al.
2011/0118810 A1	5/2011	Cowan et al.	2013/0103047 A1	4/2013	Steingisser et al.
2011/0137187 A1	6/2011	Yang et al.	2013/0103109 A1	4/2013	Jacobson
2011/0144720 A1	6/2011	Cowan et al.	2013/0110008 A1	5/2013	Bourget et al.
2011/0152970 A1	6/2011	Jollota et al.	2013/0110127 A1	5/2013	Bornzin et al.
2011/0160565 A1	6/2011	Stubbs et al.	2013/0110192 A1	5/2013	Tran et al.
2011/0160801 A1	6/2011	Markowitz et al.	2013/0110219 A1	5/2013	Bornzin et al.
2011/0160806 A1	6/2011	Lyden et al.	2013/0116529 A1	5/2013	Min et al.
2011/0166620 A1	7/2011	Cowan et al.	2013/0116738 A1	5/2013	Samade et al.
2011/0166621 A1	7/2011	Cowan et al.	2013/0116740 A1	5/2013	Bornzin et al.
2011/0184491 A1	7/2011	Kivi	2013/0116741 A1	5/2013	Bornzin et al.
2011/0190835 A1	8/2011	Brockway et al.	2013/0123872 A1	5/2013	Bornzin et al.
2011/0208260 A1	8/2011	Jacobson	2013/0123875 A1	5/2013	Varady et al.
2011/0218587 A1	9/2011	Jacobson	2013/0131591 A1	5/2013	Berthiaume et al.
2011/0230734 A1	9/2011	Fain et al.	2013/0131693 A1	5/2013	Berthiaume et al.
2011/0237967 A1	9/2011	Moore et al.	2013/0138006 A1	5/2013	Bornzin et al.
2011/0245890 A1	10/2011	Brisben et al.	2013/0150695 A1	6/2013	Biela et al.
2011/0251660 A1	10/2011	Griswold	2013/0196703 A1	8/2013	Masoud et al.
2011/0251662 A1	10/2011	Griswold et al.	2013/0197609 A1	8/2013	Moore et al.
2011/0270099 A1	11/2011	Ruben et al.	2013/0231710 A1	9/2013	Jacobson
2011/0270339 A1	11/2011	Murray, III et al.	2013/0238072 A1	9/2013	Deterre et al.
2011/0270340 A1	11/2011	Pellegrini et al.	2013/0238073 A1	9/2013	Makdissi et al.
2011/0276102 A1	11/2011	Cohen	2013/0253342 A1	9/2013	Griswold et al.
2011/0282423 A1	11/2011	Jacobson	2013/0253343 A1	9/2013	Waldhauser et al.
2012/0004527 A1	1/2012	Thompson et al.	2013/0253344 A1	9/2013	Griswold et al.
2012/0029323 A1	2/2012	Zhao	2013/0253345 A1	9/2013	Griswold et al.
2012/0041508 A1	2/2012	Rouso et al.	2013/0253346 A1	9/2013	Griswold et al.
2012/0059433 A1	3/2012	Cowan et al.	2013/0253347 A1	9/2013	Griswold et al.
2012/0059436 A1	3/2012	Fontaine et al.	2013/0261497 A1	10/2013	Pertijis et al.
2012/0078322 A1	3/2012	Dal Molin et al.	2013/0265144 A1	10/2013	Banna et al.
2012/0089198 A1	4/2012	Ostroff	2013/0268042 A1	10/2013	Hastings et al.
2012/0093245 A1	4/2012	Makdissi et al.	2013/0274828 A1	10/2013	Willis
2012/0095521 A1	4/2012	Hintz	2013/0274847 A1	10/2013	Ostroff
2012/0095539 A1	4/2012	Khairkhahan et al.	2013/0282070 A1	10/2013	Cowan et al.
2012/0101540 A1	4/2012	O'Brien et al.	2013/0282073 A1	10/2013	Cowan et al.
2012/0101553 A1	4/2012	Reddy	2013/0303872 A1	11/2013	Taff et al.
2012/0109148 A1	5/2012	Bonner et al.	2013/0324825 A1	12/2013	Ostroff et al.
2012/0109149 A1	5/2012	Bonner et al.	2013/0325081 A1	12/2013	Karst et al.
2012/0109236 A1	5/2012	Jacobson et al.	2013/0345770 A1	12/2013	Dianaty et al.
2012/0109259 A1	5/2012	Bond et al.	2014/0012344 A1	1/2014	Hastings et al.
2012/0116489 A1	5/2012	Khairkhahan et al.	2014/0018876 A1	1/2014	Ostroff
2012/0150251 A1	6/2012	Giftakis et al.	2014/0018877 A1	1/2014	Demmer et al.
			2014/0031836 A1	1/2014	Ollivier
			2014/0039570 A1	2/2014	Carroll et al.
			2014/0039591 A1	2/2014	Drasler et al.
			2014/0043146 A1	2/2014	Makdissi et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2014/0046395 A1 2/2014 Regnier et al.
 2014/0046420 A1 2/2014 Moore et al.
 2014/0058240 A1 2/2014 Mothilal et al.
 2014/0058494 A1 2/2014 Ostroff et al.
 2014/0074114 A1 3/2014 Khairkahan et al.
 2014/0074186 A1 3/2014 Faltys et al.
 2014/0094891 A1 4/2014 Pare et al.
 2014/0100627 A1 4/2014 Min
 2014/0107723 A1 4/2014 Hou et al.
 2014/0121719 A1 5/2014 Bonner et al.
 2014/0121720 A1 5/2014 Bonner et al.
 2014/0121722 A1 5/2014 Sheldon et al.
 2014/0128935 A1 5/2014 Kumar et al.
 2014/0135865 A1 5/2014 Hastings et al.
 2014/0142648 A1 5/2014 Smith et al.
 2014/0148675 A1 5/2014 Nordstrom et al.
 2014/0148815 A1 5/2014 Wenzel et al.
 2014/0155950 A1 6/2014 Hastings et al.
 2014/0169162 A1 6/2014 Romano et al.
 2014/0172060 A1 6/2014 Bornzin et al.
 2014/0180306 A1 6/2014 Grubac et al.
 2014/0180366 A1 6/2014 Edlund
 2014/0207149 A1 7/2014 Hastings et al.
 2014/0207210 A1 7/2014 Willis et al.
 2014/0214104 A1 7/2014 Greenhut et al.
 2014/0222098 A1 8/2014 Baru et al.
 2014/0222109 A1 8/2014 Moulder
 2014/0228913 A1 8/2014 Molin et al.
 2014/0236172 A1 8/2014 Hastings et al.
 2014/0243848 A1 8/2014 Auricchio et al.
 2014/0257324 A1 9/2014 Fain
 2014/0276929 A1 9/2014 Foster et al.
 2014/0303704 A1 10/2014 Suwito et al.
 2014/0309706 A1 10/2014 Jacobson
 2014/0379041 A1 12/2014 Foster
 2015/0025612 A1 1/2015 Haasl et al.
 2015/0039041 A1 2/2015 Smith et al.
 2015/0051609 A1 2/2015 Schmidt et al.
 2015/0051610 A1 2/2015 Schmidt et al.
 2015/0051611 A1 2/2015 Schmidt et al.
 2015/0051612 A1 2/2015 Schmidt et al.
 2015/0051613 A1 2/2015 Schmidt et al.
 2015/0051614 A1 2/2015 Schmidt et al.
 2015/0051615 A1 2/2015 Schmidt et al.
 2015/0051616 A1 2/2015 Haasl et al.
 2015/0051682 A1 2/2015 Schmidt et al.
 2015/0057520 A1 2/2015 Foster et al.
 2015/0057558 A1 2/2015 Stahmann et al.
 2015/0057721 A1 2/2015 Stahmann et al.
 2015/0088155 A1 3/2015 Stahmann et al.
 2015/0105836 A1 4/2015 Bonner et al.
 2015/0173655 A1 6/2015 Demmer et al.
 2015/0190638 A1 7/2015 Smith et al.
 2015/0196756 A1 7/2015 Stahmann et al.
 2015/0196757 A1 7/2015 Stahmann et al.
 2015/0196758 A1 7/2015 Stahmann et al.
 2015/0196769 A1 7/2015 Stahmann et al.
 2015/0217119 A1 8/2015 Nikolski et al.
 2015/0221898 A1 8/2015 Chi et al.
 2015/0224315 A1 8/2015 Stahmann
 2015/0224320 A1 8/2015 Stahmann
 2015/0258345 A1 9/2015 Smith et al.
 2015/0290468 A1 10/2015 Zhang
 2015/0297905 A1 10/2015 Greenhut et al.
 2015/0297907 A1 10/2015 Zhang
 2015/0305637 A1 10/2015 Greenhut et al.
 2015/0305638 A1 10/2015 Zhang
 2015/0305639 A1 10/2015 Greenhut et al.
 2015/0305640 A1 10/2015 Reinke et al.
 2015/0305641 A1 10/2015 Stadler et al.
 2015/0305642 A1 10/2015 Reinke et al.
 2015/0306374 A1 10/2015 Seifert et al.
 2015/0306375 A1 10/2015 Marshall et al.
 2015/0306406 A1 10/2015 Crutchfield et al.
 2015/0306407 A1 10/2015 Crutchfield et al.

2015/0306408 A1 10/2015 Greenhut et al.
 2015/0321016 A1 11/2015 O'Brien et al.
 2015/0328459 A1 11/2015 Chin et al.
 2016/0015322 A1 1/2016 Anderson et al.
 2016/0023000 A1 1/2016 Cho et al.
 2016/0030757 A1 2/2016 Jacobson
 2016/0033177 A1 2/2016 Barot et al.
 2016/0051823 A1 2/2016 Maile et al.
 2016/0121127 A1 5/2016 Klimovitch et al.
 2016/0121128 A1 5/2016 Fishler et al.
 2016/0121129 A1 5/2016 Persson et al.
 2016/0213919 A1 7/2016 Suwito et al.
 2016/0213937 A1 7/2016 Reinke et al.
 2016/0213939 A1 7/2016 Carney et al.
 2016/0228026 A1 8/2016 Jackson

FOREIGN PATENT DOCUMENTS

AU 2014203793 A1 7/2014
 CA 1003904 A1 1/1977
 CN 202933393 U 5/2013
 EP 0362611 A1 4/1990
 EP 503823 A2 9/1992
 EP 1702648 A2 9/2006
 EP 1904166 B1 6/2011
 EP 2433675 B1 1/2013
 EP 2441491 B1 1/2013
 EP 2452721 B1 11/2013
 EP 1948296 B1 1/2014
 EP 2662113 A3 1/2014
 EP 2471452 B1 12/2014
 EP 2760541 B1 5/2016
 EP 2833966 B1 5/2016
 JP 2000051373 A 2/2000
 JP 2002502640 A 1/2002
 JP 2004512105 A 4/2004
 JP 2005508208 A 3/2005
 JP 2005245215 A 9/2005
 JP 2008540040 A 11/2008
 JP 5199867 B2 2/2013
 WO 9500202 A1 1/1995
 WO 9636134 A1 11/1996
 WO 9826840 A1 6/1998
 WO 9939767 A1 8/1999
 WO 0234330 A2 1/2003
 WO 02098282 A2 5/2003
 WO 2005000206 A3 4/2005
 WO 2005042089 A1 5/2005
 WO 2006086435 A3 8/2006
 WO 2006113659 A1 10/2006
 WO 2006124833 A3 5/2007
 WO 2007075974 A2 7/2007
 WO 2009006531 A1 1/2009
 WO 2012054102 A1 4/2012
 WO 2013080038 A2 6/2013
 WO 2013098644 A3 8/2013
 WO 2013184787 A1 12/2013

OTHER PUBLICATIONS

Hachisuka et al., "Development and Performance Analysis of an Intra-Body Communication Device," The 12th International Conference on Solid State Sensors, Actuators and Microsystems, vol. 4A1.3, pp. 1722-1725, 2003.
 Seyed et al., "A Survey on Intrabody Communications for Body Area Network Application," IEEE Transactions on Biomedical Engineering, vol. 60(8): 2067-2079, 2013.
 Wegmüller, "Intra-Body Communication for Biomedical Sensor Networks," Diss. ETH, No. 17323, 1-173, 2007.
 Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, dated Jan. 29, 2016, 15 pages.
 Spickler et al., "Totally Self-Contained Intracardiac Pacemaker," Journal of Electrocardiology, vol. 3(3&4): 324-331, 1970.
 "Instructions for Use System 1, Leadless Cardiac Pacemaker (LCP) and Delivery Catheter," Nanostim Leadless Pacemakers, pp. 1-28, 2013.

(56)

References Cited

OTHER PUBLICATIONS

Invitation to Pay Additional Fees and, Where Applicable, Protest Fee, dated Dec. 9, 2016.

International Search Report and Written Opinion dated Feb. 6, 2017 for International Application No. PCT/US2016/048353.

* cited by examiner





FIG. 1






FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12

1

TEMPORAL CONFIGURATION OF A MOTION SENSOR IN AN IMPLANTABLE MEDICAL DEVICE

CROSS REFERENCE TO RELATED APPLICATIONS

The present application claims the benefit of and priority to U.S. Provisional Patent Application Ser. No. 62/210,882, filed Aug. 27, 2015, the disclosure of which is incorporated herein by reference.

TECHNICAL FIELD

The present disclosure generally relates to systems, devices, and methods for treating medical conditions using an implantable device, and more particularly, to systems, devices, and methods which include or use a motion sensor to detect a patient's level of activity.

BACKGROUND

Pacing instruments can be used to treat patients suffering from various heart conditions that result in a reduced ability of the heart to deliver sufficient amounts of blood to a patient's body. These heart conditions may lead to rapid, irregular, and/or inefficient heart contractions. To help alleviate some of these conditions, various devices (e.g., pacemakers, defibrillators, etc.) have been implanted in a patient's body. Such devices may monitor and provide electrical stimulation to the heart to help the heart operate in a more normal, efficient and/or safe manner. In some cases, a patient may have multiple implanted devices.

Motion detectors have been used in some pacemakers and other implantable devices to obtain a measure of the activity level of the patient. For example, rate adaptive cardiac pacemakers may adjust the rate at which the patient's heart is paced up or down in response to detected motion of the patient. By so doing, the pacemaker is able to adapt to the activity level of the patient, allowing a more active lifestyle than could be achieved without rate adaptive pacing. New and alternative approaches to the use of motion sensors are desired.

OVERVIEW

In some embodiments the present invention relates to a leadless cardiac pacemaker (LCP) or other implantable cardiac device having a motion sensor for detecting motion of the patient. The standard implant for pacemakers has long been the transvenous pacemaker, having a canister housing operational circuitry typically implanted in the upper chest of the patient and a lead which traverses the vasculature to the interior of the heart, with electrodes attached to the heart to facilitate therapy delivery and cardiac signal sensing. Such devices included a motion sensor in the canister, placed outside the ribs on the patient's chest in most examples.

For certain newer generation devices including the LCP, the entire product, including the motion sensor, may be placed inside or in close proximity to the heart. However, such placement means that the motion sensor may detect motion of the heart when it beats in addition to motion caused by bodily movement of the patient. In several embodiments the present invention is directed toward methods and devices that use the temporal patterns of cardiac movement to avoid detecting cardiac motion in place of bodily motion.

2

This overview is intended to provide an overview of subject matter of the present patent application. It is not intended to provide an exclusive or exhaustive explanation of the invention. The detailed description is included to provide further information about the present patent application.

BRIEF DESCRIPTION OF THE DRAWINGS

In the drawings, which are not necessarily drawn to scale, like numerals may describe similar components in different views. Like numerals having different letter suffixes may represent different instances of similar components. The drawings illustrate generally, by way of example, but not by way of limitation, various embodiments discussed in the present document.

FIG. 1 is a schematic block diagram of an illustrative leadless cardiac pacemaker (LCP) according to one illustrative embodiment of the present disclosure;

FIG. 2 is a graphic showing cardiac electrical events and intracardiac pressure and volume measurements on a single timeline;

FIGS. 3-6 show several data flow arrangements for illustrative motion sensors;

FIGS. 7-11 show several illustrative process flow diagrams; and

FIG. 12 shows a patient having an implantable medical device system in the heart.

DETAILED DESCRIPTION

This disclosure describes systems, devices, and methods for delivering electrical stimulation to a heart in a rate adaptive manner. Healthy people's bodies generally adjust the rate at which their hearts beat in response to higher or lower metabolic needs, for example during exercise or in response to various external stimuli. However, some people develop diseases or conditions which affect their bodies' abilities to cause their hearts to contract in an effective manner. Accordingly, devices in accordance with the present disclosure may be implanted in such people. In some instances, the implanted devices may deliver electrical stimulation on an on-going basis and adjust the rate of delivered electrical stimulation in accordance with sensed physiological parameters indicative of increased metabolic needs.

FIG. 1 is similar to FIG. 1 of commonly assigned and U.S. Provisional Patent Application 62/128,340, the disclosure of which is incorporated herein by reference as showing and describing numerous additional details which may be included in the methods, systems and devices discussed herein.

More specifically, FIG. 1 is a conceptual schematic block diagram of an exemplary leadless cardiac pacemaker (LCP) that may be implanted on the heart or within a chamber of the heart and may operate to sense physiological signals and parameters and deliver one or more types of electrical stimulation therapy to the heart of the patient. Example electrical stimulation therapy may include bradycardia pacing, rate responsive pacing therapy, cardiac resynchronization therapy (CRT), anti-tachycardia pacing (ATP) therapy and/or the like. As can be seen in FIG. 1, LCP 100 may be a compact device with all components housed within LCP 100 or directly on housing 120. In some instances, LCP 100 may include communication module 102, pulse generator module 104, electrical sensing module 106, mechanical sensing module 108, processing module 110, energy storage

module **112**, and electrodes **114**. In some examples (not shown), an optional lead or tether may be attached to an implantable device similar to LCP **100** to provide an additional electrode, extended antenna functionality, to couple to a second such implantable device, or to prevent migration.

As depicted in FIG. 1, LCP **100** may include electrodes **114**, which can be secured relative to housing **120** and electrically exposed to tissue and/or blood surrounding LCP **100**. Electrodes **114** may generally conduct electrical signals to and from LCP **100** and the surrounding tissue and/or blood. Such electrical signals can include communication signals, electrical stimulation pulses, and intrinsic cardiac electrical signals, to name a few. Intrinsic cardiac electrical signals may include electrical signals generated by the heart and may be represented by the cardiac electrogram (EGM), if observed on or in the heart, or the electrocardiogram (ECG), if observed at some distance from the heart.

Electrodes **114** may include one or more biocompatible conductive materials such as various metals or alloys that are known to be safe for implantation within a human body. In some instances, electrodes **114** may be generally disposed on either end of LCP **100** and may be in electrical communication with one or more of modules **102**, **104**, **106**, **108**, and **110**. In embodiments where electrodes **114** are secured directly to housing **120**, an insulating material may electrically isolate the electrodes **114** from adjacent electrodes, housing **120**, and/or other parts of LCP **100**. In some instances, some or all of electrodes **114** may be spaced from housing **120** and connected to housing **120** and/or other components of LCP **100** through connecting wires. In such instances, the electrodes **114** may be placed on a tail (not shown) that extends out away from the housing **120**. As shown in FIG. 1, in some embodiments, LCP **100** may include electrodes **114'**. Electrodes **114'** may be in addition to electrodes **114**, or may replace one or more of electrodes **114**. Electrodes **114'** may be similar to electrodes **114** except that electrodes **114'** are disposed on the sides of LCP **100**. In some cases, electrodes **114'** may increase the number of electrodes by which LCP **100** may deliver communication signals and/or electrical stimulation pulses, and/or may sense intrinsic cardiac electrical signals, communication signals, and/or electrical stimulation pulses.

Electrodes **114** and/or **114'** may assume any of a variety of sizes and/or shapes, and may be spaced at any of a variety of spacings. For example, electrodes **114** may have an outer diameter of two to twenty millimeters (mm). In other embodiments, electrodes **114** and/or **114'** may have a diameter of two, three, five, seven millimeters (mm), or any other suitable diameter, dimension and/or shape. Example lengths for electrodes **114** and/or **114'** may include, for example, one, three, five, ten millimeters (mm), or any other suitable length. As used herein, the length is a dimension of electrodes **114** and/or **114'** that extends away from the outer surface of the housing **120**. In some instances, at least some of electrodes **114** and/or **114'** may be spaced from one another by a distance of twenty, thirty, forty, fifty millimeters (mm), or any other suitable spacing. The electrodes **114** and/or **114'** of a single device may have different sizes with respect to each other, and the spacing and/or lengths of the electrodes on the device may or may not be uniform.

In the embodiment shown, communication module **102** may be electrically coupled to electrodes **114** and/or **114'** and may be configured to deliver communication pulses to tissues of the patient for communicating with other devices such as sensors, programmers, other medical devices, and/or the like. Communication signals, as used herein, may be any modulated signal that conveys information to another

device, either by itself or in conjunction with one or more other modulated signals. In some embodiments, communication signals may be limited to sub-threshold signals that do not result in capture of the heart yet still convey information. The communication signals may be delivered to another device that is located either external or internal to the patient's body. In some instances, the communication may take the form of distinct communication pulses separated by various amounts of time. In some of these cases, the timing between successive pulses may convey information. Communication module **102** may additionally be configured to sense for communication signals delivered by other devices, which may be located external or internal to the patient's body.

Communication module **102** may communicate to help accomplish one or more desired functions. Some example functions include delivering sensed data, using communicated data for determining occurrences of events such as arrhythmias, coordinating delivery of electrical stimulation therapy, and/or other functions. In some cases, LCP **100** may use communication signals to communicate raw information, processed information, messages and/or commands, and/or other data. Raw information may include information such as sensed electrical signals (e.g. a sensed EGM), signals gathered from coupled sensors, and the like. In some embodiments, the processed information may include signals that have been filtered using one or more signal processing techniques. Processed information may also include parameters and/or events that are determined by the LCP **100** and/or another device, such as a determined heart rate, timing of determined heartbeats, timing of other determined events, determinations of threshold crossings, expirations of monitored time periods, activity level parameters, blood-oxygen parameters, blood pressure parameters, heart sound parameters, and the like. Messages and/or commands may include instructions or the like directing another device to take action, notifications of imminent actions of the sending device, requests for reading from the receiving device, requests for writing data to the receiving device, information messages, and/or other messages commands.

In at least some embodiments, communication module **102** (or LCP **100**) may further include switching circuitry to selectively connect one or more of electrodes **114** and/or **114'** to communication module **102** in order to select which electrodes **114** and/or **114'** that communication module **102** delivers communication pulses. It is contemplated that communication module **102** may be communicating with other devices via conducted signals, radio frequency (RF) signals, optical signals, acoustic signals, inductive coupling, and/or any other suitable communication methodology. Where communication module **102** generates electrical communication signals, communication module **102** may include one or more capacitor elements and/or other charge storage devices to aid in generating and delivering communication signals. In the embodiment shown, communication module **102** may use energy stored in energy storage module **112** to generate the communication signals. In at least some examples, communication module **102** may include a switching circuit that is connected to energy storage module **112** and, with the switching circuitry, may connect energy storage module **112** to one or more of electrodes **114/114'** to generate the communication signals.

As shown in FIG. 1, a pulse generator module **104** may be electrically connected to one or more of electrodes **114** and/or **114'**. Pulse generator module **104** may be configured to generate electrical stimulation pulses and deliver the electrical stimulation pulses to tissues of a patient via one or

more of the electrodes **114** and/or **114'** to provide electrical stimulation therapies such as bradycardia pacing, ATP, CRT, cardioversion or defibrillation.

The LCP **100** may vary the rate at which pulse generator **104** generates the electrical stimulation pulses, for example in rate adaptive pacing. These are just some examples. When used to treat other ailments, the pulse generator module **104** may generate electrical stimulation pulses suitable for neurostimulation or neuromodulation therapy or the like.

Pulse generator module **104** may include one or more capacitor elements and/or other charge storage devices to aid in generating and delivering appropriate electrical stimulation pulses. In the embodiment shown, pulse generator module **104** may use energy stored in energy storage module **112** to generate the electrical stimulation pulses. In some examples, pulse generator module **104** may include a switching circuit that is connected to energy storage module **112** and may connect energy storage module **112** to one or more of electrodes **114/114'** to generate electrical stimulation pulses.

Pulse generator module **104** may include the capability to modify the electrical stimulation pulses, such as by adjusting the pulse width and/or amplitude of the electrical stimulation pulses. When pacing the heart, this may help tailor the electrical stimulation pulses to capture the heart a particular patient, sometimes with reduced battery usage. For neurostimulation therapy, adjusting the pulse width and/or amplitude may help tailor the therapy for a particular application and/or help make the therapy more effective for a particular patient.

In some embodiments, LCP **100** may include an electrical sensing module **106** and mechanical sensing module **108**. Electrical sensing module **106** may be configured to sense intrinsic cardiac electrical signals conducted from electrodes **114** and/or **114'** to electrical sensing module **106**. For example, electrical sensing module **106** may be electrically connected to one or more electrodes **114** and/or **114'** and electrical sensing module **106** may be configured to receive cardiac electrical signals conducted through electrodes **114** and/or **114'** via a sensor amplifier or the like. In some embodiments, the cardiac electrical signals may represent local information from the chamber in which LCP **100** is implanted. For instance, if LCP **100** is implanted within a ventricle of the heart, cardiac electrical signals sensed by LCP **100** through electrodes **114** and/or **114'** may represent ventricular cardiac electrical signals.

Mechanical sensing module **108** may include, or be electrically connected to, various sensors, such as accelerometers, blood pressure sensors, heart sound sensors, piezoelectric sensors, blood-oxygen sensors, and/or other sensors which measure one or more physiological parameters of the heart and/or patient. Mechanical sensing module **108** may gather signals from the sensors indicative of the various physiological parameters. Both electrical sensing module **106** and mechanical sensing module **108** may be connected to processing module **110** and may provide signals representative of the sensed cardiac electrical signals and/or physiological signals to processing module **110**. Although described with respect to FIG. 1 as separate sensing modules, in some embodiments, electrical sensing module **106** and mechanical sensing module **108** may be combined into a single module. In at least some examples, LCP **100** may only include one of electrical sensing module **106** and mechanical sensing module **108**. In some cases, any combination of the processing module **110**, electrical sensing module **106**, mechanical sensing module **108**, communica-

tion module **102**, pulse generator module **104** and/or energy storage module may be considered a controller of the LCP **100**.

The mechanical sensing module may include, for example, a micro-electro-mechanical system (MEMS) based motion sensor. This may include a 1, 2 or 3 dimensional motion sensor and may take any of numerous forms known in the art. Some examples may include a micro-machine size vibrating element that varies an electrical parameter when motion impacts it. To facilitate sensing, the motion sensor can be turned "on," requiring current drain, and the output can then be sampled to generate an output. Keeping the motion sensor "on" all the time may drain battery sourced current unnecessarily, and so duty cycling is performed to minimize current draw in some embodiments.

Processing module **110** may be configured to direct the operation of LCP **100**. For example, processing module **110** may be configured to receive cardiac electrical signals from electrical sensing module **106** and/or physiological signals from mechanical sensing module **108**. Based on the received signals, processing module **110** may determine, for example, occurrences and types of arrhythmias. Processing module **110** may further receive information from communication module **102**. In some embodiments, processing module **110** may additionally use such received information to determine occurrences and types of arrhythmias. However, in other embodiments, LCP **100** may use the received information instead of the signals received from electrical sensing module **106** and/or mechanical sensing module **108**—for instance if the received information is deemed to be more accurate than the signals received from electrical sensing module **106** and/or mechanical sensing module **108** or if electrical sensing module **106** and/or mechanical sensing module **108** have been disabled or omitted from LCP **100**.

After determining therapy is needed, processing module **110** may control pulse generator module **104** to generate electrical stimulation pulses in accordance with one or more electrical stimulation therapy regimens. For example, processing module **110** may control pulse generator module **104** to generate pacing pulses with varying parameters and in different sequences to effectuate one or more electrical stimulation therapies. As one example, in controlling pulse generator module **104** to deliver bradycardia pacing therapy, processing module **110** may control pulse generator module **104** to deliver pacing pulses designed to capture the heart of the patient at a regular interval to help prevent the heart of a patient from falling below a predetermined threshold.

In some embodiments, processing module **110** may further control communication module **102** to send information to other devices. For example, processing module **110** may control communication module **102** to generate one or more communication signals for communicating with other devices of a system of devices. For instance, processing module **110** may control communication module **102** to generate communication signals in particular pulse sequences, where the specific sequences convey different information. Communication module **102** may also receive communication signals for potential action by processing module **110**.

In some embodiments, processing module **110** may include a pre-programmed chip, such as a very-large-scale integration (VLSI) chip or an application specific integrated circuit (ASIC). In such embodiments, the chip may be pre-programmed with control logic in order to control the operation of LCP **100**. By using a pre-programmed chip, processing module **110** may use less power than other programmable circuits while able to maintain basic func-

tionality, thereby potentially increasing the battery life of LCP 100. In other instances, processing module 110 may include a programmable microprocessor or the like. Such a programmable microprocessor may allow a user to adjust the control logic of LCP 100 after manufacture, thereby allowing for greater flexibility of LCP 100 than when using a pre-programmed chip.

Processing module 110, in additional embodiments, may include a memory circuit and processing module 110 may store information on and read information from the memory circuit. In other embodiments, LCP 100 may include a separate memory circuit (not shown) that is in communication with processing module 110, such that processing module 110 may read and write information to and from the separate memory circuit. The memory circuit, whether part of processing module 110 or separate from processing module 110, may be volatile memory, non-volatile memory, or a combination of volatile memory and non-volatile memory.

Collectively the processing module 110, mechanical sensing module 108, electrical sensing module 106, pulse generator module 104, and communication module 102 may be referred to as the operational circuitry of the LCP. In some examples the individual modules 102, 104, 106, 108, 110 may be subcomponents on a single hybrid or circuit board, or even within a single VSLI or ASIC, or may be spread across several hybrids, circuit boards, VSLI or ASIC components. In some examples, certain elements of processing module 110 are performed in the digital domain—such as determining whether to deliver therapy and operating the communication module when awoken for such a purpose—while others are performed in the analog domain—such as ongoing monitoring of the received electrical and/or motion signal until a significant perturbation of either signal or a timeout occurs, allowing the digital circuitry to stay in a low power state by duty cycling to sleep. On whole, the operational circuitry may be configured to perform the various methods shown herein and below claimed, by reference to memory and/or by operation of application-specific circuitry and/or ASIC chips.

Energy storage module 112 may provide a power source to LCP 100 for its operations. In some embodiments, energy storage module 112 may be a non-rechargeable lithium-based battery. In other embodiments, the non-rechargeable battery may be made from other suitable materials. In some embodiments, energy storage module 112 may include a rechargeable battery. For embodiments with a rechargeable battery, there may additionally be a recharging circuit using, for example, a coil that receives an electrical or magnetic field to facilitate recharging transcutaneously, as is well known in the art. In other embodiments, biological energy capture devices may be used to take advantage of energy that can be generated using the cardiac or other biological motion. In still other embodiments, energy storage module 112 may include other types of energy storage devices such as super capacitors.

To implant LCP 100 inside a patient's body, an operator (e.g., a physician, clinician, etc.), may fix LCP 100 to the cardiac tissue of the patient's heart. To facilitate fixation, LCP 100 may include one or more anchors 116. The one or more anchors 116 are shown schematically in FIG. 1. The one or more anchors 116 may include any number of fixation or anchoring mechanisms. For example, one or more anchors 116 may include one or more pins, staples, threads, screws, helix, tines, and/or the like. In some embodiments, although not shown, one or more anchors 116 may include threads on its external surface that may run along at least a

partial length of an anchor member. The threads may provide friction between the cardiac tissue and the anchor to help fix the anchor member within the cardiac tissue. In some cases, the one or more anchors 116 may include an anchor member that has a cork-screw shape that can be screwed into the cardiac tissue. In other embodiments, anchor 116 may include other structures such as barbs, spikes, or the like to facilitate engagement with the surrounding cardiac tissue.

In some examples, LCP 100 may be configured to be implanted on a patient's heart or within a chamber of the patient's heart. For instance, LCP 100 may be implanted within any of a left atrium, right atrium, left ventricle, coronary sinus, or right ventricle of a patient's heart. By being implanted within a specific chamber, LCP 100 may be able to sense cardiac electrical signals originating or emanating from the specific chamber that other devices may not be able to sense with such resolution. Where LCP 100 is configured to be implanted on a patient's heart, LCP 100 may be configured to be implanted on or adjacent to one of the chambers of the heart, or on or adjacent to a path along which intrinsically generated cardiac electrical signals generally follow. In these examples, LCP 100 may also have an enhanced ability to sense localized intrinsic cardiac electrical signals and deliver localized electrical stimulation therapy.

In some instances, LCP 100 may be configured to deliver rate-adaptive pacing therapy to a patient's heart. For instance, LCP 100 may be configured to deliver electrical stimulation pulses to the heart of the patient on an on-going basis to help ensure that the patient's heart contracts in a safe and effective manner. LCP 100 may additionally sense one or more signals, for example using electrical sensing module 106 and/or mechanical sensing module 108, and determine, based on the sensed one or more signals, whether to change the rate of delivery of the electrical stimulation pulses.

For example, based on the sensed one or more signals, LCP 100 may determine that there is less of a need for cardiac output, and may decrease the rate of delivery of the electrical stimulation pulses. In other instances, based on the one or more sensed signals, LCP 100 may determine that there is a need for increased cardiac output, and may increase the rate of delivery of the electrical stimulation pulses. Adjusting the rate of delivery of the electrical stimulation pulses based on the sensed one or more signals may extend the battery life of LCP 100 by only requiring higher rates of delivery of electrical stimulation pulses when the sensed one or more signals indicate there is a need for increased cardiac output. Additionally, adjusting the rate of delivery of the electrical stimulation pulses may increase a comfort level of the patient by more closely matching the rate of delivery of electrical stimulation pulses with the cardiac output need of the patient.

Where LCP 100 adjusts the rate of delivery of electrical stimulation pulses based on the sensed one or more signals, LCP 100 may in some cases determine a respiration rate based on the sensed one or more signals. Respiration rate may be indicative of a relative cardiac output need for the patient. For example, an increased respiration rate may indicate that there is a need for increased cardiac output, and a decreased respiration rate may indicate less of a need for cardiac output. Accordingly, and when so provided, LCP 100 may adjust the rate of delivery of the electrical stimulation pulses based on the determined respiration rate.

In at least some examples, LCP 100 may include a motion sensor (such as an accelerometer) and may determine a measure related to the respiration rate based on the sensed

motion sensor signal. Where LCP **100** is implanted on a patient's heart or within the heart, the motion sensor signal may include signals indicative of movement related to a number of different causes. For instance, the motion sensor signal may include movement related to the gross movement of the patient, such as walking, bending, or other gross body movements. Additionally, the motion sensor signal may include movement related to the contraction of the heart, particularly when LCP **100** is implanted on or within the heart. Additionally, the motion sensor signal may include movement related to the inhalation and exhalation of the patient (i.e. respiration). For instance, as a patient breathes in and out, the lungs apply different pressure to the heart and the intrathoracic pressure changes accordingly. This change in the intrathoracic pressure may cause changes in the shape and size of the various chambers of the heart, as well as the movement of the heart and the heart chambers. After inhalation, the intrathoracic pressure may be relatively higher, which may decrease the volume of blood that flows into one or more of the chambers of the heart during a cardiac cycle. Conversely, after exhalation, the intrathoracic pressure may be relatively lower, which may allow relatively more blood to enter the chambers of the heart during a cardiac cycle. These differences in the amount of blood flowing into and out of the heart and any movement of the heart or heart chambers due to the changes in intrathoracic pressure may be contained in the motion sensor signal.

A motion sensor may be used to measure inotropic changes in the myocardium; either positive or negative changes. Patients having chronotropic incompetence can still have appropriate contractility responses to increased metabolic demand. For example with increased metabolic demand, contractility increases due to adrenergic excitation. The opposite occurs with decreased metabolic demand.

Although an LCP serves as the platform for much of the below description and above detail, any implantable device having a motion sensor may take advantage of the presently described enhancements. Other devices may include drug or other substance delivery systems, neurostimulator or neuromodulation systems, and implantable cardiac monitoring systems, for example.

FIG. 2 shows several different biological signals in a time-sequenced fashion. For example, the electrocardiograph is shown at **200**, including well known P-Q-R-S-T wave sequences as the heart beats. These "waves" represent the electrical signals that flow through the myocardium to trigger muscle contractions during depolarization and subsequent repolarization. At **202**, the ventricular volume is represented, with volume peaking at the time of the QRS complex and dropping in response to muscle contraction caused by the QRS complex, with refilling starting as after cardiac repolarization represented by the T-wave.

At **204**, the ventricular pressure is represented, with a peak at **222** as the cardiac volume decreases (shown by line **202**). Atrial pressure is represented at **206**. The atrial pressure **206** illustrates changes that are much smaller than those of the ventricles.

The phonocardiogram is shown at **208**, with the first heart sound at **210**, over the QRS complex during systole, the second heart sound **212** representing the end of systole and start of diastole, and the third heart sound **214** occurring still later. The first heart sound **210** corresponds to closing of the atrioventricular valves, that is, the tricuspid and mitral valves. The second heart sounds **212** correspond to closure of the aortic and pulmonary valves. The third heart sound **214** is generally less common and of lower amplitude than the first two heart sounds **210**, **212** and may relate, it is

thought, to blood filling the ventricles. The motion and sounds represented by the changing ventricular volume **202** and heart sounds **210**, **212**, **214** can all create interference for a motion sensor, which may be sensitive to each of these.

The inventors have recognized that a useful goal in this context is to identify a relatively quiet period of time, illustrated at **230**, during which cardiac-sourced interference is reduced. Although the third heart sound **214** may overlap this period **230**, it should be noted that the third heart sound **214** is not universally observed and is the lowest amplitude of the heart sounds and so is less likely to cause significant interference. The inventors have recognized that an LCP may be configured for temporal avoidance of cardiac motion interference, enhancing the signal for analysis and potentially avoiding or reducing computational burden associated with other filtering techniques.

FIGS. 3-6 shows several data flow arrangements for illustrative motion sensors. FIG. 3 shows a first example. A sample is taken at **300**. The "sample" may represent several discrete data elements. For example, a sample may include data points captured for each of several axes of a multi-axis accelerometer (X, Y, Z, for example) that may serve as a motion sensor; such a sample may be thought of as a vector sample with elements $\{x[i], y[i], z[i]\}$. Moreover, a sample may include several close-in-time data points. For example, when "sampling" is performed on a single axis of the output of the accelerometer, 2 or more data points (for example, 2 to 20 data points) may be taken. In one example, four data points may be captured at 400 Hz, yielding a 10 millisecond slice of the output signal as the sample; other rates and quantities may be used. Thus a single sample from a three axis accelerometer could be thought of as a matrix such as:

$$\begin{bmatrix} x[i], & x[i+1], & x[i+2], & x[i+3] \\ y[i], & y[i+1], & y[i+2], & y[i+3] \\ z[i], & z[i+1], & z[i+2], & z[i+3] \end{bmatrix}$$

The math is not so simple as a single number coming out. Computational burdens are presented by such math in an implanted system.

Sampling may be called on a constant basis; historically accelerometer or motion sensor outputs in implantable medical systems would be sampled at rates of 10 to 50 hertz. However, in examples further shown below, sampling occurs in response to detected heart beats identified by analyzing the cardiac electrical signal. For example, the cardiac electrical signal (sometimes referred to as the cardiac electrogram, if captured from within the heart, or electrocardiogram, if captured outside the heart) may be compared to a time-varying threshold to identify the R-wave or QRS complex representative of an individual cardiac cycle. If desired, as alternatives, heart sounds or blood pressure measurements may instead be used to identify a cardiac cycle. As discussed further below, when taking one or more samples with each cardiac cycle, timing of the samples is be selected, in some examples, to avoid certain noise sources.

In the example of FIG. 3, a single axis or multiple axes may be under analysis, with individual samples having several close in time data points. Since there are several data points, the individual data points may be passed on, or may be processed at **302** to take a sum of squares, absolute value sum, mean, or max value, as desired. An integral is taken of the several data points in a given sampling cycle at **304**. The integration at **304** may be omitted if a single data point is taken as the sample.

The output of the integral **304** is averaged over a long interval at **306** to yield a baseline. At **308**, the instantaneous output from block **304** is compared by subtraction to the

long interval average from block 306. The difference may be multiplied in a gain stage at 310 and fed into a moving average block 312, to allow smoothing of the motion sensor signal. For example, a patient rolling over in his or her sleep could be detected as significant motion by such a system, but the moving average block 312 would smooth this large motion over a period of in the range of 5 to 30 seconds. Such smoothing would avoid inappropriate rate response to isolated motion.

For simplicity, several examples herein refer a difference being calculated. In some examples, a difference is calculated relative to a baseline by subtraction. In other example, a difference may be a ratio of a measured value to a baseline value, that is, if the baseline is represented by a non-zero measurement output, the difference may be the ratio to the non-zero output. The word difference is intended to cover all such permutations of a comparison to baseline to determine a difference.

The moving average 312 may then be compared at 316 to a rate response level 314 representing the current state of rate response. For example, if the current state is at a base pacing level—that is, no rate response, then the level 314 may be zero, and an increase would be identified if the moving average is greater than level 314. The output 318, which is the temporary response level, is used to modify the existing state.

In some examples, the various blocks shown in FIG. 3 (and further below in FIGS. 4-11) may be implemented as instruction sets stored in non-transitory medium, such as the memory of an implantable medical device, for operation by a microprocessor or microcontroller. In other examples, a state machine architecture may be used with various operations taking place under control of the device as it progresses through a series of analytical states. In some examples, one or more blocks in FIGS. 3-11 may be performed by application specific integrated circuit hardware or other dedicated hardware. For example, processing and integration blocks 304, 306 may be performed by dedicated hardware, while other blocks are performed within a microprocessor.

FIG. 4 shows another example. Here, sampling is performed at block 400 on the basis of a trigger such as an R-wave trigger 402. The R-wave trigger 402 may be more broadly thought of as a trigger based on a predefined electrical cardiac event occurring. For example, a cardiac electrical signal may be monitored using electrodes (such as electrodes 114, 114' of FIG. 1) and compared to a threshold; when the threshold is crossed, a predefined electrical cardiac event is found to have occurred. The threshold may be time-varying and may be adaptive to the sensed cardiac electrical signal amplitude using various known methods in the art. Sampling may occur at first and/or second delays 404, 406 after the trigger event 402 is identified. While several of the below examples focus on identifying a useful delay, it is noted that more than one delay may be selected to take two samples from within one cardiac cycle.

The output sample is may go through computation and filtering 408 (such as amplifying, root-mean-square assessment, smoothing, etc.) and an average signal within the sample may then be calculated at 410. The pre-processing at blocks 408, 410 may be on a per-sample basis, or may be performed for all samples (if multiple are taken) within a cardiac cycle, if desired. The pre-processed sample can be compared to a long term average 412 in block 414, processed further with an optional gain stage 416, and smoothed to generate a moving average at 418. As with FIG. 3, the moving average 418 can then be compared at 422 to the

existing activity calculation 420 to yield a change, if needed, to the activity calculation at 424.

In a further example, the trigger 402 may be either a detected cardiac event, if one occurs, or pace delivery if the bradycardia pacing escape threshold is exceeded. In such a design, the first delay 402 may be configured for intrinsic (non-paced) cardiac cycles, and the second delay 404 may be configured for paced cardiac cycles. This accounts for the differences between intrinsic and paced cardiac cycles since, for example, the paced cycles may have different conduction characteristics and wider QRS complexes than intrinsic beats.

FIG. 5 shows another illustrative example. Here, the sample again is taken at 500, based on a trigger 502 and one or more delays 504, 506. In some examples, the delay(s) are selected to identify a “quiet” phase of the cardiac cycle where the heart is not moving significantly. In other examples, the peak activity phase of the heart may be sought to assist in characterizing the physiology thereof for example by identifying certain heart sounds and specifying cardiac motion.

Again, the sample 500 is pre-processed at 508 using, for example, a sum of square approach or the like, and one or more peak motion detection from the interval are identified at 510. For example, it may be desirable to take a comprehensive view of the cardiac motion artifact by sampling at a number of times within a cardiac cycle to then identify peaks and generate a histogram 512. Rank valuation can then be performed at 514, and one or more peaks passed through to the gain and integration stages 516, 520. A decay value may be incorporated as well from block 518 with the decay representing expected value within a cycle. These outputs may be used to compare to the existing state 522 in a comparison at 524 to yield an adjustment calculation 526. In other examples the method may stop with the histogram at 512 which may be useful to monitor, for example, the stages (strength or duration, for example) of cardiac contraction.

FIG. 6 shows another illustrative example. In this example, when a sample is taken at 600 from the motion sensor, the sample can be passed forward to one of the above or below described methods of analyzing the motion sensor output. In addition, the output can be provided to a comparison module at 608. In this “learning” example, a device is provided the opportunity to observe, at relatively high sampling rates (10 to 100 Hz for example) motion sensor output across the entire cardiac cycle for a short period of time—perhaps a few seconds up to a few minutes while a patient is active and/or at rest. Observing such an overall cycle while in multiple states can facilitate the development of an alignment signature 604 indicative of whether the patient is in a specific state. One state of particular interest to reduce energy consumption is the state of rest or sleep.

Alignments for one or more states, including an active state, or, alternatively, a sleep state, can be stored at 606 for use in the comparison at 608. A match threshold is applied at 610 to determine whether there is a match to an active or sleep state. If an active state is identified or cannot be eliminated, then the active motion sensor tracking mode may be set at 612. Otherwise, a passive motion sensor tracking mode is set and kept in place for a delay period, as indicated at 614, and the motion sensor subcomponents of the implantable medical device are put to sleep at 616 until the delay period expires. Illustrative delay periods may range from a minute to an hour. In one example, if the patient appears to be asleep or inactive, a thirty-minute delay is set to conserve energy.

A sleep function as shown in FIG. 6 may be called when the patient's activity level according to the rate response algorithm 602 is at baseline or minimum. In another illustration, a method or device may require the patient's activity level be at baseline for a specified period of time before attempting to determine if the patient is asleep. In another illustration, the delay period may be initially short in a first iteration (for example, 5 minutes) and then extended if the patient appears to remain asleep to longer intervals until a maximum sleep interval is reached. In yet another illustration, if the patient's sensed cardiac rate rises above a preset threshold for a predetermined period, sleep mode 616 may be interrupted.

FIGS. 7-11 show several illustrative process flow diagrams. Starting at block 700, motion sensor data is collected, as well as a second signal data 702, preferably contemporaneously though not necessarily concomitantly. For example, motion sensor data may be captured at a first interval using a first sampling period/repeat rate, while the second sensor data may be captured according to a second timing scheme. In an illustration, motion sensor data 700 may be captured in sets of data points, with each set being a sample, captured at a rate of 50 Hz to 1000 Hz, with sets of 1 to 20 data points, captured in groups at rates of 10 Hz to 50 Hz, while the second sensor data 702 is captured continuously at a rate of 100 to 1000 Hz, with 256 Hz being illustrative. In one embodiment the second signal data is the cardiac electrogram. In another embodiment the second signal data is blood pressure data, which may be captured at a lower rate, but more continuously, than the motion sensor data.

The motion sensor data and second signal data are aligned and correlated at 704, and used to generate a configuration for the motion sensor data 706. For example, the aligning and correlating step may be performed to facilitate identifying a quiet time 720 in the motion sensor data relative to alignment or reference points in the second signal data 702.

To further facilitate the configuration, patient activity 710 and/or the status of pacing therapy 712 can be controlled. For example, the data collection 700, 702 is performed, in one illustration, while the patient is told to remain at rest, thus controlling patient activity 710. In this state, the motion sensor should only identify motion caused by cardiac motion and/or sounds within the heart—since an accelerometer-based motion sensor may be sensitive to vibrations (“sounds”) occurring in the heart. Thus a quiet phase of the motion sensor output would provide a good baseline for identifying patient activity. The process may be repeated with pacing on and off, as indicated at 712, to ensure that quiet times 720 can be identified in either circumstance. Moreover, if the quiet time shifts based on whether pacing is on or off, the configuration 706 would be adjusted to ensure the right quiet time is selected for both paced and non-paced beats.

It is envisioned that a system will operate in a learning mode—that is, the system may not necessarily rely on specific landmarks or theoretical bases when selecting a quiet time. However, in reality, it is expected that devices will choose a time period as indicated by FIG. 2 above at 230, a period between the T-wave and the P-wave when the cardiac signal is in a quiescent phase. The configuration 706 that will then be stored would take the form of a value or values indicating an appropriate delay from the QRS complex or R-wave to the expected quiet time.

Alternatively, sampling, with or without delays may be triggered by a different detectable event. For example, the configuration 706 may store a time period from the T-wave

or end of the T-wave. The configuration 706 may instead be reflected in identification of a quiescent state of the electrocardiogram where the ECG or EGM is electrically at baseline for a period of time, as such a state would correspond to the period between the T-wave and the P-wave.

For those patients who exhibit a detectable third heart sound, the configuration 706 may be selected to ensure motion sensor sampling before or after the third heart sound in order to avoid it. Such a result may occur from the device learning when a quiet time takes place relative to one or more cardiac signals, or it may be ensured using inputs from a physician.

In some examples a further set of manipulations of the state of the patient may be had. Configuration may be performed while the patient is in a state of rest as well as during patient activity selected to increase the heart rate. In conjunction with the patient activity the output pacing rate may be increased by the implantable device, if needed. For example, a baseline configuration may be used during a learning period and, once data capturing and correlation steps are completed, a tailored configuration can be stored for the patient. By rechecking the configuration at increased heart rates, the appropriate timing of the quiet time at various heart rates can be determined and stored as part of the configuration 706.

In one example, the pacing rate may be increased to confirm the mechanical quiet phase remains quiet at increased rates (or, if the timing of the quiet phase moves, to allow for adjustment). That is, if the quiet time at low rates is no longer quiet at high rates due to motion intrinsic to the heart, the configuration of the quiet time can be adjusted. The quiet time may be preferably selected to avoid inappropriate feedback from the heart itself, which could perpetuate an unnecessarily high cardiac rate if not avoided.

Much of the above presumes a ventricular placement of the implantable device. If an implantable device is placed in the atrium, it may be more suitable to use the P-wave as a trigger point, since it will be the larger signal to the atrial device absent cross-chamber noise. In this instance, the implantable device is more likely to identify a quiet time that may occur during systole, that is, while the ventricles are ejecting blood to the rest of the body.

FIG. 8 shows another example. In this example, the system is shown in more of an operational state. An event is detected at 800. The device will perform sampling of a motion sensor output at 804 in response to the detected event from 800. In some examples, a delay period 802 first must expire prior to the sampling at 804.

Within FIG. 8, the detected event, in some examples, may be the delivery of a pacing output 810, either by the implantable device or by a second implantable device. In another example, the detected event may be the detection of a quiescent state 812 where, for example, the cardiac electrogram remains stable for a period of time (such as 40 milliseconds, about 10 samples at 256 Hz). In another example, the detected event is a predefined event in the electrical cardiac signal such as a P-wave, R-wave, QRS complex or T-wave, as indicated at 814.

The delay 802 may be defined or determined in a number of ways. In some examples, a learning process is used at 820, such as the process of FIG. 7 where the motion sensor output and a second signal are analyzed to look for quiet times in the motion sensor output while the patient is in a controlled state. In another example noted at 822, the delay can be based on a predictive formula; for example, using Bazett's formula or Friderica's formula, the R-T interval can be predicted from a known cardiac beat rate, and the delay can

be set to cause sampling after the T-wave is completed. In a still further example, the delay **802** may be adjusted in light of the cardiac rate of the patient, as shown at **824**. For example, at higher rates a shorter delay may be needed. Such adjustments in **824** may be made based on learning **820** or prediction **822**.

FIG. **9** illustrates a data correction method that may also be used. Following capture of a sample at **900**, a device checks a second signal, such as the electrogram, as noted at **902**. If a particular event is identified in the second signal, the sample can be discarded, as noted at **904**. For example, supposing sampling takes place in response to the R-wave and is intended to occur after the T-wave and before the P-wave, if the check of the second signal electrogram at **902** shows that the T-wave overlaps or P-wave precedes the sample **900**, then the quiet phase of the cardiac motion may have been missed. This suggests a sample which may be noisy and may mix or overlap patient motion and cardiac motion. Thus the sample is discarded at **904**. Repeated discarding may result in a decision to reconfigure the sampling system, implementation of a higher power approach to sampling (higher duty cycle), or activation of a patient or physician alert function.

Further to the example of FIG. **9**, rather than a P-wave or T-wave overlap, the presence of another signal in the electrogram at **902** can trigger discarding the sample. For example, a conducted atrial arrhythmia, or a ventricular extra-systolic beat (such as a premature ventricular contraction) identified within the cardiac electrical signal, or by some other sensor such as heart sounds or a pressure sensor, for example, may be identified at block **902** and used as a basis for discarding a motion sensor signal. The circuitry feature, or software function, which performs such identification may be spurious event identifier.

FIG. **10** shows another illustrative example. Here, motion sensor samples are captured at **1000**. A large number of such samples are averaged over time to generate a baseline motion for the patient. If desired, statistical methods may be used to eliminate outlier data prior to setting the baseline by, for example, eliminating samples more than two standard deviations away from a mean. The baselining step **1002** may occur while a patient is ambulatory but more preferably would take place in a controlled setting with the patient generally at rest.

Once a baseline is established at **1002**, a sample is taken at **1004**. The sample **1004** is then compared to the baseline at **1006**, to generate a difference that is used to assess patient activity at **1008**. If desired, several samples may be taken and averaged together, or a smoothing function may be applied to a series of samples prior to comparing to the baseline **1006**.

FIG. **11** shows a clinical method of establishing a patient configuration. Here, the patient is instructed at **1100** to assume a posture, for example as shown at **1110**. Sitting, supine, prone, laying on left or right sign, standing, or other postures may be chosen at **1110**. Alternative, the patient is instructed **1100** to engage in a movement, such as walking, jogging, or a favorite exercise, or to hold still or engage in the Valsalva maneuver, as indicated at **1112**.

Next, data capture is performed at **1102**. Data capture may include capturing data from a motion sensor as well as a second data input or sensor such as the electrogram. Capture of the motion sensor output and second signal may be continuous **1120** or at high rate **1122** for the purposes of configuration, with the intent being that once configuration is completed a lower rate may be implemented.

Steps **1100** and **1102** may be repeated as shown at **1104** with new instructions to the patient for second and subsequent iterations. Once data is captured, the method determines a quiet time in the motion sensor signal using a trigger or reference point identified in the second signal data. The analysis of this type may be performed by the implanted device **1130** or may be performed by an external device in communication with an implanted device **1132**.

FIG. **12** shows a patient having an implantable medical device system in the heart. The patient **1200** is shown having a heart **1201** in which a plurality of medical devices are implanted. In this example, a ventricular device is shown at **1204** and an atrial device at **1206**. The implantable devices **1204**, **1206** may operate independent of one another or may coordinate using conducted communication—or other communication such as RF—therebetween. An external device **1210** such as a programmer is also shown, in this instance with a wand **1212** for placement on the patient to facilitate communication to the implantable devices **1204**, **1206**.

It is not necessary to have multiple implanted devices, but it is envisioned that at least some patients will have multiple devices. In some examples, one or both implanted device **1204**, **1206** has a motion sensor. In some examples, the motion sensor of one of the devices is disabled after configuration has been performed, if it can be determined that performance of one or the other is better or worse and the devices operate in coordination with one another. In some examples, an atrial device **1206** may be of smaller size and lesser mass, and omits a motion sensor which is instead provided in the ventricular device **1204**.

Alternatively, the devices may be identical and whichever device has a greater available battery capacity is used for motion capture, while the other device renders a motion sensor inactive. For example, it may be that the atrial device **1206** is anticipated to use less power in therapy delivery than the ventricular device **1204**, such that motion sensing is performed with just the atrial device **1206**.

In some examples, the two separate devices **1204** and **1206** may provide synchronized motion capture to identify an appropriate configuration. For example, both devices **1204** and **1206** may communicate captured motion data out to the external programmer **1210**, where the motion sensing data is captured in overlapping time periods. Motion that is sensed due to patient movement should be identified in both of the devices, while local motion from cardiac chamber movement, for example, would not necessarily show up in each device's motion sensor output. By comparing the signals, the bodily motion signal can be extracted. Next, working backwards, it would be determined which time periods in one or both implanted device **1204** and **1206** is capturing the bodily motion accurately and without interference from local cardiac motion. A configuration would be identified and stored for one or both implanted devices **1204** and **1206**.

A first non-limiting example is an implantable device (ID) comprising a power source, operational circuitry, a motion sensor, and electrodes, the electrodes configured to capture a cardiac electrical signal, wherein the operational circuitry comprises: trigger means for determining that a predefined event has occurred in the heart of the patient using a signal from the electrodes; sampling means for sampling an output of the motion sensor in response to the trigger means. Illustrative examples of a trigger means includes a circuit (such as a comparator) or software implemented instruction for comparing a representation (analog or digital) of a received cardiac signal to a predetermined threshold such as a threshold as described in U.S. Pat. No. 8,565,878, the

disclosure of which is incorporated herein by reference. Such triggers are also described above. Illustrative examples of sampling means include any suitable sampling circuit such as a capacitive sample and hold circuit in which, for example, an output is switched to a capacitor, charging the capacitor up or down to a level related to the sampled signal, and a comparator is used to drive a second capacitor to match the sampling capacitor, or a comparator circuit, and an analog-to-digital convertor capable of retaining or passing to memory an output of a measurement, among others. The drawings indicate certain examples including trigger **402** and sampling **400** in FIG. **4**, trigger **502** and sampling **500** in FIG. **5**, for example.

A second non-limiting example is the ID of the first non-limiting example, wherein the sampling means further comprises delay means for waiting a delay period following activation of the trigger means before sampling the output of the motion sensor. Illustrative delay means may include a timer and associated memory or comparator for setting the duration to run the timer, or may include a capacitor that can be charged to a selected level and then discharged in predictable fashion. Delay is illustrated in the Figures, for example, at FIG. **6**, block **614**, and FIG. **8**, at **802**.

A third non-limiting example is an ID as in the second non-limiting example, wherein the motion sensor is configured to operate in a low-power mode except to facilitate the sampling means taking a sample of the output thereof. A fourth non-limiting example is an ID as in either of the second or third non-limiting examples, wherein the predefined event is one of an R-wave, a pacing impulse, or a QRS complex, and the delay period is selected to expire prior to occurrence of a P-wave. A fifth non-limiting example is an ID as in any of the second to fourth non-limiting examples further comprising a spurious event detector configured to determine whether an event occurs during or after the delay period and, if so, the spurious event detector is configured to interrupt the sampling means or cause the sampling means to discard the sampled output of the motion sensor. A sixth non-limiting example is an ID as in the fifth non-limiting example, wherein the specified cardiac event is a ventricular contraction.

A seventh non-limiting example is an ID as in any of the second to sixth non-limiting examples, wherein the operational circuitry includes means for initializing the ID including: collection means to collect a set of data points from the motion sensor and from a cardiac electrical signal from the electrodes contemporaneously; correlating means to correlate time periods within the set of data points from the motion sensor to cardiac activity reflected by the cardiac electrical signal; and setting means to store information indicating when data from the motion sensor is to be captured by reference to specific repeatable elements of the cardiac electrical signal. Illustrative collection means may take the form of a memory location for receiving data for at least temporary storage. The correlating means may take any suitable form for comparing two shapes such as a correlation waveform analysis block or signal processing chip, or a microprocessor or microcontroller with associated memory instructions for comparing two shapes by difference of area, principal components, or wavelet analysis, for example. The setting means may include a volatile or non-volatile memory. An example is in FIG. **6**, with collection at blocks **700** and **702**, correlation at **704**, and setting performed as the configuring step at **706**.

An eighth non-limiting example is an ID as in the seventh non-limiting example, wherein the delay means is configured to calculate the delay period from the information

stored by the setting means, taking into account a cardiac rate of the patient. A ninth non-limiting example is an ID as in any of the seventh or eighth non-limiting examples, wherein: the correlating means is configured to determine when intrinsic mechanical motion of the heart is detected by the motion sensor relative to electrical signals of the heart; and the setting means is configured to store information indicating a time period relative to a specified electrical signal of the heart to avoid capturing intrinsic mechanical motion of the heart with the motion sensor. A tenth non-limiting example is an ID as in any of the seventh to ninth non-limiting examples, wherein the setting means is configured to set a delay to be triggered by detection of a T-wave in the cardiac electrical signal.

An eleventh non-limiting example is an ID as in any of the first to tenth non-limiting examples, wherein the ID includes pacing means to deliver pacing therapy to the patient and the predefined event is delivery of a pacing stimulus by the ID. Illustrative pacing means may include one or more of a voltage supply (such as an amplifier output), a current source (such as a current mirror), or a capacitor (or plurality thereof) or simply a battery output, coupled via the pulse generator module **104** (such as by a multiplexor, switch array or H-Bridge) to one or more of the electrodes **114**, **114'**, for example, and associated instruction sets for operation by the processing module **110**.

A twelfth non-limiting example is an implantable device (ID) comprising a power source, operational circuitry, a motion sensor, and electrodes, the electrodes configured to capture a cardiac electrical signal, wherein the operational circuitry comprises: sampling means for sampling a signal from a motion sensor in the ID; baseline calculation means for analyzing the sampled signal over time to generate a baseline output of the motion sensor; present state means for determining a present state indicator from the sampled signal; comparing means to compare the present state indicator to the baseline to yield a difference; activity characterizing means to analyze the difference to determine the patient's activity level. Illustrative sampling means may be as described above. Illustrative baseline calculation means may include analog or digital domain memory or storage locations for capturing an average sampled output of the motion sensor over time, with associated instruction sets for the processing module **110** to use for controlling baseline. For example, block **306** (FIG. **3**) takes an average over a long interval to obtain a baseline; block **1002** (FIG. **10**) likewise identifies a baseline using captured samples **1000**.

Illustrative comparing means may include digital domain software instruction set or module for comparing two digital values, for example, or a comparator, for example, in the analog domain. A difference, as yielded, may be a subtractive difference, a ratio of two numbers/values, or other comparative output. Comparisons of this sort are noted at block **316** (FIG. **3**), block **422** (FIG. **4**), block **524** (FIG. **5**), and block **1006** (FIG. **10**).

The activity characterizing means may include a state machine, for example, which operates to change state based on the difference as calculated by the comparing means, for example, assuming baseline to a rest state for the patient, then a difference such as large subtractive difference, or large ratio to the baseline would suggest a high level of activity and be classified in an active state if meeting an active state threshold; and if the difference is a small subtractive difference or ratio, below an inactive state threshold, then the state machine may assume an inactive state. Other such means may be provided, using for example a stored memory location as a characterization of patient

activity with plural possible values such as active, inactive, or hysteresis (in-between). Illustratively, the Temporary Response Level (Temp RL, at FIG. 3, block 318; FIG. 4, block 424, and FIG. 5 block 526) may be used as shown in the high level diagram of FIG. 10 to assess activity at block 1008 by the use of binning of the Temp RL to high or low classes, with or without a hysteresis band/bin in the middle. As noted, these may drive state machine logic in some examples.

A thirteenth non-limiting example is an ID as in the twelfth non-limiting example, wherein the baseline calculation means uses a number, M, of individual samples from the motion sensor; the present state means uses a number, N, of individual samples from the motion sensor; and M is an order of magnitude larger than N.

A fourteenth non-limiting example is an ID as in any of the first to tenth, twelfth or thirteen non-limiting examples, wherein the operational circuitry comprises: pacing means to deliver pacing therapy to a patient at a pacing output rate; activity determining means configured to use an output of the motion sensor to calculate an activity level of the patient; and adjusting means to adjust the pacing output rate in view of the activity level. Such activity determining means may be as noted in block 1008 of FIG. 10 and described above. The adjusting means may operate by increasing the pacing rate output when a higher level of patient activity is observed or likely, and reducing the pacing rate output when a lower level of patient activity is observed or likely, both within reasonable boundaries. That is such adjusting would have minimum boundaries (40 to 60 bpm, for example) and upper boundaries (120 to 200 bpm, for example) which may vary depending on patient characteristics and physician decisions.

A fifteenth non-limiting example is an ID as in any of the first to fourteenth non-limiting examples, wherein the ID is configured as a leadless cardiac pacing device for implantation entirely within the heart of the patient without a lead.

A sixteenth non-limiting example is a method of operation in an implantable device comprising: initializing an implantable device (ID) for disposition within the heart of a patient, the ID comprising a motion sensor for detecting movement of the patient, the initializing step being performed by: contemporaneously collecting a set of data points from the motion sensor and from a cardiac electrical signal; correlating time periods within the set of data points from the motion sensor to cardiac activity reflected by the cardiac electrical signal; and configuring the ID to capture data from the motion sensor by reference to specific repeatable elements of the cardiac electrical signal; using the ID as configured in the initializing step to capture cardiac signals of the patient and motion signals for the patient. A seventeenth non-limiting example is a method as in the sixteenth non-limiting example, further comprising: using the motion signals to determine an activity level of the patient; and setting and implementing a pacing rate for the patient using the determined activity level.

An eighteenth non-limiting example is a method as in either of the sixteenth or seventeenth non-limiting examples, wherein the step of configuring the ID to capture data from the motion sensor is performed by: determining when intrinsic mechanical motion of the heart is detected by the motion sensor relative to electrical signals of the heart; and setting a data capture period for the motion sensor relative to a specified electrical signal of the heart to avoid capturing the intrinsic mechanical motion of the heart with the motion sensor.

A nineteenth non-limiting example is a method as in any of the sixteenth to eighteenth non-limiting examples, wherein the step of configuring the ID to capture data from the motion sensor includes determining a delay after a T-wave in the cardiac electrical signal. A twentieth non-limiting example is a method as in the nineteenth non-limiting example, wherein the delay is configured as a function of cardiac rate. A twenty-first non-limiting example is a method as in the twentieth non-limiting example, wherein the cardiac rate is determined as a rate of pacing output of the ID. A twenty-second non-limiting example is a method as in the twentieth non-limiting example, wherein the cardiac rate is determined as an intrinsic rate of the patient's heart.

A twenty-third non-limiting example is a method of operating a motion sensor in an implantable device (ID) for disposition within the heart of a patient, the ID comprising a motion sensor for detecting movement of the patient, the method comprising: the ID determining a predefined event has occurred in the heart of the patient; and the ID waiting a predetermined period of time after the predefined electrical event and sampling an output of the motion sensor.

A twenty-fourth non-limiting example is a method as in the twenty-third non-limiting example, further comprising duty cycling the motion sensor to operate in a window corresponding to the sampling step and otherwise be in a low-power state. A twenty-fifth non-limiting example is a method as in either of the twenty-third or twenty-fourth non-limiting examples, wherein the predefined event is one of an R-wave, a pacing pulse, or a QRS complex, and the predetermined time period is selected to expire prior to occurrence of a P-wave. A twenty-sixth non-limiting example is a method as in any of the twenty-third to twenty-fifth non-limiting examples, further comprising using the output of the motion sensor to determine whether the patient is physically active to facilitate a rate-responsive pacing by the ID. A twenty-seventh non-limiting example is a method as in any of the twenty-third to twenty-sixth non-limiting examples, further comprising using the output of the motion sensor to determine an increase or decrease in cardiac contractility to facilitate a rate-responsive pacing by the ID.

A twenty-eighth non-limiting example is a method as in any of the twenty-third to twenty-seventh non-limiting examples, further comprising determining the predetermined period of time by using an accepted formula for predicting occurrence of a cardiac mechanical or electrical event. A twenty-ninth non-limiting example is a method as in any of the twenty-third to twenty-seventh non-limiting examples further comprising determining the predetermined period of time by initializing the ID by capturing a plurality of outputs from the motion sensor over a period of time including several heart beats to determine a mechanically quiet period in the patient's cardiac cycle relative to the predefined event.

A thirtieth non-limiting example is a method as in any of the twenty-third to twenty-ninth non-limiting examples, wherein the predefined event is one of a P-wave, an R-wave, a QRS complex, a T-wave, or a quiescent period. A thirty-first non-limiting example is a method as in any of the twenty-third to twenty-ninth non-limiting examples wherein the predefined event is delivery of a pacing stimulus. A thirty-second non-limiting example is a method as in any of the twenty-third to thirty-first non-limiting examples, further comprising analyzing a cardiac electrical signal of the patient during at least the predetermined period of time to observe whether a specified cardiac electrical event occurs

and, if so, discarding the sampled output of the motion sensor. A thirty-third non-limiting example is a method as in the thirty-second non-limiting example, wherein the specified cardiac event is a ventricular contraction. A thirty-fourth non-limiting example is a method as in the thirty-second non-limiting example, wherein occurrence of the ventricular contraction is determined by identifying a P-wave, R-wave or QRS complex in the electrical cardiac signal at the same time as, or just before, the output of the motion sensor is sampled.

A thirty-fifth non-limiting example is a method of determining whether a patient is active using an implantable device (ID) for disposition within the heart of a patient, the ID comprising a motion sensor for detecting movement of the patient, the method comprising: sampling a signal from a motion sensor in the ID; analyzing the sampled signal over time to generate a baseline; generating a present state indicator from the sampled signal; comparing the present state indicator to the baseline to yield a difference; and comparing the difference to one or more thresholds to characterize the patient's activity level.

A thirty-sixth non-limiting example is a method as in the thirty-fifth non-limiting example, wherein: the present state indicator is generated by averaging a number, M, of individual samples from the motion sensor; the subtractive baseline is generated by averaging a number, N, of individual samples from the motion sensor; and wherein M is an order of magnitude smaller than N. A thirty-seventh non-limiting example is a method as in either of the thirty-fifth or thirty-sixth non-limiting examples, further comprising: providing a pacing output from the ID to the patient's heart, wherein the pacing output has a rate which is adjustable; and adjusting the pacing output rate in light of the patient's activity level.

A thirty-eighth non-limiting example is a method of operating a motion sensor in an implantable device (ID) for disposition within the heart of a patient, the ID comprising a motion sensor for detecting movement of the patient, the method comprising: instructing a patient having the ID implanted in the heart thereof to adopt a set of postures or engage in a movement; capturing a number of motion sensor outputs while the patient is in one or more postures or engaging in one or more movement while capturing a cardiac electrical signal; identifying a quiet period within the cardiac the cardiac electrical signals during which intrinsic motion of the heart does not impact the output of the motion sensor outputs; and configuring the ID to activate and capture data from the motion sensor during the quiet periods. A thirty-ninth non-limiting example is a method as in the thirty-eighth non-limiting example, wherein the quiet time is defined relative to a predetermined event in the cardiac electrogram. A fortieth non-limiting example is a method comprising repeatedly performing the method of the thirty-eighth non-limiting example using one or more of the following: with and without the patient receiving pacing therapy; and for at least first and second postures or activities.

Each of these non-limiting examples can stand on its own, or can be combined in various permutations or combinations with one or more of the other examples. The above detailed description includes references to the accompanying drawings, which form a part of the detailed description. The drawings show, by way of illustration, specific embodiments in which the invention can be practiced. These embodiments are also referred to herein as "examples." Such examples can include elements in addition to those shown or described. However, the present inventors also contemplate examples

in which only those elements shown or described are provided. Moreover, the present inventors also contemplate examples using any combination or permutation of those elements shown or described (or one or more aspects thereof), either with respect to a particular example (or one or more aspects thereof), or with respect to other examples (or one or more aspects thereof) shown or described herein.

In the event of inconsistent usages between this document and any documents so incorporated by reference, the usage in this document controls. In this document, the terms "a" or "an" are used, as is common in patent documents, to include one or more than one, independent of any other instances or usages of "at least one" or "one or more." Moreover, in the following claims, the terms "first," "second," and "third," etc. are used merely as labels, and are not intended to impose numerical requirements on their objects.

Method examples described herein can be machine or computer-implemented at least in part. Some examples can include a computer-readable medium or machine-readable medium encoded with instructions operable to configure an electronic device to perform methods as described in the above examples. An implementation of such methods can include code, such as microcode, assembly language code, a higher-level language code, or the like. Such code can include computer readable instructions for performing various methods. The code may form portions of computer program products. Further, in an example, the code can be tangibly stored on one or more volatile, non-transitory, or non-volatile tangible computer-readable media, such as during execution or at other times. Examples of these tangible computer-readable media can include, but are not limited to, hard disks, removable magnetic or optical disks, magnetic cassettes, memory cards or sticks, random access memories (RAMs), read only memories (ROMs), and the like.

The above description is intended to be illustrative, and not restrictive. For example, the above-described examples (or one or more aspects thereof) may be used in combination with each other. Other embodiments can be used, such as by one of ordinary skill in the art upon reviewing the above description.

The Abstract is provided to comply with 37 C.F.R. §1.72(b), to allow the reader to quickly ascertain the nature of the technical disclosure. It is submitted with the understanding that it will not be used to interpret or limit the scope or meaning of the claims.

Also, in the above Detailed Description, various features may be grouped together to streamline the disclosure. This should not be interpreted as intending that an unclaimed disclosed feature is essential to any claim. Rather, inventive subject matter may lie in less than all features of a particular disclosed embodiment. Thus, the following claims are hereby incorporated into the Detailed Description as examples or embodiments, with each claim standing on its own as a separate embodiment, and it is contemplated that such embodiments can be combined with each other in various combinations or permutations. The scope of the invention should be determined with reference to the appended claims, along with the full scope of equivalents to which such claims are entitled.

What is claimed is:

1. A method of operating a motion sensor in an implantable device (ID) for disposition within the heart of a patient, the ID comprising a motion sensor for detecting movement of the patient, the method comprising:

the ID determining a predefined event has occurred in the heart of the patient; and

23

the ID waiting a predetermined period of time after the predefined event and sampling an output of the motion sensor.

2. The method of claim 1 further comprising duty cycling the motion sensor to operate in a window corresponding to the sampling step and otherwise be in a low-power state.

3. The method of claim 1 wherein the predefined event is one of an R-wave, a pacing pulse, or a QRS complex, and the predetermined time period is selected to expire prior to occurrence of a P-wave.

4. The method of claim 1 further comprising using the output of the motion sensor to determine whether the patient is physically active to facilitate a rate-responsive pacing therapy by the ID.

5. The method of claim 1 further comprising using the output of the motion sensor to determine an increase or decrease in cardiac contractility to facilitate a rate-responsive pacing therapy by the ID.

6. The method of claim 1 further comprising determining the predetermined period of time by initializing the ID by capturing a plurality of outputs from the motion sensor over a period of time including several heart beats to determine a mechanically quiet period in the patient's cardiac cycle relative to the predefined event.

7. The method of claim 1 wherein the predefined event is one of a P-wave, an R-wave, a QRS complex, a T-wave, or a quiescent period.

8. The method of claim 1 wherein the predefined event is delivery of a pacing stimulus.

9. The method of claim 1 further comprising analyzing a cardiac electrical signal of the patient during at least the predetermined period of time to observe whether a specified cardiac electrical event occurs and, if so, discarding the sampled output of the motion sensor.

10. The method of claim 9 wherein the specified cardiac event is a ventricular contraction.

11. An implantable medical device adapted for implantation within the heart of a patient and comprising:

a plurality of electrodes adapted for one or more of sensing electrical cardiac activity and delivering therapy;

a motion sensor for detecting movement of the patient; and

a processing module configured to receive signals from the motion sensor and from the plurality of electrodes to determine patient status, wherein the processing module is configured to enhance the operation of the device by:

determining that a predetermined event has occurred in the heart of the patient; and

24

waiting a predetermined period of time after the predefined event and sampling an output of the motion sensor after the predetermined period of time has expired.

12. The implantable medical device of claim 11 wherein the processing module is configured to control the motion sensor by duty cycling the motion sensor to operate in a window corresponding to the sampling step and otherwise be in a low-power state.

13. The implantable medical device of claim 11 wherein the processing module is configured such that the predefined event is one of an R-wave, a pacing pulse, or a QRS complex, and the predetermined time period is selected to expire prior to occurrence of a P-wave of a subsequent cardiac cycle.

14. The implantable medical device of claim 11 further comprising a pacing therapy output circuit, wherein the processing module is configured to use the output of the motion sensor to determine whether the patient is physically active and, if so, to facilitate a rate-responsive pacing therapy for delivery by the pacing therapy output circuit.

15. The implantable medical device of claim 11 further comprising a pacing therapy output circuit, wherein the processing module is further configured to use the output of the motion sensor to determine an increase or decrease in cardiac contractility and in response thereto, to facilitate a rate-responsive pacing therapy for delivery by the pacing therapy output circuit.

16. The implantable medical device of claim 11 wherein the processing module is further configured to calculate the predetermined period of time by capturing a plurality of outputs from the motion sensor over a period of time including several heart beats to determine a mechanically quiet period in the patient's cardiac cycle relative to the predefined event.

17. The implantable medical device of claim 11 wherein the processing module is further configured such that the predefined event is one of a P-wave, an R-wave, a QRS complex, a T-wave, or a quiescent period.

18. The implantable medical device of claim 11 wherein the predefined event is delivery of a pacing stimulus to the patient's heart.

19. The implantable medical device of claim 11 wherein the processing module is further configured to analyze a cardiac electrical signal of the patient during at least the predetermined period of time to observe whether a specified cardiac electrical event occurs and, if so, to discard the sampled output of the motion sensor.

20. The implantable medical device of claim 19 wherein the specified cardiac event is a ventricular contraction.

* * * * *

专利名称(译)	可植入医疗设备中的运动传感器的时间配置		
公开(公告)号	US9956414	公开(公告)日	2018-05-01
申请号	US15/243524	申请日	2016-08-22
[标]申请(专利权)人(译)	心脏起搏器股份公司		
申请(专利权)人(译)	心脏起搏器，INC.		
当前申请(专利权)人(译)	心脏起搏器，INC.		
[标]发明人	KANE MICHAEL J LINDER WILLIAM J HAASL BENJAMIN J HUELSKAMP PAUL MAILE KEITH R BALCZEWSKI RON A MI BIN HATLESTAD JOHN D SHUROS ALLAN CHARLES		
发明人	KANE, MICHAEL J. LINDER, WILLIAM J. HAASL, BENJAMIN J. HUELSKAMP, PAUL MAILE, KEITH R. BALCZEWSKI, RON A. MI, BIN HATLESTAD, JOHN D. SHUROS, ALLAN CHARLES		
IPC分类号	A61N1/365 A61B5/0452 A61N1/375 A61N1/368 A61B5/11 A61B5/00 A61N1/37 A61N1/372		
CPC分类号	A61N1/36542 A61B5/0452 A61B5/1118 A61B5/686 A61B5/6869 A61N1/371 A61N1/3756 A61N1/3684 A61N1/37205 A61B5/1107 A61B2562/0219 A61N1/36578		
优先权	62/210882 2015-08-27 US		
其他公开文献	US20170056665A1		
外部链接	Espacenet USPTO		

摘要(译)

用于配置可植入心脏装置中运动传感器的使用的方法和和设备。观察患者心脏的电信号，并且可以将该信号与由可植入心脏装置的运动传感器检测到的心脏的物理运动相关联，以促进运动传感器数据收集的暂时配置，该运动传感器数据收集避免检测心脏运动而有利于病人的整体运动。

