



US009814418B2

(12) **United States Patent**
Weber et al.

(10) **Patent No.:** **US 9,814,418 B2**
(45) **Date of Patent:** ***Nov. 14, 2017**

(54) **SINE SATURATION TRANSFORM**

(71) Applicant: **Masimo Corporation**, Irvine, CA (US)

(72) Inventors: **Walter M. Weber**, Laguna Hills, CA (US); **Ammar Al-Ali**, San Juan Capistrano, CA (US); **Lorenzo Cazzoli**, Barcelona (ES)

(73) Assignee: **MASIMO CORPORATION**, Irvine, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 276 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **14/543,325**

(22) Filed: **Nov. 17, 2014**

(65) **Prior Publication Data**

US 2015/0141781 A1 May 21, 2015

Related U.S. Application Data

(63) Continuation of application No. 13/953,628, filed on Jul. 29, 2013, now Pat. No. 8,892,180, which is a continuation of application No. 13/043,421, filed on Mar. 8, 2011, now Pat. No. 8,498,684, which is a continuation of application No. 12/336,419, filed on (Continued)

(51) **Int. Cl.**

A61B 5/1455 (2006.01)

A61B 5/024 (2006.01)

A61B 5/00 (2006.01)

A61B 5/145 (2006.01)

(52) **U.S. Cl.**

CPC **A61B 5/14552** (2013.01); **A61B 5/024** (2013.01); **A61B 5/02433** (2013.01); **A61B 5/14551** (2013.01); **A61B 5/7282** (2013.01); **A61B 5/1455** (2013.01); **A61B 5/14532** (2013.01)

(58) **Field of Classification Search**

CPC **A61B 5/1455**; **A61B 5/14551**; **A61B 5/14552**; **A61B 5/14532**; **A61B 5/024**; **A61B 5/72**; **A61B 5/7235**; **A61B 5/7271**; **A61B 5/7278**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,960,128 A 10/1990 Gordon et al.

4,964,408 A 10/1990 Hink et al.

(Continued)

FOREIGN PATENT DOCUMENTS

WO WO 98/42250 10/1998
WO WO 02/47582 6/2002

OTHER PUBLICATIONS

US 8,845,543, 09/2014, Diab et al. (withdrawn)
(Continued)


Primary Examiner — Eric Winakur

(74) *Attorney, Agent, or Firm* — Knobbe, Martens, Olson & Bear, LLP

(57) **ABSTRACT**

A transform for determining a physiological measurement is disclosed. The transform determines a basis function index from a physiological signal obtained through a physiological sensor. A basis function waveform is generated based on basis function index. The basis function waveform is then used to determine an optimized basis function waveform. The optimized basis function waveform is used to calculate a physiological measurement.

16 Claims, 14 Drawing Sheets



Related U.S. Application Data

Dec. 16, 2008, now Pat. No. 7,904,132, which is a continuation of application No. 11/894,648, filed on Aug. 20, 2007, now Pat. No. 7,467,002, which is a continuation of application No. 11/417,914, filed on May 3, 2006, now Pat. No. 7,377,899, which is a continuation of application No. 11/048,232, filed on Feb. 1, 2005, now Pat. No. 7,373,194, which is a continuation of application No. 10/184,032, filed on Jun. 26, 2002, now Pat. No. 6,850,787.

- (60) Provisional application No. 60/302,438, filed on Jun. 29, 2001.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,041,187 A	8/1991	Hink et al.	6,067,462 A	5/2000	Diab et al.
5,069,213 A	12/1991	Polczynski	6,081,735 A	6/2000	Diab et al.
5,163,438 A	11/1992	Gordon et al.	6,083,172 A	7/2000	Baker, Jr. et al.
5,188,108 A	2/1993	Secker	6,088,607 A	7/2000	Diab et al.
5,319,355 A	6/1994	Russek	6,110,522 A	8/2000	Lepper, Jr. et al.
5,337,744 A	8/1994	Branigan	6,119,026 A	9/2000	McNulty et al.
5,341,805 A	8/1994	Stavridi et al.	6,124,597 A	9/2000	Shehada
D353,195 S	12/1994	Savage et al.	6,128,521 A	10/2000	Marro et al.
D353,196 S	12/1994	Savage et al.	6,129,675 A	10/2000	Jay
5,377,676 A	1/1995	Vari et al.	6,144,868 A	11/2000	Parker
D359,546 S	6/1995	Savage et al.	6,151,516 A	11/2000	Kiani-Azarbayjany et al.
5,431,170 A	7/1995	Mathews	6,152,754 A	11/2000	Gerhardt et al.
D361,840 S	8/1995	Savage et al.	6,157,850 A	12/2000	Diab et al.
D362,063 S	9/1995	Savage et al.	6,165,005 A	12/2000	Mills et al.
5,452,717 A	9/1995	Branigan et al.	6,184,521 B1	2/2001	Coffin, IV et al.
D363,120 S	10/1995	Savage et al.	6,206,830 B1	3/2001	Diab et al.
5,456,252 A	10/1995	Vari et al.	6,229,856 B1	5/2001	Diab et al.
5,479,934 A	1/1996	Imran	6,232,609 B1	5/2001	Snyder et al.
5,482,036 A	1/1996	Diab et al.	6,236,872 B1	5/2001	Diab et al.
5,490,505 A	2/1996	Diab et al.	6,241,683 B1	6/2001	Macklem et al.
5,494,043 A	2/1996	O'Sullivan et al.	6,253,097 B1	6/2001	Aronow et al.
5,533,511 A	7/1996	Kaspari et al.	6,256,523 B1	7/2001	Diab et al.
5,534,851 A	7/1996	Russek	6,263,222 B1	7/2001	Diab et al.
5,561,275 A	10/1996	Savage et al.	6,278,522 B1	8/2001	Lepper, Jr. et al.
5,562,002 A	10/1996	Lalin	6,280,213 B1	8/2001	Tobler et al.
5,590,649 A	1/1997	Caro et al.	6,285,896 B1	9/2001	Tobler et al.
5,602,924 A	2/1997	Durand et al.	6,301,493 B1	10/2001	Marro et al.
5,632,272 A	5/1997	Diab et al.	6,317,627 B1	11/2001	Ennen et al.
5,638,816 A	6/1997	Kiani-Azarbayjany et al.	6,321,100 B1	11/2001	Parker
5,638,818 A	6/1997	Diab et al.	6,325,761 B1	12/2001	Jay
5,645,440 A	7/1997	Tobler et al.	6,334,065 B1	12/2001	Al-Ali et al.
5,685,299 A	11/1997	Diab et al.	6,343,224 B1	1/2002	Parker
D393,830 S	4/1998	Tobler et al.	6,349,228 B1	2/2002	Kiani et al.
5,743,262 A	4/1998	Lepper, Jr. et al.	6,360,114 B1	3/2002	Diab et al.
5,758,644 A	6/1998	Diab et al.	6,368,283 B1	4/2002	Xu et al.
5,760,910 A	6/1998	Lepper, Jr. et al.	6,371,921 B1	4/2002	Caro et al.
5,769,785 A	6/1998	Diab et al.	6,377,829 B1	4/2002	Al-Ali
5,782,757 A	7/1998	Diab et al.	6,388,240 B2	5/2002	Schulz et al.
5,785,659 A	7/1998	Caro et al.	6,397,091 B2	5/2002	Diab et al.
5,791,347 A	8/1998	Flaherty et al.	6,430,437 B1	8/2002	Marro
5,810,734 A	9/1998	Caro et al.	6,430,525 B1	8/2002	Weber et al.
5,823,950 A	10/1998	Diab et al.	6,463,311 B1	10/2002	Diab
5,830,131 A	11/1998	Caro et al.	6,470,199 B1	10/2002	Kopotic et al.
5,833,618 A	11/1998	Caro et al.	6,501,975 B2	12/2002	Diab et al.
5,853,364 A	12/1998	Baker, Jr. et al.	6,505,059 B1	1/2003	Kollias et al.
5,860,919 A	1/1999	Kiani-Azarbayjany et al.	6,515,273 B2	2/2003	Al-Ali
5,890,929 A	4/1999	Mills et al.	6,519,486 B1	2/2003	Edgar et al.
5,904,654 A	5/1999	Wohltmann et al.	6,519,487 B1	2/2003	Parker
5,919,134 A	7/1999	Diab	6,525,386 B1	2/2003	Mills et al.
5,934,925 A	8/1999	Tobler et al.	6,526,300 B1	2/2003	Kiani et al.
5,940,182 A	8/1999	Lepper, Jr. et al.	6,541,756 B2	4/2003	Schulz et al.
5,995,855 A	11/1999	Kiani et al.	6,542,764 B1	4/2003	Al-Ali et al.
5,997,343 A	12/1999	Mills et al.	6,580,086 B1	6/2003	Schulz et al.
6,002,952 A	12/1999	Diab et al.	6,584,336 B1	6/2003	Ali et al.
6,011,986 A	1/2000	Diab et al.	6,595,316 B2	7/2003	Cybulski et al.
6,027,452 A	2/2000	Flaherty et al.	6,597,932 B2	7/2003	Tian et al.
6,036,642 A	3/2000	Diab et al.	6,597,933 B2	7/2003	Kiani et al.
6,045,509 A	4/2000	Caro et al.	6,606,511 B1	8/2003	Ali et al.
			6,632,181 B2	10/2003	Flaherty et al.
			6,639,668 B1	10/2003	Trepagnier
			6,640,116 B2	10/2003	Diab
			6,643,530 B2	11/2003	Diab et al.
			6,650,917 B2	11/2003	Diab et al.
			6,654,624 B2	11/2003	Diab et al.
			6,658,276 B2	12/2003	Kiani et al.
			6,661,161 B1	12/2003	Lanzo et al.
			6,671,531 B2	12/2003	Al-Ali et al.
			6,678,543 B2	1/2004	Diab et al.
			6,684,090 B2	1/2004	Ali et al.
			6,684,091 B2	1/2004	Parker
			6,697,656 B1	2/2004	Al-Ali
			6,697,657 B1	2/2004	Shehada et al.
			6,697,658 B2	2/2004	Al-Ali
			RE38,476 E	3/2004	Diab et al.
			6,699,194 B1	3/2004	Diab et al.
			6,714,804 B2	3/2004	Al-Ali et al.
			RE38,492 E	4/2004	Diab et al.
			6,721,582 B2	4/2004	Trepagnier et al.
			6,721,585 B1	4/2004	Parker

(56)

References Cited

U.S. PATENT DOCUMENTS

6,725,075	B2	4/2004	Al-Ali	7,371,981	B2	5/2008	Abdul-Hafiz
6,728,560	B2	4/2004	Kollias et al.	7,373,193	B2	5/2008	Al-Ali et al.
6,735,459	B2	5/2004	Parker	7,373,194	B2	5/2008	Weber et al.
6,745,060	B2	6/2004	Diab et al.	7,376,453	B1	5/2008	Diab et al.
6,760,607	B2	7/2004	Al-Ali	7,377,794	B2	5/2008	Al-Ali et al.
6,770,028	B1	8/2004	Ali et al.	7,377,899	B2	5/2008	Weber et al.
6,771,994	B2	8/2004	Kiani et al.	7,383,070	B2	6/2008	Diab et al.
6,792,300	B1	9/2004	Diab et al.	7,415,297	B2	8/2008	Al-Ali et al.
6,813,511	B2	11/2004	Diab et al.	7,428,432	B2	9/2008	Ali et al.
6,816,741	B2	11/2004	Diab	7,438,683	B2	10/2008	Al-Ali et al.
6,822,564	B2	11/2004	Al-Ali	7,440,787	B2	10/2008	Diab
6,826,419	B2	11/2004	Diab et al.	7,454,240	B2	11/2008	Diab et al.
6,830,711	B2	12/2004	Mills et al.	7,467,002	B2	12/2008	Weber et al.
6,850,787	B2	2/2005	Weber et al.	7,469,157	B2	12/2008	Diab et al.
6,850,788	B2	2/2005	Al-Ali	7,471,969	B2	12/2008	Diab et al.
6,852,083	B2	2/2005	Caro et al.	7,471,971	B2	12/2008	Diab et al.
6,861,639	B2	3/2005	Al-Ali	7,483,729	B2	1/2009	Al-Ali et al.
6,898,452	B2	5/2005	Al-Ali et al.	7,483,730	B2	1/2009	Diab et al.
6,920,345	B2	7/2005	Al-Ali et al.	7,489,958	B2	2/2009	Diab et al.
6,931,268	B1	8/2005	Kiani-Azarbayjany et al.	7,496,391	B2	2/2009	Diab et al.
6,934,570	B2	8/2005	Kiani et al.	7,496,393	B2	2/2009	Diab et al.
6,939,305	B2	9/2005	Flaherty et al.	D587,657	S	3/2009	Al-Ali et al.
6,943,348	B1	9/2005	Coffin, IV	7,499,741	B2	3/2009	Diab et al.
6,950,687	B2	9/2005	Al-Ali	7,499,835	B2	3/2009	Weber et al.
6,961,598	B2	11/2005	Diab	7,500,950	B2	3/2009	Al-Ali et al.
6,970,792	B1	11/2005	Diab	7,509,154	B2	3/2009	Diab et al.
6,979,812	B2	12/2005	Al-Ali	7,509,494	B2	3/2009	Al-Ali
6,985,764	B2	1/2006	Mason et al.	7,510,849	B2	3/2009	Schurman et al.
6,993,371	B2	1/2006	Kiani et al.	7,526,328	B2	4/2009	Diab et al.
6,996,427	B2	2/2006	Ali et al.	7,530,942	B1	5/2009	Diab
6,999,904	B2	2/2006	Weber et al.	7,530,949	B2	5/2009	Al Ali et al.
7,003,338	B2	2/2006	Weber et al.	7,530,955	B2	5/2009	Diab et al.
7,003,339	B2	2/2006	Diab et al.	7,563,110	B2	7/2009	Al-Ali et al.
7,015,451	B2	3/2006	Dalke et al.	7,596,398	B2	9/2009	Al-Ali et al.
7,024,233	B2	4/2006	Ali et al.	7,618,375	B2	11/2009	Flaherty
7,027,849	B2	4/2006	Al-Ali	D606,659	S	12/2009	Kiani et al.
7,030,749	B2	4/2006	Al-Ali	7,647,083	B2	1/2010	Al-Ali et al.
7,039,449	B2	5/2006	Al-Ali	D609,193	S	2/2010	Al-Ali et al.
7,041,060	B2	5/2006	Flaherty et al.	D614,305	S	4/2010	Al-Ali et al.
7,044,918	B2	5/2006	Diab	RE41,317	E	5/2010	Parker
7,067,893	B2	6/2006	Mills et al.	7,729,733	B2	6/2010	Al-Ali et al.
7,096,052	B2	8/2006	Mason et al.	7,734,320	B2	6/2010	Al-Ali
7,096,054	B2	8/2006	Abdul-Hafiz et al.	7,761,127	B2	7/2010	Al-Ali et al.
7,132,641	B2	11/2006	Schulz et al.	7,761,128	B2	7/2010	Al-Ali et al.
7,142,901	B2	11/2006	Kiani et al.	7,764,982	B2	7/2010	Dalke et al.
7,149,561	B2	12/2006	Diab	D621,516	S	8/2010	Kiani et al.
7,186,966	B2	3/2007	Al-Ali	7,791,155	B2	9/2010	Diab
7,190,261	B2	3/2007	Al-Ali	7,801,581	B2	9/2010	Diab
7,215,984	B2	5/2007	Diab	7,822,452	B2	10/2010	Schurman et al.
7,215,986	B2	5/2007	Diab	RE41,912	E	11/2010	Parker
7,221,971	B2	5/2007	Diab	7,844,313	B2	11/2010	Kiani et al.
7,225,006	B2	5/2007	Al-Ali et al.	7,844,314	B2	11/2010	Al-Ali
7,225,007	B2	5/2007	Al-Ali	7,844,315	B2	11/2010	Al-Ali
RE39,672	E	6/2007	Shehada et al.	7,865,222	B2	1/2011	Weber et al.
7,239,905	B2	7/2007	Kiani-Azarbayjany et al.	7,873,497	B2	1/2011	Weber et al.
7,245,953	B1	7/2007	Parker	7,880,606	B2	2/2011	Al-Ali
7,254,429	B2	8/2007	Schurman et al.	7,880,626	B2	2/2011	Al-Ali et al.
7,254,431	B2	8/2007	Al-Ali	7,891,355	B2	2/2011	Al-Ali et al.
7,254,433	B2	8/2007	Diab et al.	7,894,868	B2	2/2011	Al-Ali et al.
7,254,434	B2	8/2007	Schulz et al.	7,899,507	B2	3/2011	Al-Ali et al.
7,272,425	B2	9/2007	Al-Ali	7,899,518	B2	3/2011	Trepagnier et al.
7,274,955	B2	9/2007	Kiani et al.	7,904,132	B2	3/2011	Weber et al.
D554,263	S	10/2007	Al-Ali	7,909,772	B2	3/2011	Popov et al.
7,280,858	B2	10/2007	Al-Ali et al.	7,910,875	B2	3/2011	Al-Ali
7,289,835	B2	10/2007	Mansfield et al.	7,919,713	B2	4/2011	Al-Ali et al.
7,292,883	B2	11/2007	De Felice et al.	7,937,128	B2	5/2011	Al-Ali
7,295,866	B2	11/2007	Al-Ali	7,937,129	B2	5/2011	Mason et al.
7,328,053	B1	2/2008	Diab et al.	7,937,130	B2	5/2011	Diab et al.
7,332,784	B2	2/2008	Mills et al.	7,941,199	B2	5/2011	Kiani
7,340,287	B2	3/2008	Mason et al.	7,951,086	B2	5/2011	Flaherty et al.
7,341,559	B2	3/2008	Schulz et al.	7,957,780	B2	6/2011	Lamego et al.
7,343,186	B2	3/2008	Lamego et al.	7,962,188	B2	6/2011	Kiani et al.
D566,282	S	4/2008	Al-Ali et al.	7,962,190	B1	6/2011	Diab et al.
7,355,512	B1	4/2008	Al-Ali	7,976,472	B2	7/2011	Kiani
7,356,365	B2	4/2008	Schurman	7,988,637	B2	8/2011	Diab
				7,990,382	B2	8/2011	Kiani
				7,991,446	B2	8/2011	Al-Ali et al.
				8,000,761	B2	8/2011	Al-Ali
				8,008,088	B2	8/2011	Bellott et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

RE42,753 E	9/2011	Kiani-Azarbayjany et al.	8,509,867 B2	8/2013	Workman et al.
8,019,400 B2	9/2011	Diab et al.	8,515,509 B2	8/2013	Bruinsma et al.
8,028,701 B2	10/2011	Al-Ali et al.	8,523,781 B2	9/2013	Al-Ali
8,029,765 B2	10/2011	Bellott et al.	8,529,301 B2	9/2013	Al-Ali et al.
8,036,727 B2	10/2011	Schurman et al.	8,532,727 B2	9/2013	Ali et al.
8,036,728 B2	10/2011	Diab et al.	8,532,728 B2	9/2013	Diab et al.
8,046,040 B2	10/2011	Ali et al.	D692,145 S	10/2013	Al-Ali et al.
8,046,041 B2	10/2011	Diab et al.	8,547,209 B2	10/2013	Kiani et al.
8,046,042 B2	10/2011	Diab et al.	8,548,548 B2	10/2013	Al-Ali
8,048,040 B2	11/2011	Kiani	8,548,549 B2	10/2013	Schurman et al.
8,050,728 B2	11/2011	Al-Ali et al.	8,548,550 B2	10/2013	Al-Ali et al.
RE43,169 E	2/2012	Parker	8,560,032 B2	10/2013	Al-Ali et al.
8,118,620 B2	2/2012	Al-Ali et al.	8,560,034 B1	10/2013	Diab et al.
8,126,528 B2	2/2012	Diab et al.	8,570,167 B2	10/2013	Al-Ali
8,128,572 B2	3/2012	Diab et al.	8,570,503 B2	10/2013	Vo et al.
8,130,105 B2	3/2012	Al-Ali et al.	8,571,617 B2	10/2013	Reichgott et al.
8,145,287 B2	3/2012	Diab et al.	8,571,618 B1	10/2013	Lamego et al.
8,150,487 B2	4/2012	Diab et al.	8,571,619 B2	10/2013	Al-Ali et al.
8,175,672 B2	5/2012	Parker	8,577,431 B2	11/2013	Lamego et al.
8,180,420 B2	5/2012	Diab et al.	8,581,732 B2	11/2013	Al-Ali et al.
8,182,443 B1	5/2012	Kiani	8,584,345 B2	11/2013	Al-Ali et al.
8,185,180 B2	5/2012	Diab et al.	8,588,880 B2	11/2013	Abdul-Hafiz et al.
8,190,223 B2	5/2012	Al-Ali et al.	8,600,467 B2	12/2013	Al-Ali et al.
8,190,227 B2	5/2012	Diab et al.	8,606,342 B2	12/2013	Diab
8,203,438 B2	6/2012	Kiani et al.	8,626,255 B2	1/2014	Al-Ali et al.
8,203,704 B2	6/2012	Merritt et al.	8,630,691 B2	1/2014	Lamego et al.
8,204,566 B2	6/2012	Schurman et al.	8,634,889 B2	1/2014	Al-Ali et al.
8,219,172 B2	7/2012	Schurman et al.	8,641,631 B2	2/2014	Sierra et al.
8,224,411 B2	7/2012	Al-Ali et al.	8,652,060 B2	2/2014	Al-Ali
8,228,181 B2	7/2012	Al-Ali	8,663,107 B2	3/2014	Kiani
8,229,533 B2	7/2012	Diab et al.	8,666,468 B1	3/2014	Al-Ali
8,233,955 B2	7/2012	Al-Ali et al.	8,667,967 B2	3/2014	Al-Ali et al.
8,244,325 B2	8/2012	Al-Ali et al.	8,670,811 B2	3/2014	O'Reilly
8,255,026 B1	8/2012	Al-Ali	8,670,814 B2	3/2014	Diab et al.
8,255,027 B2	8/2012	Al-Ali et al.	8,676,286 B2	3/2014	Weber et al.
8,255,028 B2	8/2012	Al-Ali et al.	8,682,407 B2	3/2014	Al-Ali
8,260,577 B2	9/2012	Weber et al.	RE44,823 E	4/2014	Parker
8,265,723 B1	9/2012	McHale et al.	RE44,875 E	4/2014	Kiani et al.
8,274,360 B2	9/2012	Sampath et al.	8,690,799 B2	4/2014	Telfort et al.
8,301,217 B2	10/2012	Al-Ali et al.	8,700,112 B2	4/2014	Kiani
8,306,596 B2	11/2012	Schurman et al.	8,702,627 B2	4/2014	Telfort et al.
8,310,336 B2	11/2012	Muhsin et al.	8,706,179 B2	4/2014	Parker
8,315,683 B2	11/2012	Al-Ali et al.	8,712,494 B1	4/2014	MacNeish, III et al.
RE43,860 E	12/2012	Parker	8,715,206 B2	5/2014	Telfort et al.
8,337,403 B2	12/2012	Al-Ali et al.	8,718,735 B2	5/2014	Lamego et al.
8,346,330 B2	1/2013	Lamego	8,718,737 B2	5/2014	Diab et al.
8,353,842 B2	1/2013	Al-Ali et al.	8,718,738 B2	5/2014	Blank et al.
8,355,766 B2	1/2013	MacNeish, III et al.	8,720,249 B2	5/2014	Al-Ali
8,359,080 B2	1/2013	Diab et al.	8,721,541 B2	5/2014	Al-Ali et al.
8,364,223 B2	1/2013	Al-Ali et al.	8,721,542 B2	5/2014	Al-Ali et al.
8,364,226 B2	1/2013	Diab et al.	8,723,677 B1	5/2014	Kiani
8,374,665 B2	2/2013	Lamego	8,740,792 B1	6/2014	Kiani et al.
8,385,995 B2	2/2013	Al-Ali et al.	8,754,776 B2	6/2014	Poeze et al.
8,385,996 B2	2/2013	Smith et al.	8,755,535 B2	6/2014	Telfort et al.
8,388,353 B2	3/2013	Kiani et al.	8,755,856 B2	6/2014	Diab et al.
8,399,822 B2	3/2013	Al-Ali	8,755,872 B1	6/2014	Marinow
8,401,602 B2	3/2013	Kiani	8,761,850 B2	6/2014	Lamego
8,405,608 B2	3/2013	Al-Ali et al.	8,764,671 B2	7/2014	Kiani
8,414,499 B2	4/2013	Al-Ali et al.	8,768,423 B2	7/2014	Shakespeare et al.
8,418,524 B2	4/2013	Al-Ali	8,771,204 B2	7/2014	Telfort et al.
8,423,106 B2	4/2013	Lamego et al.	8,777,634 B2	7/2014	Kiani et al.
8,428,967 B2	4/2013	Olsen et al.	8,781,543 B2	7/2014	Diab et al.
8,430,817 B1	4/2013	Al-Ali et al.	8,781,544 B2	7/2014	Al-Ali et al.
8,437,825 B2	5/2013	Dalvi et al.	8,781,549 B2	7/2014	Al-Ali et al.
8,455,290 B2	6/2013	Siskavich	8,788,003 B2	7/2014	Schurman et al.
8,457,703 B2	6/2013	Al-Ali	8,790,268 B2	7/2014	Al-Ali
8,457,707 B2	6/2013	Kiani	8,801,613 B2	8/2014	Al-Ali et al.
8,463,349 B2	6/2013	Diab et al.	8,821,397 B2	9/2014	Al-Ali et al.
8,466,286 B2	6/2013	Bellot et al.	8,821,415 B2	9/2014	Al-Ali et al.
8,471,713 B2	6/2013	Poeze et al.	8,830,449 B1	9/2014	Lamego et al.
8,473,020 B2	6/2013	Kiani et al.	8,831,700 B2	9/2014	Schurman et al.
8,483,787 B2	7/2013	Al-Ali et al.	8,840,549 B2	9/2014	Al-Ali et al.
8,489,364 B2	7/2013	Weber et al.	8,847,740 B2	9/2014	Kiani et al.
8,498,684 B2	7/2013	Weber et al.	8,849,365 B2	9/2014	Smith et al.
8,504,128 B2	8/2013	Blank et al.	8,852,094 B2	10/2014	Al-Ali et al.
			8,852,994 B2	10/2014	Wojtczuk et al.
			8,868,147 B2	10/2014	Stippick et al.
			8,868,150 B2	10/2014	Al-Ali et al.
			8,870,792 B2	10/2014	Al-Ali et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

8,886,271	B2	11/2014	Kiani et al.	9,368,671	B2	6/2016	Wojtczuk et al.
8,888,539	B2	11/2014	Al-Ali et al.	9,370,325	B2	6/2016	Al-Ali et al.
8,888,708	B2	11/2014	Diab et al.	9,370,326	B2	6/2016	McHale et al.
8,892,180	B2	11/2014	Weber et al.	9,370,335	B2	6/2016	Al-Ali et al.
8,897,847	B2	11/2014	Al-Ali	9,375,185	B2	6/2016	Ali et al.
8,909,310	B2	12/2014	Lamego et al.	9,386,953	B2	7/2016	Al-Ali
8,911,377	B2	12/2014	Al-Ali	9,386,961	B2	7/2016	Al-Ali et al.
8,912,909	B2	12/2014	Al-Ali et al.	9,392,945	B2	7/2016	Al-Ali et al.
8,920,317	B2	12/2014	Al-Ali et al.	9,397,448	B2	7/2016	Al-Ali et al.
8,921,699	B2	12/2014	Al-Ali et al.	9,408,542	B1	8/2016	Kinast et al.
8,922,382	B2	12/2014	Al-Ali et al.	9,436,645	B2	9/2016	Al-Ali et al.
8,929,964	B2	1/2015	Al-Ali et al.	9,445,759	B1	9/2016	Lamego et al.
8,942,777	B2	1/2015	Diab et al.	9,466,919	B2	10/2016	Kiani et al.
8,948,834	B2	2/2015	Diab et al.	9,474,474	B2	10/2016	Lamego et al.
8,948,835	B2	2/2015	Diab	9,480,422	B2	11/2016	Al-Ali
8,965,471	B2	2/2015	Lamego	9,480,435	B2	11/2016	Olsen
8,983,564	B2	3/2015	Al-Ali	9,492,110	B2	11/2016	Al-Ali et al.
8,989,831	B2	3/2015	Al-Ali et al.	9,510,779	B2	12/2016	Poeze et al.
8,996,085	B2	3/2015	Kiani et al.	9,517,024	B2	12/2016	Kiani et al.
8,998,809	B2	4/2015	Kiani	9,532,722	B2	1/2017	Lamego et al.
9,028,429	B2	5/2015	Telfort et al.	9,538,949	B2	1/2017	Al-Ali et al.
9,037,207	B2	5/2015	Al-Ali et al.	9,538,980	B2	1/2017	Telfort et al.
9,060,721	B2	6/2015	Reichgott et al.	9,549,696	B2	1/2017	Lamego et al.
9,066,666	B2	6/2015	Kiani	9,554,737	B2	1/2017	Schurman et al.
9,066,680	B1	6/2015	Al-Ali et al.	9,560,996	B2	2/2017	Kiani
9,072,474	B2	7/2015	Al-Ali et al.	9,560,998	B2	2/2017	Al-Ali et al.
9,078,560	B2	7/2015	Schurman et al.	9,566,019	B2	2/2017	Al-Ali et al.
9,084,569	B2	7/2015	Weber et al.	9,579,039	B2	2/2017	Jansen et al.
9,095,316	B2	8/2015	Welch et al.	9,591,975	B2	3/2017	Dalvi et al.
9,106,038	B2	8/2015	Telfort et al.	9,622,693	B2	4/2017	Diab
9,107,625	B2	8/2015	Telfort et al.	2007/0282478	A1	12/2007	Al-Ali et al.
9,107,626	B2	8/2015	Al-Ali et al.	2009/0247984	A1	10/2009	Lamego et al.
9,113,831	B2	8/2015	Al-Ali	2009/0275813	A1	11/2009	Davis
9,113,832	B2	8/2015	Al-Ali	2009/0275844	A1	11/2009	Al-Ali
9,119,595	B2	9/2015	Lamego	2010/0004518	A1	1/2010	Vo et al.
9,131,881	B2	9/2015	Diab et al.	2010/0030040	A1	2/2010	Poeze et al.
9,131,882	B2	9/2015	Al-Ali et al.	2010/0069725	A1	3/2010	Al-Ali
9,131,883	B2	9/2015	Al-Ali	2010/0261979	A1	10/2010	Kiani
9,131,917	B2	9/2015	Telfort et al.	2010/0317936	A1	12/2010	Al-Ali et al.
9,138,180	B1	9/2015	Coverston et al.	2011/0001605	A1	1/2011	Kiani et al.
9,138,182	B2	9/2015	Al-Ali et al.	2011/0082711	A1	4/2011	Poeze et al.
9,138,192	B2	9/2015	Weber et al.	2011/0105854	A1	5/2011	Kiani et al.
9,142,117	B2	9/2015	Muhsin et al.	2011/0125060	A1	5/2011	Telfort et al.
9,153,112	B1	10/2015	Kiani et al.	2011/0172967	A1	7/2011	Al-Ali et al.
9,153,121	B2	10/2015	Kiani et al.	2011/0208015	A1	8/2011	Welch et al.
9,161,696	B2	10/2015	Al-Ali et al.	2011/0209915	A1	9/2011	Telfort et al.
9,161,713	B2	10/2015	Al-Ali et al.	2011/0213212	A1	9/2011	Al-Ali
9,167,995	B2	10/2015	Lamego et al.	2011/0230733	A1	9/2011	Al-Ali
9,176,141	B2	11/2015	Al-Ali et al.	2011/0237911	A1	9/2011	Lamego et al.
9,186,102	B2	11/2015	Bruinsma et al.	2011/0237969	A1	9/2011	Eckerbom et al.
9,192,312	B2	11/2015	Al-Ali	2011/0288383	A1	11/2011	Diab
9,192,329	B2	11/2015	Al-Ali	2012/0041316	A1	2/2012	Al-Ali et al.
9,192,351	B1	11/2015	Telfort et al.	2012/0046557	A1	2/2012	Kiani
9,195,385	B2	11/2015	Al-Ali et al.	2012/0059267	A1	3/2012	Lamego et al.
9,211,072	B2	12/2015	Kiani	2012/0088984	A1	4/2012	Al-Ali et al.
9,211,095	B1	12/2015	Al-Ali	2012/0116175	A1	5/2012	Al-Ali et al.
9,218,454	B2	12/2015	Kiani et al.	2012/0165629	A1	6/2012	Merritt et al.
9,226,696	B2	1/2016	Kiani	2012/0179006	A1	7/2012	Jansen et al.
9,241,662	B2	1/2016	Al-Ali et al.	2012/0209082	A1	8/2012	Al-Ali
9,245,668	B1	1/2016	Vo et al.	2012/0209084	A1	8/2012	Olsen et al.
9,259,185	B2	2/2016	Abdul-Hafiz et al.	2012/0227739	A1	9/2012	Kiani
9,267,572	B2	2/2016	Barker et al.	2012/0265039	A1	10/2012	Kiani
9,277,880	B2	3/2016	Poeze et al.	2012/0283524	A1	11/2012	Kiani et al.
9,289,167	B2	3/2016	Diab et al.	2012/0286955	A1	11/2012	Welch et al.
9,295,421	B2	3/2016	Kiani et al.	2012/0296178	A1	11/2012	Lamego et al.
9,307,928	B1	4/2016	Al-Ali et al.	2012/0302894	A1	11/2012	Diab et al.
9,323,894	B2	4/2016	Kiani	2012/0319816	A1	12/2012	Al-Ali
D755,392	S	5/2016	Hwang et al.	2012/0330112	A1	12/2012	Lamego et al.
9,326,712	B1	5/2016	Kiani	2013/0023775	A1	1/2013	Lamego et al.
9,333,316	B2	5/2016	Kiani	2013/0041591	A1	2/2013	Lamego
9,339,220	B2	5/2016	Lamego et al.	2013/0045685	A1	2/2013	Kiani
9,341,565	B2	5/2016	Lamego et al.	2013/0046204	A1	2/2013	Lamego et al.
9,351,673	B2	5/2016	Diab et al.	2013/0060108	A1	3/2013	Schurman et al.
9,351,675	B2	5/2016	Al-Ali et al.	2013/0060147	A1	3/2013	Welch et al.
9,364,181	B2	6/2016	Kiani et al.	2013/0079610	A1	3/2013	Al-Ali
				2013/0096405	A1	4/2013	Garfio
				2013/0096936	A1	4/2013	Sampath et al.
				2013/0109935	A1	5/2013	Al-Ali et al.
				2013/0162433	A1	6/2013	Muhsin et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2013/0178749	A1	7/2013	Lamego	2014/0316217	A1	10/2014	Purdon et al.
2013/0190581	A1	7/2013	Al-Ali et al.	2014/0316218	A1	10/2014	Purdon et al.
2013/0197328	A1	8/2013	Diab et al.	2014/0316228	A1	10/2014	Blank et al.
2013/0211214	A1	8/2013	Olsen	2014/0323825	A1	10/2014	Al-Ali et al.
2013/0243021	A1	9/2013	Siskavich	2014/0323897	A1	10/2014	Brown et al.
2013/0253334	A1	9/2013	Al-Ali et al.	2014/0323898	A1	10/2014	Purdon et al.
2013/0267804	A1	10/2013	Al-Ali	2014/0330092	A1	11/2014	Al-Ali et al.
2013/0274571	A1	10/2013	Diab et al.	2014/0330098	A1	11/2014	Merritt et al.
2013/0296672	A1	11/2013	O'Neil et al.	2014/0330099	A1	11/2014	Al-Ali et al.
2013/0296713	A1	11/2013	Al-Ali et al.	2014/0333440	A1	11/2014	Kiani
2013/0317327	A1	11/2013	Al-Ali et al.	2014/0336481	A1	11/2014	Shakespeare et al.
2013/0317370	A1	11/2013	Dalvi et al.	2014/0343436	A1	11/2014	Kiani
2013/0324808	A1	12/2013	Al-Ali et al.	2014/0357966	A1	12/2014	Al-Ali et al.
2013/0324817	A1	12/2013	Diab	2015/0005600	A1	1/2015	Blank et al.
2013/0331660	A1	12/2013	Al-Ali et al.	2015/0011907	A1	1/2015	Purdon et al.
2013/0331670	A1	12/2013	Kiani	2015/0012231	A1	1/2015	Poeze et al.
2013/0338461	A1	12/2013	Lamego et al.	2015/0018650	A1	1/2015	Al-Ali et al.
2014/0012100	A1	1/2014	Al-Ali et al.	2015/0025406	A1	1/2015	Al-Ali
2014/0025306	A1	1/2014	Weber et al.	2015/0032029	A1	1/2015	Al-Ali et al.
2014/0031650	A1	1/2014	Weber et al.	2015/0038859	A1	2/2015	Dalvi et al.
2014/0034353	A1	2/2014	Al-Ali et al.	2015/0045637	A1	2/2015	Dalvi
2014/0051952	A1	2/2014	Reichgott et al.	2015/0051462	A1	2/2015	Olsen
2014/0051953	A1	2/2014	Lamego et al.	2015/0080754	A1	3/2015	Purdon et al.
2014/0051954	A1	2/2014	Al-Ali et al.	2015/0087936	A1	3/2015	Al-Ali et al.
2014/0058230	A1	2/2014	Abdul-Hafiz et al.	2015/0094546	A1	4/2015	Al-Ali
2014/0066783	A1	3/2014	Kiani et al.	2015/0097701	A1	4/2015	Al-Ali et al.
2014/0073167	A1	3/2014	Al-Ali et al.	2015/0099950	A1	4/2015	Al-Ali et al.
2014/0077956	A1	3/2014	Sampath et al.	2015/0099951	A1	4/2015	Al-Ali et al.
2014/0081097	A1	3/2014	Al-Ali et al.	2015/0099955	A1	4/2015	Al-Ali et al.
2014/0081100	A1	3/2014	Muhsin et al.	2015/0101844	A1	4/2015	Al-Ali et al.
2014/0081175	A1	3/2014	Telfort	2015/0106121	A1	4/2015	Muhsin et al.
2014/0094667	A1	4/2014	Schurman et al.	2015/0112151	A1	4/2015	Muhsin et al.
2014/0100434	A1	4/2014	Diab et al.	2015/0116076	A1	4/2015	Al-Ali et al.
2014/0114199	A1	4/2014	Lamego et al.	2015/0126830	A1	5/2015	Schurman et al.
2014/0120564	A1	5/2014	Workman et al.	2015/0133755	A1	5/2015	Smith et al.
2014/0121482	A1	5/2014	Merritt et al.	2015/0165312	A1	6/2015	Kiani
2014/0121483	A1	5/2014	Kiani	2015/0196237	A1	7/2015	Lamego
2014/0125495	A1	5/2014	Al-Ali	2015/0216459	A1	8/2015	Al-Ali et al.
2014/0127137	A1	5/2014	Bellott et al.	2015/0230755	A1	8/2015	Al-Ali et al.
2014/0128696	A1	5/2014	Al-Ali	2015/0238722	A1	8/2015	Al-Ali
2014/0128699	A1	5/2014	Al-Ali et al.	2015/0245773	A1	9/2015	Lamego et al.
2014/0129702	A1	5/2014	Lamego et al.	2015/0245794	A1	9/2015	Al-Ali
2014/0135588	A1	5/2014	Al-Ali et al.	2015/0257689	A1	9/2015	Al-Ali et al.
2014/0142399	A1	5/2014	Al-Ali et al.	2015/0272514	A1	10/2015	Kiani et al.
2014/0142401	A1	5/2014	Al-Ali et al.	2015/0351697	A1	12/2015	Weber et al.
2014/0142402	A1	5/2014	Al-Ali et al.	2015/0351704	A1	12/2015	Kiani et al.
2014/0155712	A1	6/2014	Lamego et al.	2015/0359429	A1	12/2015	Al-Ali et al.
2014/0163344	A1	6/2014	Al-Ali	2015/0366472	A1	12/2015	Kiani
2014/0163402	A1	6/2014	Lamego et al.	2015/0366507	A1	12/2015	Blank
2014/0166076	A1	6/2014	Kiani et al.	2015/0374298	A1	12/2015	Al-Ali et al.
2014/0171763	A1	6/2014	Diab	2015/0380875	A1	12/2015	Coverston et al.
2014/0180038	A1	6/2014	Kiani	2016/0000362	A1	1/2016	Diab et al.
2014/0180154	A1	6/2014	Sierra et al.	2016/0007930	A1	1/2016	Weber et al.
2014/0180160	A1	6/2014	Brown et al.	2016/0029932	A1	2/2016	Al-Ali
2014/0187973	A1	7/2014	Brown et al.	2016/0045118	A1	2/2016	Kiani
2014/0194709	A1	7/2014	Al-Ali et al.	2016/0051205	A1	2/2016	Al-Ali et al.
2014/0194711	A1	7/2014	Al-Ali	2016/0058338	A1	3/2016	Schurman et al.
2014/0194766	A1	7/2014	Al-Ali et al.	2016/0058347	A1	3/2016	Reichgott et al.
2014/0200420	A1	7/2014	Al-Ali	2016/0066823	A1	3/2016	Al-Ali et al.
2014/0200422	A1	7/2014	Weber et al.	2016/0066824	A1	3/2016	Al-Ali et al.
2014/0206963	A1	7/2014	Al-Ali	2016/0066879	A1	3/2016	Telfort et al.
2014/0213864	A1	7/2014	Abdul-Hafiz et al.	2016/0072429	A1	3/2016	Kiani et al.
2014/0243627	A1	8/2014	Diab et al.	2016/0081552	A1	3/2016	Wojtczuk et al.
2014/0266790	A1	9/2014	Al-Ali et al.	2016/0095543	A1	4/2016	Telfort et al.
2014/0275808	A1	9/2014	Poeze et al.	2016/0095548	A1	4/2016	Al-Ali et al.
2014/0275835	A1	9/2014	Lamego et al.	2016/0103598	A1	4/2016	Al-Ali et al.
2014/0275871	A1	9/2014	Lamego et al.	2016/0113527	A1	4/2016	Al-Ali et al.
2014/0275872	A1	9/2014	Merritt et al.	2016/0143548	A1	5/2016	Al-Ali
2014/0275881	A1	9/2014	Lamego et al.	2016/0166182	A1	6/2016	Al-Ali et al.
2014/0276115	A1	9/2014	Dalvi et al.	2016/0166183	A1	6/2016	Poeze et al.
2014/0288400	A1	9/2014	Diab et al.	2016/0166188	A1	6/2016	Bruinsma et al.
2014/0296664	A1	10/2014	Bruinsma et al.	2016/0166210	A1	6/2016	Al-Ali
2014/0303520	A1	10/2014	Telfort et al.	2016/0192869	A1	7/2016	Kiani et al.
2014/0309506	A1	10/2014	Lamego et al.	2016/0196388	A1	7/2016	Lamego
2014/0309559	A1	10/2014	Telfort et al.	2016/0197436	A1	7/2016	Barker et al.
				2016/0213281	A1	7/2016	Eckerbom et al.
				2016/0228043	A1	8/2016	O'Neil et al.
				2016/0233632	A1	8/2016	Scruggs et al.
				2016/0234944	A1	8/2016	Schmidt et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2016/0270735	A1	9/2016	Diab et al.
2016/0283665	A1	9/2016	Sampath et al.
2016/0287090	A1	10/2016	Al-Ali et al.
2016/0287786	A1	10/2016	Kiani
2016/0296169	A1	10/2016	McHale et al.
2016/0310052	A1	10/2016	Al-Ali et al.
2016/0314260	A1	10/2016	Kiani
2016/0324486	A1	11/2016	Al-Ali et al.
2016/0324488	A1	11/2016	Olsen
2016/0327984	A1	11/2016	Al-Ali et al.
2016/0328528	A1	11/2016	Al-Ali et al.
2016/0331332	A1	11/2016	Al-Ali
2016/0367173	A1	12/2016	Dalvi et al.
2017/0007134	A1	1/2017	Al-Ali et al.
2017/0007190	A1	1/2017	Al-Ali et al.
2017/0007198	A1	1/2017	Al-Ali et al.
2017/0014084	A1	1/2017	Al-Ali et al.
2017/0021099	A1	1/2017	Al-Ali et al.
2017/0027456	A1	2/2017	Kinast et al.
2017/0042488	A1	2/2017	Muhsin
2017/0055847	A1	3/2017	Kiani et al.
2017/0055851	A1	3/2017	Al-Ali
2017/0055882	A1	3/2017	Al-Ali et al.
2017/0055887	A1	3/2017	Al-Ali
2017/0055896	A1	3/2017	Al-Ali et al.
2017/0079594	A1	3/2017	Telfort et al.
2017/0086723	A1	3/2017	Al-Ali et al.

OTHER PUBLICATIONS

US 9,579,050, 02/2017, Al-Ali (withdrawn)

Smith, Steven W., "The Scientist and Engineer's Guide to Digital Signal Processing", Section 8, 1st Edition, 1997, California Technical Publishing.




FIG. 1A




FIG. 1B




FIG. 1C




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8A




FIG. 8B




FIG. 9




FIG. 10




FIG. 11

SINE SATURATION TRANSFORM

INCORPORATION BY REFERENCE TO ANY
PRIORITY APPLICATIONS

Any and all applications for which a foreign or domestic priority claim is identified in the Application Data Sheet as filed with the present application are incorporated by reference under 37 CFR 1.57 and made a part of this specification.

BACKGROUND OF THE INVENTION

Early detection of low blood oxygen is critical in the medical field, for example in critical care and surgical applications, because an insufficient supply of oxygen can result in brain damage and death in a matter of minutes. Pulse oximetry is a widely accepted noninvasive procedure for measuring the oxygen saturation level of arterial blood, an indicator of oxygen supply. A pulse oximeter typically provides a numerical readout of the patient's oxygen saturation and pulse rate. A pulse oximetry system consists of a sensor attached to a patient, a monitor, and a cable connecting the sensor and monitor. Conventionally, a pulse oximetry sensor has both red (RD) and infrared (IR) light-emitting diode (LED) emitters and a photodiode detector. The pulse oximeter measurements are based upon the absorption by arterial blood of the two wavelengths emitted by the sensor. The pulse oximeter alternately activates the RD and IR sensor emitters and reads the resulting RD and IR sensor signals, i.e. the current generated by the photodiode in proportion to the detected RD and IR light intensity, in order to derive an arterial oxygen saturation value, as is well-known in the art. A pulse oximeter contains circuitry for controlling the sensor, processing the sensor signals and displaying the patient's oxygen saturation and pulse rate.

SUMMARY OF THE INVENTION

FIG. 1A illustrates a plethysmograph waveform **110**, which is a display of blood volume, shown along the ordinate **101**, over time, shown along the abscissa **102**. The shape of the plethysmograph waveform **110** is a function of heart stroke volume, pressure gradient, arterial elasticity and peripheral resistance. Ideally, the waveform **110** displays a short, steep inflow phase **111** during ventricular systole followed by a typically three to four times longer outflow phase **112** during diastole. A dirotic notch **116** is generally attributed to closure of the aortic valve at the end of ventricular systole.

FIG. 1B illustrates a corresponding RD or IR sensor signal $s(t)$ **130**, such as described above. The typical plethysmograph waveform **110** (FIG. 1A), being a function of blood volume, also provides a light absorption profile. A pulse oximeter, however, does not directly detect light absorption and, hence, does not directly measure the plethysmograph waveform **110**. However, IR or RD sensor signals are 180° out-of-phase versions of the waveform **110**. That is, peak detected intensity **134** occurs at minimum absorption **114** and minimum detected intensity **138** occurs at maximum absorption **118**.

FIG. 1C illustrates the corresponding spectrum of $s(t)$, which is a display of signal spectral magnitude $|S(\omega)|$, shown along the ordinate **105**, versus frequency, shown along the abscissa **106**. The plethysmograph spectrum is depicted under both high signal quality **150** and low signal quality **160** conditions. Low signal quality can result when

a pulse oximeter sensor signal is distorted by motion-artifact and noise. Signal processing technologies such as described in U.S. Pat. No. 5,632,272, assigned to the assignee of the present invention and incorporated by reference herein, allow pulse oximetry to function through patient motion and other low signal quality conditions.

Ideally, plethysmograph energy is concentrated at the pulse rate frequency **172** and associated harmonics **174**, **176**. Accordingly, motion-artifact and noise may be reduced and pulse oximetry measurements improved by filtering out sensor signal frequencies that are not related to the pulse rate. Under low signal quality conditions, however, the frequency spectrum is corrupted and the pulse rate fundamental **152** and harmonics **154**, **156** can be obscured or masked, resulting in errors in the computed pulse rate. In addition, a pulse rate, physiologically, is dynamic, potentially varying significantly between different measurement periods. Hence, maximum plethysmograph energy may not correspond to the computed pulse rate except under high signal quality conditions and stable pulse rates. Further, an oxygen saturation value calculated from an optical density ratio, such as a normalized red over infrared ratio, at the pulse rate frequency can be sensitive to computed pulse rate errors. In order to increase the robustness of oxygen saturation measurements, therefore, it is desirable to improve pulse rate based measurements by identifying sensor signal components that correspond to an optimization, such as maximum signal energy.

One aspect of a signal component processor comprises a physiological signal, a basis function index determined from the signal, a basis function waveform generated according to the index, a component derived from the sensor signal and the waveform, and a physiological measurement responsive to the component. In one embodiment, the component is responsive to the inner product of the sensor signal and the waveform. In another embodiment, the index is a frequency and the waveform is a sinusoid at the frequency. In that embodiment, the signal processor may further comprise a pulse rate estimate derived from the signal wherein the frequency is selected from a window including the pulse rate estimate. The physiological measurement may be an oxygen saturation value responsive to a magnitude of the component.

Another aspect of a signal component processor comprises a signal input, a basis function indicator derived from the signal input, a plurality of basis functions generated according to the indicator, a plurality of characteristics of the signal input corresponding to the basis functions and an optimization of the characteristics so as to identify at least one of said basis functions. In one embodiment, the indicator is a pulse rate estimate and the processor further comprises a window configured to include the pulse rate estimate, and a plurality of frequencies selected from within the window. In another embodiment, the characteristic comprises a plurality of signal remainders corresponding to the basis functions and a plurality of magnitudes of the signal remainders. In that embodiment, the optimization comprises a minima of the magnitudes. In a further embodiment, the characteristic comprises a plurality of components corresponding to the basis functions and a plurality of magnitudes of the components. In this embodiment, the optimization comprises a maxima of the magnitudes.

An aspect of a signal component processing method comprises the steps of receiving a sensor signal, calculating an estimated pulse rate, determining an optimization of the sensor signal proximate the estimated pulse rate, defining a frequency corresponding to the optimization, and outputting

3

a physiological measurement responsive to a component of the sensor signal at the frequency. In one embodiment the determining step comprises the substeps of transforming the sensor signal to a frequency spectrum encompassing the estimated pulse rate and detecting an extrema of the spectrum indicative of the frequency. The transforming step may comprise the substeps of defining a window including the estimated pulse rate, defining a plurality of selected frequencies within the window, canceling the selected frequencies, individually, from the sensor signal to generate a plurality of remainder signals and calculating a plurality of magnitudes of the remainder signals. The detecting step may comprise the substep of locating a minima of the magnitudes.

In another embodiment, the outputting step comprises the substeps of inputting a red (RD) portion and an infrared (IR) portion of the sensor signal, deriving a RD component of the RD portion and an IR component of the IR portion corresponding to the frequency and computing an oxygen saturation based upon a magnitude ratio of the RD component and the IR component. The deriving step may comprise the substeps of generating a sinusoidal waveform at the frequency and selecting the RD component and the IR component utilizing the waveform. The selecting step may comprise the substep of calculating the inner product between the waveform and the RD portion and the inner product between the waveform and the IR portion. The selecting step may comprise the substeps of canceling the waveform from the RD portion and the IR portion, leaving a RD remainder and an IR remainder, and subtracting the RD remainder from the RD portion and the IR remainder from the IR portion.

A further aspect of a signal component processor comprises a first calculator means for deriving an optimization frequency from a pulse rate estimate input and a sensor signal, and a second calculator means for deriving a physiological measurement responsive to a sensor signal component at the frequency. In one embodiment, the first calculator means comprises a signal component transform means for determining a plurality of signal values corresponding to a plurality of selected frequencies within a window including the pulse rate estimate, and a detection means for determining a particular one of the selected frequencies corresponding to an optimization of the sensor signal. The second calculator means may comprise a waveform means for generating a sinusoidal signal at the frequency, a frequency selection means for determining a component of the sensor signal from the sinusoidal signal and a calculator means for deriving a ratio responsive to the component.

BRIEF DESCRIPTION OF THE DRAWINGS

FIGS. 1A-C are graphical representations of a pulse oximetry sensor signal;

FIG. 1A is a typical plethysmograph illustrating blood volume versus time;

FIG. 1B is a pulse oximetry sensor signal illustrating detected light intensity versus time;

FIG. 1C is a pulse oximetry sensor signal spectrum illustrating both high signal quality and low signal quality conditions;

FIGS. 2-3 are magnitude versus frequency graphs for a pulse oximetry sensor signal illustrating an example of signal component processing;

FIG. 2 illustrates a frequency window around an estimated pulse rate; and

FIG. 3 illustrates an associated signal component transform;

4

FIGS. 4-7 are functional block diagrams of one embodiment of a signal component processor;

FIG. 4 is a top-level functional block diagram of a signal component processor;

FIG. 5 is a functional block diagram of a frequency calculator;

FIG. 6 is a functional block diagram of a saturation calculator; and

FIG. 7 is a functional block diagram of one embodiment of a frequency selection;

FIGS. 8A-B are flowcharts of an iterative embodiment of a frequency calculator; and

FIGS. 9-11 are functional block diagrams of another embodiment of a signal component processor;

FIG. 9 is a top-level functional block diagram of a signal component processor;

FIG. 10 is a functional block diagram of an index calculator; and

FIG. 11 is a functional block diagram of a measurement calculator.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

FIGS. 2 and 3 provide graphical illustration examples of signal component processing. Advantageously, signal component processing provides a direct method for the calculation of saturation based on pulse rate. For example, it is not necessary to compute a frequency transform, such as an FFT, which derives an entire frequency spectrum. Rather, signal component processing singles out specific signal components, as described in more detail below. Further, signal component processing advantageously provides a method of refinement for the calculation of saturation based on pulse rate.

FIG. 2 illustrates high and low signal quality sensor signal spectrums 150, 160 as described with respect to FIG. 1C, above. A frequency window 220 is created, including a pulse rate estimate PR 210. A pulse rate estimate can be calculated as disclosed in U.S. Pat. No. 6,002,952, entitled "Signal Processing Apparatus and Method," assigned to the assignee of the present invention and incorporated by reference herein. A search is conducted within this window 220 for a component frequency f_0 at an optimization. In particular, selected frequencies 230, which include PR, are defined within the window 220. The components of a signal $s(t)$ at each of these frequencies 230 are then examined for an optimization indicative of an extrema of energy, power or other signal characteristic. In an alternative embodiment, the components of the signal $s(t)$ are examined for an optimization over a continuous range of frequencies within the window 220.

FIG. 3 illustrates an expanded portion of the graph described with respect to FIG. 2, above. Superimposed on the high signal quality 150 and low signal quality 160 spectrums is a signal component transform 310. In one embodiment, a signal component transform 310 is indicative of sensor signal energy and is calculated at selected signal frequencies 230 within the window 220. A signal component transform 310 has an extrema 320 that indicates, in this embodiment, energy optimization at a particular one 330 of the selected frequencies 230. The extrema 320 can be, for example, a maxima, minima or inflection point. In the embodiment illustrated, each point of the transform 310 is the magnitude of the signal remaining after canceling a sensor signal component at one of the selected frequencies. The extrema 320 is a minima, which indicates that canceling

the corresponding frequency **330** removes the most signal energy. In an alternative embodiment, not illustrated, the transform **310** is calculated as the magnitude of signal components at each of the selected frequencies **230**. In that embodiment, the extrema is a maxima, which indicates the largest energy signal at the corresponding frequency. The result of a signal component transform **310** is identification of a frequency f_0 **330** determined from the frequency of a signal component transform extrema **320**. Frequency f_0 **330** is then used to calculate an oxygen saturation. A signal component transform and corresponding oxygen saturation calculations are described in additional detail with respect to FIGS. 4-8, below. Although signal component processing is described above with respect to identifying a particular frequency within a window including a pulse rate estimate PR, a similar procedure could be performed on 2PR, 3PR etc. resulting in the identification of multiple frequencies f_{01} , f_{02} , etc., which could be used for the calculation of oxygen saturation as well.

Advantageously, a signal component transform **310** is calculated over any set of selected frequencies, unrestricted by the number or spacing of these frequencies. In this manner, a signal component transform **310** differs from a FFT or other standard frequency transforms. For example, a FFT is limited to N evenly-distributed frequencies spaced at a resolution of f_s/N , where N is the number of signal samples and f_s is the sampling frequency. That is, for a FFT, a relatively high sampling rate or a relatively large record length or both are needed to achieve a relatively high resolution in frequency. Signal component processing, as described herein, is not so limited. Further, a signal component transform **310** is advantageously calculated only over a range of frequencies of interest. A FFT or similar frequency transformation may be computationally more burdensome than signal component processing, in part because such a transform is computed over all frequencies within a range determined by the sampling frequency, f_s .

FIGS. 4-7 illustrate one embodiment of a signal component processor. FIG. 4 is a top-level functional block diagram of a signal component processor **400**. The signal component processor **400** has a frequency calculator **410** and a saturation calculator **460**. The frequency calculator **410** has an IR signal input **402**, a pulse rate estimate signal PR input **408** and a component frequency f_0 output **412**. The frequency calculator **410** performs a signal component transform based upon the PR input **408** and determines the f_0 output **412**, as described with respect to FIGS. 2-3, above. The frequency calculator **410** is described in further detail with respect to FIG. 5, below.

In an alternative embodiment, the frequency calculator **410** determines f_0 **412** based upon a RD signal input substituted for, or in addition to, the IR signal input **402**. Similarly, one of ordinary skill in the art will recognize that f_0 can be determined by the frequency calculator **410** based upon one or more inputs responsive to a variety of sensor wavelengths.

The saturation calculator **460** has an IR signal input **402**, a RD signal input **404**, a component frequency f_0 input **412** and an oxygen saturation output, SAT f_0 **462**. The saturation calculator **460** determines values of the IR signal input **402** and the RD signal input **404** at the component frequency f_0 **412** and computes a ratio of those values to determine SAT f_0 **462**, as described with respect to FIG. 6, below. The IR signal input **402** and RD signal input **404** can be expressed as:

$$IR = \begin{bmatrix} IR_0 \\ \vdots \\ IR_{N-1} \end{bmatrix}; \quad (1)$$

$$RD = \begin{bmatrix} RD_0 \\ \vdots \\ RD_{N-1} \end{bmatrix}$$

where N is the number of samples of each signal input.

FIG. 5 shows one embodiment of the frequency calculator **410**. In this particular embodiment, the frequency calculator functions are window generation **520**, frequency cancellation **540**, magnitude calculation **560** and minima determination **580**. Window generation **520**, frequency cancellation **540** and magnitude calculation **560** combine to create a signal component transform **310** (FIG. 3), as described with respect to FIG. 3, above. Minima determination **580** locates the signal component transform extrema **320** (FIG. 3), which identifies f_0 **412**, also described with respect to FIG. 3, above.

As shown in FIG. 5, window generation **520** has a PR input **408** and defines a window **220** (FIG. 3) about PR **210** (FIG. 3) including a set of selected frequencies **230** (FIG. 3)

$$\{f_m; m = 0, \dots, M-1\}; \quad (2)$$

$$f = \begin{bmatrix} f_0 \\ \vdots \\ f_{M-1} \end{bmatrix}$$

where M is the number of selected frequencies **230** (FIG. 3) within the window **220** (FIG. 3). Window generation **520** has a sinusoidal output X_f, Y_f **522**, which is a set of sinusoidal waveforms $x_{n,f}, y_{n,f}$ each corresponding to one of the set of selected frequencies **230** (FIG. 3). Specifically

$$X_f = \begin{bmatrix} x_{0,f} \\ \vdots \\ x_{N-1,f} \end{bmatrix}; \quad (3a)$$

$$Y_f = \begin{bmatrix} y_{0,f} \\ \vdots \\ y_{N-1,f} \end{bmatrix}$$

$$\begin{aligned} x_{n,f} &= \sin(2\pi f n); \\ y_{n,f} &= \cos(2\pi f n) \end{aligned} \quad (3b)$$

Also shown in FIG. 5, the frequency cancellation **540** has IR **402** and X_f, Y_f **522** inputs and a remainder output R_f **542**, which is a set of remainder signals $r_{n,f}$ each corresponding to one of the sinusoidal waveforms $x_{n,f}, y_{n,f}$. For each selected frequency f **230** (FIG. 3), frequency cancellation **540** cancels that frequency component from the input signal IR **402** to generate a remainder signal $r_{n,f}$. In particular, frequency cancellation **540** generates a remainder R_f **542**

$$R_f = \begin{bmatrix} r_{0,f} \\ \vdots \\ r_{N-1,f} \end{bmatrix} \quad (4a)$$

7

-continued

$$R_f = IR - \frac{IR \cdot X_f}{|X_f|^2} X_f - \frac{IR \cdot Y_f}{|Y_f|^2} Y_f \quad (4b)$$

Additionally, as shown in FIG. 5, the magnitude calculation 560 has a remainder input R_f 542 and generates a magnitude output W_f 562, where

$$W_f = |R_f| = \sqrt{\sum_{n=0}^{N-1} r_{n,f}^2} \quad (5)$$

Further shown in FIG. 5, the minima determination 580 has the magnitude values W_f 562 as inputs and generates a component frequency f_0 output. Frequency f_0 is the particular frequency associated with the minimum magnitude value

$$W_{f_0} = \min \{W_f\} \quad (6)$$

FIG. 6 shows that the saturation calculator 460 functions are sinusoid generation 610, frequency selection 620, 640 and ratio calculation 670. Sinusoid generation has a component frequency f_0 input 208 and a sinusoidal waveform X_{f_0} , Y_{f_0} 612, which has a frequency of f_0 . Frequency selection 620, 640 has a sensor signal input, which is either an IR signal 202 or a RD signal 204 and a sinusoid waveform X_{f_0} , Y_{f_0} input 612. Frequency selection 620, 640 provides magnitude outputs z_{IR,f_0} 622 and z_{RD,f_0} 642 which are the frequency components of the IR 202 and RD 204 sensor signals at the f_0 frequency. Specifically, from equation 3(a)

$$X_{f_0} = \begin{bmatrix} x_{0,f_0} \\ \vdots \\ x_{N-1,f_0} \end{bmatrix}; \quad (7)$$

$$Y_{f_0} = \begin{bmatrix} y_{0,f_0} \\ \vdots \\ y_{N-1,f_0} \end{bmatrix}$$

Then, referring to equation 1

$$z_{IR,f_0} = \left| \frac{IR \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} + \frac{IR \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \right| = \sqrt{\frac{(IR \cdot X_{f_0})^2}{|X_{f_0}|^2} + \frac{(IR \cdot Y_{f_0})^2}{|Y_{f_0}|^2}} \quad (8a)$$

$$z_{RD,f_0} = \left| \frac{RD \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} + \frac{RD \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \right| = \sqrt{\frac{(RD \cdot X_{f_0})^2}{|X_{f_0}|^2} + \frac{(RD \cdot Y_{f_0})^2}{|Y_{f_0}|^2}} \quad (8b)$$

For simplicity of illustration, EQS. 8a-b assume that the cross-product of X_{f_0} and Y_{f_0} is zero, although generally this is not the case. The ratio calculation and mapping 670 has z_{IR,f_0} 622 and z_{RD,f_0} 642 as inputs and provides SAT $_{f_0}$ 262 as an output. That is

$$\text{SAT}_{f_0} = g\{z_{RD,f_0}/z_{IR,f_0}\} \quad (9)$$

where g is a mapping of the red-over-IR ratio to oxygen saturation, which may be an empirically derived lookup table, for example.

FIG. 7 illustrates an alternative embodiment of frequency selection 620 (FIG. 6), as described above. In this embodiment, frequency cancellation 540 and magnitude calculation 560, as described with respect to FIG. 5, can also be used, advantageously, to perform frequency selection. Specifi-

8

cally, frequency cancellation 540 has IR 202 and X_{f_0} , Y_{f_0} 612 as inputs and generates a remainder signal R_{f_0} 712 as an output, where

$$R_{f_0} = IR - \frac{IR \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} - \frac{IR \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \quad (10)$$

The remainder R_{f_0} 712 is subtracted 720 from IR 202 to yield

$$\begin{aligned} Z_{f_0} &= IR - \left[\frac{IR \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} + \frac{IR \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \right] \\ &= \frac{IR \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} + \frac{IR \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \end{aligned} \quad (11)$$

where Z_{f_0} 722 is the component of IR 202 at the f_0 frequency. The magnitude calculation 560 has Z_{f_0} 722 as an input and calculates

$$\begin{aligned} |Z_{f_0}| &= \left| \frac{IR \cdot X_{f_0}}{|X_{f_0}|^2} X_{f_0} + \frac{IR \cdot Y_{f_0}}{|Y_{f_0}|^2} Y_{f_0} \right| \\ &= \sqrt{\frac{(IR \cdot X_{f_0})^2}{|X_{f_0}|^2} + \frac{(IR \cdot Y_{f_0})^2}{|Y_{f_0}|^2}} \end{aligned} \quad (12)$$

which is equivalent to equation 8a, above.

FIGS. 8A-B illustrate an iterative embodiment of the frequency calculator 410 (FIG. 4) described above. An iterative frequency calculator 410 has an initialization 810, a signal component transform 820, an extrema detection 850, a resolution decision 860 and a resolution refinement 880 and provides a component frequency f_0 870. Initialization 810 defines a window around the pulse rate estimate PR and a frequency resolution within that window.

As shown in FIG. 8A, a signal component transform 820 has an initial frequency selection 822, a frequency cancellation 824 and an magnitude calculation 828. A decision block 830 determines if the magnitude calculation 828 has been performed at each frequency within the window. If not, the loop of frequency cancellation 824 and magnitude calculation 828 is repeated for another selected frequency in the window. The frequency cancellation 824 removes a frequency component from the IR sensor signal, as described with respect to FIG. 5, above. The magnitude calculation 828 determines the magnitude of the remainder signal, also described with respect to FIG. 5, above. If the decision block 830 determines that the remainder signal magnitudes have been calculated at each of the selected frequencies, then the signal component transform loop 820 is exited to the steps described with respect to FIG. 8B.

As shown in FIG. 8B, the extrema detector 850 finds a minima of a signal component transform 820 and a resolution decision block 860 determines if the final frequency resolution of a signal component transform is achieved. If not, resolution refinement 880 is performed. If the final resolution is achieved, the component frequency output f_0 is equated to the frequency of the minima 870, i.e. a signal component transform minima determined by the extrema detector 850.

Further shown in FIG. 8B, the resolution refinement 880 has a set frequency estimate 882, a window decrease 884 and a frequency resolution increase 888. Specifically, the

frequency estimate **882** is set to a signal component transform minima, as determined by the extrema detector **850**. The window decrease **884** defines a new and narrower window around the frequency estimate, and the frequency resolution increase **888** reduces the spacing of the selected frequencies within that window prior to the next iteration of a signal component transform **820**. In this manner, a signal component transform **820** and the resulting frequency estimate are refined to a higher resolution with each iteration of signal component transform **820**, extrema detection **850**, and resolution refinement **880**.

In a particular embodiment, the component calculation requires three iterations. A frequency resolution of 4 beats per minute or 4 BPM is used initially and a window of five or seven selected frequencies, including that of the initial pulse rate estimate PR, is defined. That is, a window of either 16 BPM or 24 BPM centered on PR is defined, and a signal component transform is computed for a set of 5 or 7 selected frequencies evenly spaced at 4 BPM. The result is a frequency estimate f_1 . Next, the frequency resolution is reduced from 4 BPM to 2 BPM and a 4 BPM window centered on f_1 is defined with three selected frequencies, i.e. f_1-2 BPM, f_1 , and f_1+2 BPM. The result is a higher resolution frequency estimate f_2 . On the final iteration, the frequency resolution is reduced to 1 BPM and a 2 BPM window centered on f_2 is defined with three selected frequencies, i.e. f_2-1 BPM, f_2 , and f_2+1 BPM. The final result is the component frequency f_0 determined by a signal component transform to within a 1 BPM resolution. This component frequency f_0 is then used to calculate the oxygen saturation, SAT_{f_0} , as described above.

The signal component processor has been described above with respect to pulse oximetry and oxygen saturation measurements based upon a frequency component that optimizes signal energy. The signal component processor, however, is applicable to other physiological measurements, such as blood glucose, carboxy-hemoglobin, respiration rate and blood pressure to name a few. Further, the signal component processor is generally applicable to identifying, selecting and processing any basis function signal components, of which single frequency components are one embodiment, as described in further detail with respect to FIG. 9, below.

FIGS. 9-11 illustrate another embodiment of a signal component processor **900**. As shown in FIG. 9, the processor **900** has an index calculator **910** and a measurement calculator **960**. The index calculator has a sensor signal input S **902** and outputs a basis function index κ_0 **912**, as described with respect to FIG. 10, below. The measurement calculator **960** inputs the basis function index κ_0 **912** and outputs a physiological measurement U_{κ_0} **962**, as described with respect to FIG. 11, below. The processor **900** also has a basis function indicator **980**, which is responsive to the sensor signal input S **902** and provides a parameter ϵ **982** that indicates a set of basis functions to be utilized by the index calculator **910**, as described with respect to FIG. 10, below.

As shown in FIG. 10, the functions of the index calculator **910** are basis subset generation **1020**, component cancellation **1040** and optimization calculation **1060**. The basis subset generation **1020** outputs a subset Φ_{κ} **1022** of basis function waveforms corresponding to a set of selected basis function indices κ . The basis functions can be any complete set of functions such that

$$S = \sum_{\kappa} a_{\kappa} \Phi_{\kappa} \quad (13)$$

For simplicity of illustration purposes, these basis functions are assumed to be orthogonal

$$\langle \vec{\Phi}_{\gamma}, \vec{\Phi}_{\eta} \rangle = 0; \gamma \neq \eta \quad (14)$$

where $\langle \rangle$ denotes an inner product. As such

$$\alpha_{\kappa} = \langle S, \Phi_{\kappa} \rangle / \langle \Phi_{\kappa}, \Phi_{\kappa} \rangle \quad (15)$$

$$S_{\kappa} = \alpha_{\kappa} \Phi_{\kappa} \quad (16)$$

In general, the basis functions may be non-orthogonal. The subset of basis functions generated is determined by an input parameter ϵ **982**. In the embodiment described with respect to FIG. 5, above, the basis functions are sinusoids, the indices are the sinusoid frequencies and the input parameter ϵ **982** is a pulse rate estimate that determines a frequency window.

As shown in FIG. 10, the component cancellation **1040** generates a remainder output R_{κ} **1042**, which is a set of remainder signals corresponding to the subset of basis function waveforms Φ_{κ} **1022**. For each basis function waveform generated, component cancellation removes the corresponding basis function component from the sensor signal S **902** to generate a remainder signal. In an alternative embodiment, component cancellation **1040** is replaced with a component selection that generates a corresponding basis function component of the sensor signal S **902** for each basis function generated. The optimization calculation **1060** generates a particular index κ_0 **912** associated with an optimization of the remainders R_{κ} **1042** or, alternatively, an optimization of the selected basis function signal components.

As shown in FIG. 11, the functions of the measurement calculator **960** are basis function generation **1120**, component selection **1140**, and physiological measurement calculation **1170**. The component selection **1140** inputs the sensor signal S **902** and a particular basis function waveform Φ_{κ} **1122** and outputs a sensor signal component S_{κ_0} **1142**. The physiological measurement **1170** inputs the sensor signal component S_{κ_0} **1142** and outputs the physiological measurement U_{κ_0} **962**, which is responsive to the sensor signal component S_{κ_0} **1142**. In the embodiment described with respect to FIG. 6, above, the basis functions Φ_{κ} are sinusoids and the index κ_0 is a particular sinusoid frequency. The basis function generation **1120** creates sine and cosine waveforms at this frequency. The component selection **1140** selects corresponding frequency components of the sensor signal portions, RD and IR. Also, the physiological measurement **1170** computes an oxygen saturation based upon a magnitude ratio of these RD and IR frequency components.

The signal component processor has been disclosed in detail in connection with various embodiments. These embodiments are disclosed by way of examples only and are not to limit the scope of the claims that follow. One of ordinary skill in the art will appreciate many variations and modifications.

What is claimed is:

1. A pulse oximeter system comprising:

an input configured to accept from a noninvasive optical sensor signals indicative of light attenuated by body tissue of a monitored patient; and

a hardware processor, responsive to said signals, operatively communicating with said input and configured to electronically:

determine a basis function index based, at least in part, on said one or more signals;

generate at least one basis function waveform based, at least in part, on said basis function index;

11

determine at least one optimized basis function waveform based, at least in part, on said at least one basis function waveform;

determine signal components based, at least in part, on said one or more signals and said at least one optimized basis function waveform; and

generate a physiological measurement responsive to said signal components;

a display configured to provide visual indicia of said physiological measurement.

2. The system of claim 1, wherein said generate at least one basis function waveform includes generate one or more sinusoidal waves.

3. The system of claim 1, wherein said determine at least one basis function index includes determine a frequency corresponding to said at least one basis function index.

4. The system of claim 1, wherein said signal components comprise frequency components based, at least in part, on said one or more signals and said at least one basis function waveform.

5. The system of claim 1, wherein said at least one basis function index corresponds to a pulse rate.

6. The system of claim 1, wherein said one or more signals comprises an IR signal and a RD signal.

7. The system of claim 6, wherein said hardware processor is configured to determine signal components responsive to said IR signal and said RD signal.

8. The system of claim 1, wherein said at least one basis function index corresponds to a pulse rate.

9. A method of determining a physiological parameter of a monitored patient attached to a noninvasive optical sensor, the method comprising:

receiving one or more signals indicative of light attenuated by body tissue of said monitored patient, said one or more signals usable to determine measurements for a physiological parameter of said monitored patient;

electronically determining at least one basis function index based, at least in part, on said one or more signals;

electronically generating at least one basis function waveform based, at least in part, on said at least one basis function index;

electronically determining at least one optimized basis function waveform based, at least in part, on said at least one basis function waveform;

12

electronically determining signal components of said one or more signals based, at least in part, on said at least one optimized basis function waveform and said one or more signals; and

electronically processing said signal components of said one or more signals to determine an output measurement of said physiological parameter.

10. The method of claim 9, wherein said generating at least one basis function waveform comprises generating one or more sinusoidal waves.

11. The method of claim 9, wherein said determining at least one basis function index includes determining a frequency corresponding to said at least one basis function index.

12. The method of claim 9, wherein said at least one basis function index corresponds to a pulse rate.

13. The method of claim 9, wherein said one or more physiological parameters comprises oxygen saturation.

14. The method of claim 9, further comprising outputting said physiological measurement to a display device.

15. The method of claim 9, wherein said electronically determining signal components of said one or more signals comprises determining frequency components of said one or more signals based, at least in part, on said at least one basis function waveform and said one or more signals.

16. A pulse oximeter system capable of determining a physiological parameter of a monitored patient attached to a noninvasive optical sensor, the pulse oximeter comprising:

means for receiving one or more signals indicative of light attenuated by body tissue of a monitored patient;

means for communicating with said input and determining a basis function index based, at least in part, on said one or more signals;

means for generating at least one basis function waveform based, at least in part, on said basis function index;

means for determining at least one optimized basis function waveform based, at least in part, on said at least one basis function waveform;

means for determining signal components based, at least in part, on said one or more signals and said at least one optimized basis function waveform; and

means for generating a physiological measurement responsive to said signal components.

* * * * *

专利名称(译)	正弦饱和变换		
公开(公告)号	US9814418	公开(公告)日	2017-11-14
申请号	US14/543325	申请日	2014-11-17
[标]申请(专利权)人(译)	梅西莫股份有限公司		
申请(专利权)人(译)	Masimo公司		
当前申请(专利权)人(译)	Masimo公司		
[标]发明人	WEBER WALTER M AL ALI AMMAR CAZZOLI LORENZO		
发明人	WEBER, WALTER M. AL-ALI, AMMAR CAZZOLI, LORENZO		
IPC分类号	A61B5/1455 A61B5/00 A61B5/024 A61B5/145 A61B5/02		
CPC分类号	A61B5/14552 A61B5/024 A61B5/02433 A61B5/7282 A61B5/14551 A61B5/14532 A61B5/1455		
优先权	13/043421 2013-07-30 US 12/336419 2011-03-08 US 11/894648 2008-12-16 US 11/417914 2008-05-27 US 11/048232 2008-05-13 US 10/184032 2005-02-01 US 60/302438 2001-06-29 US		
其他公开文献	US20150141781A1		
外部链接	Espacenet USPTO		

摘要(译)

公开了一种用于确定生理测量的变换。变换根据通过生理传感器获得的生理信号确定基函数指数。基于基函数索引生成基函数波形。然后使用基函数波形来确定优化的基函数波形。优化的基函数波形用于计算生理测量。

