




US 20150335264A1

(19) **United States**(12) **Patent Application Publication**
ROSENBERG et al.(10) **Pub. No.: US 2015/0335264 A1**(43) **Pub. Date: Nov. 26, 2015**(54) **METHOD AND SYSTEM FOR DETERMINING
A DEVICE MOVEMENT IRRESPECTIVE OF
MOVEMENT OF A REFERENCE FRAME***A61B 5/11* (2006.01)*A61B 5/00* (2006.01)(52) **U.S. Cl.**CPC *A61B 5/073* (2013.01); *A61B 5/1123*
(2013.01); *A61B 5/7282* (2013.01); *A61B*
5/1107 (2013.01); *A61B 1/041* (2013.01);
A61B 1/045 (2013.01); *A61B 1/0002*
(2013.01); *A61B 1/00006* (2013.01); *A61B*
2562/0219 (2013.01); *A61B 2562/166*
(2013.01); *A61B 2562/227* (2013.01)(71) Applicant: **GIVEN IMAGING LTD.**, Yoqneam
(IL)(72) Inventors: **Oren ROSENBERG**, Kiryat Ono (IL);
Semion KHAIT, Tiberias (IL)(21) Appl. No.: **14/761,320**(22) PCT Filed: **Feb. 6, 2014**(86) PCT No.: **PCT/IL2014/050133**

§ 371 (c)(1),

(2) Date: **Jul. 16, 2015****Related U.S. Application Data**(60) Provisional application No. 61/762,401, filed on Feb.
8, 2013.**Publication Classification**(51) **Int. Cl.***A61B 5/07* (2006.01)*A61B 1/00* (2006.01)*A61B 1/04* (2006.01)*A61B 1/045* (2006.01)(57) **ABSTRACT**

A swallowable in-vivo device contains a movement detection unit that includes a movement sensing unit, a frequency analyzing unit (FAU) and a time analyzing unit (TAU). The movement sensing unit senses movements of the in-vivo device relative to a non-stationary three-dimensional reference frame, and outputs a movement signal. The frequency analyzing unit may analyze the movement signal spectrally to detect a potential command-invoking movement, and the time analyzing unit may analyze the potential CIM temporally, possibly in conjunction with a series of other movement events, to determine whether the potential CIM is a genuine CIM. If the potential CIM is determined to be a genuine CIM, the in-vivo device may execute a predetermined command associated with the CIM. Otherwise, the in-vivo device may refrain from executing a CIM-related command. A PCB including the movement detection unit and a processor for processing their output is provided for the vivo sensing device.






Fig. 1C




Fig. 1B




Fig. 1A








Fig. 2









Fig. 7




Fig. 8




Fig. 9




Fig. 10A




Fig. 10C




Fig. 10B

METHOD AND SYSTEM FOR DETERMINING A DEVICE MOVEMENT IRRESPECTIVE OF MOVEMENT OF A REFERENCE FRAME

FIELD OF THE INVENTION

[0001] The present invention generally relates to detection of movement of objects (e.g., in-vivo sensing capsules, endoscopy capsules, etc.), and more specifically to an object capable of detecting its movement in a non-stationary three-dimensional frame irrespective of movement of the three-dimensional frame.

BACKGROUND

[0002] In-vivo measuring systems are known in the art. Some autonomous capsule like in-vivo devices, which traverse the gastrointestinal (“GI”) system, may include an imaging sensor, or imager, for imaging (e.g., acquiring images of) the interior of the GI system, and a transmitter for transmitting image frames to an external system (e.g., data receiver/recorder). An in-vivo device may include sensors of other types (e.g., pH, pressure and temperature), and/or various types of tools (e.g., micro electro-mechanical system), for example to perform surgical operations in vivo and/or to administer medication in the GI system, for example from a container contained in an in-vivo device. An in-vivo device may be capable of changing a rate at which image frames are acquired).

[0003] Some in-vivo devices are configured to transmit image frames (with or without additional sensory data) to an external system (e.g., data receiver/recorder) at some constant frames per second (“FPS”) rate, for example at a rate of four FPS. Other devices may be configured to transmit image frames at a rate that depends on, or is a function of, for example, movement of the in-vivo device. For example, when a device moves slowly, a relatively slow FPS rate may be preferable (e.g., to save battery energy), whereas when a device moves faster, a higher FPS rate may be preferable (e.g., to obtain or maintain a certain rate of frames per unit of intestine’s length).

[0004] An in-vivo device capable of varying its FPS rate and external systems (e.g., receiver/recorder) capable of transmitting a command to the in-vivo device to change its FPS rate may be said to have an adaptive frame rate (“AFR”) capability. (Typically, a decision regarding movement of an in-vivo device that has an AFR capability is taken externally, for example by an external receiver or recorder, based on, for example, image data or other information that the external system may receive from the in-vivo device.)

[0005] While AFR capability of an in-vivo device is beneficial, this capability cannot be used if the external receiver/recorder with which the in-vivo device cooperates does not have AFR capability. It would be beneficial to have an in-vivo device that can exercise AFR even if the external receiver/recorder is AFR-incompatible, and, in general, it would be beneficial to have an in-vivo device that can execute also other movement-dependent commands independently of the external receiver/recorder (e.g., autonomously).

SUMMARY OF THE INVENTION

[0006] Embodiments of a method are provided for conditional execution of a command by a swallowable in-vivo device, where the device may move relative to a non-stationary, three-dimensional, reference frame (e.g., GI system,

earth) and configured to execute the command in response to a command-warranting movement. Embodiments of a system using or performing embodiments of the method are also provided.

[0007] Embodiments of the invention may include predefining a group of fiducial command-invoking movements (“CIMs”) of, or for, an in-vivo sensing device, and characterizing each fiducial CIM spectrally and/or temporally. Fiducial CIMs are reference CIMs against which movements of the in-vivo sensing device are equated in order to determine whether the device’s movements are (potential) CIMs. (A fiducial CIM may be characterized spectrally, or temporally, or both spectrally and temporally, independently of other fiducial CIMs, or depending on, or in conjunction with, other fiducial CIMs.) A fiducial CIM, or a CIM represented by a fiducial CIM, may be, represent, include, or otherwise be associated with a device movement that, when detected by a sensor of the device, may invoke a predetermined command associated with the detected movement. (Such a device movement is referred to herein as a “command-invoking movement”, or “CIM”). A predetermined command associated with a particular CIM, or group of CIMs, may be, for example, a command to change a rate at which an imager or camera of the in-vivo device acquires, or captures, images in the GI system, or a command to change a mode of operation or state of the in-vivo device (e.g., a command to switch the device “off” when the device is in a particular location in the GI tract, or to substitute reference data, or activate or deactivate a system or sensor in the in-vivo device, etc.), or a command to transmit a message to a receiver external to the in-vivo device, etc. The predetermined command may be a command that, when executed, triggers a series of predetermined operations.

[0008] A fiducial CIM may also, or additionally, be characterized according to, or factor in, the orientation and/or location of the in-vivo device. For example, a certain movement of the in-vivo device may be classified or regarded as, or determined to be, a CIM only if the device is in a particular location in the GI system (e.g., stomach, small bowel, etc.) and/or has a particular spatial orientation. A particular device movement may be regarded as a CIM when the device movement occurs at a particular location and/or in some orientation in the GI system, or as a non CIM (e.g., as noise) when it occurs at another location or in another orientation. A fiducial CIM may be selected for use according to the location and/or orientation of the in-vivo sensing device, for example it may be used to detect a CIM, or refrained from being used, depending on the location and/or orientation of the in-vivo device, for example, in the GI system. For example, in one embodiment when the device is in the stomach, a movement signal including three movement signals corresponding to three-dimensional movement of the device movement (i.e., movement in three directions) may be analyzed to detect a CIM. When the device is, for example, in the small bowel, in one embodiment only a movement signal representing one-dimensional movement of the device may be analyzed to detect a CIM.

[0009] Embodiments of the present invention may include obtaining a movement signal (e.g., by using images captured in vivo by the in-vivo device, or by using an acceleration sensor, magnetometer, gyroscope, etc.) representative or indicating a movement of the in-vivo device, detecting movement in or from the movement signal, and determining whether the detected movement is a CIM or, for example, an interference

movement. (In other words, a detected movement may be analyzed in order to classify it as a CIM or as an interference movement, depending on analysis of the detected movement.) Determining whether a detected movement is a CIM or not may be based on comparison of spectral characteristics or temporal characteristics, or both spectral and temporal characteristics, of the detected device movement to pre-stored spectral and/or temporal characteristics of fiducial CIMs and, optionally, also of interference movements. If, based on the comparison result, the detected device movement is determined to be (i.e., it is classified as) a CIM, the in-vivo device may execute the predetermined command associated with the CIM, and if the detected movement is determined not to be CIM (e.g., it is classified as an interference movement), the in-vivo device may refrain from executing any command that is invokeable by a movement (e.g., the in-vivo device may ignore such movements). A CIM (and a corresponding fiducial CIM may be characterized accordingly) may be selectable for use from a group consisting of: movement of the in-vivo device due to muscle contraction(s) of the small bowel, movement of the in-vivo device due to muscle contraction(s) of the colon, movement of the in-vivo device due to muscle contraction(s) of the stomach, and movement of the in-vivo device due to intestine constipation. (A device movement may be regarded as a CIM; e.g., after comparing it to one or more fiducial CIMs, using, or as per, other or additional criteria.)

[0010] Embodiments of the present invention may also include defining a group of interference movements that may occasionally be superimposed on, and interfere with, a CIM, or CIMs, sensed by an in-vivo device. Each interference movement, which is a movement of the device that should not invoke a command, may be characterized spectrally and/or temporally. An interference movement may be a movement selectable from a group consisting of: movement of the in-vivo device due to human's body gestures (e.g., moving a hand in any direction and with any speed, bending the subject's body forward, changing body's position, etc.), movement of the in-vivo device due to walking, respiration and heart beating. In general, any movement that is superimposed on the movement of the GI portion containing the in-vivo device, may be regarded as extraneous movement, and, therefore, as interference movement. Movements of the in-vivo device which are not due to the activity of the GI system/anatomy, and movements of the in-vivo device which are due to movement of a remote portion of the GI system (e.g., GI portion not containing the in-vivo device) are example extraneous/interference movements. (Other, or additional, types of movements may be regarded as extraneous/interference movements.)

[0011] Detecting a CIM in or from the movement signal may include filtering out or removing an interference movement from the movement signal, for example by analyzing the movement signal spectrally and/or temporally vis-a-vis pre-stored spectral characteristics and/or temporal characteristics that are known to characterize interference movements. Analyzing a movement signal 'vis-a-vis' pre-stored characteristics, as used herein, may refer to an analysis process that includes comparing spectral characteristics, or temporal characteristics, or both spectral and temporal characteristics of a detected movement or movement signal, to stored characteristics that are known to characterize spectrally, or temporally, or both spectrally and temporally predetermined interference movements or predetermined CIMs, as the case

may be. Filtering out or removing interference movement(s) from the movement signal may result in an interference movement free movement signal. After interference movement(s) is/are removed (filtered out) from the movement signal, the interference movement(s) free signal may represent, embody or include a movement that may potentially be a CIM. A movement detected in the interference movement(s) free signal may be regarded as a potential CIM if the detected movement resembles a fiducial CIM spectrally. A final decision, regarding whether the potential CIM is, or is not, a CIM, may be made based on temporal analysis of the potential CIM vis-a-vis pre-stored temporal characteristics of interference movements. A decision, regarding whether a potential CIM is, or is not, a CIM, may also depend on the location of the in-vivo device in the GI system and/or on the spatial orientation of the in-vivo device. The movement signal, or an interim processing result thereof, may be analyzed spectrally and/or temporally one or more times, or iteratively or repeatedly, and at any order (e.g., first spectrally and then temporally, or vice versa) before the final decision is made. For example, removing an interference movement from the movement signal may include analyzing the movement signal spectrally and then temporally, or temporally and then spectrally, using known spectral and temporal characteristics, and/or using information indicative of a location and/or an orientation of the in-vivo device. According to another example, removing an interference movement from the movement signal may include analyzing the movement signal by iteratively or alternately performing spectral analysis and temporal analysis.

[0012] Determining whether a movement detected in a movement signal, or in an interference movement free movement signal, is a CIM may include repeatedly or iteratively applying spectral analysis and/or temporal analysis to the movement signal vis-a-vis known, or reference, spectral and/or temporal characteristics. Determining whether a detected movement is a CIM may include analyzing the related movement signal spectrally and then temporally, or temporally and then spectrally. Determining whether the detected movement is a CIM may include analyzing the movement signal by iteratively or alternately performing spectral analysis and temporal analysis. A movement signal may include three movement signals respectively corresponding to three directions or represent movement in three directions.

[0013] A movement of the in-vivo device may be classified as a CIM or as an interference movement also depending, or based, on the location and/or orientation of the in-vivo device relative to the three-dimensional reference frame. The three-dimensional reference frame may be the GI tract, or a portion thereof containing the in-vivo device, or earth.

[0014] The in-vivo device may include a movement detection unit ("MDU") that may include one or more movement sensors (e.g., acceleration sensor(s)) for detecting movement of the in-vivo device, a processor (in conjunction with a frequency analyzing unit ("FAU") and time analysis unit ("TAU") to analyze the MDU's output spectrally and/or temporally and, based on the analysis, to determine the type of movement (CIM or non-CIM; e.g., interference movement), and a controller to execute a predetermined associated command if the processor determines that the detected movement is a CIM. The in-vivo device may have a longitudinal axis and include one acceleration sensor whose sensitivity direction/axis coincides with the longitudinal axis of the in-vivo device, or is at an angle relative to the longitudinal axis. The in-vivo device may also include a foldable printed circuit board

(“PCB”) on which the MDU, FAU, TAU, processor and/or controller, etc. (e.g., camera, other sensors) are mounted.

BRIEF DESCRIPTION OF THE DRAWINGS

[0015] Various exemplary embodiments are illustrated in the accompanying figures with the intent that these examples not be restrictive. It will be appreciated that for simplicity and clarity of the illustration, elements shown in the figures referenced below are not necessarily drawn to scale. Also, where considered appropriate, reference numerals may be repeated among the figures to indicate like, corresponding or analogous elements. Of the accompanying figures:

[0016] FIGS. 1A-1C show a capsule type in-vivo device in three, typical, positions relative to gravity force according to embodiments of the present invention;

[0017] FIGS. 2A-2C respectively show velocity, acceleration and distance curves associated with movement of an autonomous in-vivo device according to embodiments of the present invention;

[0018] FIGS. 2D-2G show typical movements associated with movement of an autonomous in-vivo device according to embodiments of the present invention;

[0019] FIGS. 3A-3B show example spectral content of typical movements according to embodiments of the present invention;

[0020] FIG. 4 shows a movement detection unit (“MDU”) according to an embodiment of the present invention;

[0021] FIG. 5 shows a frequency analyzing unit (“FAU”) according to an embodiment of the present invention;

[0022] FIG. 6A shows a time analyzing unit (“TAU”) according to an embodiment of the present invention;

[0023] FIGS. 6B-6C demonstrate typical movement decisions according to embodiments of the present invention;

[0024] FIG. 7 shows a TAU according to an embodiment of the present invention;

[0025] FIG. 8 is a block diagram of an example in-vivo system according to an example embodiment of the present invention;

[0026] FIG. 9 shows a method for detecting a command-invoking movement (CIM) of an in-vivo device (e.g., the device of FIG. 8) according to an embodiment of the present invention; and

[0027] FIGS. 10A-10C depict a printed circuit board according to an example embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0028] The description that follows provides various details of exemplary embodiments. However, this description is not intended to limit the scope of the claims but instead to explain various principles of the invention and the manner of practicing it.

[0029] Due to the nature of GI peristalsis, an accelerometer is a ‘natural’ candidate for sensing movement of an autonomous in-vivo device (e.g., in-vivo imaging capsule) in the gastrointestinal system. That is, an accelerometer is a natural candidate for sensing movement of an autonomous in-vivo device because a movement of an in-vivo device is to be detected relative to the GI tract, which has a dynamically changing posture. Therefore, the GI tract can be regarded as a non-stationary, three-dimensional, reference frame. That is, the GI tract reference frame is ‘non-stationary’ for two reasons: (1) the GI tract can change its posture (e.g., as a result of

intestine activity or body movement), and (2) the reference frame may be ‘local’, meaning that the reference frame’s coordinates spatial directions are determined as per a GI portion currently containing the in-vivo device. (The reference frame may be regarded as moving along with the in-vivo device.)

[0030] In addition, since acceleration of a body or body parts (e.g., arms, legs, etc.) is far lower than (hence ignorable comparing to) acceleration of the in-vivo device in the GI tract, using an accelerometer inherently provides for some filtering of accelerations due to such extraneous movements. Accelerometers typically use a weight or strain gauge that can move, or is sensitive, only in a certain direction in response to acceleration force, so that the accelerometer can sense accelerations only in that particular direction that is referred to herein as ‘sensitivity direction’ or ‘sensing direction’.

[0031] FIGS. 1A through 1C show a capsule type in-vivo sensing device 100 in three typical positions relative to the direction of earth’s gravity according to an embodiment of the present invention. FIG. 1A shows movements of in-vivo device 100 in direction 120, in plane X-Y 130, that is perpendicular to the direction 110 of gravity. An acceleration sensor sensitive to acceleration in a direction coinciding with, or lying on, the X-Y plane 130 is insensitive to gravity because, in FIG. 1A, the weight used to sense/measure acceleration can move horizontally (in direction 120) but not in other directions; e.g., in direction 110 which is the gravitation direction. A movement signal that would be output from an acceleration sensor whose sensitivity/sensing direction is perpendicular to the direction of gravity force would be insensitive to walking steps’ impact because walking steps typically elicit/produce acceleration/deceleration force in a direction that substantially coincides with the gravity’s direction 110, which is orthogonal to the sensor’s sensitivity/sensing direction 130. (A different situation is shown in FIG. 1B, where the sensor’s sensitivity/sensing direction 150 substantially coincides with gravity’s direction 110.)

[0032] It may be determined that movement of capsule 100 in direction 120 may be regarded as a movement worth analyzing (e.g., to determine if it is a command-invoking movement or an interference movement) if the acceleration signal, which the accelerometer outputs, has a value $V(\text{acc})$ that is greater than some predetermined positive threshold value V_{th} , or smaller than a negative value $-V_{th}$; that is, if condition (1) is met:

$$V(\text{acc}) > +V_{th} \text{ (or } V(\text{acc}) < -V_{th}) \quad (1)$$

[0033] FIG. 1B shows movements of in-vivo device 100 in direction 140, in the Z axis/direction 150 that coincides with the direction 110 of gravity. An acceleration sensor sensitive to acceleration in a direction coinciding with the Z direction 150 is sensitive to gravity because, in FIG. 1B, the weight used to sense/measure acceleration can move vertically, in direction 140 that is the gravitation’s direction. Sensitivity of an accelerometer to gravity means that the accelerometer’s weight deviates from, or is biased or decentered from the weight’s balanced, or neutral, position due to the gravitational force. Such deviations may (if not compensated for) erroneously indicate that the device including the accelerometer is accelerating. The accelerometer’s erroneous position due to gravity must, therefore, be compensated for.

[0034] As in FIG. 1A, it may be determined that movement of device 100 in direction 140 may be regarded as a movement worth analyzing (e.g., to determine if it is a command-

invoking movement or interference movement) if the acceleration signal, which the accelerometer outputs, has a value that is greater than some predetermined threshold value biased by (in this case by the full effect) of gravity (g); that is, if condition (2) is met:

$$V(\text{acc}) > g + V_{th} \text{ (or } V(\text{acc}) < g - V_{th}) \quad (2)$$

[0035] FIG. 1B shows a situation where the sensor's sensitivity/sensing direction 150 substantially coincides with the gravity's direction 110. Under these circumstances, a movement signal that would be output from the acceleration sensor would be most sensitive to the impact of walking steps.

[0036] FIG. 1C shows movements 160 of in-vivo device 100 in direction 170, which is at angle of 45 degrees (the angle is shown at 180) relative to the gravity direction 110. Since the gravity vector has a component in direction 170, which is the accelerometer's sensitivity/sensing direction, the accelerometer is sensitive to gravity, though less than when the accelerometer's sensitivity/sensing direction coincides with the gravity's direction (as demonstrated by FIG. 1B). All accelerometer sensitivity/sensing directions that are not perpendicular to the gravity's direction result in erroneous indications due to some gravity effect, that the device including the accelerometer is accelerating (moving). (The more an accelerometer sensitivity/sensing direction is parallel to the gravity direction, the greater the effect gravity has on the accelerometer's output signal and, therefore, the greater the acceleration measurement error.) The accelerometer's erroneous position due to gravity must, therefore, be compensated for.

[0037] As in FIGS. 1A and FIG. 1B, it may be determined that movement of capsule in direction 170 may be regarded as a movement worth analyzing (e.g., to determine there from if it is a CIM or interference movement) if the acceleration signal, which the accelerometer outputs, has a value that is greater than some predetermined threshold value which is biased due to some effect (E) of gravity (g) that depends on the angle α (shown at 180, FIG. 1C) between the acceleration sensitivity/sensing direction 170 and the gravity's direction 110; that is, if condition (3) is met:

$$V(\text{acc}) > g * \cos(\alpha) + V_{th} \text{ (or } V(\text{acc}) < g * \cos(\alpha) - V_{th}) \quad (3)$$

[0038] Since the threshold value against which V(accelerometer) is compared depends on angle α (180, FIG. 1C), and α cannot be determined if the an in-vivo device's orientation cannot be determined, condition (3) above may result in erroneous decisions regarding movements of the in-vivo device. In order to obtain a reliable measurement of the movement of the in-vivo device regardless of the angle alpha (180), the effect of gravity has to be neutralized, or compensated for, completely regardless of the value of angle α . FIG. 1C shows a situation where the sensor's sensitivity/sensing direction 170 is at angle with respect to the gravity's direction 110. Under these circumstances, a movement signal that would be output from the acceleration sensor would be sensitive to the impact of walking steps to some extent.

[0039] FIGS. 2A-2C respectively show velocity (202), acceleration (204) and distance (206) curves associated with movement of an autonomous in-vivo device according to embodiments of the present invention. A swallowable autonomous in-vivo sensor (e.g., in-vivo imaging device) typically moves in the GI tract in a pulsating pattern that is governed by peristalsis. A typical movement event/occurrence, of such a device is shown at 202 in FIG. 2A. The movement event starts at time t1, when the velocity V(t) is zero, and the velocity increases until it reaches its peak at time

t2, and then decreases until it becomes zero at time t3. Curve 204 of FIG. 2B shows the acceleration/deceleration corresponding to velocity curve (movement event) 202, and curve 206 of FIG. 2C shows the distance, d (shown at 208 in FIG. 2C), traveled by the in-vivo device during velocity pulse/event 202 (during time period t1-t3), where d is equal to the difference between point x1 (the initial position of the device at time t1) and point x2 (the position of the device at time t3).

[0040] FIGS. 2D-2G show examples of four movement events (210, 220, 230 and 240) according to embodiments of the present invention. (The vertical axis in FIGS. 2D-2G denotes velocity, V.) FIG. 2D shows a relatively fast, spike-like, movement event 210 of a relatively short duration T1; FIG. 2E shows a relatively slower movement event 220 of duration T2 (T2>T1); FIG. 2F shows a slower movement event 230 of duration T3 (T3>T2>T1), and FIG. 2G shows the slowest movement event 240 of duration T4 (T4>T3>T2>T1). Some device movements may pertain to (caused by) extraneous (noise) movements in the sense described herein, and other device movements may pertain to, or be, CIMs. For example, movement event 210 may be sensed due to (caused by) an impact of a walking step or due to coughing; movement event 220 may typically be, represent or pertain to movement of an in-vivo device in the colon; movement event 230 may typically be, represent or pertain to a movement event of the in-vivo device in the small bowel, and movement 240 may typically be, represent or pertain to a body gesture (e.g., moving a hand or leg, bending over or sideways, etc.). Body gestures, which are regarded as noise/interference movements (and therefore they should not invoke a command or cause a command to be invoked) are usually slow relative to movements of an autonomous in-vivo device due to peristalsis.

[0041] Each device movement represented by a movement event shown in FIGS. 2E-2G, and possibly other types of movements, may be characterized spectrally to distinguish between them. However, in some cases, analyzing device movements only spectrally may not suffice to determine if a certain device movement is, represents or derived from, a CIM or not. That is, a detected movement event may resemble a CIM spectrally. However, a following temporal analysis of the movement event may result in a conclusion that it is not a CIM. That is, temporal analysis of a movement event that is spectrally assumed to be, or suspected as representing, a CIM helps 'putting' the suspected movement in a right 'context', as demonstrated below, for example in connection with FIGS. 6B-6C. (A particular movement that, after spectrum analysis, is initially assumed to be a CIM may be analyzed temporally in conjunction with adjacent movement events in order to corroborate the assumption or to refute it.)

[0042] FIGS. 3A-3B show spectral content of typical device movements according to example embodiments of the present invention. FIG. 3A shows a spectrum 310 of a device movement that, based only on frequency analysis, may resemble a CIM. Also shown in

[0043] FIG. 3A is a direct current ("DC") component 320 due to the gravity (g) force, and a high pass filter ("HPF") 330 that filters out or removes the DC component 320. As explained above, other types of movements (e.g., movements having similar frequency components as a CIM, or higher frequency components) may be sensed, which are not to invoke a command invokeable by a CIM's type of movement.

(Such movements are regarded as noises or interference movements that have to be ignored or filtered out or removed too).

[0044] FIG. 3B shows spectrums **310**, **320** as in FIG. 3A, and, in addition, a spectrum **340**, which may characterize or represent relatively slow movements that should not invoke a command (but they may erroneously invoke a command if they are not cancelled out or removed), and a spectrum **350** that may characterize or represent relatively fast movements that also should not invoke a command (but they may invoke it if they are not cancelled out or removed). While HPF **330** of FIG. 3A may filter out or remove the DC component (**320**), and, if designed properly, all, or most of, the slow movements (**340**), it may pass high frequency components representing or making up fast movements (e.g., movements **350**) that also should not invoke a command (but they may do so if they are not cancelled out).

[0045] Therefore, a band pass filter (“BPF”) **360** may be used to pass only frequency spectrum representing, corresponding to or making up movements that can initially/potentially be regarded as a CIM. A device movement may initially be regarded as, or determined to be, a potential CIM after analyzing it vis-a-vis fiducial CIMs. Analyzing a movement (event) vis-a-vis a fiducial CIM may include comparing frequency spectrum of the movement (event) to frequency spectrum of the fiducial CIM, and/or calculating temporal correlation between the movement (event) and the fiducial CIM.

[0046] FIG. 3B shows one BPF (**360**) by way of example. However, the number of BPFs that may be used may vary according to the number and frequency characteristics of the movements that have been predefined as command invoking movements, and/or of movements that are worth further checking (e.g., by temporally analyzing them individually or collectively) whether they, indeed, are (or one of them is) a CIM. A filter used to detect resemblance between movement events and CIMs may be a matched filters array module (“MFAM”).

[0047] FIG. 4 shows a movement detection unit (MDU) **400** according to an embodiment of the present invention. MDU **400** may include an acceleration sensor(s) unit (“ASU”) **410** that may include one acceleration sensor or more than one acceleration sensor (e.g., two acceleration sensors, three acceleration sensors, etc.) for sensing acceleration in one or more directions/axes. MDU may, in general, include one or more sensors selected from a group consisting of accelerometer (to sense acceleration), magnetometer (to sense location and orientation) and gyroscope (to sense orientation). MDU **400** may also include a transducer **420** for converting the acceleration(s) sensed by the acceleration sensor(s) into a corresponding analog movement signal(s), an anti-aliasing circuit **430** to remove sampling side effects, an analog-to-digital converter (“ADC”) **440** for converting the (analog) movement signal(s) into digital data, and a processing and analyzing unit (“PAU”) **450**. PAU **450** may include a memory unit **492**. Memory unit **492** may store, among other things, the digital data representing the analog movement signal(s), and information/data representing fiducial CIMs (e.g., frequency and/or temporal characteristics of fiducial CIMs) and interference movements (e.g., frequency and/or temporal characteristics of interference movements). Memory unit **492** may also store time specifics defining time templates against which movement events may be compared or analyzed in order to corroborate or refute an initial deter-

mination, or assumption, that a device movement, which frequency-wise resembles a fiducial CIM (e.g., a PCIM), is a CIM.

[0048] PAU **450** may also include a frequency analyzing unit (FAU) **460** to analyze movement signals/events spectrally (e.g., by comparing frequency characteristics of them to frequency characteristics of stored fiducial CIMs), a time analyzing unit (TAU) **470** to analyze movement signals/events temporally (e.g., by comparing time characteristics of them to time characteristics of stored fiducial CIMs and/or to stored time specifics of time templates), a comparator **480** to compare spectral features of the spectrally analyzed movement signals/events to frequency characteristics stored in the memory, and to compare temporal features of the temporally analyzed movement signals/events to temporal characteristics stored in the memory. FAU **460** may include or use a frequency filter (e.g., BPF) or a set of frequency filters (e.g., multiple BPFs), or matched filters (array) to detect frequency features of the analyzed movement signal(s)/events. TAU **470** may include or use one or more timers and/or counters to detect time features of the analyzed movement signal(s)/events. Comparator **480** may include or use a correlator to determine the extent to which the frequency and time features of the analyzed movement signal(s)/events respectively resemble one or more of the spectral and temporal characteristics which are pre-stored in memory **492**.

[0049] PAU **450** may also include a controller **490** to control, among other things, operation of FAU **460** (e.g., set its filters’ boundaries/windows/coefficients, etc.), TAU **470** (e.g., set and reset a timer or a counter, etc.) and comparator **480** (e.g., determine which frequency and time feature should respectively be compared to which pre-stored spectral characteristics and temporal characteristics), and, ultimately, to determine if a movement event sensed by movement sensor **415** is, or includes, a CIM. If controller **490** determines that a movement event sensed by movement sensor **415** is, or includes, a CIM, controller **490** may execute the command associated with the movement event, or cause (e.g., instruct) another device to execute the command. In one embodiment, if controller **490** determines that a movement event sensed by movement sensor **415** is, or includes, a CIM, controller **490** may execute the same command (or instruct another device to execute the command) regardless of the type of the command-invoking movement. (The same command may be invoked by all movements that are determined by controller **490** to be CIMs.) In another embodiment, a command may be executed as per one CIM or as per a group of CIMs. (A particular command may be invoked only by (e.g., assigned to) a specific CIM, e.g. on a command-per-movement’s type basis, or by (e.g., assigned to) a specific group of CIMs.) Controller (or processor) **490** (or controller or processor **818** of FIG. 8), by executing software or instructions, may carry out steps/procedures which are performed by any one or more of FAU **460**, TAU **470**, FAU **500**, TAU **600** and TAU **700**, and thus may function as these units. Each of controller or processor **490**, **818** may be or include computer processors, central processing units, etc.

[0050] An in-vivo device identical or similar to the one shown in FIG. 8 (in-vivo device **810**, described below), may include a MDU (e.g., MDU **828**) that may function like, or in a similar way as, MDU **400**, for example.

[0051] PAU **450** may also include a magnetometer or a gyroscope to facilitate determination of the spatial orientation

of in-vivo device relative to, for example, earth, or to another reference frame or coordinate system.

[0052] FIG. 5 shows a frequency analyzing unit (FAU) 500 according to an example embodiment of the present invention. FAU 500 may include or use a matched filters array module (MFAM) 510. MFAM 510 may receive movement data (512), or movement signal, that may be output or transferred, for example, by/from an ADC (e.g., ADC 440), and use various BPFs to cancel/filter out, or remove, noise signals due to, for example, interference movements and other noises. MFAM 510 may output signals that are spectrally resembling, or representing, CIMS. MFAM 510 may include as many BPFs as there are CIMS. For example, MFAM 510 may include one BPF for each type of CIM. MFAM 510 may detect frequency features in movement data/signal 512, and output (514) data or signal that represents detected movement events, where each detected movement event may potentially be a CIM.

[0053] FAU 500 may also include or use a potential CIM detector ("PCIMD") 520 to analyze the detected movement events spectrally (e.g., vis-a-vis fiducial CIMS) in order to detect movement events that resemble CIMS. PCIMD 520 may detect a movement event that resembles a CIM by analyzing the frequency features output (514) by, or transferred from, MFAM 510 vis-a-vis frequency features of fiducial CIMS. (A movement event resembling a CIM is regarded herein as a 'potential CIM' that is subjected to a CIM corroboration/refutation process.)

[0054] PCIMD 520 may output (522), for example in real-time, a (continuous) series of 'decision' pulses where each decision pulse may denote or represent a detected movement event that is a potential CIM. An example series of pulses corresponding to or representing a series of such movement events is shown at 524. By way of example, pulse/decision series 524 is shown having two distinct levels (530 and 540) and three detected movement events 551, 552 and 553 that are regarded as potential CIMS. Level 530 may indicate, or be associated with, a detected movement, and level 540 may indicate, or be associated with, absence of movement. (The functionalities of the two levels may be swapped, and the number of detected movement events, and their temporal spacing and width, may vary according to the number, frequency and type of the detected movements.) By way of example, movement event 551—the first detected potential CIM—starts at time t_1 and has time duration T_1 ; movement event 552—the second detected potential CIM—starts at time t_2 and has time duration T_3 that may differ from T_1 , and movement event 553 starts at time t_3 and has time duration T_5 that may differ from T_1 and T_3 . (Time periods T_2 and T_4 , which may be different, are periods determined by PCIMD 520 as not including movement event(s) that resemble CIMS.)

[0055] Time specifics (e.g., relative occurrences, start times, time durations, etc.) of all the movement events may be stored in a memory similar to the memory mentioned in connection with PAU 450 (FIG. 4) for time analysis. Times t_1 , t_2 , t_3 , and time periods T_1 , T_2 , T_3 , T_4 and T_5 are example of time specifics that may temporarily be stored and analyzed to enhance the determination process regarding whether a potential CIM (a non-interference movement) is, indeed, a genuine CIM. Time analysis is used to rule out an interference movement, or other noise signal, that resembles a CIM spectrally. That is, while spectral analysis of a particular movement may result in the assumption that a particular movement is a CIM (e.g., that the particular movement is a PCIM),

temporal analysis of a series of movements including the particular movement may either corroborate the assumption or refute it. In other words, the particular PCIM may be analyzed vis-a-vis one or more interference movements in order to determine whether the particular PCIM is a CIM or an interference movement.

[0056] Enhancing the aforesaid determination process may include determining the location of a movement event/pulse (e.g., movement event/pulse 551) relative to other movement events/pulses (e.g., to adjacent movement events/pulses) in the series, or to the density of the movement pulses. Other time criteria may be used to enhance the aforesaid determination process. For example, a pattern of movement pulses (e.g. movement pulses 551, 552 and 553) may be compared to one or more pre-stored time templates, or time specifics, that may characterize one or more interference movements, and if a particular movement pulse (e.g., movement pulse 552), along with e.g., its adjacent movement pulses, does not match any of the time templates, it may be decided that particular movement pulse is a CIM. Otherwise (the particular movement pulse, along with e.g., its adjacent movement pulses, does match a time template), it may be decided that the particular movement pulse is not a CIM (e.g., it is an interference movement). For example, applying spectral analysis on a movement signal may provide frequency features that may resemble frequency features of a CIM (e.g., movement due to a colon contraction), and, consequently, may result in a movement pulse, e.g. movement pulse 551. However, the same, or similar, frequency features may also characterize movement due to, for example, a walking step. Since each walking step may produce a similar movement pulse (e.g., movement pulses 552 and 553 are similar), and a walking pace (and hence the frequency of the movement pulses caused by walking) is known (within a known margin), a movement event/pulse may be ruled out if it is part of, or contained in, a series of movement events/pulses that collectively represent a non CIM. Similar considerations may be taken into account with respect to other types of reoccurring movement events, for example movement events recurring due to running, heartbeats, respiration process, finger tapping on a tough object, waving of a hand, etc. A movement event resulting from a CIM may also reoccur, but in this case, and in similar cases, the movement event should still be regarded as a CIM. For example, a movement event caused by, or sensed due to, a contraction of, say, the colon, may still be regarded as a CIM despite of it being part of a series of like movement events caused by peristalsis. A time analysis of a movement event, for example vis-a-vis a series of adjacent movement events, may render the determination process more reliable. (Time analysis is further described, for example, below in connection with FIGS. 6A-6C.)

[0057] FIG. 6A shows a time analyzing unit (TAU) 600 according to an example embodiment of the present invention. TAU 600 may include a memory device 610, a time pattern detector ("TPD") 620 and a movement decision logic ("MDL") 630. TAU 600 may receive (612) a series of movement pulses/events (e.g., movement pulses/events 524) that may be output/transferred by/from a FAU (e.g., FAU 500), and it may store the series of movement pulses/events in memory device 610 in order to enable analysis thereof by TPD 620. TPD 620 may compare the series of movement pulses/events (e.g., a movement pulse/pulse at a time) to one or more time templates or time specifics that may be pre-stored in memory device 610. The one or more time tem-

plates, or selected time specifics, may be derived from, correspond to or represent a series of repeating movements that, when considered as a whole, a movement pulse/event, which is part of the series of movement pulses/events, may be determined not to be a CIM (but; e.g., an interference movement). Memory device **610** may store digital data representing an analog movement signal, and information/data representing fiducial CIMs (e.g., frequency and/or temporal characteristics of fiducial CIMs) and interference movements (e.g., frequency and/or temporal characteristics of interference movements). Memory device **610** may also store time specifics defining time templates against which movement events may be compared or analyzed in order to corroborate or refute an initial determination, or assumption, that a device movement, which frequency-wise resembles a fiducial CIM (e.g., a PCIM), is a CIM.

[0058] MDL **630** may determine whether a particular movement pulse in the series of movement pulses represents a CIM based on the comparison results, and output (**632**) a signal indicating that a decision that the particular movement pulse is a CIM, as shown at **640**, or a signal indicating that it is not a CIM, as shown at **650**.

[0059] FIGS. 6B-6C show example movement pulses according to an embodiment of the present invention. FIG. 6B shows one movement pulse **660** that may be the result of, for example, a walking step that a controller (e.g., controller **490**) detected. If movement pulse **660** is considered individually, it may erroneously be regarded as a movement pulse representing a CIM. FIG. 6C, on the other hand, shows a pulse series **670** of movement pulses **672**, **674**, **676** and **678** that may be the result of four detected walking steps. If any of movement pulses **672**, **674**, **676** and **678** is considered individually, it may also be decided as representing, or resulting from, a CIM. However, if any particular movement pulse of movement pulses **672**, **674**, **676** and **678** (e.g., movement pulse **674**) is considered with respect to other (e.g., adjacent) movement pulses (e.g., adjacent movement pulses **672** and **676**), thus considering it in a broader context (rather than individually), the particular movement pulse may correctly be determined by the detector to be a non CIM.

[0060] FIG. 7 shows a time analyzing unit (TAU) **700** according to an example embodiment of the present invention. TAU **700** may include an N-Pulses Register ("NPR"), or N-data cells unit ("DCUs") **710**, a time pattern detector (TPD) **720**, a movement decision logic (MDL) **730** and a timing unit **740**. NPR (also referred to as "DCU") **710** may receive a series of movement pulses **712** (e.g., from a FAU's output; e.g., from FAU **500**), and may be configured to hold/store up to n data units at a time, in n cells (the register's cells are designated as M1, M2, M3, . . . , Mn). "Data unit" may be data including time specifics (e.g., start time, duration) representing a movement event and/or time specifics representing a non-movement period. ("Non-movement period" is a time period that precedes or succeeds a movement event.)

[0061] A data unit representing a first movement event in a series of movement events may be stored in cell M1. When a second movement event is output (or shortly thereafter), for example by FAU **500**, the time specifics pertaining to a first non-movement period that follows the first movement event may be determined in order to produce a data unit representative of the non-movement period. Upon producing the time specifics representative of the first non-movement period, or shortly thereafter, the content of cell M1 may right-shift one cell; e.g., to the next cell (to cell M2), and the data unit

representing the first non-movement period may be stored in cell M1. The same process may be repeated for each new movement event that the FAU outputs, such that with each new data unit that is produced, the content of each cell Mi ($1 \leq i \leq n$) is right-shifted one cell, the new data unit is stored in cell M1, and the data unit stored in cell Mn is replaced by the data unit currently stored in cell Mn-1.

[0062] After a new data unit is stored in cell M1 (regardless of whether the data unit represents a movement event or a non-movement period), and the other data units are right-shifted one cell, all of the data units stored in the N data cells of DCUs **710** may respectively be transferred to n inputs (designated as a1, a2, a3, . . . , an) of time pattern detector (TPD) **720** for evaluation. TPD **720** may function in a similar way as TPD **620**, and movement decision logic (MDL) **730** may function in a similar way as MDL **630**. For example, MDL **730** may output (**732**) a first data or signal indicating a decision that a particular detected movement is a CIM, or a second data or signal indicating a decision that the particular movement is not a CIM. Timing unit **740** may time, or coordinate, data shifts in NPR (DCU) **710** and, in general, it may coordinate operations of NPR/DCU **710** and TPD **720**.

[0063] FIG. 8 is a schematic diagram of an in-vivo imaging/sensing system **800** according to an example embodiment of the invention. In-vivo imaging system **800** may include an in-vivo imaging device **810**, external (extra-body) receiver **820** that may function as a data recorder, workstation **830** (e.g., personal computer), and a display device **832**. In-vivo imaging device **810** may be, for example a swallowable device, capturing images and transmitting corresponding image frames to an external receiving apparatus (e.g., to receiver **820**). The image frames may be presented in real-time or after processing, be combined into an image stream for display to a user, for example by using display **832**.

[0064] An in-vivo imaging device may have at least one imager and/or sensor(s) of other type(s). By way of example, imaging device **810** includes one imager; e.g., imager **812** (more than one or two imagers may be used). In-vivo imaging device **810** may also include a light/illumination source **814**, a data (e.g., image data or) frame generator **816**, a controller **818**, a storage unit **822**, a transceiver **824**, and a power source **826** for powering them. Controller **818**, among other things, may controllably operate illumination source **814** to illuminate areas traversed by in-vivo device **810**, and coordinates the images capturing timing of imager **812**. Controller **818** may momentarily store captured images and related image frames in storage unit **822**. Controller **818** may also perform various calculations and store calculation results in storage unit **522**.

[0065] Frames generator **816** may receive image data **813** from imager **812** and use the image data to produce an image frame ("frame" for short) for the pertinent captured image. A frame typically includes a header field that contains information and/or metadata related to the frame itself (e.g., information identifying the frame, the serial number of the frame, the time the frame, the bit-wise length of the frame, etc.). A frame may also include an uncompressed version of the image data and/or a compressed version thereof. The header may include additional sensory information. Controller **818** may operate illumination source **814** to illuminate, for example, four times per second to enable capturing four images per second, and transceiver **824** to concurrently transmit corresponding frames at the same rate or at a different rate. Controller **818** may operate illumination source **814** to capture more images

per second, for example seventeen images or more than seventeen images per second, and transceiver **824** to concurrently transmit corresponding frames at the same rate. After frames generator **816** produces a frame for a currently captured image, controller **518** wirelessly communicates **825** the frame to receiver/data recorder **820** by using transceiver **824**. Receiver **820** may be a stand-alone receiver that is located close enough to the person swallowing the in-vivo device in order to facilitate receiving and processing of the transmitted frames by data recorder **820**.

[0066] Data recorder (receiver) **820** may include a transceiver **844**, a frame parser **846**, and a processor **848** for managing transceiver **844** and frame parser **846**. Data recorder **820** may include additional components (e.g., USB interface, Secure Digital (“SD”) card driver/interface, controllers, etc.), elements or units, for example, for communicating with (e.g., transferring frames, data, etc. to) an external processing/displaying system that may be configured to process images captured by in-vivo device **810**.

[0067] Transceiver **844** may receive a frame corresponding to a particular captured image, and frame parser **846** may parse the frame to extract the various data entities contained therein (e.g., image data and, optionally, other type of sensory data).

[0068] In-vivo imaging system **800** may also include a workstation **830**. Workstation **830** may include a display or be functionally connected to one or more external displays, for example to display or monitor **832**. Workstation **830** may receive image frames, and other types of data from data recorder **820**, and present them in real-time, for example as live video, or produce a video stream. Workstation **830** may include a memory, such as memory **834**, for storing the frames (and possibly data of other types) transferred from data recorder **820**, and a processor, such as processor **836**, for processing the stored data (e.g., image data). Signals that are transmitted from in-vivo device **810** (e.g., by transceiver **824**) may be received by antennas that are attached or laid in proximity to the body of the person swallowing the in-vivo device. The signals received by the antennas may be forwarded to data recorder **820**, for analysis and interpretation, via a communication cable. (The antennas and the communication cable are not shown in FIG. 8.)

[0069] In-vivo imaging device **810** may also include a MDU **828** for detecting various types of command-invoking movements while filtering out or removing non command-invoking movements. MDU **828** may be implemented using any of the configurations described in connection with FIGS. 4, 5, 6A-6C and 7, and using any method that is described herein. For example, MDU **828** may include the components of MDU **400** (or similar components) and it may function like, or in a similar way as MDU **400**. Controller **818** may be configured to function also as controller **490** of FIG. 4, or vice versa.

[0070] Functionality of a movement detection unit and the consequent execution of a predetermined command may be distributed between in-vivo device **810** and receiver/recorder **820**, or among in-vivo device **810**, receiver/recorder **820** and workstation **830**. For example, in-vivo device **810** may detect movement of in-vivo device **810** using on-board movement sensor(s), and transmit (**825**) movement data to receiver/recorder **820**. Receiver/recorder **820** may analyze the movement data using a FAU and/or a TAU, and, based on the analysis result, determine whether the movement detected by in-vivo device **810** is a CIM or not. If receiver/recorder **820**

determines that the movement is a CIM, receiver/recorder **820** may transmit (**825**) to in-vivo device **810** an instruction to execute a predetermined command, for example, to change an image capturing rate, to change a mode of operation, etc.

[0071] Controller or processor **818** (or controller or processor **836**, **848**), by executing software or instructions, may carry out steps and/or procedures which are performed by any one or more of MDU **828**, MDU **400**, FAU **460**, TAU **470**, FAU **500**, TAU **600** and TAU **700**, and thus may function as these units. Each of controller or processor **818**, **836**, **848** may be or include computer processors, central processing units, etc. In-vivo device **810** may have a longitudinal axis, and movement sensor (which may be part of MDU **828**) may include one accelerometer whose sensing direction coincides with the longitudinal axis of the in-vivo device. Components of in-vivo imaging/sensing system **800** may be similar to components used in a capsule endoscopy system commercially available from the common assignee of the present application, which capsule endoscopy system is commercially known as the PillCam® capsule, or may be similar to other capsule endoscopy systems.

[0072] FIG. 9 shows a method for detecting a command invoking movement of an in-vivo sensing device (e.g., device **810** of FIG. 8) according to an example embodiment of the present invention. At step **900**, a swallowable in-vivo device (e.g., in-vivo device **810**) is swallowed and its movement may continuously, intermittently or occasionally be monitored relative to a non-stationary three-dimensional reference frame. At step **910**, a group of fiducial CIMs and a group of interference movements are predefined, and spectral and temporal characteristics that characterize each movement in each group may be predefined and stored, for example, in storage unit **822**. Spectral and temporal characteristics of fiducial CIMs and interference movements may be defined and stored (e.g., in storage unit **822** prior to the activation or swallowing of the in-vivo device, e.g., they may be stored at the time of manufacture. Storage unit **822** may also store time specifics defining time templates against which movement events may be compared or analyzed in order to corroborate or refute an initial determination, or assumption, that a device movement (PCIM), which frequency-wise resembles a fiducial CIM, is a CIM.

[0073] At step **920**, a movement signal representative of movement of the in-vivo device may be obtained, for example, by using one or more movement sensors, for example accelerometers that are mentioned in connection with acceleration sensor(s) unit **410**. (Other sensors facilitating detection of movement may be used; e.g., magnetometer(s), gyroscope(s), etc.) The accelerometers (or another sensor) may be used to detect a series of movements, or movement events, of the in-vivo device in the non-stationary three-dimensional reference frame. A determination whether a particular movement event, which may be detected in the movement signal is, or is not, a CIM may include spectrally analyzing the particular movement event vis-a-vis fiducial CIMs to determine whether the particular movement is a potential CIM (PCIM), as per step **930**, and performing temporal analysis, as per step **940**, to corroborate, or refute, the determination.

[0074] At step **930** the movement signal may be analyzed spectrally (e.g., by a FAU similar to FAU **500**) vis-a-vis fiducial CIMs to detect one or more PCIMs, with each command-invoking movement is associated a command The spectral analysis of the movement signal may include comparing

spectral features of the detected movement to spectral features of fiducial CIMs. The movement signal, or an interim processing version thereof, may be analyzed spectrally and/or temporally one or more times, or iteratively or repeatedly, and at any order (e.g., first spectrally and then temporally, or vice versa) before the final decision is made. (A PCIM is a movement that resembles a CIM but it may not be a CIM despite the resemblance. For example, a PCIM may be a movement event that is part of a series of interference movements.) However, a final decision regarding classification of this movement event as a CIM or an interference movement (for example) may be made using time analysis, as described and demonstrated herein. (The movement signal may be analyzed temporally and/or spectrally vis-a-vis the interference movements before it is spectrally analyzed vis-a-vis the fiducial CIMs, in order to remove (filter out) interference movements from the movement signal and, thereby, simplify detection of PCIMs in the movement signal.)

[0075] A determination whether a particular movement event (e.g., PCIM) in a series of movements is, or is not, a CIM (e.g., classifying the particular movement event, or PCIM, as a CIM or as an interference movement) may further include temporally analyzing (e.g., by a TAU similar to TAU **620** or TAU **700**) a series of movement events (e.g., PCIMs), including the particular movement event (PCIM), as a whole (e.g., en masse) in order to determine whether the particular movement event (PCIM) is, or is not, a (genuine) CIM, as per step **940**. Step **940** may include temporally analyzing a particular one of the one or more PCIMs vis-a-vis one or more interference movements to determine whether the particular PCIM is a CIM or, for example, an interference movement.

[0076] In step **950** the particular movement event, or PCIM may be classified. If it is determined that the PCIM is a (genuine) CIM (shown as “Y” at step **950**), then, at step **960**, the predetermined command associated with the particular movement event (the command associated with the detected CIM), may be executed (e.g., by a controller similar to controller **490** or controller **818**) in order to perform a predefined operation or operations.

[0077] However, if it is determined that the PCIM is not a CIM (shown as “N” at step **950**), the controller may refrain from executing any predetermined command associated with any CIM, and loop **970** may be repeated or iterated as long as the movement signal is continued to be produced and monitored, in order to detect another movement event, and to determine whether each detected movement event represents, or is related to, elicited by or derived from a CIM or from an interference movement.

[0078] Filtering out an interference movement from a movement signal may include using information indicative of a location and/or an orientation of the in-vivo device for which movement is to be detected. Selection of a fiducial CIM for use may depend on the location of the in-vivo device: different sets of fiducial CIMs may be used for different locations of the device. (Different sets of fiducial CIMs may include common fiducial CIM(s). A set of fiducial CIMs may include one CIM.) Filtering out an interference movement from a movement signal may include analyzing the movement signal by iteratively performing spectral analysis and temporal analysis. A movement of the in-vivo device may be classified as a command-invoking movement or as an interference movement depending (e.g., based) on the location and/or orientation of the in-vivo device relative to any of a

non-stationary three-dimensional reference frame (e.g., the gastrointestinal tract or a portion thereof containing the in-vivo device).

[0079] According to embodiments of the present invention, a printed circuit board (PCB) for enabling (e.g., an in-vivo device) detection of CIMs is also provided, which PCB may include: a primary branch comprising installation units, a processor mounted on a first installation unit, and a first movement sensor mounted on a second installation unit; and a first secondary branch comprising installation units and a second movement sensor mounted on an installation unit of the first secondary branch. The first secondary branch may be connected, for example perpendicularly, to the primary branch via a common installation unit. The PCB may include a second secondary branch including installation units and an imaging sensor that may be mounted on an installation unit of the second secondary branch. The second secondary branch may be connected to the primary branch via a common installation unit. The PCB may be foldable so that the installation units of the primary branch and the installation units of the two secondary branches are stacked along a common lengthwise axis. The processor may be configured to for example detect a series of movements of the in-vivo sensing device from data obtained/originating from the first movement sensor and/or the second movement sensor; spectrally analyze the series of movements vis-a-vis fiducial CIMs, where each fiducial CIM represents a device movement invoking an associated command, to detect a potential CIM, and temporally analyze the series of movements to determine whether the potential CIM is, or is not, a genuine CIM. The processor may further be configured to execute a command associated with the potential CIM if, based on the temporal analysis, the potential CIM is determined (e.g., by the processor) to be a genuine CIM. The processor may perform other functions for example as described herein. An example PCB implementing embodiments of the methods disclosed herein is depicted in FIGS. **10A-10C**, which are described below.

[0080] FIGS. **10A** and **10B** depict a spread out PCB **1000** according to an example embodiment. (FIG. **10B** is a flip over depiction of the PCB of FIG. **10A**.) FIG. **10C** is a three-dimensional depiction of PCB **1000** of FIGS. **10A-10B**. PCB **1000**, which is flexible, may include a primary PCB branch and two secondary PCB branches that are connected to primary PCB branch **1010**. (The primary PCB branch and the secondary PCB branches are respectively shown at **10**, **1020** and **1030** in FIG. **10B**.) Secondary PCB branches **1020** and **1030** are perpendicular to primary PCB branch **1010**.

[0081] Primary PCB branch **1010** may include PCB installation units **1012**, **1014**, **1016** and **1018**, a flexible connection unit **1013** that interconnects PCB installation units **1012** and **1014**, a flexible connection unit **1015** that interconnects PCB installation units **1014** and **1016**, and a flexible connection unit **1017** that interconnects PCB installation units **1016** and **1018**. A first secondary PCB branch **1020** may include PCB installation units **1014** and **1024** and a flexible connection unit **1022** that interconnects them. A second secondary PCB branch **1030** may include PCB installation units **1016** and **1036** and a flexible connection unit **1032** that interconnects them. PCB installation unit **1014** is common to primary PCB branch **1010** and to secondary branch **1020**, and PCB installation unit **1016** is common to primary PCB branch **1010** and to secondary branch **1030**. The common PCB installation

units **1014** and **1016** may be regarded as ‘PCB hubs’ via which the various branches of PCB **1000** are mechanically and functionally connected.

[0082] Each PCB installation unit of PCB **1000** may include (e.g. have mounted thereon) an optical and/or an electrical (or electromechanical) component of the in-vivo device. For example, PCB installation unit **1024** may include an imager **1026** and for example four illumination sources (e.g., four LEDs, one of which is shown at **1028**). (Imager **1026** and the illumination sources may respectively be similar to imager **812** and light source **814** of FIG. 8.) PCB installation unit **1018** may include a sensor module **1040** that may be or include three accelerometers to sense movement of an in-vivo sensing device in three directions. PCB installation unit **1036** may include a sensor module **1050** that may be or include three magnetometers to facilitate sensing of the location and orientation of the in-vivo device. PCB installation unit **1012** may include a radio frequency (“RF”) communication antenna **1003**; PCB installation unit **1014** may include a RF transmitter **1005** and PCB installation unit **1016** may include a processor **1007** for processing acceleration data and/or magnetic data and/or gyroscopic data (depending on the implementation). Other PCB installation units may include, for example, a crystal oscillator, a remotely operated “on/off” switch to switch an in-vivo sensing device on and off, a battery contact (e.g., in the form of a spring coil) to contact a positive or negative pole of a battery, a data storage unit to store an executable instruction code for implementing the methods disclosed herein, etc. By way of example, PCB installation units **1024**, **1014**, **1016** and **1018** may respectively include spring coils **1060**, **1070**, **1080** and **1090**.

[0083] Sensor module **1040** may preferably be located at (or approximately at) the center of mass of PCB **1000** in order to minimize detection of mechanical moments due to rotational movement of the folded PCB (see FIG. 10C) relative to the center of mass of PCB **1000**. In FIG. 10C, the space between spring coils **1060** and **1090** is used to accommodate one or more batteries, and the space between spring coils **1070** and **1080** is also used to accommodate one or more batteries. Due to their considerable weight and location, when the batteries are put in place, the center of mass of the PCB (with the batteries and mounted components) is between PCB installation units **1016** and **1018**. As explained herein, sensor module **1040** is to be interposed between the two batteries, hence the location of sensor module **1040** between PCB installation units **1016** and **1018**. Sensor module **1050**, on the other hand, is to be preferably located as far from the batteries as possible (e.g., furthest, or distanced away, from the center of mass of the in-vivo device) in order to minimize the distortion effect of the batteries on the magnetic field that is to be sensed by the magnetometer(s) of component **1050**. Therefore, sensor module **1050** is mounted on PCB installation unit **1036** which, after folding of PCB **100**, is the farthest PCB installation unit from the batteries.

[0084] FIGS. 10A-10C depict an example configuration where the acceleration sensor(s) and the magnetometer are physically separated (e.g., the accelerometer(s) and the magnetometer(s) are mounted on different installation units) for ease of operation and processing. However, other configurations may be used, where the two functionalities are integrated into one device, and the device may be mounted on installation unit **1018** or on installation unit **1036**. For example, if a maximum mechanical moment expected to be applied to an accelerometer(s) is weak, the accelerometer can

be distanced away from the center of mass of folded PCB **1000** (e.g., it can be mounted on installation unit **1036**, for example together with the magnetometer(s) **1050**). If the distortion in the magnetic field due to, for example, the batteries is small, or if the magnetic field is mathematically restorable from the distorted magnetic field, the magnetometer(s) can be positioned at (or near) the center of mass of folded PCB **100** (e.g., it can be mounted on installation unit **1018**, for example together with accelerometer(s) **1040**).

[0085] The FXOS8700CQ sensor provided by Freescale Semiconductor features a small form factor (3 mm by 3 mm by 1.2 mm), low-power, device integrating linear accelerometer and magnetometer sensors. Components **1040** and/or **1050** may be or include such a sensor or another suitable sensor. If component **1040** is to function as an accelerometer, the magnetometer functionality of the FXOS8700CQ device may be disabled, and if component **1050** is to function as a magnetometer, the accelerometer functionality of the FXOS8700CQ device may be disabled. The BMX055 sensor provided by BOSCH features a small form factor device integrating triaxial accelerometer, triaxial gyroscope and triaxial geomagnetic sensor, which makes it a candidate for sensor modules **1040** and **1050**. (Other off the shelf sensors, and devices that may be specifically devised, may be used as sensor modules **1040** and **1050**.)

[0086] PCB **1000** may be fully flexible or partly rigid and partly flexible (e.g., it may be rigid-flex, which may for example include flexible portions and rigid portions). For example, each of PCB installation units **1012**, **1014**, **1016**, **1018**, **1024** and **1036**, may be rigid or flexible. Flexible connection units **1013**, **1015**, **1017**, **1022** and **1032** enable folding PCB **1000** into a cylindrically shape object. PCB **1000** of FIGS. 10A-10B is shown in FIG. 10C folded to a three-dimensional object **1004** whose general shape resembles a cylinder having a lengthwise axis **1002**. (Flexible PCB **1000** is foldable so that the six installation units are stacked along common lengthwise axis **1002**.) When PCB **100** is folded, all of its PCB installation units are parallel and perpendicular to lengthwise axis **1002**. By imparting to PCB **1000** a shape of a cylinder (e.g., after folding the PCB), PCB **1000** may snugly fit into a cylindrical housing of a capsule-like in-vivo sensing device. As illustrated in FIGS. 10A-10C, the accelerometer(s) (component **1040**) is mounted on primary PCB branch **1010** and the magnetometer(s) (component **1050**) is mounted on secondary PCB branch **1030**. As described above, this PCB configuration ‘puts’ the accelerometer(s), after the PCB is folded, at or near the center of mass of the PCB, and distances the magnetometer(s) as far as possible from the batteries.

[0087] Each installation unit and connection portion of PCB **1000** may have n layers ($n=1, 2, 3, \dots$), and circuit components, which may be mounted on the various layers, may be electrically interconnected through for example micro vias.

[0088] A flexible circuit board **1000** may have a primary PCB branch **1010** and two secondary PCB branches (branches **1020** and **1030**) that are perpendicular to primary PCB branch **1010**. According to this configuration, accelerometer **1040** may be mounted on primary PCB branch **1010** and magnetometer **1050** may be mounted on one of the two secondary PCB branches (e.g., on secondary PCB branch **1020**).

[0089] Flexible circuit board **1000** has a component side, which is shown in FIG. 10A, and a second side, which is shown in FIG. 10B. The circuit board may include: a first

installation unit **1012** that has a first side on which RF antenna **1003** is disposed; a second installation unit **1014** that has a first side on which RF transmitter **1005** is disposed, and a second side on which a battery contact (spring coil) **1070** is mounted, the second installation unit (**1014**) is connected to the first installation unit (**1012**) by flexible connection unit **1013**; a third installation unit (**1016**) having a first side on which processor **1005** is disposed, and a second side on which a battery contact (spring coil) **1080** is mounted, the third installation unit (**1016**) is connected to the second installation unit (**1014**) by flexible connection unit **1015**; a fourth installation unit (**1018**) having a first side on which an accelerometer **1040**, or magnetometer **1050**, or both accelerometer **1040** and magnetometer **1050** is/are disposed, and a second side on which a battery contact (spring coil) **1090** is mounted, the fourth installation unit (**1018**) is connected to the third installation unit (**1016**) by flexible connection unit **1017**; a fifth installation unit (**1024**) having a first side on which imager **1026** is disposed, and a second side on which a battery contact (spring coil) **1060** is mounted, the fifth installation unit (**1024**) is connected to the second installation unit (**1014**) by flexible connection unit **1022**; and a sixth installation unit (**1036**) having a first side on which an accelerometer **1040**, or magnetometer **1050**, or both accelerometer **1040** and magnetometer **1050** is/are disposed, the sixth installation unit (**1036**) is connected to the third installation unit (**1016**) by flexible connection unit **1032**.

[0090] According to an example embodiment, flexible PCB **100** is configured such that after it is folded, the first, second, third, fourth, fifth and sixth flexible installation units are stacked along a common lengthwise axis (e.g., axis **1002**) and form an object whose shape is generally cylindrical. According to an example embodiment, processor **1007** may be configured to process data representing acceleration and/or magnetic field and/or gyroscopic information and/or altimeter information (if an altimeter is incorporated into the in-vivo sensing device) in order to detect movement and/or location and/or orientation of an in-vivo sensing device, and to execute a program that implements the methods disclosed herein in order to determine, among other things, whether a detected movement is a CIM, or not. For example, processor **1007** may be configured to detect a movement of the in-vivo sensing device by using information that is obtained from any of the sensors mounted on PCB **100**, and to determine whether the detected movement is a CIM, or not, and to execute a predetermined command if the detected movement is a CIM, or refrain from executing a CIM-related command if the movement is not a CIM.

[0091] Embodiments of the invention may include an article such as a computer or processor readable non-transitory storage medium, such as for example a memory, a disk drive, or a USB flash memory device encoding, including or storing instructions, e.g., computer-executable instructions, which when executed by a processor or controller, cause the processor or controller to carry out methods disclosed herein. The various processors or controllers discussed herein may in some embodiments be configured to carry out methods according to embodiments of the invention by for example being connected to a memory storing software or instructions which when executed cause the processor to carry out such methods.

[0092] The articles “a” and “an” are used herein to refer to one or to more than one (e.g., to at least one) of the grammatical object of the article, depending on the context. By way of

example, depending on the context, “an element” can mean one element or more than one element. The term “including” is used herein to mean, and is used interchangeably with, the phrase “including but not limited to”. The terms “or” and “and” are used herein to mean, and are used interchangeably with, the term “and/or,” unless context clearly indicates otherwise. The term “such as” is used herein to mean, and is used interchangeably, with the phrase “such as but not limited to”. [0093] Having thus described exemplary embodiments of the invention, it will be apparent to those skilled in the art that modifications of the disclosed embodiments will be within the scope of the invention. Alternative embodiments may, accordingly, include more modules, fewer modules and/or functionally equivalent modules. Features (e.g., frequency features, temporal features) of certain embodiments may be used with other embodiments shown herein. The present disclosure is relevant to various types of in-vivo devices (e.g., in-vivo devices with one or more imagers, in-vivo devices with no imagers at all, etc.). Hence the scope of the claims that follow is not limited by the disclosure herein.

1. A method for executing a command by a swallowable in-vivo device, the method comprising:

in a swallowable in-vivo device moving relative to a non-stationary three-dimensional reference frame and comprising a movement sensor, performing,

spectrally analyzing a movement signal outputted from the movement sensor vis-a-vis fiducial command-invoking movements to detect one or more potential command-invoking movements, wherein each command-invoking movement is associated with a command;

temporally analyzing a particular one of the one or more potential command-invoking movements vis-a-vis one or more interference movements to classify the particular potential command-invoking movement as a command-invoking movement or as an interference movement;

if the particular potential command-invoking movement is classified as a command-invoking movement, executing a command associated with the command-invoking movement; and

if the particular potential command-invoking movement is classified as an interference movement, refraining from executing any command that is associated with any command-invoking movement.

2. The method as in claim 1, comprising filtering out an interference movement from the movement signal prior to the spectral analysis of the movement signal.

3. The method as in claim 2, wherein filtering out the interference movement from the movement signal comprises analyzing the movement signal spectrally, or temporally, or both spectrally and temporally vis-a-vis spectral characteristics, or temporal characteristics, or both spectral and temporal characteristics of the interference movement.

4. The method as in claim 2, wherein filtering out the interference movement from the movement signal comprises any of: (i) analyzing the movement signal spectrally and then temporally, or temporally and then spectrally, using the pertinent spectral and temporal characteristics; (ii) using information indicative of a location, or an orientation, or both a location and an orientation of the in-vivo device; and (iii) analyzing the movement signal by iteratively performing spectral analysis and temporal analysis.

5. (canceled)

6. (canceled)

7. The method as in claim 1, wherein classifying a potential command invoking movement as a command-invoking movement or as an interference movement depends on a location, or orientation, or both location and orientation of the in-vivo device relative to the non-stationary three-dimensional reference frame.

8. The method as in claim 1, wherein determining whether the particular potential command-invoking movement is a command-invoking movement comprises analyzing the movement signal spectrally and then temporally, or temporally and then spectrally.

9. The method as in claim 1, wherein determining whether the particular potential command-invoking movement is a command-invoking movement comprises analyzing the movement signal by iteratively performing spectral analysis and temporal analysis.

10. The method as in claim 1, wherein the non-stationary three-dimensional reference frame is the gastrointestinal tract or a portion thereof containing the in-vivo device.

11. The method as in claim 1, wherein a command associated with a command-invoking movement is selected from the group consisting of: command to change an image capturing rate of a camera of the in-vivo device, a command to change an operation mode or state of the in-vivo device and a command to transmit a message to a receiver external to the in-vivo device.

12. The method as in claim 1, wherein command-invoking movement is selected from a group consisting of: movement due to contraction of the small bowel, movement due to contraction of the colon, movement due to contraction of the stomach, and movement due to intestine constipation, wherein an interference movement is a movement selected from a group consisting of: movement due to human body gestures, movement due to human walking/running, movement due to respiration, movement due to coughing, movement due to finger tapping, and movement due to heart beating.

13. (canceled)

14. The method as in claim 1, wherein the movement signal comprises three movement signals corresponding to movement in three directions.

15. The method as in claim 14, comprising analyzing the three movement signals to detect a command-invoking movement when the in-vivo device is in the stomach, and analyzing one movement signal to detect a command-invoking movement when the in-vivo device is in the small bowel.

16. A method for executing a command by a swallowable in-vivo device, the method comprising:

in a swallowable in-vivo device moving relative to a non-stationary three-dimensional reference frame and comprising a movement sensor, performing,

spectrally analyzing a movement signal outputted from the movement sensor vis-a-vis fiducial command-invoking movements to detect a potential command-invoking movement associated with a command;

temporally analyzing the potential command-invoking movements vis-a-vis interference movements to classify the particular potential command-invoking movement as a command-invoking movement or as an interference movement; and

executing the command if the potential command-invoking movement is classified as the command-invoking movement, and refraining from executing the command

if the potential command-invoking movement is classified as the interference movement.

17. A swallowable in-vivo device comprising:

a memory device to store (i) spectral characteristics and temporal characteristics of fiducial command-invoking movements respectively representing device movements invoking commands, and (ii) spectral characteristics and temporal characteristics of interference movements;

a movement sensor to output a movement signal representing movement of the in-vivo device; and

a controller configured to,

(i) spectrally analyze the movement signal vis-a-vis fiducial command-invoking movements to detect one or more potential command-invoking movements, with each command-invoking movement is associated a command;

(ii) temporally analyze a particular one of the one or more potential command-invoking movements vis-a-vis one or more interference movements to determine whether the particular potential command-invoking movement is a command-invoking movement or an interference movement; and

(iii) execute a command associated with the command-invoking movement or refrain from executing any command-invoking movement related command based on the results of the spectral analysis and temporal analysis.

18. The swallowable in-vivo device as in claim 17, wherein the movement sensor comprises a sensor selected from a group consisting of accelerometer, magnetometer and gyroscope.

19. The swallowable in-vivo device as in claim 17, further comprising a matched filters array module configured to detect a command-invoking movement from the movement signal relative to a non-stationary three-dimensional reference frame.

20. The swallowable in-vivo device as in claim 19, wherein the matched filters array module comprises a band pass filter for each command-invoking movement or for a group of command-invoking movements.

21. The swallowable in-vivo device as in claim 17, wherein the movement sensor comprises an accelerometer whose sensing direction coincides with a longitudinal axis of the in-vivo device.

22. A circuit board for an in-vivo sensing device, comprising:

a primary branch comprising installation units interconnected by flexible connection units, a processor mounted on a first installation unit, and a first movement sensor mounted on a second installation unit; and

a first secondary branch comprising installation units interconnected by a flexible connection unit, and a second movement sensor mounted on an installation unit of said first secondary branch, said first secondary branch is connected to said primary branch via a common installation unit,

a second secondary branch comprising installation units interconnected by a flexible connection unit, and an imaging sensor mounted on an installation unit of said second secondary branch, said second secondary branch is connected to said primary branch via a common installation unit,

wherein the circuit board is foldable so that the installation units of the primary branch and the installation units of the two secondary branches are stacked along a common lengthwise axis,

wherein the processor is configured to,

- (i) detect a series of movements of the in-vivo sensing device from information obtained from the first sensor and/or the second sensor,
- (ii) spectrally analyze the series of movements vis-a-vis fiducial command-invoking movements to detect a potential command-invoking movement, each fiducial command-invoking movement representing a device movement invoking an associated command, and
- (iii) temporally analyze the series of movements to determine whether the potential command-invoking movement is, or is not, a command-invoking movement; and

execute a command associated with the potential command-invoking movement if, based on the temporal analysis, the potential command-invoking movement is determined to be a genuine command-invoking movement.

23. The circuit board as in claim 22, wherein when the circuit board is folded, the first movement sensor is positioned at, or approximately at, a center of mass of the circuit board, and the second movement sensor is positioned as far as possible from the center of gravity of the in-vivo device.

* * * * *

专利名称(译)	用于确定设备移动的方法和系统，而与参考帧的移动无关		
公开(公告)号	US20150335264A1	公开(公告)日	2015-11-26
申请号	US14/761320	申请日	2014-02-06
[标]申请(专利权)人(译)	基文影像公司		
申请(专利权)人(译)	基文影像有限公司.		
当前申请(专利权)人(译)	基文影像有限公司.		
[标]发明人	ROSENBERG OREN KHAIT SEMION		
发明人	ROSENBERG, OREN KHAIT, SEMION		
IPC分类号	A61B5/07 A61B1/00 A61B1/04 A61B1/045 A61B5/11 A61B5/00		
CPC分类号	A61B5/073 A61B5/1123 A61B5/7282 A61B5/1107 A61B1/041 A61B2562/227 A61B1/0002 A61B1/00006 A61B2562/0219 A61B2562/166 A61B1/045 A61B5/067 A61B5/7475		
优先权	61/762401 2013-02-08 US		
其他公开文献	US9949666		
外部链接	Espacenet USPTO		

摘要(译)

可吞咽的体内装置包含运动检测单元，该运动检测单元包括运动传感单元，频率分析单元（FAU）和时间分析单元（TAU）。运动感测单元感测体内装置相对于非静止三维参考系的运动，并输出运动信号。频率分析单元可以在光谱上分析运动信号以检测潜在的命令调用运动，并且时间分析单元可以在时间上分析潜在的CIM，可能结合一系列其他运动事件，以确定潜在的CIM是否是真正的CIM。如果确定潜在的CIM是真正的CIM，则体内设备可以执行与CIM相关联的预定命令。否则，体内设备可以避免执行与CIM相关的命令。为体内感测装置提供包括移动检测单元和用于处理其输出的处理器的PCB。

