



US009861343B2

(12) **United States Patent**
Matsumura

(10) **Patent No.:** **US 9,861,343 B2**
(45) **Date of Patent:** **Jan. 9, 2018**

(54) **TGC CONTROLS FOR AN ULTRASONIC DIAGNOSTIC IMAGING SYSTEM**

(71) Applicant: **KONINKLIJKE PHILIPS N.V.**,
Eindhoven (NL)

(72) Inventor: **Towa Matsumura**, Eindhoven (NL)

(73) Assignee: **KONINKLIJKE PHILIPS N.V.**,
Eindhoven (NL)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **15/022,392**

(22) PCT Filed: **Sep. 10, 2014**

(86) PCT No.: **PCT/IB2014/064360**

§ 371 (c)(1),

(2) Date: **Mar. 16, 2016**

(87) PCT Pub. No.: **WO2015/040524**

PCT Pub. Date: **Mar. 26, 2015**

(65) **Prior Publication Data**

US 2016/0228099 A1 Aug. 11, 2016

Related U.S. Application Data

(60) Provisional application No. 61/879,781, filed on Sep. 19, 2013.

(51) **Int. Cl.**

A61B 8/14 (2006.01)

A61B 8/00 (2006.01)

G01S 7/52 (2006.01)

F21V 23/00 (2015.01)

F21V 33/00 (2006.01)

G01S 15/89 (2006.01)

A61B 90/30 (2016.01)

F21Y 101/00 (2016.01)

(52) **U.S. Cl.**

CPC **A61B 8/54** (2013.01); **A61B 8/14** (2013.01); **A61B 8/467** (2013.01); **F21V 23/003** (2013.01); **F21V 33/0068** (2013.01); **G01S 7/52033** (2013.01); **A61B 8/461** (2013.01); **A61B 2090/309** (2016.02); **F21Y 2101/00** (2013.01); **G01S 15/8925** (2013.01)

(58) **Field of Classification Search**

CPC **A61B 8/14**; **A61B 8/467**; **F21V 23/003**; **F21V 33/0068**; **G01S 15/8925**; **G01S 7/52033**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,482,045 A 1/1996 Rust et al.
5,997,479 A 12/1999 Savord et al.
(Continued)

FOREIGN PATENT DOCUMENTS


JP 2012061239 A1 3/2012

Primary Examiner — Mark Remaly

(57) **ABSTRACT**

The TGC slide switches (20) which provide the TGC control of an ultrasonic diagnostic imaging system have LEDs (10) mounted on the sliders (22) of the slide switches so that the switches can be easily visualized in a darkened room. The light emitted by the LED of a switch is changed to an indicative color or brightness when the slider of the switch is set in its default position (36) for the application of a nominal gain to echo signals received from a given depth.

15 Claims, 4 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

6,436,048	B1	8/2002	Pesque	
2003/0187353	A1	10/2003	Ng	
2006/0112033	A1 *	5/2006	Vion	 G06N 99/005 706/16
2007/0230759	A1 *	10/2007	Tamura	 G01S 7/52033 382/128
2009/0069682	A1 *	3/2009	Hastings	 G01S 7/52084 600/443
2011/0054317	A1 *	3/2011	Lin	 G01S 7/52033 600/443
2013/0096575	A1 *	4/2013	Olson	 G06T 19/003 606/130

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4a




FIG. 4b




FIG. 5a




FIG. 5b

TGC CONTROLS FOR AN ULTRASONIC DIAGNOSTIC IMAGING SYSTEM

This application is the U.S. National Phase application under 35 U.S.C. §371 of International Application No. PCT/IB2014/064360, filed on Sep. 10, 2014, which claims the benefit of U.S. Provisional Application No. 61/879,781 filed Sep. 19, 2013. These applications are hereby incorporated by reference herein.

This invention relates to medical diagnostic ultrasound systems and, in particular, to ultrasound systems with controls for time gain compensation of received ultrasonic echo signals.

When ultrasound signals are transmitted into the body by an ultrasound imaging probe, the waves are continuously attenuated during their passage through tissue, and the returning echoes are further attenuated as they travel back to the transducer. As a consequence echoes are increasingly attenuated as a function of the depth in the body from which they return. The time-honored solution to this attenuation problem is to amplify the received echo signals as a function of the time at which they are received: echoes returning later from the time of transmit are amplified more greatly than those received earlier from shallower depths. The circuitry which performs this amplification is known as time gain compensation (TGC) circuitry, also referred to as sensitivity time control (STC). But the relationship between time and attenuation is not a purely linear one. The echoes experience different degrees of attenuation depending upon the tissue through which they travel. For instance, when imaging the heart relatively little attenuation is experienced as echoes travel through the blood in the heart chamber, and greater attenuation is experienced as echoes travel through the heart muscle, the myocardium. Accordingly the controls for TGC are a series of switches which affect the gain applied at different depths over the depth of the ultrasound image. Typically the switches are slide switches arranged in a column on the ultrasound system control panel. The columnar orientation is immediately seen to correspond to successively greater depths of the image. The switches are generally slide switches with a center position which sets a nominal gain for the corresponding image depth. The slide switches can be moved laterally in either direction to apply more or less than the nominal gain at each depth. Thus the gain profile can be set nonlinearly to vary the gain in relation to the anatomical makeup of the region of the body being imaged. In modern ultrasound systems gain profiles can be stored for particular imaging applications and recalled, applied, and adjusted by the slide switches as appropriate to produce an image of uniform brightness and grey shades over the depth of the image as described in U.S. Pat. No. 5,482,045 (Rust et al.)

Ultrasound exams are often performed in a darkened room so that the sonographer can most easily discern the appearance of the images and subtle structures and functions (e.g., blood flow) being imaged. To enable the sonographer to readily see the controls of the system control panel, the control are often back-lit to aid visibility. The TGC controls can be lighted in various ways. But even with effective back-lighting, the sonographer is often not able to distinguish the specific positions of the TGC switches. In particular, it is frequently difficult for the sonographer to see whether the TGC switches are still set in their nominal center positions or have been adjusted to a different gain setting. Accordingly it is desirable to provide TGC controls which are easily discernible and their setting readily visualized in a darkened exam room.

In accordance with the principles of the present invention, a diagnostic ultrasound system is described with illumination provided for the individual switches of the TGC control. The illumination is uniquely controlled or modulated when a switch is in its center position as by color or brightness modulation or control. The sonographer is thereby readily able to visualize the gain setting of the switches from their orientation pattern and to immediately discern those switches which are set in their nominal center positions.

In the drawings:

FIG. 1 illustrates the control panel of an ultrasonic diagnostic imaging system.

FIG. 2 is a detailed view of the TGC control of the ultrasound system of FIG. 1 constructed in accordance with the principles of the present invention.

FIG. 3 illustrates in block diagram form the major components of an ultrasound system including TGC circuitry.

FIGS. 4a and 4b illustrate illuminated TGC controls of the present invention when viewed in a darkened room.

FIGS. 5a and 5b illustrate implementations of the present invention by pulse width modulation and color control of an LED on a TGC control.

Referring first to FIG. 1, an ultrasound system control panel 28 is shown in a perspective view. When a user desires to perform a particular ultrasonic examination such as imaging the liver, the user selects the desired procedure by using the controls on the control panel 28. This may involve interaction with a menu of parameters and performance choices shown on the display monitor 62 using the trackball and a select button on the control panel to select the desired parameters. Upon selection of an imaging procedure the system will select an optimal TGC characteristic stored in the system memory for the procedure and apply it to the TGC circuitry as described below. The TGC circuitry will then control the gain of the TGC amplifier in the system's signal path in accordance with this optimal TGC characteristic. The system will also supply graphical information to the image display so that a visual representation of the optimal TGC characteristic will be shown on the image display 62 adjacent to the image. This TGC curve then illustrates the relative amounts of gain applied to echoes returning from progressively deeper depth of the image region.

The optimal, predetermined TGC characteristic will be displayed and used to control the amplifier of the TGC circuitry when the slide switches 20 on the control panel are vertically aligned in their central position 36 as shown in FIG. 2. If the clinician finds that variation from the predetermined characteristic is needed to better image a particular patient, the clinician will move the slide switches to the right or left to reset the slope segments of the TGC gain characteristic. As the switches are moved the changes are communicated from the control panel 28 to the TGC circuitry, which applies the incremental changes to the predetermined characteristic. The effects of these changes are shown by visual changes to the displayed TGC characteristic on the display screen. When the clinician is finished adjusting the TGC switches 20 the variation from the predetermined characteristic is indicated by the new physical positions of the switches on the control panel and the final TGC characteristic is shown on the display screen. A uniform gain adjustment over the full image depth is applied by adjusting a gain control adjustment 26.

Referring to FIG. 3, an ultrasound system constructed in accordance with the principles of the present invention is shown in block diagram form. In this implementation the ultrasound probe includes a two dimensional array trans-

ducer **500** and a microbeamformer **502**. The present invention may be used with probes employing either one dimensional or two dimensional transducer arrays. The microbeamformer contains circuitry which controls the signals applied to groups of elements ("patches") of the array transducer **500** and does some combining of the echo signals received by elements of each group. Micro-beamforming in the probe advantageously reduces the number of conductors in the cable **503** between the probe and the ultrasound system and is described in U.S. Pat. No. 5,997,479 (Savord et al.) and in U.S. Pat. No. 6,436,048 (Pesque).

The probe is coupled to the scanner **310** of the ultrasound system. The scanner includes a beamform controller **312** which is responsive to a user control on the control panel, such as a probe select control, and provides control signals to the microbeamformer **502** instructing the probe as to the timing, frequency, direction and focusing of transmit beams for the desired image and the selected probe. The beamform controller also control the beamforming of received echo signals by its coupling to the analog-to-digital (A/D) converters **316** and a beamformer **116**. Echo signals received by the probe are amplified by preamplifier and an amplifier of the TGC (time gain control) circuitry **314**, then digitized by the A/D converters **316**. The digitized echo signals are then formed into beams by the beamformer **116**. The echo signals from individual elements or patches of elements of the array **500** are then processed by an image processor **318** which performs digital filtering, B mode detection, and/or Doppler processing, and can also perform other signal processing such as harmonic separation, speckle reduction through frequency compounding, digital gain (including digital TGC) and other desired image or signal processing.

The echo signals produced by the scanner **310** are coupled to a display subsystem **320** which processes the echo signals for display in the desired image format. The echo signals are processed by an image line processor **322** which is capable of sampling the echo signals, splicing segments of beams into complete line signals, and averaging line signals for signal-to-noise improvement or flow persistence. The image lines of each image are scan converted into the desired image format by a scan converter **324** which performs R-theta conversion as is known in the art. The images are then stored in an image memory **328** from which they can be displayed on the display **150**. The images in memory are also overlaid with graphics to be displayed with the images, such as the TGC characteristic described above, which are generated by a graphics generator **330** which is responsive to a user control. Individual image frames or image frame sequences can be stored in a cine memory **326** during capture of image loops.

In accordance with the principles of the present invention, each slider switch **22** of the TGC controls is lighted with an LED **10** mounted on the slider of the switch as shown in FIG. **2**. Each slider has a range of control dictated by the extent of a cutout **24** in the control panel along which the slider can travel laterally. Thus, if the uppermost slider (corresponding to the shallowest depth) is moved to the left it will appear to the left of the column of the LEDs of the other switches. The sonographer can see at a glance that at the shallowest depth a low gain setting is in place, while the gains applied at the deeper depths are all nominal gain settings. The illuminated LEDs on the switch sliders will make this visibly clear even in a darkened room.

In accordance with a further aspect of the present invention, each LED **10** produces a distinguishing illumination when it is set in its nominal central position **36**. A variety of different illumination differentiation techniques may be

used. One is to illuminate the LED brightly when the slider **22** is in its center position, and dimmer when the slider is moved away from the center position. FIG. **5a** illustrates a potentiometer **12** of a TGC slider switch with a slider arm **14**. When the slider is centered, the differential amplifier **16** switches to a low output, which disables the input of a pulse width modulator **17**. In this null state, the LED **10** is driven by a steady voltage, producing a bright illumination. But when the slider arm **14** is moved off center, the differential amplifier **16** switches to a high output, enabling the pulse width modulator **17**, which drives the LED **10** with a pulse width modulated pulse train. The LED illumination is then dimmer.

Another approach to illumination variation is to vary the color of the light of the LED when the slider **22** is in its center position. In FIG. **5b** when the slider arm **14** is centered the differential amplifier **16** causes the LED to be illuminated with a predetermined color such as red. This can be done with a color controller **17** that selects the color of an RGB LED, or by varying the color temperature of the LED **10**. When the slider arm is moved off center, the color controller **17** selects a different color for an RGB LED, white instead of red, for instance, or changes the color temperature to a different one than used in the centered position.

Each TGC control will produce a value (digital or analog) depending upon its setting, which is coupled to an illumination controller. The illumination controller compares the digital value against the known value of the center position setting. If the two values are not equal the difference value is used to control the pulse width modulation duty cycle and/or frequency to dim the illumination. For the color modulation implementation three independent pulse width modulators are used to control the duty cycle or frequency of each color of an RGB LED to produce virtually any desired color.

FIGS. **4a** and **4b** illustrate the effect of such color modulation. FIG. **4a** illustrates a series of lights on eight TGC sliders. The settings range from a low gain at the shallow depths by the top sliders, which are set to the left of center, and ranging down to greater than nominal gains at the deepest depths where it is seen that the lower-most sliders have been moved to the right. This curved pattern of white LEDs gives little indication of which sliders were untouched and remain in their nominal gain positions. But in the example of FIG. **4b**, the LEDs for the third, fifth, and sixth sliders **26**, **27**, and **28** are modulated to produce a reddish color (as represented by the dotted patterns), which clearly stand out in relation to the other white LEDs. The sonographer can see at a glance that no adjustment has been made to the nominal gains at these depths.

Other illumination schemes will readily occur to those skilled in the art. The LEDs could be illuminated red when moved to a higher gain setting (to the right), green when moved to a lower gain setting (to the left), and white when set in the nominal center position, for instance. Another alternative is to use the pulse width modulator to blink the LEDs on and off to indicate by the blinking those that are in the center position or those that have been moved.

What is claimed is:

1. A diagnostic ultrasound system with time gain compensation comprising:
 - an ultrasound system control panel and a plurality of TGC controls located on the ultrasound system control panel and configured to be set in a nominal position or adjusted to other positions to control time gain compensation;

5

wherein the system further comprises:

- a plurality of lighting devices, each located on one of the TGC controls; and
- an illumination controller that is responsive to the setting of a TGC control in its nominal position, is coupled to at least one lighting device of the TGC control, is configured to generate visibly distinguishing illumination by the lighting device when its TGC control is set in the nominal position.

2. The diagnostic ultrasound system of claim 1, wherein the TGC controls further comprise slide switches.

3. The diagnostic ultrasound system of claim 2, wherein the lighting devices further comprise LEDs; wherein the slide switches each further comprise a user-operable slider; wherein an LED is mounted on each slider.

4. The diagnostic ultrasound system of claim 3, wherein each slider can be moved along a lateral range of adjustment; wherein the nominal position is the center of the lateral range.

5. The diagnostic ultrasound system of claim 4, further comprising a slider position sensor responsive to movement of a slider along its range of adjustment which senses when the slider is in the center of the lateral range.

6. The diagnostic ultrasound system of claim 5, wherein the illumination controller is further responsive to the slider position sensor.

7. The diagnostic ultrasound system of claim 6, wherein the slider position sensor further comprises a differential amplifier.

8. The diagnostic ultrasound system of claim 1, wherein the illumination controller further acts to visibly distinguish illumination by the lighting device by changing the color of light produced.

6

9. The diagnostic ultrasound system of claim 1, wherein the illumination controller further acts to visibly distinguish illumination by the lighting device by changing the brightness of light produced.

10. The diagnostic ultrasound system of claim 9, wherein the illumination controller further comprises a pulse width modulator.

11. The diagnostic ultrasound system of claim 10, wherein the lighting devices further comprise LEDs; wherein the pulse width modulator drives an LED with a width-modulated pulse to reduce the brightness of light produced by the LED.

12. The diagnostic ultrasound system of claim 8, wherein the lighting devices further comprise LEDs; wherein the illumination controller further acts to change the color of light produced by an LED by changing the color temperature of the LED.

13. The diagnostic ultrasound system of claim 12, wherein the color of light produced by an LED is set to a reddish color when a TGC control is set in its nominal position.

14. The diagnostic ultrasound system of claim 8, wherein the lighting devices further comprise RGB LEDs; wherein the illumination controller further comprises an LED color controller.

15. The diagnostic ultrasound system of claim 1, wherein the TGC controls further act to control time gain compensation by enabling user adjustment of the amplification applied to ultrasonic echo signals received from different depths of imaging.

* * * * *

专利名称(译)	TGC控制超声诊断成像系统		
公开(公告)号	US9861343	公开(公告)日	2018-01-09
申请号	US15/022392	申请日	2014-09-10
[标]申请(专利权)人(译)	皇家飞利浦电子股份有限公司		
申请(专利权)人(译)	皇家飞利浦N.V.		
当前申请(专利权)人(译)	皇家飞利浦N.V.		
[标]发明人	MATSUMURA TOWA		
发明人	MATSUMURA, TOWA		
IPC分类号	A61B8/14 A61B8/00 F21V33/00 F21V23/00 G01S7/52 G01S15/89 A61B90/30 F21Y101/00		
CPC分类号	A61B8/54 A61B8/14 A61B8/467 F21V23/003 G01S7/52033 F21V33/0068 G01S15/8925 A61B8/461 A61B2090/309 F21Y2101/00 A61B8/00 G01N29/00 G01S7/52		
优先权	61/879781 2013-09-19 US		
其他公开文献	US20160228099A1		
外部链接	Espacenet USPTO		

摘要(译)

TGC滑动开关 (20) 提供超声诊断成像系统的TGC控制, LED (10) 安装在滑块上 (22 滑动开关使得开关可以在黑暗的房间中容易地看到。当开关的滑块设置在默认位置 (36) 时, 开关LED发出的光会变为指示颜色或亮度, 以便为接收的回波信号施加标称增益从给定的深度。

