



US 20090124905A1

(19) **United States**(12) **Patent Application Publication****Ahn et al.**(10) **Pub. No.: US 2009/0124905 A1**(43) **Pub. Date: May 14, 2009**(54) **ULTRASOUND SYSTEM AND METHOD FOR FORMING BC-MODE IMAGE**(76) Inventors: **Chi Young Ahn**, Seoul (KR); **Woo Youl Lee**, Seoul (KR)

Correspondence Address:

JONES DAY**222 EAST 41ST ST****NEW YORK, NY 10017 (US)**(21) Appl. No.: **12/270,750**(22) Filed: **Nov. 13, 2008**(30) **Foreign Application Priority Data**

Nov. 14, 2007 (KR) 10-2007-0116212

Publication Classification(51) **Int. Cl.****A61B 8/00**

(2006.01)

(52) **U.S. Cl.** **600/443**(57) **ABSTRACT**

The present invention relates to an ultrasound system. A control generates a first control signal for a B-mode scan and a second control signal for a C-mode scan. A transmit/receive unit transmits ultrasound signals along a plurality of scan lines set in a target object and form receive signals based on the ultrasound echo signals reflected from the target object. The receive signals include first receive signals corresponding to the scan lines and second receive signals corresponding to a portion of scan lines within the color box. The image processing unit forms a B-mode image and a C-mode image based on the first and second receive signals, and combine the B-mode image with the C-mode image to form a BC-mode image. The control unit computes a time ratio of a first time required to form the B-mode image to a second time required to form the C-mode image, and generates a third control signal for a B-mode scan along scan lines, which are not within the color box, based on the time ratio to form third receive signals. The image processing unit forms a B-mode image based on the third receive signals and the second signals.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7





FIG. 8



ULTRASOUND SYSTEM AND METHOD FOR FORMING BC-MODE IMAGE

[0001] The present application claims priority from Korean Patent Application No. 10-2007-0116212 filed on Nov. 14, 2007, the entire subject matter of which is incorporated herein by reference.

BACKGROUND OF THE INVENTION

[0002] 1. Technical Field

[0003] The present invention generally relates to ultrasound systems, and more particularly to an ultrasound system and a method for forming a BC-mode image.

[0004] 2. Background Art

[0005] An ultrasound system has become an important and popular diagnostic tool due to its non-invasive and non-destructive nature. Modern high-performance ultrasound imaging diagnostic systems and techniques are commonly used to produce two- or three-dimensional images of internal features of patients.

[0006] The ultrasound system may provide a BC-mode image indicating a blood flow or a motion of a target object, which is estimated by using a Doppler effect, on a B-mode image. The BC-mode image is a combination image comprising a B-mode image of a grey scale and a color flow image (i.e., C-mode image) indicating the blood flow or the motion of the target object. The BC-mode image may provide anatomical information as well as information regarding the blood flow or the motion of the target object.

[0007] The conventional ultrasound image may form the B-mode image and the C-mode image with different frame rates and then combine the B-mode image with the C-mode image to thereby form the BC-mode image. Since the frame rate of the B-mode may not be enough to obtain information regarding blood flow or the motion of the target object such as a cardiac muscle, the frame rate of the BC-mode must be improved such that motion information of the target object such as a cardiac muscle, which is rapidly moved, can be accurately provided.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] FIG. 1 is a block diagram showing an embodiment of an ultrasound system.

[0009] FIG. 2 is a schematic diagram showing an embodiment of a control unit.

[0010] FIG. 3 is a schematic diagram illustrating a display example of a B-mode image, a plurality of scan lines and a color box.

[0011] FIGS. 4 to 8 are schematic diagrams showing examples of forming a B-mode image in forming a BC-mode image in accordance with one embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0012] FIG. 1 is a block diagram showing an embodiment of an ultrasound system. As shown in FIG. 1, the ultrasound system 100 may include a control unit 110, a transmit/receive unit 120, a storage unit 130, an image processing unit 140 and a display unit 150. The ultrasound system 110 may further include an input unit (not shown) to receive input information from a user. The input information may include setup infor-

mation for setting a color box on a B-mode image, i.e., position and size information of the color box.

[0013] The control unit 110 may be operable to control the formation of a BC-mode image in consideration of a time required to form a B-mode image and a time required to form a C-mode image. The control unit 110 may be further operable to control operations of the transmit/receive unit 120, the storage unit 130, the image processing unit 140 and the display unit 150.

[0014] FIG. 2 is a block diagram showing an illustrative embodiment of the control unit 110. A time computing unit 111 may be operable to compute a time required to form a B-mode image ("first time") and a time required to form a C-mode image ("second time"). The first time (T_B) and the second time (T_C) may be computed by using the following equations (1) and (2).

$$T_B = N_B / PRF_B \quad (1)$$

$$T_C = N_C \times PS / PRF_C \quad (2)$$

wherein N_B represents the number of scan lines used to form the B-mode image, PRF_B represents a pulse repetition frequency used to form the B-mode image, N_C represents the number of the scan lines used to form the C-mode image, PS represents a packet size indicating repetition times of transmitting and receiving an ultrasound beam along one scan line, and PRF_C represents a pulse repetition frequency used to form the C-mode image.

[0015] A ratio computing unit 112 may be operable to compute a time ratio of the first time T_B to the second time T_C . The time ratio may be computed by dividing the first time T_B by the second time T_C in accordance with one embodiment of the present invention. For example, when the first time T_B is 8 ms and the second time T_C is 2 ms, the time ratio is 4 (=8 ms/2 ms). When there is a fractional part in the division result, the time ratio may be determined with only integer part.

[0016] A determining unit 113 may be operable to compare the time ratio with a preset critical value (e.g., 1) to check whether the time ratio exceeds the critical value. If the time ratio exceeds the critical value, the determining unit 113 may output first determination information containing the time ratio. On the contrary, if not, the determining unit 113 may output second determination information.

[0017] If the first determination information is inputted, a scan line group setting unit 114 may be operable to set a plurality of scan line groups as many as the time ratio indicated by the first determination information. For example, when the time ratio is "4," scan lines S_1 - S_{64} illustrated in FIG. 3 may be divided into four scan line groups SG_1 , SG_2 , SG_3 and SG_4 , as follows.

[0018] First scan line group $SG_1 = \{S_1, S_5, S_9, S_{13}, S_{17}, \dots, S_{53}, S_{57}, S_{61}\}$

[0019] Second scan line group $SG_2 = \{S_2, S_6, S_{10}, S_{14}, S_{18}, \dots, S_{54}, S_{58}, S_{62}\}$

[0020] Third scan line group $SG_3 = \{S_3, S_7, S_{11}, S_{15}, S_{19}, \dots, S_{55}, S_{59}, S_{63}\}$

[0021] Fourth scan line group $SG_4 = \{S_4, S_8, S_{12}, S_{16}, S_{20}, \dots, S_{56}, S_{60}, S_{64}\}$

[0022] A control signal generating unit 115 may be operable to generate a control signal for controlling transmission and reception of the ultrasound beam. The control signal may include a first control signal for controlling the formation of a B-mode image 210, i.e., a B-mode scan such that the ultrasound beam is transmitted and received along the scan lines S_1 - S_{64} . The control signal may further include a second con-

control signal for controlling the formation of the C-mode image, i.e., a C-mode scan such that the ultrasound beam is transmitted and received along scan lines S_{10} to S_{56} within a color box **220** set on the B-mode image **210** (see FIG. 3). The control signal also includes a third control signal for controlling the transmission and reception of the ultrasound beam such that the ultrasound beam for the B-mode image is alternately transmitted and received along scan lines included in the respective scan line groups.

[0023] If the second determination information is inputted from the determining unit **113**, the control signal generating unit **115** may be operable to generate a fourth control signal for a B-mode scan such that the ultrasound beam is transmitted along scan lines S_1 - S_9 and S_{57} - S_{64} , which do not belong to the color box **220**.

[0024] The transmit/receive unit **120** may be operable to transmit the ultrasound beam along scan lines set in a target object and receive ultrasound echoes reflected from the target object in response to the control signal. If the first control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to sequentially transmit the ultrasound beam along the scan lines S_1 - S_{64} in response to the first control signal and receive ultrasound echoes reflected from the target object to thereby form receive signals corresponding to the scan lines S_1 - S_{64} ("first receive signals") for a B-mode image. The first receive signals may include information associated with the scan lines, e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained at the sampling points and the like.

[0025] If the second control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} belonging to the color box **220** in response to the second control signal and receive ultrasound echoes reflected from the target object to thereby form receive signals corresponding to the scan lines S_{10} - S_{56} ("second receive signals") for the C-mode image. The second receive signals may include information associated with the scan lines S_{10} - S_{56} , e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained from the sampling points and the like.

[0026] If the third control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_1 , S_5 , S_9 , S_{13} , S_{17} , S_{21} , S_{25} , S_{29} , S_{33} , S_{37} and S_{61} included in the first scan line group SG_1 and receive ultrasound echoes from the target object in response to the third control signal to thereby form receive signals corresponding to the scan lines included in the first scan line group SG_1 ("first scan line group receive signals"). The first scan line group receive signals may include information associated with the scan lines of the first scan line group SG_1 , e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained from the sampling points and the like. Thereafter, if the second control signal is inputted, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} within the color box **220** and receive ultrasound echoes reflected from the target object in response to the second control signal to thereby form new second receive signals for a C-mode image.

[0027] Subsequently, if the third control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan

lines S_2 , S_6 , S_{10} , S_{14} , S_{18} , S_{22} , S_{26} , S_{30} , S_{34} , S_{38} and S_{62} included in the second scan line group SG_2 and receive ultrasound echoes from the target object in response to the third control signal to thereby form receive signals corresponding to the scan lines included in the second scan line group SG_2 ("second scan line group receive signals"). The second scan line group receive signals may include information associated with the scan lines of the first scan line group SG_2 , e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained from the sampling points and the like. Thereafter, if the second control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} within the color box **220** and receive ultrasound echoes reflected from the target object in response to the second control signal to thereby form new second receive signals.

[0028] Successively, if the third control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_3 , S_7 , S_{11} , S_{15} , S_{19} , S_{23} , S_{27} , S_{31} , S_{35} , S_{39} and S_{63} included in the third scan line group SG_3 and receive ultrasound echoes from the target object in response to the third control signal to thereby form receive signals corresponding to the scan lines included in the third scan line group SG_3 ("third scan line group receive signals"). The third scan line group receive signals may include information associated with the scan lines of the third scan line group SG_3 , e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained from the sampling points and the like. Thereafter, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} within the color box **220** and receive ultrasound echoes reflected from the target object in response to the second control signal to thereby form new second receive signals.

[0029] If the third control signal is inputted again from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_4 , S_8 , S_{12} , S_{16} , S_{20} , S_{24} , S_{28} , S_{32} , S_{36} , S_{40} and S_{64} included in the fourth scan line group SG_4 and receive ultrasound echoes from the target object in response to the third control signal to thereby form receive signals corresponding to the scan lines included in the fourth scan line group SG_4 ("fourth scan line group receive signals"). The fourth scan line group receive signals may include information associated with the scan lines of the fourth scan line group SG_4 , e.g., position information of the scan lines, position information of sampling points on the scan lines, data obtained from the sampling points and the like. Thereafter, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} within the color box **220** and receive ultrasound echoes reflected from the target object in response to the second control signal to thereby form new second receive signals. The transmit/receive unit **120** may be operable to repeat the above process until an end request is inputted.

[0030] In the meantime, if the fourth control signal is inputted from the control unit **110**, the transmit/receive unit **120** may be operable to transmit the ultrasound beam along scan lines S_1 - S_9 and S_{57} - S_{64} , which are not within the color box **220** among the scan lines S_1 - S_{64} , and receive ultrasound echoes reflected from the target object to thereby form receive signals corresponding to the scan lines S_1 - S_9 and S_{57} - S_{64} ("third receive signals"). In such a case, the third receive signals may contain information associated with the scan

lines S_1 - S_9 and S_{57} - S_{64} , i.e., position information of the scan lines, position information of sampling points on the scan lines, data obtained at the sampling points and the like. Thereafter, if the second control signal is inputted from the control unit 110, the transmit/receive unit 120 may be operable to transmit the ultrasound beam along the scan lines S_{10} - S_{56} within the color box 220 and receive ultrasound echoes reflected from the target object in response to the second control signal to thereby form new second receive signals. The transmit/receive unit 120 may be operable to repeat the above process until an end request is inputted from the control unit 110.

[0031] The storage unit 130 may sequentially store the first receive signals, the second receive signals, the first to fourth scan line group receive signals and the third receive signals.

[0032] The image processing unit 140 may be operable to extract the first receive signals from the storage unit 130 and form a B-mode image based on the first receive signals. The image processing unit may be operable to extract the second receive signals from the storage unit 130 and form a C-mode image based on the extracted second receive signals. The image processing unit 140 may be operable to combine the B-mode image with the C-mode image to form a BC-mode image. Subsequently, the image processing unit 140 may be operable to extract the first scan line group receive signals and first receive signals in which first receive signals corresponding to the scan lines S_1 , S_5 , S_9 , S_{13} , S_{17} , ..., S_{53} , S_{57} and S_{61} included in the first scan line group SG_1 are excluded, and then update the first receive signals with the extracted first scan line group receive signals. The image processing unit 140 may be operable to form a B-mode image 310 based on the updated first receive signals, as illustrated in FIG. 4. The image processing unit may extract the new second receive signals from the storage unit 130 and form a C-mode image based on the extracted second receive signals. Thereafter, the image processing unit 140 may be operable to combine the B-mode image 310 with the C-mode image to form a BC-mode image.

[0033] The image processing unit 140 may be operable to extract the second scan line group receive signals and first receive signals excepting the receive signals corresponding to the scan lines included in the second scan line group SG_2 to update the first receive signals. The image processing unit 140 may be operable to form a B-mode image 320 based on the updated first receive signals, as illustrated in FIG. 5. The image processing unit may extract the new second receive signals from the storage unit 130 and form a C-mode image based on the extracted new second receive signals. Thereafter, the image processing unit 140 may be operable to combine the B-mode image 320 with the C-mode image to form a BC-mode image.

[0034] The image processing unit 140 may be operable to extract the third scan line group receive signals and first receive signals in which the receive signals corresponding to the scan lines included in the third scan line group SG_3 are excluded to update the first receive signals. The image processing unit 140 may be operable to form a B-mode image 330 based on the updated first receive signals, as illustrated in FIG. 6. The image processing unit may extract the new second receive signals from the storage unit 130 and form a C-mode image based on the extracted second receive signals. Thereafter, the image processing unit 140 may be operable to combine the B-mode image 330 with the C-mode image to form a BC-mode image.

[0035] The image processing unit 140 may be operable to extract the fourth scan line group receive signals and first receive signals in which the receive signals corresponding to the scan lines included in the fourth scan line group SG_4 are excluded to update the first receive signals. The image processing unit 140 may be operable to form a B-mode image 340 based on the updated first receive signals, as illustrated in FIG. 7. The image processing unit may extract the new second receive signals from the storage unit 130 and form a C-mode image based on the extracted second receive signals. Thereafter, the image processing unit 140 may be operable to combine the B-mode image 340 with the C-mode image to form a BC-mode image. The image processing unit 140 may repeatedly carry out the above process until an end request is inputted from the control unit 110.

[0036] In the meantime, the image processing unit 140 may extract the third receive signals and the first receive signals from the storage unit 130, and then form a B-mode image 350 based on the extracted third and second receive signals, as illustrated in FIG. 8. Thereafter, the image processing unit 140 may extract the second receive signals and form a C-mode image based on the extracted second receive signals. The image processing unit 140 may combine the B-mode image with the C-mode image to form a BC-mode image.

[0037] The display unit 150 may be operable to display the B-mode image and the BC-mode image formed in the image processing unit 140.

[0038] As mentioned above, since the time required to form the B-mode image may be reduced in accordance with the present invention, the frame rate of the BC-mode image may be improved. Thus, an ultrasound image of a rapidly moving target object may be clearly provided.

[0039] In accordance with one embodiment of the present invention, there is provided an ultrasound system, comprising: a control unit operable to generate a first control signal for a B-mode scan and a second control signal for a C-mode scan; an input unit operable to receive color box information for setting a color box; a transmit/receive unit responsive to the first and second control signals and operable to transmit ultrasound signals along a plurality of scan lines set in a target object and form receive signals based on the ultrasound echo signals reflected from the target object, said receive signals including first receive signals corresponding to the scan lines formed in response to the first control signal and second receive signals corresponding to a portion of scan lines within the color box formed in response to the second control signal; an image processing unit operable to form a B-mode image and a C-mode image based on the first and second receive signals, and combine the B-mode image with the C-mode image to form a BC-mode image, wherein the control unit is further operable to compute a time ratio of a first time required to form the B-mode image to a second time required to form the C-mode image, and generate a third control signal for a B-mode scan along scan lines, which are not within the color box, based on the time ratio, wherein the receive signals further include third receive signals formed in response to the third control signal, and the image processing unit is further operable to form a B-mode image based on the third receive signals and the second signals.

[0040] In accordance with another embodiment of the present invention, there is provided a method of forming a BC-mode image, comprising: a) generating a first control signal for a B-mode scan and a second control signal for a C-mode scan; b) transmitting ultrasound signals along a plu-

ality of scan lines set in a target object and form first receive signals based on the ultrasound echo signals reflected from the target object in response to the first control signals; c) forming a B-mode image based on the first receive signals; d) receiving color setup information for setting a color box on the B-mode image; e) transmitting ultrasound signals along scan lines within the color box in response to the second control signal; f) combining the B-mode image with the C-mode image to form a BC-mode image; g) computing a time ratio of a first time required to form the B-mode image to a second time required to form the C-mode image; h) generating a third control signal for a B-mode scan along scan lines, which are not within the color box, based on the time ratio, to form third receive signals; i) forming a new B-mode image based on the third receive signals and the second signals; j) generating the second control signal to thereby form new C-mode image and combining the new B-mode image with the new C-mode image to form a new BC-mode image; and i) repeating h) to j).

[0041] Any reference in this specification to “one embodiment,” “an embodiment,” “example embodiment,” etc. means that a particular feature, structure or characteristic described in connection with the embodiment is included in at least one embodiment of the present invention. The appearances of such phrases in various places in the specification are not necessarily all referring to the same embodiment. Further, when a particular feature, structure or characteristic is described in connection with any embodiment, it is submitted that it is within the purview of one skilled in the art to effect such feature, structure or characteristic in connection with other ones of the embodiments.

[0042] Although embodiments have been described with reference to a number of illustrative embodiments thereof, it should be understood that numerous other modifications and embodiments can be devised by those skilled in the art that will fall within the spirit and scope of the principles of this disclosure. More particularly, numerous variations and modifications are possible in the component parts and/or arrangements of the subject combination arrangement within the scope of the disclosure, the drawings and the appended claims. In addition to variations and modifications in the component parts and/or arrangements, alternative uses will also be apparent to those skilled in the art.

What is claimed is:

1. An ultrasound system, comprising:

a control unit operable to generate a first control signal for a B-mode scan and a second control signal for a C-mode scan;

an input unit operable to receive color box information for setting a color box;

a transmit/receive unit responsive to the first and second control signals and operable to transmit ultrasound signals along a plurality of scan lines set in a target object and form receive signals based on ultrasound echo signals reflected from the target object, said receive signals including first receive signals corresponding to the scan lines formed in response to the first control signal and second receive signals corresponding to a portion of scan lines within the color box formed in response to the second control signal;

an image processing unit operable to form a B-mode image and a C-mode image based on the first and second receive signals, and combine the B-mode image with the C-mode image to form a BC-mode image,

wherein the control unit is further operable to compute a time ratio of a first time required to form the B-mode image to a second time required to form the C-mode image, and generate a third control signal for a B-mode scan along scan lines, which are not within the color box, based on the time ratio,

wherein the receive signals further include third receive signals formed in response to the third control signal, and the image processing unit is further operable to form a B-mode image based on the third receive signals and the second signals.

2. The ultrasound system of claim 1, further comprising a storage unit to store the first, second and third receive signals.

3. The ultrasound system of claim 2, wherein the control unit includes:

a time computing unit configured to compute the first and second times;

a ratio computing unit configured to compute the time ratio;

a determining unit configured to check whether the time ratio is greater or less than a critical value, the determining unit further being configured to generate first determination information when the time ratio is greater than the critical value and second determination information when the time ratio is less than the critical value;

a scan line group setting unit configured to divide the scan lines to the plurality of scan line groups based on the time, wherein each of the scan line groups include different scan lines; and

a control signal generating unit configured to generate the third control signal based on the first determination information and a fourth control signal for an alternate B-mode scan along scan lines of the respective scan line groups based on the second determination information.

4. The ultrasound system of claim 3, wherein the receive signals further include scan line group receive signals formed in response to the fourth control signal, and the image processing unit is further operable to update the first receive signals with the scan line group receive signals and form a B-mode image based on the updated first receive signals,

wherein the control unit is further operable to alternately generate the fourth control signal and the second control signal.

5. The ultrasound system of claim 3, wherein the ratio computing unit computes the time ratio as the following equation:

$$\text{Time ratio} = \text{first time} / \text{second time}.$$

6. A method of forming a BC-mode image, comprising:

a) generating a first control signal for a B-mode scan and a second control signal for a C-mode scan;

b) transmitting ultrasound signals along a plurality of scan lines set in a target object and form first receive signals based on ultrasound echo signals reflected from the target object in response to the first control signals;

c) forming a B-mode image based on the first receive signals;

d) receiving color box information for setting a color box on the B-mode image;

e) transmitting ultrasound signals along scan lines within the color box in response to the second control signal;

f) combining the B-mode image with the C-mode image to form a BC-mode image;

- g) computing a time ratio of a first time required to form the B-mode image to a second time required to form the C-mode image;
 - h) generating a third control signal for a B-mode scan along scan lines, which are not within the color box, based on the time ratio, to form third receive signals;
 - i) forming a new B-mode image based on the third receive signals and the second signals;
 - j) generating the second control signal to thereby form a new C-mode image and combining the new B-mode image with the new C-mode image to form a new BC-mode image; and
 - i) repeating h) to j).
7. The method of claim 6, further comprising storing the first, second and third receive signals.
8. The method of claim 7, wherein g) includes:
- g1) computing the first and second times;
 - g2) computing the time ratio of the first time to the second time;
 - g3) checking whether the time ratio is greater or less than a critical value;
 - g4) if it is determined that the time ratio is greater than the critical value, generating first determination information,

and if it is determined that the time ratio is less than the critical value, generating second determination information;

- g5) dividing the scan lines to the plurality of scan line groups based on the time ratio, wherein each of the scan line groups include different scan lines; and
- g6) generating the third control signal based on the first determination information and a fourth control signal for an alternate B-mode scan along scan lines of the respective scan line groups based on the second determination information.

9. The method of claim 8, wherein the receive signals further include scan line group receive signals formed in response to the fourth control signal, wherein the method further comprises updating the first receive signals with the scan line group receive signals, forming a B-mode image based on the updated first receive signals, and alternately generating the fourth control signal and the second control signal.

10. The method of claim 9, wherein the time ratio is computed as the following equation:

$$\text{Time ratio} = \text{first time} / \text{second time}.$$

* * * * *

专利名称(译)	超声系统及形成BC模式图像的方法		
公开(公告)号	US20090124905A1	公开(公告)日	2009-05-14
申请号	US12/270750	申请日	2008-11-13
[标]申请(专利权)人(译)	AHN CHI YOUNG LEE WOO烈		
申请(专利权)人(译)	AHN CHI YOUNG LEE WOO烈		
当前申请(专利权)人(译)	AHN CHI YOUNG LEE WOO烈		
[标]发明人	AHN CHI YOUNG LEE WOO YOUL		
发明人	AHN, CHI YOUNG LEE, WOO YOUL		
IPC分类号	A61B8/00		
CPC分类号	G01S7/52025 G01S15/8988 G01S7/52085 G01S7/52063 A61B8/08		
优先权	1020070116212 2007-11-14 KR		
其他公开文献	US8216141		
外部链接	Espacenet USPTO		

摘要(译)

超声系统技术领域本发明涉及超声系统。控制器产生用于B模式扫描的第一控制信号和用于C模式扫描的第二控制信号。发送/接收单元沿着设置在目标对象中的多条扫描线发送超声信号，并基于从目标对象反射的超声回波信号形成接收信号。接收信号包括对应于扫描线的第一接收信号和对应于彩色盒内的一部分扫描线的第二接收信号。图像处理单元基于第一和第二接收信号形成B模式图像和C模式图像，并将B模式图像与C模式图像组合以形成BC模式图像。控制单元计算形成B模式图像所需的第一时间与形成C模式图像所需的第二时间的的时间比，并产生用于沿扫描线的B模式扫描的第三控制信号，不在彩盒内，根据时间比例形成第三接收信号。图像处理单元基于第三接收信号和第二信号形成B模式图像。

