



US006970733B2

(12) **United States Patent**
Willis et al.

(10) **Patent No.:** **US 6,970,733 B2**
(45) **Date of Patent:** ***Nov. 29, 2005**

(54) **SYSTEM AND METHOD FOR ELECTRODE LOCALIZATION USING ULTRASOUND**

FOREIGN PATENT DOCUMENTS

(75) Inventors: **N. Parker Willis**, Atherton, CA (US);
Axel Briskén, Fremont, CA (US);
Jinglin Zeng, San Jose, CA (US);
Marsha Hurd, Clayton, CA (US)

EP 0 499 491 A2 8/1992
EP 0 775 466 A2 5/1997

(73) Assignee: **SciMed Life Systems, Inc.**, Maple Grove, MN (US)

OTHER PUBLICATIONS

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 291 days.

de Zwart, M. et al., "Endocardial Catheter Mapping—Development of An Interactive Expert System for the Measurement of Local Activation and 3-Dimensional Electrode Position," *IEEE*, 1988, pp. 105–108.

Smith, W. et al., "Three Dimensional Ultrasonic Micrometer for Use in Cardiovascular Research," Annual International Conference of the IEEE Engineering in Medicine and Biology Society, vol. 13, No. 4, 1991, pp. 1520–1521.

This patent is subject to a terminal disclaimer.

Gubbels, Andrew, "Sonomicrometer Enhancement Implementing 16-Bit Counters into EPLDs," E.S. 400– Project Report, Mar. 25, 1993, pp. 1–72.

(21) Appl. No.: **10/273,468**

Klein, R., et al., "A System For 3D Tracking of Limb Movement," (1990) *IEEE*, Ninth Ann. Conf. of Eng. in Med. & Biol. Sci. (2 pages).

(22) Filed: **Oct. 21, 2002**

(65) **Prior Publication Data**

(Continued)

US 2003/0036696 A1 Feb. 20, 2003

Related U.S. Application Data

Primary Examiner—Ruth S. Smith

(74) Attorney, Agent, or Firm—Bingham McCutchen LLP

(63) Continuation of application No. 08/905,090, filed on Aug. 1, 1997, now Pat. No. 6,490,474.

(57) **ABSTRACT**

(51) **Int. Cl.**⁷ **A61B 5/04**

The present invention is a device localization system that uses one or more ultrasound reference catheters to establish a fixed three-dimensional coordinate system within a patient's heart using principles of triangulation. The coordinate system is represented graphically in three-dimensions on a video monitor and aids the clinician in guiding other medical devices, which are provided with ultrasound transducers, through the body to locations at which they are needed to perform clinical procedures. In one embodiment of a system according to the present invention, the system is used in the heart to help the physician guide mapping catheters for measuring electrical activity, and ablation catheters for ablating selected regions of cardiac tissue, to desired locations within the heart.

(52) **U.S. Cl.** **600/424; 600/374; 606/41; 607/122**

(58) **Field of Search** **600/373, 374, 600/424, 509; 606/32, 34, 41, 45, 49; 607/122, 126**


(56) **References Cited**

U.S. PATENT DOCUMENTS

4,100,916 A 7/1978 King
4,173,228 A 11/1979 Van Steenwyk et al.
4,304,239 A 12/1981 Perlin

(Continued)

33 Claims, 26 Drawing Sheets



U.S. PATENT DOCUMENTS

4,431,005 A 2/1984 McCormick
 4,444,195 A 4/1984 Gold
 4,499,493 A 2/1985 Nishimura
 4,522,212 A 6/1985 Gelinas et al.
 4,573,473 A 3/1986 Hess
 4,613,866 A 9/1986 Blood
 4,628,937 A 12/1986 Hess et al.
 4,649,924 A 3/1987 Taccardi
 4,697,595 A 10/1987 Breyer et al.
 4,699,147 A 10/1987 Chilson et al.
 4,777,955 A 10/1988 Brayton et al.
 4,785,817 A 11/1988 Stouffer
 4,812,976 A 3/1989 Lundy
 4,821,206 A 4/1989 Arora
 4,821,731 A 4/1989 Martinelli et al.
 4,899,750 A 2/1990 Ekwall
 4,922,912 A 5/1990 Watanabe
 4,940,064 A 7/1990 Desai
 4,945,305 A 7/1990 Blood
 5,000,190 A 3/1991 Petre
 5,012,814 A 5/1991 Mills et al.
 5,025,786 A 6/1991 Siegel
 5,041,973 A 8/1991 Lebron et al.
 5,042,486 A 8/1991 Pfeiler et al.
 5,054,492 A 10/1991 Scribner et al.
 5,054,496 A 10/1991 Wen et al.
 5,056,517 A 10/1991 Fenici
 5,081,993 A 1/1992 Kitney et al.
 5,104,393 A 4/1992 Isner et al.
 5,107,746 A 4/1992 Bauer
 5,154,501 A 10/1992 Svenson et al.
 5,156,151 A 10/1992 Imran
 5,158,092 A 10/1992 Glace
 5,161,536 A 11/1992 Vilkomerson et al.
 5,172,699 A 12/1992 Svenson et al.
 5,214,615 A 5/1993 Bauer
 5,220,924 A 6/1993 Frazin
 5,222,501 A 6/1993 Ideker et al.
 5,246,016 A 9/1993 Lieber et al.
 5,295,484 A 3/1994 Marcus et al.
 5,297,549 A 3/1994 Beatty et al.
 5,311,873 A 5/1994 Savard et al.
 5,335,663 A 8/1994 Oakley et al.
 5,341,807 A 8/1994 Nardella
 5,357,956 A 10/1994 Nardella
 5,367,614 A 11/1994 Bisey
 5,385,148 A 1/1995 Lesh et al.
 5,391,199 A 2/1995 Ben-Haim
 5,412,619 A 5/1995 Bauer
 5,443,489 A 8/1995 Ben-Haim
 5,480,422 A 1/1996 Ben-Haim
 5,515,853 A 5/1996 Smith et al.
 5,546,951 A 8/1996 Ben-Haim
 5,553,611 A 9/1996 Budd et al.
 5,588,432 A 12/1996 Crowley
 5,590,657 A 1/1997 Cain et al.
 5,669,878 A 9/1997 Dickinson et al.
 5,722,402 A 3/1998 Swanson et al.
 5,782,899 A 7/1998 Imran
 5,868,673 A 2/1999 Vesely
 5,938,602 A 8/1999 Lloyd
 5,954,649 A 9/1999 Chia et al.

OTHER PUBLICATIONS

Langberg, J. et al., "The Echo-Transponder Electrode Catheter: A New Method for Mapping the Left Ventricle," *JACC*, vol. 12, No. 1 Jul. 1998, pp. 218-223.

Fenici, R., et al., "Catheter Ablation of Cardiac Arrhythmias: Magnetocardiographic Localization of Electrocatheters and Arrhythmogenic Foci," 8th International Congress "The New Frontiers of Arrhythmias," Marilleva, Italy, Jan. 31-Feb. 4, 1998, pp. 723-731.

Fenici, R., et al. "Magnetocardiographic Localization of a Pacing Catheter," *Advances in Biomagnetism*, 1989, pp. 361-364.

Moshage, W. et al., "Biomagnetic Localization of Ventricular Arrhythmias¹," *Radiology*, Sep. 1991, pp. 686-692.

Potratz, J. et al., "Echocardiographic Guiding of Catheter-Electrode During Endocardial Mapping to Determine Location of Late Fractionated Potentials in Patients with Acute Myocardial Infarction," *European Heart Journal*, vol. 12, Abstract Supplement, p. 235, abstract 1242 (Aug. 1991).

Fenici, R., et al., "Biomagnetically localizable multipurpose catheter and method for MCG guided intracardiac electrophysiology, biopsy and ablation of cardiac arrhythmias," *International Journal of Cardiac Imaging*, 1991, vol. 7, pp. 207-215.

Saumarez, R. et al., "Geometrically Accurate Transaortic Mapping of Left Ventricular Endocardial Activation During Surgery," *JACC*, vol. 19, No. 1, Jan. 1992, pp. 125-129.

Aoyagi, S. et al., "Using Ultrasonic Naves," *IEEE*, (1991) pp. 2466-2471.

Cikes, I., et al., "Cardiac Catheterisation Guided By Ultrasound," *Echocardiography in Cardiac Interventions*, 1989, pp. 77-88.

Ferek-Petric, B., et al., "Ultrasonically Marked Pacing System," *Echocardiography in Cardiac Interventions*, 1989, pp. 88-97.

Sonomicrometer Module—Model 201, Product Information Sheets (6 pages) Triton Technology, Inc., 1995.

Josephson, M. et al., "Role of Catheter Mapping in the Preoperative Evaluation of Vestricular Tachycardia," *The American Journal of Cardiology*, Jan. 1982, vol. 49, pp. 207-220.

Josephson, M. et al., "Comparison of Endocardial Catheter Mapping with Intraoperative Mapping of Ventricular Tachycardia," *Circulation*, vol. 61, No. 2, Feb. 1980, pp. 395-404.

Josephson, M. et al., "Ventricular Activation During Ventricular Endocardial Pacing. II. Role of Pace-Mapping to Localize Orgin of Ventricular Tachycardia," *The American Journal of Cardiology*, Jul. 1982, vol. 50, pp. 11-22.

Witkowski, F., et al., "An Automated Simultaneous Transmural Cardiac Mapping System," *The American Physiological Society*, 1984, pp. H661-H668.

Fann, J. et al., "Endocardial Activation Mapping and Endocardial Pace-Mapping Using a Balloon Apparatus," *Amer. J. Cardiol.*, vol. 55, Apr. 1, 1985, pp. 1076-1083.

Hauer, R. et al., "Endocardial Catheter Mapping: Wire Skeleton Technique for Representation of Computed Arrhythmogenic Sites Compared With Intraoperative Mapping," *Circulation*, vol. 74, No. 6, Dec. 1986, pp. 1346-1354.

Huang, S. et al., "Radiofrequency Catheter Ablation of the Left and Right Ventricles: Anatomic and Electrophysiologic Observations," *Pace*, vol. 11, Apr. 1988, pp 449-459.

Shenasa, M. et al., "Cardiac Mapping. Part I: Wolff-Parkinson-White Syndrome," *Pace*, vol. 13 Feb. 1990, pp. 223-230.

Scheinman, M. "Current Role of Catheter Ablative Procedures in Patients With Cardiac Arrhythmias," *Circulation*, vol. 83, No. 6, Jun. 1991, pp. 2146-2153.

- Buckles, D. et al., "Computer-Enhanced Mapping of Activation Sequences in the Surgical Treatment of Supraventricular Arrhythmias," *Pace*, vol. 13, Nov. 1990, pp. 1401-1407.
- Tanigawa, M. et al., "Prolonged and Fractionated Right Atrial Electrograms During Sinus Rhythm in Patients With Paroxysmal Atrial Fibrillation and Sick Sinus Node Syndrome," *The American College of Cardiology*, Feb. 1991, vol. 17, No. 2, pp. 403-408.
- Kaltenbrunner, W. et al., "Epicardial and Endocardial Mapping of Ventricular Tachycardia in Patient With Myocardial Infarction," *Circulation*, Sep. 1991, vol. 84, No. 3, pp. 1058-1071.
- Massé, S. et al., "A Three-Dimensional Display for Cardiac Activation Mapping," *Pace*, vol. 14, Apr. 1991, Part I, pp. 538-545.
- Desai, J. et al., "Orthogonal Electrode Catheter Array for Mapping of Endocardial Focal Site of Ventricular Activation," *Pace*, vol. 14, Apr. 1991, Part I, pp. 557-574.
- Pollak, S. et al., "Intraoperative Identification of a Radiofrequency Lesion Allowing Validation of Catheter Mapping of Ventricular Tachycardia with a Computerized Balloon Mapping System," *Pace*, vol. 15, Jun. 1992, pp. 854-858.
- Chen, S. et al., "Reappraisal of Electrical Cure of Atrioventricular Nodal Reentrant Tachycardia—Lessons From a Modified Catheter Ablation Technique," *International Journal of Cardiology*, (1992) vol. 37, pp. 51-60.
- Chen, S. et al., "Radiofrequency Catheter Ablation For Treatment of Wolff-Parkinson-White Syndrome—Short- and Long-term Follow-up," *International Journal of Cardiology*, vol. 37 (1992) pp. 199-207.
- Scheinman, M. "North American Society of Pacing and Electrophysiology (NASPE) Survey on Radiofrequency Catheter Ablation: Implications for Clinicians, Third Party Insurers, and Government Regulatory Agencies," *Pace*, vol. 15, Dec. 1992, pp. 2228-2231.
- Silka, M. et al., "Phase Image Analysis of Anomalous Ventricular Activation in Pediatric Patients With Preexcitation Syndromes or Ventricular Tachycardia," *American Heart Journal*, Feb. 1993, vol. 125, pp. 372-380.
- Josephson, M., "Recurrent Ventricular Tachycardia," pp. 566-580; 608-615; and "Surgical and Nonsurgical Ablation in the Therapy of Arrhythmias," pp. 770-783, *Clinical Cardiac Electrophysiology: Techniques and Interpretations*, Sec. Ed., Lea & Febiger, 1993.
- Kuchar, D. et al., "Electrocardiographic Localization of the Site of Origin of Ventricular Tachycardia in Patients With Prior Myocardial Infarction," *JACC*, Mar. 15, 1989, vol. 13, No. 4, pp. 893-900.
- Holt, P. et al., "Ventricular Arrhythmias," *British Heart Journal*, 1985, vol. 53, pp. 417-430.
- Ratcliffe, M. et al., "Use of Sonomicrometry and Multidimensional Scaling to Determine the Three-Dimensional Coordinates of Multiple Cardiac Locations: Feasibility and Initial Implementation," *IEEE Transactions on Biomedical Engineering*, vol. 42, No. 6, Jun. 1995, pp. 587-598.
- Meyer, S. et al., "Application of Sonomicrometry and Multidimensional Scaling to Cardiac Catheter Tracking," *IEEE Transactions on Biomedical Engineering*, vol. 44, No. 11, Nov. 1997, pp. 1061-1067.
- Jackman, W. et al., "New Catheter Technique for Recording Left Free-Wall Accessory Atrioventricular Pathway Activation," *Circulation*, Sep. 1988, vol. 78, No. 3, pp. 598-611.
- Pagé, P. et al., "Surgical Treatment of Ventricular Tachycardia," *Circulation*, Sep. 1989, vol. 80 (suppl I) pp. I-124-I-134.
- Tweddell, J. et al., "Potential Mapping in Septal Tachycardia," *Circulation*, Sep. 1989, vol. 80 (suppl I) pp. I-97-I-108.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 10




FIG. 9




FIG. 11




FIG. 12




FIG. 13




FIG. 14A




FIG. 14B




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 20




FIG. 21




FIG. 22




FIG. 23






FIG. 24






FIG. 27A







FIG. 27B






FIG. 29





FIG. 30A






FIG. 31




FIG. 32






FIG. 33






FIG. 34C




FIG. 34D




FIG. 35




FIG. 36A




FIG. 36B




FIG. 36C

SYSTEM AND METHOD FOR ELECTRODE LOCALIZATION USING ULTRASOUND

RELATED APPLICATION DATA

This application is a continuation of application Ser. No. 08/905,090, filed Aug. 1, 1997 (now U.S. Pat. No. 6,490,474).

FIELD OF THE INVENTION

The present invention relates generally to the field of ultrasound tracking systems. More specifically, it relates to systems for tracking the positions of devices within the human body.

BACKGROUND OF THE INVENTION

For certain types of minimally invasive medical procedures, endoscopic visualization of the treatment site within the body is unavailable or does not assist the clinician in guiding the needed medical devices to the treatment site.

Examples of such procedures are those used to diagnose and treat supra-ventricular tachycardia (SVT), atrial fibrillation (AF), atrial flutter (AFL) and ventricular tachycardia (VT). SVT, AFL, AF and VT are conditions in the heart which cause abnormal electrical signals to be generated in the endocardial tissue to cause irregular beating of the heart.

A procedure for diagnosing and treating SVT or VT involves measuring the electrical activity of the heart using an electrophysiology catheter introduced into the heart via the patient's vasculature. The catheter carries mapping electrodes which are positioned within the heart and used to measure electrical activity. The position of the catheter within the heart is ascertained using fluoroscopic images. A map of the measured activity is created based on the fluoroscopic images and is shown on a graphical display. A physician uses the map to identify the region of the endocardium which s/he believes to be the source of the abnormal electrical activity. An ablation catheter is then inserted through the patient's vasculature and into the heart where it is used to ablate the region identified by the physician.

To treat atrial fibrillation (AF), an ablation catheter is maneuvered into the right or left atrium where it is used to create elongated ablation lesions in the heart. These lesions are intended to stop the irregular beating of the heart by creating non-conductive barriers between regions of the atria. These barriers halt passage through the heart of the abnormal electrical activity generated by the endocardium. Following the ablation procedure, a mapping catheter is positioned in the heart where it is used to measure the electrical activity within the atria so that the physician may evaluate whether additional lesions are needed to form a sufficient line of block against passage of abnormal currents. S/he may also attempt to induce atrial fibrillation using a pacing electrode, and then further evaluate the line of block by analyzing the time required for the induced electrical activity to pass from one side of the block to the other.

The procedures used to diagnose and treat SVT, VT, AFL and AF utilize catheters which are maneuvered within the heart under fluoroscopy. Because the fluoroscopic image is in two-dimensions and has fairly poor resolution, it may be difficult for the physician to be certain of the catheter positions. Thus, for example, once a physician has identified an area which is to be ablated (using a map of the measured electrical activity of the heart) it may be difficult to navigate an ablation catheter to the appropriate location in order to accurately ablate the area of concern. It is therefore desirable

to provide a system by which the positions of medical devices such as mapping and ablation catheters may be accurately guided to selected regions of the body.

Prior art tracking devices of the type which may track the positions of medical devices are described in U.S. Pat. No. 5,515,853 (Smith et al) and U.S. Pat. No. 5,546,951 (Ben Haim). While useful, neither of the disclosed systems provides for determining medical device locations relative to a fixed coordinate system within the body. The lack of a fixed coordinate system within the body can lead to tracking errors which in turn render it difficult to guide medical devices to the desired locations within the body.

It is therefore desirable to provide an ultrasound tracking system for medical devices which permits the tracking of devices relative to a fixed internal coordinate system. The system according to the present invention meets this objective as well as many others which enhance the accuracy and usefulness of the tracking system.

SUMMARY OF THE INVENTION

The present invention is a device localization system that uses one or more ultrasound reference catheters to establish a fixed three-dimensional coordinate system within a patient's heart, preferably using principles of triangulation. The coordinate system is represented graphically in three-dimensions on a video monitor and aids the clinician in guiding other medical devices, which also carry ultrasound transducers, through the body to locations at which they are needed to perform clinical procedures. In one embodiment of a system according to the present invention, the system is used in the heart to help the physician guide mapping catheters for measuring electrical activity, and ablation catheters for ablating selected regions of cardiac tissue, to desired locations within the heart.

Three-dimensional images are shown on a video display which represent the three-dimensional positions and orientations of at least portions of the medical devices used with the system, such as the reference catheter, and the electrodes of the mapping catheter and ablation catheter. The video display may additionally include representations of the electrical activity measured by each mapping electrode at its respective location on the three-dimensional display. It may also represent ablation lesions formed within the body at the appropriate three-dimensional locations, and/or certain anatomic structures which may facilitate navigation of the medical device(s) within the patient.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic representation of the system according to the present invention, showing the major components of the system.

FIG. 2 is a schematic representation of a three-dimensional coordinate system established using a reference catheter according to the present invention.

FIG. 3 is a side elevation view of a reference catheter for use with the system according to the present invention.

FIG. 4 is a side elevation view of a first alternative embodiment of a reference catheter for use with the system according to the present invention, in which ultrasound transducers are included on a catheter of a type conventionally used in the RV apex.

FIG. 5 is a side elevation view of a second alternative embodiment of a reference catheter for use with the system according to the present invention, in which ultrasound transducers are included on a catheter of a type conventionally used in the coronary sinus.

FIG. 6 is a perspective view of a piezoelectric cylinder of a type which may be used on catheters according to the present invention, including those shown in FIGS. 3-5.

FIG. 7 is a side elevation view of the piezoelectric cylinder of FIG. 6 mounted on a catheter and modified to include a divergent lens.

FIG. 8 is a perspective view of a mandrel having a polymer piezoelectric wrapped around it for use with a reference catheter according to the present invention.

FIG. 9 is a side elevation view of a catheter for use with the system of the present invention which is provided with marking and ablation capabilities.

FIG. 10 is a perspective view of a first alternative embodiment of a catheter with marking and ablation capabilities according to the present invention.

FIGS. 11 and 12 are side section views of second and third alternative embodiments of catheters having marking and ablation capabilities according to the present invention.

FIG. 13 is a side elevation view of a mapping catheter for use with the system of the present invention. As with all of the catheters shown herein, the sizes of the electrodes and transducers are exaggerated for purposes of illustration.

FIG. 14A is a front elevation view of the mapping catheter of FIG. 13, showing the spacing of the basket arms.

FIG. 14B is a view similar to the view of FIG. 14A showing alternate basket arm spacing.

FIG. 15 is a cross-section view of the mapping catheter taken along the plane designated 15-15 in FIG. 13.

FIG. 16 is a plan view of an arm of the mapping catheter of FIG. 13.

FIG. 17 is a cross-section view of the arm of FIG. 16, taken along the plane designated 17-17.

FIG. 18 is a side elevation view of a linear lesion catheter for use in the system according to the present invention.

FIG. 19 is a side section view of the linear lesion catheter of FIG. 18.

FIG. 20 is a cross-section view taken along the plane designated 20-20 in FIG. 19.

FIG. 21 is a cross-section view taken along the plane designated 21-21 in FIG. 19.

FIG. 22 is a cross-section view taken along the plane designated 22-22 in FIG. 19.

FIG. 23 is a side section view, similar to the view of FIG. 19, of an alternative embodiment of a linear lesion catheter for use with the system of the present invention.

FIG. 24 is a cross-section view taken along the plane designated 24-24 in FIG. 23.

FIG. 25 is a side section view, similar to the view of FIG. 19, of an alternative embodiment of a linear lesion catheter for use with the system of the present invention.

FIG. 26 is a cross-section view taken along the plane designated 26-26 in FIG. 25.

FIG. 27A is a schematic drawing showing ultrasound ranging hardware and its interaction with the ultrasound hardware control and timing systems.

FIG. 27B is a schematic diagram illustrating in greater detail ultrasound ranging hardware and ultrasound hardware control and timing systems of the type shown in FIG. 27A.

FIG. 28A is a plot of the voltage over time on an ultrasound transmit line following initiation of a transmit pulse, and illustrates the ringing which occurs on the transmit line following the transmit pulse.

FIG. 28B is a plot of the voltage over time on an ultrasound receive line which is located near the transmit

line at the time the transmit pulse of FIG. 28A is initiated. The figure shows the ringing which results from the ringing on the transmit line, and also shows a receive pulse following the ringing.

FIG. 28C is a plot of the voltage over time on an ultrasound receive line which is located very close to a transmit wire at the time the transmit pulse of FIG. 28A is instituted, and it illustrates that the receive pulse may be lost in the ringing.

FIG. 28D is a plot of the voltage over time on an ultrasound transmit line which is short circuited immediately following the initiation of a transmit pulse.

FIG. 28E is a plot of the voltage over time on an ultrasound receive line which is adjacent to the transmit line represented in FIG. 28D. The figure shows that ringing is eliminated on the receive line when the transmit line is short circuited just after the transmit pulse is sent.

FIG. 29 is a schematic diagram illustrating a pulse generator circuit which includes a switch for short circuiting the transmit line just after the transmit pulse is sent.

FIG. 30A is a schematic illustration of the sample and hold system used for gating position information to the cardiac cycle.

FIG. 30B shows an EKG plot together with a plot of transducer coordinates and illustrates a sample and hold sequence which takes transducer coordinates at the end of diastole.

FIGS. 31 and 32 illustrate the graphical user interface of the system according to the present invention. FIG. 31 illustrates display of anatomical features, reference catheters, a linear lesion catheter, and burns formed in the heart using the linear lesion catheter. FIG. 32 illustrates display of the reference catheters, anatomical features, burns formed in the heart, and a basket catheter together with its mapping electrode positions.

FIG. 33 is a flow diagram illustrating use of the catheters of FIGS. 3, 9 and 13 to treat ventricular tachycardia.

FIGS. 34A-34C are a series of views of a heart illustrating certain of the steps of FIG. 33: FIG. 34A is an anterior section view of the heart showing placement of a reference catheter in the right ventricle and a marking catheter in the left ventricle. FIG. 34B is a lateral view of the heart showing a reference catheter in the coronary sinus. FIG. 34C is an anterior section view of the heart showing a reference catheter in the right ventricle and a mapping catheter in the left ventricle. FIG. 34D is a view similar to the view of FIG. 34C showing introduction of an ablation catheter into the mapping catheter.

FIG. 35 is a flow diagram illustrating use of the system according to the present invention together with the catheters of FIGS. 3, 9, 13 and 18 to treat atrial fibrillation.

FIGS. 36A-36C are a series of views of a heart illustrating certain of the steps of FIG. 35: FIG. 36A is an anterior section view of the heart showing placement of a reference catheter in the RV apex and a marking catheter in left atria; FIG. 36B is an anterior section view of the heart showing a linear lesion ablation catheter in the left atria; FIG. 36C is an anterior section view of the heart showing a mapping catheter in the left atria.

DETAILED DESCRIPTION

Localization System Overview

The localization system and procedure will next be described in general terms. Specific examples of procedures which may be carried out using the system will be described

in the Operation section of this description. The system is described primarily with respect to catheters in the heart, but it should be understood that the system is intended for use with other medical devices and in other regions of the body as well.

Referring to FIG. 1, the present invention is a device localization system 100 that uses one or more ultrasound reference catheters 10 to establish a three-dimensional coordinate system within a patient's heart. The system allows the positions of one or more additional catheters 12, 14, 16, to be represented graphically on a graphical user interface 124 relative to a coordinate system. This aids the clinician in guiding the additional catheter(s) 12, 14, 16 through the heart to locations at which they are needed to perform clinical procedures.

In one embodiment of a system according to the present invention, the additional catheters include mapping catheters 14 for measuring electrical activity within the heart and ablation catheters 12, 16 for ablating selected regions of cardiac tissue. These catheters 12-16 may also be described as "electrophysiology catheters" or "EP catheters."

Each of the reference catheters 10 carries a plurality of ultrasound transducers, with there being a total of at least four such transducers employed during use of the system. The reference catheter transducers can function as ultrasound receivers by converting acoustic pressure to voltage, and as ultrasound transmitters by converting voltage to acoustic pressure. Each of the additional catheters 12, 14, 16 carries at least one ultrasound transducer which preferably functions as an ultrasound receiver but which may also function as a transmitter or a transmitter/receiver.

Using known techniques, the distance between each transducer and other ones of the transducers may be computed by measuring the respective time for an ultrasound pulse to travel from a transmitting transducer to each receiving transducer. These distance measurements are preferably carried out in parallel. In other words, when an ultrasound pulse is emitted by a reference catheter transducer, the system simultaneously measures the respective times it takes for the pulse to reach each of the other transducers being used in the system.

The velocity of an acoustic signal in the heart is approximately 1570-1580 mm/msec, with very small variations caused by blood and tissue. The time for an acoustic pulse to travel from one transducer to another may therefore be converted to the distance between the transducers by multiplying the time of flight by the velocity of an acoustic pulse in the heart (i.e. by 1570-1580 mm/msec). As detailed below, the system of the present invention uses this "time of flight" principal in combination with the geometric principal of triangulation to establish a three-dimensional coordinate system using the reference transducers on the reference catheter 10, and to then use the additional catheter transducers to track the location of an additional catheter 12, 14, 16, relative to the coordinate system.

During use of the system of the invention, one or more of the reference catheters 10 is introduced into the heart or the surrounding vasculature (or even into other areas such as the esophagus) and is left in place for the duration of the procedure. Once reference catheter(s) 10 are positioned within or near a patient's heart, the system first measures the distances between each of the reference catheter transducers using the "time of flight" principal. It then uses these distances to establish the relative positions of the reference transducers and therefore to establish a three-dimensional coordinate system.

Referring to FIG. 2, establishing the coordinate system requires placement of the reference catheter(s) 10 such that

at least four reference transducers, designated T_{REF1} through T_{REF4} in FIG. 2, are available to define a 3-dimensional coordinate system as follows: T_{REF1} through T_{REF3} , define the plane P at $z=0$; one reference transducer T_{REF1} defines the origin of the coordinate system; a line between T_{REF1} and T_{REF2} defines the x-axis of the system; and T_{REF3} lies in the plane $z=0$. The fourth reference transducer, T_{REF4} , lies on one side of the plane P, at $z>0$. Given these constraints, the coordinates of the reference transducers can be computed using the law of cosines. See, for example, Advanced Mathematics, A preparation for calculus, 2nd Ed., Coxford, A. F., Payne J. N., Harcourt Brace Jovanovich, New York, 1978, p. 160.

Each of the reference transducers T_{REF1} through T_{REF4} must be capable of both receiving and transmitting ultrasound pulses. As discussed, each reference transducer is separately made to emit acoustic pulses that are received by each of the other reference transducers so that the distances $d1$ through $d6$ shown in FIG. 2 are calculated using the respective times it takes for an acoustic pulse to travel between each pair of the reference transducers. These distances are triangulated to establish the positions of the reference transducers relative to each other, and therefore to establish a three-dimensional coordinate system.

Once a 3-dimensional coordinate system is established in the manner described, the three-dimensional location of an additional catheter transducer placed near or within the heart (such as a transducer on a mapping or ablation catheter 12, 14, or 16) can be calculated as follows. First, using the "time of flight" method, the distances between each of the reference transducers T_{REF1} through T_{REF4} and the additional catheter transducer (designated T_{CATH} in FIG. 2) are established, in parallel. In practice, these distances are preferably also performed in parallel with the distance measurements that are made to establish the coordinate system. Next, using basic algebra and the law of cosines (see, e.g., the Advanced Mathematics text cited above), the coordinates of T_{CATH} relative to the reference transducers are calculated using the measured distances from T_{REF1} through T_{REF4} to T_{CATH} . This process is referred to as triangulation.

The locations of all or portions of the reference catheters may be displayed as well. The system is preferably programmed to extrapolate catheter position from the coordinates of the transducer locations based on models of the various catheters pre-programmed into the system, and to display each catheter's position and orientation on a graphical user display (see display 124 in FIG. 1). The locations of all or portions of the additional catheters (such as, for example, their distal tips, their electrodes or ablation sections, if any, or other sections which may be of interest) are displayed.

The reference catheter(s) 10 thereby establish an internal coordinate system by which the relative positions of EP catheter transducers in the heart may be calculated using triangulation and shown in real-time on a three dimensional display.

Ultrasound Catheters

Catheters of the type which may be used with the system according to the present invention are shown in FIGS. 3, 9, 13 and 18. These include a reference catheter 10 (FIG. 2), a marking and ablation catheter 12 (FIG. 9), a basket-type mapping catheter 14 (FIG. 13), and a linear lesion ablation catheter 16 (FIG. 18).

Reference Catheters

Referring to FIG. 3, a reference catheter 10 according to the present invention is an elongate catheter having a

plurality of ultrasound transducers **18** positioned at its distal end. The transducers **18** are piezoelectric transducers capable of transmitting and receiving ultrasound signals.

The reference catheters can be integrated with typical EP catheters by providing the ultrasound transducers described above. This allows the system to utilize the localization function using catheters which are already needed for the EP procedure. Thus, use of the system does not require the physician to use more catheters than would be used had the EP procedure been carried out without the localization function.

For example, referring to FIG. 4, the reference catheter **10a** may be an RV apex catheter having a distal pair of EP electrodes **30**, an ultrasound transducer **18a** at the distal tip, and additional ultrasound transducers **18** proximally of the distal tip. It may also be a coronary sinus reference catheter **10b** (FIG. 5) having at least three bipole pairs of EP electrodes **30** distributed over the section of the catheter that is positioned in the coronary sinus, and having at least three ultrasound transducers also distributed over the section of the catheter that is in the coronary sinus.

Referring to FIG. 6, a preferred transducer **18** is a piezoelectric cylindrical tube having inner and outer surfaces. The cylindrical transducer may be made of PZT-5H, PZT-5A, PMN (lead metaniobate or lead magnesium niobate) or other piezoelectric ceramic materials.

Electrodes **20** are positioned on the inner and outer surfaces of the transducer. The electrodes are metal surfaces not limited to materials such as sputtered chrome and gold, electroless nickel, or fired silver. The piezoelectric ceramic is polarized in the thickness mode, i.e., between the two electrodes **20**.

The cylinder includes an outside diameter (designated "OD" in FIG. 6) of approximately 0.040 to 0.250 inches, and preferably approximately 0.060 to 0.090 inches. The cylinder has a length L of approximately 0.020 to 0.125 inches and preferably approximately 0.030 to 0.060 inches. Wall thickness W is approximately 0.004 to 0.030 inches and preferably approximately 0.006 inches to 0.015 inches. The transducers **18** are spaced from one another along the catheter **20** (FIG. 3) by a distance of approximately 0.5–10 cm, and most preferably 1–3 cm.

Preferably, the localization system is operated using the same operating frequencies for all transducers. The optimal operating frequency for the system is determined by considering the resonant frequencies of the ultrasound transducers used for the catheters in the system. It has been found that, given the dimensions and thus the resonances of the preferred transducers being used in the system, the transducers are most preferably operated at a frequency of approximately 1.0–3.0 MHz, which in the case of the transducer **18** is the transducer resonance in the length mode. Transducer **18** further has a beam width of approximately 114°, where the beam width is defined as the angle over which the signal amplitude does not drop below 6 dB from the peak amplitude. If desired, a diverging lens **22** (FIG. 7), in the form of a spherical bead of epoxy or other material may be formed over the ceramic cylinder to make the signal strength more uniform over the beam width.

Referring to FIG. 8, the reference catheter transducers **18b** may alternatively be formed of piezoelectric polymer films of copolymers such as PVDF. Such films would have thicknesses of approximately 0.005–1.0 mm, and preferably approximately 0.007–0.100 mm, and would preferably include gold film electrodes on the inner and outer surfaces. As shown in FIG. 8, the polymer film would be wrapped around a mandrel **24** (which may be part of the catheter shaft

10c itself or a separate polymer plug inside the catheter **10**). A transducer configuration of this type operates with a very large band width and does not have a specific resonance due to the polymer piezoelectric.

Electrode leads (not shown) are attached to the inner and outer transducer electrodes (such as electrodes **20** of FIG. 6). If piezoelectric ceramics are used as in FIGS. 6 and 7, leads may be attached using low temperature solders which typically contain large proportions of indium metal. Leads may alternatively be attached with silver epoxy. It is important that the leads be attached using a minimum amount of material to minimize distortion of the acoustic field. In the case of the polymer transducers of FIG. 8, photo lithographic techniques are typically used to create electrodes and their associated lead tabs. In this manner, the one side electroded polymer at the tab site does not contribute to the acoustic field. Leads are typically attached to these tabs with either low temperature indium based solders or with silver epoxy. Therefore, for these polymer transducers, the amount of material on the connection tab does not affect the acoustic field.

The reference catheter preferably includes at least four such transducers so that a three-dimensional coordinate system can be established using a single catheter. If desired, the reference catheter may have more transducers or it may have fewer transducers if more than one reference catheter is to be used to establish the three-dimensional coordinate system. Using more than four reference transducers is advantageous in that it adds redundancy to the system and thus enhances the accuracy of the system. When more than four reference transducers are used, the problem of determining the location of catheter transducers is over determined. The additional redundancy may provide greater accuracy if the measured distances between the reference transducers and catheter transducers are noisy. The over-determined problem can be solved using multi-dimensional scaling as described in "Use of Sonomicrometry and Multidimensional Scaling to Determine 3D Coordinates of Multiple Cardiac Locations: feasibility and implementation", Ratcliffe et. al, IEEE Transactions Biomedical Engineering, Vol. 42, no. 6, June 1995.

Referring again to FIG. 3, a connector **32** enables the catheter to be electrically coupled to the ultrasound ranging hardware **116** (described below and shown in FIG. 1).

Four twisted pairs **26** of Teflon coated forty-two gauge copper wire (one pair can be seen in the cutout section shown in FIG. 3) extend from connector **32** through the catheter **10**. Each twisted pair **26** is electrically coupled to a corresponding one of the ultrasound transducers **18**, with one wire from each pair **26** coupled to one of the transducer electrodes **20** (FIG. 6). When a transducer is to act as an ultrasound transmitter, a high voltage pulse (i.e., approximately 10–200V) is applied across the corresponding twisted pair **21** and causes the transducer **18** to generate an ultrasound pulse. When a transducer is to act as an ultrasound receiver, the ultrasound ranging hardware **116** (FIGS. 27A–27B, described below) awaits receive pulses of approximately 0.01–100 mV across the twisted pairs corresponding to receiving transducers. Additional leads (not shown) couple the EP electrodes **30** to the EP hardware **114** (FIG. 1).

To facilitate manipulation of the reference catheter through a patient's vessels and into the heart, the reference catheter **10** may have a pre-shaped (e.g. curved) distal end. Marking/Ablation Catheter

Referring to FIG. 9, the system of the present invention preferably utilizes a catheter **12** to identify the locations of

anatomical landmarks (such as the septal wall) relative to the coordinate system so that the landmarks may be included on the three-dimensional display. Showing anatomical landmarks on the display correlates the three-dimensional coordinate system to discrete anatomical locations and thereby assists the physician in navigating EP catheters to the desired locations within the heart.

The marking catheter **12** is preferably a 7 French steerable catheter having one or more ultrasound transducer(s) **34** mounted at or near its distal tip. Preferably, the catheter **12** includes one transducer at or near its distal tip and a second transducer spaced from the distal tip by approximately 0.5–4.0 cm. The marking catheter **12** need not be one which is limited to use in marking anatomical sites. It can be a catheter useful for other purposes as well; the term “marking catheter” is being used in this description as a matter of convenience. Catheter **12** may also include an ablation electrode **36** at its distal tip, so that it may also be used to ablate tissue while the position of the ablation electrode **36** is tracked using the localization system **100**. It may also include other electrophysiology electrodes **38** which may be used for pacing and/or mapping as desired by the user.

The transducers **34** may be similar to the reference catheter transducers **18**. While the outer diameter and wall thickness of the transducers **34** may differ from that of transducer **18** to accommodate mounting requirements, the length of the transducers **34** is preferably the same as that of the transducers **18** to assure a common operating frequency of approximately 1.0–3.0 MHz.

Alternatively, the more distal transducer might be packaged differently than the reference catheter transducers. For example, referring to FIG. **10**, the transducer **34** may be mounted just proximal of the distal ablation tip **36**. Alternatively, a cylindrical transducer **34a** or a plate transducer **34b** may be positioned inside the distal ablation tip, in FIGS. **11** and **12**, respectively. An internal piezoelectric transducer would be embedded in a bead of epoxy **40** positioned in the catheter tip. This bead would preferably have a spherical contour across the distal end so that it would act as a divergent lens for the ultrasound energy. The metal forming the ablation tip **36** must be very thin (i.e., less than a small fraction of a wavelength) to facilitate the transmission of acoustic energy to and from an internal transducer.

The marking catheter **12** may additionally be provided with EP electrodes **38**. As shown in FIG. **9**, a handle **42** and a knob **44** for actuating a pull wire (not shown) allow the marking catheter **12** to be maneuvered through a patient's vessels and heart using conventional steering mechanisms. A connector **46** enables the catheter **12** to be electrically coupled to the EP hardware **114** and the ultrasound ranging hardware **116** (described below, see FIG. **1**).

Mapping Catheter

FIG. **13** shows a first embodiment of a mapping catheter **14** for use with the system according to the present invention. The catheter **14** is of the type known in the art as a “basket” catheter. It includes an elongate shaft **48** carrying a mapping basket **50** at its distal end. The basket **50** is formed of preferably eight arms **52**. Arms **52** are constructed of ribbons of a shape memory material such as Nitinol. The shape memory material is treated such that the ribbons assume the basket structure shown in FIG. **13** when in an unstressed condition.

The arms **52** may be concentrated at one section of the basket (FIG. **14A**) so that during use mapping may be concentrated in one area of a cardiac chamber. The arms may alternatively be uniformly spaced as shown in FIG. **14B**. Basket catheters of these types are shown and described in

U.S. Pat. No. 5,156,151, the disclosure of which is incorporated herein by reference.

A sheath **54** is disposed around shaft **48**. Sheath **54** is longitudinally slidable between the proximal position in FIG. **13** and a distal position in which the basket **50** is compressed within it. During use the sheath **54** is moved to the distal position to compress the basket before the catheter **14** is inserted into the patient, so that the basket can be easily moved through the patient's vessels and into the patient's heart. Once the basket is within the desired chamber of the patient's heart, the sheath is withdrawn, the basket is opened into its expanded condition, (either by spring action of the arms **52** or by a separate actuator) and the arms to map electrical activity of the chamber wall.

Each arm **52** of the basket catheter **14** carries a plurality of EP mapping electrodes **56** designed to detect the electrical activity of underlying cardiac tissue. A plurality of ultrasound receiving transducers **58** are also mounted to each arm **52**. Preferably, the mapping electrodes **56** and the ultrasound transducers **58** alternate with each other along the length of each arm **52**, although there need not be one-to-one correspondence between the transducers and electrodes.

FIG. **16** is a plan view of one arm **52** of basket catheter **14**, and FIG. **17** is a side section view of the arm of FIG. **16**. As shown, the mapping electrodes **56** and ultrasound transducers **58** are preferably formed on a flex circuit **60** which is attached to the arm **52**. Copper leads **62** are formed on the flex circuit and each lead is electrically connected to one of the EP electrodes **56** and one of the ultrasound transducers **58**, and to the EP and localization hardware **110** (FIG. **1**). Each arm **52**, including its associated flex circuit **60**, is covered in polyethylene shrink tubing **64**, with only the electrodes **56** being exposed through the shrink tubing **64**.

Referring to FIG. **16**, a preferred piezoelectric transducer for the mapping catheter comprises a flat piezoelectric ceramic plate **66**. The plate **66** may be made of PZT-5H, PZT-5A, PMN (lead metaniobate or lead magnesium niobate) or other piezoelectric materials.

The transducer includes a depth D and length L, each of approximately 0.010 to 0.060 inches, and preferably approximately 0.025 to 0.040 inches. The transducer has a wall thickness W of approximately 0.004 to 0.030 inches and preferably approximately 0.006 to 0.015 inches. The length and depth resonances of the transducer fall in the range from 1.0 MHz to 3 MHz and thus contribute to the overall performance of the system. The beam width considerations are the same as those described above for the reference catheter transducers **18** (FIG. **6**).

Electrodes **68a**, **68b** are positioned on the upper and lower flat surfaces of the plate. The electrodes are metal surfaces not limited to materials such as sputtered chrome and gold, electroless nickel, or fired silver. The piezoelectric ceramic is polarized in the thickness mode, i.e., between the two electrodes.

The mapping catheter transducers **58** may alternatively be formed of piezoelectric polymer films of copolymers such as PVDF. Such films would have thicknesses of approximately 0.005–1.0 mm, and preferably approximately 0.007–0.100 mm, and would preferably include gold film electrodes on the inner and outer surfaces. The polymer film would preferably be taped to the printed wiring board of the basket arm, and leads attached to the top electrodes in a manner similar to that mentioned above for the reference catheter transducers. Alternatively, the polymer film could be used to form the entire flex circuit.

Lead wires **70a**, **70b** extend between the copper leads **62** and the electrodes **68a**, **68b**. It is important to note that each

of the leads **62** electrically connects both an ultrasound transducer **58** and an EP electrode **56** to the EP and localization hardware **110**. Each lead **62** therefore carries electrical activity measured by EP electrodes **56** as well as receive signals from the ultrasound transducers **58** to the hardware **110**. It is possible to do this because EP signals have a lower frequency (i.e., on the order of 1 Hz–3 kHz) than the ultrasonic signals, which have frequencies of approximately 500 kHz–30 MHz. Thus, the EP signals can be removed from the recorded signal using low-pass filtering while the ultrasound signal can be removed using high pass filtering.

Combining EP and ultrasound signals on the same lead **62** has the advantage of reducing the total number of conductors in the catheter **14**. While this is advantageous, it is not a requirement for functionality of the system. Naturally, the system may also be provided using separate leads for the EP and ultrasound signals.

For both piezoelectric ceramic and polymer transducers, one lead **70b** will most typically be attached by bonding the bottom electrode **68b** of the piezoelectric (e.g., plate **66**) with silver epoxy to the printed circuit of the basket arm. Leads **70a** may be attached to the top electrodes **68a** in a manner similar to that set forth with respect to the reference catheter transducers. For the piezoelectric ceramics **66**, the top lead **70a** may be attached with low temperature solders which typically contain large proportions of indium metal. It is important that the leads be attached using a minimum amount of material to minimize distortion of the acoustic field. Top leads **70a** may also be attached with silver epoxy. In the case of the polymer piezoelectrics, metallization of the electrodes and leads is typically achieved using photo lithographic techniques. In this manner, the one side electroded polymer at the lead site does not contribute to the acoustic field as discussed previously for the polymer transducer of the reference catheter.

Acoustic wave propagation does not occur across a vacuum or air gap, consequently it is necessary to provide a rubber path or a path through an insulating polymer in order to fill air gaps around the transducers. For example, after the top lead **70a** has been attached, the entire top surface and surrounding areas including the inner surface of the shrink tubing is coated with a rubber primer. Subsequently, the area between and around the top surface of the piezoelectric and the shrink tubing is filled with a silicone rubber material.

Alternatively, the top surface of the piezoelectric and the electrical lead may be coated with an insulating polymer. After the heat shrink tubing is attached to the basket strut, a small area over and around the top electrode of the ceramic may be cut out of the shrink tubing to provide an unobstructed exposure of the transducer to the blood field.

The EP electrodes **56** are preferably platinum black electrodes having a size of approximately 0.009×0.030 inches. For these small electrodes, platinum black is used for low impedance, i.e., approximately less than 5.0 k Ohms over the frequency range (approximately 1 Hz–3 kHz) of interest for EP signals. This is important in that it prevents the impedance of the ultrasound transducers from loading the output of the EP electrodes.

FIG. **15** is a cross-section view of the portion of the catheter **14** which is proximal of the basket **50**. The catheter shaft **48** is formed of an inner shaft **72** and an outer, braided shaft **74** preferably made from stainless steel braid of a type conventionally known in the art. The inclusion of the braid improves the torque characteristics of the shaft **48** and thus makes the shaft **48** easier to maneuver through patient's vessels and heart.

Inner shaft **72** includes a center lumen **76** through which ribbon cables **78** extend. Leads (not shown) are formed on the ribbon cables **78** and function to carry signals corresponding to signals received by the ultrasound transducers **58** and by the electrophysiology electrodes **56** to the system hardware **110** (FIG. **1**). An ablation catheter lumen **80** extends through the shaft **48** and allows an ablation catheter such as catheter **12** to be introduced through the shaft **48** and into contact with tissue surrounding the basket **50**.

Inner shaft **72** further includes a deflection lumen **82**. A pull wire (not shown) extends through the deflection lumen **82** and facilitates steering of the basket using means that are conventional in the art.

Linear Lesion Ablation Catheter

FIGS. **18** through **26** show a linear lesion ablation catheter **16** for use with the system **100** of the present invention. Catheter **16** is an elongate shaft preferably constructed of a thermoplastic polymer, polyamid ether, polyurethane or other material having similar properties. An ablation section **84**, the section of the catheter **16** at which ablation is carried out, is located at the distal end of the shaft.

As shown in FIG. **18**, an elongate window **86** is formed in the wall of the ablation section **84**. The window **86** may be made from heat shrink polyethylene, silicone, or other polymeric material having a plurality of small holes or perforations formed in it. It may alternatively be formed of the same material as the remainder of the shaft and simply include a plurality of holes formed through it.

Referring to FIG. **19**, a foam block **88** is disposed within the catheter, next to the window **86**. The foam block **88** is formed of open cell polyurethane, cotton-like material, open-cell sponge, hydrogels, or other foam-like materials or materials that are permeable by conductive fluids. A plurality of RF ablation electrodes **90** line the edge of the foam block **88** such that the foam block lies between the electrodes **90** and the window **86**.

Ultrasound transducers **92** are positioned at the distal and proximal ends of the foam block **88**. The transducers **92** are preferably formed of piezoelectric ceramic rings having electrodes bonded to their inner and outer surfaces, although the transducers may also be formed in a variety of alternative shapes.

Referring to FIGS. **20–22**, several lumen extend through the catheter **16**. The first is a fluid lumen **94** that extends the length of the catheter **16** and is fluidly coupled to a fluid port **96** (FIG. **18**) at the proximal end of the catheter. It should be noted, with reference to FIG. **20**, that the walls of the fluid lumen are cut away at the ablation section **84** to accommodate placement of the foam block **88** and the RF electrodes **90** within the catheter.

A pair of lead lumen **98** house lead wires **100** that carry RF energy to the electrodes **90** and lead wires **102** that carry voltage signals from the transducers **92**. A fourth lumen **104** houses a Nitinol core wire **106** which provides rigidity to the catheter.

Because breaks in a linear lesion can reduce the success of an ablation procedure by leaving a path through which current may travel during atrial fibrillation episodes, the fluid lumen, foam, and window are provided to improve the coupling of the RF energy to the cardiac tissue to minimize the likelihood of breaks in the lesion.

Specifically, during use, the window **86** of ablation section **84** of the apparatus is positioned adjacent to the body tissue that is to be ablated. RF energy is delivered to the electrodes **90** while saline or other conductive fluid is simultaneously delivered through the fluid lumen **94**. The conductive fluid passes out of the fluid lumen **94** and into the

foam **88**, and contacts the electrodes **90**. The fluid also flows through the window **86** into contact with the body tissue, thereby improving the coupling of the RF energy from the electrodes **90** to the tissue and improving the efficiency of the ablation of the tissue.

Using a conductive liquid dispersed over the desired area as a mechanism for coupling RF energy to the tissue produces lesions having greater continuity (and thus fewer breaks through which current can pass during atrial fibrillation episodes) than lesions formed by apparatuses that rely solely on direct contact between the electrodes and the body tissues, decreasing the likelihood of thrombus formation on the electrodes and thus decreasing the chance of an embolism. The foam and the window improve ablation in that the conductive liquid is uniformly dispersed within the foam and then is focused onto the body tissue as it passes through the holes or pores in the window. This concept, and several alternate ways of configuring linear lesion catheters that may be adapted to include ultrasound transducers and used in the system of the present invention, are described in published International Application PCT/US96/17536, the disclosure of which is incorporated herein by reference.

FIGS. **23** and **24** show a first alternative embodiment of a linear lesion catheter according to the present invention. The first alternative embodiment **16a** differs from the embodiment of FIG. **19** primarily in the shape and placement of the transducers. Transducers **92a** of the first alternative embodiment are piezoelectric chips embedded within the foam block **88**. Each transducer **92a** includes a pair of electrodes on its opposite faces and is encapsulated in an insulating cocoon **108** of epoxy, acrylic, or silicone rubber which prevents the fluid in the foam from creating a short circuit between the electrodes.

A second alternative embodiment of a linear lesion catheter according to the present invention is shown in FIGS. **25** and **26**. The second alternative embodiment also differs from the preferred embodiment only in the form and placement of the transducers. Each transducer **92b** and its leads **102b** is inside an epoxy capsule **109** embedded in the foam block **88**. It should be noted, then, that only the RF electrode leads **100** extend through the lumen **98**. The leads **102b** of the second alternative embodiment extend through fluid lumen **94** as shown.

System Components

Referring to FIG. **1**, the system **100** generally includes amplification and localization hardware **110**, catheters **10**, **12**, **14** and **16**, and a microprocessor workstation **112**.

Hardware **110** includes conventional signal amplifiers **114** of the type used for electrophysiology procedures (for example, the Model 8100/8300 Arrhythmia Mapping System available from Cardiac Pathways Corporation, Sunnyvale, Calif.). It also includes ultrasound ranging hardware **116** and an ultrasound hardware control and timing component **118** which together initiate, detect, and measure the time of flight of ultrasound pulses emitted and received from the ultrasound transducers on the reference and EP catheters **10-16**.

Signal amplifiers **114** and the ranging hardware **116** and controller **118** are electronically coupled to a microprocessor workstation **112**. The microprocessor work station **112** is designed to control the system hardware and the data processing for both the EP and ultrasound functions of the system, and to generate a visual display of EP and catheter position data for use by the clinician.

For EP functions, the microprocessor **112** includes an amplifier controller **120** that delivers mapping, and/or pacing commands to the EP signal amplifiers **114**. Signal

processors **122** receive data corresponding to electrical activity measured by the mapping catheters **14**, **16** and generate graphical representations of the measured data for display on graphical interface display **124**. The mapping signals shown on the graphical display can represent any number of parameters or characteristics, such as measured signal values or impedance values, indicators of electrode contact, or indicators of the probability that there is an arrhythmic site in the area, etc.

Ultrasound hardware controller **118** and a triangulation processor **126** control the catheter localization functions and data processing. During use, controller **118** directs the ultrasound ranging hardware **116** to initiate an ultrasound pulse from a selected transmitting transducer. It further directs the hardware **116** to (1) detect, in parallel, voltages corresponding to reception of the ultrasound pulse by the receiving transducers, and (2) measure the elapsed time (time of flight) between transmission of the ultrasound pulse and its detection by the selected receiving transducers. Triangulation processor **126** receives data corresponding to these time of flight measurements from the ranging hardware **116** and uses it to calculate the locations of the EP catheter transducers relative to the reference transducers (see Localization System Overview). Data corresponding to catheter position, as calculated from transducer locations, and measured EP signals is shown in graphical form on graphical user interface display **124**.

The ultrasound ranging hardware **116** may be configured to detect an acoustic pulse received by a receiving transducer in a number of ways. For example, if the transmitting transducer is made to generate a short burst of high frequency ultrasound energy, the hardware **116** may be configured to detect the first signal excursion above or below a predetermined maximum and minimum voltage threshold, or the peak of a received signal. Alternatively, the transducer may be made to generate a continuous wave of low frequency ultrasound, in which case the hardware **116** would be configured to measure the difference in phase between the standing wave as generated by the transmitting transducer and as detected by the receiving transducer.

Referring to FIG. **27A**, the ultrasound ranging hardware **116** includes a plurality of channels **128a**, **128b**, each of which is electronically coupled to one of the ultrasound transducers in the system. Depending on whether a transducer is intended to transmit and receive ultrasound signals (as in the case of a reference catheter transducer **18**) or to receive ultrasound signals only (as in the case of an additional catheter transducer **34**, **58** or **92**), a transducer's corresponding channel circuitry may be configured to permit transmission and receipt of ultrasound signals by the transducer, or it may be configured only to allow receipt of signals by the transducer. Accordingly, transmit/receive channels **128a** are each connected to a corresponding one of the reference catheter transducers **18** (FIG. **3**), and receive channels **128b** are each connected to a catheter transducer **34**, **58**, **92** (e.g., FIGS. **9**, **13** and **19**).

Referring to FIG. **27B**, the circuitry of each of the channels **128a**, **128b** generates digital data corresponding to the time of flight of an ultrasound transmit pulse from a transmitting transducer to the transducers corresponding to each of the channels **128a**, **128b**. Each channel **128a**, **128b** includes an amplifier **130** which amplifies voltage signals generated by the ultrasound transducers in response to receive pulses. The transmit/receive channels **128a** additionally include transmitters **132** which, in response to signals from transmit and receive controller **142** (discussed below), apply voltages across the reference transducers **18** to trigger ultrasound pulses.

Each channel **128a**, **128b** further includes a threshold detector **134** which triggers a latch **136** once a received signal exceeds a threshold level. Latch **136** is coupled to distance register **138** which is in turn coupled to place distance output data onto data bus **140** upon activation of the latch **136**.

Ultrasound hardware control and timing component **118** includes transmit and receive controller **142**. Controller **142** is electronically coupled to a system clock **141** that drives a distance counter **144**, and to a threshold amplitude generator **146** which provides the threshold reference input for threshold detectors **134**.

As will be discussed in greater detail, count values from the distance counter **144** are used by the system of the invention to calculate the distances between transmitting transducers and receiving transducers. Because system clock **141** drives the distance counter **144**, it is the frequency of the system clock that determines the resolution of measured distances between transducers. The higher the frequency of the clock, the greater the resolution of the distance measured. Clock **141** is therefore a high frequency counter which preferably operates at least approximately 5–50 MHz, which is equivalent to a resolution of approximately 0.3–0.03 mm.

The threshold amplitude generator **146** produces time varying positive and negative thresholds that are used as inputs to the threshold detectors **134** of each channel **128a**, **128b**. Preferably, one threshold amplitude generator **146** is used for the entire system in order to minimize the amount of hardware in the system. However, the system may alternatively use a separate threshold amplitude generator for each channel, or separate threshold amplitude generators for different groups of channels. For example, different threshold amplitude generators may be used for different types of receiving transducers, since some produce weaker signals and therefore require lower thresholds. As another alternative, a fixed threshold may be used together with a variable gain amplifier in place of amplifier **130**.

The threshold amplitudes are preferably varied by the threshold amplitude generator **146** so that they are large at the time a transmit pulse is initiated and so that they decrease as time passes following transmission of a pulse. Using a variable threshold rather than a fixed one is beneficial because the dynamic range (i.e., the ratio of the largest signal to be detected to the smallest signal to be detected) is quite large, and may even be as high as 70 dB due to factors such as anisotropy of the transmit and receive beam profiles, signal decay due to ultrasound wave propagation, and attenuation of the signal caused by blood and tissue. Because transducer receiving wires for a catheter based system must be closely spaced, a fixed dynamic range of this magnitude could lead to erroneous data, because cross-talk between the closely spaced receiving wires could be interpreted by the system to be actual receive signals.

It should be noted that both positive and negative thresholds are used so as to increase the accuracy of the detection time, since a negative oscillation of a transmit pulse may reach the detection threshold before a positive oscillation. Latch **136** will therefore be triggered by whichever of the positive or negative thresholds is achieved first.

When a transmit pulse **T** (FIG. **28A**) is being sent to a transducer, oscillation, or “ringing”, designated “**R_T**”, can occur on the corresponding twisted pair **26** (FIG. **3**). The ringing in the transmit line is not problematic in and of itself. However, in catheters such as the reference catheter **10** which includes transducers which can both transmit and receive ultrasound signals, the close proximity of the transmitting and receiving lines can cause the ringing to cross over to the receiving line. This problem arises most frequently when the system is computing the relative orientations of the reference transducers **18** (FIG. **3**) in order to

establish the three-dimensional coordinate system, since that procedure requires measuring the time it takes for a pulse emitted by one of the reference transducers **18** to be received by the other reference transducers **18** on the same catheter. The ringing (which is designated “**R_R**” in FIGS. **28B** and **28C**) can be of similar magnitude to a receive signal “**S**” and can therefore make it difficult to determine whether a receive signal has been detected.

If the transmitting and receiving transducers are far apart, a receive signal on a receiving line (such as twisted pair **26**) will be measured by the ultrasound system circuitry despite the ringing, because transmission of the receive signal on the receiving line will happen only after the ringing has diminished. See FIG. **28B**. However, if the transmitting and receiving transducers are close together (i.e., separated by less than approximately 2 cm), the receive pulse will be lost in the ringing on the receive line, because the receive pulse will reach the receiving line while the ringing is still occurring. See FIG. **28C**.

It has been found that this problem may be avoided by including circuitry which will short the conductors of the transmit line immediately after the transmit pulse is sent. An example of such circuitry is shown in FIG. **29**. The circuit includes the pulse generator **148** and center tapped transformer **150** which comprise basic pulse generating circuitry, plus a switch **152** which is closed immediately after a transmit pulse in order to short the ringing to ground. A small impedance **154** is placed in series with the switch in order to dampen the ringing through the short circuit. As illustrated in FIGS. **28D** and **28E**, by eliminating the ringing from the transmitting line, the switch eliminates the ringing from the receiving line as well.

Referring again to FIG. **27B**, during use of the system, each transmit/receive channel **128a** is sequentially selected for transmission of a transmit pulse, and all channels **128a**, **128b** are simultaneously selected for parallel reception of distance data. Transmit and receive controller **142** selects which of the transmit/receive channel **128a** will initiate an ultrasound pulse, and cycles through each transmit/receive channel, causing sequential transmission of pulses by the reference transducers **18** (FIG. **3**). It uses the system clock **141** to generate a lower frequency transmit clock, which in turn controls how often ultrasound pulses are transmitted.

Each time a transmit pulse is to be initiated, the transmit and receive controller **142** performs the following sequence of steps. The distance counter **144** is first reset to zero, and the threshold amplitude generator **146** is reset. A detection hold off and reset signal is next sent by controller **142** to all channels **128a**, **128b**. This resets the latch **136** for each channel and prevents it from latching for a specified time period to prevent detection due to electromagnetic coupling of ringing after transmission of a transmit pulse. This “hold off” period is determined by the smallest distance within the patient that is to be measured, and is calculated according to the following equation:

$$\text{hold off period} = \text{smallest distance} * 1 / (\text{velocity of transmit signal}).$$

Thus, if the smallest distance to be measured is 10 mm, the “hold off period” is:

$$10 \text{ mm} * \frac{1}{1.5 \frac{\text{mm}}{\mu\text{sec}}} = 6.66 \mu\text{sec}$$

After the hold off and reset signals, a transmit control signal is sent to a selected one of the transmit/receive channels **128a**, causing it to initiate a transmit pulse. Shortly afterwards, a signal is sent to the same transmitter to initiate damping in order to prevent/reduce ringing as described above.

When a transmit pulse is initiated, the distance counter **144** is simultaneously activated. After a transmit pulse is triggered, each channel **128a**, **128b** "listens for" a receive pulse. When the threshold detector **134** for a particular channel detects a receive pulse that exceeds the threshold set by the threshold amplitude generator **146**, the latch **136** for that channel is activated. Once the latch **136** is activated, a load data command is sent to the associated distance register **138** and the current contents of the distance counter **144** are loaded into the distance register **138** for that channel. This data is subsequently placed on the distance data bus **140** along with data indicating which channel transmitted the pulse. Thus, the data bus receives a number of distance values which correspond to the number of transmit/receive and receive only channels. These distance values are then used by the triangulation processor **126** (FIG. 1) to determine the relative positions of the ultrasound transducers, and the microprocessor **112** uses the position data to create a three-dimensional display of the catheters.

Graphical Display Features

As described, the three-dimensional positions of the integrated ultrasound transducers (such as those on catheters **10**, **12**, **14** and **16**) may be continuously displayed in real-time on the graphical user interface display **124** (FIG. 1). The three-dimensional positions of the catheters (**10**, **12**, **14** and **16**), or portions thereof, may also or alternatively be continuously displayed based on the position of the transducers by extrapolating the catheter position using a known model of the catheter programmed into the system. The three-dimensional positions of the transducers and/or catheters may also be stored in the system's memory and selectively displayed on the graphical display user interface display **124** as required during a procedure.

For example, data corresponding to electrode locations on a mapping basket **14** may be saved in the system memory, together with data representing EP measurements taken by EP electrodes corresponding to the transducer locations. If, after the mapping basket **14** has been removed from the patient, the user wishes to guide an ablation catheter to a location corresponding to one of the basket electrodes, s/he may elect to display the saved location information for the basket simultaneously with the real time position of the ablation catheter.

The graphical user interface is further provided with several additional functions that improve the accuracy and usefulness of the system.

For example, the microprocessor **112** includes software which enhances the accuracy of the system by "gating out" the effects of cardiac motion on the position data calculated for the transducers and/or catheters. Because a beating heart contracts and expands with each beat, the catheter will move with the heart throughout the cardiac cycle even when a catheter is at a mechanically stable location within the heart. Thus, a real time display of the catheter (or transducer) position would show the catheter or transducer moving on the display because of the cardiac movement.

Such movement of the catheter/transducer on the display does not present problems in and of itself. However, if the user elects to save in the system memory the position of the catheter so that it may be used later during the procedure (such as to indicate anatomical landmarks, ablation locations, mapping locations, etc.), the effects of the movement on the saved locations can lead to inaccuracies if the user attempts to navigate a catheter (shown in real time on the display) with respect to the representation on the graphical display of the previous catheter position data.

To eliminate this problem, the patient's electrocardiogram (EKG) is monitored during use of the system, and the EKG

is used to synchronize the acquisition of position data so that all position data is acquired at the same point in the cardiac cycle. Thus, for example, when EP signals are recorded from catheters having integrated localization transducers, the relative position/location information for the EP electrodes is accurate when displayed because all of the location information will have been collected during the same phase of the cardiac cycle. Gating is similarly carried out for the ablation and marking catheters, by collecting the appropriate position/location data for such catheters and the anatomical landmarks during the same phase of the cardiac cycle.

FIG. 30B shows an EKG signal along with corresponding electrode position data recorded over the cardiac cycle. It has been found that the end of diastole, at the Q-R wave of the EKG signal, is a convenient point for gating the position measurements. FIG. 30A schematically shows a gating system in which a patient's EKG signal is passed through an amplifier **302** and a detector **304** which initiates a sample and hold sequence **306** of position data when the initiation of a Q-R wave is detected.

The user preferably has the option of showing the gated position, or the actual (moving) position, or both on the real time display. The actual position of a catheter may be useful for assessing whether a catheter is in firm contact with the wall of the heart, because if the catheter is spaced away from the wall it will not move with the wall. A display of actual position may also be helpful during steering of a catheter because it provides more rapid feedback of a catheter's position and orientation.

It should be emphasized, however, that gated position information is essential during navigation of a catheter to a location which has been saved in the three-dimensional display, because unless the catheter position and the stored location are gated to the same point in the cardiac cycle, the user cannot be certain that the catheter has been navigated to the proper location.

Similarly, if EP signals are to be displayed in the form of an isochronal map on the three-dimensional display, the position used in the isochronal map to display an activation time for that location should be an EKG gated location.

Similar gating may also be provided to eliminate inaccuracies in location information due to the rising and falling of the chest during respiration. For respiratory gating, chest movement would be monitored using a bellows or other device and the sample and hold sequence would be triggered at a desired portion of the respiratory cycle.

Referring to FIG. 31, the gated positions of lesions and anatomical landmarks may be stored in the system software and added and deleted from the display as needed by the user by manipulating a cursor using a mouse or other user input device to the appropriate item in marker box **156**.

The microprocessor **112** is preferably further provided with software which allows the physician to manipulate the display in many ways so that the maximum benefit may be obtained from the system. For example, referring again to FIG. 31, the user can rotate the display in three-dimensions by guiding the cursor to the appropriate icon in manipulation box **158**. The user may likewise "zoom" towards or away from the image in the same manner. S/he may also elect which of the catheters **10**, **10a**, **12**, **16** to display in real time using real time box **156**.

The system further allows the user to select one of the standard orientations used in fluoroscopy such as anterior-posterior ("AP"), lateral, right anterior oblique ("RAO") or left anterior oblique ("LAO") by selecting the appropriate icon in orientation box **160**. In the RAO view, the plane formed by the aortic-valve ring ("AV ring") is approximately

perpendicular to the plane of the display, with the end of the coronary sinus pointing to approximately the 2–3 o'clock position on the AV ring. In the LAO view, the apex of the heart is oriented such that it "points" towards a user viewing the display.

When the system of the invention is used is a preferred mode, the transducers of a reference catheter positioned in the coronary sinus ("CS reference catheter") define the AV ring, and the distal tip of a second reference catheter is positioned in the RV apex ("RV apex catheter"). The system can orient the display to an RAO orientation by deriving the location of the AV ring from the location of the transducers on the CS reference catheter, and re-orienting the display until the AV ring is perpendicular to the display and until the distal tip of the CS reference catheter points towards the 2 o'clock position.

With the AV ring perpendicular to the display, the system may also display straight anterior, posterior, left lateral, and right lateral views by orienting the CS catheter distal tip at the 12 o'clock, 6 o'clock, 3 o'clock, and 9 o'clock positions, respectively.

Similarly, the system can orient the display to an LAO orientation by deriving the location of the RV apex from the locations of the transducers on the RV apex catheter, and by orienting the display so that the RV apex points out of the display.

Operation

Two examples of procedures which may be carried out using the system of the present invention will next be described. It should be appreciated, however, that the system **100** may be utilized in any procedure in which three-dimensional navigation of devices relative to one another is required.

FIG. **33** is a flow diagram giving a sample methodology for using the system according to the present invention for diagnosis and treatment of ventricular tachycardia. The steps shown in the flow diagram will be discussed with reference to the illustrations of the heart shown in FIGS. **34A** through **34D**.

First, step **200**, a reference catheter **10** is introduced into the inferior vena cava and is passed under fluoroscopy into the right ventricle (designated RV). The catheter is positioned with its distal tip at the apex (A). A second reference catheter **10a** is introduced via the superior vena cava into the coronary sinus (a vein, shown and designated CS in FIG. **34B**, that extends around the edge of the AV ring separating the left atrium and the left ventricle). The reference catheters may be positioned elsewhere without departing from the scope of the present invention. However, the RV and CS are suitable locations because they allow the catheters to remain mechanically stable within the heart. Moreover, these reference catheters will include the EP electrodes equivalent to those already used on CS and RV apex catheters, i.e. they will replace conventional CS and RV apex catheters. Placement of the reference catheters using these approaches therefore does not require introduction of additional introducer sheaths or catheters into the patient.

Throughout the procedure, the system calculates the relative positions of the ultrasound reference transducers **18** (FIG. **3**) using time-of-flight measurements and triangulation, establishes the three-dimensional coordinate system, and displays at least a portion of the reference catheter on the graphical interface **124**.

Next, referring again to FIG. **34A**, marking catheter **12** is preferably (but optionally) introduced into the left ventricle. Catheter **12** is guided under fluoroscopy to sequentially position its distal tip against various anatomical landmarks,

such as the apex, septal wall, lateral wall, etc. The location of each transducer **34** (FIG. **9**) relative to the reference catheters is calculated again using time-of-flight measurements and triangulation. The location of the catheter distal tip and thus the location of the anatomical site is extrapolated from the transducer location using a model of the catheter **12** pre-programmed into the system, and it may be subsequently displayed on the graphical display. Once the desired landmarks are identified and displayed, the marking catheter **12** is removed from the heart. Steps **202–208**.

Referring to FIG. **34C**, basket catheter **14** (FIG. **13**) is next introduced under fluoroscopy into the left ventricle (LV), at a location at which the clinician suspects there may be arrhythmogenic tissue. Step **210**. Because the basket arms **52** include ultrasound transducers **58** as well as mapping electrodes **56**, the locations of the mapping electrodes can be determined relative to the reference catheters and displayed on the graphical display based on a model of the basket **50** programmed into the system. Step **212**.

Electrical activity within the heart is recorded from the mapping electrodes **56** and mapping data derived from the recorded activity is displayed on the graphical display. The EP signal display may be displayed separately from the three-dimensional display, such as in the signal display window **162** shown in FIG. **32**. Each graph in the signal display window **162** represents the voltage data over time, as measured by one of the EP electrodes **56** on the basket catheter **14**.

The EP signals may alternatively be displayed in the form of an isochronal map on the three-dimensional display. A display of this type would be generated by first placing an activation time on each signal, where an activation time is the time at which the tissue under a mapping electrode **56** activates. The activation times can be either placed automatically using an algorithm or manually by the user. The map is generated by showing a color on the three-dimensional display that represents an activation time at a location corresponding to the location of the electrodes that measured the signal. It may be in the form of discrete color dots or an interpolated color surface or sheet which passes through the locations of the EP electrodes.

The EP display may alternatively take the form of an isopotential display on the three-dimensional display. An isopotential map is similar to an isochronal map except that it is a time varying color display that is proportional to signal amplitude rather than a static display of activation time.

Other mapping data derived from the EP signals may also be shown on the display. For example, data indicating the adequacy of contact between the electrodes and the tissue, or indicating the probability that there is an arrhythmogenic site at the mapped location may be represented on the display. The physician may induce electrical activity for subsequent measurement by pacing the heart from the basket electrodes **56**. Step **214**.

If an arrhythmogenic region is identified by the clinician on the visual display, a marking and ablation catheter **12** (FIG. **9**) is inserted into the center lumen **80** of mapping catheter **14** (FIG. **15**) and is guided into the left ventricle. The three-dimensional position of the ablation electrode **36** is displayed (using ultrasound receiving transducer **18** to track its position) in real time to aid the physician in guiding the electrode **36** to the arrhythmogenic region of the endocardium. FIG. **34D** and step **216**. Once the ablation electrode is positioned at the arrhythmogenic region, ablation is carried out by supplying RF energy to the electrode **36**.

The clinician next attempts to induce ventricular tachycardia by pacing the site from the basket catheter electrodes

56 or from electrodes on another catheter. Step 220. If VT cannot be induced, the procedure is considered successful and the catheters 10, 14 are removed. Step 222. If VT is induced, additional mapping and ablation steps are formed until the VT appears to be eradicated.

It should be noted that if mapping is carried out using a basket catheter that is not provided with a center lumen 39, the basket catheter may be removed after its electrode positions and corresponding mapping signals (which may include a visual identification of the arrhythmogenic region) are saved in the system memory, and a separate ablation catheter may be introduced into the heart and guided to the arrhythmogenic region identified on a visual display of the gated positions of the mapping electrodes.

FIG. 35 is a flow diagram illustrating use of the system according to the present invention with a linear lesion catheter of the type shown in FIGS. 18–26 to treat atrial fibrillation. The steps shown in the flow diagram will be discussed with reference to the illustrations of the heart shown in FIGS. 36A–36C and the examples of the graphical user interface shown in FIGS. 31 and 32.

First, reference catheters 10, 10a are placed in the coronary sinus and RV apex as illustrated in FIGS. 34A and 34B. The reference catheters 10, 10a are preferably represented on the graphical display as shown in FIG. 31. Step 300. Although only the reference transducer positions are precisely known, the catheter locations can be estimated using the transducer positions, the known spacing of the transducers along the catheter bodies, and a known model of the catheter.

Next, referring to FIG. 36A, marking catheter 12 (FIG. 9) is positioned in the left atrium, preferably by inserting it through a transeptal sheath passed from the right atrium, through the septum and into the left atrium. Steps 302–304. Marking catheter 12 is sequentially positioned with its distal tip at anatomical landmarks, such as the pulmonary veins, septal wall, mitral valve, etc.

The location of each ultrasound transducer 34 on the marking catheter 12 relative to the 3-D coordinate system is calculated using time-of-flight measurements and triangulation. The position of the distal tip is extrapolated from the transducer using a model of the catheter pre-programmed into the system, and is subsequently displayed on the graphical display when the distal tip is positioned at a desired anatomical site (as verified using fluoroscopy), the user adds an appropriate indicator to the display at the distal tip location by entering the necessary input at marker box 156 (FIG. 31). For example, see FIG. 31 in which the left superior pulmonary vein and left inferior pulmonary vein are identified as “LS” and “LI”. After the appropriate landmarks are added to the 3-D display, the marking catheter 12 is removed from the heart.

Next, using a mouse or other user input device, lines representing target locations for linear lesions are added to the display. Step 312. These lines are identified by the dashed lines on FIG. 31. The linear lesion catheter 16 (FIG. 8) is next inserted into the left atrium, preferably via the transeptal sheath 87 shown in FIG. 36A. During placement of the linear lesion catheter, the position of ablation window 86 (FIG. 19) is tracked in real time by tracking the positions of the transducers 92 using the localization system 100 and by deriving the window location from the transducer location. An arrow A1 or other icon representing the length of the catheter 16 lying between the transducers 92 is shown on the display as shown in FIG. 31.

Referring to FIG. 36B, lesion catheter 16b (shown in FIG. 36B) to have an ablation section slidable on a looped baffle

wire as described in PCT/US96/17536), is guided using the localization system 100 to a first one of the desired ablation locations marked onto the display by the physician. By manipulating the catheter 16 such that the display shows arrow A1 lying over the area marked as a target location, the physician can ensure that the window 86 through which ablation will occur is at the correct location. If a different type of ablation catheter is used, including one which does not involve the use of an electrolytic fluid, the physician may use a similar procedure to align the ablation section (which may be an electrode, an electrode array, or another region of the ablation catheter at which ablation will be carried out) with the target location.

RF energy is supplied to the RF electrodes 90 (FIG. 19) while a conductive fluid is supplied to the fluid port 96 (FIG. 18), to create a linear lesion in the target tissue. Step 318. Arrows A2 or other icons representing the window 86 positions during each ablation are added to the display to indicate the location of a linear lesion. These arrows may be coded by color or other means to indicate characteristics of the lesion, such as the wattage used to create the lesion or the impedance during the ablation. The linear lesion catheter is then repositioned for additional ablation steps until all of the desired ablation locations have been treated.

Next, the linear lesion catheter is removed, and mapping basket 50 is inserted into the left atrium as shown in FIG. 36C. Steps 322, 324. The positions of basket electrodes and arms are determined using the ultrasound localization system and are displayed on the 3-D display in the manner described above. FIG. 32 illustrates the positions of the arms 52 with solid lines and the position of the recording electrodes 56 with stars. Pacing and mapping is carried out using the electrodes 56 in a conventional manner to determine whether the linear lesions have blocked transmission of the electrical currents that traverse the left atrium during an atrial fibrillation episode. The electrical activity measured by the mapping electrodes 56 is shown in the form of an isochronal map over the lesion locations A2 on the three-dimensional display. Steps 328–330. If the linear lesions are found to be successful, the basket catheter is removed and the procedure ended. If additional lesions are necessary, the locating, the ablating, pacing and mapping steps are repeated.

One embodiment of the system of the present invention has been described, and it has been described primarily with respect to EP catheters and cardiovascular procedures. It should be appreciated, however, that the system and its components may be used in a variety of medical and non-medical contexts in which three-dimensional representation of structures and surfaces is needed. Thus, the present invention is not to be limited by the specific embodiments and procedures described herein, but should be defined only in terms of the following claims.

What is claimed is:

1. A medical system, comprising:
 - one or more reference catheters having a plurality of ultrasound reference transducers;
 - a medical device having one or more ultrasound target transducers; and
 - localization processing circuitry coupled to the ultrasound reference and target transducers, the processing circuitry configured for causing the ultrasound reference transducers to transmit and receive ultrasound signals between each other in order to establish a three-dimensional coordinate system, and for causing the plurality of ultrasound reference transducers and the one or more ultrasound target transducers to transmit

and receive ultrasound signals between each other in order to determine a position of the one or more ultrasound target transducers within the three-dimensional coordinate system.

2. The system of claim 1, wherein the processing circuitry is configured for causing the one or more ultrasound target transducers to receive ultrasound signals from the plurality of reference transducers in order to determine the position of the one or more ultrasound target transducers within the three-dimensional coordinate system.

3. The system of claim 1, wherein the processing circuitry is further configured for measuring elapsed time between transmission of ultrasound signals by transmitting transducers and receipt of the signals by receiving transducers, and for calculating distances between the transducers using the measured elapsed times.

4. The system of claim 1, further comprising a graphical display, wherein the processing circuitry is further configured for generating a three-dimensional image of at least a portion of the medical device for display on the graphical display.

5. The system of claim 1, wherein the medical device comprises a catheter.

6. The system of claim 5, wherein the catheter is a mapping catheter.

7. The system of claim 6, wherein the mapping catheter has one or more mapping electrodes, the system further comprising electrophysiology processing circuitry coupled to the one or more mapping electrodes for receiving mapping signals corresponding to electrical activity measured by the one or more mapping electrodes.

8. The system of claim 7, further comprising a graphical display, wherein the localization processing circuitry is further configured for generating a three-dimensional image of at least a portion of the mapping catheter for display on the graphical display, and for generating data representing the received mapping signals for display on the graphical display.

9. The system of claim 5, wherein the catheter is an ablation catheter.

10. The system of claim 9, wherein the ablation catheter comprises one or more ablation electrodes, the system further comprising a radio frequency generator coupled to the one or more ablation electrodes for creating a lesion on tissue.

11. The system of claim 10, further comprising a graphical display, wherein the localization processing circuitry is further configured for generating a three-dimensional image of at least a portion of the ablation catheter for display on the graphical display, and for generating data representing a three-dimensional position of the lesion.

12. The system of claim 5, wherein the medical device is marking catheter.

13. The system of claim 1, wherein the one or more reference catheters comprises the medical device.

14. The system of claim 1, wherein the one or more reference catheters and medical device are separate.

15. The system of claim 1, wherein the one or more reference catheters comprises a plurality of reference catheters.

16. The system of claim 1, wherein the one or more ultrasound tracking transducers comprises a single tracking transducer.

17. The system of claim 1, wherein the one or more ultrasound tracking transducers comprises a plurality of tracking transducers.

18. The system of claim 1, wherein each of the one or more reference catheters comprises a single spline.

19. A method of performing a medical procedure on a body, comprising:

positioning one or more reference catheters within the body, the one or more reference catheters having a plurality of ultrasound reference transducers;

positioning a medical device within the body, the medical device having one or more ultrasound target transducers;

causing the ultrasound reference transducers to transmit and receive ultrasound signals between each other in order to establish a three-dimensional coordinate system; and

causing the plurality of ultrasound reference transducers and the one or more ultrasound target transducers to transmit and receive ultrasound signals between each other in order to determine a position of one or more ultrasound target transducers within the three-dimensional coordinate system.

20. The method of claim 19, wherein the one or more ultrasound target transducers receive ultrasound signals from the plurality of reference transducers in order to determine the position of the one or more ultrasound target transducers within the three-dimensional coordinate system.

21. The method of claim 19, further comprising:

measuring elapsed time between transmission of ultrasound signals by transmitting transducers and receipt of the signals by receiving transducers; and

calculating distances between the transducers using the measured elapsed times.

22. The method of claim 19, further comprising generating a three-dimensional image of at least a portion of the medical device for display.

23. The method of claim 19, further comprising using the medical device to measure the electrical activity of body tissue.

24. The method of claim 19, further comprising using the medical device to ablate body tissue.

25. The method of claim 19, wherein the medical device is positioned in the heart chamber of the body.

26. The method of claim 25, wherein one of the one or more reference catheters are positioned within the coronary sinus of the heart.

27. The method of claim 25, wherein one of the one or more reference catheters is positioned within the coronary sinus of the heart, and another of the one or more reference catheters is positioned in the right ventricle of the heart.

28. The method of claim 19, wherein the one or more reference catheters comprises the medical device.

29. The method of claim 19, wherein the one or more reference catheters and medical device are separate.

30. The method of claim 19, wherein the one or more reference catheters comprises a plurality of reference catheters.

31. The method of claim 19, wherein the one or more ultrasound tracking transducers comprises a single tracking transducer.

32. The method of claim 19, wherein the one or more ultrasound tracking transducers comprises a plurality of tracking transducers.

33. The method of claim 19, wherein each of the one or more reference catheters comprises a single spline.

| | | | |
|----------------|--|---------|------------|
| 专利名称(译) | 使用超声波进行电极定位的系统和方法 | | |
| 公开(公告)号 | US6970733 | 公开(公告)日 | 2005-11-29 |
| 申请号 | US10/273468 | 申请日 | 2002-10-21 |
| [标]申请(专利权)人(译) | 心脏PATHWAYS | | |
| 申请(专利权)人(译) | 心脏PATHWAYS CORPORATION | | |
| 当前申请(专利权)人(译) | SCIMED LIFE SYSTEMS INC. | | |
| [标]发明人 | WILLIS N PARKER BRISKEN AXEL ZENG JINGLIN HURD MARSHA | | |
| 发明人 | WILLIS, N. PARKER BRISKEN, AXEL ZENG, JINGLIN HURD, MARSHA | | |
| IPC分类号 | A61B5/042 A61B5/06 A61B8/08 A61B8/12 A61B18/14 A61B5/04 | | |
| CPC分类号 | A61B5/0422 A61B5/06 A61B5/6855 A61B5/6856 A61B5/6858 A61B8/0833 A61B8/12 A61B18/1492 A61B8/445 A61B8/543 A61B2017/00106 A61B2018/00065 A61B2018/00113 A61B2018/00214 A61B2018/00351 A61B2018/00577 A61B2018/00839 A61B2019/5251 A61B2019/5263 A61B2218/002 A61B2562/0209 A61B2562/043 A61N2007/0078 A61B2034/2051 A61B2034/2063 A61B2562/0215 | | |
| 代理机构(译) | BINGHAM MCCUTCHEN LLP | | |
| 其他公开文献 | US20030036696A1 | | |
| 外部链接 | Espacenet USPTO | | |

摘要(译)

本发明是一种装置定位系统，其使用一个或多个超声参考导管使用三角测量原理在患者心脏内建立固定的三维坐标系。坐标系在视频监视器上以三维图形表示，并且帮助临床医生引导其他医疗设备（其配备有超声换能器）通过身体到达执行临床程序所需的位置。在根据本发明的系统的一个实施例中，该系统用于心脏中以帮助医生指导用于测量电活动的导管的映射，以及用于消融心脏组织的选定区域的消融导管到心脏内的期望位置。

