



US006241677B1

(12) **United States Patent**
Guracar et al.

(10) **Patent No.:** **US 6,241,677 B1**
(45) **Date of Patent:** **Jun. 5, 2001**

(54) **METHOD AND APPARATUS FOR
ULTRASOUND IMAGE QUANTIFICATION**

(75) Inventors: **Ismayil M. Guracar**, Redwood City;
Samuel H. Maslak, Woodside; **John
W. Allison**, Sunnyvale; **Paul E.
Chandler**, Santa Cruz; **John I.
Jackson**, Menlo Park; **Arvind Jain**,
San Jose; **Laurence S. McCabe**,
Sunnyvale, all of CA (US)

(73) Assignee: **Acuson Corporation**, Mountain View,
CA (US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 0 days.

(21) Appl. No.: **09/478,662**

(22) Filed: **Jan. 6, 2000**

Related U.S. Application Data

(62) Division of application No. 08/753,999, filed on Dec. 4,
1996.

(51) **Int. Cl.**⁷ **A61B 8/00**

(52) **U.S. Cl.** **600/453; 600/455**

(58) **Field of Search** 600/447, 437,
600/455, 454, 449

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,067,236 1/1978 Hottinger .
4,103,679 8/1978 Aronson .
4,265,126 5/1981 Papadofrangakis et al. .

(List continued on next page.)

FOREIGN PATENT DOCUMENTS

0 838 288 A1 8/1990 (EP) .
0 222 913 B1 10/1990 (EP) .
0 415 324 B1 3/1991 (EP) .
0 520 338 A2 12/1992 (EP) .
2-126835 5/1990 (JP) .
H6-217976 8/1994 (JP) .

WO 86/00516 1/1986 (WO) .
WO 90/02517 3/1990 (WO) .
WO 91/15999 10/1991 (WO) .
WO 92/07514 5/1992 (WO) .
WO 92/10135 6/1992 (WO) .

OTHER PUBLICATIONS

Doppler Ultrasound, Physics, Instrumentation, And Clinical
Applications, John Wiley & Sons, 1989, Chapter 11, pp.
188-205.

*Time Domain Formulation Of Pulse-Doppler Ultrasound
And Blood Velocity Estimation By Cross-Correlation*, O.
Bonnefous And P. Pesque, 1986, pp. 73-85.

Angle Independent Doppler Color Imaging: Determination
Of Accuracy And A Method Of Dispaly, Ding-Yu Fei Et Al.,
Ultrasound In Med. & Biol., vol. 20, No. 2, 1994, pp.
147-155.

(List continued on next page.)

Primary Examiner—Marvin M. Lateef


Assistant Examiner—Maulin Patel

(74) *Attorney, Agent, or Firm*—Craig A. Summerfield,
Esq.; Brinks Hofer Gilson & Lione

(57) **ABSTRACT**

A method and apparatus for quantifying and displaying
ultrasound signals in an ultrasonic system are provided. A
first signal value for each of at least one spatial location in
a region of interest is acquired at a first time, and the signal
values are summed to obtain a first surface integral value. A
second signal value for each of said at least one spatial
location in said region of interest is acquired at a second
time, and the second signal values are summed to obtain a
second surface integral value. The first surface integral value
is summed with the second surface integral value to obtain
a time based integral. The time based integral is displayed.
Other quantities based on any of various ultrasound
parameters, such as Doppler energy, Doppler velocity and
B-mode intensity, are calculated and displayed as quantities
or as waveforms as a function of time. Furthermore, various
comparisons of quantities and waveforms are provided.
Image plane data or other ultrasound data are used in the
calculations. Finally, a histogram data structure is provided
to aid calculation of the various quantities.

9 Claims, 16 Drawing Sheets



U.S. PATENT DOCUMENTS

4,373,533	2/1983	Linuma .	
4,476,874	10/1984	Taenzer et al. .	
4,509,526	4/1985	Barnes et al. .	
4,790,322	12/1988	Linuma .	
4,800,891	1/1989	Kim .	
4,873,985	10/1989	Nakajima .	
4,928,698	5/1990	Bonnefous .	
5,010,528	4/1991	Ohtsuki et al. .	
5,014,710	5/1991	Maslak et al. .	
5,062,427	11/1991	Seo et al. .	
5,063,931	11/1991	Leavitt .	
5,165,413	11/1992	Maslak et al. .	
5,195,521	3/1993	Melton, Jr. et al. .	
5,224,481	7/1993	Ishihara et al. .	
5,233,994	8/1993	Shmulewitz .	
5,235,984	8/1993	D'Sa .	
5,241,473	8/1993	Ishihara et al. .	
5,280,787	1/1994	Wilson et al. .	
5,287,753	2/1994	Routh et al. .	
5,322,067	6/1994	Prater et al. .	
5,471,990	12/1995	Thirsk .	
5,505,204	* 4/1996	Picot et al.	600/447
5,515,857	5/1996	Tsujino et al. .	
5,538,003	7/1996	Gadonniex et al. .	
5,555,534	9/1996	Maslak et al. .	
5,623,930	* 4/1997	Wright et al.	600/447
5,675,554	10/1997	Cole et al. .	
5,769,079	* 6/1998	Hossack et al.	600/454
5,800,356	9/1998	Criton et al. .	
5,953,439	* 9/1999	Ishihara et al.	382/107

OTHER PUBLICATIONS

Quantative Measurement Of Volume Flow Rate (Cardiac Output) By The Multibeam Doppler Method, H. Tsujino Et Al., Medical Systems Division, Toshiba Corporation, Roshiba Medical Engineering Corporation, 1995, pp. 621-630.

Fractional Moving Blood Volume: Estimation with Power Doppler U.S. Jonathan M. Rubin et al., Radiology, Oct. 1995, pp. 183-190.

Toshiba Systems Data No. MSDUS0007EA Ultrasound Diagnostic System Powervision™ SSA-380 (1994).

Toshiba How to measure cardiac output accurately within just seconds. (Date Unknown).

National Cancer Institute—Grant Application R01 CA55076-02, Jul. 8, 1993.

Approximate Quantification of Detected Fractional Blood Volume and Perfusion From 3-D Color Flow and Doppler Power Signal Imaging, Paul L. Carson et al., 1993 Ultrasonics Symposium, IEEE pp. 1023-1026.

The dependence of myocardial ultrasonic intgrated backscatter on contractile performance, Samuel A. Wickline et al., Circulation 72, No. 1, Jul., 1985.

A Real-Time Integrated Backscatter Measurement System for Quantitative Cardiac Tissue Characterization, Lewis J. Thomas, III et al., IEEE Transactions on Ultrasonics, Ferroelectrics and Frequency Control, vol. UFFC-33, No. 1, Jan. 1986 (1985).

Ultrasound Integrated Backscatter Tissue Characterization of Remote Myocardial Infraction in Human Subjects, Zvi Vered et al., JACC vol. 13, No. 1 Jan. 1989; 84-91.

Ultrasonic Tissue Characterization With a Real Time Integrated Backscatter Imaging System in Normal and Aging Human Hearts, Tohru Masuyama et al., JACC vol. 14, No. 7, Dec. 1989; 1702-8.

Maternal and fetal haemodynamics in hypertensive pregnancies during maternal treatment with intravenous hydralazine or labetalol, Ann Harper et al., British Journal of Obstetrics and Gynaecology, vol. 98, No. 5, May 1991, pp. 453-459.

Laser Doppler imaging of axial and random pattern flaps in the maxillo-facial area. A preliminary report, Wolfgang Eichhorn et al., Journal of Cranio-Maxillo-Facial Surgery, vol. 22, No. 5, Oct. 1994, pp. 301-306.

Indication of Doppler Sampling on the Video Image of a Linear Scanner Without Modification of Commercial Equipment, Knut Matre et al., Ultrasound in medicine biology, vol. 11, No. 4, Jul./Aug. 1985, pp. 585-589.

Usefulness and Limitations of Digital Echocardiography in Detecting Wall Motion Abnormally During Stress Echocardiography in Detecting Wall Motion Abnormally During Stress Echocardiography, Jun Koyama et al., Jpn J Med Ultrasonics vol. 21, No. 11, (1994), pp. 695-701.

Visualizing Tumor Blood Flow by 3-Dimensional Color Doppler Ultrasound.

Arterial Wall Tissue Characterization by Analysis of Railo Frequency Signal Using Intravascular Ultrasound, Y. Takano et al., jpn J Med Ultrasonics vol. 21, No. 2 (1994), pp. 84-89.

An On-Line Computer Analysis of Exercise Capacity Using Continous Wave Doppler Flowmetry, H. Komura, Jpn J Med Ultrasonic vol. 20, No. 6 (1993) pp.

Experimental and Clinical Study of Tissue Characterization of Prostate using Amplitude Image and Mean Frequency Image, Akifumi Yamane, Jpn J Ultrasonics vol. 20, No. 6, (1993), pp. 362-367.

Telemetry of Human Gastric Temperature with Quartz Crystal Resonator Using Ultrasonic Detection, The Japanese Journal of Medicine Instrumentation, vol. 60, No. 7 (1990), pp. 309-314.

Title Unknown, author unknown, Ika Kikai Gaku, vol. 57, No. 2, (1987), pp. 78-83.

Determination of Blood Flow Volume of Skin by Laser Dopler Method-Development of a New Data Analysis System, H. Sugihara et al., Ika Kikai Gaku, vol. 62, No. 10 (1992), pp. 470-474.

Tosbee Compact, Easy-to-operate Diagnostic Ultrasound System, K. Hara, Tishiba Review, vol. 46, No. 2, (1991), pp. 96-10.

Fully Digital Ultrasound Diagnostic System, K. Okubo et al., Tishiba Review, vol. 49, No. 2 (1994), pp. 84-88.

* cited by examiner

FIG. 1A







FIG. 1B










FIG. 5




FIG.6A

$$E_{NSI} = \frac{\sum_{ROI} D(E\lambda) \quad T\lambda(E\lambda, V\lambda)}{\sum_{ROI} T\lambda(E\lambda, V\lambda)}$$

WHERE D=FUNCTION TO REVERSE LOG COMPRESSION

T=FUNCTION TO THRESHOLD





FIG. 7

$$E_{\text{TNSI}}(n) = \sum_{t=T_{n-1}}^{t=T_n} E_{\text{NSI}}(t)$$

FIG. 8A




FIG. 8B




FIG. 9




FIG. 10




FIG. 11




FIG. 12A




FIG. 12B




FIG. 13A




FIG. 13B




FIG. 14A




FIG. 14B




FIG. 14E




FIG. 14D




FIG. 14C




FIG. 15A




FIG. 15B




FIG. 16





FIG. 17



8/6/21





FIG. 19



METHOD AND APPARATUS FOR ULTRASOUND IMAGE QUANTIFICATION

This application is a division of application Ser. No. 08/753,999, filed Dec. 4, 1996, (pending).

A portion of the disclosure of this patent document contains material which is subject to copyright protection. The copyright owner has no objection to the facsimile reproduction by anyone of the patent document or the patent disclosure, as it appears in the Patent and Trademark Office patent file or records, but otherwise reserves all copyright rights whatsoever.

This application includes one microfiche appendix. The appendix contains 1 microfiche with 36 frames.

FIELD OF THE INVENTION

This invention relates in general to ultrasound systems and in particular to quantification, display and other uses of various parameter data, including surface and time integral data, in ultrasound systems.

BACKGROUND OF THE INVENTION

In traditional ultrasound imaging and display, color Doppler imaging (CDI), spectral Doppler imaging (SD), or B-mode imaging are available. CDI refers to color Doppler F-mode imaging techniques. CDI provides a qualitative evaluation of fluid dynamics and tissue motion in a body that is imaged. Thus, CDI techniques currently provide the user with limited quantitative information. B-mode imaging, with the associated gray-scale display, also provides a qualitative display with limited quantitative information. SD, on the other hand, provides the user with information about a single point or position in space. SD provides flow information as a display of the brightness of the spectrum and a velocity scale display.

Quantitative calculation of a surface integral or area average for a particular region of interest provides a measurement-based calculation—Doppler energy or power related to the amount of blood in a cross-sectional area or volume of tissue in the body. "Approximate Quantification Of Detected Fractional Blood Volume And Perfusion From 3-D Colorflow And Doppler Power Signal Imaging" by Carson et al., 1993 Ultrasonics Symposium, pp. 1023–26 discusses such a calculation. The article by Carson et al. discloses a signal power-weighted color pixel density calculated by summing the Doppler energy for the various pixels in the region of interest and dividing by the number of such pixels.

Limited use of linearization of B-mode data to aid in quantification is known. In U.S. Pat. No. 5,235,984 to D'Sa, a method for undoing the log compression and other processing to generate a linearized average of B-mode intensity in a region of interest is disclosed. D'Sa discloses averaging B-mode intensity for a region of interest and then linearizing the average B-mode intensity value. The quantified B-mode data is displayed. D'Sa also teaches a display of multiple B-mode intensity curves from sequential trace operations at one or more regions of interest.

Other techniques to aid quantification of Doppler velocity are known. One way to acquire Doppler velocity information and process the Doppler velocity information is by a one-dimensional histogram. The Doppler velocity histogram may then be displayed on an ultrasound display with the color display.

The color display of Doppler data is controlled by application of a threshold. Once color Doppler data of a particular

parameter is obtained, the data is mapped to a color display. Before mapping, a threshold for the same particular parameter is applied to the data so that only data with a value above the threshold remains. Thus, the thresholded values are used for any calculations.

None of the ultrasound systems for obtaining and displaying ultrasound data is entirely satisfactory. As discussed above, only limited quantification is known. It is therefore desirable to provide an improved ultrasound system for obtaining and displaying ultrasound data.

SUMMARY OF THE INVENTION

The invention provides an efficient method for processing and displaying various ultrasound data. In one aspect, a method and apparatus for quantifying and displaying Doppler signals in an ultrasonic Doppler system are provided. A first Doppler signal value for each of at least one spatial location in a region of interest is acquired at a first time, and the Doppler signal values are summed to obtain a first surface integral value. A second Doppler signal value for each of said at least one spatial location in said region of interest is acquired at a second time, and the second Doppler signal values are summed to obtain a second surface integral value. The first surface integral value is summed with the second surface integral value to obtain a time based integral. The time based integral is displayed. In another aspect of the invention, the time based integral is normalized by the number of surface integrals summed.

In another aspect of the invention, a method and apparatus for displaying multiple quantities obtained at different times from data corresponding to a region of interest are provided. The region of interest is selected and includes at least one spatial location. First and second ultrasound signal values for each of said at least one spatial location are acquired at first and second times, respectively. Comparison data are created as a function of said first and second ultrasound signal values and displayed.

In yet another aspect of the invention, a method and apparatus for displaying multiple quantities obtained at the same or different times from data corresponding to multiple regions of interest are provided. First and second regions of interest are selected to include at least a first and second spatial location, respectively. First and second ultrasound signal values are acquired for each of the first and second spatial locations. The second ultrasound signal value is derived from the same type of ultrasound parameter as the first ultrasound signal value. Comparison data are created as a function of the first and second ultrasound signals and displayed.

In another aspect of the invention, a method and apparatus for displaying multiple quantities obtained from data corresponding to different regions of interest are provided. First and second regions of interest are selected. First and second ultrasound signal values are obtained for said first and second region of interests. The second ultrasound signal value is derived from a different type of ultrasound parameter than the first ultrasound signal value. Comparison data are created as a function of said first and second ultrasound signals.

In yet another aspect of the invention, a method and apparatus for displaying multiple quantities obtained from a region of interest are provided. A region of interest is selected, and a B-mode intensity associated with said region of interest is obtained. Further, an ultrasound signal value selected from the group of Doppler energy and Doppler velocity is also obtained. Comparison data are created as a function of said B-mode intensity and said ultrasound signal value.

In another aspect of the invention, a method and apparatus for displaying multiple results obtained from a region of interest are provided. A region of interest is selected, and a Doppler velocity and energy associated with the region of interest are obtained. Comparison data are created as a function of the Doppler velocity and Doppler energy and displayed.

In another aspect of the invention, a method and apparatus for providing flow quantities data by thresholding are provided. A Doppler energy and velocity for each of multiple spatial locations in a region of interest are acquired at a first time. A threshold is applied to the Doppler energies based on the Doppler velocities to obtain remaining Doppler energies. The remaining Doppler energies are summed to obtain a surface integral energy value.

In another aspect of the invention, a method and apparatus for deriving a quantity with a histogram are provided. An ultrasound signal value selected from the group of Doppler energy and Doppler variance is acquired for each of multiple spatial locations in a region of interest. The histogram includes multiple bins corresponding to bin ultrasound signal values. The counts in the appropriate bins are incremented based on the acquired ultrasound signal values, and a quantity is derived from the histogram. In yet another aspect of the invention, the histogram is displayed without deriving a quantity.

In another aspect of the invention, a method and apparatus for deriving a quantity based on a threshold are provided. Ultrasonic signal values for multiple spatial locations in a region of interest are acquired. A histogram is created based on the values. The threshold is applied to the histogram, and a quantity is derived from the histogram after applying the threshold.

In yet another aspect of the invention, a method and apparatus for using data in an ultrasound system over time to derive a quantity are provided. First ultrasonic signal values for multiple spatial locations in a region of interest are acquired at a first time and used to create a histogram. Second ultrasonic signal values, derived from the same type of ultrasound parameter as the first ultrasound values, are acquired for the multiple spatial locations in the region of interest at a second time. A second dimension of the histogram is created as a function of the second ultrasound values. A quantity is derived from the histogram.

In another aspect of the invention, a method and apparatus for setting the integration interval for time integrated surface integrals are provided. At least first and second ultrasound signal values for each of multiple spatial locations in a region of interest are acquired at first and second times, respectively. At least said first and second Doppler signal values are summed to obtain at least first and second surface integral values, respectively. A time period is selected from a waveform comprising at least first and second times corresponding to the first and second surface integral values. The surface integrals within the selected time period are summed to obtain said time integrated surface integral.

In another aspect of the invention, a method and apparatus for adjusting a color image on an ultrasound display are provided. A region of interest is selected in an ultrasound image display having at least two dimensions. A controller assigns an area of color measurement and display to encompass the region of interest, and a color image is mapped onto the display for the area.

In yet another aspect of the invention, a method and apparatus for automatically detecting a border without altering data for performing a calculation for a region of interest

are provided. A region of interest associated with an ultrasound image display having at least two dimensions is selected. A first ultrasound value for each of multiple spatial locations in the region of interest is obtained. A threshold is applied to the first ultrasound values to detect a border within the region of interest. A calculation is performed to derive a surface integral of the first ultrasound values within the border including the first ultrasound values that are below and above the threshold. In yet another aspect of the invention, a second type of ultrasound signal value is used to derive the surface integral.

In yet another aspect of the invention, a method and apparatus for quantifying and displaying Doppler signal strength signals associated with a point or line are provided. Color values based on image plane data representative of different Doppler signal strengths are mapped at multiple spatial locations. A color Doppler signal strength display is created based on said color values, and a point or line is selected. A Doppler signal strength value associated with the point or line is obtained from the image plane data. A quantity derived from said Doppler signal strength value or values is displayed. In a further aspect of the invention, an area is selected. The values are obtained prior to color mapping, and the displayed quantity is derived from the values.

BRIEF DESCRIPTION OF THE DRAWINGS

FIGS. 1A and 1B form a block diagram of an ultrasound imaging system that incorporates a preferred embodiment of the present invention. FIGS. 1A and 1B will be referred to as FIG. 1 below, when reference is to the composite.

FIG. 2 is a schematic view of a two-dimensional ultrasound image on the display unit of the ultrasound system of FIGS. 1A and 1B or FIGS. 15A and 15B.

FIG. 3 is a block flow diagram for performing linear calculations using a histogram.

FIG. 4A is a graphical representation of a one-dimensional histogram.

FIG. 4B is a graphical representation of a two-dimensional histogram.

FIG. 4C is another graphical representation of a two-dimensional histogram for use by a microprocessor.

FIG. 5 is a flow diagram for performing linear calculations using a two-dimensional histogram.

FIG. 6A is a mathematical representation of a normalized surface integral of Doppler energy.

FIG. 6B is a graphical representation of the normalized surface integral of Doppler energy of FIG. 6A plotted over time.

FIG. 6C is a graphical representation of the reverse log compression function.

FIG. 7 is a mathematical representation of a time integral of the normalized surface integral of Doppler energy.

FIG. 8A is a graphical representation of the normalized surface integral of Doppler energy plotted over time and displayed on the ultrasound system for time period selection.

FIG. 8B is a graphical representation of an ECG trace for display on the ultrasound system.

FIG. 9 is a schematic view of a two-dimensional ultrasound image on the display unit of FIG. 1B with a box for display of calculations and waveforms.

FIG. 10 is a schematic view of a two-dimensional ultrasound image on the display unit of FIG. 1B or FIG. 15B with automatic region of interest determination and a box for display of calculations and waveforms.

FIG. 11 is a block diagram of the F-mode processor of FIG. 1A.

FIG. 12A is a block diagram of the parameter estimator of FIG. 1A.

FIG. 12B is a graphical representation of a log compression function.

FIG. 13A is a block diagram of the B-mode processor of FIG. 1A.

FIG. 13B is a graphical representation of a log compression function.

FIG. 14A is a schematic view of a vessel on a two-dimensional ultrasound display showing a region of interest and a flow profile for the region of interest.

FIG. 14B is a graphical representation of the velocity profile of FIG. 14A sensed by ultrasound system before baseline shifting.

FIG. 14C is a graphical representation of a histogram created from the velocity profile of FIG. 14B.

FIG. 14D is a graphical representation of the histogram of FIG. 14C after baseline shifting.

FIG. 14E is a graphical representation of the velocity profile of FIG. 14B after baseline shifting.

FIGS. 15A, 15B together form a block diagram of an alternative ultrasound system for calculating various quantities. FIGS. 15A and 15B will be referred to as FIG. 15, where reference is to the composite.

FIG. 16 is a circuit diagram illustrating in more detail a portion of the circuit of FIG. 15B.

FIG. 17 is a block diagram illustrating in more detail one implementation of the circuit of FIG. 16.

FIG. 18 illustrates another implementation of the circuit of FIG. 16.

FIG. 19 is a schematic circuit diagram illustrating a circuit useful for implementing the circuit of FIG. 18.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Definitions:

Surface integral: the sum of values associated with a set of data corresponding to a two-dimensional slice of a body.

Mapping: obtaining a second value from a table based on a first value.

Parameters: any of various ultrasonic signal measurements, such as energy, velocity, variance or B-mode intensity.

Image plane data: ultrasonic information in a raster grid. Referring now to FIGS. 1 and 15, ultrasound systems 100, 400 for acquiring ultrasound data and displaying the data are shown. FIG. 1 illustrates one of the preferred embodiments of the invention. Generally, ultrasound systems such as the Acuson 128XP or the system disclosed in U.S. application Ser. No. 08/620,283, filed on Mar. 22, 1996, the disclosure of which is herein incorporated by reference, can be used for ultrasound system of FIG. 1, supplemented with the image quantification features described below.

FIG. 15 illustrates another one of the preferred embodiments of the invention. Generally, ultrasound systems such as the Acuson Sequoia™ or Aspen™ systems or the system disclosed in U.S. application Ser. No. 08/432,858, filed on May 2, 1995, the disclosure of which is herein incorporated by reference, can be used for the ultrasound system of FIG. 15, supplemented with the image quantification features described below.

In either system, image plane data is used to calculate various quantities. In the system of FIG. 1, a microprocessor

127 acquires image plane data to perform various calculations. Preferably, the microprocessor 127 is a TMS 320C25 by Texas Instruments. In the system of FIG. 15, look-up tables 446 and accumulators 444 acquire image plane data to perform various calculations. Acoustic data or color values may also be used to calculate any of the various quantities.

Image plane data is created by applying signals to a body, detecting echo signals and processing the echo signals. Referring to FIG. 1A, the ultrasound system 100 includes a transducer 104 connected to a beamformer 102. Beamformer 102 applies appropriate signals to the transducer 104, to cause the transducer 104 to transmit ultrasound signals towards a body. Referring to FIG. 15A, a beamformer 402 generates similar signals for transmission by a transducer 430. Generally, the discussion below refers to the embodiments of both FIG. 1 and FIG. 15 simultaneously.

The transducers 104, 430, scan a region in a body to be imaged with ultrasound signals in one of several possible formats, such as linear, steered linear, sector, VECTOR® and curved linear array formats. The ultrasound signals are transmitted sequentially along scan lines (not shown) spanning a scan plane in a region of interest. Portions of the ultrasound signals echo off structures and fluids within the body.

The transducer 104, 430 detects the echoes, and the detected echo signals are output to the beamformer 102, 402. The beamformer 102, 402 processes the signals as known in the art.

The output of the beamformer 102, 402 is further processed by a B-mode processing unit 105, 404 and an F-mode processing unit 107, 406. These two units operate in parallel. For the sake of simplicity, the B-mode processing unit 105 and F-mode processing unit 107 of the embodiment shown in FIG. 1 are described below. The B-mode processing unit 404 and F-mode processing unit 406 of the embodiment shown in FIG. 15 operate similarly.

B-mode processing unit 105 provides data for creating a gray-scale B-mode intensity image, which is generally indicative of echo signals from structure. The overall function of the B-mode processing unit 105 is to demodulate the signal from beamformer 102 and to provide a compressed digital output.

Referring to FIG. 13A, the B-mode processing unit 105 includes a log detection unit 170 that converts the input signal from the beamformer 102 to a log (dB) scale. Envelope detector 172 filters the log scale signal and outputs the envelope of the signal. Video low pass filter 174 removes further undesirable high frequency variations from the envelope signal. A gain unit 176 amplifies the low pass filtered envelope signal. The amount of gain provided by gain unit 176 is controlled by the system operator, who adjusts gain to alter the brightness of the B-mode intensity gray scale image displayed on display unit 132.

The B-mode processor unit 101 also includes a log compression unit 178 that compresses the gain adjusted signal. FIG. 13B illustrates the preferred log compression function applied by the log compression unit 178. The B-mode log compression function preferably depends on operator input from user interface 133, as known in the art. Finally, an A/D converter 180 converts the analog compressed signal to a digital signal. The B-mode processing unit 105 outputs digital B-mode intensity data on an acoustic grid (B-mode ultrasound signal values).

Referring back to FIG. 1, the F-mode processing unit 107 generates Doppler information from the analog output of the beamformer 102. Doppler information is derived from echo signals from moving reflectors.

Referring now to FIG. 1, the F-mode processing unit 107 is shown in detail. A demodulator 150 divides the echo signals into in-phase (I) and quadrature (Q) components, as known in the art. A/D converters 152, 154 convert the I and Q analog signals into digital signals. High pass filters 156, 158 remove wall or clutter from the digital signals. When tissue movement is imaged, the high pass filters 156, 158 may be bypassed. An auto-correlation unit 160 computes real and imaginary signals as a function of the auto-correlation of the I and Q filtered signals, as known in the art. A zero (0) to one (1) sample lag is used, and the resulting signals are referred to as the auto-correlation values $R(0)$, $R(1)_r$, $R(1)_i$. The $R(0)$, $R(1)_r$, $R(1)_i$ signals represent Doppler data. As an alternative embodiment, the Doppler data is acquired according to the time shift techniques described by Bonnefous in U.S. Pat. No. 4,928,698.

The Doppler and B-mode data from F-mode and B-mode processing units 107 and 105 is stored. Referring to FIG. 1, a CINE 112 stores the Doppler data from the F-mode processing unit 107. Preferably, the auto-correlation values are stored in unit 112. A separate CINE 182 stores the B-mode data from B-mode processing unit 105. The stored B-mode and Doppler data is retrievable for later playback.

Alternatively and referring to FIG. 15, a single CINE 408 stores data from both the B-mode processing unit 404 and F-mode processing unit 406. The reading and writing of image information into or out of memory 408 is controlled by microprocessor 420 employing a write address unit 422 and a read address unit 424. In the embodiment shown in FIG. 15, the F-mode processor 406 further processes the Doppler data to detect Doppler parameter information. Obtaining Doppler parameter information is discussed below with respect to FIG. 12.

An estimator unit 114 derives Doppler parameter information from the Doppler data in CINE 112. Doppler parameter information includes data for different types of parameters, such as energy, mean velocity, variance and acceleration values. Referring to FIG. 12A, the estimator unit 114 includes parameter estimator 162 that derives values for the Doppler parameters, as known in the art. For example, the energy value is equal to $R(0)$. The terms Doppler power and Doppler energy are used synonymously and are intended to refer generally to parameters that vary with the signal strength of a Doppler signal.

An estimator gain unit 164 amplifies the energy value. The amount of gain provided by estimator gain unit 164 depends on input from the operator of the ultrasound system 100. Gain adjustments alter the color corresponding to each Doppler energy value displayed on display unit 132.

Compressor 166 compresses the amplified energy value. FIG. 12B illustrates a preferred compression function which is dependent on the operator's control of the dynamic range. In particular, a toggle switch on user interface 133 provides operator input for selection of the output level. The operator changes the dynamic range, as known in the art, to alter the mapping of input energy values to the range of output values for eventual display. Alternatively, the ultrasound system 100 may be preprogrammed with a particular output level.

The parameter selection and threshold unit 168 applies thresholds to selected ones of the compressed energy values and the other output values of the parameter estimator 162. The level of any given threshold depends on operator input or programmed threshold levels. The programmed threshold levels are preferably selected as appropriate for particular applications of the ultrasound system 100. The thresholds are applied to any of Doppler velocity, variance or energy. Threshold values associated with one parameter may be

used to threshold another parameter. For example, an energy threshold value is applied to energy values associated with a particular signal for setting velocity values corresponding to the same signal to zero. A threshold table is used to compare and to threshold the digital parameter values.

The parameter selection and threshold unit 168 also implements selection of various parameters, as known in the art. The selection is controlled by the operator via user interface 133. The selected parameter is output from estimator unit 114 for display and other processing. The output is an acoustic frame of data associated with a particular Doppler parameter, such as acoustic Doppler energy data. While one output line is shown for variance or energy, separate output lines for each parameter can be provided.

Referring to FIG. 1, the estimated parameters in acoustic frames are then scan converted to create frames of image plane data of Doppler ultrasound signal values. Scan conversion unit 120 converts the acoustic grid Doppler data to display grid Doppler data. The scan conversion unit 120 provides Doppler energy image plane data, Doppler velocity image plane data and any other Doppler parameter image plane data to buffer 123.

Likewise, the acoustic grid B-mode intensity data from CINE 182 is converted by a scan conversion unit 121. The B-mode intensity ultrasound signal values image plane data is also stored in buffer 123. B-mode image plane data, other than intensity, may be provided to and stored in buffer 123.

Referring now to the embodiment shown in FIG. 15, the B-mode intensity and Doppler ultrasound signal value data stored in CINE 408 is also scan converted and stored. A scan conversion unit 410 converts both the Doppler and B-mode acoustic data into image plane data. The image plane data is stored in buffers 412, 414, corresponding to image type 0 and image type 1, respectively.

Referring to both FIGS. 1 and 15, the image plane data in buffers 123, 412, and 414, along with any other image plane data, typically comprises the identity of pixels or spatial locations corresponding to particular areas of a body. The image plane data is divided into frames of image plane data. Each frame of image plane data contains data acquired from the body at a particular time. Each of the buffers 123, 412, 414 is divided into sections for storing frames of the different types of image plane data, such as B-mode intensity, Doppler energy, Doppler variance, or Doppler velocity. For any particular type of parameter, values for each spatial location are stored in buffers 123, 412, and 414.

While the scan converted data is written into buffers 123, 412, 414, other previously stored image plane data is retrieved from the buffers 123, 412, and 414. The image plane data is used to create a display on display unit 132, 440. The microprocessor 127, 420 controls storage and retrieval of the image plane data.

Referring to FIG. 15, image plane data is applied along signal path 438 to display unit 440 for displaying B-mode and Doppler images in a manner known to those skilled in the art. Generally, the B-mode and Doppler images are created as discussed below with reference to FIG. 1. Referring to FIG. 1, the B-mode or Doppler image plane data from buffer 123 is provided to color mapping unit 126. The color mapping unit 126 derives display information, such as RGB color values, therefrom for display as image 130 on the display unit 132. For color Doppler display, a color corresponding to the Doppler parameter value at any given pixel is selected for display. For gray scale B-mode display, a gray intensity corresponding to the B-mode intensity value at any given pixel is selected for display. Thus, the color values also represent ultrasound signal values.

The particular B-mode or Doppler image **130** displayed is a function of operator input. Operator selection of the type of image **130** is input with the user interface **133**. Preferably, the user interface **133** comprises a QWERTY keyboard. The possible types of image **130** include a display of either Doppler parameters (such as velocity, velocity variance or energy), B-mode parameters (such as intensity), or a combination of parameters.

One combination of parameters includes a B-mode intensity image with a Doppler energy image displayed within the B-mode image. An example of such a display is shown in FIG. 2. A color Doppler image **400** overlays a B-mode image **402**. The color Doppler image **400** represents the area of the body and area of the B-mode image **402** where Doppler echo signals are acquired and processed as discussed earlier. The shape of the color Doppler image **400** preferably conforms to the scan line format used. For spatial locations corresponding to both B-mode and Doppler information, a combined color value is selected. The combined color value is clipped to a maximum color value if the combined value is larger than the maximum color value. Alternatively, for each spatial location within image **130**, either a Doppler value or a B-mode value is selected and mapped to a color or grey scale value, respectively.

Another combination display includes the color display of an image **130** of blended parameters. For example, the color mapping unit **126** applies a RAM based look-up table to map two parameters, such as Doppler energy and velocity. Doppler energy and velocity data for each pixel are mapped to values in the table of Doppler energy and velocity values and an output of a particular color is selected from the table. Thus, a velocity-energy image **130** is created.

Once the type of image **130** is selected, field control map **125** determines what image plane data from buffer **123** to use for the display for any given pixel. Preferably, field control map **125** is a memory device for prioritization of image data and for rejecting low velocities for velocity imaging. Field control map **125** controls overlaying of images **130**. For example, a display of B-mode intensity with color Doppler energy overlaid is created. Typically, the field control map **125** uses the Doppler velocity image plane data to determine whether a particular pixel is associated with tissue or structure for display of the appropriate image plane data. One particular velocity value or any lower values are associated with tissue, while any higher velocities are associated with fluid. The particular tissue versus fluid velocity value depends on the operator control of the selectable velocity scale and filter, as known in the art. Field control map **125** then selects the appropriate image plane data from buffer **123**, such as B-mode intensity data for a pixel associated with tissue and Doppler energy data for a pixel associated with fluid. Display of other combinations of ultrasound parameters and applying a threshold to parameters other than Doppler velocity are possible.

Real-time display derived from image plane data, alone or in combination with other data, is displayed on display unit **132**. For example, a frame of real-time color mapped energy values displayed over a B-mode image is displayed followed by a frame of average energy values displayed over the B-mode image. This display process is then repeated for each new frame. The average data may be of any parameter and from any time period, including the two most immediately preceding real-time frames of image plane data. Further, any combination or no combination of real-time data with an average data or other calculated data may be displayed on display unit **132**. The order of displaying frames may not correspond to the order in which the frames were acquired.

Other various combinations of display are possible. For example, a display derived from one frame of B-mode image plane data is frozen on the display unit **132** for one or several time periods while displays derived from multiple frames of Doppler image plane data are displayed over the B-mode display. As another example, the microprocessor **127** compares each frame of image plane data and retains the highest or lowest parameter value for each pixel. Thus, an accumulated frame of the highest or lowest parameter values over one or more time periods is created. The display is then derived from the accumulated frame. Other values, such as the mean value could also be retained.

Referring to FIG. 2, once the image **130** is displayed, a region of interest **131** is selected by the operator. Referring to FIGS. 1 and 2, as shown by block **127a** in FIG. 1, the microprocessor **127** receives the input from the user interface **133** and controls the display unit **132** for selection of the region of interest **131**. The operator selects the region of interest **131** from the image **130** on display unit **132**. The operator manipulates the user interface **133**, such as a track ball or other device known in the art. The operator positions icons to create a border for the region of interest **131**, draws the region of interest **131** or designates a size and shape of the region of interest **131** around a positioned icon. The icon or drawing of the region of interest **131** is displayed on display unit **132** in real-time as the user manipulates user interface **133**. Referring to FIG. 15, the microprocessor **420** controls the selection of the region of interest **131** as discussed above for microprocessor **127** (FIG. 1). Further, the operator may select multiple regions of interest **131** which may or may not overlap.

Referring to FIG. 2, the region of interest **131** as shown surrounds multiple spatial locations. As an alternative to selecting the region of interest **131** representing multiple spatial locations, the operator designates either a single point represented by icon **270**, a line **272** or a volume as the region of interest. In this way, one or more spatial locations corresponding to the region of interest **131** are selected for further processing. For the sake of simplicity, the discussion below deals with an example where the region of interest **131** includes multiple spatial locations. Similar processing is performed whether the region of interest **131** comprises a single spatial location, multiple spatial locations corresponding to a line **272**, multiple spatial locations corresponding to an area, or multiple spatial locations corresponding to a volume.

Referring to FIGS. 1 and 15, once the region of interest **131** is selected by the user, the microprocessor **127**, **420** determines the spatial location address for each pixel within the region of interest **131**. In the embodiment of FIG. 1, the address information is stored in the microprocessor **127**. In the embodiment of FIG. 15, the address information is stored in the region Id buffer within the buffers **412**, **414**.

The discussion above generally explains the acquisition and display of ultrasound information. Either of the two embodiments disclosed above acquire the ultrasound information. Other systems and methods may also be used to acquire the ultrasound information. The discussion below explains the various uses and calculations for the ultrasound information. Many of the calculations and uses described below are new. For each region of interest **131**, the ultrasound system **100**, **400** has various types of parameter image plane data, such as Doppler energy data. The image plane data or any other ultrasound signal value data associated with spatial locations within any region of interest **131** are used for various calculations and display adjustments.

One such display adjustment avoids calculations based on unavailable data. Referring to FIG. 2, some spatial locations

associated with the region of interest 131 are outside the border 406 of the color Doppler image 400. Doppler echo signals and associated image plane data for part of the region of interest 131 are not created. Any calculations for the region of interest 131 based on the Doppler image plane data do not account for the portion of the region of interest 131 outside of the color Doppler image 400.

Preferably, the region of interest 131 is within both the color Doppler image 400 and the B-mode image 402 and no further adjustments of the color Doppler image 400 are made. Where adjustment is needed, several alternative solutions are possible. First and referring to FIG. 1, the operator configures the ultrasound system 100 so that the region of interest 131 is the only area in the image 130 that Doppler image plane data is obtained and displayed. As known in the art, the microprocessor 127 controls the beamformer 102 and transducer 104 to obtain echo signals from particular locations. Echo signals are obtained for the spatial locations represented by the region of interest 131.

Alternatively and referring to FIG. 2, the color Doppler image 400 overlaying the B-mode image 402 is moved to encompass the region of interest 131. The microprocessor 127 controls movement of the color Doppler image 400 by comparing region ID data with Doppler image plane data associated with each spatial location. The center point of the region of interest 131 is aligned with the center point of the Doppler display 400 or the color Doppler image is moved toward any locations of the region of interest 131 not in the color Doppler image 400. If spatial locations in the region of interest 131 fall outside the color Doppler image 400 after movement, the microprocessor 127 increases the size of the color Doppler image 400. The size is increased until the color Doppler image 400 covers and the ultrasound system 100 acquires echo signals for every spatial location in the region of interest 131.

Movement of the color Doppler image 400 is preferable to obtaining Doppler image plane data for only the region of interest 131 as discussed above. Less processing is required if the color Doppler image 400 is shaped as a function of the scan line format instead of conformed to the region of interest 131. Thus, the color Doppler image 400 preferably has a wedge or other sector shape.

The microprocessor 127 also controls reduction of the size of the color Doppler image 400 to more closely conform to the size of the region of interest 131. First, the microprocessor 127 determines that every spatial location within the region of interest 131 or border 404 are within the area of color Doppler image 400. Second, the microprocessor 127 reduces the size of color Doppler image 400 by control of beamformer 102 and transducer 104. The size is reduced until a spatial location on the border 406 of the color Doppler image 400 is in the same location as a spatial location of the border 404 of the region of interest 131. By automatically reducing the size of the color Doppler image 400, the frame rate of the color Doppler image 400 is increased. Increased frame rate provides better resolution.

The automatic region of interest adjustments discussed above can be used for any combination of ultrasound parameters. For example, display 400 may be a B-mode intensity display. Further, the ultrasound system 400 shown in FIG. 15 also automatically adjusts the color Doppler image 400, or any other image 130, as discussed above. In particular, the microprocessor 420 controls beamformer 402 and transducer 430 to obtain echo signals and move the color Doppler image 400. Alternatively, the microprocessor 127 (FIG. 1), 420 may not allow a region of interest 131 to be designated outside of the color Doppler image 400.

In addition to controlling movement of the color Doppler image 400, the microprocessor 127 alters the image plane data. Referring to FIGS. 1 and 2, the ultrasound system 100 allows operator designation of velocity direction angles within a region of interest 131 for velocity angle correction. Using the user interface 133 in combination with the microprocessor 127, the operator places an icon 270 within the region of interest 131. A line passing through icon 270 displays an angle. Further, a numeric display of the angle is also placed on the image 130. The line is positioned parallel to the flow of fluid in the region of interest 131 by the operator. The angle of the line passing through the icon 270 is incremented by the operator using user interface 133, a paddle switch or rotating knob in particular. Preferably, the angle is incremented in one degree increments either clockwise or counter-clockwise, depending on the paddle switch or rotating knob operation. The microprocessor 127 then assigns the angle associated with icon 270 as the velocity direction angle for each spatial location within the region of interest 131.

For multiple regions of interest 131, a velocity direction angle is determined for each region of interest 131. Furthermore, the microprocessor 127 may automatically place the icon 270 in the center of a selected region of interest 131 for convenience of the operator.

Multiple designations of the velocity direction angle within a particular region of interest 131 are possible. The operator controls user interface 133 to place multiple icons 270 in the particular region of interest 131. Velocity direction angles are selected for each of the icons 270.

Application of the multiple velocity direction angles to spatial locations within the region of interest 131 is performed by several alternative methods. One method generates an interpolated angle for spatial locations between two icons 270, as for example by linear interpolation. For other spatial locations within the region of interest, the angle is extrapolated based on the angles associated with the nearest icons 270.

A second method uses a nearest neighbor technique. For all spatial locations in the region of interest 131, the microprocessor 127 assigns the angle associated with the nearest icon 270 as the velocity direction angle.

Once the velocity direction angle for each spatial location in the region of interest 131 is assigned, microprocessor 127 obtains Doppler velocity image plane data from buffer 123. The microprocessor 127 then corrects the Doppler velocity image plane data in accordance with a velocity correction angle. The velocity correction angle at any point in the region of interest 131 is the difference between the Doppler line angle and the velocity direction angle at that point. At each point (X_i, Y_i) in the region of interest 131, the Doppler line angle in the display raster XY coordinate space is given by $\arctan((X_i - X_{apex}) / (Y_i - Y_{apex}))$ where (X_{apex}, Y_{apex}) are the display coordinates of the apex of the scan format. The velocity value for each location is then divided by the cosine of the velocity correction angle.

The velocity values from the Doppler velocity image plane data are also corrected in accordance with a line dependent direction angle. Where the ultrasound scan lines are in the linear or steered linear format, the ultrasound lines are all parallel and at a constant angle to the region of interest 131, and no line dependent correction is made. However, in the sector, VECTOR® and curved linear array formats, angle correction is further dependent on the Doppler line angle. The angle correction is adjusted as function of the difference of each scan line angle from the user entered velocity direction angle.

The angle corrected Doppler velocity image plane data is used for various calculations and displays. For example, the angle corrected Doppler velocity image plane data is displayed as an angle corrected flow profile for a cross section. By angle correcting the Doppler velocity values, the velocity image plane data more accurately represents the velocities in the region of interest **131**.

Referring to FIG. **15**, the microprocessor **420** also corrects the Doppler velocity image plane data as discussed above. Doppler velocity image plane data from both buffers **412** and **414** is corrected.

Other alterations of the image plane data are desirable, such as conversion to a linear scale. Due to log compression of the echo signals, the image plane data is in the log scale.

The conversion from log scale to linear scale is complicated by quantization effects due to the spacing of the higher linear values. The microprocessor **127** applies an algorithm to reduce any quantization effects. The echo signal may also be preconditioned to remove quantization effects.

Image plane data for each point in a particular region of interest **131** is converted by applying a reverse log compression and scaling algorithm ("reverse log compression"). The microprocessor **127** applies the algorithm to the image plane data. For reverse scaling, the image plane data value for each point is applied to a look-up table to determine a reversed scaled value. The reverse scaled value is then compared to look-up table values to determine a reversed compressed value. The reversed compressed value is in the linear scale. The linear values are used to perform various calculations.

For example, a linear average B-mode intensity is calculated for the region of interest **131**. Each B-mode intensity value is obtained from buffer **123**. The microprocessor **127** reverse log compresses each value. The linear B-mode intensity values are added to obtain a total linear B-mode intensity for the region of interest **131**. The total linear B-mode intensity is divided by the number of points in the region of interest **131** to obtain the linear average B-mode intensity. Further, the linear average B-mode intensity calculation is limited to B-mode intensities within a selected range of values. In this limited range calculation, the number of points corresponds to the number of points associated with B-mode intensities in the selected range.

Referring to FIG. **15**, the microprocessor **420**, using the look-up table **446**, passes linear values to the accumulator **444**. As discussed below, the accumulator **444** sums values for use in various calculations. Thus, the ultrasound system **400** is also capable of converting the image plane data to a linear scale.

Referring to the embodiment shown in FIG. **1**, an alternative method to convert data to a linear scale is provided. Instead of converting each value to a linear scale, a histogram format is used. The microfiche appendix contains code for applying the histogram format. Generally, the coordinates 1X, 1Y, 2X and 2Y are provided. The code uses the coordinates to define an area. Image plane data within the area is obtained and a histogram is created. This method, as represented in FIG. **3**, increases the speed of calculating higher order statistics.

As represented by block **127b**, a histogram format is applied by the microprocessor **127**. The microprocessor **127** obtains the image plane data from buffer **123**. The microprocessor **127** uses the histogram format to calculate a quantity as represented by block **127c**. Referring to FIG. **4**, the histogram format is symbolized graphically as histogram **200**. Preferably, the histogram **200** has two hundred and fifty six (**256**) bin ultrasound values corresponding with **256** bins **201**. Histograms **200** of other sizes could be used.

Referring to FIGS. **3** and **4**, to convert the image plane data to the linear scale, the histogram **200** is computed as represented by block **202**. As an example, B-mode intensity may be selected as the ultrasound parameter of interest within a selected region of interest **131**. Other ultrasound parameters may be used. In this example, the B-mode intensity for each point within the region of interest **131** is compared to bin B-mode intensity values of the histogram **200** as shown by block **204**. For each B-mode intensity equal to or within the range of one of the histogram's bin B-mode intensity values, the bin **201** corresponding to the bin B-mode intensity value is incremented by one as shown by block **206**. Thus, the histogram **200** is computed with a weight assigned to each bin of the histogram. The total weight associated with each of the bins **201** comprises bin data.

The bin B-mode intensity value for each of the bins **201** is converted in block **208** to the linear scale. For each of the bin B-mode intensity values, a reverse log compression algorithm is applied as shown by block **210**. Preferably, a look-up table contains the reverse log compressed values for each of the known bin B-mode intensity values.

Referring to FIG. **1**, the reverse log compression function is based on the operator's log compression adjustment of image **130**, as discussed above with respect to FIG. **12B**. The microprocessor **127** obtains the log compression setting and generates the look-up table based on the log compression setting. The look-up table provides a linear value for each bin value in the log scale. FIG. **6C** demonstrates one possible function for reverse log compression. Referring back to FIGS. **3** and **4**, a linear bin ultrasound value is obtained for each of the **256** bins **201** in block **210**. Any subsequent calculations based on the bin ultrasound values and the bin data are in the linear scale.

As an alternative to applying the one-dimensional histogram **200**, in some applications a two-dimensional histogram **216** is applied to convert data to the linear scale. Referring to FIGS. **1**, **4B** and **5**, the microprocessor **127** creates two-dimensional histograms **216**. Creation of the histogram is demonstrated by block **218** in FIG. **5**. The two-dimensional histogram **216** shown in FIG. **4B** comprises velocity and energy dimensions. Other information or ultrasound parameters can be used.

The histogram **216** includes **64** velocity bins or columns along the velocity axis and **64** energy bins or rows along the energy axis. Each velocity bin has a bin velocity value while each energy bin has a bin energy value. The intersection of an energy bin with a velocity bin represents a particular bin velocity value and energy value. Other sized two-dimensional histograms **216** may be used.

The microprocessor **127** obtains the energy value and velocity value from the image plane data in buffer **123** for each spatial location in the region of interest. The energy and velocity values are compared to the bin energy and velocity values, respectively, of the two dimensional histogram **216** in block **217** until a match is found. The weight (*w*) of the intersection of the matched bin velocity value with the matched bin energy value is increased by one (**1**) in block **219**. After all the energy and velocity values associated with each spatial location are matched, the two-dimensional histogram **216** is complete.

For use in the microprocessor **127** based system of the preferred embodiment, the two-dimensional histogram **216** is treated as a series of one-dimensional histograms **200**. For the example above and as shown in FIG. **4C**, each histogram **200** of velocity bins (**0-63**) represents a particular energy bin as shown in FIG. **4C**. Thus, sixty four (**0-63**) energy histograms **200** are provided.

Once the two-dimensional histogram **216** is created, microprocessor **127** converts the bin ultrasound values to the linear scale. Alternatively, the set ultrasound values remain in the log scale for calculations in the log scale.

Three dimensional histograms are also created. Thus, yet another ultrasound parameter or time is used in creating the histogram. Any bin ultrasound values associated with the third dimension are also converted to the linear scale for linear calculations.

The histogram format is also useful for altering the image plane data by applying a threshold or baseline shift. For the embodiment shown in FIG. **15**, the application of a baseline shift and any threshold is controlled by microprocessor **420** without creating the histogram, as discussed below.

Referring to FIGS. **1** and **4**, the baseline shift discussion below demonstrates application of the baseline shift to the one-dimensional histogram **200**. Application to the two-dimensional histogram **216** is comparable.

Baseline shift, as known in the art, accounts for obviously erroneous values in the velocity image plane data in buffer **123**. Erroneous velocity values from the velocity image plane data in buffer **123** are reassigned the appropriate value by microprocessor **127**.

For applying a baseline shift, the histogram **200** is created from Doppler velocity values from the image plane data. Using the histogram **200**, the baseline shift is performed on the bin velocity values. Referring to FIG. **14A**, a region of interest **131** is selected across a vessel. FIG. **14B** demonstrates the actual velocity values obtained before baseline shift as a function of distance for the region of interest **131**.

FIG. **14C** graphically demonstrates the histogram **200** created from the actual velocity values. For this example, the negative bin velocity values are erroneous. The negative bin velocity values represent velocity values above positive V_{max} and are reassigned to histogram bin velocity values greater than positive V_{max} .

More particularly, the histogram **200**, assuming sixty four (64) velocity bins, has positive velocity values assigned to bins zero (0) through thirty one (31). Bin thirty two (32) is assigned the largest negative value with incrementally smaller negative values assigned through bin sixty three (63). Exceeding the bin value associated with bin thirty one (31) represents exceeding the Nyquist velocity. For this example, all bin values associated with negative velocity are shifted to associate with positive velocities. Thus, bin values for bins thirty two (32) through sixty three (63) are baseline shifted. Alternatively, the baseline shift operation occurs as the histogram is created.

In the example above, the microprocessor **127** baseline shifted all negative bin velocity values, or bins **201** associated with a one (1) V_{max} range. More or less baseline shifting of the two (2) V_{max} range, resulting in more or fewer positive values, may be used. The baseline may be shifted by fractions of the number of bins **201** in the histogram **200**. Generally, positive versus negative values demonstrate flow towards or away from the transducer **104**.

FIG. **14D** represents baseline shifting the histogram **200** of FIG. **14C** by $\frac{2}{3}$ of V_{max} . Bins **201** numbered **32** through **54** are baseline shifted. FIG. **14E** demonstrates a velocity profile curve created from the histogram **200** of FIG. **14D**. The baseline shifted linear velocity surface integral waveform, or profile, is displayed within the region of interest in FIG. **14A**.

The histogram **200** also provides a convenient method for applying a threshold to the image plane data. As known in the art, the operator can adjust the user interface **133** to select a threshold to be applied to the image plane data, such as for

rejecting lower velocities. Referring to FIGS. **1** and **4**, the microprocessor **127** applies the threshold to the histogram **200**, two dimensional histogram **216** or a three dimensional histogram. Applying the threshold removes the weight associated with particular values in the image plane data. For example, applying a threshold to the two dimensional histogram **216** is discussed below.

The microprocessor **127** applies the threshold to the bin ultrasound values of any of the ultrasound parameters, such as color Doppler energy, velocity or variance or B-mode intensity. In the two-dimensional histogram **216**, the threshold is applied to the bin ultrasound values associated with one parameter prior to calculations based on image plane data associated with either parameter of the histogram.

A threshold process is shown in FIG. **5**. As discussed above with respect to creation of the two dimensional histogram, the two dimensional histogram **216** corresponding to energy and velocity values is created in block **218**. Other ultrasound parameters or time could be used.

To apply the threshold as shown by block **224**, the threshold cut-off value is obtained in block **226** from the user interface **133** via the microprocessor **127**. For velocity, the threshold cut-off value is applied to positive and negative bin velocity values. As shown by block **228**, the bin data corresponding to intersections of bin energy values with a positive or negative bin velocity value below or above the positive or negative cut-off value, respectively, are set to zero. For example and in reference to FIG. **4C**, the velocity bins below the cut-off in each energy histogram are set to zero. As a further example and assuming a cut-off value of two, the bin data associated with the cross hatched area in FIG. **4B** is set to zero. Thus, the two-dimensional histogram **216** contains bin data above zero corresponding to spatial locations above the velocity threshold. The threshold may also be applied to remove high values, a range of values or high and low values.

Many possible combinations can be used to threshold various parameters based on other various parameters to more accurately reflect what the user sees on the ultrasound image **130** or to obtain various measurements. One example is discussed below with respect to automatic area detection.

Turning to FIG. **10**, a region of interest **131** includes portions of a blood vessel **300**. The microprocessor **127** obtains image plane data (such as Doppler velocity values) for each spatial location within the region of interest **131**. A threshold cut-off is then selected. In the velocity example above, the threshold cut-off defines a velocity value separating velocity values corresponding to tissue motion from velocity values corresponding to fluid or blood motion. The threshold cut-off may vary, as previously discussed, due to operator input and the structure represented within the region of interest **131**. Based on the threshold cut-off and the velocity values for each point in the region of interest **131**, the microprocessor **127** determines a microprocessor region of interest **302**. The microprocessor region of interest **302** corresponds to spatial locations within the region of interest **131** with corresponding velocity values above the cut-off.

As another example, a threshold cut-off is applied to B-mode intensity values. The echo signals used to derive the B-mode intensity values are obtained and passed through a spatial or temporal low pass filter to smooth the echo signals for reliability. The threshold cut-off is then applied to the corresponding B-mode intensity values from the image plane data. Preferably, the threshold cut-off is selected to define B-mode intensities associated with structure from B-mode intensities not associated with structure. The pixels corresponding to structure surrounding pixels corresponding

with no structure define the area of the microprocessor region of interest **302**. The microprocessor region of interest **302** may not be a set of contiguous points. For example, a blockage or other tissue may exist within or protruding into a vessel and not be included in the microprocessor region of interest **302**. Once the microprocessor region of interest **302** is determined, the microprocessor region of interest **302** is highlighted on the image **130**.

For structure that changes position or size over time, such as the heart, the microprocessor **127** creates multiple microprocessor region of interests **302** as a function of time. The same operator region of interest **131** is used for creating each microprocessor region of interest **302**. The heart walls change in size and shape over time, based on the heart cycle. The microprocessor **127** automatically accounts for the changes by creating the microprocessor region of interest **302** on a per frame or multiple frame basis over a portion of a heart cycle, a single heart cycle or multiple heart cycles.

Referring to FIGS. **1** and **10**, the region of interest **131** or microprocessor region of interest **302** are used for various calculations. The microprocessor **127**, as demonstrated by block **127c**, calculates any desired quantities based on the corrected and/or converted image plane data in buffer **123**. The calculations are based on displayed image plane data or non-displayed image plane data. Alternatively, the calculations are based on acoustic ultrasound signal values or color value based ultrasound signal values. The quantities are derived using the histogram **200**, two-dimensional histogram **216** or three dimensional histogram.

Using different parameter values, such as Doppler energies or B-mode intensities, for the calculations provides different measurements indicative of conditions in the body. For example, the surface area of Doppler energy for a given time is calculated to provide a measure of blood perfusion.

Referring to FIGS. **3** and **4**, use of the histogram **200** to calculate a quantity is shown. For example, a linear average B-mode intensity is calculated. The histogram **200** derived from B-mode intensities and converted to the linear scale is obtained as discussed above. Each linear bin B-mode intensity value is multiplied by the histogram weight associated with the bin B-mode intensity value. The resulting weighted linear bin B-mode values are then summed for each bin **201** in block **212**. The sum represents a total linear B-mode intensity for the region of interest **131**.

The average linear B-mode intensity is calculated by dividing the total linear B-mode intensity by the number of points in the region of interest **131**, the sum of the bin data. The average linear B-mode intensity can be log scaled and compressed so that the value conforms to the units (dB) of the image **130**. Furthermore, the bin ultrasound values can be left in the log scale to obtain an average log B-mode intensity.

Other higher order quantities are conveniently calculated using the bin data of histogram **200**. A waveform or curve of the bin data of histogram **200** is created as a function of the bin ultrasound values. The waveform represents the weight or number of occurrences of a particular value as a function of the various bin ultrasound values. Various quantities are derived from the waveform. For example, the standard deviation of the waveform is calculated. As another example, the linear standard deviation is readily available from the histogram **200** after converting the bin ultrasound values to the linear scale.

A waveform of the bin data of histogram **200** as a function of bin ultrasound values in the log scale is also created by microprocessor **127**. From the waveform of the histogram **200** in the log scale, a log weighted average or log weighted

standard deviation is calculated. Using appropriate reverse log compression and the bin data of histogram **200**, a variety of quantitative values and waveforms are calculated.

The microprocessor **127** also calculates quantities using the bin data and bin ultrasound values of the two-dimensional histogram **216**. For the example and as demonstrated by FIG. **5**, an average energy for fluid in a linear scale is calculated using the bin data from the two-dimensional histogram **216**. Other quantities, calculated as a function of energy values or values associated with other ultrasound parameters may be used.

As discussed above with respect to FIG. **5**, the two-dimensional histogram **216** is derived from energy and velocity values. Also as discussed above, the threshold cut-off is applied to the two-dimensional histogram **216** to set the bin data associated with low velocity values to zero.

A total energy in the linear scale is then calculated as shown in block **229**. As discussed above, the bin energy values are converted to the linear scale in block **230**. The weight corresponding to each bin energy value is then obtained in block **232**. The weights from each intersection of each particular bin energy value with the various bin velocity values are added. For velocities below the threshold, the weight is set to zero, so the low velocity energies are not added to the weight of each bin energy value. The linear bin energy values are multiplied by the weight corresponding to each bin energy value as shown in block **234**. Finally, the weighted linear bin energy values for each bin **201** or bin energy value are summed in block **236** to obtain a total linear energy or surface integral of Doppler energy.

To determine the average linear Doppler energy, the number of points corresponding to velocities greater than the threshold are calculated in block **238**. All the weighting values, or bin data, in the two-dimensional histogram **216** are summed by microprocessor **127**. Since the weights associated with low bin velocity values are set to zero, the spatial locations associated with the low velocity values are not included in the summation. The summation represents the total number of spatial locations with a velocity value above the threshold.

Finally, in block **240**, the total linear Doppler energy is divided by the total number of spatial locations with a velocity value above the threshold. The result is the average linear Doppler energy or the normalized surface integral of Doppler energy. Further, since low velocity points are removed by applying the threshold, energy signals associated with slow moving tissue are removed. Only energy values from the image plane data associated with the more rapidly moving fluids are included in the calculation. To calculate average linear Doppler energy for all energies in the region of interest **131**, the velocity threshold cut-off is not applied.

Other calculations are made using the two-dimensional histogram **216**. Referring to FIG. **4** and for example, the two-dimensional histogram **216** where one dimension corresponds to time and the second dimension corresponds to an ultrasound parameter, such as Doppler energy, is created. The two-dimensional histogram **216** is used to create a time averaged histogram **200**.

The histogram **200** of the average weight over time as a function of the bin energy values is created by the microprocessor **127**. The weights from the intersection of all the time bins with each bin energy value of the two-dimensional histogram **216** are summed. The summed weights are then divided by the number of time bins to obtain an average weight as a function of time for each energy bin. The result is histogram **200** with bin data corresponding to the average occurrence of the bin energy values as a function of time.

The histogram **200** of Doppler energy averaged as a function of time is used to calculate various quantities, such as a surface integral of Doppler energy averaged as a function of time. Other histograms **200** may be created representing a weighting of one ultrasound parameter distributed across the bin values for another ultrasound parameter or time.

The histogram format is used to calculate quantities associated with the microprocessor region of interest **302**. Using microprocessor region of interest **302**, quantities are calculated without applying a threshold to the image plane data used for the calculation. For the embodiment shown in FIG. 1, a two-dimensional histogram of low pass filtered B-mode intensities and B-mode intensities is created. Low pass filtering the B-mode intensities spatially averages the intensities as known in the art. As discussed above, a threshold is applied to the low pass filtered B-mode intensities to determine the microprocessor region of interest **302**. The remaining B-mode intensities are then used to perform various calculations, such as the integration of B-mode intensity over an area. The quantities include B-mode intensities above and below the low-pass filtered B-mode threshold value. Other parameters, such as energy, can be used.

Various calculations and displays are also based on each microprocessor region of interest **302** over time. For example, the microprocessor region of interest **302** and an average Doppler energy value for the microprocessor region of interest **302** for each of multiple frames of image plane data is determined.

Referring to FIG. 15, the same calculations as discussed above are performed without applying the histogram format. Instead, a look-up table and accumulator structure is provided for determining various quantities.

In particular, the output of multiplexer **432** includes the image plane data and/or region Id. Alternatively, acoustic or color value based ultrasound signal values are used. The image plane data is applied along signal path **436** to a parameter selector **442**, and the region Id information is applied to calculation area accumulators **444**. The parameter selector **442**, in response to the microprocessor **420**, selects the appropriate data from the image plane data, such as data corresponding to Doppler energy values. The appropriate data is supplied to the lookup table **446**. Lookup table **446** maps such data onto values that are supplied to accumulators **444**. Some of the output values are in the linear or log scales as discussed above. Instead of lookup tables **446**, other mapping devices such as threshold or scaling devices may also be used. The threshold cut-off value is selected as a high, low or range to remove various values. The accumulators **444** output quantities summed from the input values.

FIG. 16 is a schematic circuit diagram illustrating in more detail the functions and construction of the parameter selector **442**, accumulators **444** and the lookup table **446**. As shown in FIG. 16, the parameter selector **442** includes two parameter select logic circuits **442a**, **442b** for selecting the appropriate B-mode and Doppler image plane data.

The bits selected by the parameter select logic circuit **442a** are supplied to the lookup table **446a**. The lookup table **446a** applies a threshold to the selected bits to determine whether there is valid fluid flow data associated with the particular pixel. If there is valid fluid flow, the lookup table **446a** outputs a 1 to AND-gate **450**. Otherwise, the lookup table **446a** supplies a 0 to the AND-gate **450**. The enable bit of line **436** is also supplied to the AND-gate **450**. If the particular pixel data processed is not within the region of interest **131**, the enable bit of line **456** is set to 0, thereby forcing the gate output to 0 so that such pixel is not counted in the accumulator **444a**; otherwise a 1 is supplied to gate **450**.

If AND-gate **450** supplies a 1 to an adder **452**, the adder **452** adds 1 to the value stored in the accumulator register **444a** and applies this updated value to replace the one stored in the accumulator register **444a**. In this manner, the B-mode and/or Doppler image plane data is used to determine whether the pixel is counted as part of the region of interest **131** associated with fluid flow. For example, if the B-mode intensity is high, the corresponding Doppler values may not be a reliable indication of fluid flow. In this case, the lookup table **446a** outputs a 0 rather than a 1. In some applications, the Doppler data above, such as Doppler velocity data, may be adequate for determining the validity of the data. The same considerations also apply to qualifying the validity of the image plane data processed in the parallel path described below.

In parallel, the parameter select logic **442b** selects the appropriate bits, such as Doppler energy or B-mode values, from the image plane data from multiplexer **432**. The selected bits are supplied to the lookup table **446b**. In a manner similar to that described above for lookup table **446a**, lookup table **446b** applies a selection criteria to output the selected bits if the data is qualified, such as through application of a threshold, and a 0 if the data is not qualified as valid. The output is supplied to AND-gate **454**. AND-gate **454** is a multi-bit gate. AND-gate **454** is also controlled by the region Id enable bit in a manner similar to AND-gate **450**. Adder **456** then adds the output of AND-gate **454** to the stored value in accumulation register **444b** and supplies the updated value to replace the stored value in accumulator register **444b**.

The buffers **412** and **414** each store an entire frame of image plane data. After an entire frame of information is processed through the two signal paths in FIG. 16, accumulator **444a** contains a count indicating the number of qualified pixels where there is significant fluid flow in the region of interest. Accumulator register **444b** contains a summed value of a parameter, such as velocity. The values stored in the two accumulator registers **444a**, **444b** are then read by the microprocessor **420** through two tri-state buffers **458** controlled by the microprocessor **420** and stored in the microprocessor memory. The above-described process for counting the number of qualified pixels and integrating qualified parameter values is performed for each of multiple frames.

The microprocessor **420** performs calculations using the accumulated information. By multiplying the number of pixels by the area per pixel, an area measurement is obtained for the region of interest **131** for each of the multiple frames. By dividing the sum of qualified parameter values by the number of qualified pixels, an average parameter for each of the several frames is obtained. Other calculations may be performed using this information.

One implementation of the embodiment of FIG. 16 is illustrated in more detail in the block diagram of FIG. 17. The embodiment shown in FIG. 17 includes circuit functions equivalent to the image planes shown in FIG. 15A and the circuit **500** which performs all the functions of FIG. 16. The circuit **500** receives Doppler and B-mode image plane data from three buffers **512**, **514** and **516**. Buffers **512**, **514** and **516** correspond respectively to the Image Type 0, Image Type 1 and Image Type 2 planes of data in buffers **412**, **414** of FIG. 15A. The image plane data from the buffers **512**, **514** and **516** is supplied in parallel to two multiplexers **542a** and **542b**. Multiplexers **542a** and **542b** are controlled by register **502** using two select lines, A select and B select. Each of the two multiplexers **542a** and **542b** selects the appropriate bits of information from buffers **512**, **514** and **516** and supplies

the bits to a corresponding lookup table **546a** or **546b**. Lookup tables **546a** and **546b** comprise random access memory devices. The lookup tables **546a** and **546b** are controlled by register **502** using page selects PAGEA and PAGEB.

The circuit **500** includes two pairs of accumulators: a first pair **544a(1)**, **544a(2)** and a second pair **544b(1)**, **544b(2)**. In each pair of accumulators, one accumulator **544a(1)** and **544b(1)** accumulates or integrates image plane data associated with even-numbered pixels and the other accumulator **544a(2)** and **544b(2)** accumulates or integrates image plane data associated with odd-numbered pixels. The accumulators within each of the first pair **544a(1)** and **544a(2)** and the second pair **544b(1)** and **544b(2)** are arranged in parallel to increase the speed of the accumulation process.

The lookup tables **546a** and **546b** map the received bits onto selected stored values and supply outputs to two sign extension controls **548**. Each of the sign extension controls **548** supplies sign extended signals to one of the first pair **544a(1)** and **544a(2)** or the second pair **544b(1)** and **544b(2)** of accumulators. Each of the four accumulators has sixteen registers addressed by a four bit region address signal from pixel control map **518**. Pixel control map **518** performs a function similar to that of the region Id section of the image planes of FIG. **15A**. In this manner, each of the four accumulators is capable of accumulating up to sixteen different calculation areas. The calculation areas correspond to multiple regions of interest **131** (FIG. **2**).

Pixel control map **518** provides control bits for A enable and B enable. The control bits control accumulation of a single quantity, such as area or velocity, without accumulating the values of a second quantity.

FIG. **18** illustrates an alternative embodiment to that of FIG. **17** for accumulating quantities. As shown in FIG. **18**, system **600** has essentially the same overall structure as shown in FIG. **17** except that the number of multiplexers (e.g. **642**), lookup tables (e.g. **646**) and accumulators (e.g. **644(1)**, **644(2)**) are reduced. Additional control circuits, such as control register file **602**, A/B select register **604**, and multiplexers **606**, **608**, are provided to control parameter multiplexer **642**, lookup table **646**, sign extension control **648**, and accumulators **644 (1)**, **644 (2)**. The additional control circuits control selection of particular image plane data corresponding to the particular region of interest **131** (FIG. **2**) and the desired quantity.

Referring to FIG. **19**, a schematic circuit diagram illustrating a circuit **750** useful for the device shown in FIG. **18** is shown. The accumulators **644(1)** and **(2)** are replaced with the circuit **750**. Obtaining a value from each of the two accumulators **644(1)**, **644(2)** takes considerable time. When the value is sent to adder **652**, as shown in FIG. **18**, the value may already be stale. The circuit shown in of FIG. **19** compensates for stale values from accumulators **644(1)** and **644(2)** by using the circuit **750**. A region Id collision detector **751** compares the region Id that is associated with the value at the input to the accumulator with the region Id associated with the value being written to memory **744**. Based on the comparison, the region Id collision detector **751** selects which of the multiplexer **760** inputs to be applied to adder **752**.

For either of the alternative embodiments shown in FIGS. **17**, **18** and **19**, quantities are calculated using accumulators. Calculating the quantities occurs immediately after real-time acquisition of the echo signals or at a later point in time as the data is read out of the CINE **408** (FIG. **15**). One quantity calculated is the cross-sectional area. Cross-sectional area is calculated by counting qualified pixels and multiplying the

count by the pixel area. Other methods of integrating qualified area portions may be used and are within the scope of the invention. The cross-sectional area, or other quantities, are calculated for multiple frames of image plane data.

One possible processing sequence for acquiring frames of image plane data is:

REPEAT FOR (selected set of acquisition angles)

FOR EACH DISPLAYED FRAME

Processor waits for the start of vertical blank (FIG. **15A**)

Processor acquires from the hardware for the previously displayed frame

FOR EACH REGION-ID

read from the hardware the total number of pixels displaying

qualified color as calculated by the hardware

read from the hardware the sum of all qualified velocity values at pixels in a given region

processor clears accumulators

As averaged area measurements and averaged parameter values, such as velocity in this example, for each of multiple frames are computed, a temporal average is calculated based on the multiple frames of data. The temporal averaged area measurement and averaged velocity values correspond to a particular angle of measurement θ between the scan plane and the fluid flow in the vessel. The image plane data can be acquired for multiple angles of scanning, and the calculations can be derived from image plane data corresponding to the multiple angles.

As a further example of the ability of the embodiment shown in FIG. **15** to perform the same calculations as the embodiment of FIG. **1**, the accumulators and look-up tables are used to obtain a quantity for the microprocessor region of interest **302**. The accumulation of B-mode values is configured to depend on the low pass filtered B-mode value. If the low pass filtered B-mode value is below the threshold, then the associated spatial location is not within microprocessor region of interest **302** and the associated B-mode intensity is not accumulated. The remaining B-mode values are accumulated even if the B-mode value is above or below the low pass filtered B-mode threshold. Like the embodiment of FIG. **1**, other parameters, such as energy, can be used.

Quantities are also calculated over time. Consecutive frames of image plane data spanning several Rwave cycles are obtained. A time stamp corresponding to the time of acquisition is associated with each frame of image plane data. Other times, such as the time at which various reference signals occurred (e.g., the Rwave trigger in a cardiac cycle) are also acquired and saved. ECG leads and processor **403** in FIG. **15A** acquire electrocardiograms for deriving Rwave trigger signals. The time information is used to average quantities over a cardiac cycle, a portion of a cycle or multiple cycles.

An example of calculating a quantity over time corresponding to multiple angles of scanning is shown below:

Let $F(i,j,k)$ represent the k th acoustic frame acquired relative to the j th Rwave trigger for the i th unique angle of scan.

The following frames of data are acquired:

$F(1,2,1), F(1,2,2), F(1,2,3), F(1,2,4), F(1,2,5), F(1,2,6), F(1,2,7), F(1,2,8)$

$F(1,3,1), F(1,3,2), F(1,3,3), F(1,3,4), F(1,3,5), F(1,3,6), F(1,3,7), F(1,3,8)$

$F(2,1,1), F(2,1,2), F(2,1,3), F(2,1,4), F(2,1,5), F(2,1,6), F(2,1,7), F(2,1,8)$

F(2,2,1),F(2,2,2),F(2,2,3),F(2,2,4),F(2,2,5),F(2,2,6),F(2,2,7),F(2,2,8)
 F(2,3,1),F(2,3,2),F(2,3,3),F(2,3,4),F(2,3,5),F(2,3,6),F(2,3,7),F(2,3,8)
 F(3,1,1),F(3,1,2),F(3,1,3),F(3,1,4),F(3,1,5),F(3,1,6),F(3,1,7),F(3,1,8)

The microprocessor 420 obtains sums from the accumulator registers 444a and 444b. In particular, sums over all j and k for each of the three frames 1, 2, and 3 are obtained. The sums are divided by 24 (the number frames between each Rwave trigger) to obtain an average. For example, the velocity average and pixel count average for each of the three angles scanned are obtained. A least mean square error calculation is then performed to find an area value and a velocity or other parameter value that minimizes the error for the averages acquired at the three angles. These values are then used to make various additional calculations.

One such additional calculation is the normalized surface integral of Doppler energy for the region of interest 131. The normalized surface integral of Doppler energy provides a measurement indicative of fluid conditions in the body. Either the look-up table and accumulator embodiment shown in FIG. 15, the histogram format embodiment shown in FIG. 1, or other embodiments are used to calculate the normalized surface integral or any of various other quantities.

The normalized Doppler energy for a given region of interest at any given time is represented by FIG. 6A. Other parameters, such as velocity, variance or B-mode intensity, can be used. Generally, energy values associated with low velocities are removed by applying a threshold. The function T represents applying the threshold.

The total Doppler energy in the linear scale is calculated. The total Doppler energy in the linear scale is represented by the summation from one to the number of points in the region of interest of D(Ei). D represents the reverse log compression, and Ei represents the 10 Doppler energy value at a particular spatial location (i) within the region of interest. If the histogram 200, two-dimensional histogram 216 or three dimensional histogram is used, Ei represents a weighted bin Doppler energy value. A graphical representation of D(Ei) is shown in FIG. 6C. This graph is used to develop the reverse log compression look-up table discussed above.

The total Doppler energy in the linear scale is normalized by dividing by the number of points, or spatial locations, with corresponding values above the threshold. The number of points remaining after applying the threshold is represented in FIG. 6A by the summation over all the points in the region of interest (Ti(Ei, Vi)). Thus, an average parameter is calculated. This average does not change as a function of the magnification level of acquisition and display in the ultrasound system.

The surface integral of the Doppler velocity or any other parameter may also be normalized by area. The number of points remaining is multiplied by the area of each point as part of the normalization step described above. The area represented by any given pixel is used to determine the area. Thus, a parameter density is calculated such as velocity density.

The average or other quantities, such as density, are instantaneous values. Multiple instantaneous quantities are used to derive a waveform. For example, instantaneous normalized surface integrals of Doppler energy for multiple frames of image plane data are calculated. Preferably, each surface integral is normalized by the number of points associated with energies added to the total energy. A wave-

form of the normalized surface integral of Doppler energy is created as a function of time. The waveform demonstrates a change in flow over time and is shown in FIG. 6B. The variation in the normalized surface integral of FIG. 6B shows a change in amount of flow over time and corresponds to changes in blood flow based on the heart cycle. Other curves as a function of other parameters may also be created.

Various quantities are derived from the normalized surface integral as a function of the heart cycle. For example, a time integral of the normalized surface integral of Doppler energy as a function of time is calculated. Referring to FIG. 1, block 127d represents the microprocessor 127 calculation of the time integral. The time integral of the normalized surface integral, as represented in FIG. 7, provides a quantity indicative of volume flow for a particular time period, Tn-1 to Tn.

Selection of the time period depends on the particular use of the ultrasound system 100 (FIG. 1) or 400 (FIG. 15). For example, the various quantities are a function of a single heart cycle, multiple heart cycles, or a portion of a heart cycle. Such calculations include the period of the heart cycle, demarcation of certain heart cycle events, ejection fraction and others.

Referring to FIGS. 1, 8 and 15 and as known in the art, ECG leads and processor 137 (FIG. 1), 403 (FIG. 15) trigger the beginning and end of the time period. Block 127e represents the microprocessor 127 use of the trigger signal from the ECG leads and processor 137 for computing further quantities. A graphical representation of the trigger signal is shown in FIG. 8B.

Instead of using ECG leads and processor 137, 403 to detect heart cycle periods, the normalized surface integral of Doppler energy is used. Other parameters may be used, such as B-mode intensities. The normalized surface integral is displayed on display unit 132 or 440, as described below. The operator, using user interface 133 or 431, selects a time period for integration. In particular, icons 270 are activated and placed on the waveform. Alternatively, the user inputs the number or portion of heart cycles to integrate over. The microprocessor 127 or 420 then determines the points on the normalized surface integral waveform representing the selected time period. FIG. 8A shows selection of one heart cycle at times Tn-1 to Tn. Thus, the time integral of the normalized surface integral of FIG. 7 is calculated over time Tn-1 to Tn.

The time integral is used to calculate an average surface integral of Doppler energy. The time integral of the normalized surface integral is normalized by time. In particular, the time integral is divided by the time period of integration, such as the number of frames of image plane data used to calculate the time integral of the normalized surface integral. Normalized time integrals of other parameters may also be calculated. Further, any calculation as a function of time for any parameter may be normalized by the time period.

Time periods derived from the normalized surface integral are also used to trigger various functions of the ultrasound system 100 or 400. For example, the beginning of the heart cycle triggers recording of echo signals in CINE 112, 182 or 408. The operator inputs a time period, as discussed above. The microprocessor 127 or 420 monitors the normalized surface integral waveform data for a reoccurrence of the selected begin point of the heart cycle. The microprocessor 127 or 420 then controls CINE 112, 182 or 408 to store data derived from echo signals until the end point is reached.

Various other quantities, other than those discussed above, are derived from the image plane data as instantaneous or

period based calculations. Alternatively, acoustic or color value based ultrasound signal values are used to derive quantities. Other functions or other ultrasound parameter values could be used. For example, the average value of a parameter in a region of interest is calculated. Further, the area of the region of interest is also calculated. The average value or any other quantity is multiplied or divided by the area or a unit area to determine various quantities, such as volumetric flow (average velocity multiplied by area).

Other complex functions are also calculated, such as the product of energy and velocity. This product may predict the amount of blood flow in jets and may be of use in perfusion. Energy and velocity values associated with each particular pixel are added to create an energy-velocity product frame of image plane data. The surface integral calculation or any other calculations are performed on the energy-velocity product image plane data. Further quantities, such as the time integral, are also calculated. Thus, the combination of image plane data associated with different parameters prior to performing various calculations also results in useful information. Functions other than the product may be used to obtain the complex function image plane data.

Any of the calculations discussed above or below, including complex functions, are also derived from image plane data associated with a 3-dimensional display. For example, instead of a surface integral, a volume integral is calculated. The volume integral or any other quantity is normalized by volume or time. The region of interest determinations discussed above apply to selecting a three-dimensional region of interest.

Generally, the quantities discussed above are relative values. Various variables, such as the power of the ultrasound signal provided by the transducer 104, 430 and depth attenuation, affect the values in the image plane data. Likewise, quantities calculated as a ratio are also relative.

Quantities associated with multiple regions of interest 131 acquired simultaneously or sequentially are compared or combined. The microprocessor 127 or 420 combines various quantities or waveforms. The combination creates comparison data. Preferably, the various settings of the ultrasound system 100 or 400, such as gain, are the same for acquisition and processing of echo signals to create comparison data. For combination or comparison discussed above, a region of interest 131 comprises a single spatial location, an entire organ or a volume.

As an example of combination or comparison, two regions of interest 131 in a person's liver are selected with input from the operator. The image plane data from the two regions of interest 131 are compared to determine the relative amount of perfusion at a certain time. For example, the surface integral of energy is calculated for each region of interest 131. Each surface integral provides a measure of perfusion. A ratio of the two surface integrals is created. The relative amount of perfusion is indicative of an infarction. The ratio function based on values in the linear scale is equivalent to the difference function based on values in a log scale.

Another example of comparing or combining quantities is the combination of quantities associated with two regions of interest 131 in different parts of the body, such as contralateral organs. Contralateral organs include kidneys, breasts, and testicles. As a further example, the surface integral of Doppler energy from the different regions of interest 131 is determined as a function of time to create two waveforms. The two waveforms are combined as a ratio, or other function, into one waveform. Combining these or other quantities accounts for differing gain, frequency, or other

signal properties when the echo signals are acquired and processed. Contralateral organs provide good comparisons. The organs have similar properties, so any abnormality in one organ is likely to be highlighted when compared to the same type of organ in the same body.

As another example, image plane data for one region of interest 131 acquired at a first time is compared with image plane data for another region of interest 131 acquired at a different time. Thus, image plane data from one region of interest is used as a constant for comparison or combination with a second region of interest 131. The portion of the body represented by the second region of interest 131 may be operated on or subject to an injection of some substance, such as a contrast agent. The time difference is seconds, hours or days apart.

Heart area comparisons are an example of a comparison of one region of interest at one time with a different region of interest at another time. One region of interest is selected to correspond to the left ventricle at the ventricle's largest size. The second region is selected to correspond to the left ventricle at the ventricle's smallest size. Alternatively, the microprocessor region of interest is used as it varies as a function of time. Generally, the second region of interest is enclosed within the first region of interest. The image plane data from the first region of interest 131 is used to calculate an area corresponding to the largest area value for the left ventricle. The image plane data from the second region of interest 131 is used to calculate an area corresponding to the smallest value for the left ventricle. Both areas are combined as a ratio, a product or some other function.

Surface and time integral quantities associated with a single region of interest acquired sequentially are also used for comparison or combination. For example, the first acquired quantity is used as a constant and compared or combined with the second quantity. The second quantity is derived from image plane data acquired after surgery or an injection, such as an injection of a contrast agent.

The times or time periods for calculating the sequential quantities are based on any desired event, such as heart cycle, time of washout of an injected contrast agent, or an arbitrary time. For example, the time period of calculation of a mean is set to a portion of a heart cycle, one heart cycle or multiple heart cycles. Image plane data is then acquired over the time period. The calculation is triggered by the microprocessor 127 or 420 based on an input, such as ECG leads and processor 137 or 403, or based on the surface integral as discussed above. The trigger prevents false weighting of any period based quantities.

A ratio of a quantity from a first time period to the quantity from another time period is obtained. For example, the average velocity for one cardiac cycle is combined as a ratio with the average velocity for another cardiac cycle. Further, the average velocities as a function of time for each cardiac cycle are combined as a ratio waveform.

Quantities derived from image plane data associated with one region of interest and the same period of time are also combined. For example, the mean of a parameter associated with the region of interest over the selected time period is determined. A high and low value over the selected time period are also determined. The high and low values are each divided by the mean. Further, the high versus low values, divided by the mean, are also combined as a ratio. For example, the highest velocity for a region of interest over the selected time period as a function of the mean is compared or combined with the lowest velocity for a region of interest over the selected time period as a function of the mean.

Quantities associated with different parameters for the same region of interest 131 taken at the same time are also

used for comparison or combination. For example, a Doppler energy surface integral and a B-mode intensity surface integral for a region of interest are computed. A waveform for each computed value as a function of time is also created. Further, a waveform of the ratio of these computed values is generated.

This particular Doppler energy to B-mode intensity ratio is indicative of the amount of blood compared to tissue. Since the amount of tissue is invariant, the ratio is used to determine the amount of blood at any give time, such as over a cardiac cycle. Any of the singular or multiple region of interest **131** comparisons and combinations described above and below could also be based on a comparison or combination quantities derived from different parameters.

Instead of using a ratio, other functions for combining the quantities may be used, such as product functions to create the comparison data. Further, any of the various quantities, such as surface integrals, means, areas or time integrals, can be combined. Other ultrasound parameters, or types of signals, can also be used, such as variance, velocity, energy, B-mode intensity or others. Any of the various comparison data can be created as a function of time. Thus, a waveform of comparison data is created.

A ratio metric comparison tends to cancel out differences due to gain, angle dependence, level of fluid and other differences to provide more accurate results. Further, any differences between the settings of the ultrasound system **100** or **400** while acquiring echo signals, such as differing gain, frequency, transmit power or bandwidth, are preferably corrected prior to any calculations. These differences are available since the ultrasound system **100** or **400** uses the gain, frequency, transmit power and bandwidth to obtain the image plane data. The frequency and bandwidth are scaled, and the gain and transmit power are logarithmically adjusted.

Multiple regions of interest **131** are also selected to remove depth dependent attenuation. The regions of interest **131** are selected to have comparable depths. The operator subjectively selects multiple regions of interest **131** with approximately the same depth position in the image **130**. Comparable depth regions of interest **131** are generally easily selected in the same organ or contralateral organs. Thus, depth dependent attenuation is removed by the selection of regions of interest **131** in the same organ or contralateral organs. Quantities associated with volume regions of interest may also be combined or compared as discussed above.

Selection of regions of interest **131**, any of the various combinations, calculations, waveforms or other processing are also performed using CINE playback. CINE **112**, **182** or **408** plays back Doppler and B-mode data. CINE **112**, **182** or **408** records the data used to create multiple frames of image plane data over a time period, such as ten (10) seconds.

Using CINE **112**, **182** or **408**, a particular frame of image plane data is played back multiple times for quantification and comparison. The CINE **112**, **182** or **408** also allows for creation of more stable values for the image plane data by allowing adjustment of the region of interest **131** or of any threshold for rejection of undesirable data. The time period, including beginning points and end points, are also adjusted using CINE playback. Icons or margins are positioned on either a waveform or frame count to designate the beginning and ending points of the time period.

For example, a different threshold for determination of a microprocessor region or regions of interest **302** is applied. The quantities and waveforms derived from the new microprocessor regions of interest **302** for the same frame or

frames of image plane data are calculated, such as the surface integral of Doppler energy. Different data stored within CINE **112**, **182** or **408** could also be selected for various calculations, including contiguous or non-contiguous time frames for the same or different regions of interest **131**.

Referring to FIGS. **1** and **15**, any of the various quantities, waveforms, regions of interest **131** and histograms discussed above are displayed on display unit **132** or **440**. The various information for display is created as either as part of CINE **112**, **182** or **408** playback or in real-time. The microprocessor **127**, **420** has an output to graphics memory unit **129**, **462**, as represented by block **127f** (FIG. **1**). Graphics memory unit **129**, **462** provides information to combining unit **124**, **463**. Combining unit **124**, **463** combines the microprocessor **127**, **420** output with the appropriate image **130** for display on display unit **132**, **440**. For example, the average linear B-mode intensity is displayed on display unit **132**.

As shown in FIG. **9**, the quantity calculated for the time integral of the normalized surface integral of Doppler energy is displayed on the screen of display unit **132** in box **250**. Other calculated values could also be displayed in box **250**. Multiple quantities and waveforms are displayed simultaneously.

Waveforms, such as the normalized surface integral of Doppler energy as a function of time, are displayed as shown in FIG. **8A**. The waveforms are displayed with the image **130** and box **250**.

A profile curve of ultrasound signal values as a function of spatial location is displayed. The profile is displayed in conjunction with selection of a line **272** as the region of interest **131**.

The data associated with histograms **200**, two-dimensional histograms **216** or three-dimensional histograms are also displayed as a waveform. The waveform comprises the bin data as a function of the bin ultrasound values. Furthermore, the histograms are displayed before or after any alteration, such as converting to a linear scale.

The bin data and bin ultrasound values of the two-dimensional histogram **216** are displayed as a series of curves or as a three dimensional graph. For the series of curves display, each curve corresponds to a particular bin ultrasound value along one dimension. Three-dimensional histograms are displayed as a series of two-dimensional histogram displays.

Displaying waveforms and quantities derived from different regions of interest **131** or at different times allows users to compare the waveforms and quantities. The various comparisons or combinations discussed above, either as quantities or waveforms, are displayed. Different regions of interest **131** or time periods for the same region of interest **131** are selected as discussed above. For example, different regions of interest **131** or time periods are selected during multiple CINE **112**, **182**, **408** playback of echo signals. The waveform and quantity data is stored. Once all the waveforms and quantities are calculated, a comparison of the waveforms and quantities derived from the first region of interest **131** or time period to the subsequent region of interest **131** or time period is displayed.

The waveforms, calculations and other information displayed as discussed above is updated once per frame displayed on display unit **132**. A moving average of the various waveforms and quantities is created for time period based quantities or waveforms. The moving average is obtained by overlapping the integration interval for successive measurements. Alternatively, the waveforms, calculations and other

information may be updated at the end of any interval, such as every heart cycle or any other time period.

The display of particular waveforms and calculations in one or more time periods could also be based on a comparison of image plane data, quantities, waveforms or combinations of the image plane data. For example, a surface integral quantity associated with the time period with the greatest surface integral quantity is displayed. As another example, the frames of Doppler energy image plane data within a time period with the highest velocity value are displayed.

Other than display, various quantities are used to control the ultrasound system **100, 400**. The microprocessor **127, 420** controls various internal processes or outputs control signals on line **138, 421** based on the quantities. For example, a depth gain compensation automatic adjustment is provided. The mean B-mode intensity for a region of interest **131** is calculated. The mean is calculated as discussed above, or any other method. Another mean B-mode intensity for the same region of interest **131** at a different time or for a different region of interest **131** is calculated. If the means are different, then the image plane data associated with one of the regions of interest **131** or times is altered by changing the operation of the beamformer **102, 402** to yield an equal mean.

Alternatively, high order quantities may be examined for bell curve distribution. If the quantity is not distributed as a bell curve, the image plane data is altered to yield a bell curve. Altering the image plane data compensates for differing gains. Other internal processes could be controlled by the microprocessor **127, 420** based on various quantities.

As another example of control based on quantities, injection of contrast agents is controlled. A calculation is performed that changes over time based on events, such as decay of a contrast agent. For decay of contrast agent, the mean B-mode intensity or surface integral of Doppler energy is calculated. Once the mean or surface integral reaches a particular low value, the microprocessor **127, 420** outputs a control signal on line **138, 421**. The control signal is used by an external device, such as an injection pump, to trigger particular operations. For example, the injection pump injects more contrast agent based on the control signal. Other external devices may be controlled by the microprocessor **127, 420**. Formation of an ice ball for cryogenics may be monitored and controlled. Various quantities associated with various calculations may be used to trigger the control signal.

Either the embodiment of FIGS. **1A** and **1B**, the embodiment of FIGS. **15A** and **15B**, or other embodiments are capable of using various aspects of the above described invention. While the invention has been described above by reference to various embodiments, it will be understood that different changes and modifications can be made without departing from the scope of the invention.

It is therefore intended that the foregoing detailed description be understood as an illustration of the presently preferred embodiments of the invention, and not as a definition

of the invention. It is only the following claims, including all equivalents, that are intended to define the scope of this invention.

We claim:

1. A method of providing flow quantity data by thresholding in an ultrasonic apparatus comprising the steps of:

acquiring a Doppler energy for each of multiple spatial locations in a region of interest at a first time;

acquiring a Doppler velocity for each of said multiple spatial locations in said region of interest at said first time;

applying a threshold to said Doppler energies based on the Doppler velocities to obtain remaining Doppler energies; and

summing said remaining Doppler energies.

2. The method of claim 1, said thresholding step comprising the steps of:

determining said threshold as a Doppler velocity cut-off value; and

setting the Doppler energy to zero for each of said multiple spatial locations where the Doppler velocity is below the Doppler velocity cut-off value.

3. The method of claim 1 further comprising displaying said sum.

4. The method of claim 3, the step of displaying comprising the step of displaying a waveform of said sum as a function of time.

5. The method of claim 1 wherein the steps of acquiring said Doppler energy for each of said multiple spatial locations in said region of interest at said first time and acquiring said Doppler velocity for each of said multiple spatial locations in said region of interest at said first time comprise acquiring values for each of multiple spatial locations in a volume region of interest.

6. The method of claim 1 wherein the step of applying said threshold to said Doppler energies based on said Doppler velocities comprises applying a histogram.

7. The method of claim 1 wherein the step of summing said remaining Doppler energies to obtain said sum comprises applying a histogram.

8. An ultrasound apparatus for providing flow quantities by applying a threshold comprising:

a buffer for storing Doppler energy and Doppler velocity data for each of multiple spatial locations in a region of interest;

a threshold value data;

a microprocessor for applying said threshold data to said Doppler velocity data to remove Doppler energy data associated with Doppler velocities below said threshold value data and for summing the remaining of said Doppler energy data.

9. The ultrasound apparatus of claim 8 further comprising a display device including display associated with said sum data.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 6,241,677 B1
DATED : June 5, 2001
INVENTOR(S) : Ismayil M. Guracar

Page 1 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Title page.

Item [12], delete "**et al.**".

Item [75], delete "; **Samuel H. Maslak**, Woodside; **John W. Allison**, Sunnyvale; **Paul E. Chandler**, Santa Cruz; **John L. Jackson**, Menlo Park; **Arvind Jain**, San Jose; **Laurence S. McCabe**, Sunnivale, all of CA" and substitute -- , CA -- in its place.

Item [56], **References Cited**, U.S. PATENT DOCUMENTS, delete

"Linuma" and substitute -- Iinuma -- in its place. (two occurrences)

OTHER PUBLICATIONS, delete "Quantative" and substitute -- Quantitative -- in its place.

Delete "Railo" and substitute -- Radio -- in its place.

Delete "jpn" and substitute -- Jpn -- in its place.

Delete "Continous" and substitute -- Continuous -- in its place.

Delete "Frequency" and substitute -- Frequency -- in its place.

Delete "Medicine" and substitute -- Medical -- in its place.

Column 5.

Line 15, insert -- an -- before "ultrasound".

Column 7.

Line 1, delete "FIG. 1," and substitute -- FIG. 11, -- in its place.

Column 22.

Line 57, delete "(ij,k)" and substitute -- (i, j, k) -- in its place.

Column 23.

Line 37, delete "10".

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 6,241,677 B1
DATED : June 5, 2001
INVENTOR(S) : Ismayil M. Guracar

Page 2 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Column 30,

Line 54, after "including" insert -- a --.

Signed and Sealed this

Twenty-ninth Day of October, 2002

Attest:

A handwritten signature in black ink, appearing to read "James E. Rogan", with a long horizontal flourish extending from the bottom of the signature.

Attesting Officer

JAMES E. ROGAN
Director of the United States Patent and Trademark Office

专利名称(译)	用于超声图像量化的方法和设备		
公开(公告)号	US6241677	公开(公告)日	2001-06-05
申请号	US09/478662	申请日	2000-01-06
[标]申请(专利权)人(译)	阿库森公司		
申请(专利权)人(译)	ACUSON CORPORATION		
当前申请(专利权)人(译)	ACUSON CORPORATION		
[标]发明人	GURACAR ISMAYIL M MASLAK SAMUEL H ALLISON JOHN W CHANDLER PAUL E JACKSON JOHN I JAIN ARVIND MCCABE LAURENCE S		
发明人	GURACAR, ISMAYIL M. MASLAK, SAMUEL H. ALLISON, JOHN W. CHANDLER, PAUL E. JACKSON, JOHN I. JAIN, ARVIND MCCABE, LAURENCE S.		
IPC分类号	A61B8/08 G01S15/89 G01S15/00 G01S7/52 A61B8/00		
CPC分类号	A61B8/08 G01S7/52023 G01S7/52034 G01S7/52063 G01S7/52071 G01S15/895 G01S15/8979 G01S15/8988 G01S7/52025 G01S7/52038		
助理审查员(译)	帕特尔MAULIN		
外部链接	Espacenet USPTO		

摘要(译)

提供了一种用于在超声系统中量化和显示超声信号的方法和装置。在第一时间获取感兴趣区域中的至少一个空间位置中的每一个的第一信号值，并且将信号值相加以获得第一表面积分值。在第二时间获取所述感兴趣区域中的所述至少一个空间位置中的每一个的第二信号值，并且将第二信号值相加以获得第二表面积分值。将第一表面积分值与第二表面积分值相加以获得基于时间的积分。显示基于时间的积分。基于各种超声参数中的任何一种的其他量，例如多普勒能量，多普勒速度和B模式强度，被计算并显示为作为时间的函数的量或波形。此外，提供了数量和波形的各种比较。在计算中使用图像平面数据或其他超声数据。最后，提供直方图数据结构以帮助计算各种量。

